GNU Compiler Collection Internals

For GCC version 4.10.0 (pre-release)

(GCC)

Richard M. Stallman and the GCC Developer Community

Copyright © 1988-2014 Free Software Foundation, Inc.

Permission is granted to copy, distribute and/or modify this document under the terms of the GNU Free Documentation License, Version 1.3 or any later version published by the Free Software Foundation; with the Invariant Sections being "Funding Free Software", the Front-Cover Texts being (a) (see below), and with the Back-Cover Texts being (b) (see below). A copy of the license is included in the section entitled "GNU Free Documentation License".

(a) The FSF's Front-Cover Text is:

A GNU Manual

(b) The FSF's Back-Cover Text is:

You have freedom to copy and modify this GNU Manual, like GNU software. Copies published by the Free Software Foundation raise funds for GNU development.

Short Contents

Introduction 1
1 Contributing to GCC Development 3
2 GCC and Portability 5
3 Interfacing to GCC Output 7
4 The GCC low-level runtime library 9
5 Language Front Ends in GCC 59
6 Source Tree Structure and Build System 61
7 Testsuites 77
8 Option specification files 105
9 Passes and Files of the Compiler 113
10 GENERIC 129
11 GIMPLE 175
12 Analysis and Optimization of GIMPLE tuples 211
13 RTL Representation 223
14 Control Flow Graph 277
15 Analysis and Representation of Loops 287
16 Machine Descriptions 297
17 Target Description Macros and Functions 421
18 Host Configuration 591
19 Makefile Fragments 595
20 `collect2` 599
21 Standard Header File Directories 601
22 Memory Management and Type Information 603
23 Plugins 615
24 Link Time Optimization 623
Funding Free Software 631
The GNU Project and GNU/Linux 633
GNU General Public License 635
GNU Free Documentation License 647
Contributors to GCC 655
Option Index 671
Concept Index 673

Table of Contents

Introduction 1

1 Contributing to GCC Development 3

2 GCC and Portability 5

3 Interfacing to GCC Output 7

4 The GCC low-level runtime library 9

4.1 Routines for integer arithmetic 9
4.1.1 Arithmetic functions 9
4.1.2 Comparison functions 10
4.1.3 Trapping arithmetic functions 11
4.1.4 Bit operations 11
4.2 Routines for floating point emulation 12
4.2.1 Arithmetic functions 12
4.2.2 Conversion functions 13
4.2.3 Comparison functions 15
4.2.4 Other floating-point functions 16
4.3 Routines for decimal floating point emulation 16
4.3.1 Arithmetic functions 17
4.3.2 Conversion functions 17
4.3.3 Comparison functions 20
4.4 Routines for fixed-point fractional emulation 22
4.4.1 Arithmetic functions 22
4.4.2 Comparison functions 30
4.4.3 Conversion functions 30
4.5 Language-independent routines for exception handling 56
4.6 Miscellaneous runtime library routines 57
4.6.1 Cache control functions 57
4.6.2 Split stack functions and variables 57

5 Language Front Ends in GCC 59

6 Source Tree Structure and Build System 61

6.1 Configure Terms and History 61
6.2 Top Level Source Directory 61
6.3 The ‘`gcc`’ Subdirectory 63
6.3.1 Subdirectories of ‘`gcc`’ 63
6.3.2 Configuration in the ‘`gcc`’ Directory 64
6.3.2.1 Scripts Used by ‘`configure`’ 64

6.3.2.2 The 'config.build'; 'config.host'; and 'config.gcc' Files ... 64
6.3.2.3 Files Created by configure ... 65
6.3.3 Build System in the 'gcc' Directory ... 66
6.3.4 Makefile Targets ... 66
6.3.5 Library Source Files and Headers under the 'gcc' Directory ... 68
6.3.6 Headers Installed by GCC ... 68
6.3.7 Building Documentation ... 69
6.3.7.1 Texinfo Manuals ... 69
6.3.7.2 Man Page Generation ... 70
6.3.7.3 Miscellaneous Documentation ... 71
6.3.8 Anatomy of a Language Front End ... 71
6.3.8.1 The Front End '*language*' Directory ... 72
6.3.8.2 The Front End 'config-lang.in' File ... 73
6.3.8.3 The Front End 'Make-lang.in' File ... 74
6.3.9 Anatomy of a Target Back End ... 75

7 Testsuites ... 77

7.1 Idioms Used in Testsuite Code ... 77
7.2 Directives used within DejaGnu tests ... 78
7.2.1 Syntax and Descriptions of test directives ... 78
7.2.1.1 Specify how to build the test ... 78
7.2.1.2 Specify additional compiler options ... 79
7.2.1.3 Modify the test timeout value ... 79
7.2.1.4 Skip a test for some targets ... 79
7.2.1.5 Expect a test to fail for some targets ... 80
7.2.1.6 Expect the test executable to fail ... 80
7.2.1.7 Verify compiler messages ... 80
7.2.1.8 Verify output of the test executable ... 81
7.2.1.9 Specify additional files for a test ... 81
7.2.1.10 Add checks at the end of a test ... 81
7.2.2 Selecting targets to which a test applies ... 82
7.2.3 Keywords describing target attributes ... 82
7.2.3.1 Data type sizes ... 82
7.2.3.2 Fortran-specific attributes ... 83
7.2.3.3 Vector-specific attributes ... 83
7.2.3.4 Thread Local Storage attributes ... 85
7.2.3.5 Decimal floating point attributes ... 85
7.2.3.6 ARM-specific attributes ... 86
7.2.3.7 MIPS-specific attributes ... 87
7.2.3.8 PowerPC-specific attributes ... 87
7.2.3.9 Other hardware attributes ... 88
7.2.3.10 Environment attributes ... 89
7.2.3.11 Other attributes ... 90
7.2.3.12 Local to tests in gcc.target/i386 ... 92
7.2.3.13 Local to tests in gcc.target/spu/ea ... 92
7.2.3.14 Local to tests in gcc.test-framework ... 92

7.2.4 Features for `dg-add-options` ... 92
7.2.5 Variants of `dg-require-support` ... 93
7.2.6 Commands for use in `dg-final` ... 94
7.2.6.1 Scan a particular file ... 94
7.2.6.2 Scan the assembly output ... 94
7.2.6.3 Scan optimization dump files ... 95
7.2.6.4 Verify that an output files exists or not ... 95
7.2.6.5 Check for LTO tests ... 95
7.2.6.6 Checks for `gcov` tests ... 95
7.2.6.7 Clean up generated test files ... 95
7.3 Ada Language Testsuites ... 96
7.4 C Language Testsuites ... 97
7.5 The Java library testsuites ... 99
7.6 Support for testing link-time optimizations ... 99
7.7 Support for testing `gcov` ... 100
7.8 Support for testing profile-directed optimizations ... 100
7.9 Support for testing binary compatibility ... 101
7.10 Support for torture testing using multiple options ... 102

8 Option specification files ... 105
8.1 Option file format ... 105
8.2 Option properties ... 107

9 Passes and Files of the Compiler ... 113
9.1 Parsing pass ... 113
9.2 Cilk Plus Transformation ... 114
9.3 Gimplification pass ... 115
9.4 Pass manager ... 115
9.5 Tree SSA passes ... 116
9.6 RTL passes ... 122
9.7 Optimization info ... 126
9.7.1 Dump setup ... 126
9.7.2 Optimization groups ... 126
9.7.3 Dump files and streams ... 127
9.7.4 Dump output verbosity ... 127
9.7.5 Dump types ... 127
9.7.6 Dump examples ... 128

10 GENERIC . . . 129
10.1 Deficiencies . . . 129
10.2 Overview . . . 129
10.2.1 Trees . . . 130
10.2.2 Identifiers . . . 131
10.2.3 Containers . . . 131
10.3 Types . . . 131
10.4 Declarations . . . 136
10.4.1 Working with declarations . . . 136
10.4.2 Internal structure . . . 138
10.4.2.1 Current structure hierarchy . . . 138
10.4.2.2 Adding new DECL node types . . . 139
10.5 Attributes in trees . . . 140
10.6 Expressions . . . 141
10.6.1 Constant expressions . . . 141
10.6.2 References to storage . . . 143
10.6.3 Unary and Binary Expressions . . . 144
10.6.4 Vectors . . . 151
10.7 Statements . . . 153
10.7.1 Basic Statements . . . 153
10.7.2 Blocks . . . 154
10.7.3 Statement Sequences . . . 155
10.7.4 Empty Statements . . . 155
10.7.5 Jumps . . . 155
10.7.6 Cleanups . . . 155
10.7.7 OpenMP . . . 156
10.8 Functions . . . 158
10.8.1 Function Basics . . . 158
10.8.2 Function Properties . . . 160
10.9 Language-dependent trees . . . 161
10.10 C and C++ Trees . . . 161
10.10.1 Types for C++ . . . 162
10.10.2 Namespaces . . . 164
10.10.3 Classes . . . 165
10.10.4 Functions for C++ . . . 167
10.10.5 Statements for C++ . . . 169
10.10.5.1 Statements . . . 169
10.10.6 C++ Expressions . . . 172
10.11 Java Trees . . . 173

11 GIMPLE 175

11.1 Tuple representation 176
11.1.1 `gimple_statement_base` (gsbase) 176
11.1.2 `gimple_statement_with_ops` 177
11.1.3 `gimple_statement_with_memory_ops` 177
11.2 GIMPLE instruction set 180
11.3 Exception Handling 181
11.4 Temporaries 181
11.5 Operands 182
11.5.1 Compound Expressions 182
11.5.2 Compound Lvalues 182
11.5.3 Conditional Expressions 183
11.5.4 Logical Operators 183
11.5.5 Manipulating operands 183
11.5.6 Operand vector allocation 184
11.5.7 Operand validation 184
11.5.8 Statement validation 185
11.6 Manipulating GIMPLE statements 185
11.6.1 Common accessors 186
11.7 Tuple specific accessors 188
11.7.1 `GIMPLE_ASM` 188
11.7.2 `GIMPLE_ASSIGN` 189
11.7.3 `GIMPLE_BIND` 191
11.7.4 `GIMPLE_CALL` 191
11.7.5 `GIMPLE_CATCH` 193
11.7.6 `GIMPLE_COND` 193
11.7.7 `GIMPLE_DEBUG` 194
11.7.8 `GIMPLE_EH_FILTER` 195
11.7.9 `GIMPLE_LABEL` 196
11.7.10 `GIMPLE_NOP` 196
11.7.11 `GIMPLE_OMP_ATOMIC_LOAD` 197
11.7.12 `GIMPLE_OMP_ATOMIC_STORE` 197
11.7.13 `GIMPLE_OMP_CONTINUE` 197
11.7.14 `GIMPLE_OMP_CRITICAL` 198
11.7.15 `GIMPLE_OMP_FOR` 198
11.7.16 `GIMPLE_OMP_MASTER` 199
11.7.17 `GIMPLE_OMP_ORDERED` 199
11.7.18 `GIMPLE_OMP_PARALLEL` 200
11.7.19 `GIMPLE_OMP_RETURN` 201
11.7.20 `GIMPLE_OMP_SECTION` 201
11.7.21 `GIMPLE_OMP_SECTIONS` 201
11.7.22 `GIMPLE_OMP_SINGLE` 202
11.7.23 `GIMPLE_PHI` 202
11.7.24 `GIMPLE_RESX` 202
11.7.25 `GIMPLE_RETURN` 203
11.7.26 `GIMPLE_SWITCH` 203
11.7.27 `GIMPLE_TRY` 204
11.7.28 `GIMPLE_WITH_CLEANUP_EXPR` 204

11.8 GIMPLE sequences . . . 205
11.9 Sequence iterators . . . 206
11.10 Adding a new GIMPLE statement code . . . 209
11.11 Statement and operand traversals . . . 209

12 Analysis and Optimization of GIMPLE tuples . . . 211

12.1 Annotations . . . 211
12.2 SSA Operands . . . 211
12.2.1 Operand Iterators And Access Routines . . . 213
12.2.2 Immediate Uses . . . 215
12.3 Static Single Assignment . . . 216
12.3.1 Preserving the SSA form . . . 217
12.3.2 Preserving the virtual SSA form . . . 219
12.3.3 Examining `SSA_NAME` nodes . . . 219
12.3.4 Walking the dominator tree . . . 220
12.4 Alias analysis . . . 220
12.5 Memory model . . . 222

13 RTL Representation . . . 223

13.1 RTL Object Types . . . 223
13.2 RTL Classes and Formats . . . 224
13.3 Access to Operands . . . 226
13.4 Access to Special Operands . . . 227
13.5 Flags in an RTL Expression . . . 230
13.6 Machine Modes . . . 235
13.7 Constant Expression Types . . . 240
13.8 Registers and Memory . . . 243
13.9 RTL Expressions for Arithmetic . . . 249
13.10 Comparison Operations . . . 253
13.11 Bit-Fields . . . 254
13.12 Vector Operations . . . 255
13.13 Conversions . . . 255
13.14 Declarations . . . 257
13.15 Side Effect Expressions . . . 257
13.16 Embedded Side-Effects on Addresses . . . 263
13.17 Assembler Instructions as Expressions . . . 264
13.18 Variable Location Debug Information in RTL . . . 264
13.19 Insns . . . 265
13.20 RTL Representation of Function-Call Insns . . . 273
13.21 Structure Sharing Assumptions . . . 274
13.22 Reading RTL . . . 275

14 Control Flow Graph ... 277

14.1 Basic Blocks ... 277
14.2 Edges ... 279
14.3 Profile information ... 282
14.4 Maintaining the CFG ... 283
14.5 Liveness information ... 285

15 Analysis and Representation of Loops ... 287

15.1 Loop representation ... 287
15.2 Loop querying ... 289
15.3 Loop manipulation ... 290
15.4 Loop-closed SSA form ... 290
15.5 Scalar evolutions ... 291
15.6 IV analysis on RTL ... 292
15.7 Number of iterations analysis ... 292
15.8 Data Dependency Analysis ... 293
15.9 Omega a solver for linear programming problems ... 295

16 Machine Descriptions ... 297

16.1 Overview of How the Machine Description is Used ... 297
16.2 Everything about Instruction Patterns ... 297
16.3 Example of `define_insn` ... 298
16.4 RTL Template ... 299
16.5 Output Templates and Operand Substitution ... 303
16.6 C Statements for Assembler Output ... 304
16.7 Predicates ... 305
16.7.1 Machine-Independent Predicates ... 306
16.7.2 Defining Machine-Specific Predicates ... 308
16.8 Operand Constraints ... 310
16.8.1 Simple Constraints ... 310
16.8.2 Multiple Alternative Constraints ... 314
16.8.3 Register Class Preferences ... 315
16.8.4 Constraint Modifier Characters ... 315
16.8.5 Constraints for Particular Machines ... 317
16.8.6 Disable insn alternatives using the `enabled` attribute ... 345
16.8.7 Defining Machine-Specific Constraints ... 346
16.8.8 Testing constraints from C ... 348
16.9 Standard Pattern Names For Generation ... 349
16.10 When the Order of Patterns Matters ... 379
16.11 Interdependence of Patterns ... 379
16.12 Defining Jump Instruction Patterns ... 380
16.13 Defining Looping Instruction Patterns ... 380
16.14 Canonicalization of Instructions ... 382
16.15 Defining RTL Sequences for Code Generation ... 383
16.16 Defining How to Split Instructions ... 386
16.17 Including Patterns in Machine Descriptions ... 389
16.17.1 RTL Generation Tool Options for Directory Search ... 390

16.18 Machine-Specific Peephole Optimizers . . . 390
16.18.1 RTL to Text Peephole Optimizers . . . 391
16.18.2 RTL to RTL Peephole Optimizers . . . 393
16.19 Instruction Attributes . . . 394
16.19.1 Defining Attributes and their Values . . . 394
16.19.2 Attribute Expressions . . . 396
16.19.3 Assigning Attribute Values to Insns . . . 398
16.19.4 Example of Attribute Specifications . . . 400
16.19.5 Computing the Length of an Insn . . . 401
16.19.6 Constant Attributes . . . 402
16.19.7 Mnemonic Attribute . . . 402
16.19.8 Delay Slot Scheduling . . . 403
16.19.9 Specifying processor pipeline description . . . 404
16.20 Conditional Execution . . . 409
16.21 RTL Templates Transformations . . . 411
16.21.1 `define_subst` Example . . . 411
16.21.2 Pattern Matching in `define_subst` . . . 412
16.21.3 Generation of output template in `define_subst` . . . 413
16.22 Constant Definitions . . . 413
16.23 Iterators . . . 415
16.23.1 Mode Iterators . . . 415
16.23.1.1 Defining Mode Iterators . . . 416
16.23.1.2 Substitution in Mode Iterators . . . 416
16.23.1.3 Mode Iterator Examples . . . 417
16.23.2 Code Iterators . . . 417
16.23.3 Int Iterators . . . 419
16.23.4 Subst Iterators . . . 420

17 Target Description Macros and Functions . . . 421

17.1 The Global `targetm` Variable . . . 421
17.2 Controlling the Compilation Driver, '`gcc`' . . . 422
17.3 Run-time Target Specification . . . 428
17.4 Defining data structures for per-function information. . . . 431
17.5 Storage Layout . . . 432
17.6 Layout of Source Language Data Types . . . 441
17.7 Register Usage . . . 447
17.7.1 Basic Characteristics of Registers . . . 447
17.7.2 Order of Allocation of Registers . . . 449
17.7.3 How Values Fit in Registers . . . 450
17.7.4 Handling Leaf Functions . . . 452
17.7.5 Registers That Form a Stack . . . 453
17.8 Register Classes . . . 453
17.9 Obsolete Macros for Defining Constraints . . . 463
17.10 Stack Layout and Calling Conventions . . . 465
17.10.1 Basic Stack Layout . . . 465
17.10.2 Exception Handling Support . . . 469
17.10.3 Specifying How Stack Checking is Done . . . 471

17.10.4 Registers That Address the Stack Frame 472
17.10.5 Eliminating Frame Pointer and Arg Pointer 475
17.10.6 Passing Function Arguments on the Stack 476
17.10.7 Passing Arguments in Registers 478
17.10.8 How Scalar Function Values Are Returned 484
17.10.9 How Large Values Are Returned 486
17.10.10 Caller-Saves Register Allocation 488
17.10.11 Function Entry and Exit 488
17.10.12 Generating Code for Profiling 491
17.10.13 Permitting tail calls 492
17.10.14 Stack smashing protection 493
17.11 Implementing the Varargs Macros 493
17.12 Trampolines for Nested Functions 495
17.13 Implicit Calls to Library Routines 497
17.14 Addressing Modes 499
17.15 Anchored Addresses 505
17.16 Condition Code Status 506
17.16.1 Representation of condition codes using `(cc0)` 507
17.16.2 Representation of condition codes using registers 508
17.17 Describing Relative Costs of Operations 510
17.18 Adjusting the Instruction Scheduler 515
17.19 Dividing the Output into Sections (Texts, Data, . . .) 521
17.20 Position Independent Code 527
17.21 Defining the Output Assembler Language 527
17.21.1 The Overall Framework of an Assembler File 527
17.21.2 Output of Data 531
17.21.3 Output of Uninitialized Variables 533
17.21.4 Output and Generation of Labels 535
17.21.5 How Initialization Functions Are Handled 542
17.21.6 Macros Controlling Initialization Routines 544
17.21.7 Output of Assembler Instructions 546
17.21.8 Output of Dispatch Tables 550
17.21.9 Assembler Commands for Exception Regions 551
17.21.10 Assembler Commands for Alignment 553
17.22 Controlling Debugging Information Format 555
17.22.1 Macros Affecting All Debugging Formats 555
17.22.2 Specific Options for DBX Output 556
17.22.3 Open-Ended Hooks for DBX Format 558
17.22.4 File Names in DBX Format 558
17.22.5 Macros for SDB and DWARF Output 559
17.22.6 Macros for VMS Debug Format 562
17.23 Cross Compilation and Floating Point 562
17.24 Mode Switching Instructions 563
17.25 Defining target-specific uses of `__attribute__` 565
17.26 Emulating TLS 567
17.27 Defining coprocessor specifics for MIPS targets. 569
17.28 Parameters for Precompiled Header Validity Checking 569
17.29 C++ ABI parameters 570

17.30 Adding support for named address spaces ... 571
17.31 Miscellaneous Parameters ... 573

18 Host Configuration ... 591

18.1 Host Common ... 591
18.2 Host Filesystem ... 592
18.3 Host Misc ... 593

19 Makefile Fragments ... 595

19.1 Target Makefile Fragments ... 595
19.2 Host Makefile Fragments ... 598

20 `collect2` ... 599

21 Standard Header File Directories ... 601

22 Memory Management and Type Information ... 603

22.1 The Inside of a `GTY(())` ... 604
22.2 Support for inheritance ... 609
22.3 Support for user-provided GC marking routines ... 610
22.3.1 User-provided marking routines for template types ... 610
22.4 Marking Roots for the Garbage Collector ... 611
22.5 Source Files Containing Type Information ... 611
22.6 How to invoke the garbage collector ... 612
22.7 Troubleshooting the garbage collector ... 613

23 Plugins ... 615

23.1 Loading Plugins ... 615
23.2 Plugin API ... 615
23.2.1 Plugin license check ... 615
23.2.2 Plugin initialization ... 615
23.2.3 Plugin callbacks ... 616
23.3 Interacting with the pass manager ... 618
23.4 Interacting with the GCC Garbage Collector ... 619
23.5 Giving information about a plugin ... 619
23.6 Registering custom attributes or pragmas ... 619
23.7 Recording information about pass execution ... 620
23.8 Controlling which passes are being run ... 621
23.9 Keeping track of available passes ... 621
23.10 Building GCC plugins ... 621

24 Link Time Optimization **623**
24.1 Design Overview 623
24.1.1 LTO modes of operation 624
24.2 LTO file sections 624
24.3 Using summary information in IPA passes 626
24.3.1 Virtual clones 627
24.3.2 IPA references 628
24.3.3 Jump functions 628
24.4 Whole program assumptions, linker plugin and symbol visibilities 628
24.5 Internal flags controlling `lto1` 630

Funding Free Software **631**

The GNU Project and GNU/Linux **633**

GNU General Public License **635**

GNU Free Documentation License **647**
ADDENDUM: How to use this License for your documents 654

Contributors to GCC **655**

Option Index **671**

Concept Index **673**

Introduction

This manual documents the internals of the GNU compilers, including how to port them to new targets and some information about how to write front ends for new languages. It corresponds to the compilers (GCC) version 4.10.0. The use of the GNU compilers is documented in a separate manual. See Section "Introduction" in *Using the GNU Compiler Collection (GCC)*.

This manual is mainly a reference manual rather than a tutorial. It discusses how to contribute to GCC (see Chapter 1 [Contributing], page 3), the characteristics of the machines supported by GCC as hosts and targets (see Chapter 2 [Portability], page 5), how GCC relates to the ABIs on such systems (see Chapter 3 [Interface], page 7), and the characteristics of the languages for which GCC front ends are written (see Chapter 5 [Languages], page 59). It then describes the GCC source tree structure and build system, some of the interfaces to GCC front ends, and how support for a target system is implemented in GCC.

Additional tutorial information is linked to from `http://gcc.gnu.org/readings.html`.

1 Contributing to GCC Development

If you would like to help pretest GCC releases to assure they work well, current development sources are available by SVN (see http://gcc.gnu.org/svn.html). Source and binary snapshots are also available for FTP; see http://gcc.gnu.org/snapshots.html.

If you would like to work on improvements to GCC, please read the advice at these URLs:

http://gcc.gnu.org/contribute.html
http://gcc.gnu.org/contributewhy.html

for information on how to make useful contributions and avoid duplication of effort. Suggested projects are listed at http://gcc.gnu.org/projects/.

2 GCC and Portability

GCC itself aims to be portable to any machine where `int` is at least a 32-bit type. It aims to target machines with a flat (non-segmented) byte addressed data address space (the code address space can be separate). Target ABIs may have 8, 16, 32 or 64-bit `int` type. `char` can be wider than 8 bits.

GCC gets most of the information about the target machine from a machine description which gives an algebraic formula for each of the machine's instructions. This is a very clean way to describe the target. But when the compiler needs information that is difficult to express in this fashion, ad-hoc parameters have been defined for machine descriptions. The purpose of portability is to reduce the total work needed on the compiler; it was not of interest for its own sake.

GCC does not contain machine dependent code, but it does contain code that depends on machine parameters such as endianness (whether the most significant byte has the highest or lowest address of the bytes in a word) and the availability of autoincrement addressing. In the RTL-generation pass, it is often necessary to have multiple strategies for generating code for a particular kind of syntax tree, strategies that are usable for different combinations of parameters. Often, not all possible cases have been addressed, but only the common ones or only the ones that have been encountered. As a result, a new target may require additional strategies. You will know if this happens because the compiler will call `abort`. Fortunately, the new strategies can be added in a machine-independent fashion, and will affect only the target machines that need them.

3 Interfacing to GCC Output

GCC is normally configured to use the same function calling convention normally in use on the target system. This is done with the machine-description macros described (see Chapter 17 [Target Macros], page 421).

However, returning of structure and union values is done differently on some target machines. As a result, functions compiled with PCC returning such types cannot be called from code compiled with GCC, and vice versa. This does not cause trouble often because few Unix library routines return structures or unions.

GCC code returns structures and unions that are 1, 2, 4 or 8 bytes long in the same registers used for `int` or `double` return values. (GCC typically allocates variables of such types in registers also.) Structures and unions of other sizes are returned by storing them into an address passed by the caller (usually in a register). The target hook `TARGET_STRUCT_VALUE_RTX` tells GCC where to pass this address.

By contrast, PCC on most target machines returns structures and unions of any size by copying the data into an area of static storage, and then returning the address of that storage as if it were a pointer value. The caller must copy the data from that memory area to the place where the value is wanted. This is slower than the method used by GCC, and fails to be reentrant.

On some target machines, such as RISC machines and the 80386, the standard system convention is to pass to the subroutine the address of where to return the value. On these machines, GCC has been configured to be compatible with the standard compiler, when this method is used. It may not be compatible for structures of 1, 2, 4 or 8 bytes.

GCC uses the system's standard convention for passing arguments. On some machines, the first few arguments are passed in registers; in others, all are passed on the stack. It would be possible to use registers for argument passing on any machine, and this would probably result in a significant speedup. But the result would be complete incompatibility with code that follows the standard convention. So this change is practical only if you are switching to GCC as the sole C compiler for the system. We may implement register argument passing on certain machines once we have a complete GNU system so that we can compile the libraries with GCC.

On some machines (particularly the SPARC), certain types of arguments are passed "by invisible reference". This means that the value is stored in memory, and the address of the memory location is passed to the subroutine.

If you use `longjmp`, beware of automatic variables. ISO C says that automatic variables that are not declared `volatile` have undefined values after a `longjmp`. And this is all GCC promises to do, because it is very difficult to restore register variables correctly, and one of GCC's features is that it can put variables in registers without your asking it to.

4 The GCC low-level runtime library

GCC provides a low-level runtime library, '`libgcc.a`' or '`libgcc_s.so.1`' on some platforms. GCC generates calls to routines in this library automatically, whenever it needs to perform some operation that is too complicated to emit inline code for.

Most of the routines in `libgcc` handle arithmetic operations that the target processor cannot perform directly. This includes integer multiply and divide on some machines, and all floating-point and fixed-point operations on other machines. `libgcc` also includes routines for exception handling, and a handful of miscellaneous operations.

Some of these routines can be defined in mostly machine-independent C. Others must be hand-written in assembly language for each processor that needs them.

GCC will also generate calls to C library routines, such as `memcpy` and `memset`, in some cases. The set of routines that GCC may possibly use is documented in Section "Other Builtins" in *Using the GNU Compiler Collection (GCC)*.

These routines take arguments and return values of a specific machine mode, not a specific C type. See Section 13.6 [Machine Modes], page 235, for an explanation of this concept. For illustrative purposes, in this chapter the floating point type `float` is assumed to correspond to `SFmode`; `double` to `DFmode`; and `long double` to both `TFmode` and `XFmode`. Similarly, the integer types `int` and `unsigned int` correspond to `SImode`; `long` and `unsigned long` to `DImode`; and `long long` and `unsigned long long` to `TImode`.

4.1 Routines for integer arithmetic

The integer arithmetic routines are used on platforms that don't provide hardware support for arithmetic operations on some modes.

4.1.1 Arithmetic functions

`int __ashlsi3` (*int* `a`, *int* `b`) [Runtime Function]
`long __ashldi3` (*long* `a`, *int* `b`) [Runtime Function]
`long long __ashlti3` (*long long* `a`, *int* `b`) [Runtime Function]

These functions return the result of shifting *a* left by *b* bits.

`int __ashrsi3` (*int* `a`, *int* `b`) [Runtime Function]
`long __ashrdi3` (*long* `a`, *int* `b`) [Runtime Function]
`long long __ashrti3` (*long long* `a`, *int* `b`) [Runtime Function]

These functions return the result of arithmetically shifting *a* right by *b* bits.

`int __divsi3` (*int* `a`, *int* `b`) [Runtime Function]
`long __divdi3` (*long* `a`, *long* `b`) [Runtime Function]
`long long __divti3` (*long long* `a`, *long long* `b`) [Runtime Function]

These functions return the quotient of the signed division of *a* and *b*.

`int __lshrsi3` (*int* `a`, *int* `b`) [Runtime Function]
`long __lshrdi3` (*long* `a`, *int* `b`) [Runtime Function]
`long long __lshrti3` (*long long* `a`, *int* `b`) [Runtime Function]

These functions return the result of logically shifting *a* right by *b* bits.

`int __modsi3` (*int* `a`, *int* `b`) [Runtime Function]
`long __moddi3` (*long* `a`, *long* `b`) [Runtime Function]
`long long __modti3` (*long long* `a`, *long long* `b`) [Runtime Function]

These functions return the remainder of the signed division of *a* and *b*.

`int __mulsi3` (*int* `a`, *int* `b`) [Runtime Function]
`long __muldi3` (*long* `a`, *long* `b`) [Runtime Function]
`long long __multi3` (*long long* `a`, *long long* `b`) [Runtime Function]

These functions return the product of *a* and *b*.

`long __negdi2` (*long* `a`) [Runtime Function]
`long long __negti2` (*long long* `a`) [Runtime Function]

These functions return the negation of *a*.

`unsigned int __udivsi3` (*unsigned int* `a`, *unsigned int* `b`) [Runtime Function]
`unsigned long __udivdi3` (*unsigned long* `a`, *unsigned long* `b`) [Runtime Function]
`unsigned long long __udivti3` (*unsigned long long* `a`, *unsigned long long* `b`) [Runtime Function]

These functions return the quotient of the unsigned division of *a* and *b*.

`unsigned long __udivmoddi4` (*unsigned long* `a`, *unsigned long* `b`, *unsigned long* `*c`) [Runtime Function]
`unsigned long long __udivmodti4` (*unsigned long long* `a`, *unsigned long long* `b`, *unsigned long long* `*c`) [Runtime Function]

These functions calculate both the quotient and remainder of the unsigned division of *a* and *b*. The return value is the quotient, and the remainder is placed in variable pointed to by *c*.

`unsigned int __umodsi3` (*unsigned int* `a`, *unsigned int* `b`) [Runtime Function]
`unsigned long __umoddi3` (*unsigned long* `a`, *unsigned long* `b`) [Runtime Function]
`unsigned long long __umodti3` (*unsigned long long* `a`, *unsigned long long* `b`) [Runtime Function]

These functions return the remainder of the unsigned division of *a* and *b*.

4.1.2 Comparison functions

The following functions implement integral comparisons. These functions implement a low-level compare, upon which the higher level comparison operators (such as less than and greater than or equal to) can be constructed. The returned values lie in the range zero to two, to allow the high-level operators to be implemented by testing the returned result using either signed or unsigned comparison.

`int __cmpdi2` (*long* `a`, *long* `b`) [Runtime Function]
`int __cmpti2` (*long long* `a`, *long long* `b`) [Runtime Function]

These functions perform a signed comparison of *a* and *b*. If *a* is less than *b*, they return 0; if *a* is greater than *b*, they return 2; and if *a* and *b* are equal they return 1.

`int __ucmpdi2` (*unsigned long* `a`, *unsigned long* `b`) [Runtime Function]
`int __ucmpti2` (*unsigned long long* `a`, *unsigned long long* `b`) [Runtime Function]

These functions perform an unsigned comparison of *a* and *b*. If *a* is less than *b*, they return 0; if *a* is greater than *b*, they return 2; and if *a* and *b* are equal they return 1.

4.1.3 Trapping arithmetic functions

The following functions implement trapping arithmetic. These functions call the libc function `abort` upon signed arithmetic overflow.

`int __absvsi2` (*int* `a`) [Runtime Function]
`long __absvdi2` (*long* `a`) [Runtime Function]

These functions return the absolute value of *a*.

`int __addvsi3` (*int* `a`, *int* `b`) [Runtime Function]
`long __addvdi3` (*long* `a`, *long* `b`) [Runtime Function]

These functions return the sum of *a* and *b*; that is `a + b`.

`int __mulvsi3` (*int* `a`, *int* `b`) [Runtime Function]
`long __mulvdi3` (*long* `a`, *long* `b`) [Runtime Function]

The functions return the product of *a* and *b*; that is `a * b`.

`int __negvsi2` (*int* `a`) [Runtime Function]
`long __negvdi2` (*long* `a`) [Runtime Function]

These functions return the negation of *a*; that is `-a`.

`int __subvsi3` (*int* `a`, *int* `b`) [Runtime Function]
`long __subvdi3` (*long* `a`, *long* `b`) [Runtime Function]

These functions return the difference between *b* and *a*; that is `a - b`.

4.1.4 Bit operations

`int __clzsi2` (*int* `a`) [Runtime Function]
`int __clzdi2` (*long* `a`) [Runtime Function]
`int __clzti2` (*long long* `a`) [Runtime Function]

These functions return the number of leading 0-bits in *a*, starting at the most significant bit position. If *a* is zero, the result is undefined.

`int __ctzsi2` (*int* `a`) [Runtime Function]
`int __ctzdi2` (*long* `a`) [Runtime Function]
`int __ctzti2` (*long long* `a`) [Runtime Function]

These functions return the number of trailing 0-bits in *a*, starting at the least significant bit position. If *a* is zero, the result is undefined.

`int __ffsdi2` (*long* `a`) [Runtime Function]
`int __ffsti2` (*long long* `a`) [Runtime Function]

These functions return the index of the least significant 1-bit in *a*, or the value zero if *a* is zero. The least significant bit is index one.

`int __paritysi2` (*int* `a`) [Runtime Function]
`int __paritydi2` (*long* `a`) [Runtime Function]
`int __parityti2` (*long long* `a`) [Runtime Function]

These functions return the value zero if the number of bits set in *a* is even, and the value one otherwise.

`int __popcountsi2 (int a)` [Runtime Function]
`int __popcountdi2 (long a)` [Runtime Function]
`int __popcountdi2 (long long a)` [Runtime Function]

These functions return the number of bits set in *a*.

`int32_t __bswapsi2 (int32_t a)` [Runtime Function]
`int64_t __bswapdi2 (int64_t a)` [Runtime Function]

These functions return the *a* byteswapped.

4.2 Routines for floating point emulation

The software floating point library is used on machines which do not have hardware support for floating point. It is also used whenever '`-msoft-float`' is used to disable generation of floating point instructions. (Not all targets support this switch.)

For compatibility with other compilers, the floating point emulation routines can be renamed with the `DECLARE_LIBRARY_RENAMES` macro (see Section 17.13 [Library Calls], page 497). In this section, the default names are used.

Presently the library does not support `XFmode`, which is used for `long double` on some architectures.

4.2.1 Arithmetic functions

`float __addsf3 (float a, float b)` [Runtime Function]
`double __adddf3 (double a, double b)` [Runtime Function]
`long double __addtf3 (long double a, long double b)` [Runtime Function]
`long double __addxf3 (long double a, long double b)` [Runtime Function]

These functions return the sum of *a* and *b*.

`float __subsf3 (float a, float b)` [Runtime Function]
`double __subdf3 (double a, double b)` [Runtime Function]
`long double __subtf3 (long double a, long double b)` [Runtime Function]
`long double __subxf3 (long double a, long double b)` [Runtime Function]

These functions return the difference between *b* and *a*; that is, $a - b$.

`float __mulsf3 (float a, float b)` [Runtime Function]
`double __muldf3 (double a, double b)` [Runtime Function]
`long double __multf3 (long double a, long double b)` [Runtime Function]
`long double __mulxf3 (long double a, long double b)` [Runtime Function]

These functions return the product of *a* and *b*.

`float __divsf3 (float a, float b)` [Runtime Function]
`double __divdf3 (double a, double b)` [Runtime Function]
`long double __divtf3 (long double a, long double b)` [Runtime Function]
`long double __divxf3 (long double a, long double b)` [Runtime Function]

These functions return the quotient of *a* and *b*; that is, a/b.

`float __negsf2 (float a)` [Runtime Function]
`double __negdf2 (double a)` [Runtime Function]
`long double __negtf2 (long double a)` [Runtime Function]

`long double __negxf2` (*long double* `a`) [Runtime Function]

These functions return the negation of *a*. They simply flip the sign bit, so they can produce negative zero and negative NaN.

4.2.2 Conversion functions

`double __extendsfdf2` (*float* `a`) [Runtime Function]
`long double __extendsftf2` (*float* `a`) [Runtime Function]
`long double __extendsfxf2` (*float* `a`) [Runtime Function]
`long double __extenddftf2` (*double* `a`) [Runtime Function]
`long double __extenddfxf2` (*double* `a`) [Runtime Function]

These functions extend *a* to the wider mode of their return type.

`double __truncxfdf2` (*long double* `a`) [Runtime Function]
`double __trunctfdf2` (*long double* `a`) [Runtime Function]
`float __truncxfsf2` (*long double* `a`) [Runtime Function]
`float __trunctfsf2` (*long double* `a`) [Runtime Function]
`float __truncdfsf2` (*double* `a`) [Runtime Function]

These functions truncate *a* to the narrower mode of their return type, rounding toward zero.

`int __fixsfsi` (*float* `a`) [Runtime Function]
`int __fixdfsi` (*double* `a`) [Runtime Function]
`int __fixtfsi` (*long double* `a`) [Runtime Function]
`int __fixxfsi` (*long double* `a`) [Runtime Function]

These functions convert *a* to a signed integer, rounding toward zero.

`long __fixsfdi` (*float* `a`) [Runtime Function]
`long __fixdfdi` (*double* `a`) [Runtime Function]
`long __fixtfdi` (*long double* `a`) [Runtime Function]
`long __fixxfdi` (*long double* `a`) [Runtime Function]

These functions convert *a* to a signed long, rounding toward zero.

`long long __fixsfti` (*float* `a`) [Runtime Function]
`long long __fixdfti` (*double* `a`) [Runtime Function]
`long long __fixtfti` (*long double* `a`) [Runtime Function]
`long long __fixxfti` (*long double* `a`) [Runtime Function]

These functions convert *a* to a signed long long, rounding toward zero.

`unsigned int __fixunssfsi` (*float* `a`) [Runtime Function]
`unsigned int __fixunsdfsi` (*double* `a`) [Runtime Function]
`unsigned int __fixunstfsi` (*long double* `a`) [Runtime Function]
`unsigned int __fixunsxfsi` (*long double* `a`) [Runtime Function]

These functions convert *a* to an unsigned integer, rounding toward zero. Negative values all become zero.

`unsigned long __fixunssfdi` (*float* `a`) [Runtime Function]
`unsigned long __fixunsdfdi` (*double* `a`) [Runtime Function]
`unsigned long __fixunstfdi` (*long double* `a`) [Runtime Function]

`unsigned long __fixunsxfdi` (*long double* `a`) [Runtime Function]

These functions convert *a* to an unsigned long, rounding toward zero. Negative values all become zero.

`unsigned long long __fixunssfti` (*float* `a`) [Runtime Function]
`unsigned long long __fixunsdfti` (*double* `a`) [Runtime Function]
`unsigned long long __fixunstfti` (*long double* `a`) [Runtime Function]
`unsigned long long __fixunsxfti` (*long double* `a`) [Runtime Function]

These functions convert *a* to an unsigned long long, rounding toward zero. Negative values all become zero.

`float __floatsisf` (*int* `i`) [Runtime Function]
`double __floatsidf` (*int* `i`) [Runtime Function]
`long double __floatsitf` (*int* `i`) [Runtime Function]
`long double __floatsixf` (*int* `i`) [Runtime Function]

These functions convert *i*, a signed integer, to floating point.

`float __floatdisf` (*long* `i`) [Runtime Function]
`double __floatdidf` (*long* `i`) [Runtime Function]
`long double __floatditf` (*long* `i`) [Runtime Function]
`long double __floatdixf` (*long* `i`) [Runtime Function]

These functions convert *i*, a signed long, to floating point.

`float __floattisf` (*long long* `i`) [Runtime Function]
`double __floattidf` (*long long* `i`) [Runtime Function]
`long double __floattitf` (*long long* `i`) [Runtime Function]
`long double __floattixf` (*long long* `i`) [Runtime Function]

These functions convert *i*, a signed long long, to floating point.

`float __floatunsisf` (*unsigned int* `i`) [Runtime Function]
`double __floatunsidf` (*unsigned int* `i`) [Runtime Function]
`long double __floatunsitf` (*unsigned int* `i`) [Runtime Function]
`long double __floatunsixf` (*unsigned int* `i`) [Runtime Function]

These functions convert *i*, an unsigned integer, to floating point.

`float __floatundisf` (*unsigned long* `i`) [Runtime Function]
`double __floatundidf` (*unsigned long* `i`) [Runtime Function]
`long double __floatunditf` (*unsigned long* `i`) [Runtime Function]
`long double __floatundixf` (*unsigned long* `i`) [Runtime Function]

These functions convert *i*, an unsigned long, to floating point.

`float __floatuntisf` (*unsigned long long* `i`) [Runtime Function]
`double __floatuntidf` (*unsigned long long* `i`) [Runtime Function]
`long double __floatuntitf` (*unsigned long long* `i`) [Runtime Function]
`long double __floatuntixf` (*unsigned long long* `i`) [Runtime Function]

These functions convert *i*, an unsigned long long, to floating point.

4.2.3 Comparison functions

There are two sets of basic comparison functions.

`int __cmpsf2` (*float* `a`, *float* `b`) [Runtime Function]
`int __cmpdf2` (*double* `a`, *double* `b`) [Runtime Function]
`int __cmptf2` (*long double* `a`, *long double* `b`) [Runtime Function]

These functions calculate $a <=> b$. That is, if a is less than b, they return -1; if a is greater than b, they return 1; and if a and b are equal they return 0. If either argument is NaN they return 1, but you should not rely on this; if NaN is a possibility, use one of the higher-level comparison functions.

`int __unordsf2` (*float* `a`, *float* `b`) [Runtime Function]
`int __unorddf2` (*double* `a`, *double* `b`) [Runtime Function]
`int __unordtf2` (*long double* `a`, *long double* `b`) [Runtime Function]

These functions return a nonzero value if either argument is NaN, otherwise 0.

There is also a complete group of higher level functions which correspond directly to comparison operators. They implement the ISO C semantics for floating-point comparisons, taking NaN into account. Pay careful attention to the return values defined for each set. Under the hood, all of these routines are implemented as

```
if (__unordXf2 (a, b))
  return E;
return __cmpXf2 (a, b);
```

where E is a constant chosen to give the proper behavior for NaN. Thus, the meaning of the return value is different for each set. Do not rely on this implementation; only the semantics documented below are guaranteed.

`int __eqsf2` (*float* `a`, *float* `b`) [Runtime Function]
`int __eqdf2` (*double* `a`, *double* `b`) [Runtime Function]
`int __eqtf2` (*long double* `a`, *long double* `b`) [Runtime Function]

These functions return zero if neither argument is NaN, and a and b are equal.

`int __nesf2` (*float* `a`, *float* `b`) [Runtime Function]
`int __nedf2` (*double* `a`, *double* `b`) [Runtime Function]
`int __netf2` (*long double* `a`, *long double* `b`) [Runtime Function]

These functions return a nonzero value if either argument is NaN, or if a and b are unequal.

`int __gesf2` (*float* `a`, *float* `b`) [Runtime Function]
`int __gedf2` (*double* `a`, *double* `b`) [Runtime Function]
`int __getf2` (*long double* `a`, *long double* `b`) [Runtime Function]

These functions return a value greater than or equal to zero if neither argument is NaN, and a is greater than or equal to b.

`int __ltsf2` (*float* `a`, *float* `b`) [Runtime Function]
`int __ltdf2` (*double* `a`, *double* `b`) [Runtime Function]
`int __lttf2` (*long double* `a`, *long double* `b`) [Runtime Function]

These functions return a value less than zero if neither argument is NaN, and a is strictly less than b.

`int __lesf2` (*float* `a`, *float* `b`) [Runtime Function]
`int __ledf2` (*double* `a`, *double* `b`) [Runtime Function]
`int __letf2` (*long double* `a`, *long double* `b`) [Runtime Function]

These functions return a value less than or equal to zero if neither argument is NaN, and a is less than or equal to b.

`int __gtsf2` (*float* `a`, *float* `b`) [Runtime Function]
`int __gtdf2` (*double* `a`, *double* `b`) [Runtime Function]
`int __gttf2` (*long double* `a`, *long double* `b`) [Runtime Function]

These functions return a value greater than zero if neither argument is NaN, and a is strictly greater than b.

4.2.4 Other floating-point functions

`float __powisf2` (*float* `a`, *int* `b`) [Runtime Function]
`double __powidf2` (*double* `a`, *int* `b`) [Runtime Function]
`long double __powitf2` (*long double* `a`, *int* `b`) [Runtime Function]
`long double __powixf2` (*long double* `a`, *int* `b`) [Runtime Function]

These functions convert raise a to the power b.

`complex float __mulsc3` (*float* `a`, *float* `b`, *float* `c`, *float* `d`) [Runtime Function]
`complex double __muldc3` (*double* `a`, *double* `b`, *double* `c`, *double* `d`) [Runtime Function]
`complex long double __multc3` (*long double* `a`, *long double* `b`, *long double* `c`, *long double* `d`) [Runtime Function]
`complex long double __mulxc3` (*long double* `a`, *long double* `b`, *long double* `c`, *long double* `d`) [Runtime Function]

These functions return the product of $a + ib$ and $c + id$, following the rules of C99 Annex G.

`complex float __divsc3` (*float* `a`, *float* `b`, *float* `c`, *float* `d`) [Runtime Function]
`complex double __divdc3` (*double* `a`, *double* `b`, *double* `c`, *double* `d`) [Runtime Function]
`complex long double __divtc3` (*long double* `a`, *long double* `b`, *long double* `c`, *long double* `d`) [Runtime Function]
`complex long double __divxc3` (*long double* `a`, *long double* `b`, *long double* `c`, *long double* `d`) [Runtime Function]

These functions return the quotient of $a + ib$ and $c + id$ (i.e., $(a + ib)/(c + id)$), following the rules of C99 Annex G.

4.3 Routines for decimal floating point emulation

The software decimal floating point library implements IEEE 754-2008 decimal floating point arithmetic and is only activated on selected targets.

The software decimal floating point library supports either DPD (Densely Packed Decimal) or BID (Binary Integer Decimal) encoding as selected at configure time.

4.3.1 Arithmetic functions

`_Decimal32 __dpd_addsd3 (_Decimal32 a, _Decimal32 b)` [Runtime Function]
`_Decimal32 __bid_addsd3 (_Decimal32 a, _Decimal32 b)` [Runtime Function]
`_Decimal64 __dpd_adddd3 (_Decimal64 a, _Decimal64 b)` [Runtime Function]
`_Decimal64 __bid_adddd3 (_Decimal64 a, _Decimal64 b)` [Runtime Function]
`_Decimal128 __dpd_addtd3 (_Decimal128 a, _Decimal128 b)` [Runtime Function]
`_Decimal128 __bid_addtd3 (_Decimal128 a, _Decimal128 b)` [Runtime Function]

These functions return the sum of a and b.

`_Decimal32 __dpd_subsd3 (_Decimal32 a, _Decimal32 b)` [Runtime Function]
`_Decimal32 __bid_subsd3 (_Decimal32 a, _Decimal32 b)` [Runtime Function]
`_Decimal64 __dpd_subdd3 (_Decimal64 a, _Decimal64 b)` [Runtime Function]
`_Decimal64 __bid_subdd3 (_Decimal64 a, _Decimal64 b)` [Runtime Function]
`_Decimal128 __dpd_subtd3 (_Decimal128 a, _Decimal128 b)` [Runtime Function]
`_Decimal128 __bid_subtd3 (_Decimal128 a, _Decimal128 b)` [Runtime Function]

These functions return the difference between b and a; that is, $a - b$.

`_Decimal32 __dpd_mulsd3 (_Decimal32 a, _Decimal32 b)` [Runtime Function]
`_Decimal32 __bid_mulsd3 (_Decimal32 a, _Decimal32 b)` [Runtime Function]
`_Decimal64 __dpd_muldd3 (_Decimal64 a, _Decimal64 b)` [Runtime Function]
`_Decimal64 __bid_muldd3 (_Decimal64 a, _Decimal64 b)` [Runtime Function]
`_Decimal128 __dpd_multd3 (_Decimal128 a, _Decimal128 b)` [Runtime Function]
`_Decimal128 __bid_multd3 (_Decimal128 a, _Decimal128 b)` [Runtime Function]

These functions return the product of a and b.

`_Decimal32 __dpd_divsd3 (_Decimal32 a, _Decimal32 b)` [Runtime Function]
`_Decimal32 __bid_divsd3 (_Decimal32 a, _Decimal32 b)` [Runtime Function]
`_Decimal64 __dpd_divdd3 (_Decimal64 a, _Decimal64 b)` [Runtime Function]
`_Decimal64 __bid_divdd3 (_Decimal64 a, _Decimal64 b)` [Runtime Function]
`_Decimal128 __dpd_divtd3 (_Decimal128 a, _Decimal128 b)` [Runtime Function]
`_Decimal128 __bid_divtd3 (_Decimal128 a, _Decimal128 b)` [Runtime Function]

These functions return the quotient of a and b; that is, a/b.

`_Decimal32 __dpd_negsd2 (_Decimal32 a)` [Runtime Function]
`_Decimal32 __bid_negsd2 (_Decimal32 a)` [Runtime Function]
`_Decimal64 __dpd_negdd2 (_Decimal64 a)` [Runtime Function]
`_Decimal64 __bid_negdd2 (_Decimal64 a)` [Runtime Function]
`_Decimal128 __dpd_negtd2 (_Decimal128 a)` [Runtime Function]
`_Decimal128 __bid_negtd2 (_Decimal128 a)` [Runtime Function]

These functions return the negation of a. They simply flip the sign bit, so they can produce negative zero and negative NaN.

4.3.2 Conversion functions

`_Decimal64 __dpd_extendsddd2 (_Decimal32 a)` [Runtime Function]
`_Decimal64 __bid_extendsddd2 (_Decimal32 a)` [Runtime Function]
`_Decimal128 __dpd_extendsdtd2 (_Decimal32 a)` [Runtime Function]
`_Decimal128 __bid_extendsdtd2 (_Decimal32 a)` [Runtime Function]

`_Decimal128 __dpd_extendddtd2 (_Decimal64 a)` [Runtime Function]
`_Decimal128 __bid_extendddtd2 (_Decimal64 a)` [Runtime Function]
`_Decimal32 __dpd_truncddsd2 (_Decimal64 a)` [Runtime Function]
`_Decimal32 __bid_truncddsd2 (_Decimal64 a)` [Runtime Function]
`_Decimal32 __dpd_trunctdsd2 (_Decimal128 a)` [Runtime Function]
`_Decimal32 __bid_trunctdsd2 (_Decimal128 a)` [Runtime Function]
`_Decimal64 __dpd_trunctddd2 (_Decimal128 a)` [Runtime Function]
`_Decimal64 __bid_trunctddd2 (_Decimal128 a)` [Runtime Function]

These functions convert the value a from one decimal floating type to another.

`_Decimal64 __dpd_extendsfdd (float a)` [Runtime Function]
`_Decimal64 __bid_extendsfdd (float a)` [Runtime Function]
`_Decimal128 __dpd_extendsftd (float a)` [Runtime Function]
`_Decimal128 __bid_extendsftd (float a)` [Runtime Function]
`_Decimal128 __dpd_extenddftd (double a)` [Runtime Function]
`_Decimal128 __bid_extenddftd (double a)` [Runtime Function]
`_Decimal128 __dpd_extendxftd (long double a)` [Runtime Function]
`_Decimal128 __bid_extendxftd (long double a)` [Runtime Function]
`_Decimal32 __dpd_truncdfsd (double a)` [Runtime Function]
`_Decimal32 __bid_truncdfsd (double a)` [Runtime Function]
`_Decimal32 __dpd_truncxfsd (long double a)` [Runtime Function]
`_Decimal32 __bid_truncxfsd (long double a)` [Runtime Function]
`_Decimal32 __dpd_trunctfsd (long double a)` [Runtime Function]
`_Decimal32 __bid_trunctfsd (long double a)` [Runtime Function]
`_Decimal64 __dpd_truncxfdd (long double a)` [Runtime Function]
`_Decimal64 __bid_truncxfdd (long double a)` [Runtime Function]
`_Decimal64 __dpd_trunctfdd (long double a)` [Runtime Function]
`_Decimal64 __bid_trunctfdd (long double a)` [Runtime Function]

These functions convert the value of a from a binary floating type to a decimal floating type of a different size.

`float __dpd_truncddsf (_Decimal64 a)` [Runtime Function]
`float __bid_truncddsf (_Decimal64 a)` [Runtime Function]
`float __dpd_trunctdsf (_Decimal128 a)` [Runtime Function]
`float __bid_trunctdsf (_Decimal128 a)` [Runtime Function]
`double __dpd_extendsddf (_Decimal32 a)` [Runtime Function]
`double __bid_extendsddf (_Decimal32 a)` [Runtime Function]
`double __dpd_trunctddf (_Decimal128 a)` [Runtime Function]
`double __bid_trunctddf (_Decimal128 a)` [Runtime Function]
`long double __dpd_extendsdxf (_Decimal32 a)` [Runtime Function]
`long double __bid_extendsdxf (_Decimal32 a)` [Runtime Function]
`long double __dpd_extendddxf (_Decimal64 a)` [Runtime Function]
`long double __bid_extendddxf (_Decimal64 a)` [Runtime Function]
`long double __dpd_trunctdxf (_Decimal128 a)` [Runtime Function]
`long double __bid_trunctdxf (_Decimal128 a)` [Runtime Function]
`long double __dpd_extendsdtf (_Decimal32 a)` [Runtime Function]
`long double __bid_extendsdtf (_Decimal32 a)` [Runtime Function]
`long double __dpd_extendddtf (_Decimal64 a)` [Runtime Function]

`long double __bid_extendddtf (_Decimal64 a)` [Runtime Function]

These functions convert the value of *a* from a decimal floating type to a binary floating type of a different size.

`_Decimal32 __dpd_extendsfsd (float a)` [Runtime Function]
`_Decimal32 __bid_extendsfsd (float a)` [Runtime Function]
`_Decimal64 __dpd_extenddfdd (double a)` [Runtime Function]
`_Decimal64 __bid_extenddfdd (double a)` [Runtime Function]
`_Decimal128 __dpd_extendtftd (long double a)` [Runtime Function]
`_Decimal128 __bid_extendtftd (long double a)` [Runtime Function]
`float __dpd_truncsdsf (_Decimal32 a)` [Runtime Function]
`float __bid_truncsdsf (_Decimal32 a)` [Runtime Function]
`double __dpd_truncdddf (_Decimal64 a)` [Runtime Function]
`double __bid_truncdddf (_Decimal64 a)` [Runtime Function]
`long double __dpd_trunctdtf (_Decimal128 a)` [Runtime Function]
`long double __bid_trunctdtf (_Decimal128 a)` [Runtime Function]

These functions convert the value of *a* between decimal and binary floating types of the same size.

`int __dpd_fixsdsi (_Decimal32 a)` [Runtime Function]
`int __bid_fixsdsi (_Decimal32 a)` [Runtime Function]
`int __dpd_fixddsi (_Decimal64 a)` [Runtime Function]
`int __bid_fixddsi (_Decimal64 a)` [Runtime Function]
`int __dpd_fixtdsi (_Decimal128 a)` [Runtime Function]
`int __bid_fixtdsi (_Decimal128 a)` [Runtime Function]

These functions convert *a* to a signed integer.

`long __dpd_fixsddi (_Decimal32 a)` [Runtime Function]
`long __bid_fixsddi (_Decimal32 a)` [Runtime Function]
`long __dpd_fixdddi (_Decimal64 a)` [Runtime Function]
`long __bid_fixdddi (_Decimal64 a)` [Runtime Function]
`long __dpd_fixtddi (_Decimal128 a)` [Runtime Function]
`long __bid_fixtddi (_Decimal128 a)` [Runtime Function]

These functions convert *a* to a signed long.

`unsigned int __dpd_fixunssdsi (_Decimal32 a)` [Runtime Function]
`unsigned int __bid_fixunssdsi (_Decimal32 a)` [Runtime Function]
`unsigned int __dpd_fixunsddsi (_Decimal64 a)` [Runtime Function]
`unsigned int __bid_fixunsddsi (_Decimal64 a)` [Runtime Function]
`unsigned int __dpd_fixunstdsi (_Decimal128 a)` [Runtime Function]
`unsigned int __bid_fixunstdsi (_Decimal128 a)` [Runtime Function]

These functions convert *a* to an unsigned integer. Negative values all become zero.

`unsigned long __dpd_fixunssddi (_Decimal32 a)` [Runtime Function]
`unsigned long __bid_fixunssddi (_Decimal32 a)` [Runtime Function]
`unsigned long __dpd_fixunsdddi (_Decimal64 a)` [Runtime Function]
`unsigned long __bid_fixunsdddi (_Decimal64 a)` [Runtime Function]
`unsigned long __dpd_fixunstddi (_Decimal128 a)` [Runtime Function]

`unsigned long __bid_fixunstddi (_Decimal128 a)` [Runtime Function]

These functions convert *a* to an unsigned long. Negative values all become zero.

`_Decimal32 __dpd_floatsisd (int i)` [Runtime Function]
`_Decimal32 __bid_floatsisd (int i)` [Runtime Function]
`_Decimal64 __dpd_floatsidd (int i)` [Runtime Function]
`_Decimal64 __bid_floatsidd (int i)` [Runtime Function]
`_Decimal128 __dpd_floatsitd (int i)` [Runtime Function]
`_Decimal128 __bid_floatsitd (int i)` [Runtime Function]

These functions convert *i*, a signed integer, to decimal floating point.

`_Decimal32 __dpd_floatdisd (long i)` [Runtime Function]
`_Decimal32 __bid_floatdisd (long i)` [Runtime Function]
`_Decimal64 __dpd_floatdidd (long i)` [Runtime Function]
`_Decimal64 __bid_floatdidd (long i)` [Runtime Function]
`_Decimal128 __dpd_floatditd (long i)` [Runtime Function]
`_Decimal128 __bid_floatditd (long i)` [Runtime Function]

These functions convert *i*, a signed long, to decimal floating point.

`_Decimal32 __dpd_floatunssisd (unsigned int i)` [Runtime Function]
`_Decimal32 __bid_floatunssisd (unsigned int i)` [Runtime Function]
`_Decimal64 __dpd_floatunssidd (unsigned int i)` [Runtime Function]
`_Decimal64 __bid_floatunssidd (unsigned int i)` [Runtime Function]
`_Decimal128 __dpd_floatunssitd (unsigned int i)` [Runtime Function]
`_Decimal128 __bid_floatunssitd (unsigned int i)` [Runtime Function]

These functions convert *i*, an unsigned integer, to decimal floating point.

`_Decimal32 __dpd_floatunsdisd (unsigned long i)` [Runtime Function]
`_Decimal32 __bid_floatunsdisd (unsigned long i)` [Runtime Function]
`_Decimal64 __dpd_floatunsdidd (unsigned long i)` [Runtime Function]
`_Decimal64 __bid_floatunsdidd (unsigned long i)` [Runtime Function]
`_Decimal128 __dpd_floatunsditd (unsigned long i)` [Runtime Function]
`_Decimal128 __bid_floatunsditd (unsigned long i)` [Runtime Function]

These functions convert *i*, an unsigned long, to decimal floating point.

4.3.3 Comparison functions

`int __dpd_unordsd2 (_Decimal32 a, _Decimal32 b)` [Runtime Function]
`int __bid_unordsd2 (_Decimal32 a, _Decimal32 b)` [Runtime Function]
`int __dpd_unorddd2 (_Decimal64 a, _Decimal64 b)` [Runtime Function]
`int __bid_unorddd2 (_Decimal64 a, _Decimal64 b)` [Runtime Function]
`int __dpd_unordtd2 (_Decimal128 a, _Decimal128 b)` [Runtime Function]
`int __bid_unordtd2 (_Decimal128 a, _Decimal128 b)` [Runtime Function]

These functions return a nonzero value if either argument is NaN, otherwise 0.

There is also a complete group of higher level functions which correspond directly to comparison operators. They implement the ISO C semantics for floating-point comparisons, taking NaN into account. Pay careful attention to the return values defined for each set. Under the hood, all of these routines are implemented as

```
if (__bid_unordXd2 (a, b))
  return E;
return __bid_cmpXd2 (a, b);
```

where E is a constant chosen to give the proper behavior for NaN. Thus, the meaning of the return value is different for each set. Do not rely on this implementation; only the semantics documented below are guaranteed.

`int __dpd_eqsd2 (_Decimal32 a, _Decimal32 b)` [Runtime Function]
`int __bid_eqsd2 (_Decimal32 a, _Decimal32 b)` [Runtime Function]
`int __dpd_eqdd2 (_Decimal64 a, _Decimal64 b)` [Runtime Function]
`int __bid_eqdd2 (_Decimal64 a, _Decimal64 b)` [Runtime Function]
`int __dpd_eqtd2 (_Decimal128 a, _Decimal128 b)` [Runtime Function]
`int __bid_eqtd2 (_Decimal128 a, _Decimal128 b)` [Runtime Function]

These functions return zero if neither argument is NaN, and a and b are equal.

`int __dpd_nesd2 (_Decimal32 a, _Decimal32 b)` [Runtime Function]
`int __bid_nesd2 (_Decimal32 a, _Decimal32 b)` [Runtime Function]
`int __dpd_nedd2 (_Decimal64 a, _Decimal64 b)` [Runtime Function]
`int __bid_nedd2 (_Decimal64 a, _Decimal64 b)` [Runtime Function]
`int __dpd_netd2 (_Decimal128 a, _Decimal128 b)` [Runtime Function]
`int __bid_netd2 (_Decimal128 a, _Decimal128 b)` [Runtime Function]

These functions return a nonzero value if either argument is NaN, or if a and b are unequal.

`int __dpd_gesd2 (_Decimal32 a, _Decimal32 b)` [Runtime Function]
`int __bid_gesd2 (_Decimal32 a, _Decimal32 b)` [Runtime Function]
`int __dpd_gedd2 (_Decimal64 a, _Decimal64 b)` [Runtime Function]
`int __bid_gedd2 (_Decimal64 a, _Decimal64 b)` [Runtime Function]
`int __dpd_getd2 (_Decimal128 a, _Decimal128 b)` [Runtime Function]
`int __bid_getd2 (_Decimal128 a, _Decimal128 b)` [Runtime Function]

These functions return a value greater than or equal to zero if neither argument is NaN, and a is greater than or equal to b.

`int __dpd_ltsd2 (_Decimal32 a, _Decimal32 b)` [Runtime Function]
`int __bid_ltsd2 (_Decimal32 a, _Decimal32 b)` [Runtime Function]
`int __dpd_ltdd2 (_Decimal64 a, _Decimal64 b)` [Runtime Function]
`int __bid_ltdd2 (_Decimal64 a, _Decimal64 b)` [Runtime Function]
`int __dpd_lttd2 (_Decimal128 a, _Decimal128 b)` [Runtime Function]
`int __bid_lttd2 (_Decimal128 a, _Decimal128 b)` [Runtime Function]

These functions return a value less than zero if neither argument is NaN, and a is strictly less than b.

`int __dpd_lesd2 (_Decimal32 a, _Decimal32 b)` [Runtime Function]
`int __bid_lesd2 (_Decimal32 a, _Decimal32 b)` [Runtime Function]
`int __dpd_ledd2 (_Decimal64 a, _Decimal64 b)` [Runtime Function]
`int __bid_ledd2 (_Decimal64 a, _Decimal64 b)` [Runtime Function]
`int __dpd_letd2 (_Decimal128 a, _Decimal128 b)` [Runtime Function]

`int __bid_letd2 (_Decimal128 a, _Decimal128 b)` [Runtime Function]

These functions return a value less than or equal to zero if neither argument is NaN, and *a* is less than or equal to *b*.

`int __dpd_gtsd2 (_Decimal32 a, _Decimal32 b)` [Runtime Function]
`int __bid_gtsd2 (_Decimal32 a, _Decimal32 b)` [Runtime Function]
`int __dpd_gtdd2 (_Decimal64 a, _Decimal64 b)` [Runtime Function]
`int __bid_gtdd2 (_Decimal64 a, _Decimal64 b)` [Runtime Function]
`int __dpd_gttd2 (_Decimal128 a, _Decimal128 b)` [Runtime Function]
`int __bid_gttd2 (_Decimal128 a, _Decimal128 b)` [Runtime Function]

These functions return a value greater than zero if neither argument is NaN, and *a* is strictly greater than *b*.

4.4 Routines for fixed-point fractional emulation

The software fixed-point library implements fixed-point fractional arithmetic, and is only activated on selected targets.

For ease of comprehension `fract` is an alias for the `_Fract` type, `accum` an alias for `_Accum`, and `sat` an alias for `_Sat`.

For illustrative purposes, in this section the fixed-point fractional type `short fract` is assumed to correspond to machine mode `QQmode`; `unsigned short fract` to `UQQmode`; `fract` to `HQmode`; `unsigned fract` to `UHQmode`; `long fract` to `SQmode`; `unsigned long fract` to `USQmode`; `long long fract` to `DQmode`; and `unsigned long long fract` to `UDQmode`. Similarly the fixed-point accumulator type `short accum` corresponds to `HAmode`; `unsigned short accum` to `UHAmode`; `accum` to `SAmode`; `unsigned accum` to `USAmode`; `long accum` to `DAmode`; `unsigned long accum` to `UDAmode`; `long long accum` to `TAmode`; and `unsigned long long accum` to `UTAmode`.

4.4.1 Arithmetic functions

`short fract __addqq3 (short fract a, short fract b)` [Runtime Function]
`fract __addhq3 (fract a, fract b)` [Runtime Function]
`long fract __addsq3 (long fract a, long fract b)` [Runtime Function]
`long long fract __adddq3 (long long fract a, long long fract b)` [Runtime Function]
`unsigned short fract __adduqq3 (unsigned short fract a, unsigned short fract b)` [Runtime Function]
`unsigned fract __adduhq3 (unsigned fract a, unsigned fract b)` [Runtime Function]
`unsigned long fract __addusq3 (unsigned long fract a, unsigned long fract b)` [Runtime Function]
`unsigned long long fract __addudq3 (unsigned long long fract a, unsigned long long fract b)` [Runtime Function]
`short accum __addha3 (short accum a, short accum b)` [Runtime Function]
`accum __addsa3 (accum a, accum b)` [Runtime Function]
`long accum __addda3 (long accum a, long accum b)` [Runtime Function]
`long long accum __addta3 (long long accum a, long long accum b)` [Runtime Function]

`unsigned short accum __adduha3` (*unsigned short accum* `a`, *unsigned short accum* `b`) [Runtime Function]
`unsigned accum __addusa3` (*unsigned accum* `a`, *unsigned accum* `b`) [Runtime Function]
`unsigned long accum __adduda3` (*unsigned long accum* `a`, *unsigned long accum* `b`) [Runtime Function]
`unsigned long long accum __adduta3` (*unsigned long long accum* `a`, *unsigned long long accum* `b`) [Runtime Function]

These functions return the sum of *a* and *b*.

`short fract __ssaddqq3` (*short fract* `a`, *short fract* `b`) [Runtime Function]
`fract __ssaddhq3` (*fract* `a`, *fract* `b`) [Runtime Function]
`long fract __ssaddsq3` (*long fract* `a`, *long fract* `b`) [Runtime Function]
`long long fract __ssadddq3` (*long long fract* `a`, *long long fract* `b`) [Runtime Function]
`short accum __ssaddha3` (*short accum* `a`, *short accum* `b`) [Runtime Function]
`accum __ssaddsa3` (*accum* `a`, *accum* `b`) [Runtime Function]
`long accum __ssaddda3` (*long accum* `a`, *long accum* `b`) [Runtime Function]
`long long accum __ssaddta3` (*long long accum* `a`, *long long accum* `b`) [Runtime Function]

These functions return the sum of *a* and *b* with signed saturation.

`unsigned short fract __usadduqq3` (*unsigned short fract* `a`, *unsigned short fract* `b`) [Runtime Function]
`unsigned fract __usadduhq3` (*unsigned fract* `a`, *unsigned fract* `b`) [Runtime Function]
`unsigned long fract __usaddusq3` (*unsigned long fract* `a`, *unsigned long fract* `b`) [Runtime Function]
`unsigned long long fract __usaddudq3` (*unsigned long long fract* `a`, *unsigned long long fract* `b`) [Runtime Function]
`unsigned short accum __usadduha3` (*unsigned short accum* `a`, *unsigned short accum* `b`) [Runtime Function]
`unsigned accum __usaddusa3` (*unsigned accum* `a`, *unsigned accum* `b`) [Runtime Function]
`unsigned long accum __usadduda3` (*unsigned long accum* `a`, *unsigned long accum* `b`) [Runtime Function]
`unsigned long long accum __usadduta3` (*unsigned long long accum* `a`, *unsigned long long accum* `b`) [Runtime Function]

These functions return the sum of *a* and *b* with unsigned saturation.

`short fract __subqq3` (*short fract* `a`, *short fract* `b`) [Runtime Function]
`fract __subhq3` (*fract* `a`, *fract* `b`) [Runtime Function]
`long fract __subsq3` (*long fract* `a`, *long fract* `b`) [Runtime Function]
`long long fract __subdq3` (*long long fract* `a`, *long long fract* `b`) [Runtime Function]
`unsigned short fract __subuqq3` (*unsigned short fract* `a`, *unsigned short fract* `b`) [Runtime Function]

`unsigned fract __subuhq3` (*unsigned fract* `a`, *unsigned fract* `b`) [Runtime Function]
`unsigned long fract __subusq3` (*unsigned long fract* `a`, *unsigned long fract* `b`) [Runtime Function]
`unsigned long long fract __subudq3` (*unsigned long long fract* `a`, *unsigned long long fract* `b`) [Runtime Function]
`short accum __subha3` (*short accum* `a`, *short accum* `b`) [Runtime Function]
`accum __subsa3` (*accum* `a`, *accum* `b`) [Runtime Function]
`long accum __subda3` (*long accum* `a`, *long accum* `b`) [Runtime Function]
`long long accum __subta3` (*long long accum* `a`, *long long accum* `b`) [Runtime Function]
`unsigned short accum __subuha3` (*unsigned short accum* `a`, *unsigned short accum* `b`) [Runtime Function]
`unsigned accum __subusa3` (*unsigned accum* `a`, *unsigned accum* `b`) [Runtime Function]
`unsigned long accum __subuda3` (*unsigned long accum* `a`, *unsigned long accum* `b`) [Runtime Function]
`unsigned long long accum __subuta3` (*unsigned long long accum* `a`, *unsigned long long accum* `b`) [Runtime Function]

These functions return the difference of *a* and *b*; that is, `a - b`.

`short fract __sssubqq3` (*short fract* `a`, *short fract* `b`) [Runtime Function]
`fract __sssubhq3` (*fract* `a`, *fract* `b`) [Runtime Function]
`long fract __sssubsq3` (*long fract* `a`, *long fract* `b`) [Runtime Function]
`long long fract __sssubdq3` (*long long fract* `a`, *long long fract* `b`) [Runtime Function]
`short accum __sssubha3` (*short accum* `a`, *short accum* `b`) [Runtime Function]
`accum __sssubsa3` (*accum* `a`, *accum* `b`) [Runtime Function]
`long accum __sssubda3` (*long accum* `a`, *long accum* `b`) [Runtime Function]
`long long accum __sssubta3` (*long long accum* `a`, *long long accum* `b`) [Runtime Function]

These functions return the difference of *a* and *b* with signed saturation; that is, `a - b`.

`unsigned short fract __ussubuqq3` (*unsigned short fract* `a`, *unsigned short fract* `b`) [Runtime Function]
`unsigned fract __ussubuhq3` (*unsigned fract* `a`, *unsigned fract* `b`) [Runtime Function]
`unsigned long fract __ussubusq3` (*unsigned long fract* `a`, *unsigned long fract* `b`) [Runtime Function]
`unsigned long long fract __ussubudq3` (*unsigned long long fract* `a`, *unsigned long long fract* `b`) [Runtime Function]
`unsigned short accum __ussubuha3` (*unsigned short accum* `a`, *unsigned short accum* `b`) [Runtime Function]
`unsigned accum __ussubusa3` (*unsigned accum* `a`, *unsigned accum* `b`) [Runtime Function]
`unsigned long accum __ussubuda3` (*unsigned long accum* `a`, *unsigned long accum* `b`) [Runtime Function]

`unsigned long long accum __ussubuta3` (*unsigned long long accum* `a`, *unsigned long long accum* `b`) [Runtime Function]

These functions return the difference of *a* and *b* with unsigned saturation; that is, `a - b`.

`short fract __mulqq3` (*short fract* `a`, *short fract* `b`) [Runtime Function]
`fract __mulhq3` (*fract* `a`, *fract* `b`) [Runtime Function]
`long fract __mulsq3` (*long fract* `a`, *long fract* `b`) [Runtime Function]
`long long fract __muldq3` (*long long fract* `a`, *long long fract* `b`) [Runtime Function]
`unsigned short fract __muluqq3` (*unsigned short fract* `a`, *unsigned short fract* `b`) [Runtime Function]
`unsigned fract __muluhq3` (*unsigned fract* `a`, *unsigned fract* `b`) [Runtime Function]
`unsigned long fract __mulusq3` (*unsigned long fract* `a`, *unsigned long fract* `b`) [Runtime Function]
`unsigned long long fract __muludq3` (*unsigned long long fract* `a`, *unsigned long long fract* `b`) [Runtime Function]
`short accum __mulha3` (*short accum* `a`, *short accum* `b`) [Runtime Function]
`accum __mulsa3` (*accum* `a`, *accum* `b`) [Runtime Function]
`long accum __mulda3` (*long accum* `a`, *long accum* `b`) [Runtime Function]
`long long accum __multa3` (*long long accum* `a`, *long long accum* `b`) [Runtime Function]
`unsigned short accum __muluha3` (*unsigned short accum* `a`, *unsigned short accum* `b`) [Runtime Function]
`unsigned accum __mulusa3` (*unsigned accum* `a`, *unsigned accum* `b`) [Runtime Function]
`unsigned long accum __muluda3` (*unsigned long accum* `a`, *unsigned long accum* `b`) [Runtime Function]
`unsigned long long accum __muluta3` (*unsigned long long accum* `a`, *unsigned long long accum* `b`) [Runtime Function]

These functions return the product of *a* and *b*.

`short fract __ssmulqq3` (*short fract* `a`, *short fract* `b`) [Runtime Function]
`fract __ssmulhq3` (*fract* `a`, *fract* `b`) [Runtime Function]
`long fract __ssmulsq3` (*long fract* `a`, *long fract* `b`) [Runtime Function]
`long long fract __ssmuldq3` (*long long fract* `a`, *long long fract* `b`) [Runtime Function]
`short accum __ssmulha3` (*short accum* `a`, *short accum* `b`) [Runtime Function]
`accum __ssmulsa3` (*accum* `a`, *accum* `b`) [Runtime Function]
`long accum __ssmulda3` (*long accum* `a`, *long accum* `b`) [Runtime Function]
`long long accum __ssmulta3` (*long long accum* `a`, *long long accum* `b`) [Runtime Function]

These functions return the product of *a* and *b* with signed saturation.

`unsigned short fract __usmuluqq3` (*unsigned short fract* `a`, *unsigned short fract* `b`) [Runtime Function]
`unsigned fract __usmuluhq3` (*unsigned fract* `a`, *unsigned fract* `b`) [Runtime Function]
`unsigned long fract __usmulusq3` (*unsigned long fract* `a`, *unsigned long fract* `b`) [Runtime Function]
`unsigned long long fract __usmuludq3` (*unsigned long long fract* `a`, *unsigned long long fract* `b`) [Runtime Function]
`unsigned short accum __usmuluha3` (*unsigned short accum* `a`, *unsigned short accum* `b`) [Runtime Function]
`unsigned accum __usmulusa3` (*unsigned accum* `a`, *unsigned accum* `b`) [Runtime Function]
`unsigned long accum __usmuluda3` (*unsigned long accum* `a`, *unsigned long accum* `b`) [Runtime Function]
`unsigned long long accum __usmuluta3` (*unsigned long long accum* `a`, *unsigned long long accum* `b`) [Runtime Function]

These functions return the product of a and b with unsigned saturation.

`short fract __divqq3` (*short fract* `a`, *short fract* `b`) [Runtime Function]
`fract __divhq3` (*fract* `a`, *fract* `b`) [Runtime Function]
`long fract __divsq3` (*long fract* `a`, *long fract* `b`) [Runtime Function]
`long long fract __divdq3` (*long long fract* `a`, *long long fract* `b`) [Runtime Function]
`short accum __divha3` (*short accum* `a`, *short accum* `b`) [Runtime Function]
`accum __divsa3` (*accum* `a`, *accum* `b`) [Runtime Function]
`long accum __divda3` (*long accum* `a`, *long accum* `b`) [Runtime Function]
`long long accum __divta3` (*long long accum* `a`, *long long accum* `b`) [Runtime Function]

These functions return the quotient of the signed division of a and b.

`unsigned short fract __udivuqq3` (*unsigned short fract* `a`, *unsigned short fract* `b`) [Runtime Function]
`unsigned fract __udivuhq3` (*unsigned fract* `a`, *unsigned fract* `b`) [Runtime Function]
`unsigned long fract __udivusq3` (*unsigned long fract* `a`, *unsigned long fract* `b`) [Runtime Function]
`unsigned long long fract __udivudq3` (*unsigned long long fract* `a`, *unsigned long long fract* `b`) [Runtime Function]
`unsigned short accum __udivuha3` (*unsigned short accum* `a`, *unsigned short accum* `b`) [Runtime Function]
`unsigned accum __udivusa3` (*unsigned accum* `a`, *unsigned accum* `b`) [Runtime Function]
`unsigned long accum __udivuda3` (*unsigned long accum* `a`, *unsigned long accum* `b`) [Runtime Function]
`unsigned long long accum __udivuta3` (*unsigned long long accum* `a`, *unsigned long long accum* `b`) [Runtime Function]

These functions return the quotient of the unsigned division of a and b.

`short fract __ssdivqq3` (*short fract* `a`, *short fract* `b`) [Runtime Function]
`fract __ssdivhq3` (*fract* `a`, *fract* `b`) [Runtime Function]
`long fract __ssdivsq3` (*long fract* `a`, *long fract* `b`) [Runtime Function]
`long long fract __ssdivdq3` (*long long fract* `a`, *long long fract* `b`) [Runtime Function]
`short accum __ssdivha3` (*short accum* `a`, *short accum* `b`) [Runtime Function]
`accum __ssdivsa3` (*accum* `a`, *accum* `b`) [Runtime Function]
`long accum __ssdivda3` (*long accum* `a`, *long accum* `b`) [Runtime Function]
`long long accum __ssdivta3` (*long long accum* `a`, *long long accum* `b`) [Runtime Function]

These functions return the quotient of the signed division of *a* and *b* with signed saturation.

`unsigned short fract __usdivuqq3` (*unsigned short fract* `a`, *unsigned short fract* `b`) [Runtime Function]
`unsigned fract __usdivuhq3` (*unsigned fract* `a`, *unsigned fract* `b`) [Runtime Function]
`unsigned long fract __usdivusq3` (*unsigned long fract* `a`, *unsigned long fract* `b`) [Runtime Function]
`unsigned long long fract __usdivudq3` (*unsigned long long fract* `a`, *unsigned long long fract* `b`) [Runtime Function]
`unsigned short accum __usdivuha3` (*unsigned short accum* `a`, *unsigned short accum* `b`) [Runtime Function]
`unsigned accum __usdivusa3` (*unsigned accum* `a`, *unsigned accum* `b`) [Runtime Function]
`unsigned long accum __usdivuda3` (*unsigned long accum* `a`, *unsigned long accum* `b`) [Runtime Function]
`unsigned long long accum __usdivuta3` (*unsigned long long accum* `a`, *unsigned long long accum* `b`) [Runtime Function]

These functions return the quotient of the unsigned division of *a* and *b* with unsigned saturation.

`short fract __negqq2` (*short fract* `a`) [Runtime Function]
`fract __neghq2` (*fract* `a`) [Runtime Function]
`long fract __negsq2` (*long fract* `a`) [Runtime Function]
`long long fract __negdq2` (*long long fract* `a`) [Runtime Function]
`unsigned short fract __neguqq2` (*unsigned short fract* `a`) [Runtime Function]
`unsigned fract __neguhq2` (*unsigned fract* `a`) [Runtime Function]
`unsigned long fract __negusq2` (*unsigned long fract* `a`) [Runtime Function]
`unsigned long long fract __negudq2` (*unsigned long long fract* `a`) [Runtime Function]
`short accum __negha2` (*short accum* `a`) [Runtime Function]
`accum __negsa2` (*accum* `a`) [Runtime Function]
`long accum __negda2` (*long accum* `a`) [Runtime Function]
`long long accum __negta2` (*long long accum* `a`) [Runtime Function]
`unsigned short accum __neguha2` (*unsigned short accum* `a`) [Runtime Function]
`unsigned accum __negusa2` (*unsigned accum* `a`) [Runtime Function]
`unsigned long accum __neguda2` (*unsigned long accum* `a`) [Runtime Function]

`unsigned long long accum __neguta2` (*unsigned long long accum* `a`) [Runtime Function]

These functions return the negation of *a*.

`short fract __ssnegqq2` (*short fract* `a`) [Runtime Function]
`fract __ssneghq2` (*fract* `a`) [Runtime Function]
`long fract __ssnegsq2` (*long fract* `a`) [Runtime Function]
`long long fract __ssnegdq2` (*long long fract* `a`) [Runtime Function]
`short accum __ssnegha2` (*short accum* `a`) [Runtime Function]
`accum __ssnegsa2` (*accum* `a`) [Runtime Function]
`long accum __ssnegda2` (*long accum* `a`) [Runtime Function]
`long long accum __ssnegta2` (*long long accum* `a`) [Runtime Function]

These functions return the negation of *a* with signed saturation.

`unsigned short fract __usneguqq2` (*unsigned short fract* `a`) [Runtime Function]
`unsigned fract __usneguhq2` (*unsigned fract* `a`) [Runtime Function]
`unsigned long fract __usnegusq2` (*unsigned long fract* `a`) [Runtime Function]
`unsigned long long fract __usnegudq2` (*unsigned long long fract* `a`) [Runtime Function]
`unsigned short accum __usneguha2` (*unsigned short accum* `a`) [Runtime Function]
`unsigned accum __usnegusa2` (*unsigned accum* `a`) [Runtime Function]
`unsigned long accum __usneguda2` (*unsigned long accum* `a`) [Runtime Function]
`unsigned long long accum __usneguta2` (*unsigned long long accum* `a`) [Runtime Function]

These functions return the negation of *a* with unsigned saturation.

`short fract __ashlqq3` (*short fract* `a`, *int* `b`) [Runtime Function]
`fract __ashlhq3` (*fract* `a`, *int* `b`) [Runtime Function]
`long fract __ashlsq3` (*long fract* `a`, *int* `b`) [Runtime Function]
`long long fract __ashldq3` (*long long fract* `a`, *int* `b`) [Runtime Function]
`unsigned short fract __ashluqq3` (*unsigned short fract* `a`, *int* `b`) [Runtime Function]
`unsigned fract __ashluhq3` (*unsigned fract* `a`, *int* `b`) [Runtime Function]
`unsigned long fract __ashlusq3` (*unsigned long fract* `a`, *int* `b`) [Runtime Function]
`unsigned long long fract __ashludq3` (*unsigned long long fract* `a`, *int* `b`) [Runtime Function]
`short accum __ashlha3` (*short accum* `a`, *int* `b`) [Runtime Function]
`accum __ashlsa3` (*accum* `a`, *int* `b`) [Runtime Function]
`long accum __ashlda3` (*long accum* `a`, *int* `b`) [Runtime Function]
`long long accum __ashlta3` (*long long accum* `a`, *int* `b`) [Runtime Function]
`unsigned short accum __ashluha3` (*unsigned short accum* `a`, *int* `b`) [Runtime Function]
`unsigned accum __ashlusa3` (*unsigned accum* `a`, *int* `b`) [Runtime Function]
`unsigned long accum __ashluda3` (*unsigned long accum* `a`, *int* `b`) [Runtime Function]

`unsigned long long accum __ashluta3` (*unsigned long long accum* a, *int* b) [Runtime Function]

These functions return the result of shifting *a* left by *b* bits.

`short fract __ashrqq3` (*short fract* a, *int* b) [Runtime Function]
`fract __ashrhq3` (*fract* a, *int* b) [Runtime Function]
`long fract __ashrsq3` (*long fract* a, *int* b) [Runtime Function]
`long long fract __ashrdq3` (*long long fract* a, *int* b) [Runtime Function]
`short accum __ashrha3` (*short accum* a, *int* b) [Runtime Function]
`accum __ashrsa3` (*accum* a, *int* b) [Runtime Function]
`long accum __ashrda3` (*long accum* a, *int* b) [Runtime Function]
`long long accum __ashrta3` (*long long accum* a, *int* b) [Runtime Function]

These functions return the result of arithmetically shifting *a* right by *b* bits.

`unsigned short fract __lshruqq3` (*unsigned short fract* a, *int* b) [Runtime Function]
`unsigned fract __lshruhq3` (*unsigned fract* a, *int* b) [Runtime Function]
`unsigned long fract __lshrusq3` (*unsigned long fract* a, *int* b) [Runtime Function]
`unsigned long long fract __lshrudq3` (*unsigned long long fract* a, *int* b) [Runtime Function]
`unsigned short accum __lshruha3` (*unsigned short accum* a, *int* b) [Runtime Function]
`unsigned accum __lshrusa3` (*unsigned accum* a, *int* b) [Runtime Function]
`unsigned long accum __lshruda3` (*unsigned long accum* a, *int* b) [Runtime Function]
`unsigned long long accum __lshruta3` (*unsigned long long accum* a, *int* b) [Runtime Function]

These functions return the result of logically shifting *a* right by *b* bits.

`fract __ssashlhq3` (*fract* a, *int* b) [Runtime Function]
`long fract __ssashlsq3` (*long fract* a, *int* b) [Runtime Function]
`long long fract __ssashldq3` (*long long fract* a, *int* b) [Runtime Function]
`short accum __ssashlha3` (*short accum* a, *int* b) [Runtime Function]
`accum __ssashlsa3` (*accum* a, *int* b) [Runtime Function]
`long accum __ssashlda3` (*long accum* a, *int* b) [Runtime Function]
`long long accum __ssashlta3` (*long long accum* a, *int* b) [Runtime Function]

These functions return the result of shifting *a* left by *b* bits with signed saturation.

`unsigned short fract __usashluqq3` (*unsigned short fract* a, *int* b) [Runtime Function]
`unsigned fract __usashluhq3` (*unsigned fract* a, *int* b) [Runtime Function]
`unsigned long fract __usashlusq3` (*unsigned long fract* a, *int* b) [Runtime Function]
`unsigned long long fract __usashludq3` (*unsigned long long fract* a, *int* b) [Runtime Function]
`unsigned short accum __usashluha3` (*unsigned short accum* a, *int* b) [Runtime Function]

`unsigned accum __usashlusa3` (*unsigned accum* a, *int* b) [Runtime Function]
`unsigned long accum __usashluda3` (*unsigned long accum* a, *int* b) [Runtime Function]
`unsigned long long accum __usashluta3` (*unsigned long long accum* a, *int* b) [Runtime Function]

These functions return the result of shifting *a* left by *b* bits with unsigned saturation.

4.4.2 Comparison functions

The following functions implement fixed-point comparisons. These functions implement a low-level compare, upon which the higher level comparison operators (such as less than and greater than or equal to) can be constructed. The returned values lie in the range zero to two, to allow the high-level operators to be implemented by testing the returned result using either signed or unsigned comparison.

`int __cmpqq2` (*short fract* a, *short fract* b) [Runtime Function]
`int __cmphq2` (*fract* a, *fract* b) [Runtime Function]
`int __cmpsq2` (*long fract* a, *long fract* b) [Runtime Function]
`int __cmpdq2` (*long long fract* a, *long long fract* b) [Runtime Function]
`int __cmpuqq2` (*unsigned short fract* a, *unsigned short fract* b) [Runtime Function]
`int __cmpuhq2` (*unsigned fract* a, *unsigned fract* b) [Runtime Function]
`int __cmpusq2` (*unsigned long fract* a, *unsigned long fract* b) [Runtime Function]
`int __cmpudq2` (*unsigned long long fract* a, *unsigned long long fract* b) [Runtime Function]
`int __cmpha2` (*short accum* a, *short accum* b) [Runtime Function]
`int __cmpsa2` (*accum* a, *accum* b) [Runtime Function]
`int __cmpda2` (*long accum* a, *long accum* b) [Runtime Function]
`int __cmpta2` (*long long accum* a, *long long accum* b) [Runtime Function]
`int __cmpuha2` (*unsigned short accum* a, *unsigned short accum* b) [Runtime Function]
`int __cmpusa2` (*unsigned accum* a, *unsigned accum* b) [Runtime Function]
`int __cmpuda2` (*unsigned long accum* a, *unsigned long accum* b) [Runtime Function]
`int __cmputa2` (*unsigned long long accum* a, *unsigned long long accum* b) [Runtime Function]

These functions perform a signed or unsigned comparison of *a* and *b* (depending on the selected machine mode). If *a* is less than *b*, they return 0; if *a* is greater than *b*, they return 2; and if *a* and *b* are equal they return 1.

4.4.3 Conversion functions

`fract __fractqqhq2` (*short fract* a) [Runtime Function]
`long fract __fractqqsq2` (*short fract* a) [Runtime Function]
`long long fract __fractqqdq2` (*short fract* a) [Runtime Function]
`short accum __fractqqha` (*short fract* a) [Runtime Function]
`accum __fractqqsa` (*short fract* a) [Runtime Function]
`long accum __fractqqda` (*short fract* a) [Runtime Function]
`long long accum __fractqqta` (*short fract* a) [Runtime Function]
`unsigned short fract __fractqquqq` (*short fract* a) [Runtime Function]
`unsigned fract __fractqquhq` (*short fract* a) [Runtime Function]

`unsigned long fract __fractqqusq` (*short fract* a) [Runtime Function]
`unsigned long long fract __fractqqudq` (*short fract* a) [Runtime Function]
`unsigned short accum __fractqquha` (*short fract* a) [Runtime Function]
`unsigned accum __fractqqusa` (*short fract* a) [Runtime Function]
`unsigned long accum __fractqquda` (*short fract* a) [Runtime Function]
`unsigned long long accum __fractqquta` (*short fract* a) [Runtime Function]
`signed char __fractqqqi` (*short fract* a) [Runtime Function]
`short __fractqqhi` (*short fract* a) [Runtime Function]
`int __fractqqsi` (*short fract* a) [Runtime Function]
`long __fractqqdi` (*short fract* a) [Runtime Function]
`long long __fractqqti` (*short fract* a) [Runtime Function]
`float __fractqqsf` (*short fract* a) [Runtime Function]
`double __fractqqdf` (*short fract* a) [Runtime Function]
`short fract __fracthqqq2` (*fract* a) [Runtime Function]
`long fract __fracthqsq2` (*fract* a) [Runtime Function]
`long long fract __fracthqdq2` (*fract* a) [Runtime Function]
`short accum __fracthqha` (*fract* a) [Runtime Function]
`accum __fracthqsa` (*fract* a) [Runtime Function]
`long accum __fracthqda` (*fract* a) [Runtime Function]
`long long accum __fracthqta` (*fract* a) [Runtime Function]
`unsigned short fract __fracthquqq` (*fract* a) [Runtime Function]
`unsigned fract __fracthquhq` (*fract* a) [Runtime Function]
`unsigned long fract __fracthqusq` (*fract* a) [Runtime Function]
`unsigned long long fract __fracthqudq` (*fract* a) [Runtime Function]
`unsigned short accum __fracthquha` (*fract* a) [Runtime Function]
`unsigned accum __fracthqusa` (*fract* a) [Runtime Function]
`unsigned long accum __fracthquda` (*fract* a) [Runtime Function]
`unsigned long long accum __fracthquta` (*fract* a) [Runtime Function]
`signed char __fracthqqi` (*fract* a) [Runtime Function]
`short __fracthqhi` (*fract* a) [Runtime Function]
`int __fracthqsi` (*fract* a) [Runtime Function]
`long __fracthqdi` (*fract* a) [Runtime Function]
`long long __fracthqti` (*fract* a) [Runtime Function]
`float __fracthqsf` (*fract* a) [Runtime Function]
`double __fracthqdf` (*fract* a) [Runtime Function]
`short fract __fractsqqq2` (*long fract* a) [Runtime Function]
`fract __fractsqhq2` (*long fract* a) [Runtime Function]
`long long fract __fractsqdq2` (*long fract* a) [Runtime Function]
`short accum __fractsqha` (*long fract* a) [Runtime Function]
`accum __fractsqsa` (*long fract* a) [Runtime Function]
`long accum __fractsqda` (*long fract* a) [Runtime Function]
`long long accum __fractsqta` (*long fract* a) [Runtime Function]
`unsigned short fract __fractsquqq` (*long fract* a) [Runtime Function]
`unsigned fract __fractsquhq` (*long fract* a) [Runtime Function]
`unsigned long fract __fractsqusq` (*long fract* a) [Runtime Function]
`unsigned long long fract __fractsqudq` (*long fract* a) [Runtime Function]
`unsigned short accum __fractsquha` (*long fract* a) [Runtime Function]

`unsigned accum __fractsqusa` (*long fract* a) [Runtime Function]
`unsigned long accum __fractsquda` (*long fract* a) [Runtime Function]
`unsigned long long accum __fractsquta` (*long fract* a) [Runtime Function]
`signed char __fractsqqi` (*long fract* a) [Runtime Function]
`short __fractsqhi` (*long fract* a) [Runtime Function]
`int __fractsqsi` (*long fract* a) [Runtime Function]
`long __fractsqdi` (*long fract* a) [Runtime Function]
`long long __fractsqti` (*long fract* a) [Runtime Function]
`float __fractsqsf` (*long fract* a) [Runtime Function]
`double __fractsqdf` (*long fract* a) [Runtime Function]
`short fract __fractdqqq2` (*long long fract* a) [Runtime Function]
`fract __fractdqhq2` (*long long fract* a) [Runtime Function]
`long fract __fractdqsq2` (*long long fract* a) [Runtime Function]
`short accum __fractdqha` (*long long fract* a) [Runtime Function]
`accum __fractdqsa` (*long long fract* a) [Runtime Function]
`long accum __fractdqda` (*long long fract* a) [Runtime Function]
`long long accum __fractdqta` (*long long fract* a) [Runtime Function]
`unsigned short fract __fractdquqq` (*long long fract* a) [Runtime Function]
`unsigned fract __fractdquhq` (*long long fract* a) [Runtime Function]
`unsigned long fract __fractdqusq` (*long long fract* a) [Runtime Function]
`unsigned long long fract __fractdqudq` (*long long fract* a) [Runtime Function]
`unsigned short accum __fractdquha` (*long long fract* a) [Runtime Function]
`unsigned accum __fractdqusa` (*long long fract* a) [Runtime Function]
`unsigned long accum __fractdquda` (*long long fract* a) [Runtime Function]
`unsigned long long accum __fractdquta` (*long long fract* a) [Runtime Function]
`signed char __fractdqqi` (*long long fract* a) [Runtime Function]
`short __fractdqhi` (*long long fract* a) [Runtime Function]
`int __fractdqsi` (*long long fract* a) [Runtime Function]
`long __fractdqdi` (*long long fract* a) [Runtime Function]
`long long __fractdqti` (*long long fract* a) [Runtime Function]
`float __fractdqsf` (*long long fract* a) [Runtime Function]
`double __fractdqdf` (*long long fract* a) [Runtime Function]
`short fract __fracthaqq` (*short accum* a) [Runtime Function]
`fract __fracthahq` (*short accum* a) [Runtime Function]
`long fract __fracthasq` (*short accum* a) [Runtime Function]
`long long fract __fracthadq` (*short accum* a) [Runtime Function]
`accum __fracthasa2` (*short accum* a) [Runtime Function]
`long accum __fracthada2` (*short accum* a) [Runtime Function]
`long long accum __fracthata2` (*short accum* a) [Runtime Function]
`unsigned short fract __fracthauqq` (*short accum* a) [Runtime Function]
`unsigned fract __fracthauhq` (*short accum* a) [Runtime Function]
`unsigned long fract __fracthausq` (*short accum* a) [Runtime Function]
`unsigned long long fract __fracthaudq` (*short accum* a) [Runtime Function]
`unsigned short accum __fracthauha` (*short accum* a) [Runtime Function]
`unsigned accum __fracthausa` (*short accum* a) [Runtime Function]

`unsigned long accum __fracthauda` (*short accum* a) [Runtime Function]
`unsigned long long accum __fracthauta` (*short accum* a) [Runtime Function]
`signed char __fracthaqi` (*short accum* a) [Runtime Function]
`short __fracthahi` (*short accum* a) [Runtime Function]
`int __fracthasi` (*short accum* a) [Runtime Function]
`long __fracthadi` (*short accum* a) [Runtime Function]
`long long __fracthati` (*short accum* a) [Runtime Function]
`float __fracthasf` (*short accum* a) [Runtime Function]
`double __fracthadf` (*short accum* a) [Runtime Function]
`short fract __fractsaqq` (*accum* a) [Runtime Function]
`fract __fractsahq` (*accum* a) [Runtime Function]
`long fract __fractsasq` (*accum* a) [Runtime Function]
`long long fract __fractsadq` (*accum* a) [Runtime Function]
`short accum __fractsaha2` (*accum* a) [Runtime Function]
`long accum __fractsada2` (*accum* a) [Runtime Function]
`long long accum __fractsata2` (*accum* a) [Runtime Function]
`unsigned short fract __fractsauqq` (*accum* a) [Runtime Function]
`unsigned fract __fractsauhq` (*accum* a) [Runtime Function]
`unsigned long fract __fractsausq` (*accum* a) [Runtime Function]
`unsigned long long fract __fractsaudq` (*accum* a) [Runtime Function]
`unsigned short accum __fractsauha` (*accum* a) [Runtime Function]
`unsigned accum __fractsausa` (*accum* a) [Runtime Function]
`unsigned long accum __fractsauda` (*accum* a) [Runtime Function]
`unsigned long long accum __fractsauta` (*accum* a) [Runtime Function]
`signed char __fractsaqi` (*accum* a) [Runtime Function]
`short __fractsahi` (*accum* a) [Runtime Function]
`int __fractsasi` (*accum* a) [Runtime Function]
`long __fractsadi` (*accum* a) [Runtime Function]
`long long __fractsati` (*accum* a) [Runtime Function]
`float __fractsasf` (*accum* a) [Runtime Function]
`double __fractsadf` (*accum* a) [Runtime Function]
`short fract __fractdaqq` (*long accum* a) [Runtime Function]
`fract __fractdahq` (*long accum* a) [Runtime Function]
`long fract __fractdasq` (*long accum* a) [Runtime Function]
`long long fract __fractdadq` (*long accum* a) [Runtime Function]
`short accum __fractdaha2` (*long accum* a) [Runtime Function]
`accum __fractdasa2` (*long accum* a) [Runtime Function]
`long long accum __fractdata2` (*long accum* a) [Runtime Function]
`unsigned short fract __fractdauqq` (*long accum* a) [Runtime Function]
`unsigned fract __fractdauhq` (*long accum* a) [Runtime Function]
`unsigned long fract __fractdausq` (*long accum* a) [Runtime Function]
`unsigned long long fract __fractdaudq` (*long accum* a) [Runtime Function]
`unsigned short accum __fractdauha` (*long accum* a) [Runtime Function]
`unsigned accum __fractdausa` (*long accum* a) [Runtime Function]
`unsigned long accum __fractdauda` (*long accum* a) [Runtime Function]
`unsigned long long accum __fractdauta` (*long accum* a) [Runtime Function]
`signed char __fractdaqi` (*long accum* a) [Runtime Function]

`short __fractdahi` (*long accum* a) [Runtime Function]
`int __fractdasi` (*long accum* a) [Runtime Function]
`long __fractdadi` (*long accum* a) [Runtime Function]
`long long __fractdati` (*long accum* a) [Runtime Function]
`float __fractdasf` (*long accum* a) [Runtime Function]
`double __fractdadf` (*long accum* a) [Runtime Function]
`short fract __fracttaqq` (*long long accum* a) [Runtime Function]
`fract __fracttahq` (*long long accum* a) [Runtime Function]
`long fract __fracttasq` (*long long accum* a) [Runtime Function]
`long long fract __fracttadq` (*long long accum* a) [Runtime Function]
`short accum __fracttaha2` (*long long accum* a) [Runtime Function]
`accum __fracttasa2` (*long long accum* a) [Runtime Function]
`long accum __fracttada2` (*long long accum* a) [Runtime Function]
`unsigned short fract __fracttauqq` (*long long accum* a) [Runtime Function]
`unsigned fract __fracttauhq` (*long long accum* a) [Runtime Function]
`unsigned long fract __fracttausq` (*long long accum* a) [Runtime Function]
`unsigned long long fract __fracttaudq` (*long long accum* a) [Runtime Function]
`unsigned short accum __fracttauha` (*long long accum* a) [Runtime Function]
`unsigned accum __fracttausa` (*long long accum* a) [Runtime Function]
`unsigned long accum __fracttauda` (*long long accum* a) [Runtime Function]
`unsigned long long accum __fracttauta` (*long long accum* a) [Runtime Function]
`signed char __fracttaqi` (*long long accum* a) [Runtime Function]
`short __fracttahi` (*long long accum* a) [Runtime Function]
`int __fracttasi` (*long long accum* a) [Runtime Function]
`long __fracttadi` (*long long accum* a) [Runtime Function]
`long long __fracttati` (*long long accum* a) [Runtime Function]
`float __fracttasf` (*long long accum* a) [Runtime Function]
`double __fracttadf` (*long long accum* a) [Runtime Function]
`short fract __fractuqqqq` (*unsigned short fract* a) [Runtime Function]
`fract __fractuqqhq` (*unsigned short fract* a) [Runtime Function]
`long fract __fractuqqsq` (*unsigned short fract* a) [Runtime Function]
`long long fract __fractuqqdq` (*unsigned short fract* a) [Runtime Function]
`short accum __fractuqqha` (*unsigned short fract* a) [Runtime Function]
`accum __fractuqqsa` (*unsigned short fract* a) [Runtime Function]
`long accum __fractuqqda` (*unsigned short fract* a) [Runtime Function]
`long long accum __fractuqqta` (*unsigned short fract* a) [Runtime Function]
`unsigned fract __fractuqquhq2` (*unsigned short fract* a) [Runtime Function]
`unsigned long fract __fractuqqusq2` (*unsigned short fract* a) [Runtime Function]
`unsigned long long fract __fractuqqudq2` (*unsigned short fract* a) [Runtime Function]
`unsigned short accum __fractuqquha` (*unsigned short fract* a) [Runtime Function]
`unsigned accum __fractuqqusa` (*unsigned short fract* a) [Runtime Function]

`unsigned long accum __fractuqquda` (*unsigned short fract* `a`) [Runtime Function]
`unsigned long long accum __fractuqquta` (*unsigned short fract* `a`) [Runtime Function]
`signed char __fractuqqqi` (*unsigned short fract* `a`) [Runtime Function]
`short __fractuqqhi` (*unsigned short fract* `a`) [Runtime Function]
`int __fractuqqsi` (*unsigned short fract* `a`) [Runtime Function]
`long __fractuqqdi` (*unsigned short fract* `a`) [Runtime Function]
`long long __fractuqqti` (*unsigned short fract* `a`) [Runtime Function]
`float __fractuqqsf` (*unsigned short fract* `a`) [Runtime Function]
`double __fractuqqdf` (*unsigned short fract* `a`) [Runtime Function]
`short fract __fractuhqqq` (*unsigned fract* `a`) [Runtime Function]
`fract __fractuhqhq` (*unsigned fract* `a`) [Runtime Function]
`long fract __fractuhqsq` (*unsigned fract* `a`) [Runtime Function]
`long long fract __fractuhqdq` (*unsigned fract* `a`) [Runtime Function]
`short accum __fractuhqha` (*unsigned fract* `a`) [Runtime Function]
`accum __fractuhqsa` (*unsigned fract* `a`) [Runtime Function]
`long accum __fractuhqda` (*unsigned fract* `a`) [Runtime Function]
`long long accum __fractuhqta` (*unsigned fract* `a`) [Runtime Function]
`unsigned short fract __fractuhquqq2` (*unsigned fract* `a`) [Runtime Function]
`unsigned long fract __fractuhqusq2` (*unsigned fract* `a`) [Runtime Function]
`unsigned long long fract __fractuhqudq2` (*unsigned fract* `a`) [Runtime Function]
`unsigned short accum __fractuhquha` (*unsigned fract* `a`) [Runtime Function]
`unsigned accum __fractuhqusa` (*unsigned fract* `a`) [Runtime Function]
`unsigned long accum __fractuhquda` (*unsigned fract* `a`) [Runtime Function]
`unsigned long long accum __fractuhquta` (*unsigned fract* `a`) [Runtime Function]
`signed char __fractuhqqi` (*unsigned fract* `a`) [Runtime Function]
`short __fractuhqhi` (*unsigned fract* `a`) [Runtime Function]
`int __fractuhqsi` (*unsigned fract* `a`) [Runtime Function]
`long __fractuhqdi` (*unsigned fract* `a`) [Runtime Function]
`long long __fractuhqti` (*unsigned fract* `a`) [Runtime Function]
`float __fractuhqsf` (*unsigned fract* `a`) [Runtime Function]
`double __fractuhqdf` (*unsigned fract* `a`) [Runtime Function]
`short fract __fractusqqq` (*unsigned long fract* `a`) [Runtime Function]
`fract __fractusqhq` (*unsigned long fract* `a`) [Runtime Function]
`long fract __fractusqsq` (*unsigned long fract* `a`) [Runtime Function]
`long long fract __fractusqdq` (*unsigned long fract* `a`) [Runtime Function]
`short accum __fractusqha` (*unsigned long fract* `a`) [Runtime Function]
`accum __fractusqsa` (*unsigned long fract* `a`) [Runtime Function]
`long accum __fractusqda` (*unsigned long fract* `a`) [Runtime Function]
`long long accum __fractusqta` (*unsigned long fract* `a`) [Runtime Function]
`unsigned short fract __fractusquqq2` (*unsigned long fract* `a`) [Runtime Function]
`unsigned fract __fractusquhq2` (*unsigned long fract* `a`) [Runtime Function]

`unsigned long long fract __fractusqudq2` (*unsigned long fract* a) [Runtime Function]
`unsigned short accum __fractusquha` (*unsigned long fract* a) [Runtime Function]
`unsigned accum __fractusqusa` (*unsigned long fract* a) [Runtime Function]
`unsigned long accum __fractusquda` (*unsigned long fract* a) [Runtime Function]
`unsigned long long accum __fractusquta` (*unsigned long fract* a) [Runtime Function]
`signed char __fractusqqi` (*unsigned long fract* a) [Runtime Function]
`short __fractusqhi` (*unsigned long fract* a) [Runtime Function]
`int __fractusqsi` (*unsigned long fract* a) [Runtime Function]
`long __fractusqdi` (*unsigned long fract* a) [Runtime Function]
`long long __fractusqti` (*unsigned long fract* a) [Runtime Function]
`float __fractusqsf` (*unsigned long fract* a) [Runtime Function]
`double __fractusqdf` (*unsigned long fract* a) [Runtime Function]
`short fract __fractudqqq` (*unsigned long long fract* a) [Runtime Function]
`fract __fractudqhq` (*unsigned long long fract* a) [Runtime Function]
`long fract __fractudqsq` (*unsigned long long fract* a) [Runtime Function]
`long long fract __fractudqdq` (*unsigned long long fract* a) [Runtime Function]
`short accum __fractudqha` (*unsigned long long fract* a) [Runtime Function]
`accum __fractudqsa` (*unsigned long long fract* a) [Runtime Function]
`long accum __fractudqda` (*unsigned long long fract* a) [Runtime Function]
`long long accum __fractudqta` (*unsigned long long fract* a) [Runtime Function]
`unsigned short fract __fractudquqq2` (*unsigned long long fract* a) [Runtime Function]
`unsigned fract __fractudquhq2` (*unsigned long long fract* a) [Runtime Function]
`unsigned long fract __fractudqusq2` (*unsigned long long fract* a) [Runtime Function]
`unsigned short accum __fractudquha` (*unsigned long long fract* a) [Runtime Function]
`unsigned accum __fractudqusa` (*unsigned long long fract* a) [Runtime Function]
`unsigned long accum __fractudquda` (*unsigned long long fract* a) [Runtime Function]
`unsigned long long accum __fractudquta` (*unsigned long long fract* a) [Runtime Function]
`signed char __fractudqqi` (*unsigned long long fract* a) [Runtime Function]
`short __fractudqhi` (*unsigned long long fract* a) [Runtime Function]
`int __fractudqsi` (*unsigned long long fract* a) [Runtime Function]
`long __fractudqdi` (*unsigned long long fract* a) [Runtime Function]
`long long __fractudqti` (*unsigned long long fract* a) [Runtime Function]
`float __fractudqsf` (*unsigned long long fract* a) [Runtime Function]
`double __fractudqdf` (*unsigned long long fract* a) [Runtime Function]
`short fract __fractuhaqq` (*unsigned short accum* a) [Runtime Function]
`fract __fractuhahq` (*unsigned short accum* a) [Runtime Function]
`long fract __fractuhasq` (*unsigned short accum* a) [Runtime Function]
`long long fract __fractuhadq` (*unsigned short accum* a) [Runtime Function]
`short accum __fractuhaha` (*unsigned short accum* a) [Runtime Function]

`accum __fractuhasa` (*unsigned short accum* `a`) [Runtime Function]
`long accum __fractuhada` (*unsigned short accum* `a`) [Runtime Function]
`long long accum __fractuhata` (*unsigned short accum* `a`) [Runtime Function]
`unsigned short fract __fractuhauqq` (*unsigned short accum* `a`) [Runtime Function]
`unsigned fract __fractuhauhq` (*unsigned short accum* `a`) [Runtime Function]
`unsigned long fract __fractuhausq` (*unsigned short accum* `a`) [Runtime Function]
`unsigned long long fract __fractuhaudq` (*unsigned short accum* `a`) [Runtime Function]
`unsigned accum __fractuhausa2` (*unsigned short accum* `a`) [Runtime Function]
`unsigned long accum __fractuhauda2` (*unsigned short accum* `a`) [Runtime Function]
`unsigned long long accum __fractuhauta2` (*unsigned short accum* `a`) [Runtime Function]
`signed char __fractuhaqi` (*unsigned short accum* `a`) [Runtime Function]
`short __fractuhahi` (*unsigned short accum* `a`) [Runtime Function]
`int __fractuhasi` (*unsigned short accum* `a`) [Runtime Function]
`long __fractuhadi` (*unsigned short accum* `a`) [Runtime Function]
`long long __fractuhati` (*unsigned short accum* `a`) [Runtime Function]
`float __fractuhasf` (*unsigned short accum* `a`) [Runtime Function]
`double __fractuhadf` (*unsigned short accum* `a`) [Runtime Function]
`short fract __fractusaqq` (*unsigned accum* `a`) [Runtime Function]
`fract __fractusahq` (*unsigned accum* `a`) [Runtime Function]
`long fract __fractusasq` (*unsigned accum* `a`) [Runtime Function]
`long long fract __fractusadq` (*unsigned accum* `a`) [Runtime Function]
`short accum __fractusaha` (*unsigned accum* `a`) [Runtime Function]
`accum __fractusasa` (*unsigned accum* `a`) [Runtime Function]
`long accum __fractusada` (*unsigned accum* `a`) [Runtime Function]
`long long accum __fractusata` (*unsigned accum* `a`) [Runtime Function]
`unsigned short fract __fractusauqq` (*unsigned accum* `a`) [Runtime Function]
`unsigned fract __fractusauhq` (*unsigned accum* `a`) [Runtime Function]
`unsigned long fract __fractusausq` (*unsigned accum* `a`) [Runtime Function]
`unsigned long long fract __fractusaudq` (*unsigned accum* `a`) [Runtime Function]
`unsigned short accum __fractusauha2` (*unsigned accum* `a`) [Runtime Function]
`unsigned long accum __fractusauda2` (*unsigned accum* `a`) [Runtime Function]
`unsigned long long accum __fractusauta2` (*unsigned accum* `a`) [Runtime Function]
`signed char __fractusaqi` (*unsigned accum* `a`) [Runtime Function]
`short __fractusahi` (*unsigned accum* `a`) [Runtime Function]
`int __fractusasi` (*unsigned accum* `a`) [Runtime Function]
`long __fractusadi` (*unsigned accum* `a`) [Runtime Function]
`long long __fractusati` (*unsigned accum* `a`) [Runtime Function]
`float __fractusasf` (*unsigned accum* `a`) [Runtime Function]
`double __fractusadf` (*unsigned accum* `a`) [Runtime Function]
`short fract __fractudaqq` (*unsigned long accum* `a`) [Runtime Function]

`fract __fractudahq` (*unsigned long accum* `a`) [Runtime Function]
`long fract __fractudasq` (*unsigned long accum* `a`) [Runtime Function]
`long long fract __fractudadq` (*unsigned long accum* `a`) [Runtime Function]
`short accum __fractudaha` (*unsigned long accum* `a`) [Runtime Function]
`accum __fractudasa` (*unsigned long accum* `a`) [Runtime Function]
`long accum __fractudada` (*unsigned long accum* `a`) [Runtime Function]
`long long accum __fractudata` (*unsigned long accum* `a`) [Runtime Function]
`unsigned short fract __fractudauqq` (*unsigned long accum* `a`) [Runtime Function]
`unsigned fract __fractudauhq` (*unsigned long accum* `a`) [Runtime Function]
`unsigned long fract __fractudausq` (*unsigned long accum* `a`) [Runtime Function]
`unsigned long long fract __fractudaudq` (*unsigned long accum* `a`) [Runtime Function]
`unsigned short accum __fractudauha2` (*unsigned long accum* `a`) [Runtime Function]
`unsigned accum __fractudausa2` (*unsigned long accum* `a`) [Runtime Function]
`unsigned long long accum __fractudauta2` (*unsigned long accum* `a`) [Runtime Function]
`signed char __fractudaqi` (*unsigned long accum* `a`) [Runtime Function]
`short __fractudahi` (*unsigned long accum* `a`) [Runtime Function]
`int __fractudasi` (*unsigned long accum* `a`) [Runtime Function]
`long __fractudadi` (*unsigned long accum* `a`) [Runtime Function]
`long long __fractudati` (*unsigned long accum* `a`) [Runtime Function]
`float __fractudasf` (*unsigned long accum* `a`) [Runtime Function]
`double __fractudadf` (*unsigned long accum* `a`) [Runtime Function]
`short fract __fractutaqq` (*unsigned long long accum* `a`) [Runtime Function]
`fract __fractutahq` (*unsigned long long accum* `a`) [Runtime Function]
`long fract __fractutasq` (*unsigned long long accum* `a`) [Runtime Function]
`long long fract __fractutadq` (*unsigned long long accum* `a`) [Runtime Function]
`short accum __fractutaha` (*unsigned long long accum* `a`) [Runtime Function]
`accum __fractutasa` (*unsigned long long accum* `a`) [Runtime Function]
`long accum __fractutada` (*unsigned long long accum* `a`) [Runtime Function]
`long long accum __fractutata` (*unsigned long long accum* `a`) [Runtime Function]
`unsigned short fract __fractutauqq` (*unsigned long long accum* `a`) [Runtime Function]
`unsigned fract __fractutauhq` (*unsigned long long accum* `a`) [Runtime Function]
`unsigned long fract __fractutausq` (*unsigned long long accum* `a`) [Runtime Function]
`unsigned long long fract __fractutaudq` (*unsigned long long accum* `a`) [Runtime Function]
`unsigned short accum __fractutauha2` (*unsigned long long accum* `a`) [Runtime Function]
`unsigned accum __fractutausa2` (*unsigned long long accum* `a`) [Runtime Function]
`unsigned long accum __fractutauda2` (*unsigned long long accum* `a`) [Runtime Function]

`signed char __fractutaqi` (*unsigned long long accum* a) [Runtime Function]
`short __fractutahi` (*unsigned long long accum* a) [Runtime Function]
`int __fractutasi` (*unsigned long long accum* a) [Runtime Function]
`long __fractutadi` (*unsigned long long accum* a) [Runtime Function]
`long long __fractutati` (*unsigned long long accum* a) [Runtime Function]
`float __fractutasf` (*unsigned long long accum* a) [Runtime Function]
`double __fractutadf` (*unsigned long long accum* a) [Runtime Function]
`short fract __fractqiqq` (*signed char* a) [Runtime Function]
`fract __fractqihq` (*signed char* a) [Runtime Function]
`long fract __fractqisq` (*signed char* a) [Runtime Function]
`long long fract __fractqidq` (*signed char* a) [Runtime Function]
`short accum __fractqiha` (*signed char* a) [Runtime Function]
`accum __fractqisa` (*signed char* a) [Runtime Function]
`long accum __fractqida` (*signed char* a) [Runtime Function]
`long long accum __fractqita` (*signed char* a) [Runtime Function]
`unsigned short fract __fractqiuqq` (*signed char* a) [Runtime Function]
`unsigned fract __fractqiuhq` (*signed char* a) [Runtime Function]
`unsigned long fract __fractqiusq` (*signed char* a) [Runtime Function]
`unsigned long long fract __fractqiudq` (*signed char* a) [Runtime Function]
`unsigned short accum __fractqiuha` (*signed char* a) [Runtime Function]
`unsigned accum __fractqiusa` (*signed char* a) [Runtime Function]
`unsigned long accum __fractqiuda` (*signed char* a) [Runtime Function]
`unsigned long long accum __fractqiuta` (*signed char* a) [Runtime Function]
`short fract __fracthiqq` (*short* a) [Runtime Function]
`fract __fracthihq` (*short* a) [Runtime Function]
`long fract __fracthisq` (*short* a) [Runtime Function]
`long long fract __fracthidq` (*short* a) [Runtime Function]
`short accum __fracthiha` (*short* a) [Runtime Function]
`accum __fracthisa` (*short* a) [Runtime Function]
`long accum __fracthida` (*short* a) [Runtime Function]
`long long accum __fracthita` (*short* a) [Runtime Function]
`unsigned short fract __fracthiuqq` (*short* a) [Runtime Function]
`unsigned fract __fracthiuhq` (*short* a) [Runtime Function]
`unsigned long fract __fracthiusq` (*short* a) [Runtime Function]
`unsigned long long fract __fracthiudq` (*short* a) [Runtime Function]
`unsigned short accum __fracthiuha` (*short* a) [Runtime Function]
`unsigned accum __fracthiusa` (*short* a) [Runtime Function]
`unsigned long accum __fracthiuda` (*short* a) [Runtime Function]
`unsigned long long accum __fracthiuta` (*short* a) [Runtime Function]
`short fract __fractsiqq` (*int* a) [Runtime Function]
`fract __fractsihq` (*int* a) [Runtime Function]
`long fract __fractsisq` (*int* a) [Runtime Function]
`long long fract __fractsidq` (*int* a) [Runtime Function]
`short accum __fractsiha` (*int* a) [Runtime Function]
`accum __fractsisa` (*int* a) [Runtime Function]
`long accum __fractsida` (*int* a) [Runtime Function]
`long long accum __fractsita` (*int* a) [Runtime Function]

`unsigned short fract __fractsiuqq` (*int* a) [Runtime Function]
`unsigned fract __fractsiuhq` (*int* a) [Runtime Function]
`unsigned long fract __fractsiusq` (*int* a) [Runtime Function]
`unsigned long long fract __fractsiudq` (*int* a) [Runtime Function]
`unsigned short accum __fractsiuha` (*int* a) [Runtime Function]
`unsigned accum __fractsiusa` (*int* a) [Runtime Function]
`unsigned long accum __fractsiuda` (*int* a) [Runtime Function]
`unsigned long long accum __fractsiuta` (*int* a) [Runtime Function]
`short fract __fractdiqq` (*long* a) [Runtime Function]
`fract __fractdihq` (*long* a) [Runtime Function]
`long fract __fractdisq` (*long* a) [Runtime Function]
`long long fract __fractdidq` (*long* a) [Runtime Function]
`short accum __fractdiha` (*long* a) [Runtime Function]
`accum __fractdisa` (*long* a) [Runtime Function]
`long accum __fractdida` (*long* a) [Runtime Function]
`long long accum __fractdita` (*long* a) [Runtime Function]
`unsigned short fract __fractdiuqq` (*long* a) [Runtime Function]
`unsigned fract __fractdiuhq` (*long* a) [Runtime Function]
`unsigned long fract __fractdiusq` (*long* a) [Runtime Function]
`unsigned long long fract __fractdiudq` (*long* a) [Runtime Function]
`unsigned short accum __fractdiuha` (*long* a) [Runtime Function]
`unsigned accum __fractdiusa` (*long* a) [Runtime Function]
`unsigned long accum __fractdiuda` (*long* a) [Runtime Function]
`unsigned long long accum __fractdiuta` (*long* a) [Runtime Function]
`short fract __fracttiqq` (*long long* a) [Runtime Function]
`fract __fracttihq` (*long long* a) [Runtime Function]
`long fract __fracttisq` (*long long* a) [Runtime Function]
`long long fract __fracttidq` (*long long* a) [Runtime Function]
`short accum __fracttiha` (*long long* a) [Runtime Function]
`accum __fracttisa` (*long long* a) [Runtime Function]
`long accum __fracttida` (*long long* a) [Runtime Function]
`long long accum __fracttita` (*long long* a) [Runtime Function]
`unsigned short fract __fracttiuqq` (*long long* a) [Runtime Function]
`unsigned fract __fracttiuhq` (*long long* a) [Runtime Function]
`unsigned long fract __fracttiusq` (*long long* a) [Runtime Function]
`unsigned long long fract __fracttiudq` (*long long* a) [Runtime Function]
`unsigned short accum __fracttiuha` (*long long* a) [Runtime Function]
`unsigned accum __fracttiusa` (*long long* a) [Runtime Function]
`unsigned long accum __fracttiuda` (*long long* a) [Runtime Function]
`unsigned long long accum __fracttiuta` (*long long* a) [Runtime Function]
`short fract __fractsfqq` (*float* a) [Runtime Function]
`fract __fractsfhq` (*float* a) [Runtime Function]
`long fract __fractsfsq` (*float* a) [Runtime Function]
`long long fract __fractsfdq` (*float* a) [Runtime Function]
`short accum __fractsfha` (*float* a) [Runtime Function]
`accum __fractsfsa` (*float* a) [Runtime Function]
`long accum __fractsfda` (*float* a) [Runtime Function]

`long long accum __fractsfta` (*float* a) [Runtime Function]
`unsigned short fract __fractsfuqq` (*float* a) [Runtime Function]
`unsigned fract __fractsfuhq` (*float* a) [Runtime Function]
`unsigned long fract __fractsfusq` (*float* a) [Runtime Function]
`unsigned long long fract __fractsfudq` (*float* a) [Runtime Function]
`unsigned short accum __fractsfuha` (*float* a) [Runtime Function]
`unsigned accum __fractsfusa` (*float* a) [Runtime Function]
`unsigned long accum __fractsfuda` (*float* a) [Runtime Function]
`unsigned long long accum __fractsfuta` (*float* a) [Runtime Function]
`short fract __fractdfqq` (*double* a) [Runtime Function]
`fract __fractdfhq` (*double* a) [Runtime Function]
`long fract __fractdfsq` (*double* a) [Runtime Function]
`long long fract __fractdfdq` (*double* a) [Runtime Function]
`short accum __fractdfha` (*double* a) [Runtime Function]
`accum __fractdfsa` (*double* a) [Runtime Function]
`long accum __fractdfda` (*double* a) [Runtime Function]
`long long accum __fractdfta` (*double* a) [Runtime Function]
`unsigned short fract __fractdfuqq` (*double* a) [Runtime Function]
`unsigned fract __fractdfuhq` (*double* a) [Runtime Function]
`unsigned long fract __fractdfusq` (*double* a) [Runtime Function]
`unsigned long long fract __fractdfudq` (*double* a) [Runtime Function]
`unsigned short accum __fractdfuha` (*double* a) [Runtime Function]
`unsigned accum __fractdfusa` (*double* a) [Runtime Function]
`unsigned long accum __fractdfuda` (*double* a) [Runtime Function]
`unsigned long long accum __fractdfuta` (*double* a) [Runtime Function]

These functions convert from fractional and signed non-fractionals to fractionals and signed non-fractionals, without saturation.

`fract __satfractqqhq2` (*short fract* a) [Runtime Function]
`long fract __satfractqqsq2` (*short fract* a) [Runtime Function]
`long long fract __satfractqqdq2` (*short fract* a) [Runtime Function]
`short accum __satfractqqha` (*short fract* a) [Runtime Function]
`accum __satfractqqsa` (*short fract* a) [Runtime Function]
`long accum __satfractqqda` (*short fract* a) [Runtime Function]
`long long accum __satfractqqta` (*short fract* a) [Runtime Function]
`unsigned short fract __satfractqquqq` (*short fract* a) [Runtime Function]
`unsigned fract __satfractqquhq` (*short fract* a) [Runtime Function]
`unsigned long fract __satfractqqusq` (*short fract* a) [Runtime Function]
`unsigned long long fract __satfractqqudq` (*short fract* a) [Runtime Function]
`unsigned short accum __satfractqquha` (*short fract* a) [Runtime Function]
`unsigned accum __satfractqqusa` (*short fract* a) [Runtime Function]
`unsigned long accum __satfractqquda` (*short fract* a) [Runtime Function]
`unsigned long long accum __satfractqquta` (*short fract* a) [Runtime Function]
`short fract __satfracthqqq2` (*fract* a) [Runtime Function]
`long fract __satfracthqsq2` (*fract* a) [Runtime Function]

`long long fract __satfracthqdq2` (*fract* a) [Runtime Function]
`short accum __satfracthqha` (*fract* a) [Runtime Function]
`accum __satfracthqsa` (*fract* a) [Runtime Function]
`long accum __satfracthqda` (*fract* a) [Runtime Function]
`long long accum __satfracthqta` (*fract* a) [Runtime Function]
`unsigned short fract __satfracthquqq` (*fract* a) [Runtime Function]
`unsigned fract __satfracthquhq` (*fract* a) [Runtime Function]
`unsigned long fract __satfracthqusq` (*fract* a) [Runtime Function]
`unsigned long long fract __satfracthqudq` (*fract* a) [Runtime Function]
`unsigned short accum __satfracthquha` (*fract* a) [Runtime Function]
`unsigned accum __satfracthqusa` (*fract* a) [Runtime Function]
`unsigned long accum __satfracthquda` (*fract* a) [Runtime Function]
`unsigned long long accum __satfracthquta` (*fract* a) [Runtime Function]
`short fract __satfractsqqq2` (*long fract* a) [Runtime Function]
`fract __satfractsqhq2` (*long fract* a) [Runtime Function]
`long long fract __satfractsqdq2` (*long fract* a) [Runtime Function]
`short accum __satfractsqha` (*long fract* a) [Runtime Function]
`accum __satfractsqsa` (*long fract* a) [Runtime Function]
`long accum __satfractsqda` (*long fract* a) [Runtime Function]
`long long accum __satfractsqta` (*long fract* a) [Runtime Function]
`unsigned short fract __satfractsquqq` (*long fract* a) [Runtime Function]
`unsigned fract __satfractsquhq` (*long fract* a) [Runtime Function]
`unsigned long fract __satfractsqusq` (*long fract* a) [Runtime Function]
`unsigned long long fract __satfractsqudq` (*long fract* a) [Runtime Function]
`unsigned short accum __satfractsquha` (*long fract* a) [Runtime Function]
`unsigned accum __satfractsqusa` (*long fract* a) [Runtime Function]
`unsigned long accum __satfractsquda` (*long fract* a) [Runtime Function]
`unsigned long long accum __satfractsquta` (*long fract* a) [Runtime Function]
`short fract __satfractdqqq2` (*long long fract* a) [Runtime Function]
`fract __satfractdqhq2` (*long long fract* a) [Runtime Function]
`long fract __satfractdqsq2` (*long long fract* a) [Runtime Function]
`short accum __satfractdqha` (*long long fract* a) [Runtime Function]
`accum __satfractdqsa` (*long long fract* a) [Runtime Function]
`long accum __satfractdqda` (*long long fract* a) [Runtime Function]
`long long accum __satfractdqta` (*long long fract* a) [Runtime Function]
`unsigned short fract __satfractdquqq` (*long long fract* a) [Runtime Function]
`unsigned fract __satfractdquhq` (*long long fract* a) [Runtime Function]
`unsigned long fract __satfractdqusq` (*long long fract* a) [Runtime Function]
`unsigned long long fract __satfractdqudq` (*long long fract* a) [Runtime Function]
`unsigned short accum __satfractdquha` (*long long fract* a) [Runtime Function]
`unsigned accum __satfractdqusa` (*long long fract* a) [Runtime Function]
`unsigned long accum __satfractdquda` (*long long fract* a) [Runtime Function]
`unsigned long long accum __satfractdquta` (*long long fract* a) [Runtime Function]
`short fract __satfracthaqq` (*short accum* a) [Runtime Function]
`fract __satfracthahq` (*short accum* a) [Runtime Function]

`long fract __satfracthasq` (*short accum* a) [Runtime Function]
`long long fract __satfracthadq` (*short accum* a) [Runtime Function]
`accum __satfracthasa2` (*short accum* a) [Runtime Function]
`long accum __satfracthada2` (*short accum* a) [Runtime Function]
`long long accum __satfracthata2` (*short accum* a) [Runtime Function]
`unsigned short fract __satfracthauqq` (*short accum* a) [Runtime Function]
`unsigned fract __satfracthauhq` (*short accum* a) [Runtime Function]
`unsigned long fract __satfracthausq` (*short accum* a) [Runtime Function]
`unsigned long long fract __satfracthaudq` (*short accum* a) [Runtime Function]
`unsigned short accum __satfracthauha` (*short accum* a) [Runtime Function]
`unsigned accum __satfracthausa` (*short accum* a) [Runtime Function]
`unsigned long accum __satfracthauda` (*short accum* a) [Runtime Function]
`unsigned long long accum __satfracthauta` (*short accum* a) [Runtime Function]
`short fract __satfractsaqq` (*accum* a) [Runtime Function]
`fract __satfractsahq` (*accum* a) [Runtime Function]
`long fract __satfractsasq` (*accum* a) [Runtime Function]
`long long fract __satfractsadq` (*accum* a) [Runtime Function]
`short accum __satfractsaha2` (*accum* a) [Runtime Function]
`long accum __satfractsada2` (*accum* a) [Runtime Function]
`long long accum __satfractsata2` (*accum* a) [Runtime Function]
`unsigned short fract __satfractsauqq` (*accum* a) [Runtime Function]
`unsigned fract __satfractsauhq` (*accum* a) [Runtime Function]
`unsigned long fract __satfractsausq` (*accum* a) [Runtime Function]
`unsigned long long fract __satfractsaudq` (*accum* a) [Runtime Function]
`unsigned short accum __satfractsauha` (*accum* a) [Runtime Function]
`unsigned accum __satfractsausa` (*accum* a) [Runtime Function]
`unsigned long accum __satfractsauda` (*accum* a) [Runtime Function]
`unsigned long long accum __satfractsauta` (*accum* a) [Runtime Function]
`short fract __satfractdaqq` (*long accum* a) [Runtime Function]
`fract __satfractdahq` (*long accum* a) [Runtime Function]
`long fract __satfractdasq` (*long accum* a) [Runtime Function]
`long long fract __satfractdadq` (*long accum* a) [Runtime Function]
`short accum __satfractdaha2` (*long accum* a) [Runtime Function]
`accum __satfractdasa2` (*long accum* a) [Runtime Function]
`long long accum __satfractdata2` (*long accum* a) [Runtime Function]
`unsigned short fract __satfractdauqq` (*long accum* a) [Runtime Function]
`unsigned fract __satfractdauhq` (*long accum* a) [Runtime Function]
`unsigned long fract __satfractdausq` (*long accum* a) [Runtime Function]
`unsigned long long fract __satfractdaudq` (*long accum* a) [Runtime Function]
`unsigned short accum __satfractdauha` (*long accum* a) [Runtime Function]
`unsigned accum __satfractdausa` (*long accum* a) [Runtime Function]
`unsigned long accum __satfractdauda` (*long accum* a) [Runtime Function]
`unsigned long long accum __satfractdauta` (*long accum* a) [Runtime Function]

`short fract __satfracttaqq` (*long long accum* a) [Runtime Function]
`fract __satfracttahq` (*long long accum* a) [Runtime Function]
`long fract __satfracttasq` (*long long accum* a) [Runtime Function]
`long long fract __satfracttadq` (*long long accum* a) [Runtime Function]
`short accum __satfracttaha2` (*long long accum* a) [Runtime Function]
`accum __satfracttasa2` (*long long accum* a) [Runtime Function]
`long accum __satfracttada2` (*long long accum* a) [Runtime Function]
`unsigned short fract __satfracttauqq` (*long long accum* a) [Runtime Function]
`unsigned fract __satfracttauhq` (*long long accum* a) [Runtime Function]
`unsigned long fract __satfracttausq` (*long long accum* a) [Runtime Function]
`unsigned long long fract __satfracttaudq` (*long long accum* a) [Runtime Function]
`unsigned short accum __satfracttauha` (*long long accum* a) [Runtime Function]
`unsigned accum __satfracttausa` (*long long accum* a) [Runtime Function]
`unsigned long accum __satfracttauda` (*long long accum* a) [Runtime Function]
`unsigned long long accum __satfracttauta` (*long long accum* a) [Runtime Function]
`short fract __satfractuqqqq` (*unsigned short fract* a) [Runtime Function]
`fract __satfractuqqhq` (*unsigned short fract* a) [Runtime Function]
`long fract __satfractuqqsq` (*unsigned short fract* a) [Runtime Function]
`long long fract __satfractuqqdq` (*unsigned short fract* a) [Runtime Function]
`short accum __satfractuqqha` (*unsigned short fract* a) [Runtime Function]
`accum __satfractuqqsa` (*unsigned short fract* a) [Runtime Function]
`long accum __satfractuqqda` (*unsigned short fract* a) [Runtime Function]
`long long accum __satfractuqqta` (*unsigned short fract* a) [Runtime Function]
`unsigned fract __satfractuqquhq2` (*unsigned short fract* a) [Runtime Function]
`unsigned long fract __satfractuqqusq2` (*unsigned short fract* a) [Runtime Function]
`unsigned long long fract __satfractuqqudq2` (*unsigned short fract* a) [Runtime Function]
`unsigned short accum __satfractuqquha` (*unsigned short fract* a) [Runtime Function]
`unsigned accum __satfractuqqusa` (*unsigned short fract* a) [Runtime Function]
`unsigned long accum __satfractuqquda` (*unsigned short fract* a) [Runtime Function]
`unsigned long long accum __satfractuqquta` (*unsigned short fract* a) [Runtime Function]
`short fract __satfractuhqqq` (*unsigned fract* a) [Runtime Function]
`fract __satfractuhqhq` (*unsigned fract* a) [Runtime Function]
`long fract __satfractuhqsq` (*unsigned fract* a) [Runtime Function]
`long long fract __satfractuhqdq` (*unsigned fract* a) [Runtime Function]
`short accum __satfractuhqha` (*unsigned fract* a) [Runtime Function]
`accum __satfractuhqsa` (*unsigned fract* a) [Runtime Function]
`long accum __satfractuhqda` (*unsigned fract* a) [Runtime Function]
`long long accum __satfractuhqta` (*unsigned fract* a) [Runtime Function]

`unsigned short fract __satfractuhquqq2` (*unsigned fract* a) [Runtime Function]
`unsigned long fract __satfractuhqusq2` (*unsigned fract* a) [Runtime Function]
`unsigned long long fract __satfractuhqudq2` (*unsigned fract* a) [Runtime Function]
`unsigned short accum __satfractuhquha` (*unsigned fract* a) [Runtime Function]
`unsigned accum __satfractuhqusa` (*unsigned fract* a) [Runtime Function]
`unsigned long accum __satfractuhquda` (*unsigned fract* a) [Runtime Function]
`unsigned long long accum __satfractuhquta` (*unsigned fract* a) [Runtime Function]
`short fract __satfractusqqq` (*unsigned long fract* a) [Runtime Function]
`fract __satfractusqhq` (*unsigned long fract* a) [Runtime Function]
`long fract __satfractusqsq` (*unsigned long fract* a) [Runtime Function]
`long long fract __satfractusqdq` (*unsigned long fract* a) [Runtime Function]
`short accum __satfractusqha` (*unsigned long fract* a) [Runtime Function]
`accum __satfractusqsa` (*unsigned long fract* a) [Runtime Function]
`long accum __satfractusqda` (*unsigned long fract* a) [Runtime Function]
`long long accum __satfractusqta` (*unsigned long fract* a) [Runtime Function]
`unsigned short fract __satfractusquqq2` (*unsigned long fract* a) [Runtime Function]
`unsigned fract __satfractusquhq2` (*unsigned long fract* a) [Runtime Function]
`unsigned long long fract __satfractusqudq2` (*unsigned long fract* a) [Runtime Function]
`unsigned short accum __satfractusquha` (*unsigned long fract* a) [Runtime Function]
`unsigned accum __satfractusqusa` (*unsigned long fract* a) [Runtime Function]
`unsigned long accum __satfractusquda` (*unsigned long fract* a) [Runtime Function]
`unsigned long long accum __satfractusquta` (*unsigned long fract* a) [Runtime Function]
`short fract __satfractudqqq` (*unsigned long long fract* a) [Runtime Function]
`fract __satfractudqhq` (*unsigned long long fract* a) [Runtime Function]
`long fract __satfractudqsq` (*unsigned long long fract* a) [Runtime Function]
`long long fract __satfractudqdq` (*unsigned long long fract* a) [Runtime Function]
`short accum __satfractudqha` (*unsigned long long fract* a) [Runtime Function]
`accum __satfractudqsa` (*unsigned long long fract* a) [Runtime Function]
`long accum __satfractudqda` (*unsigned long long fract* a) [Runtime Function]
`long long accum __satfractudqta` (*unsigned long long fract* a) [Runtime Function]
`unsigned short fract __satfractudquqq2` (*unsigned long long fract* a) [Runtime Function]
`unsigned fract __satfractudquhq2` (*unsigned long long fract* a) [Runtime Function]

`unsigned long fract __satfractudqusq2` (*unsigned long long fract* a) [Runtime Function]
`unsigned short accum __satfractudquha` (*unsigned long long fract* a) [Runtime Function]
`unsigned accum __satfractudqusa` (*unsigned long long fract* a) [Runtime Function]
`unsigned long accum __satfractudquda` (*unsigned long long fract* a) [Runtime Function]
`unsigned long long accum __satfractudquta` (*unsigned long long fract* a) [Runtime Function]
`short fract __satfractuhaqq` (*unsigned short accum* a) [Runtime Function]
`fract __satfractuhahq` (*unsigned short accum* a) [Runtime Function]
`long fract __satfractuhasq` (*unsigned short accum* a) [Runtime Function]
`long long fract __satfractuhadq` (*unsigned short accum* a) [Runtime Function]
`short accum __satfractuhaha` (*unsigned short accum* a) [Runtime Function]
`accum __satfractuhasa` (*unsigned short accum* a) [Runtime Function]
`long accum __satfractuhada` (*unsigned short accum* a) [Runtime Function]
`long long accum __satfractuhata` (*unsigned short accum* a) [Runtime Function]
`unsigned short fract __satfractuhauqq` (*unsigned short accum* a) [Runtime Function]
`unsigned fract __satfractuhauhq` (*unsigned short accum* a) [Runtime Function]
`unsigned long fract __satfractuhausq` (*unsigned short accum* a) [Runtime Function]
`unsigned long long fract __satfractuhaudq` (*unsigned short accum* a) [Runtime Function]
`unsigned accum __satfractuhausa2` (*unsigned short accum* a) [Runtime Function]
`unsigned long accum __satfractuhauda2` (*unsigned short accum* a) [Runtime Function]
`unsigned long long accum __satfractuhauta2` (*unsigned short accum* a) [Runtime Function]
`short fract __satfractusaqq` (*unsigned accum* a) [Runtime Function]
`fract __satfractusahq` (*unsigned accum* a) [Runtime Function]
`long fract __satfractusasq` (*unsigned accum* a) [Runtime Function]
`long long fract __satfractusadq` (*unsigned accum* a) [Runtime Function]
`short accum __satfractusaha` (*unsigned accum* a) [Runtime Function]
`accum __satfractusasa` (*unsigned accum* a) [Runtime Function]
`long accum __satfractusada` (*unsigned accum* a) [Runtime Function]
`long long accum __satfractusata` (*unsigned accum* a) [Runtime Function]
`unsigned short fract __satfractusauqq` (*unsigned accum* a) [Runtime Function]
`unsigned fract __satfractusauhq` (*unsigned accum* a) [Runtime Function]
`unsigned long fract __satfractusausq` (*unsigned accum* a) [Runtime Function]
`unsigned long long fract __satfractusaudq` (*unsigned accum* a) [Runtime Function]

`unsigned short accum __satfractusauha2` (*unsigned accum* a) [Runtime Function]
`unsigned long accum __satfractusauda2` (*unsigned accum* a) [Runtime Function]
`unsigned long long accum __satfractusauta2` (*unsigned accum* a) [Runtime Function]
`short fract __satfractudaqq` (*unsigned long accum* a) [Runtime Function]
`fract __satfractudahq` (*unsigned long accum* a) [Runtime Function]
`long fract __satfractudasq` (*unsigned long accum* a) [Runtime Function]
`long long fract __satfractudadq` (*unsigned long accum* a) [Runtime Function]
`short accum __satfractudaha` (*unsigned long accum* a) [Runtime Function]
`accum __satfractudasa` (*unsigned long accum* a) [Runtime Function]
`long accum __satfractudada` (*unsigned long accum* a) [Runtime Function]
`long long accum __satfractudata` (*unsigned long accum* a) [Runtime Function]
`unsigned short fract __satfractudauqq` (*unsigned long accum* a) [Runtime Function]
`unsigned fract __satfractudauhq` (*unsigned long accum* a) [Runtime Function]
`unsigned long fract __satfractudausq` (*unsigned long accum* a) [Runtime Function]
`unsigned long long fract __satfractudaudq` (*unsigned long accum* a) [Runtime Function]
`unsigned short accum __satfractudauha2` (*unsigned long accum* a) [Runtime Function]
`unsigned accum __satfractudausa2` (*unsigned long accum* a) [Runtime Function]
`unsigned long long accum __satfractudauta2` (*unsigned long accum* a) [Runtime Function]
`short fract __satfractutaqq` (*unsigned long long accum* a) [Runtime Function]
`fract __satfractutahq` (*unsigned long long accum* a) [Runtime Function]
`long fract __satfractutasq` (*unsigned long long accum* a) [Runtime Function]
`long long fract __satfractutadq` (*unsigned long long accum* a) [Runtime Function]
`short accum __satfractutaha` (*unsigned long long accum* a) [Runtime Function]
`accum __satfractutasa` (*unsigned long long accum* a) [Runtime Function]
`long accum __satfractutada` (*unsigned long long accum* a) [Runtime Function]
`long long accum __satfractutata` (*unsigned long long accum* a) [Runtime Function]
`unsigned short fract __satfractutauqq` (*unsigned long long accum* a) [Runtime Function]
`unsigned fract __satfractutauhq` (*unsigned long long accum* a) [Runtime Function]
`unsigned long fract __satfractutausq` (*unsigned long long accum* a) [Runtime Function]
`unsigned long long fract __satfractutaudq` (*unsigned long long accum* a) [Runtime Function]
`unsigned short accum __satfractutauha2` (*unsigned long long accum* a) [Runtime Function]

`unsigned accum __satfractutausa2` (*unsigned long long accum* a) [Runtime Function]
`unsigned long accum __satfractutauda2` (*unsigned long long accum* a) [Runtime Function]
`short fract __satfractqiqq` (*signed char* a) [Runtime Function]
`fract __satfractqihq` (*signed char* a) [Runtime Function]
`long fract __satfractqisq` (*signed char* a) [Runtime Function]
`long long fract __satfractqidq` (*signed char* a) [Runtime Function]
`short accum __satfractqiha` (*signed char* a) [Runtime Function]
`accum __satfractqisa` (*signed char* a) [Runtime Function]
`long accum __satfractqida` (*signed char* a) [Runtime Function]
`long long accum __satfractqita` (*signed char* a) [Runtime Function]
`unsigned short fract __satfractqiuqq` (*signed char* a) [Runtime Function]
`unsigned fract __satfractqiuhq` (*signed char* a) [Runtime Function]
`unsigned long fract __satfractqiusq` (*signed char* a) [Runtime Function]
`unsigned long long fract __satfractqiudq` (*signed char* a) [Runtime Function]
`unsigned short accum __satfractqiuha` (*signed char* a) [Runtime Function]
`unsigned accum __satfractqiusa` (*signed char* a) [Runtime Function]
`unsigned long accum __satfractqiuda` (*signed char* a) [Runtime Function]
`unsigned long long accum __satfractqiuta` (*signed char* a) [Runtime Function]
`short fract __satfracthiqq` (*short* a) [Runtime Function]
`fract __satfracthihq` (*short* a) [Runtime Function]
`long fract __satfracthisq` (*short* a) [Runtime Function]
`long long fract __satfracthidq` (*short* a) [Runtime Function]
`short accum __satfracthiha` (*short* a) [Runtime Function]
`accum __satfracthisa` (*short* a) [Runtime Function]
`long accum __satfracthida` (*short* a) [Runtime Function]
`long long accum __satfracthita` (*short* a) [Runtime Function]
`unsigned short fract __satfracthiuqq` (*short* a) [Runtime Function]
`unsigned fract __satfracthiuhq` (*short* a) [Runtime Function]
`unsigned long fract __satfracthiusq` (*short* a) [Runtime Function]
`unsigned long long fract __satfracthiudq` (*short* a) [Runtime Function]
`unsigned short accum __satfracthiuha` (*short* a) [Runtime Function]
`unsigned accum __satfracthiusa` (*short* a) [Runtime Function]
`unsigned long accum __satfracthiuda` (*short* a) [Runtime Function]
`unsigned long long accum __satfracthiuta` (*short* a) [Runtime Function]
`short fract __satfractsiqq` (*int* a) [Runtime Function]
`fract __satfractsihq` (*int* a) [Runtime Function]
`long fract __satfractsisq` (*int* a) [Runtime Function]
`long long fract __satfractsidq` (*int* a) [Runtime Function]
`short accum __satfractsiha` (*int* a) [Runtime Function]
`accum __satfractsisa` (*int* a) [Runtime Function]
`long accum __satfractsida` (*int* a) [Runtime Function]
`long long accum __satfractsita` (*int* a) [Runtime Function]
`unsigned short fract __satfractsiuqq` (*int* a) [Runtime Function]

`unsigned fract __satfractsiuhq` (*int* a) [Runtime Function]
`unsigned long fract __satfractsiusq` (*int* a) [Runtime Function]
`unsigned long long fract __satfractsiudq` (*int* a) [Runtime Function]
`unsigned short accum __satfractsiuha` (*int* a) [Runtime Function]
`unsigned accum __satfractsiusa` (*int* a) [Runtime Function]
`unsigned long accum __satfractsiuda` (*int* a) [Runtime Function]
`unsigned long long accum __satfractsiuta` (*int* a) [Runtime Function]
`short fract __satfractdiqq` (*long* a) [Runtime Function]
`fract __satfractdihq` (*long* a) [Runtime Function]
`long fract __satfractdisq` (*long* a) [Runtime Function]
`long long fract __satfractdidq` (*long* a) [Runtime Function]
`short accum __satfractdiha` (*long* a) [Runtime Function]
`accum __satfractdisa` (*long* a) [Runtime Function]
`long accum __satfractdida` (*long* a) [Runtime Function]
`long long accum __satfractdita` (*long* a) [Runtime Function]
`unsigned short fract __satfractdiuqq` (*long* a) [Runtime Function]
`unsigned fract __satfractdiuhq` (*long* a) [Runtime Function]
`unsigned long fract __satfractdiusq` (*long* a) [Runtime Function]
`unsigned long long fract __satfractdiudq` (*long* a) [Runtime Function]
`unsigned short accum __satfractdiuha` (*long* a) [Runtime Function]
`unsigned accum __satfractdiusa` (*long* a) [Runtime Function]
`unsigned long accum __satfractdiuda` (*long* a) [Runtime Function]
`unsigned long long accum __satfractdiuta` (*long* a) [Runtime Function]
`short fract __satfracttiqq` (*long long* a) [Runtime Function]
`fract __satfracttihq` (*long long* a) [Runtime Function]
`long fract __satfracttisq` (*long long* a) [Runtime Function]
`long long fract __satfracttidq` (*long long* a) [Runtime Function]
`short accum __satfracttiha` (*long long* a) [Runtime Function]
`accum __satfracttisa` (*long long* a) [Runtime Function]
`long accum __satfracttida` (*long long* a) [Runtime Function]
`long long accum __satfracttita` (*long long* a) [Runtime Function]
`unsigned short fract __satfracttiuqq` (*long long* a) [Runtime Function]
`unsigned fract __satfracttiuhq` (*long long* a) [Runtime Function]
`unsigned long fract __satfracttiusq` (*long long* a) [Runtime Function]
`unsigned long long fract __satfracttiudq` (*long long* a) [Runtime Function]
`unsigned short accum __satfracttiuha` (*long long* a) [Runtime Function]
`unsigned accum __satfracttiusa` (*long long* a) [Runtime Function]
`unsigned long accum __satfracttiuda` (*long long* a) [Runtime Function]
`unsigned long long accum __satfracttiuta` (*long long* a) [Runtime Function]
`short fract __satfractsfqq` (*float* a) [Runtime Function]
`fract __satfractsfhq` (*float* a) [Runtime Function]
`long fract __satfractsfsq` (*float* a) [Runtime Function]
`long long fract __satfractsfdq` (*float* a) [Runtime Function]
`short accum __satfractsfha` (*float* a) [Runtime Function]
`accum __satfractsfsa` (*float* a) [Runtime Function]
`long accum __satfractsfda` (*float* a) [Runtime Function]
`long long accum __satfractsfta` (*float* a) [Runtime Function]

`unsigned short fract __satfractsfuqq` (*float* a) [Runtime Function]
`unsigned fract __satfractsfuhq` (*float* a) [Runtime Function]
`unsigned long fract __satfractsfusq` (*float* a) [Runtime Function]
`unsigned long long fract __satfractsfudq` (*float* a) [Runtime Function]
`unsigned short accum __satfractsfuha` (*float* a) [Runtime Function]
`unsigned accum __satfractsfusa` (*float* a) [Runtime Function]
`unsigned long accum __satfractsfuda` (*float* a) [Runtime Function]
`unsigned long long accum __satfractsfuta` (*float* a) [Runtime Function]
`short fract __satfractdfqq` (*double* a) [Runtime Function]
`fract __satfractdfhq` (*double* a) [Runtime Function]
`long fract __satfractdfsq` (*double* a) [Runtime Function]
`long long fract __satfractdfdq` (*double* a) [Runtime Function]
`short accum __satfractdfha` (*double* a) [Runtime Function]
`accum __satfractdfsa` (*double* a) [Runtime Function]
`long accum __satfractdfda` (*double* a) [Runtime Function]
`long long accum __satfractdfta` (*double* a) [Runtime Function]
`unsigned short fract __satfractdfuqq` (*double* a) [Runtime Function]
`unsigned fract __satfractdfuhq` (*double* a) [Runtime Function]
`unsigned long fract __satfractdfusq` (*double* a) [Runtime Function]
`unsigned long long fract __satfractdfudq` (*double* a) [Runtime Function]
`unsigned short accum __satfractdfuha` (*double* a) [Runtime Function]
`unsigned accum __satfractdfusa` (*double* a) [Runtime Function]
`unsigned long accum __satfractdfuda` (*double* a) [Runtime Function]
`unsigned long long accum __satfractdfuta` (*double* a) [Runtime Function]

The functions convert from fractional and signed non-fractionals to fractionals, with saturation.

`unsigned char __fractunsqqqi` (*short fract* a) [Runtime Function]
`unsigned short __fractunsqqhi` (*short fract* a) [Runtime Function]
`unsigned int __fractunsqqsi` (*short fract* a) [Runtime Function]
`unsigned long __fractunsqqdi` (*short fract* a) [Runtime Function]
`unsigned long long __fractunsqqti` (*short fract* a) [Runtime Function]
`unsigned char __fractunshqqi` (*fract* a) [Runtime Function]
`unsigned short __fractunshqhi` (*fract* a) [Runtime Function]
`unsigned int __fractunshqsi` (*fract* a) [Runtime Function]
`unsigned long __fractunshqdi` (*fract* a) [Runtime Function]
`unsigned long long __fractunshqti` (*fract* a) [Runtime Function]
`unsigned char __fractunssqqi` (*long fract* a) [Runtime Function]
`unsigned short __fractunssqhi` (*long fract* a) [Runtime Function]
`unsigned int __fractunssqsi` (*long fract* a) [Runtime Function]
`unsigned long __fractunssqdi` (*long fract* a) [Runtime Function]
`unsigned long long __fractunssqti` (*long fract* a) [Runtime Function]
`unsigned char __fractunsdqqi` (*long long fract* a) [Runtime Function]
`unsigned short __fractunsdqhi` (*long long fract* a) [Runtime Function]
`unsigned int __fractunsdqsi` (*long long fract* a) [Runtime Function]
`unsigned long __fractunsdqdi` (*long long fract* a) [Runtime Function]
`unsigned long long __fractunsdqti` (*long long fract* a) [Runtime Function]

`unsigned char __fractunshaqi` (*short accum* a) [Runtime Function]
`unsigned short __fractunshahi` (*short accum* a) [Runtime Function]
`unsigned int __fractunshasi` (*short accum* a) [Runtime Function]
`unsigned long __fractunshadi` (*short accum* a) [Runtime Function]
`unsigned long long __fractunshati` (*short accum* a) [Runtime Function]
`unsigned char __fractunssaqi` (*accum* a) [Runtime Function]
`unsigned short __fractunssahi` (*accum* a) [Runtime Function]
`unsigned int __fractunssasi` (*accum* a) [Runtime Function]
`unsigned long __fractunssadi` (*accum* a) [Runtime Function]
`unsigned long long __fractunssati` (*accum* a) [Runtime Function]
`unsigned char __fractunsdaqi` (*long accum* a) [Runtime Function]
`unsigned short __fractunsdahi` (*long accum* a) [Runtime Function]
`unsigned int __fractunsdasi` (*long accum* a) [Runtime Function]
`unsigned long __fractunsdadi` (*long accum* a) [Runtime Function]
`unsigned long long __fractunsdati` (*long accum* a) [Runtime Function]
`unsigned char __fractunstaqi` (*long long accum* a) [Runtime Function]
`unsigned short __fractunstahi` (*long long accum* a) [Runtime Function]
`unsigned int __fractunstasi` (*long long accum* a) [Runtime Function]
`unsigned long __fractunstadi` (*long long accum* a) [Runtime Function]
`unsigned long long __fractunstati` (*long long accum* a) [Runtime Function]
`unsigned char __fractunsuqqqi` (*unsigned short fract* a) [Runtime Function]
`unsigned short __fractunsuqqhi` (*unsigned short fract* a) [Runtime Function]
`unsigned int __fractunsuqqsi` (*unsigned short fract* a) [Runtime Function]
`unsigned long __fractunsuqqdi` (*unsigned short fract* a) [Runtime Function]
`unsigned long long __fractunsuqqti` (*unsigned short fract* a) [Runtime Function]
`unsigned char __fractunsuhqqi` (*unsigned fract* a) [Runtime Function]
`unsigned short __fractunsuhqhi` (*unsigned fract* a) [Runtime Function]
`unsigned int __fractunsuhqsi` (*unsigned fract* a) [Runtime Function]
`unsigned long __fractunsuhqdi` (*unsigned fract* a) [Runtime Function]
`unsigned long long __fractunsuhqti` (*unsigned fract* a) [Runtime Function]
`unsigned char __fractunsusqqi` (*unsigned long fract* a) [Runtime Function]
`unsigned short __fractunsusqhi` (*unsigned long fract* a) [Runtime Function]
`unsigned int __fractunsusqsi` (*unsigned long fract* a) [Runtime Function]
`unsigned long __fractunsusqdi` (*unsigned long fract* a) [Runtime Function]
`unsigned long long __fractunsusqti` (*unsigned long fract* a) [Runtime Function]
`unsigned char __fractunsudqqi` (*unsigned long long fract* a) [Runtime Function]
`unsigned short __fractunsudqhi` (*unsigned long long fract* a) [Runtime Function]
`unsigned int __fractunsudqsi` (*unsigned long long fract* a) [Runtime Function]
`unsigned long __fractunsudqdi` (*unsigned long long fract* a) [Runtime Function]
`unsigned long long __fractunsudqti` (*unsigned long long fract* a) [Runtime Function]
`unsigned char __fractunsuhaqi` (*unsigned short accum* a) [Runtime Function]
`unsigned short __fractunsuhahi` (*unsigned short accum* a) [Runtime Function]
`unsigned int __fractunsuhasi` (*unsigned short accum* a) [Runtime Function]

`unsigned long __fractunsuhadi` (*unsigned short accum* `a`) [Runtime Function]
`unsigned long long __fractunsuhati` (*unsigned short accum* `a`) [Runtime Function]
`unsigned char __fractunsusaqi` (*unsigned accum* `a`) [Runtime Function]
`unsigned short __fractunsusahi` (*unsigned accum* `a`) [Runtime Function]
`unsigned int __fractunsusasi` (*unsigned accum* `a`) [Runtime Function]
`unsigned long __fractunsusadi` (*unsigned accum* `a`) [Runtime Function]
`unsigned long long __fractunsusati` (*unsigned accum* `a`) [Runtime Function]
`unsigned char __fractunsudaqi` (*unsigned long accum* `a`) [Runtime Function]
`unsigned short __fractunsudahi` (*unsigned long accum* `a`) [Runtime Function]
`unsigned int __fractunsudasi` (*unsigned long accum* `a`) [Runtime Function]
`unsigned long __fractunsudadi` (*unsigned long accum* `a`) [Runtime Function]
`unsigned long long __fractunsudati` (*unsigned long accum* `a`) [Runtime Function]
`unsigned char __fractunsutaqi` (*unsigned long long accum* `a`) [Runtime Function]
`unsigned short __fractunsutahi` (*unsigned long long accum* `a`) [Runtime Function]
`unsigned int __fractunsutasi` (*unsigned long long accum* `a`) [Runtime Function]
`unsigned long __fractunsutadi` (*unsigned long long accum* `a`) [Runtime Function]
`unsigned long long __fractunsutati` (*unsigned long long accum* `a`) [Runtime Function]
`short fract __fractunsqiqq` (*unsigned char* `a`) [Runtime Function]
`fract __fractunsqihq` (*unsigned char* `a`) [Runtime Function]
`long fract __fractunsqisq` (*unsigned char* `a`) [Runtime Function]
`long long fract __fractunsqidq` (*unsigned char* `a`) [Runtime Function]
`short accum __fractunsqiha` (*unsigned char* `a`) [Runtime Function]
`accum __fractunsqisa` (*unsigned char* `a`) [Runtime Function]
`long accum __fractunsqida` (*unsigned char* `a`) [Runtime Function]
`long long accum __fractunsqita` (*unsigned char* `a`) [Runtime Function]
`unsigned short fract __fractunsqiuqq` (*unsigned char* `a`) [Runtime Function]
`unsigned fract __fractunsqiuhq` (*unsigned char* `a`) [Runtime Function]
`unsigned long fract __fractunsqiusq` (*unsigned char* `a`) [Runtime Function]
`unsigned long long fract __fractunsqiudq` (*unsigned char* `a`) [Runtime Function]
`unsigned short accum __fractunsqiuha` (*unsigned char* `a`) [Runtime Function]
`unsigned accum __fractunsqiusa` (*unsigned char* `a`) [Runtime Function]
`unsigned long accum __fractunsqiuda` (*unsigned char* `a`) [Runtime Function]
`unsigned long long accum __fractunsqiuta` (*unsigned char* `a`) [Runtime Function]
`short fract __fractunshiqq` (*unsigned short* `a`) [Runtime Function]
`fract __fractunshihq` (*unsigned short* `a`) [Runtime Function]
`long fract __fractunshisq` (*unsigned short* `a`) [Runtime Function]
`long long fract __fractunshidq` (*unsigned short* `a`) [Runtime Function]
`short accum __fractunshiha` (*unsigned short* `a`) [Runtime Function]
`accum __fractunshisa` (*unsigned short* `a`) [Runtime Function]

`long accum __fractunshida` (*unsigned short* `a`) [Runtime Function]
`long long accum __fractunshita` (*unsigned short* `a`) [Runtime Function]
`unsigned short fract __fractunshiuqq` (*unsigned short* `a`) [Runtime Function]
`unsigned fract __fractunshiuhq` (*unsigned short* `a`) [Runtime Function]
`unsigned long fract __fractunshiusq` (*unsigned short* `a`) [Runtime Function]
`unsigned long long fract __fractunshiudq` (*unsigned short* `a`) [Runtime Function]
`unsigned short accum __fractunshiuha` (*unsigned short* `a`) [Runtime Function]
`unsigned accum __fractunshiusa` (*unsigned short* `a`) [Runtime Function]
`unsigned long accum __fractunshiuda` (*unsigned short* `a`) [Runtime Function]
`unsigned long long accum __fractunshiuta` (*unsigned short* `a`) [Runtime Function]
`short fract __fractunssiqq` (*unsigned int* `a`) [Runtime Function]
`fract __fractunssihq` (*unsigned int* `a`) [Runtime Function]
`long fract __fractunssisq` (*unsigned int* `a`) [Runtime Function]
`long long fract __fractunssidq` (*unsigned int* `a`) [Runtime Function]
`short accum __fractunssiha` (*unsigned int* `a`) [Runtime Function]
`accum __fractunssisa` (*unsigned int* `a`) [Runtime Function]
`long accum __fractunssida` (*unsigned int* `a`) [Runtime Function]
`long long accum __fractunssita` (*unsigned int* `a`) [Runtime Function]
`unsigned short fract __fractunssiuqq` (*unsigned int* `a`) [Runtime Function]
`unsigned fract __fractunssiuhq` (*unsigned int* `a`) [Runtime Function]
`unsigned long fract __fractunssiusq` (*unsigned int* `a`) [Runtime Function]
`unsigned long long fract __fractunssiudq` (*unsigned int* `a`) [Runtime Function]
`unsigned short accum __fractunssiuha` (*unsigned int* `a`) [Runtime Function]
`unsigned accum __fractunssiusa` (*unsigned int* `a`) [Runtime Function]
`unsigned long accum __fractunssiuda` (*unsigned int* `a`) [Runtime Function]
`unsigned long long accum __fractunssiuta` (*unsigned int* `a`) [Runtime Function]
`short fract __fractunsdiqq` (*unsigned long* `a`) [Runtime Function]
`fract __fractunsdihq` (*unsigned long* `a`) [Runtime Function]
`long fract __fractunsdisq` (*unsigned long* `a`) [Runtime Function]
`long long fract __fractunsdidq` (*unsigned long* `a`) [Runtime Function]
`short accum __fractunsdiha` (*unsigned long* `a`) [Runtime Function]
`accum __fractunsdisa` (*unsigned long* `a`) [Runtime Function]
`long accum __fractunsdida` (*unsigned long* `a`) [Runtime Function]
`long long accum __fractunsdita` (*unsigned long* `a`) [Runtime Function]
`unsigned short fract __fractunsdiuqq` (*unsigned long* `a`) [Runtime Function]
`unsigned fract __fractunsdiuhq` (*unsigned long* `a`) [Runtime Function]
`unsigned long fract __fractunsdiusq` (*unsigned long* `a`) [Runtime Function]
`unsigned long long fract __fractunsdiudq` (*unsigned long* `a`) [Runtime Function]
`unsigned short accum __fractunsdiuha` (*unsigned long* `a`) [Runtime Function]
`unsigned accum __fractunsdiusa` (*unsigned long* `a`) [Runtime Function]
`unsigned long accum __fractunsdiuda` (*unsigned long* `a`) [Runtime Function]

`unsigned long long accum __fractunsdiuta` (*unsigned long* a) [Runtime Function]
`short fract __fractunstiqq` (*unsigned long long* a) [Runtime Function]
`fract __fractunstihq` (*unsigned long long* a) [Runtime Function]
`long fract __fractunstisq` (*unsigned long long* a) [Runtime Function]
`long long fract __fractunstidq` (*unsigned long long* a) [Runtime Function]
`short accum __fractunstiha` (*unsigned long long* a) [Runtime Function]
`accum __fractunstisa` (*unsigned long long* a) [Runtime Function]
`long accum __fractunstida` (*unsigned long long* a) [Runtime Function]
`long long accum __fractunstita` (*unsigned long long* a) [Runtime Function]
`unsigned short fract __fractunstiuqq` (*unsigned long long* a) [Runtime Function]
`unsigned fract __fractunstiuhq` (*unsigned long long* a) [Runtime Function]
`unsigned long fract __fractunstiusq` (*unsigned long long* a) [Runtime Function]
`unsigned long long fract __fractunstiudq` (*unsigned long long* a) [Runtime Function]
`unsigned short accum __fractunstiuha` (*unsigned long long* a) [Runtime Function]
`unsigned accum __fractunstiusa` (*unsigned long long* a) [Runtime Function]
`unsigned long accum __fractunstiuda` (*unsigned long long* a) [Runtime Function]
`unsigned long long accum __fractunstiuta` (*unsigned long long* a) [Runtime Function]

These functions convert from fractionals to unsigned non-fractionals; and from unsigned non-fractionals to fractionals, without saturation.

`short fract __satfractunsqiqq` (*unsigned char* a) [Runtime Function]
`fract __satfractunsqihq` (*unsigned char* a) [Runtime Function]
`long fract __satfractunsqisq` (*unsigned char* a) [Runtime Function]
`long long fract __satfractunsqidq` (*unsigned char* a) [Runtime Function]
`short accum __satfractunsqiha` (*unsigned char* a) [Runtime Function]
`accum __satfractunsqisa` (*unsigned char* a) [Runtime Function]
`long accum __satfractunsqida` (*unsigned char* a) [Runtime Function]
`long long accum __satfractunsqita` (*unsigned char* a) [Runtime Function]
`unsigned short fract __satfractunsqiuqq` (*unsigned char* a) [Runtime Function]
`unsigned fract __satfractunsqiuhq` (*unsigned char* a) [Runtime Function]
`unsigned long fract __satfractunsqiusq` (*unsigned char* a) [Runtime Function]
`unsigned long long fract __satfractunsqiudq` (*unsigned char* a) [Runtime Function]
`unsigned short accum __satfractunsqiuha` (*unsigned char* a) [Runtime Function]
`unsigned accum __satfractunsqiusa` (*unsigned char* a) [Runtime Function]
`unsigned long accum __satfractunsqiuda` (*unsigned char* a) [Runtime Function]

`unsigned long long accum __satfractunsqiuta` (*unsigned char* a) [Runtime Function]
`short fract __satfractunshiqq` (*unsigned short* a) [Runtime Function]
`fract __satfractunshihq` (*unsigned short* a) [Runtime Function]
`long fract __satfractunshisq` (*unsigned short* a) [Runtime Function]
`long long fract __satfractunshidq` (*unsigned short* a) [Runtime Function]
`short accum __satfractunshiha` (*unsigned short* a) [Runtime Function]
`accum __satfractunshisa` (*unsigned short* a) [Runtime Function]
`long accum __satfractunshida` (*unsigned short* a) [Runtime Function]
`long long accum __satfractunshita` (*unsigned short* a) [Runtime Function]
`unsigned short fract __satfractunshiuqq` (*unsigned short* a) [Runtime Function]
`unsigned fract __satfractunshiuhq` (*unsigned short* a) [Runtime Function]
`unsigned long fract __satfractunshiusq` (*unsigned short* a) [Runtime Function]
`unsigned long long fract __satfractunshiudq` (*unsigned short* a) [Runtime Function]
`unsigned short accum __satfractunshiuha` (*unsigned short* a) [Runtime Function]
`unsigned accum __satfractunshiusa` (*unsigned short* a) [Runtime Function]
`unsigned long accum __satfractunshiuda` (*unsigned short* a) [Runtime Function]
`unsigned long long accum __satfractunshiuta` (*unsigned short* a) [Runtime Function]
`short fract __satfractunssiqq` (*unsigned int* a) [Runtime Function]
`fract __satfractunssihq` (*unsigned int* a) [Runtime Function]
`long fract __satfractunssisq` (*unsigned int* a) [Runtime Function]
`long long fract __satfractunssidq` (*unsigned int* a) [Runtime Function]
`short accum __satfractunssiha` (*unsigned int* a) [Runtime Function]
`accum __satfractunssisa` (*unsigned int* a) [Runtime Function]
`long accum __satfractunssida` (*unsigned int* a) [Runtime Function]
`long long accum __satfractunssita` (*unsigned int* a) [Runtime Function]
`unsigned short fract __satfractunssiuqq` (*unsigned int* a) [Runtime Function]
`unsigned fract __satfractunssiuhq` (*unsigned int* a) [Runtime Function]
`unsigned long fract __satfractunssiusq` (*unsigned int* a) [Runtime Function]
`unsigned long long fract __satfractunssiudq` (*unsigned int* a) [Runtime Function]
`unsigned short accum __satfractunssiuha` (*unsigned int* a) [Runtime Function]
`unsigned accum __satfractunssiusa` (*unsigned int* a) [Runtime Function]
`unsigned long accum __satfractunssiuda` (*unsigned int* a) [Runtime Function]
`unsigned long long accum __satfractunssiuta` (*unsigned int* a) [Runtime Function]
`short fract __satfractunsdiqq` (*unsigned long* a) [Runtime Function]
`fract __satfractunsdihq` (*unsigned long* a) [Runtime Function]
`long fract __satfractunsdisq` (*unsigned long* a) [Runtime Function]

`long long fract __satfractunsdidq` (*unsigned long* a) [Runtime Function]
`short accum __satfractunsdiha` (*unsigned long* a) [Runtime Function]
`accum __satfractunsdisa` (*unsigned long* a) [Runtime Function]
`long accum __satfractunsdida` (*unsigned long* a) [Runtime Function]
`long long accum __satfractunsdita` (*unsigned long* a) [Runtime Function]
`unsigned short fract __satfractunsdiuqq` (*unsigned long* a) [Runtime Function]
`unsigned fract __satfractunsdiuhq` (*unsigned long* a) [Runtime Function]
`unsigned long fract __satfractunsdiusq` (*unsigned long* a) [Runtime Function]
`unsigned long long fract __satfractunsdiudq` (*unsigned long* a) [Runtime Function]
`unsigned short accum __satfractunsdiuha` (*unsigned long* a) [Runtime Function]
`unsigned accum __satfractunsdiusa` (*unsigned long* a) [Runtime Function]
`unsigned long accum __satfractunsdiuda` (*unsigned long* a) [Runtime Function]
`unsigned long long accum __satfractunsdiuta` (*unsigned long* a) [Runtime Function]
`short fract __satfractunstiqq` (*unsigned long long* a) [Runtime Function]
`fract __satfractunstihq` (*unsigned long long* a) [Runtime Function]
`long fract __satfractunstisq` (*unsigned long long* a) [Runtime Function]
`long long fract __satfractunstidq` (*unsigned long long* a) [Runtime Function]
`short accum __satfractunstiha` (*unsigned long long* a) [Runtime Function]
`accum __satfractunstisa` (*unsigned long long* a) [Runtime Function]
`long accum __satfractunstida` (*unsigned long long* a) [Runtime Function]
`long long accum __satfractunstita` (*unsigned long long* a) [Runtime Function]
`unsigned short fract __satfractunstiuqq` (*unsigned long long* a) [Runtime Function]
`unsigned fract __satfractunstiuhq` (*unsigned long long* a) [Runtime Function]
`unsigned long fract __satfractunstiusq` (*unsigned long long* a) [Runtime Function]
`unsigned long long fract __satfractunstiudq` (*unsigned long long* a) [Runtime Function]
`unsigned short accum __satfractunstiuha` (*unsigned long long* a) [Runtime Function]
`unsigned accum __satfractunstiusa` (*unsigned long long* a) [Runtime Function]
`unsigned long accum __satfractunstiuda` (*unsigned long long* a) [Runtime Function]
`unsigned long long accum __satfractunstiuta` (*unsigned long long* a) [Runtime Function]

These functions convert from unsigned non-fractionals to fractionals, with saturation.

4.5 Language-independent routines for exception handling

document me!

`_Unwind_DeleteException`

```
_Unwind_Find_FDE
_Unwind_ForcedUnwind
_Unwind_GetGR
_Unwind_GetIP
_Unwind_GetLanguageSpecificData
_Unwind_GetRegionStart
_Unwind_GetTextRelBase
_Unwind_GetDataRelBase
_Unwind_RaiseException
_Unwind_Resume
_Unwind_SetGR
_Unwind_SetIP
_Unwind_FindEnclosingFunction
_Unwind_SjLj_Register
_Unwind_SjLj_Unregister
_Unwind_SjLj_RaiseException
_Unwind_SjLj_ForcedUnwind
_Unwind_SjLj_Resume
__deregister_frame
__deregister_frame_info
__deregister_frame_info_bases
__register_frame
__register_frame_info
__register_frame_info_bases
__register_frame_info_table
__register_frame_info_table_bases
__register_frame_table
```

4.6 Miscellaneous runtime library routines

4.6.1 Cache control functions

`void __clear_cache` (*char *beg, char *end*) [Runtime Function]

This function clears the instruction cache between *beg* and *end*.

4.6.2 Split stack functions and variables

`void * __splitstack_find` (*void *segment_arg, void *sp, size_t len, void **next_segment, void **next_sp, void **initial_sp*) [Runtime Function]

When using '`-fsplit-stack`', this call may be used to iterate over the stack segments. It may be called like this:

```
void *next_segment = NULL;
void *next_sp = NULL;
void *initial_sp = NULL;
void *stack;
size_t stack_size;
while ((stack = __splitstack_find (next_segment, next_sp,
                                   &stack_size, &next_segment,
                                   &next_sp, &initial_sp))
       != NULL)
  {
    /* Stack segment starts at stack and is
       stack_size bytes long.  */
  }
```

There is no way to iterate over the stack segments of a different thread. However, what is permitted is for one thread to call this with the *segment_arg* and *sp* arguments NULL, to pass *next_segment*, *next_sp*, and *initial_sp* to a different thread, and then to suspend one way or another. A different thread may run the subsequent `__splitstack_find` iterations. Of course, this will only work if the first thread is suspended while the second thread is calling `__splitstack_find`. If not, the second thread could be looking at the stack while it is changing, and anything could happen.

`__morestack_segments` [Variable]
`__morestack_current_segment` [Variable]
`__morestack_initial_sp` [Variable]

Internal variables used by the '`-fsplit-stack`' implementation.

5 Language Front Ends in GCC

The interface to front ends for languages in GCC, and in particular the `tree` structure (see Chapter 10 [GENERIC], page 129), was initially designed for C, and many aspects of it are still somewhat biased towards C and C-like languages. It is, however, reasonably well suited to other procedural languages, and front ends for many such languages have been written for GCC.

Writing a compiler as a front end for GCC, rather than compiling directly to assembler or generating C code which is then compiled by GCC, has several advantages:

- GCC front ends benefit from the support for many different target machines already present in GCC.
- GCC front ends benefit from all the optimizations in GCC. Some of these, such as alias analysis, may work better when GCC is compiling directly from source code then when it is compiling from generated C code.
- Better debugging information is generated when compiling directly from source code than when going via intermediate generated C code.

Because of the advantages of writing a compiler as a GCC front end, GCC front ends have also been created for languages very different from those for which GCC was designed, such as the declarative logic/functional language Mercury. For these reasons, it may also be useful to implement compilers created for specialized purposes (for example, as part of a research project) as GCC front ends.

6 Source Tree Structure and Build System

This chapter describes the structure of the GCC source tree, and how GCC is built. The user documentation for building and installing GCC is in a separate manual (http://gcc.gnu.org/install/), with which it is presumed that you are familiar.

6.1 Configure Terms and History

The configure and build process has a long and colorful history, and can be confusing to anyone who doesn't know why things are the way they are. While there are other documents which describe the configuration process in detail, here are a few things that everyone working on GCC should know.

There are three system names that the build knows about: the machine you are building on (*build*), the machine that you are building for (*host*), and the machine that GCC will produce code for (*target*). When you configure GCC, you specify these with '`--build=`', '`--host=`', and '`--target=`'.

Specifying the host without specifying the build should be avoided, as `configure` may (and once did) assume that the host you specify is also the build, which may not be true.

If build, host, and target are all the same, this is called a *native*. If build and host are the same but target is different, this is called a *cross*. If build, host, and target are all different this is called a *canadian* (for obscure reasons dealing with Canada's political party and the background of the person working on the build at that time). If host and target are the same, but build is different, you are using a cross-compiler to build a native for a different system. Some people call this a *host-x-host*, *crossed native*, or *cross-built native*. If build and target are the same, but host is different, you are using a cross compiler to build a cross compiler that produces code for the machine you're building on. This is rare, so there is no common way of describing it. There is a proposal to call this a *crossback*.

If build and host are the same, the GCC you are building will also be used to build the target libraries (like `libstdc++`). If build and host are different, you must have already built and installed a cross compiler that will be used to build the target libraries (if you configured with '`--target=foo-bar`', this compiler will be called `foo-bar-gcc`).

In the case of target libraries, the machine you're building for is the machine you specified with '`--target`'. So, build is the machine you're building on (no change there), host is the machine you're building for (the target libraries are built for the target, so host is the target you specified), and target doesn't apply (because you're not building a compiler, you're building libraries). The configure/make process will adjust these variables as needed. It also sets `$with_cross_host` to the original '`--host`' value in case you need it.

The `libiberty` support library is built up to three times: once for the host, once for the target (even if they are the same), and once for the build if build and host are different. This allows it to be used by all programs which are generated in the course of the build process.

6.2 Top Level Source Directory

The top level source directory in a GCC distribution contains several files and directories that are shared with other software distributions such as that of GNU Binutils. It also contains several subdirectories that contain parts of GCC and its runtime libraries:

'boehm-gc'
: The Boehm conservative garbage collector, used as part of the Java runtime library.

'config'
: Autoconf macros and Makefile fragments used throughout the tree.

'contrib'
: Contributed scripts that may be found useful in conjunction with GCC. One of these, 'contrib/texi2pod.pl', is used to generate man pages from Texinfo manuals as part of the GCC build process.

'fixincludes'
: The support for fixing system headers to work with GCC. See 'fixincludes/README' for more information. The headers fixed by this mechanism are installed in '*libsubdir*/include-fixed'. Along with those headers, 'README-fixinc' is also installed, as '*libsubdir*/include-fixed/README'.

'gcc'
: The main sources of GCC itself (except for runtime libraries), including optimizers, support for different target architectures, language front ends, and testsuites. See Section 6.3 [The 'gcc' Subdirectory], page 63, for details.

'gnattools'
: Support tools for GNAT.

'include'
: Headers for the libiberty library.

'intl'
: GNU libintl, from GNU gettext, for systems which do not include it in libc.

'libada'
: The Ada runtime library.

'libatomic'
: The runtime support library for atomic operations (e.g. for __sync and __atomic).

'libcpp'
: The C preprocessor library.

'libdecnumber'
: The Decimal Float support library.

'libffi'
: The libffi library, used as part of the Java runtime library.

'libgcc'
: The GCC runtime library.

'libgfortran'
: The Fortran runtime library.

'libgo'
: The Go runtime library. The bulk of this library is mirrored from the master Go repository.

'libgomp'
: The GNU OpenMP runtime library.

'libiberty'
: The libiberty library, used for portability and for some generally useful data structures and algorithms. See Section "Introduction" in GNU *libiberty*, for more information about this library.

'libitm'
: The runtime support library for transactional memory.

'`libjava`' The Java runtime library.

'`libobjc`' The Objective-C and Objective-C++ runtime library.

'`libquadmath`'
The runtime support library for quad-precision math operations.

'`libssp`' The Stack protector runtime library.

'`libstdc++-v3`'
The C++ runtime library.

'`lto-plugin`'
Plugin used by the linker if link-time optimizations are enabled.

'`maintainer-scripts`'
Scripts used by the `gccadmin` account on `gcc.gnu.org`.

'`zlib`' The `zlib` compression library, used by the Java front end, as part of the Java runtime library, and for compressing and uncompressing GCC's intermediate language in LTO object files.

The build system in the top level directory, including how recursion into subdirectories works and how building runtime libraries for multilibs is handled, is documented in a separate manual, included with GNU Binutils. See Section "GNU configure and build system" in *The GNU configure and build system*, for details.

6.3 The '`gcc`' Subdirectory

The '`gcc`' directory contains many files that are part of the C sources of GCC, other files used as part of the configuration and build process, and subdirectories including documentation and a testsuite. The files that are sources of GCC are documented in a separate chapter. See Chapter 9 [Passes and Files of the Compiler], page 113.

6.3.1 Subdirectories of '`gcc`'

The '`gcc`' directory contains the following subdirectories:

'*`language`*'
Subdirectories for various languages. Directories containing a file '`config-lang.in`' are language subdirectories. The contents of the subdirectories '`c`' (for C), '`cp`' (for C++), '`objc`' (for Objective-C), '`objcp`' (for Objective-C++), and '`lto`' (for LTO) are documented in this manual (see Chapter 9 [Passes and Files of the Compiler], page 113); those for other languages are not. See Section 6.3.8 [Anatomy of a Language Front End], page 71, for details of the files in these directories.

'`common`' Source files shared between the compiler drivers (such as `gcc`) and the compilers proper (such as '`cc1`'). If an architecture defines target hooks shared between those places, it also has a subdirectory in '`common/config`'. See Section 17.1 [Target Structure], page 421.

'`config`' Configuration files for supported architectures and operating systems. See Section 6.3.9 [Anatomy of a Target Back End], page 75, for details of the files in this directory.

'doc' Texinfo documentation for GCC, together with automatically generated man pages and support for converting the installation manual to HTML. See Section 6.3.7 [Documentation], page 69.

'ginclude' System headers installed by GCC, mainly those required by the C standard of freestanding implementations. See Section 6.3.6 [Headers Installed by GCC], page 68, for details of when these and other headers are installed.

'po' Message catalogs with translations of messages produced by GCC into various languages, '*language*.po'. This directory also contains 'gcc.pot', the template for these message catalogues, 'exgettext', a wrapper around gettext to extract the messages from the GCC sources and create 'gcc.pot', which is run by 'make gcc.pot', and 'EXCLUDES', a list of files from which messages should not be extracted.

'testsuite' The GCC testsuites (except for those for runtime libraries). See Chapter 7 [Testsuites], page 77.

6.3.2 Configuration in the 'gcc' Directory

The 'gcc' directory is configured with an Autoconf-generated script 'configure'. The 'configure' script is generated from 'configure.ac' and 'aclocal.m4'. From the files 'configure.ac' and 'acconfig.h', Autoheader generates the file 'config.in'. The file 'cstamp-h.in' is used as a timestamp.

6.3.2.1 Scripts Used by 'configure'

'configure' uses some other scripts to help in its work:

- The standard GNU 'config.sub' and 'config.guess' files, kept in the top level directory, are used.
- The file 'config.gcc' is used to handle configuration specific to the particular target machine. The file 'config.build' is used to handle configuration specific to the particular build machine. The file 'config.host' is used to handle configuration specific to the particular host machine. (In general, these should only be used for features that cannot reasonably be tested in Autoconf feature tests.) See Section 6.3.2.2 [The 'config.build'; 'config.host'; and 'config.gcc' Files], page 64, for details of the contents of these files.
- Each language subdirectory has a file '*language*/config-lang.in' that is used for front-end-specific configuration. See Section 6.3.8.2 [The Front End 'config-lang.in' File], page 73, for details of this file.
- A helper script 'configure.frag' is used as part of creating the output of 'configure'.

6.3.2.2 The 'config.build'; 'config.host'; and 'config.gcc' Files

The 'config.build' file contains specific rules for particular systems which GCC is built on. This should be used as rarely as possible, as the behavior of the build system can always be detected by autoconf.

The 'config.host' file contains specific rules for particular systems which GCC will run on. This is rarely needed.

The '`config.gcc`' file contains specific rules for particular systems which GCC will generate code for. This is usually needed.

Each file has a list of the shell variables it sets, with descriptions, at the top of the file.

FIXME: document the contents of these files, and what variables should be set to control build, host and target configuration.

6.3.2.3 Files Created by `configure`

Here we spell out what files will be set up by '`configure`' in the '`gcc`' directory. Some other files are created as temporary files in the configuration process, and are not used in the subsequent build; these are not documented.

- '`Makefile`' is constructed from '`Makefile.in`', together with the host and target fragments (see Chapter 19 [Makefile Fragments], page 595) '`t-`*`target`*' and '`x-`*`host`*' from '`config`', if any, and language Makefile fragments '*`language`*`/Make-lang.in`'.
- '`auto-host.h`' contains information about the host machine determined by '`configure`'. If the host machine is different from the build machine, then '`auto-build.h`' is also created, containing such information about the build machine.
- '`config.status`' is a script that may be run to recreate the current configuration.
- '`configargs.h`' is a header containing details of the arguments passed to '`configure`' to configure GCC, and of the thread model used.
- '`cstamp-h`' is used as a timestamp.
- If a language '`config-lang.in`' file (see Section 6.3.8.2 [The Front End 'config-lang.in' File], page 73) sets `outputs`, then the files listed in `outputs` there are also generated.

The following configuration headers are created from the Makefile, using '`mkconfig.sh`', rather than directly by '`configure`'. '`config.h`', '`bconfig.h`' and '`tconfig.h`' all contain the '`xm-`*`machine`*`.h`' header, if any, appropriate to the host, build and target machines respectively, the configuration headers for the target, and some definitions; for the host and build machines, these include the autoconfigured headers generated by '`configure`'. The other configuration headers are determined by '`config.gcc`'. They also contain the typedefs for `rtx`, `rtvec` and `tree`.

- '`config.h`', for use in programs that run on the host machine.
- '`bconfig.h`', for use in programs that run on the build machine.
- '`tconfig.h`', for use in programs and libraries for the target machine.
- '`tm_p.h`', which includes the header '*`machine`*`-protos.h`' that contains prototypes for functions in the target '*`machine`*`.c`' file. The header '*`machine`*`-protos.h`' can include prototypes of functions that use rtl and tree data structures inside appropriate `#ifdef RTX_CODE` and `#ifdef TREE_CODE` conditional code segements. The '*`machine`*`-protos.h`' is included after the '`rtl.h`' and/or '`tree.h`' would have been included. The '`tm_p.h`' also includes the header '`tm-preds.h`' which is generated by '`genpreds`' program during the build to define the declarations and inline functions for the predicate functions.

6.3.3 Build System in the 'gcc' Directory

FIXME: describe the build system, including what is built in what stages. Also list the various source files that are used in the build process but aren't source files of GCC itself and so aren't documented below (see Chapter 9 [Passes], page 113).

6.3.4 Makefile Targets

These targets are available from the 'gcc' directory:

`all` This is the default target. Depending on what your build/host/target configuration is, it coordinates all the things that need to be built.

`doc` Produce info-formatted documentation and man pages. Essentially it calls '`make man`' and '`make info`'.

`dvi` Produce DVI-formatted documentation.

`pdf` Produce PDF-formatted documentation.

`html` Produce HTML-formatted documentation.

`man` Generate man pages.

`info` Generate info-formatted pages.

`mostlyclean`
Delete the files made while building the compiler.

`clean` That, and all the other files built by '`make all`'.

`distclean`
That, and all the files created by `configure`.

`maintainer-clean`
Distclean plus any file that can be generated from other files. Note that additional tools may be required beyond what is normally needed to build GCC.

`srcextra` Generates files in the source directory that are not version-controlled but should go into a release tarball.

`srcinfo`
`srcman` Copies the info-formatted and manpage documentation into the source directory usually for the purpose of generating a release tarball.

`install` Installs GCC.

`uninstall`
Deletes installed files, though this is not supported.

`check` Run the testsuite. This creates a '`testsuite`' subdirectory that has various '`.sum`' and '`.log`' files containing the results of the testing. You can run subsets with, for example, '`make check-gcc`'. You can specify specific tests by setting `RUNTESTFLAGS` to be the name of the '`.exp`' file, optionally followed by (for some tests) an equals and a file wildcard, like:

```
make check-gcc RUNTESTFLAGS="execute.exp=19980413-*"
```

Note that running the testsuite may require additional tools be installed, such as Tcl or DejaGnu.

The toplevel tree from which you start GCC compilation is not the GCC directory, but rather a complex Makefile that coordinates the various steps of the build, including bootstrapping the compiler and using the new compiler to build target libraries.

When GCC is configured for a native configuration, the default action for `make` is to do a full three-stage bootstrap. This means that GCC is built three times—once with the native compiler, once with the native-built compiler it just built, and once with the compiler it built the second time. In theory, the last two should produce the same results, which '`make compare`' can check. Each stage is configured separately and compiled into a separate directory, to minimize problems due to ABI incompatibilities between the native compiler and GCC.

If you do a change, rebuilding will also start from the first stage and "bubble" up the change through the three stages. Each stage is taken from its build directory (if it had been built previously), rebuilt, and copied to its subdirectory. This will allow you to, for example, continue a bootstrap after fixing a bug which causes the stage2 build to crash. It does not provide as good coverage of the compiler as bootstrapping from scratch, but it ensures that the new code is syntactically correct (e.g., that you did not use GCC extensions by mistake), and avoids spurious bootstrap comparison failures[1].

Other targets available from the top level include:

`bootstrap-lean`
: Like `bootstrap`, except that the various stages are removed once they're no longer needed. This saves disk space.

`bootstrap2`
`bootstrap2-lean`
: Performs only the first two stages of bootstrap. Unlike a three-stage bootstrap, this does not perform a comparison to test that the compiler is running properly. Note that the disk space required by a "lean" bootstrap is approximately independent of the number of stages.

`stage`*N*`-bubble (`*N* `= 1...4, profile, feedback)`
: Rebuild all the stages up to *N*, with the appropriate flags, "bubbling" the changes as described above.

`all-stage`*N* `(`*N* `= 1...4, profile, feedback)`
: Assuming that stage *N* has already been built, rebuild it with the appropriate flags. This is rarely needed.

`cleanstrap`
: Remove everything ('`make clean`') and rebuilds ('`make bootstrap`').

`compare`
: Compares the results of stages 2 and 3. This ensures that the compiler is running properly, since it should produce the same object files regardless of how it itself was compiled.

`profiledbootstrap`
: Builds a compiler with profiling feedback information. In this case, the second and third stages are named '`profile`' and '`feedback`', respectively. For more information, see Section "Building with profile feedback" in *Installing GCC*.

[1] Except if the compiler was buggy and miscompiled some of the files that were not modified. In this case, it's best to use `make restrap`.

`restrap` Restart a bootstrap, so that everything that was not built with the system compiler is rebuilt.

`stage`*N*`-start (`*N* `= 1...4, profile, feedback)`
For each package that is bootstrapped, rename directories so that, for example, '`gcc`' points to the stage*N* GCC, compiled with the stage*N-1* GCC[2].

You will invoke this target if you need to test or debug the stage*N* GCC. If you only need to execute GCC (but you need not run '`make`' either to rebuild it or to run test suites), you should be able to work directly in the '`stage`*N*`-gcc`' directory. This makes it easier to debug multiple stages in parallel.

`stage` For each package that is bootstrapped, relocate its build directory to indicate its stage. For example, if the '`gcc`' directory points to the stage2 GCC, after invoking this target it will be renamed to '`stage2-gcc`'.

If you wish to use non-default GCC flags when compiling the stage2 and stage3 compilers, set `BOOT_CFLAGS` on the command line when doing '`make`'.

Usually, the first stage only builds the languages that the compiler is written in: typically, C and maybe Ada. If you are debugging a miscompilation of a different stage2 front-end (for example, of the Fortran front-end), you may want to have front-ends for other languages in the first stage as well. To do so, set `STAGE1_LANGUAGES` on the command line when doing '`make`'.

For example, in the aforementioned scenario of debugging a Fortran front-end miscompilation caused by the stage1 compiler, you may need a command like

```
make stage2-bubble STAGE1_LANGUAGES=c,fortran
```

Alternatively, you can use per-language targets to build and test languages that are not enabled by default in stage1. For example, `make f951` will build a Fortran compiler even in the stage1 build directory.

6.3.5 Library Source Files and Headers under the '`gcc`' Directory

FIXME: list here, with explanation, all the C source files and headers under the '`gcc`' directory that aren't built into the GCC executable but rather are part of runtime libraries and object files, such as '`crtstuff.c`' and '`unwind-dw2.c`'. See Section 6.3.6 [Headers Installed by GCC], page 68, for more information about the '`ginclude`' directory.

6.3.6 Headers Installed by GCC

In general, GCC expects the system C library to provide most of the headers to be used with it. However, GCC will fix those headers if necessary to make them work with GCC, and will install some headers required of freestanding implementations. These headers are installed in '*`libsubdir`*`/include`'. Headers for non-C runtime libraries are also installed by GCC; these are not documented here. (FIXME: document them somewhere.)

Several of the headers GCC installs are in the '`ginclude`' directory. These headers, '`iso646.h`', '`stdarg.h`', '`stdbool.h`', and '`stddef.h`', are installed in '*`libsubdir`*`/include`', unless the target Makefile fragment (see Section 19.1 [Target Fragment], page 595) overrides this by setting `USER_H`.

[2] Customarily, the system compiler is also termed the '`stage0`' GCC.

In addition to these headers and those generated by fixing system headers to work with GCC, some other headers may also be installed in '*libsubdir*/include'. 'config.gcc' may set extra_headers; this specifies additional headers under 'config' to be installed on some systems.

GCC installs its own version of <float.h>, from 'ginclude/float.h'. This is done to cope with command-line options that change the representation of floating point numbers.

GCC also installs its own version of <limits.h>; this is generated from 'glimits.h', together with 'limitx.h' and 'limity.h' if the system also has its own version of <limits.h>. (GCC provides its own header because it is required of ISO C freestanding implementations, but needs to include the system header from its own header as well because other standards such as POSIX specify additional values to be defined in <limits.h>.) The system's <limits.h> header is used via '*libsubdir*/include/syslimits.h', which is copied from 'gsyslimits.h' if it does not need fixing to work with GCC; if it needs fixing, 'syslimits.h' is the fixed copy.

GCC can also install <tgmath.h>. It will do this when 'config.gcc' sets use_gcc_tgmath to yes.

6.3.7 Building Documentation

The main GCC documentation is in the form of manuals in Texinfo format. These are installed in Info format; DVI versions may be generated by 'make dvi', PDF versions by 'make pdf', and HTML versions by 'make html'. In addition, some man pages are generated from the Texinfo manuals, there are some other text files with miscellaneous documentation, and runtime libraries have their own documentation outside the 'gcc' directory. FIXME: document the documentation for runtime libraries somewhere.

6.3.7.1 Texinfo Manuals

The manuals for GCC as a whole, and the C and C++ front ends, are in files 'doc/*.texi'. Other front ends have their own manuals in files '*language*/*.texi'. Common files 'doc/include/*.texi' are provided which may be included in multiple manuals; the following files are in 'doc/include':

'fdl.texi'
: The GNU Free Documentation License.

'funding.texi'
: The section "Funding Free Software".

'gcc-common.texi'
: Common definitions for manuals.

'gpl_v3.texi'
: The GNU General Public License.

'texinfo.tex'
: A copy of 'texinfo.tex' known to work with the GCC manuals.

DVI-formatted manuals are generated by 'make dvi', which uses texi2dvi (via the Makefile macro $(TEXI2DVI)). PDF-formatted manuals are generated by 'make pdf', which uses texi2pdf (via the Makefile macro $(TEXI2PDF)). HTML formatted manuals are generated

by '`make html`'. Info manuals are generated by '`make info`' (which is run as part of a bootstrap); this generates the manuals in the source directory, using `makeinfo` via the Makefile macro `$(MAKEINFO)`, and they are included in release distributions.

Manuals are also provided on the GCC web site, in both HTML and PostScript forms. This is done via the script '`maintainer-scripts/update_web_docs_svn`'. Each manual to be provided online must be listed in the definition of `MANUALS` in that file; a file '*name*`.texi`' must only appear once in the source tree, and the output manual must have the same name as the source file. (However, other Texinfo files, included in manuals but not themselves the root files of manuals, may have names that appear more than once in the source tree.) The manual file '*name*`.texi`' should only include other files in its own directory or in '`doc/include`'. HTML manuals will be generated by '`makeinfo --html`', PostScript manuals by `texi2dvi` and `dvips`, and PDF manuals by `texi2pdf`. All Texinfo files that are parts of manuals must be version-controlled, even if they are generated files, for the generation of online manuals to work.

The installation manual, '`doc/install.texi`', is also provided on the GCC web site. The HTML version is generated by the script '`doc/install.texi2html`'.

6.3.7.2 Man Page Generation

Because of user demand, in addition to full Texinfo manuals, man pages are provided which contain extracts from those manuals. These man pages are generated from the Texinfo manuals using '`contrib/texi2pod.pl`' and `pod2man`. (The man page for `g++`, '`cp/g++.1`', just contains a '`.so`' reference to '`gcc.1`', but all the other man pages are generated from Texinfo manuals.)

Because many systems may not have the necessary tools installed to generate the man pages, they are only generated if the '`configure`' script detects that recent enough tools are installed, and the Makefiles allow generating man pages to fail without aborting the build. Man pages are also included in release distributions. They are generated in the source directory.

Magic comments in Texinfo files starting '`@c man`' control what parts of a Texinfo file go into a man page. Only a subset of Texinfo is supported by '`texi2pod.pl`', and it may be necessary to add support for more Texinfo features to this script when generating new man pages. To improve the man page output, some special Texinfo macros are provided in '`doc/include/gcc-common.texi`' which '`texi2pod.pl`' understands:

`@gcctabopt`
: Use in the form '`@table @gcctabopt`' for tables of options, where for printed output the effect of '`@code`' is better than that of '`@option`' but for man page output a different effect is wanted.

`@gccoptlist`
: Use for summary lists of options in manuals.

`@gol`
: Use at the end of each line inside '`@gccoptlist`'. This is necessary to avoid problems with differences in how the '`@gccoptlist`' macro is handled by different Texinfo formatters.

FIXME: describe the '`texi2pod.pl`' input language and magic comments in more detail.

6.3.7.3 Miscellaneous Documentation

In addition to the formal documentation that is installed by GCC, there are several other text files in the '`gcc`' subdirectory with miscellaneous documentation:

'`ABOUT-GCC-NLS`'
: Notes on GCC's Native Language Support. FIXME: this should be part of this manual rather than a separate file.

'`ABOUT-NLS`'
: Notes on the Free Translation Project.

'`COPYING`'
'`COPYING3`'
: The GNU General Public License, Versions 2 and 3.

'`COPYING.LIB`'
'`COPYING3.LIB`'
: The GNU Lesser General Public License, Versions 2.1 and 3.

'`*ChangeLog*`'
'`*/ChangeLog*`'
: Change log files for various parts of GCC.

'`LANGUAGES`'
: Details of a few changes to the GCC front-end interface. FIXME: the information in this file should be part of general documentation of the front-end interface in this manual.

'`ONEWS`'
: Information about new features in old versions of GCC. (For recent versions, the information is on the GCC web site.)

'`README.Portability`'
: Information about portability issues when writing code in GCC. FIXME: why isn't this part of this manual or of the GCC Coding Conventions?

FIXME: document such files in subdirectories, at least '`config`', '`c`', '`cp`', '`objc`', '`testsuite`'.

6.3.8 Anatomy of a Language Front End

A front end for a language in GCC has the following parts:

- A directory '*`language`*' under '`gcc`' containing source files for that front end. See Section 6.3.8.1 [The Front End '*language*' Directory], page 72, for details.
- A mention of the language in the list of supported languages in '`gcc/doc/install.texi`'.
- A mention of the name under which the language's runtime library is recognized by '`--enable-shared=`*`package`*' in the documentation of that option in '`gcc/doc/install.texi`'.
- A mention of any special prerequisites for building the front end in the documentation of prerequisites in '`gcc/doc/install.texi`'.
- Details of contributors to that front end in '`gcc/doc/contrib.texi`'. If the details are in that front end's own manual then there should be a link to that manual's list in '`contrib.texi`'.

- Information about support for that language in '`gcc/doc/frontends.texi`'.
- Information about standards for that language, and the front end's support for them, in '`gcc/doc/standards.texi`'. This may be a link to such information in the front end's own manual.
- Details of source file suffixes for that language and '`-x lang`' options supported, in '`gcc/doc/invoke.texi`'.
- Entries in `default_compilers` in '`gcc.c`' for source file suffixes for that language.
- Preferably testsuites, which may be under '`gcc/testsuite`' or runtime library directories. FIXME: document somewhere how to write testsuite harnesses.
- Probably a runtime library for the language, outside the '`gcc`' directory. FIXME: document this further.
- Details of the directories of any runtime libraries in '`gcc/doc/sourcebuild.texi`'.
- Check targets in '`Makefile.def`' for the top-level '`Makefile`' to check just the compiler or the compiler and runtime library for the language.

If the front end is added to the official GCC source repository, the following are also necessary:

- At least one Bugzilla component for bugs in that front end and runtime libraries. This category needs to be added to the Bugzilla database.
- Normally, one or more maintainers of that front end listed in '`MAINTAINERS`'.
- Mentions on the GCC web site in '`index.html`' and '`frontends.html`', with any relevant links on '`readings.html`'. (Front ends that are not an official part of GCC may also be listed on '`frontends.html`', with relevant links.)
- A news item on '`index.html`', and possibly an announcement on the `gcc-announce@gcc.gnu.org` mailing list.
- The front end's manuals should be mentioned in '`maintainer-scripts/update_web_docs_svn`' (see Section 6.3.7.1 [Texinfo Manuals], page 69) and the online manuals should be linked to from '`onlinedocs/index.html`'.
- Any old releases or CVS repositories of the front end, before its inclusion in GCC, should be made available on the GCC FTP site `ftp://gcc.gnu.org/pub/gcc/old-releases/`.
- The release and snapshot script '`maintainer-scripts/gcc_release`' should be updated to generate appropriate tarballs for this front end.
- If this front end includes its own version files that include the current date, '`maintainer-scripts/update_version`' should be updated accordingly.

6.3.8.1 The Front End '*language*' Directory

A front end '*language*' directory contains the source files of that front end (but not of any runtime libraries, which should be outside the '`gcc`' directory). This includes documentation, and possibly some subsidiary programs built alongside the front end. Certain files are special and other parts of the compiler depend on their names:

'`config-lang.in`'
: This file is required in all language subdirectories. See Section 6.3.8.2 [The Front End '`config-lang.in`' File], page 73, for details of its contents

'`Make-lang.in`'
: This file is required in all language subdirectories. See Section 6.3.8.3 [The Front End '`Make-lang.in`' File], page 74, for details of its contents.

'`lang.opt`'
: This file registers the set of switches that the front end accepts on the command line, and their '`--help`' text. See Chapter 8 [Options], page 105.

'`lang-specs.h`'
: This file provides entries for `default_compilers` in '`gcc.c`' which override the default of giving an error that a compiler for that language is not installed.

'*`language`*`-tree.def`'
: This file, which need not exist, defines any language-specific tree codes.

6.3.8.2 The Front End '`config-lang.in`' File

Each language subdirectory contains a '`config-lang.in`' file. This file is a shell script that may define some variables describing the language:

`language`
: This definition must be present, and gives the name of the language for some purposes such as arguments to '`--enable-languages`'.

`lang_requires`
: If defined, this variable lists (space-separated) language front ends other than C that this front end requires to be enabled (with the names given being their `language` settings). For example, the Java front end depends on the C++ front end, so sets '`lang_requires=c++`'.

`subdir_requires`
: If defined, this variable lists (space-separated) front end directories other than C that this front end requires to be present. For example, the Objective-C++ front end uses source files from the C++ and Objective-C front ends, so sets '`subdir_requires="cp objc"`'.

`target_libs`
: If defined, this variable lists (space-separated) targets in the top level '`Makefile`' to build the runtime libraries for this language, such as `target-libobjc`.

`lang_dirs`
: If defined, this variable lists (space-separated) top level directories (parallel to '`gcc`'), apart from the runtime libraries, that should not be configured if this front end is not built.

`build_by_default`
: If defined to '`no`', this language front end is not built unless enabled in a '`--enable-languages`' argument. Otherwise, front ends are built by default, subject to any special logic in '`configure.ac`' (as is present to disable the Ada front end if the Ada compiler is not already installed).

`boot_language`
: If defined to '`yes`', this front end is built in stage1 of the bootstrap. This is only relevant to front ends written in their own languages.

`compilers`
: If defined, a space-separated list of compiler executables that will be run by the driver. The names here will each end with '`\$(exeext)`'.

`outputs`
: If defined, a space-separated list of files that should be generated by '`configure`' substituting values in them. This mechanism can be used to create a file '*`language`*`/Makefile`' from '*`language`*`/Makefile.in`', but this is deprecated, building everything from the single '`gcc/Makefile`' is preferred.

`gtfiles`
: If defined, a space-separated list of files that should be scanned by '`gengtype.c`' to generate the garbage collection tables and routines for this language. This excludes the files that are common to all front ends. See Chapter 22 [Type Information], page 603.

6.3.8.3 The Front End '`Make-lang.in`' File

Each language subdirectory contains a '`Make-lang.in`' file. It contains targets *`lang.hook`* (where *`lang`* is the setting of `language` in '`config-lang.in`') for the following values of *`hook`*, and any other Makefile rules required to build those targets (which may if necessary use other Makefiles specified in `outputs` in '`config-lang.in`', although this is deprecated). It also adds any testsuite targets that can use the standard rule in '`gcc/Makefile.in`' to the variable `lang_checks`.

`all.cross`
`start.encap`
`rest.encap`
: FIXME: exactly what goes in each of these targets?

`tags`
: Build an `etags` '`TAGS`' file in the language subdirectory in the source tree.

`info`
: Build info documentation for the front end, in the build directory. This target is only called by '`make bootstrap`' if a suitable version of `makeinfo` is available, so does not need to check for this, and should fail if an error occurs.

`dvi`
: Build DVI documentation for the front end, in the build directory. This should be done using `$(TEXI2DVI)`, with appropriate '`-I`' arguments pointing to directories of included files.

`pdf`
: Build PDF documentation for the front end, in the build directory. This should be done using `$(TEXI2PDF)`, with appropriate '`-I`' arguments pointing to directories of included files.

`html`
: Build HTML documentation for the front end, in the build directory.

`man`
: Build generated man pages for the front end from Texinfo manuals (see Section 6.3.7.2 [Man Page Generation], page 70), in the build directory. This target is only called if the necessary tools are available, but should ignore errors so as not to stop the build if errors occur; man pages are optional and the tools involved may be installed in a broken way.

`install-common`
: Install everything that is part of the front end, apart from the compiler executables listed in `compilers` in '`config-lang.in`'.

`install-info`
: Install info documentation for the front end, if it is present in the source directory. This target should have dependencies on info files that should be installed.

`install-man`
: Install man pages for the front end. This target should ignore errors.

`install-plugin`
: Install headers needed for plugins.

`srcextra`
: Copies its dependencies into the source directory. This generally should be used for generated files such as Bison output files which are not version-controlled, but should be included in any release tarballs. This target will be executed during a bootstrap if '`--enable-generated-files-in-srcdir`' was specified as a '`configure`' option.

`srcinfo`
`srcman`
: Copies its dependencies into the source directory. These targets will be executed during a bootstrap if '`--enable-generated-files-in-srcdir`' was specified as a '`configure`' option.

`uninstall`
: Uninstall files installed by installing the compiler. This is currently documented not to be supported, so the hook need not do anything.

`mostlyclean`
`clean`
`distclean`
`maintainer-clean`
: The language parts of the standard GNU '`*clean`' targets. See Section "Standard Targets for Users" in *GNU Coding Standards*, for details of the standard targets. For GCC, `maintainer-clean` should delete all generated files in the source directory that are not version-controlled, but should not delete anything that is.

'`Make-lang.in`' must also define a variable *`lang`*`_OBJS` to a list of host object files that are used by that language.

6.3.9 Anatomy of a Target Back End

A back end for a target architecture in GCC has the following parts:

- A directory '*`machine`*' under '`gcc/config`', containing a machine description '*`machine`*`.md`' file (see Chapter 16 [Machine Descriptions], page 297), header files '*`machine`*`.h`' and '*`machine`*`-protos.h`' and a source file '*`machine`*`.c`' (see Chapter 17 [Target Description Macros and Functions], page 421), possibly a target Makefile fragment '`t-`*`machine`*' (see Section 19.1 [The Target Makefile Fragment], page 595), and maybe some other files. The names of these files may be changed from the defaults given by explicit specifications in '`config.gcc`'.
- If necessary, a file '*`machine`*`-modes.def`' in the '*`machine`*' directory, containing additional machine modes to represent condition codes. See Section 17.16 [Condition Code], page 506, for further details.

- An optional '*machine*.opt' file in the '*machine*' directory, containing a list of target-specific options. You can also add other option files using the `extra_options` variable in '`config.gcc`'. See Chapter 8 [Options], page 105.
- Entries in '`config.gcc`' (see Section 6.3.2.2 [The '`config.gcc`' File], page 64) for the systems with this target architecture.
- Documentation in '`gcc/doc/invoke.texi`' for any command-line options supported by this target (see Section 17.3 [Run-time Target Specification], page 428). This means both entries in the summary table of options and details of the individual options.
- Documentation in '`gcc/doc/extend.texi`' for any target-specific attributes supported (see Section 17.25 [Defining target-specific uses of `__attribute__`], page 565), including where the same attribute is already supported on some targets, which are enumerated in the manual.
- Documentation in '`gcc/doc/extend.texi`' for any target-specific pragmas supported.
- Documentation in '`gcc/doc/extend.texi`' of any target-specific built-in functions supported.
- Documentation in '`gcc/doc/extend.texi`' of any target-specific format checking styles supported.
- Documentation in '`gcc/doc/md.texi`' of any target-specific constraint letters (see Section 16.8.5 [Constraints for Particular Machines], page 317).
- A note in '`gcc/doc/contrib.texi`' under the person or people who contributed the target support.
- Entries in '`gcc/doc/install.texi`' for all target triplets supported with this target architecture, giving details of any special notes about installation for this target, or saying that there are no special notes if there are none.
- Possibly other support outside the '`gcc`' directory for runtime libraries. FIXME: reference docs for this. The `libstdc++` porting manual needs to be installed as info for this to work, or to be a chapter of this manual.

If the back end is added to the official GCC source repository, the following are also necessary:

- An entry for the target architecture in '`readings.html`' on the GCC web site, with any relevant links.
- Details of the properties of the back end and target architecture in '`backends.html`' on the GCC web site.
- A news item about the contribution of support for that target architecture, in '`index.html`' on the GCC web site.
- Normally, one or more maintainers of that target listed in '`MAINTAINERS`'. Some existing architectures may be unmaintained, but it would be unusual to add support for a target that does not have a maintainer when support is added.
- Target triplets covering all '`config.gcc`' stanzas for the target, in the list in '`contrib/config-list.mk`'.

7 Testsuites

GCC contains several testsuites to help maintain compiler quality. Most of the runtime libraries and language front ends in GCC have testsuites. Currently only the C language testsuites are documented here; FIXME: document the others.

7.1 Idioms Used in Testsuite Code

In general, C testcases have a trailing '`-n.c`', starting with '`-1.c`', in case other testcases with similar names are added later. If the test is a test of some well-defined feature, it should have a name referring to that feature such as '*feature*`-1.c`'. If it does not test a well-defined feature but just happens to exercise a bug somewhere in the compiler, and a bug report has been filed for this bug in the GCC bug database, '`pr`*bug-number*`-1.c`' is the appropriate form of name. Otherwise (for miscellaneous bugs not filed in the GCC bug database), and previously more generally, test cases are named after the date on which they were added. This allows people to tell at a glance whether a test failure is because of a recently found bug that has not yet been fixed, or whether it may be a regression, but does not give any other information about the bug or where discussion of it may be found. Some other language testsuites follow similar conventions.

In the '`gcc.dg`' testsuite, it is often necessary to test that an error is indeed a hard error and not just a warning—for example, where it is a constraint violation in the C standard, which must become an error with '`-pedantic-errors`'. The following idiom, where the first line shown is line *line* of the file and the line that generates the error, is used for this:

```
/* { dg-bogus "warning" "warning in place of error" } */
/* { dg-error "regexp" "message" { target *-*-* } line } */
```

It may be necessary to check that an expression is an integer constant expression and has a certain value. To check that *E* has value *V*, an idiom similar to the following is used:

```
char x[((E) == (V) ? 1 : -1)];
```

In '`gcc.dg`' tests, `__typeof__` is sometimes used to make assertions about the types of expressions. See, for example, '`gcc.dg/c99-condexpr-1.c`'. The more subtle uses depend on the exact rules for the types of conditional expressions in the C standard; see, for example, '`gcc.dg/c99-intconst-1.c`'.

It is useful to be able to test that optimizations are being made properly. This cannot be done in all cases, but it can be done where the optimization will lead to code being optimized away (for example, where flow analysis or alias analysis should show that certain code cannot be called) or to functions not being called because they have been expanded as built-in functions. Such tests go in '`gcc.c-torture/execute`'. Where code should be optimized away, a call to a nonexistent function such as `link_failure ()` may be inserted; a definition

```
#ifndef __OPTIMIZE__
void
link_failure (void)
{
  abort ();
}
#endif
```

will also be needed so that linking still succeeds when the test is run without optimization. When all calls to a built-in function should have been optimized and no calls to the non-built-in version of the function should remain, that function may be defined as `static` to call `abort ()` (although redeclaring a function as static may not work on all targets).

All testcases must be portable. Target-specific testcases must have appropriate code to avoid causing failures on unsupported systems; unfortunately, the mechanisms for this differ by directory.

FIXME: discuss non-C testsuites here.

7.2 Directives used within DejaGnu tests

7.2.1 Syntax and Descriptions of test directives

Test directives appear within comments in a test source file and begin with `dg-`. Some of these are defined within DejaGnu and others are local to the GCC testsuite.

The order in which test directives appear in a test can be important: directives local to GCC sometimes override information used by the DejaGnu directives, which know nothing about the GCC directives, so the DejaGnu directives must precede GCC directives.

Several test directives include selectors (see Section 7.2.2 [Selectors], page 82) which are usually preceded by the keyword `target` or `xfail`.

7.2.1.1 Specify how to build the test

`{ dg-do` *`do-what-keyword`* `[{ target/xfail` *`selector`* `}] }`

do-what-keyword specifies how the test is compiled and whether it is executed. It is one of:

`preprocess`
: Compile with '`-E`' to run only the preprocessor.

`compile`
: Compile with '`-S`' to produce an assembly code file.

`assemble`
: Compile with '`-c`' to produce a relocatable object file.

`link`
: Compile, assemble, and link to produce an executable file.

`run`
: Produce and run an executable file, which is expected to return an exit code of 0.

The default is `compile`. That can be overridden for a set of tests by redefining `dg-do-what-default` within the `.exp` file for those tests.

If the directive includes the optional '`{ target` *`selector`* `}`' then the test is skipped unless the target system matches the *selector*.

If *do-what-keyword* is `run` and the directive includes the optional '`{ xfail` *`selector`* `}`' and the selector is met then the test is expected to fail. The `xfail` clause is ignored for other values of *do-what-keyword*; those tests can use directive `dg-xfail-if`.

7.2.1.2 Specify additional compiler options

`{ dg-options` *`options`* `[{ target` *`selector`* `}] }`

This DejaGnu directive provides a list of compiler options, to be used if the target system matches *selector*, that replace the default options used for this set of tests.

`{ dg-add-options` *`feature ...`* `}`

Add any compiler options that are needed to access certain features. This directive does nothing on targets that enable the features by default, or that don't provide them at all. It must come after all `dg-options` directives. For supported values of *feature* see Section 7.2.4 [Add Options], page 92.

`{ dg-additional-options` *`options`* `[{ target` *`selector`* `}] }`

This directive provides a list of compiler options, to be used if the target system matches *selector*, that are added to the default options used for this set of tests.

7.2.1.3 Modify the test timeout value

The normal timeout limit, in seconds, is found by searching the following in order:

- the value defined by an earlier `dg-timeout` directive in the test
- variable *tool_timeout* defined by the set of tests
- *gcc,timeout* set in the target board
- 300

`{ dg-timeout` *`n`* `[{target` *`selector`* `}] }`

Set the time limit for the compilation and for the execution of the test to the specified number of seconds.

`{ dg-timeout-factor` *`x`* `[{ target` *`selector`* `}] }`

Multiply the normal time limit for compilation and execution of the test by the specified floating-point factor.

7.2.1.4 Skip a test for some targets

`{ dg-skip-if` *`comment`* `{` *`selector`* `} [{` *`include-opts`* `} [{` *`exclude-opts`* `}]] }`

Arguments *include-opts* and *exclude-opts* are lists in which each element is a string of zero or more GCC options. Skip the test if all of the following conditions are met:

- the test system is included in *selector*
- for at least one of the option strings in *include-opts*, every option from that string is in the set of options with which the test would be compiled; use '`"*"`' for an *include-opts* list that matches any options; that is the default if *include-opts* is not specified
- for each of the option strings in *exclude-opts*, at least one option from that string is not in the set of options with which the test would be compiled; use '`""`' for an empty *exclude-opts* list; that is the default if *exclude-opts* is not specified

For example, to skip a test if option `-Os` is present:

```
/* { dg-skip-if "" { *-*-* }  { "-Os" } { "" } } */
```

To skip a test if both options `-O2` and `-g` are present:

```
/* { dg-skip-if "" { *-*-* }  { "-O2 -g" } { "" } } */
```

To skip a test if either `-O2` or `-O3` is present:

```
/* { dg-skip-if "" { *-*-* }  { "-O2" "-O3" } { "" } } */
```

To skip a test unless option `-Os` is present:

```
/* { dg-skip-if "" { *-*-* }  { "*" } { "-Os" } } */
```

To skip a test if either `-O2` or `-O3` is used with `-g` but not if `-fpic` is also present:

```
/* { dg-skip-if "" { *-*-* }  { "-O2 -g" "-O3 -g" } { "-fpic" } } */
```

`{ dg-require-effective-target` *`keyword`* `[{` *`selector`* `}] }`

Skip the test if the test target, including current multilib flags, is not covered by the effective-target keyword. If the directive includes the optional '`{` *`selector`* `}`' then the effective-target test is only performed if the target system matches the *selector*. This directive must appear after any `dg-do` directive in the test and before any `dg-additional-sources` directive. See Section 7.2.3 [Effective-Target Keywords], page 82.

`{ dg-require-`*`support`* `args }`

Skip the test if the target does not provide the required support. These directives must appear after any `dg-do` directive in the test and before any `dg-additional-sources` directive. They require at least one argument, which can be an empty string if the specific procedure does not examine the argument. See Section 7.2.5 [Require Support], page 93, for a complete list of these directives.

7.2.1.5 Expect a test to fail for some targets

`{ dg-xfail-if` *`comment`* `{` *`selector`* `} [{` *`include-opts`* `} [{` *`exclude-opts`* `}]] }`

Expect the test to fail if the conditions (which are the same as for `dg-skip-if`) are met. This does not affect the execute step.

`{ dg-xfail-run-if` *`comment`* `{` *`selector`* `} [{` *`include-opts`* `} [{` *`exclude-opts`* `}]] }`

Expect the execute step of a test to fail if the conditions (which are the same as for `dg-skip-if`) are met.

7.2.1.6 Expect the test executable to fail

`{ dg-shouldfail` *`comment`* `[{` *`selector`* `} [{` *`include-opts`* `} [{` *`exclude-opts`* `}]]] }`

Expect the test executable to return a nonzero exit status if the conditions (which are the same as for `dg-skip-if`) are met.

7.2.1.7 Verify compiler messages

`{ dg-error` *`regexp`* `[`*`comment`* `[{ target/xfail` *`selector`* `} [`*`line`*`] }]] }`

This DejaGnu directive appears on a source line that is expected to get an error message, or else specifies the source line associated with the message. If there is no message for that line or if the text of that message is not matched by *regexp* then the check fails and *comment* is included in the `FAIL` message. The check does not look for the string '`error`' unless it is part of *regexp*.

`{ dg-warning regexp [comment [{ target/xfail selector } [line] }]] }`

This DejaGnu directive appears on a source line that is expected to get a warning message, or else specifies the source line associated with the message. If there is no message for that line or if the text of that message is not matched by *regexp* then the check fails and *comment* is included in the `FAIL` message. The check does not look for the string '`warning`' unless it is part of *regexp*.

`{ dg-message regexp [comment [{ target/xfail selector } [line] }]] }`

The line is expected to get a message other than an error or warning. If there is no message for that line or if the text of that message is not matched by *regexp* then the check fails and *comment* is included in the `FAIL` message.

`{ dg-bogus regexp [comment [{ target/xfail selector } [line] }]] }`

This DejaGnu directive appears on a source line that should not get a message matching *regexp*, or else specifies the source line associated with the bogus message. It is usually used with '`xfail`' to indicate that the message is a known problem for a particular set of targets.

`{ dg-excess-errors comment [{ target/xfail selector }] }`

This DejaGnu directive indicates that the test is expected to fail due to compiler messages that are not handled by '`dg-error`', '`dg-warning`' or '`dg-bogus`'. For this directive '`xfail`' has the same effect as '`target`'.

`{ dg-prune-output regexp }`

Prune messages matching *regexp* from the test output.

7.2.1.8 Verify output of the test executable

`{ dg-output regexp [{ target/xfail selector }] }`

This DejaGnu directive compares *regexp* to the combined output that the test executable writes to '`stdout`' and '`stderr`'.

7.2.1.9 Specify additional files for a test

`{ dg-additional-files "filelist" }`

Specify additional files, other than source files, that must be copied to the system where the compiler runs.

`{ dg-additional-sources "filelist" }`

Specify additional source files to appear in the compile line following the main test file.

7.2.1.10 Add checks at the end of a test

`{ dg-final { local-directive } }`

This DejaGnu directive is placed within a comment anywhere in the source file and is processed after the test has been compiled and run. Multiple '`dg-final`' commands are processed in the order in which they appear in the source file. See Section 7.2.6 [Final Actions], page 94, for a list of directives that can be used within `dg-final`.

7.2.2 Selecting targets to which a test applies

Several test directives include *selector*s to limit the targets for which a test is run or to declare that a test is expected to fail on particular targets.

A selector is:

- one or more target triplets, possibly including wildcard characters; use '`*-*-*`' to match any target
- a single effective-target keyword (see Section 7.2.3 [Effective-Target Keywords], page 82)
- a logical expression

Depending on the context, the selector specifies whether a test is skipped and reported as unsupported or is expected to fail. A context that allows either '`target`' or '`xfail`' also allows '`{ target` *`selector1`* `xfail` *`selector2`* `}`' to skip the test for targets that don't match *selector1* and the test to fail for targets that match *selector2*.

A selector expression appears within curly braces and uses a single logical operator: one of '`!`', '`&&`', or '`||`'. An operand is another selector expression, an effective-target keyword, a single target triplet, or a list of target triplets within quotes or curly braces. For example:

```
{ target { ! "hppa*-*-* ia64*-*-*" } }
{ target { powerpc*-*-* && lp64 } }
{ xfail { lp64 || vect_no_align } }
```

7.2.3 Keywords describing target attributes

Effective-target keywords identify sets of targets that support particular functionality. They are used to limit tests to be run only for particular targets, or to specify that particular sets of targets are expected to fail some tests.

Effective-target keywords are defined in '`lib/target-supports.exp`' in the GCC testsuite, with the exception of those that are documented as being local to a particular test directory.

The '`effective target`' takes into account all of the compiler options with which the test will be compiled, including the multilib options. By convention, keywords ending in `_nocache` can also include options specified for the particular test in an earlier `dg-options` or `dg-add-options` directive.

7.2.3.1 Data type sizes

`ilp32` Target has 32-bit `int`, `long`, and pointers.

`lp64` Target has 32-bit `int`, 64-bit `long` and pointers.

`llp64` Target has 32-bit `int` and `long`, 64-bit `long long` and pointers.

`double64` Target has 64-bit `double`.

`double64plus`
Target has `double` that is 64 bits or longer.

`int32plus`
Target has `int` that is at 32 bits or longer.

`int16` Target has `int` that is 16 bits or shorter.

`long_neq_int`
: Target has `int` and `long` with different sizes.

`large_double`
: Target supports `double` that is longer than `float`.

`large_long_double`
: Target supports `long double` that is longer than `double`.

`ptr32plus`
: Target has pointers that are 32 bits or longer.

`size32plus`
: Target supports array and structure sizes that are 32 bits or longer.

`4byte_wchar_t`
: Target has `wchar_t` that is at least 4 bytes.

7.2.3.2 Fortran-specific attributes

`fortran_integer_16`
: Target supports Fortran `integer` that is 16 bytes or longer.

`fortran_large_int`
: Target supports Fortran `integer` kinds larger than `integer(8)`.

`fortran_large_real`
: Target supports Fortran `real` kinds larger than `real(8)`.

7.2.3.3 Vector-specific attributes

`vect_condition`
: Target supports vector conditional operations.

`vect_double`
: Target supports hardware vectors of `double`.

`vect_float`
: Target supports hardware vectors of `float`.

`vect_int` Target supports hardware vectors of `int`.

`vect_long`
: Target supports hardware vectors of `long`.

`vect_long_long`
: Target supports hardware vectors of `long long`.

`vect_aligned_arrays`
: Target aligns arrays to vector alignment boundary.

`vect_hw_misalign`
: Target supports a vector misalign access.

`vect_no_align`
: Target does not support a vector alignment mechanism.

`vect_no_int_max`
: Target does not support a vector max instruction on `int`.

`vect_no_int_add`
: Target does not support a vector add instruction on `int`.

`vect_no_bitwise`
: Target does not support vector bitwise instructions.

`vect_char_mult`
: Target supports `vector char` multiplication.

`vect_short_mult`
: Target supports `vector short` multiplication.

`vect_int_mult`
: Target supports `vector int` multiplication.

`vect_extract_even_odd`
: Target supports vector even/odd element extraction.

`vect_extract_even_odd_wide`
: Target supports vector even/odd element extraction of vectors with elements `SImode` or larger.

`vect_interleave`
: Target supports vector interleaving.

`vect_strided`
: Target supports vector interleaving and extract even/odd.

`vect_strided_wide`
: Target supports vector interleaving and extract even/odd for wide element types.

`vect_perm`
: Target supports vector permutation.

`vect_shift`
: Target supports a hardware vector shift operation.

`vect_widen_sum_hi_to_si`
: Target supports a vector widening summation of `short` operands into `int` results, or can promote (unpack) from `short` to `int`.

`vect_widen_sum_qi_to_hi`
: Target supports a vector widening summation of `char` operands into `short` results, or can promote (unpack) from `char` to `short`.

`vect_widen_sum_qi_to_si`
: Target supports a vector widening summation of `char` operands into `int` results.

`vect_widen_mult_qi_to_hi`
: Target supports a vector widening multiplication of `char` operands into `short` results, or can promote (unpack) from `char` to `short` and perform non-widening multiplication of `short`.

`vect_widen_mult_hi_to_si`
: Target supports a vector widening multiplication of `short` operands into `int` results, or can promote (unpack) from `short` to `int` and perform non-widening multiplication of `int`.

`vect_widen_mult_si_to_di_pattern`
: Target supports a vector widening multiplication of `int` operands into `long` results.

`vect_sdot_qi`
: Target supports a vector dot-product of `signed char`.

`vect_udot_qi`
: Target supports a vector dot-product of `unsigned char`.

`vect_sdot_hi`
: Target supports a vector dot-product of `signed short`.

`vect_udot_hi`
: Target supports a vector dot-product of `unsigned short`.

`vect_pack_trunc`
: Target supports a vector demotion (packing) of `short` to `char` and from `int` to `short` using modulo arithmetic.

`vect_unpack`
: Target supports a vector promotion (unpacking) of `char` to `short` and from `char` to `int`.

`vect_intfloat_cvt`
: Target supports conversion from `signed int` to `float`.

`vect_uintfloat_cvt`
: Target supports conversion from `unsigned int` to `float`.

`vect_floatint_cvt`
: Target supports conversion from `float` to `signed int`.

`vect_floatuint_cvt`
: Target supports conversion from `float` to `unsigned int`.

7.2.3.4 Thread Local Storage attributes

`tls` Target supports thread-local storage.

`tls_native`
: Target supports native (rather than emulated) thread-local storage.

`tls_runtime`
: Test system supports executing TLS executables.

7.2.3.5 Decimal floating point attributes

`dfp` Targets supports compiling decimal floating point extension to C.

`dfp_nocache`
: Including the options used to compile this particular test, the target supports compiling decimal floating point extension to C.

`dfprt`
: Test system can execute decimal floating point tests.

`dfprt_nocache`
: Including the options used to compile this particular test, the test system can execute decimal floating point tests.

`hard_dfp`
: Target generates decimal floating point instructions with current options.

7.2.3.6 ARM-specific attributes

`arm32`
: ARM target generates 32-bit code.

`arm_eabi`
: ARM target adheres to the ABI for the ARM Architecture.

`arm_hf_eabi`
: ARM target adheres to the VFP and Advanced SIMD Register Arguments variant of the ABI for the ARM Architecture (as selected with `-mfloat-abi=hard`).

`arm_hard_vfp_ok`
: ARM target supports `-mfpu=vfp -mfloat-abi=hard`. Some multilibs may be incompatible with these options.

`arm_iwmmxt_ok`
: ARM target supports `-mcpu=iwmmxt`. Some multilibs may be incompatible with this option.

`arm_neon`
: ARM target supports generating NEON instructions.

`arm_neon_hw`
: Test system supports executing NEON instructions.

`arm_neonv2_hw`
: Test system supports executing NEON v2 instructions.

`arm_neon_ok`
: ARM Target supports `-mfpu=neon -mfloat-abi=softfp` or compatible options. Some multilibs may be incompatible with these options.

`arm_neonv2_ok`
: ARM Target supports `-mfpu=neon-vfpv4 -mfloat-abi=softfp` or compatible options. Some multilibs may be incompatible with these options.

`arm_neon_fp16_ok`
: ARM Target supports `-mfpu=neon-fp16 -mfloat-abi=softfp` or compatible options. Some multilibs may be incompatible with these options.

`arm_thumb1_ok`
: ARM target generates Thumb-1 code for `-mthumb`.

`arm_thumb2_ok`
: ARM target generates Thumb-2 code for `-mthumb`.

`arm_vfp_ok`
: ARM target supports `-mfpu=vfp -mfloat-abi=softfp`. Some multilibs may be incompatible with these options.

`arm_vfp3_ok`
: ARM target supports `-mfpu=vfp3 -mfloat-abi=softfp`. Some multilibs may be incompatible with these options.

`arm_v8_vfp_ok`
: ARM target supports `-mfpu=fp-armv8 -mfloat-abi=softfp`. Some multilibs may be incompatible with these options.

`arm_v8_neon_ok`
: ARM target supports `-mfpu=neon-fp-armv8 -mfloat-abi=softfp`. Some multilibs may be incompatible with these options.

`arm_prefer_ldrd_strd`
: ARM target prefers `LDRD` and `STRD` instructions over `LDM` and `STM` instructions.

7.2.3.7 MIPS-specific attributes

`mips64` MIPS target supports 64-bit instructions.

`nomips16` MIPS target does not produce MIPS16 code.

`mips16_attribute`
: MIPS target can generate MIPS16 code.

`mips_loongson`
: MIPS target is a Loongson-2E or -2F target using an ABI that supports the Loongson vector modes.

`mips_newabi_large_long_double`
: MIPS target supports `long double` larger than `double` when using the new ABI.

`mpaired_single`
: MIPS target supports `-mpaired-single`.

7.2.3.8 PowerPC-specific attributes

`powerpc64`
: Test system supports executing 64-bit instructions.

`powerpc_altivec`
: PowerPC target supports AltiVec.

`powerpc_altivec_ok`
: PowerPC target supports `-maltivec`.

`powerpc_fprs`
: PowerPC target supports floating-point registers.

`powerpc_hard_double`
: PowerPC target supports hardware double-precision floating-point.

`powerpc_ppu_ok`
: PowerPC target supports `-mcpu=cell`.

`powerpc_spe`
: PowerPC target supports PowerPC SPE.

`powerpc_spe_nocache`
: Including the options used to compile this particular test, the PowerPC target supports PowerPC SPE.

`powerpc_spu`
: PowerPC target supports PowerPC SPU.

`spu_auto_overlay`
: SPU target has toolchain that supports automatic overlay generation.

`powerpc_vsx_ok`
: PowerPC target supports `-mvsx`.

`powerpc_405_nocache`
: Including the options used to compile this particular test, the PowerPC target supports PowerPC 405.

`vmx_hw` PowerPC target supports executing AltiVec instructions.

7.2.3.9 Other hardware attributes

`avx` Target supports compiling `avx` instructions.

`avx_runtime`
: Target supports the execution of `avx` instructions.

`cell_hw` Test system can execute AltiVec and Cell PPU instructions.

`coldfire_fpu`
: Target uses a ColdFire FPU.

`hard_float`
: Target supports FPU instructions.

`sse` Target supports compiling `sse` instructions.

`sse_runtime`
: Target supports the execution of `sse` instructions.

`sse2` Target supports compiling `sse2` instructions.

`sse2_runtime`
: Target supports the execution of `sse2` instructions.

`sync_char_short`
: Target supports atomic operations on `char` and `short`.

`sync_int_long`
: Target supports atomic operations on `int` and `long`.

`ultrasparc_hw`
: Test environment appears to run executables on a simulator that accepts only `EM_SPARC` executables and chokes on `EM_SPARC32PLUS` or `EM_SPARCV9` executables.

`vect_cmdline_needed`
: Target requires a command line argument to enable a SIMD instruction set.

7.2.3.10 Environment attributes

`c` The language for the compiler under test is C.

`c++` The language for the compiler under test is C++.

`c99_runtime`
: Target provides a full C99 runtime.

`correct_iso_cpp_string_wchar_protos`
: Target `string.h` and `wchar.h` headers provide C++ required overloads for `strchr` etc. functions.

`dummy_wcsftime`
: Target uses a dummy `wcsftime` function that always returns zero.

`fd_truncate`
: Target can truncate a file from a file descriptor, as used by '`libgfortran/io/unix.c:fd_truncate`'; i.e. `ftruncate` or `chsize`.

`freestanding`
: Target is '`freestanding`' as defined in section 4 of the C99 standard. Effectively, it is a target which supports no extra headers or libraries other than what is considered essential.

`init_priority`
: Target supports constructors with initialization priority arguments.

`inttypes_types`
: Target has the basic signed and unsigned types in `inttypes.h`. This is for tests that GCC's notions of these types agree with those in the header, as some systems have only `inttypes.h`.

`lax_strtofp`
: Target might have errors of a few ULP in string to floating-point conversion functions and overflow is not always detected correctly by those functions.

`mmap` Target supports `mmap`.

`newlib` Target supports Newlib.

`pow10` Target provides `pow10` function.

`pthread` Target can compile using `pthread.h` with no errors or warnings.

`pthread_h`
: Target has `pthread.h`.

`run_expensive_tests`
: Expensive testcases (usually those that consume excessive amounts of CPU time) should be run on this target. This can be enabled by setting the `GCC_TEST_RUN_EXPENSIVE` environment variable to a non-empty string.

`simulator`
: Test system runs executables on a simulator (i.e. slowly) rather than hardware (i.e. fast).

`stdint_types`
: Target has the basic signed and unsigned C types in `stdint.h`. This will be obsolete when GCC ensures a working `stdint.h` for all targets.

`trampolines`
: Target supports trampolines.

`uclibc`
: Target supports uClibc.

`unwrapped`
: Target does not use a status wrapper.

`vxworks_kernel`
: Target is a VxWorks kernel.

`vxworks_rtp`
: Target is a VxWorks RTP.

`wchar`
: Target supports wide characters.

7.2.3.11 Other attributes

`automatic_stack_alignment`
: Target supports automatic stack alignment.

`cxa_atexit`
: Target uses `__cxa_atexit`.

`default_packed`
: Target has packed layout of structure members by default.

`fgraphite`
: Target supports Graphite optimizations.

`fixed_point`
: Target supports fixed-point extension to C.

`fopenmp`
: Target supports OpenMP via '`-fopenmp`'.

`fpic`
: Target supports '`-fpic`' and '`-fPIC`'.

`freorder`
: Target supports '`-freorder-blocks-and-partition`'.

`fstack_protector`
: Target supports '`-fstack-protector`'.

`gas`
: Target uses GNU `as`.

`gc_sections`
: Target supports '`--gc-sections`'.

`gld`
: Target uses GNU `ld`.

`keeps_null_pointer_checks`
: Target keeps null pointer checks, either due to the use of '`-fno-delete-null-pointer-checks`' or hardwired into the target.

`lto`
: Compiler has been configured to support link-time optimization (LTO).

`naked_functions`
: Target supports the `naked` function attribute.

`named_sections`
: Target supports named sections.

`natural_alignment_32`
: Target uses natural alignment (aligned to type size) for types of 32 bits or less.

`target_natural_alignment_64`
: Target uses natural alignment (aligned to type size) for types of 64 bits or less.

`nonpic`
: Target does not generate PIC by default.

`pcc_bitfield_type_matters`
: Target defines `PCC_BITFIELD_TYPE_MATTERS`.

`pe_aligned_commons`
: Target supports '`-mpe-aligned-commons`'.

`pie`
: Target supports '`-pie`', '`-fpie`' and '`-fPIE`'.

`section_anchors`
: Target supports section anchors.

`short_enums`
: Target defaults to short enums.

`static`
: Target supports '`-static`'.

`static_libgfortran`
: Target supports statically linking '`libgfortran`'.

`string_merging`
: Target supports merging string constants at link time.

`ucn`
: Target supports compiling and assembling UCN.

`ucn_nocache`
: Including the options used to compile this particular test, the target supports compiling and assembling UCN.

`unaligned_stack`
: Target does not guarantee that its `STACK_BOUNDARY` is greater than or equal to the required vector alignment.

`vector_alignment_reachable`
: Vector alignment is reachable for types of 32 bits or less.

`vector_alignment_reachable_for_64bit`
: Vector alignment is reachable for types of 64 bits or less.

`wchar_t_char16_t_compatible`
: Target supports `wchar_t` that is compatible with `char16_t`.

`wchar_t_char32_t_compatible`
: Target supports `wchar_t` that is compatible with `char32_t`.

7.2.3.12 Local to tests in `gcc.target/i386`

`3dnow` Target supports compiling `3dnow` instructions.

`aes` Target supports compiling `aes` instructions.

`fma4` Target supports compiling `fma4` instructions.

`ms_hook_prologue`
: Target supports attribute `ms_hook_prologue`.

`pclmul` Target supports compiling `pclmul` instructions.

`sse3` Target supports compiling `sse3` instructions.

`sse4` Target supports compiling `sse4` instructions.

`sse4a` Target supports compiling `sse4a` instructions.

`ssse3` Target supports compiling `ssse3` instructions.

`vaes` Target supports compiling `vaes` instructions.

`vpclmul` Target supports compiling `vpclmul` instructions.

`xop` Target supports compiling `xop` instructions.

7.2.3.13 Local to tests in `gcc.target/spu/ea`

`ealib` Target `__ea` library functions are available.

7.2.3.14 Local to tests in `gcc.test-framework`

`no` Always returns 0.

`yes` Always returns 1.

7.2.4 Features for `dg-add-options`

The supported values of *feature* for directive `dg-add-options` are:

`arm_neon` NEON support. Only ARM targets support this feature, and only then in certain modes; see the [arm_neon_ok effective target keyword], page 86.

`arm_neon_fp16`
: NEON and half-precision floating point support. Only ARM targets support this feature, and only then in certain modes; see the [arm_neon_fp16_ok effective target keyword], page 86.

`arm_vfp3` arm vfp3 floating point support; see the [arm_vfp3_ok effective target keyword], page 87.

`bind_pic_locally`
: Add the target-specific flags needed to enable functions to bind locally when using pic/PIC passes in the testsuite.

`c99_runtime`
: Add the target-specific flags needed to access the C99 runtime.

`ieee`
: Add the target-specific flags needed to enable full IEEE compliance mode.

`mips16_attribute`
: `mips16` function attributes. Only MIPS targets support this feature, and only then in certain modes.

`tls`
: Add the target-specific flags needed to use thread-local storage.

7.2.5 Variants of `dg-require-`*`support`*

A few of the `dg-require` directives take arguments.

`dg-require-iconv` *`codeset`*
: Skip the test if the target does not support iconv. *codeset* is the codeset to convert to.

`dg-require-profiling` *`profopt`*
: Skip the test if the target does not support profiling with option *profopt*.

`dg-require-visibility` *`vis`*
: Skip the test if the target does not support the `visibility` attribute. If *vis* is `""`, support for `visibility("hidden")` is checked, for `visibility("`*`vis`*`")` otherwise.

The original `dg-require` directives were defined before there was support for effective-target keywords. The directives that do not take arguments could be replaced with effective-target keywords.

`dg-require-alias ""`
: Skip the test if the target does not support the '`alias`' attribute.

`dg-require-ascii-locale ""`
: Skip the test if the host does not support an ASCII locale.

`dg-require-compat-dfp ""`
: Skip this test unless both compilers in a '`compat`' testsuite support decimal floating point.

`dg-require-cxa-atexit ""`
: Skip the test if the target does not support `__cxa_atexit`. This is equivalent to `dg-require-effective-target cxa_atexit`.

`dg-require-dll ""`
: Skip the test if the target does not support DLL attributes.

`dg-require-fork ""`
: Skip the test if the target does not support `fork`.

`dg-require-gc-sections ""`
: Skip the test if the target's linker does not support the `--gc-sections` flags. This is equivalent to `dg-require-effective-target gc-sections`.

`dg-require-host-local ""`
: Skip the test if the host is remote, rather than the same as the build system. Some tests are incompatible with DejaGnu's handling of remote hosts, which involves copying the source file to the host and compiling it with a relative path and `"-o a.out"`.

`dg-require-mkfifo ""`
: Skip the test if the target does not support `mkfifo`.

`dg-require-named-sections ""`
: Skip the test is the target does not support named sections. This is equivalent to `dg-require-effective-target named_sections`.

`dg-require-weak ""`
: Skip the test if the target does not support weak symbols.

`dg-require-weak-override ""`
: Skip the test if the target does not support overriding weak symbols.

7.2.6 Commands for use in `dg-final`

The GCC testsuite defines the following directives to be used within `dg-final`.

7.2.6.1 Scan a particular file

`scan-file` *`filename regexp`* `[{ target/xfail` *`selector`* `}]`
: Passes if *regexp* matches text in *filename*.

`scan-file-not` *`filename regexp`* `[{ target/xfail` *`selector`* `}]`
: Passes if *regexp* does not match text in *filename*.

`scan-module` *`module regexp`* `[{ target/xfail` *`selector`* `}]`
: Passes if *regexp* matches in Fortran module *module*.

7.2.6.2 Scan the assembly output

`scan-assembler` *`regex`* `[{ target/xfail` *`selector`* `}]`
: Passes if *regex* matches text in the test's assembler output.

`scan-assembler-not` *`regex`* `[{ target/xfail` *`selector`* `}]`
: Passes if *regex* does not match text in the test's assembler output.

`scan-assembler-times` *`regex num`* `[{ target/xfail` *`selector`* `}]`
: Passes if *regex* is matched exactly *num* times in the test's assembler output.

`scan-assembler-dem` *`regex`* `[{ target/xfail` *`selector`* `}]`
: Passes if *regex* matches text in the test's demangled assembler output.

`scan-assembler-dem-not` *`regex`* `[{ target/xfail` *`selector`* `}]`
: Passes if *regex* does not match text in the test's demangled assembler output.

`scan-hidden` *`symbol`* `[{ target/xfail` *`selector`* `}]`
Passes if *symbol* is defined as a hidden symbol in the test's assembly output.

`scan-not-hidden` *`symbol`* `[{ target/xfail` *`selector`* `}]`
Passes if *symbol* is not defined as a hidden symbol in the test's assembly output.

7.2.6.3 Scan optimization dump files

These commands are available for *kind* of `tree`, `rtl`, and `ipa`.

`scan-`*`kind`*`-dump` *`regex suffix`* `[{ target/xfail` *`selector`* `}]`
Passes if *regex* matches text in the dump file with suffix *suffix*.

`scan-`*`kind`*`-dump-not` *`regex suffix`* `[{ target/xfail` *`selector`* `}]`
Passes if *regex* does not match text in the dump file with suffix *suffix*.

`scan-`*`kind`*`-dump-times` *`regex num suffix`* `[{ target/xfail` *`selector`* `}]`
Passes if *regex* is found exactly *num* times in the dump file with suffix *suffix*.

`scan-`*`kind`*`-dump-dem` *`regex suffix`* `[{ target/xfail` *`selector`* `}]`
Passes if *regex* matches demangled text in the dump file with suffix *suffix*.

`scan-`*`kind`*`-dump-dem-not` *`regex suffix`* `[{ target/xfail` *`selector`* `}]`
Passes if *regex* does not match demangled text in the dump file with suffix *suffix*.

7.2.6.4 Verify that an output files exists or not

`output-exists [{ target/xfail` *`selector`* `}]`
Passes if compiler output file exists.

`output-exists-not [{ target/xfail` *`selector`* `}]`
Passes if compiler output file does not exist.

7.2.6.5 Check for LTO tests

`scan-symbol` *`regexp`* `[{ target/xfail` *`selector`* `}]`
Passes if the pattern is present in the final executable.

7.2.6.6 Checks for `gcov` tests

`run-gcov` *`sourcefile`*
Check line counts in `gcov` tests.

`run-gcov [branches] [calls] {` *`opts sourcefile`* `}`
Check branch and/or call counts, in addition to line counts, in `gcov` tests.

7.2.6.7 Clean up generated test files

`cleanup-coverage-files`
Removes coverage data files generated for this test.

`cleanup-ipa-dump` *`suffix`*
Removes IPA dump files generated for this test.

`cleanup-modules "`*`list-of-extra-modules`*`"`
: Removes Fortran module files generated for this test, excluding the module names listed in keep-modules. Cleaning up module files is usually done automatically by the testsuite by looking at the source files and removing the modules after the test has been executed.

```
module MoD1
end module MoD1
module Mod2
end module Mod2
module moD3
end module moD3
module mod4
end module mod4
! { dg-final { cleanup-modules "mod1 mod2" } } ! redundant
! { dg-final { keep-modules "mod3 mod4" } }
```

`keep-modules "`*`list-of-modules-not-to-delete`*`"`
: Whitespace separated list of module names that should not be deleted by cleanup-modules. If the list of modules is empty, all modules defined in this file are kept.

```
module maybe_unneeded
end module maybe_unneeded
module keep1
end module keep1
module keep2
end module keep2
! { dg-final { keep-modules "keep1 keep2" } } ! just keep these two
! { dg-final { keep-modules "" } } ! keep all
```

`cleanup-profile-file`
: Removes profiling files generated for this test.

`cleanup-repo-files`
: Removes files generated for this test for '`-frepo`'.

`cleanup-rtl-dump` *`suffix`*
: Removes RTL dump files generated for this test.

`cleanup-saved-temps`
: Removes files for the current test which were kept for '`-save-temps`'.

`cleanup-tree-dump` *`suffix`*
: Removes tree dump files matching *suffix* which were generated for this test.

7.3 Ada Language Testsuites

The Ada testsuite includes executable tests from the ACATS testsuite, publicly available at http://www.ada-auth.org/acats.html.

These tests are integrated in the GCC testsuite in the '`ada/acats`' directory, and enabled automatically when running `make check`, assuming the Ada language has been enabled when configuring GCC.

You can also run the Ada testsuite independently, using `make check-ada`, or run a subset of the tests by specifying which chapter to run, e.g.:

```
$ make check-ada CHAPTERS="c3 c9"
```

The tests are organized by directory, each directory corresponding to a chapter of the Ada Reference Manual. So for example, 'c9' corresponds to chapter 9, which deals with tasking features of the language.

There is also an extra chapter called 'gcc' containing a template for creating new executable tests, although this is deprecated in favor of the 'gnat.dg' testsuite.

The tests are run using two sh scripts: 'run_acats' and 'run_all.sh'. To run the tests using a simulator or a cross target, see the small customization section at the top of 'run_all.sh'.

These tests are run using the build tree: they can be run without doing a make install.

7.4 C Language Testsuites

GCC contains the following C language testsuites, in the 'gcc/testsuite' directory:

'gcc.dg' This contains tests of particular features of the C compiler, using the more modern 'dg' harness. Correctness tests for various compiler features should go here if possible.

Magic comments determine whether the file is preprocessed, compiled, linked or run. In these tests, error and warning message texts are compared against expected texts or regular expressions given in comments. These tests are run with the options '-ansi -pedantic' unless other options are given in the test. Except as noted below they are not run with multiple optimization options.

'gcc.dg/compat'
This subdirectory contains tests for binary compatibility using 'lib/compat.exp', which in turn uses the language-independent support (see Section 7.9 [Support for testing binary compatibility], page 101).

'gcc.dg/cpp'
This subdirectory contains tests of the preprocessor.

'gcc.dg/debug'
This subdirectory contains tests for debug formats. Tests in this subdirectory are run for each debug format that the compiler supports.

'gcc.dg/format'
This subdirectory contains tests of the '-Wformat' format checking. Tests in this directory are run with and without '-DWIDE'.

'gcc.dg/noncompile'
This subdirectory contains tests of code that should not compile and does not need any special compilation options. They are run with multiple optimization options, since sometimes invalid code crashes the compiler with optimization.

'gcc.dg/special'
FIXME: describe this.

'gcc.c-torture'
This contains particular code fragments which have historically broken easily. These tests are run with multiple optimization options, so tests for features

which only break at some optimization levels belong here. This also contains tests to check that certain optimizations occur. It might be worthwhile to separate the correctness tests cleanly from the code quality tests, but it hasn't been done yet.

'`gcc.c-torture/compat`'
: FIXME: describe this.

  This directory should probably not be used for new tests.

'`gcc.c-torture/compile`'
: This testsuite contains test cases that should compile, but do not need to link or run. These test cases are compiled with several different combinations of optimization options. All warnings are disabled for these test cases, so this directory is not suitable if you wish to test for the presence or absence of compiler warnings. While special options can be set, and tests disabled on specific platforms, by the use of '`.x`' files, mostly these test cases should not contain platform dependencies. FIXME: discuss how defines such as `NO_LABEL_VALUES` and `STACK_SIZE` are used.

'`gcc.c-torture/execute`'
: This testsuite contains test cases that should compile, link and run; otherwise the same comments as for '`gcc.c-torture/compile`' apply.

'`gcc.c-torture/execute/ieee`'
: This contains tests which are specific to IEEE floating point.

'`gcc.c-torture/unsorted`'
: FIXME: describe this.

  This directory should probably not be used for new tests.

'`gcc.misc-tests`'
: This directory contains C tests that require special handling. Some of these tests have individual expect files, and others share special-purpose expect files:

  '`bprob*.c`'
  : Test '`-fbranch-probabilities`' using '`gcc.misc-tests/bprob.exp`', which in turn uses the generic, language-independent framework (see Section 7.8 [Support for testing profile-directed optimizations], page 100).

  '`gcov*.c`' Test `gcov` output using '`gcov.exp`', which in turn uses the language-independent support (see Section 7.7 [Support for testing gcov], page 100).

  '`i386-pf-*.c`'
  : Test i386-specific support for data prefetch using '`i386-prefetch.exp`'.

'`gcc.test-framework`'
: '`dg-*.c`' Test the testsuite itself using '`gcc.test-framework/test-framework.exp`'.

FIXME: merge in '`testsuite/README.gcc`' and discuss the format of test cases and magic comments more.

7.5 The Java library testsuites.

Runtime tests are executed via '`make check`' in the '*target*`/libjava/testsuite`' directory in the build tree. Additional runtime tests can be checked into this testsuite.

Regression testing of the core packages in libgcj is also covered by the Mauve testsuite. The Mauve Project develops tests for the Java Class Libraries. These tests are run as part of libgcj testing by placing the Mauve tree within the libjava testsuite sources at '`libjava/testsuite/libjava.mauve/mauve`', or by specifying the location of that tree when invoking '`make`', as in '`make MAUVEDIR=~/mauve check`'.

To detect regressions, a mechanism in '`mauve.exp`' compares the failures for a test run against the list of expected failures in '`libjava/testsuite/libjava.mauve/xfails`' from the source hierarchy. Update this file when adding new failing tests to Mauve, or when fixing bugs in libgcj that had caused Mauve test failures.

We encourage developers to contribute test cases to Mauve.

7.6 Support for testing link-time optimizations

Tests for link-time optimizations usually require multiple source files that are compiled separately, perhaps with different sets of options. There are several special-purpose test directives used for these tests.

`{ dg-lto-do` *`do-what-keyword`* `}`

do-what-keyword specifies how the test is compiled and whether it is executed. It is one of:

`assemble` Compile with '`-c`' to produce a relocatable object file.

`link` Compile, assemble, and link to produce an executable file.

`run` Produce and run an executable file, which is expected to return an exit code of 0.

The default is `assemble`. That can be overridden for a set of tests by redefining `dg-do-what-default` within the `.exp` file for those tests.

Unlike `dg-do`, `dg-lto-do` does not support an optional '`target`' or '`xfail`' list. Use `dg-skip-if`, `dg-xfail-if`, or `dg-xfail-run-if`.

`{ dg-lto-options { {` *`options`* `} [{` *`options`* `}] } [{ target` *`selector`* `}]}`

This directive provides a list of one or more sets of compiler options to override *LTO_OPTIONS*. Each test will be compiled and run with each of these sets of options.

`{ dg-extra-ld-options` *`options`* `[{ target` *`selector`* `}]}`

This directive adds *options* to the linker options used.

`{ dg-suppress-ld-options` *`options`* `[{ target` *`selector`* `}]}`

This directive removes *options* from the set of linker options used.

7.7 Support for testing gcov

Language-independent support for testing gcov, and for checking that branch profiling produces expected values, is provided by the expect file 'lib/gcov.exp'. gcov tests also rely on procedures in 'lib/gcc-dg.exp' to compile and run the test program. A typical gcov test contains the following DejaGnu commands within comments:

```
{ dg-options "-fprofile-arcs -ftest-coverage" }
{ dg-do run { target native } }
{ dg-final { run-gcov sourcefile } }
```

Checks of gcov output can include line counts, branch percentages, and call return percentages. All of these checks are requested via commands that appear in comments in the test's source file. Commands to check line counts are processed by default. Commands to check branch percentages and call return percentages are processed if the run-gcov command has arguments branches or calls, respectively. For example, the following specifies checking both, as well as passing '-b' to gcov:

```
{ dg-final { run-gcov branches calls { -b sourcefile } } }
```

A line count command appears within a comment on the source line that is expected to get the specified count and has the form count(*cnt*). A test should only check line counts for lines that will get the same count for any architecture.

Commands to check branch percentages (branch) and call return percentages (returns) are very similar to each other. A beginning command appears on or before the first of a range of lines that will report the percentage, and the ending command follows that range of lines. The beginning command can include a list of percentages, all of which are expected to be found within the range. A range is terminated by the next command of the same kind. A command branch(end) or returns(end) marks the end of a range without starting a new one. For example:

```
if (i > 10 && j > i && j < 20)  /* branch(27 50 75) */
                                /* branch(end) */
  foo (i, j);
```

For a call return percentage, the value specified is the percentage of calls reported to return. For a branch percentage, the value is either the expected percentage or 100 minus that value, since the direction of a branch can differ depending on the target or the optimization level.

Not all branches and calls need to be checked. A test should not check for branches that might be optimized away or replaced with predicated instructions. Don't check for calls inserted by the compiler or ones that might be inlined or optimized away.

A single test can check for combinations of line counts, branch percentages, and call return percentages. The command to check a line count must appear on the line that will report that count, but commands to check branch percentages and call return percentages can bracket the lines that report them.

7.8 Support for testing profile-directed optimizations

The file 'profopt.exp' provides language-independent support for checking correct execution of a test built with profile-directed optimization. This testing requires that a test program be built and executed twice. The first time it is compiled to generate profile data, and the second time it is compiled to use the data that was generated during the first execution. The second execution is to verify that the test produces the expected results.

To check that the optimization actually generated better code, a test can be built and run a third time with normal optimizations to verify that the performance is better with the profile-directed optimizations. '`profopt.exp`' has the beginnings of this kind of support.

'`profopt.exp`' provides generic support for profile-directed optimizations. Each set of tests that uses it provides information about a specific optimization:

`tool` tool being tested, e.g., `gcc`

`profile_option`
: options used to generate profile data

`feedback_option`
: options used to optimize using that profile data

`prof_ext` suffix of profile data files

`PROFOPT_OPTIONS`
: list of options with which to run each test, similar to the lists for torture tests

`{ dg-final-generate { local-directive } }`
: This directive is similar to `dg-final`, but the *local-directive* is run after the generation of profile data.

`{ dg-final-use { local-directive } }`
: The *local-directive* is run after the profile data have been used.

7.9 Support for testing binary compatibility

The file '`compat.exp`' provides language-independent support for binary compatibility testing. It supports testing interoperability of two compilers that follow the same ABI, or of multiple sets of compiler options that should not affect binary compatibility. It is intended to be used for testsuites that complement ABI testsuites.

A test supported by this framework has three parts, each in a separate source file: a main program and two pieces that interact with each other to split up the functionality being tested.

'*testname*`_main.`*suffix*'
: Contains the main program, which calls a function in file '*testname*`_x.`*suffix*'.

'*testname*`_x.`*suffix*'
: Contains at least one call to a function in '*testname*`_y.`*suffix*'.

'*testname*`_y.`*suffix*'
: Shares data with, or gets arguments from, '*testname*`_x.`*suffix*'.

Within each test, the main program and one functional piece are compiled by the GCC under test. The other piece can be compiled by an alternate compiler. If no alternate compiler is specified, then all three source files are all compiled by the GCC under test. You can specify pairs of sets of compiler options. The first element of such a pair specifies options used with the GCC under test, and the second element of the pair specifies options used with the alternate compiler. Each test is compiled with each pair of options.

'`compat.exp`' defines default pairs of compiler options. These can be overridden by defining the environment variable `COMPAT_OPTIONS` as:

```
COMPAT_OPTIONS="[list [list {tst1} {alt1}]
  ...[list {tstn} {altn}]]"
```

where *tsti* and *alti* are lists of options, with *tsti* used by the compiler under test and *alti* used by the alternate compiler. For example, with `[list [list {-g -O0} {-O3}] [list {-fpic} {-fPIC -O2}]]`, the test is first built with '`-g -O0`' by the compiler under test and with '`-O3`' by the alternate compiler. The test is built a second time using '`-fpic`' by the compiler under test and '`-fPIC -O2`' by the alternate compiler.

An alternate compiler is specified by defining an environment variable to be the full pathname of an installed compiler; for C define `ALT_CC_UNDER_TEST`, and for C++ define `ALT_CXX_UNDER_TEST`. These will be written to the '`site.exp`' file used by DejaGnu. The default is to build each test with the compiler under test using the first of each pair of compiler options from `COMPAT_OPTIONS`. When `ALT_CC_UNDER_TEST` or `ALT_CXX_UNDER_TEST` is `same`, each test is built using the compiler under test but with combinations of the options from `COMPAT_OPTIONS`.

To run only the C++ compatibility suite using the compiler under test and another version of GCC using specific compiler options, do the following from '*objdir*/gcc':

```
rm site.exp
make -k \
  ALT_CXX_UNDER_TEST=${alt_prefix}/bin/g++ \
  COMPAT_OPTIONS="lists as shown above" \
  check-c++ \
  RUNTESTFLAGS="compat.exp"
```

A test that fails when the source files are compiled with different compilers, but passes when the files are compiled with the same compiler, demonstrates incompatibility of the generated code or runtime support. A test that fails for the alternate compiler but passes for the compiler under test probably tests for a bug that was fixed in the compiler under test but is present in the alternate compiler.

The binary compatibility tests support a small number of test framework commands that appear within comments in a test file.

`dg-require-*`
: These commands can be used in '*testname*_main.*suffix*' to skip the test if specific support is not available on the target.

`dg-options`
: The specified options are used for compiling this particular source file, appended to the options from `COMPAT_OPTIONS`. When this command appears in '*testname*_main.*suffix*' the options are also used to link the test program.

`dg-xfail-if`
: This command can be used in a secondary source file to specify that compilation is expected to fail for particular options on particular targets.

7.10 Support for torture testing using multiple options

Throughout the compiler testsuite there are several directories whose tests are run multiple times, each with a different set of options. These are known as torture tests. '`lib/torture-options.exp`' defines procedures to set up these lists:

`torture-init`
: Initialize use of torture lists.

`set-torture-options`
: Set lists of torture options to use for tests with and without loops. Optionally combine a set of torture options with a set of other options, as is done with Objective-C runtime options.

`torture-finish`
: Finalize use of torture lists.

The '`.exp`' file for a set of tests that use torture options must include calls to these three procedures if:

- It calls `gcc-dg-runtest` and overrides *DG_TORTURE_OPTIONS*.
- It calls *${tool}*`-torture` or *${tool}*`-torture-execute`, where *tool* is `c`, `fortran`, or `objc`.
- It calls `dg-pch`.

It is not necessary for a '`.exp`' file that calls `gcc-dg-runtest` to call the torture procedures if the tests should use the list in *DG_TORTURE_OPTIONS* defined in '`gcc-dg.exp`'.

Most uses of torture options can override the default lists by defining *TORTURE_OPTIONS* or add to the default list by defining *ADDITIONAL_TORTURE_OPTIONS*. Define these in a '`.dejagnurc`' file or add them to the '`site.exp`' file; for example

```
set ADDITIONAL_TORTURE_OPTIONS  [list \
  { -O2 -ftree-loop-linear } \
  { -O2 -fpeel-loops } ]
```

8 Option specification files

Most GCC command-line options are described by special option definition files, the names of which conventionally end in `.opt`. This chapter describes the format of these files.

8.1 Option file format

Option files are a simple list of records in which each field occupies its own line and in which the records themselves are separated by blank lines. Comments may appear on their own line anywhere within the file and are preceded by semicolons. Whitespace is allowed before the semicolon.

The files can contain the following types of record:

- A language definition record. These records have two fields: the string '`Language`' and the name of the language. Once a language has been declared in this way, it can be used as an option property. See Section 8.2 [Option properties], page 107.
- A target specific save record to save additional information. These records have two fields: the string '`TargetSave`', and a declaration type to go in the `cl_target_option` structure.
- A variable record to define a variable used to store option information. These records have two fields: the string '`Variable`', and a declaration of the type and name of the variable, optionally with an initializer (but without any trailing '`;`'). These records may be used for variables used for many options where declaring the initializer in a single option definition record, or duplicating it in many records, would be inappropriate, or for variables set in option handlers rather than referenced by `Var` properties.
- A variable record to define a variable used to store option information. These records have two fields: the string '`TargetVariable`', and a declaration of the type and name of the variable, optionally with an initializer (but without any trailing '`;`'). '`TargetVariable`' is a combination of '`Variable`' and '`TargetSave`' records in that the variable is defined in the `gcc_options` structure, but these variables are also stored in the `cl_target_option` structure. The variables are saved in the target save code and restored in the target restore code.
- A variable record to record any additional files that the '`options.h`' file should include. This is useful to provide enumeration or structure definitions needed for target variables. These records have two fields: the string '`HeaderInclude`' and the name of the include file.
- A variable record to record any additional files that the '`options.c`' or '`options-save.c`' file should include. This is useful to provide inline functions needed for target variables and/or `#ifdef` sequences to properly set up the initialization. These records have two fields: the string '`SourceInclude`' and the name of the include file.
- An enumeration record to define a set of strings that may be used as arguments to an option or options. These records have three fields: the string '`Enum`', a space-separated list of properties and help text used to describe the set of strings in '`--help`' output. Properties use the same format as option properties; the following are valid:

`Name(name)`
: This property is required; *name* must be a name (suitable for use in C identifiers) used to identify the set of strings in `Enum` option properties.

`Type(type)`
: This property is required; *type* is the C type for variables set by options using this enumeration together with `Var`.

`UnknownError(message)`
: The message *message* will be used as an error message if the argument is invalid; for enumerations without `UnknownError`, a generic error message is used. *message* should contain a single '`%qs`' format, which will be used to format the invalid argument.

- An enumeration value record to define one of the strings in a set given in an '`Enum`' record. These records have two fields: the string '`EnumValue`' and a space-separated list of properties. Properties use the same format as option properties; the following are valid:

  `Enum(name)`
  : This property is required; *name* says which '`Enum`' record this '`EnumValue`' record corresponds to.

  `String(string)`
  : This property is required; *string* is the string option argument being described by this record.

  `Value(value)`
  : This property is required; it says what value (representable as `int`) should be used for the given string.

  `Canonical`
  : This property is optional. If present, it says the present string is the canonical one among all those with the given value. Other strings yielding that value will be mapped to this one so specs do not need to handle them.

  `DriverOnly`
  : This property is optional. If present, the present string will only be accepted by the driver. This is used for cases such as '`-march=native`' that are processed by the driver so that '`gcc -v`' shows how the options chosen depended on the system on which the compiler was run.

- An option definition record. These records have the following fields:
  1. the name of the option, with the leading "-" removed
  2. a space-separated list of option properties (see Section 8.2 [Option properties], page 107)
  3. the help text to use for '`--help`' (omitted if the second field contains the `Undocumented` property).

  By default, all options beginning with "f", "W" or "m" are implicitly assumed to take a "no-" form. This form should not be listed separately. If an option beginning with one of these letters does not have a "no-" form, you can use the `RejectNegative` property to reject it.

The help text is automatically line-wrapped before being displayed. Normally the name of the option is printed on the left-hand side of the output and the help text is printed on the right. However, if the help text contains a tab character, the text to the left of the tab is used instead of the option's name and the text to the right of the tab forms the help text. This allows you to elaborate on what type of argument the option takes.

- A target mask record. These records have one field of the form '`Mask(x)`'. The options-processing script will automatically allocate a bit in `target_flags` (see Section 17.3 [Run-time Target], page 428) for each mask name *x* and set the macro `MASK_x` to the appropriate bitmask. It will also declare a `TARGET_x` macro that has the value 1 when bit `MASK_x` is set and 0 otherwise.

  They are primarily intended to declare target masks that are not associated with user options, either because these masks represent internal switches or because the options are not available on all configurations and yet the masks always need to be defined.

8.2 Option properties

The second field of an option record can specify any of the following properties. When an option takes an argument, it is enclosed in parentheses following the option property name. The parser that handles option files is quite simplistic, and will be tricked by any nested parentheses within the argument text itself; in this case, the entire option argument can be wrapped in curly braces within the parentheses to demarcate it, e.g.:

```
Condition({defined (USE_CYGWIN_LIBSTDCXX_WRAPPERS)})
```

`Common` The option is available for all languages and targets.

`Target` The option is available for all languages but is target-specific.

`Driver` The option is handled by the compiler driver using code not shared with the compilers proper ('`cc1`' etc.).

`language` The option is available when compiling for the given language.

It is possible to specify several different languages for the same option. Each *language* must have been declared by an earlier `Language` record. See Section 8.1 [Option file format], page 105.

`RejectDriver`
The option is only handled by the compilers proper ('`cc1`' etc.) and should not be accepted by the driver.

`RejectNegative`
The option does not have a "no-" form. All options beginning with "f", "W" or "m" are assumed to have a "no-" form unless this property is used.

`Negative(`*`othername`*`)`
The option will turn off another option *othername*, which is the option name with the leading "-" removed. This chain action will propagate through the `Negative` property of the option to be turned off.

As a consequence, if you have a group of mutually-exclusive options, their `Negative` properties should form a circular chain. For example, if options '`-a`', '`-b`' and '`-c`' are mutually exclusive, their respective `Negative` properties should be '`Negative(b)`', '`Negative(c)`' and '`Negative(a)`'.

`Joined`
`Separate` The option takes a mandatory argument. `Joined` indicates that the option and argument can be included in the same `argv` entry (as with `-mflush-func=name`, for example). `Separate` indicates that the option and argument can be separate `argv` entries (as with `-o`). An option is allowed to have both of these properties.

`JoinedOrMissing`
The option takes an optional argument. If the argument is given, it will be part of the same `argv` entry as the option itself.

This property cannot be used alongside `Joined` or `Separate`.

`MissingArgError(message)`
For an option marked `Joined` or `Separate`, the message *message* will be used as an error message if the mandatory argument is missing; for options without `MissingArgError`, a generic error message is used. *message* should contain a single '`%qs`' format, which will be used to format the name of the option passed.

`Args(n)` For an option marked `Separate`, indicate that it takes *n* arguments. The default is 1.

`UInteger` The option's argument is a non-negative integer. The option parser will check and convert the argument before passing it to the relevant option handler. `UInteger` should also be used on options like `-falign-loops` where both `-falign-loops` and `-falign-loops=n` are supported to make sure the saved options are given a full integer.

`ToLower` The option's argument should be converted to lowercase as part of putting it in canonical form, and before comparing with the strings indicated by any `Enum` property.

`NoDriverArg`
For an option marked `Separate`, the option only takes an argument in the compiler proper, not in the driver. This is for compatibility with existing options that are used both directly and via '`-Wp,`'; new options should not have this property.

`Var(var)` The state of this option should be stored in variable *var* (actually a macro for `global_options.x_var`). The way that the state is stored depends on the type of option:

- If the option uses the `Mask` or `InverseMask` properties, *var* is the integer variable that contains the mask.
- If the option is a normal on/off switch, *var* is an integer variable that is nonzero when the option is enabled. The options parser will set the variable to 1 when the positive form of the option is used and 0 when the "no-" form is used.
- If the option takes an argument and has the `UInteger` property, *var* is an integer variable that stores the value of the argument.
- If the option takes an argument and has the `Enum` property, *var* is a variable (type given in the `Type` property of the '`Enum`' record whose `Name` property

has the same argument as the `Enum` property of this option) that stores the value of the argument.

- If the option has the `Defer` property, *var* is a pointer to a `VEC(cl_deferred_option,heap)` that stores the option for later processing. (*var* is declared with type `void *` and needs to be cast to `VEC(cl_deferred_option,heap)` before use.)
- Otherwise, if the option takes an argument, *var* is a pointer to the argument string. The pointer will be null if the argument is optional and wasn't given.

The option-processing script will usually zero-initialize *var*. You can modify this behavior using `Init`.

`Var(var, set)`

The option controls an integer variable *var* and is active when *var* equals *set*. The option parser will set *var* to *set* when the positive form of the option is used and `!set` when the "no-" form is used.

var is declared in the same way as for the single-argument form described above.

`Init(value)`

The variable specified by the `Var` property should be statically initialized to *value*. If more than one option using the same variable specifies `Init`, all must specify the same initializer.

`Mask(name)`

The option is associated with a bit in the `target_flags` variable (see Section 17.3 [Run-time Target], page 428) and is active when that bit is set. You may also specify `Var` to select a variable other than `target_flags`.

The options-processing script will automatically allocate a unique bit for the option. If the option is attached to '`target_flags`', the script will set the macro `MASK_name` to the appropriate bitmask. It will also declare a `TARGET_name` macro that has the value 1 when the option is active and 0 otherwise. If you use `Var` to attach the option to a different variable, the bitmask macro with be called `OPTION_MASK_name`.

`InverseMask(othername)`
`InverseMask(othername, thisname)`

The option is the inverse of another option that has the `Mask(othername)` property. If *thisname* is given, the options-processing script will declare a `TARGET_thisname` macro that is 1 when the option is active and 0 otherwise.

`Enum(name)`

The option's argument is a string from the set of strings associated with the corresponding '`Enum`' record. The string is checked and converted to the integer specified in the corresponding '`EnumValue`' record before being passed to option handlers.

`Defer` The option should be stored in a vector, specified with `Var`, for later processing.

`Alias(opt)`
`Alias(opt, arg)`
`Alias(opt, posarg, negarg)`

The option is an alias for '`-opt`' (or the negative form of that option, depending on `NegativeAlias`). In the first form, any argument passed to the alias is considered to be passed to '`-opt`', and '`-opt`' is considered to be negated if the alias is used in negated form. In the second form, the alias may not be negated or have an argument, and *posarg* is considered to be passed as an argument to '`-opt`'. In the third form, the alias may not have an argument, if the alias is used in the positive form then *posarg* is considered to be passed to '`-opt`', and if the alias is used in the negative form then *negarg* is considered to be passed to '`-opt`'.

Aliases should not specify `Var` or `Mask` or `UInteger`. Aliases should normally specify the same languages as the target of the alias; the flags on the target will be used to determine any diagnostic for use of an option for the wrong language, while those on the alias will be used to identify what command-line text is the option and what text is any argument to that option.

When an `Alias` definition is used for an option, driver specs do not need to handle it and no '`OPT_`' enumeration value is defined for it; only the canonical form of the option will be seen in those places.

`NegativeAlias`

For an option marked with `Alias(opt)`, the option is considered to be an alias for the positive form of '`-opt`' if negated and for the negative form of '`-opt`' if not negated. `NegativeAlias` may not be used with the forms of `Alias` taking more than one argument.

`Ignore`

This option is ignored apart from printing any warning specified using `Warn`. The option will not be seen by specs and no '`OPT_`' enumeration value is defined for it.

`SeparateAlias`

For an option marked with `Joined`, `Separate` and `Alias`, the option only acts as an alias when passed a separate argument; with a joined argument it acts as a normal option, with an '`OPT_`' enumeration value. This is for compatibility with the Java '`-d`' option and should not be used for new options.

`Warn(message)`

If this option is used, output the warning *message*. *message* is a format string, either taking a single operand with a '`%qs`' format which is the option name, or not taking any operands, which is passed to the '`warning`' function. If an alias is marked `Warn`, the target of the alias must not also be marked `Warn`.

`Report`

The state of the option should be printed by '`-fverbose-asm`'.

`Warning`

This is a warning option and should be shown as such in '`--help`' output. This flag does not currently affect anything other than '`--help`'.

`Optimization`
This is an optimization option. It should be shown as such in '`--help`' output, and any associated variable named using `Var` should be saved and restored when the optimization level is changed with `optimize` attributes.

`Undocumented`
The option is deliberately missing documentation and should not be included in the '`--help`' output.

`Condition(`*`cond`*`)`
The option should only be accepted if preprocessor condition *cond* is true. Note that any C declarations associated with the option will be present even if *cond* is false; *cond* simply controls whether the option is accepted and whether it is printed in the '`--help`' output.

`Save`
Build the `cl_target_option` structure to hold a copy of the option, add the functions `cl_target_option_save` and `cl_target_option_restore` to save and restore the options.

`SetByCombined`
The option may also be set by a combined option such as '`-ffast-math`'. This causes the `gcc_options` struct to have a field `frontend_set_`*`name`*, where *name* is the name of the field holding the value of this option (without the leading `x_`). This gives the front end a way to indicate that the value has been set explicitly and should not be changed by the combined option. For example, some front ends use this to prevent '`-ffast-math`' and '`-fno-fast-math`' from changing the value of '`-fmath-errno`' for languages that do not use `errno`.

`EnabledBy(`*`opt`*`)`
`EnabledBy(`*`opt && opt2`*`)`
If not explicitly set, the option is set to the value of '`-`*`opt`*'. The second form specifies that the option is only set if both *opt* and *opt2* are set.

`LangEnabledBy(`*`language, opt`*`)`
`LangEnabledBy(`*`language, opt, posarg, negarg`*`)`
When compiling for the given language, the option is set to the value of '`-`*`opt`*', if not explicitly set. In the second form, if *opt* is used in the positive form then *posarg* is considered to be passed to the option, and if *opt* is used in the negative form then *negarg* is considered to be passed to the option. It is possible to specify several different languages. Each *language* must have been declared by an earlier `Language` record. See Section 8.1 [Option file format], page 105.

`NoDWARFRecord`
The option is omitted from the producer string written by '`-grecord-gcc-switches`'.

`PchIgnore`
Even if this is a target option, this option will not be recorded / compared to determine if a precompiled header file matches.

9 Passes and Files of the Compiler

This chapter is dedicated to giving an overview of the optimization and code generation passes of the compiler. In the process, it describes some of the language front end interface, though this description is no where near complete.

9.1 Parsing pass

The language front end is invoked only once, via `lang_hooks.parse_file`, to parse the entire input. The language front end may use any intermediate language representation deemed appropriate. The C front end uses GENERIC trees (see Chapter 10 [GENERIC], page 129), plus a double handful of language specific tree codes defined in '`c-common.def`'. The Fortran front end uses a completely different private representation.

At some point the front end must translate the representation used in the front end to a representation understood by the language-independent portions of the compiler. Current practice takes one of two forms. The C front end manually invokes the gimplifier (see Chapter 11 [GIMPLE], page 175) on each function, and uses the gimplifier callbacks to convert the language-specific tree nodes directly to GIMPLE before passing the function off to be compiled. The Fortran front end converts from a private representation to GENERIC, which is later lowered to GIMPLE when the function is compiled. Which route to choose probably depends on how well GENERIC (plus extensions) can be made to match up with the source language and necessary parsing data structures.

BUG: Gimplification must occur before nested function lowering, and nested function lowering must be done by the front end before passing the data off to cgraph.

TODO: Cgraph should control nested function lowering. It would only be invoked when it is certain that the outer-most function is used.

TODO: Cgraph needs a gimplify_function callback. It should be invoked when (1) it is certain that the function is used, (2) warning flags specified by the user require some amount of compilation in order to honor, (3) the language indicates that semantic analysis is not complete until gimplification occurs. Hum... this sounds overly complicated. Perhaps we should just have the front end gimplify always; in most cases it's only one function call.

The front end needs to pass all function definitions and top level declarations off to the middle-end so that they can be compiled and emitted to the object file. For a simple procedural language, it is usually most convenient to do this as each top level declaration or definition is seen. There is also a distinction to be made between generating functional code and generating complete debug information. The only thing that is absolutely required for functional code is that function and data *definitions* be passed to the middle-end. For complete debug information, function, data and type declarations should all be passed as well.

In any case, the front end needs each complete top-level function or data declaration, and each data definition should be passed to `rest_of_decl_compilation`. Each complete type definition should be passed to `rest_of_type_compilation`. Each function definition should be passed to `cgraph_finalize_function`.

TODO: I know rest_of_compilation currently has all sorts of RTL generation semantics. I plan to move all code generation bits (both Tree and RTL) to compile_function. Should we hide cgraph from the front ends and move back to rest_of_compilation as the official

interface? Possibly we should rename all three interfaces such that the names match in some meaningful way and that is more descriptive than "rest_of".

The middle-end will, at its option, emit the function and data definitions immediately or queue them for later processing.

9.2 Cilk Plus Transformation

If Cilk Plus generation (flag '-fcilkplus') is enabled, all the Cilk Plus code is transformed into equivalent C and C++ functions. Majority of this transformation occurs toward the end of the parsing and right before the gimplification pass.

These are the major components to the Cilk Plus language extension:

- Array Notations: During parsing phase, all the array notation specific information is stored in ARRAY_NOTATION_REF tree using the function c_parser_array_notation. During the end of parsing, we check the entire function to see if there are any array notation specific code (using the function contains_array_notation_expr). If this function returns true, then we expand them using either expand_array_notation_exprs or build_array_notation_expr. For the cases where array notations are inside conditions, they are transformed using the function fix_conditional_array_notations. The C language-specific routines are located in 'c/c-array-notation.c' and the equivalent C++ routines are in the file 'cp/cp-array-notation.c'. Common routines such as functions to initialize built-in functions are stored in 'array-notation-common.c'.
- Cilk keywords:
  - _Cilk_spawn: The _Cilk_spawn keyword is parsed and the function it contains is marked as a spawning function. The spawning function is called the spawner. At the end of the parsing phase, appropriate built-in functions are added to the spawner that are defined in the Cilk runtime. The appropriate locations of these functions, and the internal structures are detailed in cilk_init_builtins in the file 'cilk-common.c'. The pointers to Cilk functions and fields of internal structures are described in 'cilk.h'. The built-in functions are described in 'cilk-builtins.def'.

    During gimplification, a new "spawn-helper" function is created. The spawned function is replaced with a spawn helper function in the spawner. The spawned function-call is moved into the spawn helper. The main function that does these transformations is gimplify_cilk_spawn in 'c-family/cilk.c'. In the spawn-helper, the gimplification function gimplify_call_expr, inserts a function call __cilkrts_detach. This function is expanded by builtin_expand_cilk_detach located in 'c-family/cilk.c'.
  - _Cilk_sync: _Cilk_sync is parsed like a keyword. During gimplification, the function gimplify_cilk_sync in 'c-family/cilk.c', will replace this keyword with a set of functions that are stored in the Cilk runtime. One of the internal functions inserted during gimplification, __cilkrts_pop_frame must be expanded by the compiler and is done by builtin_expand_cilk_pop_frame in 'cilk-common.c'.

Documentation about Cilk Plus and language specification is provided under the "Learn" section in http://www.cilkplus.org/. It is worth mentioning that the current implementation follows ABI 1.1.

9.3 Gimplification pass

Gimplification is a whimsical term for the process of converting the intermediate representation of a function into the GIMPLE language (see Chapter 11 [GIMPLE], page 175). The term stuck, and so words like "gimplification", "gimplify", "gimplifier" and the like are sprinkled throughout this section of code.

While a front end may certainly choose to generate GIMPLE directly if it chooses, this can be a moderately complex process unless the intermediate language used by the front end is already fairly simple. Usually it is easier to generate GENERIC trees plus extensions and let the language-independent gimplifier do most of the work.

The main entry point to this pass is `gimplify_function_tree` located in '`gimplify.c`'. From here we process the entire function gimplifying each statement in turn. The main workhorse for this pass is `gimplify_expr`. Approximately everything passes through here at least once, and it is from here that we invoke the `lang_hooks.gimplify_expr` callback.

The callback should examine the expression in question and return `GS_UNHANDLED` if the expression is not a language specific construct that requires attention. Otherwise it should alter the expression in some way to such that forward progress is made toward producing valid GIMPLE. If the callback is certain that the transformation is complete and the expression is valid GIMPLE, it should return `GS_ALL_DONE`. Otherwise it should return `GS_OK`, which will cause the expression to be processed again. If the callback encounters an error during the transformation (because the front end is relying on the gimplification process to finish semantic checks), it should return `GS_ERROR`.

9.4 Pass manager

The pass manager is located in '`passes.c`', '`tree-optimize.c`' and '`tree-pass.h`'. It processes passes as described in '`passes.def`'. Its job is to run all of the individual passes in the correct order, and take care of standard bookkeeping that applies to every pass.

The theory of operation is that each pass defines a structure that represents everything we need to know about that pass—when it should be run, how it should be run, what intermediate language form or on-the-side data structures it needs. We register the pass to be run in some particular order, and the pass manager arranges for everything to happen in the correct order.

The actuality doesn't completely live up to the theory at present. Command-line switches and `timevar_id_t` enumerations must still be defined elsewhere. The pass manager validates constraints but does not attempt to (re-)generate data structures or lower intermediate language form based on the requirements of the next pass. Nevertheless, what is present is useful, and a far sight better than nothing at all.

Each pass should have a unique name. Each pass may have its own dump file (for GCC debugging purposes). Passes with a name starting with a star do not dump anything. Sometimes passes are supposed to share a dump file / option name. To still give these unique names, you can use a prefix that is delimited by a space from the part that is used for the dump file / option name. E.g. When the pass name is `"ud dce"`, the name used for dump file/options is `"dce"`.

TODO: describe the global variables set up by the pass manager, and a brief description of how a new pass should use it. I need to look at what info RTL passes use first. . .

9.5 Tree SSA passes

The following briefly describes the Tree optimization passes that are run after gimplification and what source files they are located in.

- Remove useless statements

  This pass is an extremely simple sweep across the gimple code in which we identify obviously dead code and remove it. Here we do things like simplify `if` statements with constant conditions, remove exception handling constructs surrounding code that obviously cannot throw, remove lexical bindings that contain no variables, and other assorted simplistic cleanups. The idea is to get rid of the obvious stuff quickly rather than wait until later when it's more work to get rid of it. This pass is located in '`tree-cfg.c`' and described by `pass_remove_useless_stmts`.

- OpenMP lowering

  If OpenMP generation ('`-fopenmp`') is enabled, this pass lowers OpenMP constructs into GIMPLE.

  Lowering of OpenMP constructs involves creating replacement expressions for local variables that have been mapped using data sharing clauses, exposing the control flow of most synchronization directives and adding region markers to facilitate the creation of the control flow graph. The pass is located in '`omp-low.c`' and is described by `pass_lower_omp`.

- OpenMP expansion

  If OpenMP generation ('`-fopenmp`') is enabled, this pass expands parallel regions into their own functions to be invoked by the thread library. The pass is located in '`omp-low.c`' and is described by `pass_expand_omp`.

- Lower control flow

  This pass flattens `if` statements (`COND_EXPR`) and moves lexical bindings (`BIND_EXPR`) out of line. After this pass, all `if` statements will have exactly two `goto` statements in its `then` and `else` arms. Lexical binding information for each statement will be found in `TREE_BLOCK` rather than being inferred from its position under a `BIND_EXPR`. This pass is found in '`gimple-low.c`' and is described by `pass_lower_cf`.

- Lower exception handling control flow

  This pass decomposes high-level exception handling constructs (`TRY_FINALLY_EXPR` and `TRY_CATCH_EXPR`) into a form that explicitly represents the control flow involved. After this pass, `lookup_stmt_eh_region` will return a non-negative number for any statement that may have EH control flow semantics; examine `tree_can_throw_internal` or `tree_can_throw_external` for exact semantics. Exact control flow may be extracted from `foreach_reachable_handler`. The EH region nesting tree is defined in '`except.h`' and built in '`except.c`'. The lowering pass itself is in '`tree-eh.c`' and is described by `pass_lower_eh`.

- Build the control flow graph

  This pass decomposes a function into basic blocks and creates all of the edges that connect them. It is located in '`tree-cfg.c`' and is described by `pass_build_cfg`.

- Find all referenced variables

  This pass walks the entire function and collects an array of all variables referenced in the function, `referenced_vars`. The index at which a variable is found in the

array is used as a UID for the variable within this function. This data is needed by the SSA rewriting routines. The pass is located in '`tree-dfa.c`' and is described by `pass_referenced_vars`.

- Enter static single assignment form

  This pass rewrites the function such that it is in SSA form. After this pass, all `is_gimple_reg` variables will be referenced by `SSA_NAME`, and all occurrences of other variables will be annotated with `VDEFS` and `VUSES`; PHI nodes will have been inserted as necessary for each basic block. This pass is located in '`tree-ssa.c`' and is described by `pass_build_ssa`.

- Warn for uninitialized variables

  This pass scans the function for uses of `SSA_NAME`s that are fed by default definition. For non-parameter variables, such uses are uninitialized. The pass is run twice, before and after optimization (if turned on). In the first pass we only warn for uses that are positively uninitialized; in the second pass we warn for uses that are possibly uninitialized. The pass is located in '`tree-ssa.c`' and is defined by `pass_early_warn_uninitialized` and `pass_late_warn_uninitialized`.

- Dead code elimination

  This pass scans the function for statements without side effects whose result is unused. It does not do memory life analysis, so any value that is stored in memory is considered used. The pass is run multiple times throughout the optimization process. It is located in '`tree-ssa-dce.c`' and is described by `pass_dce`.

- Dominator optimizations

  This pass performs trivial dominator-based copy and constant propagation, expression simplification, and jump threading. It is run multiple times throughout the optimization process. It is located in '`tree-ssa-dom.c`' and is described by `pass_dominator`.

- Forward propagation of single-use variables

  This pass attempts to remove redundant computation by substituting variables that are used once into the expression that uses them and seeing if the result can be simplified. It is located in '`tree-ssa-forwprop.c`' and is described by `pass_forwprop`.

- Copy Renaming

  This pass attempts to change the name of compiler temporaries involved in copy operations such that SSA->normal can coalesce the copy away. When compiler temporaries are copies of user variables, it also renames the compiler temporary to the user variable resulting in better use of user symbols. It is located in '`tree-ssa-copyrename.c`' and is described by `pass_copyrename`.

- PHI node optimizations

  This pass recognizes forms of PHI inputs that can be represented as conditional expressions and rewrites them into straight line code. It is located in '`tree-ssa-phiopt.c`' and is described by `pass_phiopt`.

- May-alias optimization

  This pass performs a flow sensitive SSA-based points-to analysis. The resulting may-alias, must-alias, and escape analysis information is used to promote variables from in-memory addressable objects to non-aliased variables that can be renamed into SSA

form. We also update the VDEF/VUSE memory tags for non-renameable aggregates so that we get fewer false kills. The pass is located in 'tree-ssa-alias.c' and is described by pass_may_alias.

Interprocedural points-to information is located in 'tree-ssa-structalias.c' and described by pass_ipa_pta.

- Profiling

  This pass rewrites the function in order to collect runtime block and value profiling data. Such data may be fed back into the compiler on a subsequent run so as to allow optimization based on expected execution frequencies. The pass is located in 'predict.c' and is described by pass_profile.

- Lower complex arithmetic

  This pass rewrites complex arithmetic operations into their component scalar arithmetic operations. The pass is located in 'tree-complex.c' and is described by pass_lower_complex.

- Scalar replacement of aggregates

  This pass rewrites suitable non-aliased local aggregate variables into a set of scalar variables. The resulting scalar variables are rewritten into SSA form, which allows subsequent optimization passes to do a significantly better job with them. The pass is located in 'tree-sra.c' and is described by pass_sra.

- Dead store elimination

  This pass eliminates stores to memory that are subsequently overwritten by another store, without any intervening loads. The pass is located in 'tree-ssa-dse.c' and is described by pass_dse.

- Tail recursion elimination

  This pass transforms tail recursion into a loop. It is located in 'tree-tailcall.c' and is described by pass_tail_recursion.

- Forward store motion

  This pass sinks stores and assignments down the flowgraph closer to their use point. The pass is located in 'tree-ssa-sink.c' and is described by pass_sink_code.

- Partial redundancy elimination

  This pass eliminates partially redundant computations, as well as performing load motion. The pass is located in 'tree-ssa-pre.c' and is described by pass_pre.

  Just before partial redundancy elimination, if '-funsafe-math-optimizations' is on, GCC tries to convert divisions to multiplications by the reciprocal. The pass is located in 'tree-ssa-math-opts.c' and is described by pass_cse_reciprocal.

- Full redundancy elimination

  This is a simpler form of PRE that only eliminates redundancies that occur on all paths. It is located in 'tree-ssa-pre.c' and described by pass_fre.

- Loop optimization

  The main driver of the pass is placed in 'tree-ssa-loop.c' and described by pass_loop.

  The optimizations performed by this pass are:

Loop invariant motion. This pass moves only invariants that would be hard to handle on RTL level (function calls, operations that expand to nontrivial sequences of insns). With '`-funswitch-loops`' it also moves operands of conditions that are invariant out of the loop, so that we can use just trivial invariantness analysis in loop unswitching. The pass also includes store motion. The pass is implemented in '`tree-ssa-loop-im.c`'.

Canonical induction variable creation. This pass creates a simple counter for number of iterations of the loop and replaces the exit condition of the loop using it, in case when a complicated analysis is necessary to determine the number of iterations. Later optimizations then may determine the number easily. The pass is implemented in '`tree-ssa-loop-ivcanon.c`'.

Induction variable optimizations. This pass performs standard induction variable optimizations, including strength reduction, induction variable merging and induction variable elimination. The pass is implemented in '`tree-ssa-loop-ivopts.c`'.

Loop unswitching. This pass moves the conditional jumps that are invariant out of the loops. To achieve this, a duplicate of the loop is created for each possible outcome of conditional jump(s). The pass is implemented in '`tree-ssa-loop-unswitch.c`'. This pass should eventually replace the RTL level loop unswitching in '`loop-unswitch.c`', but currently the RTL level pass is not completely redundant yet due to deficiencies in tree level alias analysis.

The optimizations also use various utility functions contained in '`tree-ssa-loop-manip.c`', '`cfgloop.c`', '`cfgloopanal.c`' and '`cfgloopmanip.c`'.

Vectorization. This pass transforms loops to operate on vector types instead of scalar types. Data parallelism across loop iterations is exploited to group data elements from consecutive iterations into a vector and operate on them in parallel. Depending on available target support the loop is conceptually unrolled by a factor `VF` (vectorization factor), which is the number of elements operated upon in parallel in each iteration, and the `VF` copies of each scalar operation are fused to form a vector operation. Additional loop transformations such as peeling and versioning may take place to align the number of iterations, and to align the memory accesses in the loop. The pass is implemented in '`tree-vectorizer.c`' (the main driver), '`tree-vect-loop.c`' and '`tree-vect-loop-manip.c`' (loop specific parts and general loop utilities), '`tree-vect-slp`' (loop-aware SLP functionality), '`tree-vect-stmts.c`' and '`tree-vect-data-refs.c`'. Analysis of data references is in '`tree-data-ref.c`'.

SLP Vectorization. This pass performs vectorization of straight-line code. The pass is implemented in '`tree-vectorizer.c`' (the main driver), '`tree-vect-slp.c`', '`tree-vect-stmts.c`' and '`tree-vect-data-refs.c`'.

Autoparallelization. This pass splits the loop iteration space to run into several threads. The pass is implemented in '`tree-parloops.c`'.

Graphite is a loop transformation framework based on the polyhedral model. Graphite stands for Gimple Represented as Polyhedra. The internals of this infrastructure are documented in http://gcc.gnu.org/wiki/Graphite. The passes working on this representation are implemented in the various '`graphite-*`' files.

- Tree level if-conversion for vectorizer

  This pass applies if-conversion to simple loops to help vectorizer. We identify if convertible loops, if-convert statements and merge basic blocks in one big block. The idea

is to present loop in such form so that vectorizer can have one to one mapping between statements and available vector operations. This pass is located in '`tree-if-conv.c`' and is described by `pass_if_conversion`.

- Conditional constant propagation

  This pass relaxes a lattice of values in order to identify those that must be constant even in the presence of conditional branches. The pass is located in '`tree-ssa-ccp.c`' and is described by `pass_ccp`.

  A related pass that works on memory loads and stores, and not just register values, is located in '`tree-ssa-ccp.c`' and described by `pass_store_ccp`.

- Conditional copy propagation

  This is similar to constant propagation but the lattice of values is the "copy-of" relation. It eliminates redundant copies from the code. The pass is located in '`tree-ssa-copy.c`' and described by `pass_copy_prop`.

  A related pass that works on memory copies, and not just register copies, is located in '`tree-ssa-copy.c`' and described by `pass_store_copy_prop`.

- Value range propagation

  This transformation is similar to constant propagation but instead of propagating single constant values, it propagates known value ranges. The implementation is based on Patterson's range propagation algorithm (Accurate Static Branch Prediction by Value Range Propagation, J. R. C. Patterson, PLDI '95). In contrast to Patterson's algorithm, this implementation does not propagate branch probabilities nor it uses more than a single range per SSA name. This means that the current implementation cannot be used for branch prediction (though adapting it would not be difficult). The pass is located in '`tree-vrp.c`' and is described by `pass_vrp`.

- Folding built-in functions

  This pass simplifies built-in functions, as applicable, with constant arguments or with inferable string lengths. It is located in '`tree-ssa-ccp.c`' and is described by `pass_fold_builtins`.

- Split critical edges

  This pass identifies critical edges and inserts empty basic blocks such that the edge is no longer critical. The pass is located in '`tree-cfg.c`' and is described by `pass_split_crit_edges`.

- Control dependence dead code elimination

  This pass is a stronger form of dead code elimination that can eliminate unnecessary control flow statements. It is located in '`tree-ssa-dce.c`' and is described by `pass_cd_dce`.

- Tail call elimination

  This pass identifies function calls that may be rewritten into jumps. No code transformation is actually applied here, but the data and control flow problem is solved. The code transformation requires target support, and so is delayed until RTL. In the meantime `CALL_EXPR_TAILCALL` is set indicating the possibility. The pass is located in '`tree-tailcall.c`' and is described by `pass_tail_calls`. The RTL transformation is handled by `fixup_tail_calls` in '`calls.c`'.

- Warn for function return without value

  For non-void functions, this pass locates return statements that do not specify a value and issues a warning. Such a statement may have been injected by falling off the end of the function. This pass is run last so that we have as much time as possible to prove that the statement is not reachable. It is located in '`tree-cfg.c`' and is described by `pass_warn_function_return`.
- Leave static single assignment form

  This pass rewrites the function such that it is in normal form. At the same time, we eliminate as many single-use temporaries as possible, so the intermediate language is no longer GIMPLE, but GENERIC. The pass is located in '`tree-outof-ssa.c`' and is described by `pass_del_ssa`.
- Merge PHI nodes that feed into one another

  This is part of the CFG cleanup passes. It attempts to join PHI nodes from a forwarder CFG block into another block with PHI nodes. The pass is located in '`tree-cfgcleanup.c`' and is described by `pass_merge_phi`.
- Return value optimization

  If a function always returns the same local variable, and that local variable is an aggregate type, then the variable is replaced with the return value for the function (i.e., the function's DECL_RESULT). This is equivalent to the C++ named return value optimization applied to GIMPLE. The pass is located in '`tree-nrv.c`' and is described by `pass_nrv`.
- Return slot optimization

  If a function returns a memory object and is called as `var = foo()`, this pass tries to change the call so that the address of `var` is sent to the caller to avoid an extra memory copy. This pass is located in `tree-nrv.c` and is described by `pass_return_slot`.
- Optimize calls to `__builtin_object_size`

  This is a propagation pass similar to CCP that tries to remove calls to `__builtin_object_size` when the size of the object can be computed at compile-time. This pass is located in '`tree-object-size.c`' and is described by `pass_object_sizes`.
- Loop invariant motion

  This pass removes expensive loop-invariant computations out of loops. The pass is located in '`tree-ssa-loop.c`' and described by `pass_lim`.
- Loop nest optimizations

  This is a family of loop transformations that works on loop nests. It includes loop interchange, scaling, skewing and reversal and they are all geared to the optimization of data locality in array traversals and the removal of dependencies that hamper optimizations such as loop parallelization and vectorization. The pass is located in '`tree-loop-linear.c`' and described by `pass_linear_transform`.
- Removal of empty loops

  This pass removes loops with no code in them. The pass is located in '`tree-ssa-loop-ivcanon.c`' and described by `pass_empty_loop`.
- Unrolling of small loops

  This pass completely unrolls loops with few iterations. The pass is located in '`tree-ssa-loop-ivcanon.c`' and described by `pass_complete_unroll`.

- Predictive commoning

  This pass makes the code reuse the computations from the previous iterations of the loops, especially loads and stores to memory. It does so by storing the values of these computations to a bank of temporary variables that are rotated at the end of loop. To avoid the need for this rotation, the loop is then unrolled and the copies of the loop body are rewritten to use the appropriate version of the temporary variable. This pass is located in '`tree-predcom.c`' and described by `pass_predcom`.
- Array prefetching

  This pass issues prefetch instructions for array references inside loops. The pass is located in '`tree-ssa-loop-prefetch.c`' and described by `pass_loop_prefetch`.
- Reassociation

  This pass rewrites arithmetic expressions to enable optimizations that operate on them, like redundancy elimination and vectorization. The pass is located in '`tree-ssa-reassoc.c`' and described by `pass_reassoc`.
- Optimization of `stdarg` functions

  This pass tries to avoid the saving of register arguments into the stack on entry to `stdarg` functions. If the function doesn't use any `va_start` macros, no registers need to be saved. If `va_start` macros are used, the `va_list` variables don't escape the function, it is only necessary to save registers that will be used in `va_arg` macros. For instance, if `va_arg` is only used with integral types in the function, floating point registers don't need to be saved. This pass is located in `tree-stdarg.c` and described by `pass_stdarg`.

9.6 RTL passes

The following briefly describes the RTL generation and optimization passes that are run after the Tree optimization passes.

- RTL generation

  The source files for RTL generation include '`stmt.c`', '`calls.c`', '`expr.c`', '`explow.c`', '`expmed.c`', '`function.c`', '`optabs.c`' and '`emit-rtl.c`'. Also, the file '`insn-emit.c`', generated from the machine description by the program `genemit`, is used in this pass. The header file '`expr.h`' is used for communication within this pass.

  The header files '`insn-flags.h`' and '`insn-codes.h`', generated from the machine description by the programs `genflags` and `gencodes`, tell this pass which standard names are available for use and which patterns correspond to them.
- Generation of exception landing pads

  This pass generates the glue that handles communication between the exception handling library routines and the exception handlers within the function. Entry points in the function that are invoked by the exception handling library are called *landing pads*. The code for this pass is located in '`except.c`'.
- Control flow graph cleanup

  This pass removes unreachable code, simplifies jumps to next, jumps to jump, jumps across jumps, etc. The pass is run multiple times. For historical reasons, it is occasionally referred to as the "jump optimization pass". The bulk of the code for this pass is in '`cfgcleanup.c`', and there are support routines in '`cfgrtl.c`' and '`jump.c`'.

- Forward propagation of single-def values

  This pass attempts to remove redundant computation by substituting variables that come from a single definition, and seeing if the result can be simplified. It performs copy propagation and addressing mode selection. The pass is run twice, with values being propagated into loops only on the second run. The code is located in '`fwprop.c`'.

- Common subexpression elimination

  This pass removes redundant computation within basic blocks, and optimizes addressing modes based on cost. The pass is run twice. The code for this pass is located in '`cse.c`'.

- Global common subexpression elimination

  This pass performs two different types of GCSE depending on whether you are optimizing for size or not (LCM based GCSE tends to increase code size for a gain in speed, while Morel-Renvoise based GCSE does not). When optimizing for size, GCSE is done using Morel-Renvoise Partial Redundancy Elimination, with the exception that it does not try to move invariants out of loops—that is left to the loop optimization pass. If MR PRE GCSE is done, code hoisting (aka unification) is also done, as well as load motion. If you are optimizing for speed, LCM (lazy code motion) based GCSE is done. LCM is based on the work of Knoop, Ruthing, and Steffen. LCM based GCSE also does loop invariant code motion. We also perform load and store motion when optimizing for speed. Regardless of which type of GCSE is used, the GCSE pass also performs global constant and copy propagation. The source file for this pass is '`gcse.c`', and the LCM routines are in '`lcm.c`'.

- Loop optimization

  This pass performs several loop related optimizations. The source files '`cfgloopanal.c`' and '`cfgloopmanip.c`' contain generic loop analysis and manipulation code. Initialization and finalization of loop structures is handled by '`loop-init.c`'. A loop invariant motion pass is implemented in '`loop-invariant.c`'. Basic block level optimizations—unrolling, peeling and unswitching loops— are implemented in '`loop-unswitch.c`' and '`loop-unroll.c`'. Replacing of the exit condition of loops by special machine-dependent instructions is handled by '`loop-doloop.c`'.

- Jump bypassing

  This pass is an aggressive form of GCSE that transforms the control flow graph of a function by propagating constants into conditional branch instructions. The source file for this pass is '`gcse.c`'.

- If conversion

  This pass attempts to replace conditional branches and surrounding assignments with arithmetic, boolean value producing comparison instructions, and conditional move instructions. In the very last invocation after reload/LRA, it will generate predicated instructions when supported by the target. The code is located in '`ifcvt.c`'.

- Web construction

  This pass splits independent uses of each pseudo-register. This can improve effect of the other transformation, such as CSE or register allocation. The code for this pass is located in '`web.c`'.

- Instruction combination

  This pass attempts to combine groups of two or three instructions that are related by data flow into single instructions. It combines the RTL expressions for the instructions by substitution, simplifies the result using algebra, and then attempts to match the result against the machine description. The code is located in '`combine.c`'.

- Mode switching optimization

  This pass looks for instructions that require the processor to be in a specific "mode" and minimizes the number of mode changes required to satisfy all users. What these modes are, and what they apply to are completely target-specific. The code for this pass is located in '`mode-switching.c`'.

- Modulo scheduling

  This pass looks at innermost loops and reorders their instructions by overlapping different iterations. Modulo scheduling is performed immediately before instruction scheduling. The code for this pass is located in '`modulo-sched.c`'.

- Instruction scheduling

  This pass looks for instructions whose output will not be available by the time that it is used in subsequent instructions. Memory loads and floating point instructions often have this behavior on RISC machines. It re-orders instructions within a basic block to try to separate the definition and use of items that otherwise would cause pipeline stalls. This pass is performed twice, before and after register allocation. The code for this pass is located in '`haifa-sched.c`', '`sched-deps.c`', '`sched-ebb.c`', '`sched-rgn.c`' and '`sched-vis.c`'.

- Register allocation

  These passes make sure that all occurrences of pseudo registers are eliminated, either by allocating them to a hard register, replacing them by an equivalent expression (e.g. a constant) or by placing them on the stack. This is done in several subpasses:

  - The integrated register allocator (IRA). It is called integrated because coalescing, register live range splitting, and hard register preferencing are done on-the-fly during coloring. It also has better integration with the reload/LRA pass. Pseudo-registers spilled by the allocator or the reload/LRA have still a chance to get hard-registers if the reload/LRA evicts some pseudo-registers from hard-registers. The allocator helps to choose better pseudos for spilling based on their live ranges and to coalesce stack slots allocated for the spilled pseudo-registers. IRA is a regional register allocator which is transformed into Chaitin-Briggs allocator if there is one region. By default, IRA chooses regions using register pressure but the user can force it to use one region or regions corresponding to all loops.

    Source files of the allocator are '`ira.c`', '`ira-build.c`', '`ira-costs.c`', '`ira-conflicts.c`', '`ira-color.c`', '`ira-emit.c`', '`ira-lives`', plus header files '`ira.h`' and '`ira-int.h`' used for the communication between the allocator and the rest of the compiler and between the IRA files.

  - Reloading. This pass renumbers pseudo registers with the hardware registers numbers they were allocated. Pseudo registers that did not get hard registers are replaced with stack slots. Then it finds instructions that are invalid because a value has failed to end up in a register, or has ended up in a register of the wrong kind.

It fixes up these instructions by reloading the problematical values temporarily into registers. Additional instructions are generated to do the copying.

The reload pass also optionally eliminates the frame pointer and inserts instructions to save and restore call-clobbered registers around calls.

Source files are '`reload.c`' and '`reload1.c`', plus the header '`reload.h`' used for communication between them.

- This pass is a modern replacement of the reload pass. Source files are '`lra.c`', '`lra-assign.c`', '`lra-coalesce.c`', '`lra-constraints.c`', '`lra-eliminations.c`', '`lra-equivs.c`', '`lra-lives.c`', '`lra-saves.c`', '`lra-spills.c`', the header '`lra-int.h`' used for communication between them, and the header '`lra.h`' used for communication between LRA and the rest of compiler.

  Unlike the reload pass, intermediate LRA decisions are reflected in RTL as much as possible. This reduces the number of target-dependent macros and hooks, leaving instruction constraints as the primary source of control.

  LRA is run on targets for which TARGET_LRA_P returns true.

- Basic block reordering

  This pass implements profile guided code positioning. If profile information is not available, various types of static analysis are performed to make the predictions normally coming from the profile feedback (IE execution frequency, branch probability, etc). It is implemented in the file '`bb-reorder.c`', and the various prediction routines are in '`predict.c`'.

- Variable tracking

  This pass computes where the variables are stored at each position in code and generates notes describing the variable locations to RTL code. The location lists are then generated according to these notes to debug information if the debugging information format supports location lists. The code is located in '`var-tracking.c`'.

- Delayed branch scheduling

  This optional pass attempts to find instructions that can go into the delay slots of other instructions, usually jumps and calls. The code for this pass is located in '`reorg.c`'.

- Branch shortening

  On many RISC machines, branch instructions have a limited range. Thus, longer sequences of instructions must be used for long branches. In this pass, the compiler figures out what how far each instruction will be from each other instruction, and therefore whether the usual instructions, or the longer sequences, must be used for each branch. The code for this pass is located in '`final.c`'.

- Register-to-stack conversion

  Conversion from usage of some hard registers to usage of a register stack may be done at this point. Currently, this is supported only for the floating-point registers of the Intel 80387 coprocessor. The code for this pass is located in '`reg-stack.c`'.

- Final

  This pass outputs the assembler code for the function. The source files are '`final.c`' plus '`insn-output.c`'; the latter is generated automatically from the machine descrip-

tion by the tool '`genoutput`'. The header file '`conditions.h`' is used for communication between these files.

- Debugging information output

  This is run after final because it must output the stack slot offsets for pseudo registers that did not get hard registers. Source files are '`dbxout.c`' for DBX symbol table format, '`sdbout.c`' for SDB symbol table format, '`dwarfout.c`' for DWARF symbol table format, files '`dwarf2out.c`' and '`dwarf2asm.c`' for DWARF2 symbol table format, and '`vmsdbgout.c`' for VMS debug symbol table format.

9.7 Optimization info

This section is describes dump infrastructure which is common to both pass dumps as well as optimization dumps. The goal for this infrastructure is to provide both gcc developers and users detailed information about various compiler transformations and optimizations.

9.7.1 Dump setup

A dump_manager class is defined in '`dumpfile.h`'. Various passes register dumping pass-specific information via `dump_register` in '`passes.c`'. During the registration, an optimization pass can select its optimization group (see Section 9.7.2 [Optimization groups], page 126). After that optimization information corresponding to the entire group (presumably from multiple passes) can be output via command-line switches. Note that if a pass does not fit into any of the pre-defined groups, it can select `OPTGROUP_NONE`.

Note that in general, a pass need not know its dump output file name, whether certain flags are enabled, etc. However, for legacy reasons, passes could also call `dump_begin` which returns a stream in case the particular pass has optimization dumps enabled. A pass could call `dump_end` when the dump has ended. These methods should go away once all the passes are converted to use the new dump infrastructure.

The recommended way to setup the dump output is via `dump_start` and `dump_end`.

9.7.2 Optimization groups

The optimization passes are grouped into several categories. Currently defined categories in '`dumpfile.h`' are

`OPTGROUP_IPA`
: IPA optimization passes. Enabled by '`-ipa`'

`OPTGROUP_LOOP`
: Loop optimization passes. Enabled by '`-loop`'.

`OPTGROUP_INLINE`
: Inlining passes. Enabled by '`-inline`'.

`OPTGROUP_VEC`
: Vectorization passes. Enabled by '`-vec`'.

`OPTGROUP_OTHER`
: All other optimization passes which do not fall into one of the above.

`OPTGROUP_ALL`
: All optimization passes. Enabled by '`-all`'.

By using groups a user could selectively enable optimization information only for a group of passes. By default, the optimization information for all the passes is dumped.

9.7.3 Dump files and streams

There are two separate output streams available for outputting optimization information from passes. Note that both these streams accept `stderr` and `stdout` as valid streams and thus it is possible to dump output to standard output or error. This is specially handy for outputting all available information in a single file by redirecting `stderr`.

`pstream` This stream is for pass-specific dump output. For example, '`-fdump-tree-vect=foo.v`' dumps tree vectorization pass output into the given file name '`foo.v`'. If the file name is not provided, the default file name is based on the source file and pass number. Note that one could also use special file names `stdout` and `stderr` for dumping to standard output and standard error respectively.

`alt_stream`
This steam is used for printing optimization specific output in response to the '`-fopt-info`'. Again a file name can be given. If the file name is not given, it defaults to `stderr`.

9.7.4 Dump output verbosity

The dump verbosity has the following options

'`optimized`'
Print information when an optimization is successfully applied. It is up to a pass to decide which information is relevant. For example, the vectorizer passes print the source location of loops which got successfully vectorized.

'`missed`' Print information about missed optimizations. Individual passes control which information to include in the output. For example,

```
gcc -O2 -ftree-vectorize -fopt-info-vec-missed
```

will print information about missed optimization opportunities from vectorization passes on stderr.

'`note`' Print verbose information about optimizations, such as certain transformations, more detailed messages about decisions etc.

'`all`' Print detailed optimization information. This includes *optimized*, *missed*, and *note*.

9.7.5 Dump types

`dump_printf`
This is a generic method for doing formatted output. It takes an additional argument `dump_kind` which signifies the type of dump. This method outputs information only when the dumps are enabled for this particular `dump_kind`. Note that the caller doesn't need to know if the particular dump is enabled or not, or even the file name. The caller only needs to decide which dump output information is relevant, and under what conditions. This determines the associated flags.

Consider the following example from '`loop-unroll.c`' where an informative message about a loop (along with its location) is printed when any of the following flags is enabled

- optimization messages
- RTL dumps
- detailed dumps

```
int report_flags = MSG_OPTIMIZED_LOCATIONS | TDF_RTL | TDF_DETAILS;
dump_printf_loc (report_flags, locus,
                 "loop turned into non-loop; it never loops.\n");
```

`dump_basic_block`
: Output basic block.

`dump_generic_expr`
: Output generic expression.

`dump_gimple_stmt`
: Output gimple statement.

Note that the above methods also have variants prefixed with `_loc`, such as `dump_printf_loc`, which are similar except they also output the source location information.

9.7.6 Dump examples

```
gcc -O3 -fopt-info-missed=missed.all
```

outputs missed optimization report from all the passes into '`missed.all`'.

As another example,

```
gcc -O3 -fopt-info-inline-optimized-missed=inline.txt
```

will output information about missed optimizations as well as optimized locations from all the inlining passes into '`inline.txt`'.

If the *filename* is provided, then the dumps from all the applicable optimizations are concatenated into the '`filename`'. Otherwise the dump is output onto '`stderr`'. If *options* is omitted, it defaults to '`all-all`', which means dump all available optimization info from all the passes. In the following example, all optimization info is output on to '`stderr`'.

```
gcc -O3 -fopt-info
```

Note that '`-fopt-info-vec-missed`' behaves the same as '`-fopt-info-missed-vec`'.

As another example, consider

```
gcc -fopt-info-vec-missed=vec.miss -fopt-info-loop-optimized=loop.opt
```

Here the two output file names '`vec.miss`' and '`loop.opt`' are in conflict since only one output file is allowed. In this case, only the first option takes effect and the subsequent options are ignored. Thus only the '`vec.miss`' is produced which containts dumps from the vectorizer about missed opportunities.

10 GENERIC

The purpose of GENERIC is simply to provide a language-independent way of representing an entire function in trees. To this end, it was necessary to add a few new tree codes to the back end, but almost everything was already there. If you can express it with the codes in `gcc/tree.def`, it's GENERIC.

Early on, there was a great deal of debate about how to think about statements in a tree IL. In GENERIC, a statement is defined as any expression whose value, if any, is ignored. A statement will always have `TREE_SIDE_EFFECTS` set (or it will be discarded), but a non-statement expression may also have side effects. A `CALL_EXPR`, for instance.

It would be possible for some local optimizations to work on the GENERIC form of a function; indeed, the adapted tree inliner works fine on GENERIC, but the current compiler performs inlining after lowering to GIMPLE (a restricted form described in the next section). Indeed, currently the frontends perform this lowering before handing off to `tree_rest_of_compilation`, but this seems inelegant.

10.1 Deficiencies

There are many places in which this document is incomplet and incorrekt. It is, as of yet, only *preliminary* documentation.

10.2 Overview

The central data structure used by the internal representation is the `tree`. These nodes, while all of the C type `tree`, are of many varieties. A `tree` is a pointer type, but the object to which it points may be of a variety of types. From this point forward, we will refer to trees in ordinary type, rather than in `this font`, except when talking about the actual C type `tree`.

You can tell what kind of node a particular tree is by using the `TREE_CODE` macro. Many, many macros take trees as input and return trees as output. However, most macros require a certain kind of tree node as input. In other words, there is a type-system for trees, but it is not reflected in the C type-system.

For safety, it is useful to configure GCC with '`--enable-checking`'. Although this results in a significant performance penalty (since all tree types are checked at run-time), and is therefore inappropriate in a release version, it is extremely helpful during the development process.

Many macros behave as predicates. Many, although not all, of these predicates end in '`_P`'. Do not rely on the result type of these macros being of any particular type. You may, however, rely on the fact that the type can be compared to `0`, so that statements like

```
if (TEST_P (t) && !TEST_P (y))
  x = 1;
```

and

```
int i = (TEST_P (t) != 0);
```

are legal. Macros that return `int` values now may be changed to return `tree` values, or other pointers in the future. Even those that continue to return `int` may return multiple nonzero codes where previously they returned only zero and one. Therefore, you should not write code like

```
if (TEST_P (t) == 1)
```

as this code is not guaranteed to work correctly in the future.

You should not take the address of values returned by the macros or functions described here. In particular, no guarantee is given that the values are lvalues.

In general, the names of macros are all in uppercase, while the names of functions are entirely in lowercase. There are rare exceptions to this rule. You should assume that any macro or function whose name is made up entirely of uppercase letters may evaluate its arguments more than once. You may assume that a macro or function whose name is made up entirely of lowercase letters will evaluate its arguments only once.

The `error_mark_node` is a special tree. Its tree code is `ERROR_MARK`, but since there is only ever one node with that code, the usual practice is to compare the tree against `error_mark_node`. (This test is just a test for pointer equality.) If an error has occurred during front-end processing the flag `errorcount` will be set. If the front end has encountered code it cannot handle, it will issue a message to the user and set `sorrycount`. When these flags are set, any macro or function which normally returns a tree of a particular kind may instead return the `error_mark_node`. Thus, if you intend to do any processing of erroneous code, you must be prepared to deal with the `error_mark_node`.

Occasionally, a particular tree slot (like an operand to an expression, or a particular field in a declaration) will be referred to as "reserved for the back end". These slots are used to store RTL when the tree is converted to RTL for use by the GCC back end. However, if that process is not taking place (e.g., if the front end is being hooked up to an intelligent editor), then those slots may be used by the back end presently in use.

If you encounter situations that do not match this documentation, such as tree nodes of types not mentioned here, or macros documented to return entities of a particular kind that instead return entities of some different kind, you have found a bug, either in the front end or in the documentation. Please report these bugs as you would any other bug.

10.2.1 Trees

All GENERIC trees have two fields in common. First, `TREE_CHAIN` is a pointer that can be used as a singly-linked list to other trees. The other is `TREE_TYPE`. Many trees store the type of an expression or declaration in this field.

These are some other functions for handling trees:

`tree_size`

Return the number of bytes a tree takes.

`build0`
`build1`
`build2`
`build3`
`build4`
`build5`
`build6`

These functions build a tree and supply values to put in each parameter. The basic signature is '`code, type, [operands]`'. `code` is the `TREE_CODE`, and `type` is a tree representing the `TREE_TYPE`. These are followed by the operands, each of which is also a tree.

10.2.2 Identifiers

An IDENTIFIER_NODE represents a slightly more general concept than the standard C or C++ concept of identifier. In particular, an IDENTIFIER_NODE may contain a '$', or other extraordinary characters.

There are never two distinct IDENTIFIER_NODEs representing the same identifier. Therefore, you may use pointer equality to compare IDENTIFIER_NODEs, rather than using a routine like strcmp. Use get_identifier to obtain the unique IDENTIFIER_NODE for a supplied string.

You can use the following macros to access identifiers:

IDENTIFIER_POINTER
: The string represented by the identifier, represented as a char*. This string is always NUL-terminated, and contains no embedded NUL characters.

IDENTIFIER_LENGTH
: The length of the string returned by IDENTIFIER_POINTER, not including the trailing NUL. This value of IDENTIFIER_LENGTH (x) is always the same as strlen (IDENTIFIER_POINTER (x)).

IDENTIFIER_OPNAME_P
: This predicate holds if the identifier represents the name of an overloaded operator. In this case, you should not depend on the contents of either the IDENTIFIER_POINTER or the IDENTIFIER_LENGTH.

IDENTIFIER_TYPENAME_P
: This predicate holds if the identifier represents the name of a user-defined conversion operator. In this case, the TREE_TYPE of the IDENTIFIER_NODE holds the type to which the conversion operator converts.

10.2.3 Containers

Two common container data structures can be represented directly with tree nodes. A TREE_LIST is a singly linked list containing two trees per node. These are the TREE_PURPOSE and TREE_VALUE of each node. (Often, the TREE_PURPOSE contains some kind of tag, or additional information, while the TREE_VALUE contains the majority of the payload. In other cases, the TREE_PURPOSE is simply NULL_TREE, while in still others both the TREE_PURPOSE and TREE_VALUE are of equal stature.) Given one TREE_LIST node, the next node is found by following the TREE_CHAIN. If the TREE_CHAIN is NULL_TREE, then you have reached the end of the list.

A TREE_VEC is a simple vector. The TREE_VEC_LENGTH is an integer (not a tree) giving the number of nodes in the vector. The nodes themselves are accessed using the TREE_VEC_ELT macro, which takes two arguments. The first is the TREE_VEC in question; the second is an integer indicating which element in the vector is desired. The elements are indexed from zero.

10.3 Types

All types have corresponding tree nodes. However, you should not assume that there is exactly one tree node corresponding to each type. There are often multiple nodes corresponding to the same type.

For the most part, different kinds of types have different tree codes. (For example, pointer types use a POINTER_TYPE code while arrays use an ARRAY_TYPE code.) However, pointers to member functions use the RECORD_TYPE code. Therefore, when writing a switch statement that depends on the code associated with a particular type, you should take care to handle pointers to member functions under the RECORD_TYPE case label.

The following functions and macros deal with cv-qualification of types:

TYPE_MAIN_VARIANT
: This macro returns the unqualified version of a type. It may be applied to an unqualified type, but it is not always the identity function in that case.

A few other macros and functions are usable with all types:

TYPE_SIZE
: The number of bits required to represent the type, represented as an INTEGER_CST. For an incomplete type, TYPE_SIZE will be NULL_TREE.

TYPE_ALIGN
: The alignment of the type, in bits, represented as an int.

TYPE_NAME
: This macro returns a declaration (in the form of a TYPE_DECL) for the type. (Note this macro does *not* return an IDENTIFIER_NODE, as you might expect, given its name!) You can look at the DECL_NAME of the TYPE_DECL to obtain the actual name of the type. The TYPE_NAME will be NULL_TREE for a type that is not a built-in type, the result of a typedef, or a named class type.

TYPE_CANONICAL
: This macro returns the "canonical" type for the given type node. Canonical types are used to improve performance in the C++ and Objective-C++ front ends by allowing efficient comparison between two type nodes in same_type_p: if the TYPE_CANONICAL values of the types are equal, the types are equivalent; otherwise, the types are not equivalent. The notion of equivalence for canonical types is the same as the notion of type equivalence in the language itself. For instance,

  When TYPE_CANONICAL is NULL_TREE, there is no canonical type for the given type node. In this case, comparison between this type and any other type requires the compiler to perform a deep, "structural" comparison to see if the two type nodes have the same form and properties.

  The canonical type for a node is always the most fundamental type in the equivalence class of types. For instance, int is its own canonical type. A typedef I of int will have int as its canonical type. Similarly, I* and a typedef IP (defined to I*) will has int* as their canonical type. When building a new type node, be sure to set TYPE_CANONICAL to the appropriate canonical type. If the new type is a compound type (built from other types), and any of those other types require structural equality, use SET_TYPE_STRUCTURAL_EQUALITY to ensure that the new type also requires structural equality. Finally, if for some reason you cannot guarantee that TYPE_CANONICAL will point to the canonical type, use SET_TYPE_STRUCTURAL_EQUALITY to make sure that the new type–and any type constructed based on it–requires structural equality. If you suspect

that the canonical type system is miscomparing types, pass `--param verify-canonical-types=1` to the compiler or configure with `--enable-checking` to force the compiler to verify its canonical-type comparisons against the structural comparisons; the compiler will then print any warnings if the canonical types miscompare.

`TYPE_STRUCTURAL_EQUALITY_P`
This predicate holds when the node requires structural equality checks, e.g., when `TYPE_CANONICAL` is `NULL_TREE`.

`SET_TYPE_STRUCTURAL_EQUALITY`
This macro states that the type node it is given requires structural equality checks, e.g., it sets `TYPE_CANONICAL` to `NULL_TREE`.

`same_type_p`
This predicate takes two types as input, and holds if they are the same type. For example, if one type is a `typedef` for the other, or both are `typedef`s for the same type. This predicate also holds if the two trees given as input are simply copies of one another; i.e., there is no difference between them at the source level, but, for whatever reason, a duplicate has been made in the representation. You should never use `==` (pointer equality) to compare types; always use `same_type_p` instead.

Detailed below are the various kinds of types, and the macros that can be used to access them. Although other kinds of types are used elsewhere in G++, the types described here are the only ones that you will encounter while examining the intermediate representation.

`VOID_TYPE`
Used to represent the `void` type.

`INTEGER_TYPE`
Used to represent the various integral types, including `char`, `short`, `int`, `long`, and `long long`. This code is not used for enumeration types, nor for the `bool` type. The `TYPE_PRECISION` is the number of bits used in the representation, represented as an `unsigned int`. (Note that in the general case this is not the same value as `TYPE_SIZE`; suppose that there were a 24-bit integer type, but that alignment requirements for the ABI required 32-bit alignment. Then, `TYPE_SIZE` would be an `INTEGER_CST` for 32, while `TYPE_PRECISION` would be 24.) The integer type is unsigned if `TYPE_UNSIGNED` holds; otherwise, it is signed.

The `TYPE_MIN_VALUE` is an `INTEGER_CST` for the smallest integer that may be represented by this type. Similarly, the `TYPE_MAX_VALUE` is an `INTEGER_CST` for the largest integer that may be represented by this type.

`REAL_TYPE`
Used to represent the `float`, `double`, and `long double` types. The number of bits in the floating-point representation is given by `TYPE_PRECISION`, as in the `INTEGER_TYPE` case.

`FIXED_POINT_TYPE`
Used to represent the `short _Fract`, `_Fract`, `long _Fract`, `long long _Fract`, `short _Accum`, `_Accum`, `long _Accum`, and `long long _Accum` types. The num-

ber of bits in the fixed-point representation is given by TYPE_PRECISION, as in the INTEGER_TYPE case. There may be padding bits, fractional bits and integral bits. The number of fractional bits is given by TYPE_FBIT, and the number of integral bits is given by TYPE_IBIT. The fixed-point type is unsigned if TYPE_UNSIGNED holds; otherwise, it is signed. The fixed-point type is saturating if TYPE_SATURATING holds; otherwise, it is not saturating.

COMPLEX_TYPE
: Used to represent GCC built-in __complex__ data types. The TREE_TYPE is the type of the real and imaginary parts.

ENUMERAL_TYPE
: Used to represent an enumeration type. The TYPE_PRECISION gives (as an int), the number of bits used to represent the type. If there are no negative enumeration constants, TYPE_UNSIGNED will hold. The minimum and maximum enumeration constants may be obtained with TYPE_MIN_VALUE and TYPE_MAX_VALUE, respectively; each of these macros returns an INTEGER_CST.

  The actual enumeration constants themselves may be obtained by looking at the TYPE_VALUES. This macro will return a TREE_LIST, containing the constants. The TREE_PURPOSE of each node will be an IDENTIFIER_NODE giving the name of the constant; the TREE_VALUE will be an INTEGER_CST giving the value assigned to that constant. These constants will appear in the order in which they were declared. The TREE_TYPE of each of these constants will be the type of enumeration type itself.

BOOLEAN_TYPE
: Used to represent the bool type.

POINTER_TYPE
: Used to represent pointer types, and pointer to data member types. The TREE_TYPE gives the type to which this type points.

REFERENCE_TYPE
: Used to represent reference types. The TREE_TYPE gives the type to which this type refers.

FUNCTION_TYPE
: Used to represent the type of non-member functions and of static member functions. The TREE_TYPE gives the return type of the function. The TYPE_ARG_TYPES are a TREE_LIST of the argument types. The TREE_VALUE of each node in this list is the type of the corresponding argument; the TREE_PURPOSE is an expression for the default argument value, if any. If the last node in the list is void_list_node (a TREE_LIST node whose TREE_VALUE is the void_type_node), then functions of this type do not take variable arguments. Otherwise, they do take a variable number of arguments.

  Note that in C (but not in C++) a function declared like void f() is an unprototyped function taking a variable number of arguments; the TYPE_ARG_TYPES of such a function will be NULL.

`METHOD_TYPE`
: Used to represent the type of a non-static member function. Like a `FUNCTION_TYPE`, the return type is given by the `TREE_TYPE`. The type of `*this`, i.e., the class of which functions of this type are a member, is given by the `TYPE_METHOD_BASETYPE`. The `TYPE_ARG_TYPES` is the parameter list, as for a `FUNCTION_TYPE`, and includes the `this` argument.

`ARRAY_TYPE`
: Used to represent array types. The `TREE_TYPE` gives the type of the elements in the array. If the array-bound is present in the type, the `TYPE_DOMAIN` is an `INTEGER_TYPE` whose `TYPE_MIN_VALUE` and `TYPE_MAX_VALUE` will be the lower and upper bounds of the array, respectively. The `TYPE_MIN_VALUE` will always be an `INTEGER_CST` for zero, while the `TYPE_MAX_VALUE` will be one less than the number of elements in the array, i.e., the highest value which may be used to index an element in the array.

`RECORD_TYPE`
: Used to represent `struct` and `class` types, as well as pointers to member functions and similar constructs in other languages. `TYPE_FIELDS` contains the items contained in this type, each of which can be a `FIELD_DECL`, `VAR_DECL`, `CONST_DECL`, or `TYPE_DECL`. You may not make any assumptions about the ordering of the fields in the type or whether one or more of them overlap.

`UNION_TYPE`
: Used to represent `union` types. Similar to `RECORD_TYPE` except that all `FIELD_DECL` nodes in `TYPE_FIELD` start at bit position zero.

`QUAL_UNION_TYPE`
: Used to represent part of a variant record in Ada. Similar to `UNION_TYPE` except that each `FIELD_DECL` has a `DECL_QUALIFIER` field, which contains a boolean expression that indicates whether the field is present in the object. The type will only have one field, so each field's `DECL_QUALIFIER` is only evaluated if none of the expressions in the previous fields in `TYPE_FIELDS` are nonzero. Normally these expressions will reference a field in the outer object using a `PLACEHOLDER_EXPR`.

`LANG_TYPE`
: This node is used to represent a language-specific type. The front end must handle it.

`OFFSET_TYPE`
: This node is used to represent a pointer-to-data member. For a data member `X::m` the `TYPE_OFFSET_BASETYPE` is `X` and the `TREE_TYPE` is the type of `m`.

There are variables whose values represent some of the basic types. These include:

`void_type_node`
: A node for `void`.

`integer_type_node`
: A node for `int`.

`unsigned_type_node`.
: A node for `unsigned int`.

`char_type_node`.
: A node for `char`.

It may sometimes be useful to compare one of these variables with a type in hand, using `same_type_p`.

10.4 Declarations

This section covers the various kinds of declarations that appear in the internal representation, except for declarations of functions (represented by `FUNCTION_DECL` nodes), which are described in Section 10.8 [Functions], page 158.

10.4.1 Working with declarations

Some macros can be used with any kind of declaration. These include:

`DECL_NAME`
: This macro returns an `IDENTIFIER_NODE` giving the name of the entity.

`TREE_TYPE`
: This macro returns the type of the entity declared.

`EXPR_FILENAME`
: This macro returns the name of the file in which the entity was declared, as a `char*`. For an entity declared implicitly by the compiler (like `__builtin_memcpy`), this will be the string `"<internal>"`.

`EXPR_LINENO`
: This macro returns the line number at which the entity was declared, as an `int`.

`DECL_ARTIFICIAL`
: This predicate holds if the declaration was implicitly generated by the compiler. For example, this predicate will hold of an implicitly declared member function, or of the `TYPE_DECL` implicitly generated for a class type. Recall that in C++ code like:

```
struct S {};
```

is roughly equivalent to C code like:

```
struct S {};
typedef struct S S;
```

The implicitly generated `typedef` declaration is represented by a `TYPE_DECL` for which `DECL_ARTIFICIAL` holds.

The various kinds of declarations include:

`LABEL_DECL`
: These nodes are used to represent labels in function bodies. For more information, see Section 10.8 [Functions], page 158. These nodes only appear in block scopes.

`CONST_DECL`

These nodes are used to represent enumeration constants. The value of the constant is given by `DECL_INITIAL` which will be an `INTEGER_CST` with the same type as the `TREE_TYPE` of the `CONST_DECL`, i.e., an `ENUMERAL_TYPE`.

`RESULT_DECL`

These nodes represent the value returned by a function. When a value is assigned to a `RESULT_DECL`, that indicates that the value should be returned, via bitwise copy, by the function. You can use `DECL_SIZE` and `DECL_ALIGN` on a `RESULT_DECL`, just as with a `VAR_DECL`.

`TYPE_DECL`

These nodes represent `typedef` declarations. The `TREE_TYPE` is the type declared to have the name given by `DECL_NAME`. In some cases, there is no associated name.

`VAR_DECL` These nodes represent variables with namespace or block scope, as well as static data members. The `DECL_SIZE` and `DECL_ALIGN` are analogous to `TYPE_SIZE` and `TYPE_ALIGN`. For a declaration, you should always use the `DECL_SIZE` and `DECL_ALIGN` rather than the `TYPE_SIZE` and `TYPE_ALIGN` given by the `TREE_TYPE`, since special attributes may have been applied to the variable to give it a particular size and alignment. You may use the predicates `DECL_THIS_STATIC` or `DECL_THIS_EXTERN` to test whether the storage class specifiers `static` or `extern` were used to declare a variable.

If this variable is initialized (but does not require a constructor), the `DECL_INITIAL` will be an expression for the initializer. The initializer should be evaluated, and a bitwise copy into the variable performed. If the `DECL_INITIAL` is the `error_mark_node`, there is an initializer, but it is given by an explicit statement later in the code; no bitwise copy is required.

GCC provides an extension that allows either automatic variables, or global variables, to be placed in particular registers. This extension is being used for a particular `VAR_DECL` if `DECL_REGISTER` holds for the `VAR_DECL`, and if `DECL_ASSEMBLER_NAME` is not equal to `DECL_NAME`. In that case, `DECL_ASSEMBLER_NAME` is the name of the register into which the variable will be placed.

`PARM_DECL`

Used to represent a parameter to a function. Treat these nodes similarly to `VAR_DECL` nodes. These nodes only appear in the `DECL_ARGUMENTS` for a `FUNCTION_DECL`.

The `DECL_ARG_TYPE` for a `PARM_DECL` is the type that will actually be used when a value is passed to this function. It may be a wider type than the `TREE_TYPE` of the parameter; for example, the ordinary type might be `short` while the `DECL_ARG_TYPE` is `int`.

`DEBUG_EXPR_DECL`

Used to represent an anonymous debug-information temporary created to hold an expression as it is optimized away, so that its value can be referenced in debug bind statements.

`FIELD_DECL`

These nodes represent non-static data members. The `DECL_SIZE` and `DECL_ALIGN` behave as for `VAR_DECL` nodes. The position of the field within the parent record is specified by a combination of three attributes. `DECL_FIELD_OFFSET` is the position, counting in bytes, of the `DECL_OFFSET_ALIGN`-bit sized word containing the bit of the field closest to the beginning of the structure. `DECL_FIELD_BIT_OFFSET` is the bit offset of the first bit of the field within this word; this may be nonzero even for fields that are not bit-fields, since `DECL_OFFSET_ALIGN` may be greater than the natural alignment of the field's type.

If `DECL_C_BIT_FIELD` holds, this field is a bit-field. In a bit-field, `DECL_BIT_FIELD_TYPE` also contains the type that was originally specified for it, while DECL_TYPE may be a modified type with lesser precision, according to the size of the bit field.

`NAMESPACE_DECL`

Namespaces provide a name hierarchy for other declarations. They appear in the `DECL_CONTEXT` of other `_DECL` nodes.

10.4.2 Internal structure

`DECL` nodes are represented internally as a hierarchy of structures.

10.4.2.1 Current structure hierarchy

`struct tree_decl_minimal`

This is the minimal structure to inherit from in order for common `DECL` macros to work. The fields it contains are a unique ID, source location, context, and name.

`struct tree_decl_common`

This structure inherits from `struct tree_decl_minimal`. It contains fields that most `DECL` nodes need, such as a field to store alignment, machine mode, size, and attributes.

`struct tree_field_decl`

This structure inherits from `struct tree_decl_common`. It is used to represent `FIELD_DECL`.

`struct tree_label_decl`

This structure inherits from `struct tree_decl_common`. It is used to represent `LABEL_DECL`.

`struct tree_translation_unit_decl`

This structure inherits from `struct tree_decl_common`. It is used to represent `TRANSLATION_UNIT_DECL`.

`struct tree_decl_with_rtl`

This structure inherits from `struct tree_decl_common`. It contains a field to store the low-level RTL associated with a `DECL` node.

`struct tree_result_decl`

This structure inherits from `struct tree_decl_with_rtl`. It is used to represent `RESULT_DECL`.

`struct tree_const_decl`
: This structure inherits from `struct tree_decl_with_rtl`. It is used to represent `CONST_DECL`.

`struct tree_parm_decl`
: This structure inherits from `struct tree_decl_with_rtl`. It is used to represent `PARM_DECL`.

`struct tree_decl_with_vis`
: This structure inherits from `struct tree_decl_with_rtl`. It contains fields necessary to store visibility information, as well as a section name and assembler name.

`struct tree_var_decl`
: This structure inherits from `struct tree_decl_with_vis`. It is used to represent `VAR_DECL`.

`struct tree_function_decl`
: This structure inherits from `struct tree_decl_with_vis`. It is used to represent `FUNCTION_DECL`.

10.4.2.2 Adding new DECL node types

Adding a new `DECL` tree consists of the following steps

Add a new tree code for the `DECL` node
: For language specific `DECL` nodes, there is a '`.def`' file in each frontend directory where the tree code should be added. For `DECL` nodes that are part of the middle-end, the code should be added to '`tree.def`'.

Create a new structure type for the `DECL` node
: These structures should inherit from one of the existing structures in the language hierarchy by using that structure as the first member.

```
struct tree_foo_decl
{
   struct tree_decl_with_vis common;
}
```

Would create a structure name `tree_foo_decl` that inherits from `struct tree_decl_with_vis`.

For language specific `DECL` nodes, this new structure type should go in the appropriate '`.h`' file. For `DECL` nodes that are part of the middle-end, the structure type should go in '`tree.h`'.

Add a member to the tree structure enumerator for the node
: For garbage collection and dynamic checking purposes, each `DECL` node structure type is required to have a unique enumerator value specified with it. For language specific `DECL` nodes, this new enumerator value should go in the appropriate '`.def`' file. For `DECL` nodes that are part of the middle-end, the enumerator values are specified in '`treestruct.def`'.

Update `union tree_node`

In order to make your new structure type usable, it must be added to `union tree_node`. For language specific `DECL` nodes, a new entry should be added to the appropriate '`.h`' file of the form

```
struct tree_foo_decl GTY ((tag ("TS_VAR_DECL"))) foo_decl;
```

For `DECL` nodes that are part of the middle-end, the additional member goes directly into `union tree_node` in '`tree.h`'.

Update dynamic checking info

In order to be able to check whether accessing a named portion of `union tree_node` is legal, and whether a certain `DECL` node contains one of the enumerated `DECL` node structures in the hierarchy, a simple lookup table is used. This lookup table needs to be kept up to date with the tree structure hierarchy, or else checking and containment macros will fail inappropriately.

For language specific `DECL` nodes, their is an `init_ts` function in an appropriate '`.c`' file, which initializes the lookup table. Code setting up the table for new `DECL` nodes should be added there. For each `DECL` tree code and enumerator value representing a member of the inheritance hierarchy, the table should contain 1 if that tree code inherits (directly or indirectly) from that member. Thus, a `FOO_DECL` node derived from `struct decl_with_rtl`, and enumerator value `TS_FOO_DECL`, would be set up as follows

```
tree_contains_struct[FOO_DECL][TS_FOO_DECL] = 1;
tree_contains_struct[FOO_DECL][TS_DECL_WRTL] = 1;
tree_contains_struct[FOO_DECL][TS_DECL_COMMON] = 1;
tree_contains_struct[FOO_DECL][TS_DECL_MINIMAL] = 1;
```

For `DECL` nodes that are part of the middle-end, the setup code goes into '`tree.c`'.

Add macros to access any new fields and flags

Each added field or flag should have a macro that is used to access it, that performs appropriate checking to ensure only the right type of `DECL` nodes access the field.

These macros generally take the following form

```
#define FOO_DECL_FIELDNAME(NODE) FOO_DECL_CHECK(NODE)->foo_decl.fieldname
```

However, if the structure is simply a base class for further structures, something like the following should be used

```
#define BASE_STRUCT_CHECK(T) CONTAINS_STRUCT_CHECK(T, TS_BASE_STRUCT)
#define BASE_STRUCT_FIELDNAME(NODE) \
   (BASE_STRUCT_CHECK(NODE)->base_struct.fieldname
```

Reading them from the generated '`all-tree.def`' file (which in turn includes all the '`tree.def`' files), '`gencheck.c`' is used during GCC's build to generate the `*_CHECK` macros for all tree codes.

10.5 Attributes in trees

Attributes, as specified using the `__attribute__` keyword, are represented internally as a `TREE_LIST`. The `TREE_PURPOSE` is the name of the attribute, as an `IDENTIFIER_NODE`. The `TREE_VALUE` is a `TREE_LIST` of the arguments of the attribute, if any, or `NULL_TREE` if there

are no arguments; the arguments are stored as the `TREE_VALUE` of successive entries in the list, and may be identifiers or expressions. The `TREE_CHAIN` of the attribute is the next attribute in a list of attributes applying to the same declaration or type, or `NULL_TREE` if there are no further attributes in the list.

Attributes may be attached to declarations and to types; these attributes may be accessed with the following macros. All attributes are stored in this way, and many also cause other changes to the declaration or type or to other internal compiler data structures.

`tree DECL_ATTRIBUTES` (*tree* `decl`) [Tree Macro]

This macro returns the attributes on the declaration *decl*.

`tree TYPE_ATTRIBUTES` (*tree* `type`) [Tree Macro]

This macro returns the attributes on the type *type*.

10.6 Expressions

The internal representation for expressions is for the most part quite straightforward. However, there are a few facts that one must bear in mind. In particular, the expression "tree" is actually a directed acyclic graph. (For example there may be many references to the integer constant zero throughout the source program; many of these will be represented by the same expression node.) You should not rely on certain kinds of node being shared, nor should you rely on certain kinds of nodes being unshared.

The following macros can be used with all expression nodes:

`TREE_TYPE`

Returns the type of the expression. This value may not be precisely the same type that would be given the expression in the original program.

In what follows, some nodes that one might expect to always have type `bool` are documented to have either integral or boolean type. At some point in the future, the C front end may also make use of this same intermediate representation, and at this point these nodes will certainly have integral type. The previous sentence is not meant to imply that the C++ front end does not or will not give these nodes integral type.

Below, we list the various kinds of expression nodes. Except where noted otherwise, the operands to an expression are accessed using the `TREE_OPERAND` macro. For example, to access the first operand to a binary plus expression `expr`, use:

```
TREE_OPERAND (expr, 0)
```

As this example indicates, the operands are zero-indexed.

10.6.1 Constant expressions

The table below begins with constants, moves on to unary expressions, then proceeds to binary expressions, and concludes with various other kinds of expressions:

`INTEGER_CST`

These nodes represent integer constants. Note that the type of these constants is obtained with `TREE_TYPE`; they are not always of type `int`. In particular, `char` constants are represented with `INTEGER_CST` nodes. The value of the integer constant `e` is given by

```
((TREE_INT_CST_HIGH (e) << HOST_BITS_PER_WIDE_INT)
+ TREE_INST_CST_LOW (e))
```

HOST_BITS_PER_WIDE_INT is at least thirty-two on all platforms. Both `TREE_INT_CST_HIGH` and `TREE_INT_CST_LOW` return a `HOST_WIDE_INT`. The value of an `INTEGER_CST` is interpreted as a signed or unsigned quantity depending on the type of the constant. In general, the expression given above will overflow, so it should not be used to calculate the value of the constant.

The variable `integer_zero_node` is an integer constant with value zero. Similarly, `integer_one_node` is an integer constant with value one. The `size_zero_node` and `size_one_node` variables are analogous, but have type `size_t` rather than `int`.

The function `tree_int_cst_lt` is a predicate which holds if its first argument is less than its second. Both constants are assumed to have the same signedness (i.e., either both should be signed or both should be unsigned.) The full width of the constant is used when doing the comparison; the usual rules about promotions and conversions are ignored. Similarly, `tree_int_cst_equal` holds if the two constants are equal. The `tree_int_cst_sgn` function returns the sign of a constant. The value is `1`, `0`, or `-1` according on whether the constant is greater than, equal to, or less than zero. Again, the signedness of the constant's type is taken into account; an unsigned constant is never less than zero, no matter what its bit-pattern.

`REAL_CST`

FIXME: Talk about how to obtain representations of this constant, do comparisons, and so forth.

`FIXED_CST`

These nodes represent fixed-point constants. The type of these constants is obtained with `TREE_TYPE`. `TREE_FIXED_CST_PTR` points to a `struct fixed_value`; `TREE_FIXED_CST` returns the structure itself. `struct fixed_value` contains `data` with the size of two `HOST_BITS_PER_WIDE_INT` and `mode` as the associated fixed-point machine mode for `data`.

`COMPLEX_CST`

These nodes are used to represent complex number constants, that is a `__complex__` whose parts are constant nodes. The `TREE_REALPART` and `TREE_IMAGPART` return the real and the imaginary parts respectively.

`VECTOR_CST`

These nodes are used to represent vector constants, whose parts are constant nodes. Each individual constant node is either an integer or a double constant node. The first operand is a `TREE_LIST` of the constant nodes and is accessed through `TREE_VECTOR_CST_ELTS`.

`STRING_CST`

These nodes represent string-constants. The `TREE_STRING_LENGTH` returns the length of the string, as an `int`. The `TREE_STRING_POINTER` is a `char*` containing the string itself. The string may not be `NUL`-terminated, and it may contain embedded `NUL` characters. Therefore, the `TREE_STRING_LENGTH` includes the trailing `NUL` if it is present.

For wide string constants, the TREE_STRING_LENGTH is the number of bytes in the string, and the TREE_STRING_POINTER points to an array of the bytes of the string, as represented on the target system (that is, as integers in the target endianness). Wide and non-wide string constants are distinguished only by the TREE_TYPE of the STRING_CST.

FIXME: The formats of string constants are not well-defined when the target system bytes are not the same width as host system bytes.

10.6.2 References to storage

ARRAY_REF

These nodes represent array accesses. The first operand is the array; the second is the index. To calculate the address of the memory accessed, you must scale the index by the size of the type of the array elements. The type of these expressions must be the type of a component of the array. The third and fourth operands are used after gimplification to represent the lower bound and component size but should not be used directly; call array_ref_low_bound and array_ref_element_size instead.

ARRAY_RANGE_REF

These nodes represent access to a range (or "slice") of an array. The operands are the same as that for ARRAY_REF and have the same meanings. The type of these expressions must be an array whose component type is the same as that of the first operand. The range of that array type determines the amount of data these expressions access.

TARGET_MEM_REF

These nodes represent memory accesses whose address directly map to an addressing mode of the target architecture. The first argument is TMR_SYMBOL and must be a VAR_DECL of an object with a fixed address. The second argument is TMR_BASE and the third one is TMR_INDEX. The fourth argument is TMR_STEP and must be an INTEGER_CST. The fifth argument is TMR_OFFSET and must be an INTEGER_CST. Any of the arguments may be NULL if the appropriate component does not appear in the address. Address of the TARGET_MEM_REF is determined in the following way.

```
&TMR_SYMBOL + TMR_BASE + TMR_INDEX * TMR_STEP + TMR_OFFSET
```

The sixth argument is the reference to the original memory access, which is preserved for the purposes of the RTL alias analysis. The seventh argument is a tag representing the results of tree level alias analysis.

ADDR_EXPR

These nodes are used to represent the address of an object. (These expressions will always have pointer or reference type.) The operand may be another expression, or it may be a declaration.

As an extension, GCC allows users to take the address of a label. In this case, the operand of the ADDR_EXPR will be a LABEL_DECL. The type of such an expression is void*.

If the object addressed is not an lvalue, a temporary is created, and the address of the temporary is used.

`INDIRECT_REF`
: These nodes are used to represent the object pointed to by a pointer. The operand is the pointer being dereferenced; it will always have pointer or reference type.

`MEM_REF`
: These nodes are used to represent the object pointed to by a pointer offset by a constant. The first operand is the pointer being dereferenced; it will always have pointer or reference type. The second operand is a pointer constant. Its type is specifying the type to be used for type-based alias analysis.

`COMPONENT_REF`
: These nodes represent non-static data member accesses. The first operand is the object (rather than a pointer to it); the second operand is the `FIELD_DECL` for the data member. The third operand represents the byte offset of the field, but should not be used directly; call `component_ref_field_offset` instead.

10.6.3 Unary and Binary Expressions

`NEGATE_EXPR`
: These nodes represent unary negation of the single operand, for both integer and floating-point types. The type of negation can be determined by looking at the type of the expression.

  The behavior of this operation on signed arithmetic overflow is controlled by the `flag_wrapv` and `flag_trapv` variables.

`ABS_EXPR`
: These nodes represent the absolute value of the single operand, for both integer and floating-point types. This is typically used to implement the `abs`, `labs` and `llabs` builtins for integer types, and the `fabs`, `fabsf` and `fabsl` builtins for floating point types. The type of abs operation can be determined by looking at the type of the expression.

  This node is not used for complex types. To represent the modulus or complex abs of a complex value, use the `BUILT_IN_CABS`, `BUILT_IN_CABSF` or `BUILT_IN_CABSL` builtins, as used to implement the C99 `cabs`, `cabsf` and `cabsl` built-in functions.

`BIT_NOT_EXPR`
: These nodes represent bitwise complement, and will always have integral type. The only operand is the value to be complemented.

`TRUTH_NOT_EXPR`
: These nodes represent logical negation, and will always have integral (or boolean) type. The operand is the value being negated. The type of the operand and that of the result are always of `BOOLEAN_TYPE` or `INTEGER_TYPE`.

`PREDECREMENT_EXPR`
`PREINCREMENT_EXPR`
`POSTDECREMENT_EXPR`
`POSTINCREMENT_EXPR`
: These nodes represent increment and decrement expressions. The value of the single operand is computed, and the operand incremented or decremented. In

the case of PREDECREMENT_EXPR and PREINCREMENT_EXPR, the value of the expression is the value resulting after the increment or decrement; in the case of POSTDECREMENT_EXPR and POSTINCREMENT_EXPR is the value before the increment or decrement occurs. The type of the operand, like that of the result, will be either integral, boolean, or floating-point.

FIX_TRUNC_EXPR
: These nodes represent conversion of a floating-point value to an integer. The single operand will have a floating-point type, while the complete expression will have an integral (or boolean) type. The operand is rounded towards zero.

FLOAT_EXPR
: These nodes represent conversion of an integral (or boolean) value to a floating-point value. The single operand will have integral type, while the complete expression will have a floating-point type.

  FIXME: How is the operand supposed to be rounded? Is this dependent on '-mieee'?

COMPLEX_EXPR
: These nodes are used to represent complex numbers constructed from two expressions of the same (integer or real) type. The first operand is the real part and the second operand is the imaginary part.

CONJ_EXPR
: These nodes represent the conjugate of their operand.

REALPART_EXPR
IMAGPART_EXPR
: These nodes represent respectively the real and the imaginary parts of complex numbers (their sole argument).

NON_LVALUE_EXPR
: These nodes indicate that their one and only operand is not an lvalue. A back end can treat these identically to the single operand.

NOP_EXPR
: These nodes are used to represent conversions that do not require any code-generation. For example, conversion of a char* to an int* does not require any code be generated; such a conversion is represented by a NOP_EXPR. The single operand is the expression to be converted. The conversion from a pointer to a reference is also represented with a NOP_EXPR.

CONVERT_EXPR
: These nodes are similar to NOP_EXPRs, but are used in those situations where code may need to be generated. For example, if an int* is converted to an int code may need to be generated on some platforms. These nodes are never used for C++-specific conversions, like conversions between pointers to different classes in an inheritance hierarchy. Any adjustments that need to be made in such cases are always indicated explicitly. Similarly, a user-defined conversion is never represented by a CONVERT_EXPR; instead, the function calls are made explicit.

`FIXED_CONVERT_EXPR`
: These nodes are used to represent conversions that involve fixed-point values. For example, from a fixed-point value to another fixed-point value, from an integer to a fixed-point value, from a fixed-point value to an integer, from a floating-point value to a fixed-point value, or from a fixed-point value to a floating-point value.

`LSHIFT_EXPR`
`RSHIFT_EXPR`
: These nodes represent left and right shifts, respectively. The first operand is the value to shift; it will always be of integral type. The second operand is an expression for the number of bits by which to shift. Right shift should be treated as arithmetic, i.e., the high-order bits should be zero-filled when the expression has unsigned type and filled with the sign bit when the expression has signed type. Note that the result is undefined if the second operand is larger than or equal to the first operand's type size. Unlike most nodes, these can have a vector as first operand and a scalar as second operand.

`BIT_IOR_EXPR`
`BIT_XOR_EXPR`
`BIT_AND_EXPR`
: These nodes represent bitwise inclusive or, bitwise exclusive or, and bitwise and, respectively. Both operands will always have integral type.

`TRUTH_ANDIF_EXPR`
`TRUTH_ORIF_EXPR`
: These nodes represent logical "and" and logical "or", respectively. These operators are not strict; i.e., the second operand is evaluated only if the value of the expression is not determined by evaluation of the first operand. The type of the operands and that of the result are always of `BOOLEAN_TYPE` or `INTEGER_TYPE`.

`TRUTH_AND_EXPR`
`TRUTH_OR_EXPR`
`TRUTH_XOR_EXPR`
: These nodes represent logical and, logical or, and logical exclusive or. They are strict; both arguments are always evaluated. There are no corresponding operators in C or C++, but the front end will sometimes generate these expressions anyhow, if it can tell that strictness does not matter. The type of the operands and that of the result are always of `BOOLEAN_TYPE` or `INTEGER_TYPE`.

`POINTER_PLUS_EXPR`
: This node represents pointer arithmetic. The first operand is always a pointer/reference type. The second operand is always an unsigned integer type compatible with sizetype. This is the only binary arithmetic operand that can operate on pointer types.

`PLUS_EXPR`
`MINUS_EXPR`
`MULT_EXPR`
: These nodes represent various binary arithmetic operations. Respectively, these operations are addition, subtraction (of the second operand from the first) and

multiplication. Their operands may have either integral or floating type, but there will never be case in which one operand is of floating type and the other is of integral type.

The behavior of these operations on signed arithmetic overflow is controlled by the `flag_wrapv` and `flag_trapv` variables.

`MULT_HIGHPART_EXPR`
This node represents the "high-part" of a widening multiplication. For an integral type with b bits of precision, the result is the most significant b bits of the full $2b$ product.

`RDIV_EXPR`
This node represents a floating point division operation.

`TRUNC_DIV_EXPR`
`FLOOR_DIV_EXPR`
`CEIL_DIV_EXPR`
`ROUND_DIV_EXPR`
These nodes represent integer division operations that return an integer result. `TRUNC_DIV_EXPR` rounds towards zero, `FLOOR_DIV_EXPR` rounds towards negative infinity, `CEIL_DIV_EXPR` rounds towards positive infinity and `ROUND_DIV_EXPR` rounds to the closest integer. Integer division in C and C++ is truncating, i.e. `TRUNC_DIV_EXPR`.

The behavior of these operations on signed arithmetic overflow, when dividing the minimum signed integer by minus one, is controlled by the `flag_wrapv` and `flag_trapv` variables.

`TRUNC_MOD_EXPR`
`FLOOR_MOD_EXPR`
`CEIL_MOD_EXPR`
`ROUND_MOD_EXPR`
These nodes represent the integer remainder or modulus operation. The integer modulus of two operands `a` and `b` is defined as `a - (a/b)*b` where the division calculated using the corresponding division operator. Hence for `TRUNC_MOD_EXPR` this definition assumes division using truncation towards zero, i.e. `TRUNC_DIV_EXPR`. Integer remainder in C and C++ uses truncating division, i.e. `TRUNC_MOD_EXPR`.

`EXACT_DIV_EXPR`
The `EXACT_DIV_EXPR` code is used to represent integer divisions where the numerator is known to be an exact multiple of the denominator. This allows the backend to choose between the faster of `TRUNC_DIV_EXPR`, `CEIL_DIV_EXPR` and `FLOOR_DIV_EXPR` for the current target.

`LT_EXPR`
`LE_EXPR`
`GT_EXPR`
`GE_EXPR`
`EQ_EXPR`
`NE_EXPR` These nodes represent the less than, less than or equal to, greater than, greater than or equal to, equal, and not equal comparison operators. The first and second operands will either be both of integral type, both of floating type or both of vector type. The result type of these expressions will always be of integral, boolean or signed integral vector type. These operations return the result type's zero value for false, the result type's one value for true, and a vector whose elements are zero (false) or minus one (true) for vectors.

For floating point comparisons, if we honor IEEE NaNs and either operand is NaN, then `NE_EXPR` always returns true and the remaining operators always return false. On some targets, comparisons against an IEEE NaN, other than equality and inequality, may generate a floating point exception.

`ORDERED_EXPR`
`UNORDERED_EXPR`
These nodes represent non-trapping ordered and unordered comparison operators. These operations take two floating point operands and determine whether they are ordered or unordered relative to each other. If either operand is an IEEE NaN, their comparison is defined to be unordered, otherwise the comparison is defined to be ordered. The result type of these expressions will always be of integral or boolean type. These operations return the result type's zero value for false, and the result type's one value for true.

`UNLT_EXPR`
`UNLE_EXPR`
`UNGT_EXPR`
`UNGE_EXPR`
`UNEQ_EXPR`
`LTGT_EXPR`
These nodes represent the unordered comparison operators. These operations take two floating point operands and determine whether the operands are unordered or are less than, less than or equal to, greater than, greater than or equal to, or equal respectively. For example, `UNLT_EXPR` returns true if either operand is an IEEE NaN or the first operand is less than the second. With the possible exception of `LTGT_EXPR`, all of these operations are guaranteed not to generate a floating point exception. The result type of these expressions will always be of integral or boolean type. These operations return the result type's zero value for false, and the result type's one value for true.

`MODIFY_EXPR`
These nodes represent assignment. The left-hand side is the first operand; the right-hand side is the second operand. The left-hand side will be a `VAR_DECL`, `INDIRECT_REF`, `COMPONENT_REF`, or other lvalue.

These nodes are used to represent not only assignment with '=' but also compound assignments (like '+='), by reduction to '=' assignment. In other words, the representation for 'i += 3' looks just like that for 'i = i + 3'.

INIT_EXPR

These nodes are just like MODIFY_EXPR, but are used only when a variable is initialized, rather than assigned to subsequently. This means that we can assume that the target of the initialization is not used in computing its own value; any reference to the lhs in computing the rhs is undefined.

COMPOUND_EXPR

These nodes represent comma-expressions. The first operand is an expression whose value is computed and thrown away prior to the evaluation of the second operand. The value of the entire expression is the value of the second operand.

COND_EXPR

These nodes represent ?: expressions. The first operand is of boolean or integral type. If it evaluates to a nonzero value, the second operand should be evaluated, and returned as the value of the expression. Otherwise, the third operand is evaluated, and returned as the value of the expression.

The second operand must have the same type as the entire expression, unless it unconditionally throws an exception or calls a noreturn function, in which case it should have void type. The same constraints apply to the third operand. This allows array bounds checks to be represented conveniently as (i >= 0 && i < 10) ? i : abort().

As a GNU extension, the C language front-ends allow the second operand of the ?: operator may be omitted in the source. For example, x ? : 3 is equivalent to x ? x : 3, assuming that x is an expression without side-effects. In the tree representation, however, the second operand is always present, possibly protected by SAVE_EXPR if the first argument does cause side-effects.

CALL_EXPR

These nodes are used to represent calls to functions, including non-static member functions. CALL_EXPRs are implemented as expression nodes with a variable number of operands. Rather than using TREE_OPERAND to extract them, it is preferable to use the specialized accessor macros and functions that operate specifically on CALL_EXPR nodes.

CALL_EXPR_FN returns a pointer to the function to call; it is always an expression whose type is a POINTER_TYPE.

The number of arguments to the call is returned by call_expr_nargs, while the arguments themselves can be accessed with the CALL_EXPR_ARG macro. The arguments are zero-indexed and numbered left-to-right. You can iterate over the arguments using FOR_EACH_CALL_EXPR_ARG, as in:

```
tree call, arg;
call_expr_arg_iterator iter;
FOR_EACH_CALL_EXPR_ARG (arg, iter, call)
  /* arg is bound to successive arguments of call.  */
  ...;
```

For non-static member functions, there will be an operand corresponding to the `this` pointer. There will always be expressions corresponding to all of the arguments, even if the function is declared with default arguments and some arguments are not explicitly provided at the call sites.

`CALL_EXPR`s also have a `CALL_EXPR_STATIC_CHAIN` operand that is used to implement nested functions. This operand is otherwise null.

`CLEANUP_POINT_EXPR`

These nodes represent full-expressions. The single operand is an expression to evaluate. Any destructor calls engendered by the creation of temporaries during the evaluation of that expression should be performed immediately after the expression is evaluated.

`CONSTRUCTOR`

These nodes represent the brace-enclosed initializers for a structure or an array. They contain a sequence of component values made out of a vector of constructor_elt, which is a (`INDEX`, `VALUE`) pair.

If the `TREE_TYPE` of the `CONSTRUCTOR` is a `RECORD_TYPE`, `UNION_TYPE` or `QUAL_UNION_TYPE` then the `INDEX` of each node in the sequence will be a `FIELD_DECL` and the `VALUE` will be the expression used to initialize that field.

If the `TREE_TYPE` of the `CONSTRUCTOR` is an `ARRAY_TYPE`, then the `INDEX` of each node in the sequence will be an `INTEGER_CST` or a `RANGE_EXPR` of two `INTEGER_CST`s. A single `INTEGER_CST` indicates which element of the array is being assigned to. A `RANGE_EXPR` indicates an inclusive range of elements to initialize. In both cases the `VALUE` is the corresponding initializer. It is re-evaluated for each element of a `RANGE_EXPR`. If the `INDEX` is `NULL_TREE`, then the initializer is for the next available array element.

In the front end, you should not depend on the fields appearing in any particular order. However, in the middle end, fields must appear in declaration order. You should not assume that all fields will be represented. Unrepresented fields will be cleared (zeroed), unless the CONSTRUCTOR_NO_CLEARING flag is set, in which case their value becomes undefined.

`COMPOUND_LITERAL_EXPR`

These nodes represent ISO C99 compound literals. The `COMPOUND_LITERAL_EXPR_DECL_EXPR` is a `DECL_EXPR` containing an anonymous `VAR_DECL` for the unnamed object represented by the compound literal; the `DECL_INITIAL` of that `VAR_DECL` is a `CONSTRUCTOR` representing the brace-enclosed list of initializers in the compound literal. That anonymous `VAR_DECL` can also be accessed directly by the `COMPOUND_LITERAL_EXPR_DECL` macro.

`SAVE_EXPR`

A `SAVE_EXPR` represents an expression (possibly involving side-effects) that is used more than once. The side-effects should occur only the first time the expression is evaluated. Subsequent uses should just reuse the computed value. The first operand to the `SAVE_EXPR` is the expression to evaluate. The side-effects should be executed where the `SAVE_EXPR` is first encountered in a depth-first preorder traversal of the expression tree.

TARGET_EXPR

A TARGET_EXPR represents a temporary object. The first operand is a VAR_DECL for the temporary variable. The second operand is the initializer for the temporary. The initializer is evaluated and, if non-void, copied (bitwise) into the temporary. If the initializer is void, that means that it will perform the initialization itself.

Often, a TARGET_EXPR occurs on the right-hand side of an assignment, or as the second operand to a comma-expression which is itself the right-hand side of an assignment, etc. In this case, we say that the TARGET_EXPR is "normal"; otherwise, we say it is "orphaned". For a normal TARGET_EXPR the temporary variable should be treated as an alias for the left-hand side of the assignment, rather than as a new temporary variable.

The third operand to the TARGET_EXPR, if present, is a cleanup-expression (i.e., destructor call) for the temporary. If this expression is orphaned, then this expression must be executed when the statement containing this expression is complete. These cleanups must always be executed in the order opposite to that in which they were encountered. Note that if a temporary is created on one branch of a conditional operator (i.e., in the second or third operand to a COND_EXPR), the cleanup must be run only if that branch is actually executed.

VA_ARG_EXPR

This node is used to implement support for the C/C++ variable argument-list mechanism. It represents expressions like va_arg (ap, type). Its TREE_TYPE yields the tree representation for type and its sole argument yields the representation for ap.

ANNOTATE_EXPR

This node is used to attach markers to an expression. The first operand is the annotated expression, the second is an INTEGER_CST with a value from enum annot_expr_kind.

10.6.4 Vectors

VEC_LSHIFT_EXPR
VEC_RSHIFT_EXPR

These nodes represent whole vector left and right shifts, respectively. The first operand is the vector to shift; it will always be of vector type. The second operand is an expression for the number of bits by which to shift. Note that the result is undefined if the second operand is larger than or equal to the first operand's type size.

VEC_WIDEN_MULT_HI_EXPR
VEC_WIDEN_MULT_LO_EXPR

These nodes represent widening vector multiplication of the high and low parts of the two input vectors, respectively. Their operands are vectors that contain the same number of elements (N) of the same integral type. The result is a vector that contains half as many elements, of an integral type whose size is twice as wide. In the case of VEC_WIDEN_MULT_HI_EXPR the high N/2 elements of the two vector are multiplied to produce the vector of N/2 products. In the

case of VEC_WIDEN_MULT_LO_EXPR the low N/2 elements of the two vector are multiplied to produce the vector of N/2 products.

VEC_UNPACK_HI_EXPR
VEC_UNPACK_LO_EXPR
These nodes represent unpacking of the high and low parts of the input vector, respectively. The single operand is a vector that contains N elements of the same integral or floating point type. The result is a vector that contains half as many elements, of an integral or floating point type whose size is twice as wide. In the case of VEC_UNPACK_HI_EXPR the high N/2 elements of the vector are extracted and widened (promoted). In the case of VEC_UNPACK_LO_EXPR the low N/2 elements of the vector are extracted and widened (promoted).

VEC_UNPACK_FLOAT_HI_EXPR
VEC_UNPACK_FLOAT_LO_EXPR
These nodes represent unpacking of the high and low parts of the input vector, where the values are converted from fixed point to floating point. The single operand is a vector that contains N elements of the same integral type. The result is a vector that contains half as many elements of a floating point type whose size is twice as wide. In the case of VEC_UNPACK_HI_EXPR the high N/2 elements of the vector are extracted, converted and widened. In the case of VEC_UNPACK_LO_EXPR the low N/2 elements of the vector are extracted, converted and widened.

VEC_PACK_TRUNC_EXPR
This node represents packing of truncated elements of the two input vectors into the output vector. Input operands are vectors that contain the same number of elements of the same integral or floating point type. The result is a vector that contains twice as many elements of an integral or floating point type whose size is half as wide. The elements of the two vectors are demoted and merged (concatenated) to form the output vector.

VEC_PACK_SAT_EXPR
This node represents packing of elements of the two input vectors into the output vector using saturation. Input operands are vectors that contain the same number of elements of the same integral type. The result is a vector that contains twice as many elements of an integral type whose size is half as wide. The elements of the two vectors are demoted and merged (concatenated) to form the output vector.

VEC_PACK_FIX_TRUNC_EXPR
This node represents packing of elements of the two input vectors into the output vector, where the values are converted from floating point to fixed point. Input operands are vectors that contain the same number of elements of a floating point type. The result is a vector that contains twice as many elements of an integral type whose size is half as wide. The elements of the two vectors are merged (concatenated) to form the output vector.

VEC_COND_EXPR
These nodes represent ?: expressions. The three operands must be vectors of the same size and number of elements. The second and third operands must

have the same type as the entire expression. The first operand is of signed integral vector type. If an element of the first operand evaluates to a zero value, the corresponding element of the result is taken from the third operand. If it evaluates to a minus one value, it is taken from the second operand. It should never evaluate to any other value currently, but optimizations should not rely on that property. In contrast with a COND_EXPR, all operands are always evaluated.

10.7 Statements

Most statements in GIMPLE are assignment statements, represented by GIMPLE_ASSIGN. No other C expressions can appear at statement level; a reference to a volatile object is converted into a GIMPLE_ASSIGN.

There are also several varieties of complex statements.

10.7.1 Basic Statements

ASM_EXPR

Used to represent an inline assembly statement. For an inline assembly statement like:

```
asm ("mov x, y");
```

The ASM_STRING macro will return a STRING_CST node for "mov x, y". If the original statement made use of the extended-assembly syntax, then ASM_OUTPUTS, ASM_INPUTS, and ASM_CLOBBERS will be the outputs, inputs, and clobbers for the statement, represented as STRING_CST nodes. The extended-assembly syntax looks like:

```
asm ("fsinx %1,%0" : "=f" (result) : "f" (angle));
```

The first string is the ASM_STRING, containing the instruction template. The next two strings are the output and inputs, respectively; this statement has no clobbers. As this example indicates, "plain" assembly statements are merely a special case of extended assembly statements; they have no cv-qualifiers, outputs, inputs, or clobbers. All of the strings will be NUL-terminated, and will contain no embedded NUL-characters.

If the assembly statement is declared volatile, or if the statement was not an extended assembly statement, and is therefore implicitly volatile, then the predicate ASM_VOLATILE_P will hold of the ASM_EXPR.

DECL_EXPR

Used to represent a local declaration. The DECL_EXPR_DECL macro can be used to obtain the entity declared. This declaration may be a LABEL_DECL, indicating that the label declared is a local label. (As an extension, GCC allows the declaration of labels with scope.) In C, this declaration may be a FUNCTION_DECL, indicating the use of the GCC nested function extension. For more information, see Section 10.8 [Functions], page 158.

LABEL_EXPR

Used to represent a label. The LABEL_DECL declared by this statement can be obtained with the LABEL_EXPR_LABEL macro. The IDENTIFIER_NODE giving the name of the label can be obtained from the LABEL_DECL with DECL_NAME.

GOTO_EXPR
: Used to represent a `goto` statement. The GOTO_DESTINATION will usually be a LABEL_DECL. However, if the "computed goto" extension has been used, the GOTO_DESTINATION will be an arbitrary expression indicating the destination. This expression will always have pointer type.

RETURN_EXPR
: Used to represent a `return` statement. Operand 0 represents the value to return. It should either be the RESULT_DECL for the containing function, or a MODIFY_EXPR or INIT_EXPR setting the function's RESULT_DECL. It will be NULL_TREE if the statement was just

```
return;
```

LOOP_EXPR
: These nodes represent "infinite" loops. The LOOP_EXPR_BODY represents the body of the loop. It should be executed forever, unless an EXIT_EXPR is encountered.

EXIT_EXPR
: These nodes represent conditional exits from the nearest enclosing LOOP_EXPR. The single operand is the condition; if it is nonzero, then the loop should be exited. An EXIT_EXPR will only appear within a LOOP_EXPR.

SWITCH_STMT
: Used to represent a `switch` statement. The SWITCH_STMT_COND is the expression on which the switch is occurring. See the documentation for an IF_STMT for more information on the representation used for the condition. The SWITCH_STMT_BODY is the body of the switch statement. The SWITCH_STMT_TYPE is the original type of switch expression as given in the source, before any compiler conversions.

CASE_LABEL_EXPR
: Use to represent a `case` label, range of `case` labels, or a `default` label. If CASE_LOW is NULL_TREE, then this is a `default` label. Otherwise, if CASE_HIGH is NULL_TREE, then this is an ordinary `case` label. In this case, CASE_LOW is an expression giving the value of the label. Both CASE_LOW and CASE_HIGH are INTEGER_CST nodes. These values will have the same type as the condition expression in the switch statement.

  Otherwise, if both CASE_LOW and CASE_HIGH are defined, the statement is a range of case labels. Such statements originate with the extension that allows users to write things of the form:

```
case 2 ... 5:
```

  The first value will be CASE_LOW, while the second will be CASE_HIGH.

10.7.2 Blocks

Block scopes and the variables they declare in GENERIC are expressed using the BIND_EXPR code, which in previous versions of GCC was primarily used for the C statement-expression extension.

Variables in a block are collected into BIND_EXPR_VARS in declaration order through their TREE_CHAIN field. Any runtime initialization is moved out of DECL_INITIAL and into a statement in the controlled block. When gimplifying from C or C++, this initialization replaces the DECL_STMT. These variables will never require cleanups. The scope of these variables is just the body

Variable-length arrays (VLAs) complicate this process, as their size often refers to variables initialized earlier in the block. To handle this, we currently split the block at that point, and move the VLA into a new, inner BIND_EXPR. This strategy may change in the future.

A C++ program will usually contain more BIND_EXPRs than there are syntactic blocks in the source code, since several C++ constructs have implicit scopes associated with them. On the other hand, although the C++ front end uses pseudo-scopes to handle cleanups for objects with destructors, these don't translate into the GIMPLE form; multiple declarations at the same level use the same BIND_EXPR.

10.7.3 Statement Sequences

Multiple statements at the same nesting level are collected into a STATEMENT_LIST. Statement lists are modified and traversed using the interface in 'tree-iterator.h'.

10.7.4 Empty Statements

Whenever possible, statements with no effect are discarded. But if they are nested within another construct which cannot be discarded for some reason, they are instead replaced with an empty statement, generated by build_empty_stmt. Initially, all empty statements were shared, after the pattern of the Java front end, but this caused a lot of trouble in practice.

An empty statement is represented as (void)0.

10.7.5 Jumps

Other jumps are expressed by either GOTO_EXPR or RETURN_EXPR.

The operand of a GOTO_EXPR must be either a label or a variable containing the address to jump to.

The operand of a RETURN_EXPR is either NULL_TREE, RESULT_DECL, or a MODIFY_EXPR which sets the return value. It would be nice to move the MODIFY_EXPR into a separate statement, but the special return semantics in expand_return make that difficult. It may still happen in the future, perhaps by moving most of that logic into expand_assignment.

10.7.6 Cleanups

Destructors for local C++ objects and similar dynamic cleanups are represented in GIMPLE by a TRY_FINALLY_EXPR. TRY_FINALLY_EXPR has two operands, both of which are a sequence of statements to execute. The first sequence is executed. When it completes the second sequence is executed.

The first sequence may complete in the following ways:

1. Execute the last statement in the sequence and fall off the end.
2. Execute a goto statement (GOTO_EXPR) to an ordinary label outside the sequence.

3. Execute a return statement (RETURN_EXPR).
4. Throw an exception. This is currently not explicitly represented in GIMPLE.

The second sequence is not executed if the first sequence completes by calling setjmp or exit or any other function that does not return. The second sequence is also not executed if the first sequence completes via a non-local goto or a computed goto (in general the compiler does not know whether such a goto statement exits the first sequence or not, so we assume that it doesn't).

After the second sequence is executed, if it completes normally by falling off the end, execution continues wherever the first sequence would have continued, by falling off the end, or doing a goto, etc.

TRY_FINALLY_EXPR complicates the flow graph, since the cleanup needs to appear on every edge out of the controlled block; this reduces the freedom to move code across these edges. Therefore, the EH lowering pass which runs before most of the optimization passes eliminates these expressions by explicitly adding the cleanup to each edge. Rethrowing the exception is represented using RESX_EXPR.

10.7.7 OpenMP

All the statements starting with OMP_ represent directives and clauses used by the OpenMP API http://www.openmp.org/.

OMP_PARALLEL

Represents #pragma omp parallel [clause1 ... clauseN]. It has four operands:

Operand OMP_PARALLEL_BODY is valid while in GENERIC and High GIMPLE forms. It contains the body of code to be executed by all the threads. During GIMPLE lowering, this operand becomes NULL and the body is emitted linearly after OMP_PARALLEL.

Operand OMP_PARALLEL_CLAUSES is the list of clauses associated with the directive.

Operand OMP_PARALLEL_FN is created by pass_lower_omp, it contains the FUNCTION_DECL for the function that will contain the body of the parallel region.

Operand OMP_PARALLEL_DATA_ARG is also created by pass_lower_omp. If there are shared variables to be communicated to the children threads, this operand will contain the VAR_DECL that contains all the shared values and variables.

OMP_FOR

Represents #pragma omp for [clause1 ... clauseN]. It has 5 operands:

Operand OMP_FOR_BODY contains the loop body.

Operand OMP_FOR_CLAUSES is the list of clauses associated with the directive.

Operand OMP_FOR_INIT is the loop initialization code of the form VAR = N1.

Operand OMP_FOR_COND is the loop conditional expression of the form VAR {<,>,<=,>=} N2.

Operand OMP_FOR_INCR is the loop index increment of the form VAR {+=,-=} INCR.

Operand OMP_FOR_PRE_BODY contains side-effect code from operands OMP_FOR_INIT, OMP_FOR_COND and OMP_FOR_INC. These side-effects are part of the OMP_FOR block but must be evaluated before the start of loop body.

The loop index variable VAR must be a signed integer variable, which is implicitly private to each thread. Bounds N1 and N2 and the increment expression INCR are required to be loop invariant integer expressions that are evaluated without any synchronization. The evaluation order, frequency of evaluation and side-effects are unspecified by the standard.

OMP_SECTIONS

Represents #pragma omp sections [clause1 ... clauseN].

Operand OMP_SECTIONS_BODY contains the sections body, which in turn contains a set of OMP_SECTION nodes for each of the concurrent sections delimited by #pragma omp section.

Operand OMP_SECTIONS_CLAUSES is the list of clauses associated with the directive.

OMP_SECTION

Section delimiter for OMP_SECTIONS.

OMP_SINGLE

Represents #pragma omp single.

Operand OMP_SINGLE_BODY contains the body of code to be executed by a single thread.

Operand OMP_SINGLE_CLAUSES is the list of clauses associated with the directive.

OMP_MASTER

Represents #pragma omp master.

Operand OMP_MASTER_BODY contains the body of code to be executed by the master thread.

OMP_ORDERED

Represents #pragma omp ordered.

Operand OMP_ORDERED_BODY contains the body of code to be executed in the sequential order dictated by the loop index variable.

OMP_CRITICAL

Represents #pragma omp critical [name].

Operand OMP_CRITICAL_BODY is the critical section.

Operand OMP_CRITICAL_NAME is an optional identifier to label the critical section.

OMP_RETURN

This does not represent any OpenMP directive, it is an artificial marker to indicate the end of the body of an OpenMP. It is used by the flow graph (tree-cfg.c) and OpenMP region building code (omp-low.c).

OMP_CONTINUE

Similarly, this instruction does not represent an OpenMP directive, it is used by OMP_FOR and OMP_SECTIONS to mark the place where the code needs to loop to the next iteration (in the case of OMP_FOR) or the next section (in the case of OMP_SECTIONS).

In some cases, OMP_CONTINUE is placed right before OMP_RETURN. But if there are cleanups that need to occur right after the looping body, it will be emitted between OMP_CONTINUE and OMP_RETURN.

OMP_ATOMIC

Represents #pragma omp atomic.

Operand 0 is the address at which the atomic operation is to be performed.

Operand 1 is the expression to evaluate. The gimplifier tries three alternative code generation strategies. Whenever possible, an atomic update built-in is used. If that fails, a compare-and-swap loop is attempted. If that also fails, a regular critical section around the expression is used.

OMP_CLAUSE

Represents clauses associated with one of the OMP_ directives. Clauses are represented by separate subcodes defined in 'tree.h'. Clauses codes can be one of: OMP_CLAUSE_PRIVATE, OMP_CLAUSE_SHARED, OMP_CLAUSE_FIRSTPRIVATE, OMP_CLAUSE_LASTPRIVATE, OMP_CLAUSE_COPYIN, OMP_CLAUSE_COPYPRIVATE, OMP_CLAUSE_IF, OMP_CLAUSE_NUM_THREADS, OMP_CLAUSE_SCHEDULE, OMP_CLAUSE_NOWAIT, OMP_CLAUSE_ORDERED, OMP_CLAUSE_DEFAULT, OMP_CLAUSE_REDUCTION, OMP_CLAUSE_COLLAPSE, OMP_CLAUSE_UNTIED, OMP_CLAUSE_FINAL, and OMP_CLAUSE_MERGEABLE. Each code represents the corresponding OpenMP clause.

Clauses associated with the same directive are chained together via OMP_CLAUSE_CHAIN. Those clauses that accept a list of variables are restricted to exactly one, accessed with OMP_CLAUSE_VAR. Therefore, multiple variables under the same clause C need to be represented as multiple C clauses chained together. This facilitates adding new clauses during compilation.

10.8 Functions

A function is represented by a FUNCTION_DECL node. It stores the basic pieces of the function such as body, parameters, and return type as well as information on the surrounding context, visibility, and linkage.

10.8.1 Function Basics

A function has four core parts: the name, the parameters, the result, and the body. The following macros and functions access these parts of a FUNCTION_DECL as well as other basic features:

DECL_NAME

This macro returns the unqualified name of the function, as an IDENTIFIER_NODE. For an instantiation of a function template, the DECL_NAME is the unqualified name of the template, not something like f<int>. The value of DECL_NAME

is undefined when used on a constructor, destructor, overloaded operator, or type-conversion operator, or any function that is implicitly generated by the compiler. See below for macros that can be used to distinguish these cases.

`DECL_ASSEMBLER_NAME`

This macro returns the mangled name of the function, also an `IDENTIFIER_NODE`. This name does not contain leading underscores on systems that prefix all identifiers with underscores. The mangled name is computed in the same way on all platforms; if special processing is required to deal with the object file format used on a particular platform, it is the responsibility of the back end to perform those modifications. (Of course, the back end should not modify `DECL_ASSEMBLER_NAME` itself.)

Using `DECL_ASSEMBLER_NAME` will cause additional memory to be allocated (for the mangled name of the entity) so it should be used only when emitting assembly code. It should not be used within the optimizers to determine whether or not two declarations are the same, even though some of the existing optimizers do use it in that way. These uses will be removed over time.

`DECL_ARGUMENTS`

This macro returns the `PARM_DECL` for the first argument to the function. Subsequent `PARM_DECL` nodes can be obtained by following the `TREE_CHAIN` links.

`DECL_RESULT`

This macro returns the `RESULT_DECL` for the function.

`DECL_SAVED_TREE`

This macro returns the complete body of the function.

`TREE_TYPE`

This macro returns the `FUNCTION_TYPE` or `METHOD_TYPE` for the function.

`DECL_INITIAL`

A function that has a definition in the current translation unit will have a non-`NULL` `DECL_INITIAL`. However, back ends should not make use of the particular value given by `DECL_INITIAL`.

It should contain a tree of `BLOCK` nodes that mirrors the scopes that variables are bound in the function. Each block contains a list of decls declared in a basic block, a pointer to a chain of blocks at the next lower scope level, then a pointer to the next block at the same level and a backpointer to the parent `BLOCK` or `FUNCTION_DECL`. So given a function as follows:

```
void foo()
{
  int a;
  {
    int b;
  }
  int c;
}
```

you would get the following:

```
tree foo = FUNCTION_DECL;
tree decl_a = VAR_DECL;
```

```
tree decl_b = VAR_DECL;
tree decl_c = VAR_DECL;
tree block_a = BLOCK;
tree block_b = BLOCK;
tree block_c = BLOCK;
BLOCK_VARS(block_a) = decl_a;
BLOCK_SUBBLOCKS(block_a) = block_b;
BLOCK_CHAIN(block_a) = block_c;
BLOCK_SUPERCONTEXT(block_a) = foo;
BLOCK_VARS(block_b) = decl_b;
BLOCK_SUPERCONTEXT(block_b) = block_a;
BLOCK_VARS(block_c) = decl_c;
BLOCK_SUPERCONTEXT(block_c) = foo;
DECL_INITIAL(foo) = block_a;
```

10.8.2 Function Properties

To determine the scope of a function, you can use the `DECL_CONTEXT` macro. This macro will return the class (either a `RECORD_TYPE` or a `UNION_TYPE`) or namespace (a `NAMESPACE_DECL`) of which the function is a member. For a virtual function, this macro returns the class in which the function was actually defined, not the base class in which the virtual declaration occurred.

In C, the `DECL_CONTEXT` for a function maybe another function. This representation indicates that the GNU nested function extension is in use. For details on the semantics of nested functions, see the GCC Manual. The nested function can refer to local variables in its containing function. Such references are not explicitly marked in the tree structure; back ends must look at the `DECL_CONTEXT` for the referenced `VAR_DECL`. If the `DECL_CONTEXT` for the referenced `VAR_DECL` is not the same as the function currently being processed, and neither `DECL_EXTERNAL` nor `TREE_STATIC` hold, then the reference is to a local variable in a containing function, and the back end must take appropriate action.

`DECL_EXTERNAL`
: This predicate holds if the function is undefined.

`TREE_PUBLIC`
: This predicate holds if the function has external linkage.

`TREE_STATIC`
: This predicate holds if the function has been defined.

`TREE_THIS_VOLATILE`
: This predicate holds if the function does not return normally.

`TREE_READONLY`
: This predicate holds if the function can only read its arguments.

`DECL_PURE_P`
: This predicate holds if the function can only read its arguments, but may also read global memory.

`DECL_VIRTUAL_P`
: This predicate holds if the function is virtual.

`DECL_ARTIFICIAL`
: This macro holds if the function was implicitly generated by the compiler, rather than explicitly declared. In addition to implicitly generated class member

functions, this macro holds for the special functions created to implement static initialization and destruction, to compute run-time type information, and so forth.

`DECL_FUNCTION_SPECIFIC_TARGET`
This macro returns a tree node that holds the target options that are to be used to compile this particular function or `NULL_TREE` if the function is to be compiled with the target options specified on the command line.

`DECL_FUNCTION_SPECIFIC_OPTIMIZATION`
This macro returns a tree node that holds the optimization options that are to be used to compile this particular function or `NULL_TREE` if the function is to be compiled with the optimization options specified on the command line.

10.9 Language-dependent trees

Front ends may wish to keep some state associated with various GENERIC trees while parsing. To support this, trees provide a set of flags that may be used by the front end. They are accessed using `TREE_LANG_FLAG_n` where '`n`' is currently 0 through 6.

If necessary, a front end can use some language-dependent tree codes in its GENERIC representation, so long as it provides a hook for converting them to GIMPLE and doesn't expect them to work with any (hypothetical) optimizers that run before the conversion to GIMPLE. The intermediate representation used while parsing C and C++ looks very little like GENERIC, but the C and C++ gimplifier hooks are perfectly happy to take it as input and spit out GIMPLE.

10.10 C and C++ Trees

This section documents the internal representation used by GCC to represent C and C++ source programs. When presented with a C or C++ source program, GCC parses the program, performs semantic analysis (including the generation of error messages), and then produces the internal representation described here. This representation contains a complete representation for the entire translation unit provided as input to the front end. This representation is then typically processed by a code-generator in order to produce machine code, but could also be used in the creation of source browsers, intelligent editors, automatic documentation generators, interpreters, and any other programs needing the ability to process C or C++ code.

This section explains the internal representation. In particular, it documents the internal representation for C and C++ source constructs, and the macros, functions, and variables that can be used to access these constructs. The C++ representation is largely a superset of the representation used in the C front end. There is only one construct used in C that does not appear in the C++ front end and that is the GNU "nested function" extension. Many of the macros documented here do not apply in C because the corresponding language constructs do not appear in C.

The C and C++ front ends generate a mix of GENERIC trees and ones specific to C and C++. These language-specific trees are higher-level constructs than the ones in GENERIC to make the parser's job easier. This section describes those trees that aren't part of GENERIC as well as aspects of GENERIC trees that are treated in a language-specific manner.

If you are developing a "back end", be it is a code-generator or some other tool, that uses this representation, you may occasionally find that you need to ask questions not easily answered by the functions and macros available here. If that situation occurs, it is quite likely that GCC already supports the functionality you desire, but that the interface is simply not documented here. In that case, you should ask the GCC maintainers (via mail to gcc@gcc.gnu.org) about documenting the functionality you require. Similarly, if you find yourself writing functions that do not deal directly with your back end, but instead might be useful to other people using the GCC front end, you should submit your patches for inclusion in GCC.

10.10.1 Types for C++

In C++, an array type is not qualified; rather the type of the array elements is qualified. This situation is reflected in the intermediate representation. The macros described here will always examine the qualification of the underlying element type when applied to an array type. (If the element type is itself an array, then the recursion continues until a non-array type is found, and the qualification of this type is examined.) So, for example, `CP_TYPE_CONST_P` will hold of the type `const int ()[7]`, denoting an array of seven `int`s.

The following functions and macros deal with cv-qualification of types:

`cp_type_quals`
: This function returns the set of type qualifiers applied to this type. This value is `TYPE_UNQUALIFIED` if no qualifiers have been applied. The `TYPE_QUAL_CONST` bit is set if the type is `const`-qualified. The `TYPE_QUAL_VOLATILE` bit is set if the type is `volatile`-qualified. The `TYPE_QUAL_RESTRICT` bit is set if the type is `restrict`-qualified.

`CP_TYPE_CONST_P`
: This macro holds if the type is `const`-qualified.

`CP_TYPE_VOLATILE_P`
: This macro holds if the type is `volatile`-qualified.

`CP_TYPE_RESTRICT_P`
: This macro holds if the type is `restrict`-qualified.

`CP_TYPE_CONST_NON_VOLATILE_P`
: This predicate holds for a type that is `const`-qualified, but *not* `volatile`-qualified; other cv-qualifiers are ignored as well: only the `const`-ness is tested.

A few other macros and functions are usable with all types:

`TYPE_SIZE`
: The number of bits required to represent the type, represented as an `INTEGER_CST`. For an incomplete type, `TYPE_SIZE` will be `NULL_TREE`.

`TYPE_ALIGN`
: The alignment of the type, in bits, represented as an `int`.

`TYPE_NAME`
: This macro returns a declaration (in the form of a `TYPE_DECL`) for the type. (Note this macro does *not* return an `IDENTIFIER_NODE`, as you might expect,

given its name!) You can look at the DECL_NAME of the TYPE_DECL to obtain the actual name of the type. The TYPE_NAME will be NULL_TREE for a type that is not a built-in type, the result of a typedef, or a named class type.

CP_INTEGRAL_TYPE
This predicate holds if the type is an integral type. Notice that in C++, enumerations are *not* integral types.

ARITHMETIC_TYPE_P
This predicate holds if the type is an integral type (in the C++ sense) or a floating point type.

CLASS_TYPE_P
This predicate holds for a class-type.

TYPE_BUILT_IN
This predicate holds for a built-in type.

TYPE_PTRDATAMEM_P
This predicate holds if the type is a pointer to data member.

TYPE_PTR_P
This predicate holds if the type is a pointer type, and the pointee is not a data member.

TYPE_PTRFN_P
This predicate holds for a pointer to function type.

TYPE_PTROB_P
This predicate holds for a pointer to object type. Note however that it does not hold for the generic pointer to object type `void *`. You may use TYPE_PTROBV_P to test for a pointer to object type as well as `void *`.

The table below describes types specific to C and C++ as well as language-dependent info about GENERIC types.

POINTER_TYPE
Used to represent pointer types, and pointer to data member types. If TREE_TYPE is a pointer to data member type, then TYPE_PTRDATAMEM_P will hold. For a pointer to data member type of the form '`T X::*`', TYPE_PTRMEM_CLASS_TYPE will be the type `X`, while TYPE_PTRMEM_POINTED_TO_TYPE will be the type `T`.

RECORD_TYPE
Used to represent `struct` and `class` types in C and C++. If TYPE_PTRMEMFUNC_P holds, then this type is a pointer-to-member type. In that case, the TYPE_PTRMEMFUNC_FN_TYPE is a POINTER_TYPE pointing to a METHOD_TYPE. The METHOD_TYPE is the type of a function pointed to by the pointer-to-member function. If TYPE_PTRMEMFUNC_P does not hold, this type is a class type. For more information, see Section 10.10.3 [Classes], page 165.

UNKNOWN_TYPE
This node is used to represent a type the knowledge of which is insufficient for a sound processing.

TYPENAME_TYPE
: Used to represent a construct of the form `typename T::A`. The `TYPE_CONTEXT` is `T`; the `TYPE_NAME` is an `IDENTIFIER_NODE` for `A`. If the type is specified via a template-id, then `TYPENAME_TYPE_FULLNAME` yields a `TEMPLATE_ID_EXPR`. The `TREE_TYPE` is non-`NULL` if the node is implicitly generated in support for the implicit typename extension; in which case the `TREE_TYPE` is a type node for the base-class.

TYPEOF_TYPE
: Used to represent the `__typeof__` extension. The `TYPE_FIELDS` is the expression the type of which is being represented.

10.10.2 Namespaces

The root of the entire intermediate representation is the variable `global_namespace`. This is the namespace specified with `::` in C++ source code. All other namespaces, types, variables, functions, and so forth can be found starting with this namespace.

However, except for the fact that it is distinguished as the root of the representation, the global namespace is no different from any other namespace. Thus, in what follows, we describe namespaces generally, rather than the global namespace in particular.

A namespace is represented by a `NAMESPACE_DECL` node.

The following macros and functions can be used on a `NAMESPACE_DECL`:

DECL_NAME
: This macro is used to obtain the `IDENTIFIER_NODE` corresponding to the unqualified name of the name of the namespace (see Section 10.2.2 [Identifiers], page 131). The name of the global namespace is '`::`', even though in C++ the global namespace is unnamed. However, you should use comparison with `global_namespace`, rather than `DECL_NAME` to determine whether or not a namespace is the global one. An unnamed namespace will have a `DECL_NAME` equal to `anonymous_namespace_name`. Within a single translation unit, all unnamed namespaces will have the same name.

DECL_CONTEXT
: This macro returns the enclosing namespace. The `DECL_CONTEXT` for the `global_namespace` is `NULL_TREE`.

DECL_NAMESPACE_ALIAS
: If this declaration is for a namespace alias, then `DECL_NAMESPACE_ALIAS` is the namespace for which this one is an alias.

  Do not attempt to use `cp_namespace_decls` for a namespace which is an alias. Instead, follow `DECL_NAMESPACE_ALIAS` links until you reach an ordinary, non-alias, namespace, and call `cp_namespace_decls` there.

DECL_NAMESPACE_STD_P
: This predicate holds if the namespace is the special `::std` namespace.

cp_namespace_decls
: This function will return the declarations contained in the namespace, including types, overloaded functions, other namespaces, and so forth. If there are no dec-

larations, this function will return NULL_TREE. The declarations are connected through their TREE_CHAIN fields.

Although most entries on this list will be declarations, TREE_LIST nodes may also appear. In this case, the TREE_VALUE will be an OVERLOAD. The value of the TREE_PURPOSE is unspecified; back ends should ignore this value. As with the other kinds of declarations returned by cp_namespace_decls, the TREE_CHAIN will point to the next declaration in this list.

For more information on the kinds of declarations that can occur on this list, See Section 10.4 [Declarations], page 136. Some declarations will not appear on this list. In particular, no FIELD_DECL, LABEL_DECL, or PARM_DECL nodes will appear here.

This function cannot be used with namespaces that have DECL_NAMESPACE_ALIAS set.

10.10.3 Classes

Besides namespaces, the other high-level scoping construct in C++ is the class. (Throughout this manual the term *class* is used to mean the types referred to in the ANSI/ISO C++ Standard as classes; these include types defined with the class, struct, and union keywords.)

A class type is represented by either a RECORD_TYPE or a UNION_TYPE. A class declared with the union tag is represented by a UNION_TYPE, while classes declared with either the struct or the class tag are represented by RECORD_TYPEs. You can use the CLASSTYPE_DECLARED_CLASS macro to discern whether or not a particular type is a class as opposed to a struct. This macro will be true only for classes declared with the class tag.

Almost all non-function members are available on the TYPE_FIELDS list. Given one member, the next can be found by following the TREE_CHAIN. You should not depend in any way on the order in which fields appear on this list. All nodes on this list will be 'DECL' nodes. A FIELD_DECL is used to represent a non-static data member, a VAR_DECL is used to represent a static data member, and a TYPE_DECL is used to represent a type. Note that the CONST_DECL for an enumeration constant will appear on this list, if the enumeration type was declared in the class. (Of course, the TYPE_DECL for the enumeration type will appear here as well.) There are no entries for base classes on this list. In particular, there is no FIELD_DECL for the "base-class portion" of an object.

The TYPE_VFIELD is a compiler-generated field used to point to virtual function tables. It may or may not appear on the TYPE_FIELDS list. However, back ends should handle the TYPE_VFIELD just like all the entries on the TYPE_FIELDS list.

The function members are available on the TYPE_METHODS list. Again, subsequent members are found by following the TREE_CHAIN field. If a function is overloaded, each of the overloaded functions appears; no OVERLOAD nodes appear on the TYPE_METHODS list. Implicitly declared functions (including default constructors, copy constructors, assignment operators, and destructors) will appear on this list as well.

Every class has an associated *binfo*, which can be obtained with TYPE_BINFO. Binfos are used to represent base-classes. The binfo given by TYPE_BINFO is the degenerate case, whereby every class is considered to be its own base-class. The base binfos for a particular binfo are held in a vector, whose length is obtained with BINFO_N_BASE_BINFOS. The base

binfos themselves are obtained with `BINFO_BASE_BINFO` and `BINFO_BASE_ITERATE`. To add a new binfo, use `BINFO_BASE_APPEND`. The vector of base binfos can be obtained with `BINFO_BASE_BINFOS`, but normally you do not need to use that. The class type associated with a binfo is given by `BINFO_TYPE`. It is not always the case that `BINFO_TYPE (TYPE_BINFO (x))`, because of typedefs and qualified types. Neither is it the case that `TYPE_BINFO (BINFO_TYPE (y))` is the same binfo as `y`. The reason is that if `y` is a binfo representing a base-class `B` of a derived class `D`, then `BINFO_TYPE (y)` will be `B`, and `TYPE_BINFO (BINFO_TYPE (y))` will be `B` as its own base-class, rather than as a base-class of `D`.

The access to a base type can be found with `BINFO_BASE_ACCESS`. This will produce `access_public_node`, `access_private_node` or `access_protected_node`. If bases are always public, `BINFO_BASE_ACCESSES` may be `NULL`.

`BINFO_VIRTUAL_P` is used to specify whether the binfo is inherited virtually or not. The other flags, `BINFO_MARKED_P` and `BINFO_FLAG_1` to `BINFO_FLAG_6` can be used for language specific use.

The following macros can be used on a tree node representing a class-type.

`LOCAL_CLASS_P`
: This predicate holds if the class is local class *i.e.* declared inside a function body.

`TYPE_POLYMORPHIC_P`
: This predicate holds if the class has at least one virtual function (declared or inherited).

`TYPE_HAS_DEFAULT_CONSTRUCTOR`
: This predicate holds whenever its argument represents a class-type with default constructor.

`CLASSTYPE_HAS_MUTABLE`
`TYPE_HAS_MUTABLE_P`
: These predicates hold for a class-type having a mutable data member.

`CLASSTYPE_NON_POD_P`
: This predicate holds only for class-types that are not PODs.

`TYPE_HAS_NEW_OPERATOR`
: This predicate holds for a class-type that defines `operator new`.

`TYPE_HAS_ARRAY_NEW_OPERATOR`
: This predicate holds for a class-type for which `operator new[]` is defined.

`TYPE_OVERLOADS_CALL_EXPR`
: This predicate holds for class-type for which the function call `operator()` is overloaded.

`TYPE_OVERLOADS_ARRAY_REF`
: This predicate holds for a class-type that overloads `operator[]`

`TYPE_OVERLOADS_ARROW`
: This predicate holds for a class-type for which `operator->` is overloaded.

10.10.4 Functions for C++

A function is represented by a FUNCTION_DECL node. A set of overloaded functions is sometimes represented by an OVERLOAD node.

An OVERLOAD node is not a declaration, so none of the 'DECL_' macros should be used on an OVERLOAD. An OVERLOAD node is similar to a TREE_LIST. Use OVL_CURRENT to get the function associated with an OVERLOAD node; use OVL_NEXT to get the next OVERLOAD node in the list of overloaded functions. The macros OVL_CURRENT and OVL_NEXT are actually polymorphic; you can use them to work with FUNCTION_DECL nodes as well as with overloads. In the case of a FUNCTION_DECL, OVL_CURRENT will always return the function itself, and OVL_NEXT will always be NULL_TREE.

To determine the scope of a function, you can use the DECL_CONTEXT macro. This macro will return the class (either a RECORD_TYPE or a UNION_TYPE) or namespace (a NAMESPACE_DECL) of which the function is a member. For a virtual function, this macro returns the class in which the function was actually defined, not the base class in which the virtual declaration occurred.

If a friend function is defined in a class scope, the DECL_FRIEND_CONTEXT macro can be used to determine the class in which it was defined. For example, in

```
class C { friend void f() {} };
```

the DECL_CONTEXT for f will be the global_namespace, but the DECL_FRIEND_CONTEXT will be the RECORD_TYPE for C.

The following macros and functions can be used on a FUNCTION_DECL:

DECL_MAIN_P
: This predicate holds for a function that is the program entry point ::code.

DECL_LOCAL_FUNCTION_P
: This predicate holds if the function was declared at block scope, even though it has a global scope.

DECL_ANTICIPATED
: This predicate holds if the function is a built-in function but its prototype is not yet explicitly declared.

DECL_EXTERN_C_FUNCTION_P
: This predicate holds if the function is declared as an 'extern "C"' function.

DECL_LINKONCE_P
: This macro holds if multiple copies of this function may be emitted in various translation units. It is the responsibility of the linker to merge the various copies. Template instantiations are the most common example of functions for which DECL_LINKONCE_P holds; G++ instantiates needed templates in all translation units which require them, and then relies on the linker to remove duplicate instantiations.

  FIXME: This macro is not yet implemented.

DECL_FUNCTION_MEMBER_P
: This macro holds if the function is a member of a class, rather than a member of a namespace.

`DECL_STATIC_FUNCTION_P`
This predicate holds if the function a static member function.

`DECL_NONSTATIC_MEMBER_FUNCTION_P`
This macro holds for a non-static member function.

`DECL_CONST_MEMFUNC_P`
This predicate holds for a `const`-member function.

`DECL_VOLATILE_MEMFUNC_P`
This predicate holds for a `volatile`-member function.

`DECL_CONSTRUCTOR_P`
This macro holds if the function is a constructor.

`DECL_NONCONVERTING_P`
This predicate holds if the constructor is a non-converting constructor.

`DECL_COMPLETE_CONSTRUCTOR_P`
This predicate holds for a function which is a constructor for an object of a complete type.

`DECL_BASE_CONSTRUCTOR_P`
This predicate holds for a function which is a constructor for a base class sub-object.

`DECL_COPY_CONSTRUCTOR_P`
This predicate holds for a function which is a copy-constructor.

`DECL_DESTRUCTOR_P`
This macro holds if the function is a destructor.

`DECL_COMPLETE_DESTRUCTOR_P`
This predicate holds if the function is the destructor for an object a complete type.

`DECL_OVERLOADED_OPERATOR_P`
This macro holds if the function is an overloaded operator.

`DECL_CONV_FN_P`
This macro holds if the function is a type-conversion operator.

`DECL_GLOBAL_CTOR_P`
This predicate holds if the function is a file-scope initialization function.

`DECL_GLOBAL_DTOR_P`
This predicate holds if the function is a file-scope finalization function.

`DECL_THUNK_P`
This predicate holds if the function is a thunk.

These functions represent stub code that adjusts the `this` pointer and then jumps to another function. When the jumped-to function returns, control is transferred directly to the caller, without returning to the thunk. The first parameter to the thunk is always the `this` pointer; the thunk should add `THUNK_DELTA` to this value. (The `THUNK_DELTA` is an `int`, not an `INTEGER_CST`.)

Then, if THUNK_VCALL_OFFSET (an INTEGER_CST) is nonzero the adjusted this pointer must be adjusted again. The complete calculation is given by the following pseudo-code:

```
this += THUNK_DELTA
if (THUNK_VCALL_OFFSET)
  this += (*((ptrdiff_t **) this))[THUNK_VCALL_OFFSET]
```

Finally, the thunk should jump to the location given by DECL_INITIAL; this will always be an expression for the address of a function.

DECL_NON_THUNK_FUNCTION_P
: This predicate holds if the function is *not* a thunk function.

GLOBAL_INIT_PRIORITY
: If either DECL_GLOBAL_CTOR_P or DECL_GLOBAL_DTOR_P holds, then this gives the initialization priority for the function. The linker will arrange that all functions for which DECL_GLOBAL_CTOR_P holds are run in increasing order of priority before main is called. When the program exits, all functions for which DECL_GLOBAL_DTOR_P holds are run in the reverse order.

TYPE_RAISES_EXCEPTIONS
: This macro returns the list of exceptions that a (member-)function can raise. The returned list, if non NULL, is comprised of nodes whose TREE_VALUE represents a type.

TYPE_NOTHROW_P
: This predicate holds when the exception-specification of its arguments is of the form '()'.

DECL_ARRAY_DELETE_OPERATOR_P
: This predicate holds if the function an overloaded operator delete[].

10.10.5 Statements for C++

A function that has a definition in the current translation unit will have a non-NULL DECL_INITIAL. However, back ends should not make use of the particular value given by DECL_INITIAL.

The DECL_SAVED_TREE macro will give the complete body of the function.

10.10.5.1 Statements

There are tree nodes corresponding to all of the source-level statement constructs, used within the C and C++ frontends. These are enumerated here, together with a list of the various macros that can be used to obtain information about them. There are a few macros that can be used with all statements:

STMT_IS_FULL_EXPR_P
: In C++, statements normally constitute "full expressions"; temporaries created during a statement are destroyed when the statement is complete. However, G++ sometimes represents expressions by statements; these statements will not have STMT_IS_FULL_EXPR_P set. Temporaries created during such statements should be destroyed when the innermost enclosing statement with STMT_IS_FULL_EXPR_P set is exited.

Here is the list of the various statement nodes, and the macros used to access them. This documentation describes the use of these nodes in non-template functions (including instantiations of template functions). In template functions, the same nodes are used, but sometimes in slightly different ways.

Many of the statements have substatements. For example, a `while` loop will have a body, which is itself a statement. If the substatement is `NULL_TREE`, it is considered equivalent to a statement consisting of a single `;`, i.e., an expression statement in which the expression has been omitted. A substatement may in fact be a list of statements, connected via their `TREE_CHAIN`s. So, you should always process the statement tree by looping over substatements, like this:

```
void process_stmt (stmt)
     tree stmt;
{
  while (stmt)
    {
      switch (TREE_CODE (stmt))
        {
        case IF_STMT:
          process_stmt (THEN_CLAUSE (stmt));
          /* More processing here.  */
          break;

        ...
        }

      stmt = TREE_CHAIN (stmt);
    }
}
```

In other words, while the `then` clause of an `if` statement in C++ can be only one statement (although that one statement may be a compound statement), the intermediate representation will sometimes use several statements chained together.

`BREAK_STMT`
: Used to represent a `break` statement. There are no additional fields.

`CILK_SPAWN_STMT`
: Used to represent a spawning function in the Cilk Plus language extension. This tree has one field that holds the name of the spawning function. `_Cilk_spawn` can be written in C in the following way:

```
_Cilk_spawn <function_name> (<parameters>);
```

Detailed description for usage and functionality of `_Cilk_spawn` can be found at http://www.cilkplus.org

`CILK_SYNC_STMT`
: This statement is part of the Cilk Plus language extension. It indicates that the current function cannot continue in parallel with its spawned children. There are no additional fields. `_Cilk_sync` can be written in C in the following way:

```
_Cilk_sync;
```

`CLEANUP_STMT`
: Used to represent an action that should take place upon exit from the enclosing scope. Typically, these actions are calls to destructors for local objects,

but back ends cannot rely on this fact. If these nodes are in fact representing such destructors, CLEANUP_DECL will be the VAR_DECL destroyed. Otherwise, CLEANUP_DECL will be NULL_TREE. In any case, the CLEANUP_EXPR is the expression to execute. The cleanups executed on exit from a scope should be run in the reverse order of the order in which the associated CLEANUP_STMTs were encountered.

CONTINUE_STMT

Used to represent a continue statement. There are no additional fields.

CTOR_STMT

Used to mark the beginning (if CTOR_BEGIN_P holds) or end (if CTOR_END_P holds of the main body of a constructor. See also SUBOBJECT for more information on how to use these nodes.

DO_STMT

Used to represent a do loop. The body of the loop is given by DO_BODY while the termination condition for the loop is given by DO_COND. The condition for a do-statement is always an expression.

EMPTY_CLASS_EXPR

Used to represent a temporary object of a class with no data whose address is never taken. (All such objects are interchangeable.) The TREE_TYPE represents the type of the object.

EXPR_STMT

Used to represent an expression statement. Use EXPR_STMT_EXPR to obtain the expression.

FOR_STMT

Used to represent a for statement. The FOR_INIT_STMT is the initialization statement for the loop. The FOR_COND is the termination condition. The FOR_EXPR is the expression executed right before the FOR_COND on each loop iteration; often, this expression increments a counter. The body of the loop is given by FOR_BODY. Note that FOR_INIT_STMT and FOR_BODY return statements, while FOR_COND and FOR_EXPR return expressions.

HANDLER

Used to represent a C++ catch block. The HANDLER_TYPE is the type of exception that will be caught by this handler; it is equal (by pointer equality) to NULL if this handler is for all types. HANDLER_PARMS is the DECL_STMT for the catch parameter, and HANDLER_BODY is the code for the block itself.

IF_STMT

Used to represent an if statement. The IF_COND is the expression.

If the condition is a TREE_LIST, then the TREE_PURPOSE is a statement (usually a DECL_STMT). Each time the condition is evaluated, the statement should be executed. Then, the TREE_VALUE should be used as the conditional expression itself. This representation is used to handle C++ code like this:

C++ distinguishes between this and COND_EXPR for handling templates.

```
if (int i = 7) ...
```

where there is a new local variable (or variables) declared within the condition.

The THEN_CLAUSE represents the statement given by the `then` condition, while the ELSE_CLAUSE represents the statement given by the `else` condition.

SUBOBJECT

In a constructor, these nodes are used to mark the point at which a subobject of `this` is fully constructed. If, after this point, an exception is thrown before a CTOR_STMT with CTOR_END_P set is encountered, the SUBOBJECT_CLEANUP must be executed. The cleanups must be executed in the reverse order in which they appear.

SWITCH_STMT

Used to represent a `switch` statement. The SWITCH_STMT_COND is the expression on which the switch is occurring. See the documentation for an IF_STMT for more information on the representation used for the condition. The SWITCH_STMT_BODY is the body of the switch statement. The SWITCH_STMT_TYPE is the original type of switch expression as given in the source, before any compiler conversions.

TRY_BLOCK

Used to represent a `try` block. The body of the try block is given by TRY_STMTS. Each of the catch blocks is a HANDLER node. The first handler is given by TRY_HANDLERS. Subsequent handlers are obtained by following the TREE_CHAIN link from one handler to the next. The body of the handler is given by HANDLER_BODY.

If CLEANUP_P holds of the TRY_BLOCK, then the TRY_HANDLERS will not be a HANDLER node. Instead, it will be an expression that should be executed if an exception is thrown in the try block. It must rethrow the exception after executing that code. And, if an exception is thrown while the expression is executing, `terminate` must be called.

USING_STMT

Used to represent a `using` directive. The namespace is given by USING_STMT_NAMESPACE, which will be a NAMESPACE_DECL. This node is needed inside template functions, to implement using directives during instantiation.

WHILE_STMT

Used to represent a `while` loop. The WHILE_COND is the termination condition for the loop. See the documentation for an IF_STMT for more information on the representation used for the condition.

The WHILE_BODY is the body of the loop.

10.10.6 C++ Expressions

This section describes expressions specific to the C and C++ front ends.

TYPEID_EXPR

Used to represent a `typeid` expression.

NEW_EXPR
VEC_NEW_EXPR
: Used to represent a call to `new` and `new[]` respectively.

DELETE_EXPR
VEC_DELETE_EXPR
: Used to represent a call to `delete` and `delete[]` respectively.

MEMBER_REF
: Represents a reference to a member of a class.

THROW_EXPR
: Represents an instance of `throw` in the program. Operand 0, which is the expression to throw, may be `NULL_TREE`.

AGGR_INIT_EXPR
: An `AGGR_INIT_EXPR` represents the initialization as the return value of a function call, or as the result of a constructor. An `AGGR_INIT_EXPR` will only appear as a full-expression, or as the second operand of a `TARGET_EXPR`. `AGGR_INIT_EXPR`s have a representation similar to that of `CALL_EXPR`s. You can use the `AGGR_INIT_EXPR_FN` and `AGGR_INIT_EXPR_ARG` macros to access the function to call and the arguments to pass.

  If `AGGR_INIT_VIA_CTOR_P` holds of the `AGGR_INIT_EXPR`, then the initialization is via a constructor call. The address of the `AGGR_INIT_EXPR_SLOT` operand, which is always a `VAR_DECL`, is taken, and this value replaces the first argument in the argument list.

  In either case, the expression is void.

10.11 Java Trees

11 GIMPLE

GIMPLE is a three-address representation derived from GENERIC by breaking down GENERIC expressions into tuples of no more than 3 operands (with some exceptions like function calls). GIMPLE was heavily influenced by the SIMPLE IL used by the McCAT compiler project at McGill University, though we have made some different choices. For one thing, SIMPLE doesn't support `goto`.

Temporaries are introduced to hold intermediate values needed to compute complex expressions. Additionally, all the control structures used in GENERIC are lowered into conditional jumps, lexical scopes are removed and exception regions are converted into an on the side exception region tree.

The compiler pass which converts GENERIC into GIMPLE is referred to as the '`gimplifier`'. The gimplifier works recursively, generating GIMPLE tuples out of the original GENERIC expressions.

One of the early implementation strategies used for the GIMPLE representation was to use the same internal data structures used by front ends to represent parse trees. This simplified implementation because we could leverage existing functionality and interfaces. However, GIMPLE is a much more restrictive representation than abstract syntax trees (AST), therefore it does not require the full structural complexity provided by the main tree data structure.

The GENERIC representation of a function is stored in the `DECL_SAVED_TREE` field of the associated `FUNCTION_DECL` tree node. It is converted to GIMPLE by a call to `gimplify_function_tree`.

If a front end wants to include language-specific tree codes in the tree representation which it provides to the back end, it must provide a definition of `LANG_HOOKS_GIMPLIFY_EXPR` which knows how to convert the front end trees to GIMPLE. Usually such a hook will involve much of the same code for expanding front end trees to RTL. This function can return fully lowered GIMPLE, or it can return GENERIC trees and let the main gimplifier lower them the rest of the way; this is often simpler. GIMPLE that is not fully lowered is known as "High GIMPLE" and consists of the IL before the pass `pass_lower_cf`. High GIMPLE contains some container statements like lexical scopes (represented by `GIMPLE_BIND`) and nested expressions (e.g., `GIMPLE_TRY`), while "Low GIMPLE" exposes all of the implicit jumps for control and exception expressions directly in the IL and EH region trees.

The C and C++ front ends currently convert directly from front end trees to GIMPLE, and hand that off to the back end rather than first converting to GENERIC. Their gimplifier hooks know about all the `_STMT` nodes and how to convert them to GENERIC forms. There was some work done on a genericization pass which would run first, but the existence of `STMT_EXPR` meant that in order to convert all of the C statements into GENERIC equivalents would involve walking the entire tree anyway, so it was simpler to lower all the way. This might change in the future if someone writes an optimization pass which would work better with higher-level trees, but currently the optimizers all expect GIMPLE.

You can request to dump a C-like representation of the GIMPLE form with the flag '`-fdump-tree-gimple`'.

11.1 Tuple representation

GIMPLE instructions are tuples of variable size divided in two groups: a header describing the instruction and its locations, and a variable length body with all the operands. Tuples are organized into a hierarchy with 3 main classes of tuples.

11.1.1 `gimple_statement_base` (gsbase)

This is the root of the hierarchy, it holds basic information needed by most GIMPLE statements. There are some fields that may not be relevant to every GIMPLE statement, but those were moved into the base structure to take advantage of holes left by other fields (thus making the structure more compact). The structure takes 4 words (32 bytes) on 64 bit hosts:

Field	Size (bits)
`code`	8
`subcode`	16
`no_warning`	1
`visited`	1
`nontemporal_move`	1
`plf`	2
`modified`	1
`has_volatile_ops`	1
`references_memory_p`	1
`uid`	32
`location`	32
`num_ops`	32
`bb`	64
`block`	63
Total size	32 bytes

- `code` Main identifier for a GIMPLE instruction.
- `subcode` Used to distinguish different variants of the same basic instruction or provide flags applicable to a given code. The `subcode` flags field has different uses depending on the code of the instruction, but mostly it distinguishes instructions of the same family. The most prominent use of this field is in assignments, where subcode indicates the operation done on the RHS of the assignment. For example, a = b + c is encoded as `GIMPLE_ASSIGN <PLUS_EXPR, a, b, c>`.
- `no_warning` Bitflag to indicate whether a warning has already been issued on this statement.
- `visited` General purpose "visited" marker. Set and cleared by each pass when needed.
- `nontemporal_move` Bitflag used in assignments that represent non-temporal moves. Although this bitflag is only used in assignments, it was moved into the base to take advantage of the bit holes left by the previous fields.
- `plf` Pass Local Flags. This 2-bit mask can be used as general purpose markers by any pass. Passes are responsible for clearing and setting these two flags accordingly.
- `modified` Bitflag to indicate whether the statement has been modified. Used mainly by the operand scanner to determine when to re-scan a statement for operands.

- `has_volatile_ops` Bitflag to indicate whether this statement contains operands that have been marked volatile.
- `references_memory_p` Bitflag to indicate whether this statement contains memory references (i.e., its operands are either global variables, or pointer dereferences or anything that must reside in memory).
- `uid` This is an unsigned integer used by passes that want to assign IDs to every statement. These IDs must be assigned and used by each pass.
- `location` This is a `location_t` identifier to specify source code location for this statement. It is inherited from the front end.
- `num_ops` Number of operands that this statement has. This specifies the size of the operand vector embedded in the tuple. Only used in some tuples, but it is declared in the base tuple to take advantage of the 32-bit hole left by the previous fields.
- `bb` Basic block holding the instruction.
- `block` Lexical block holding this statement. Also used for debug information generation.

11.1.2 `gimple_statement_with_ops`

This tuple is actually split in two: `gimple_statement_with_ops_base` and `gimple_statement_with_ops`. This is needed to accommodate the way the operand vector is allocated. The operand vector is defined to be an array of 1 element. So, to allocate a dynamic number of operands, the memory allocator (`gimple_alloc`) simply allocates enough memory to hold the structure itself plus `N - 1` operands which run "off the end" of the structure. For example, to allocate space for a tuple with 3 operands, `gimple_alloc` reserves `sizeof (struct gimple_statement_with_ops) + 2 * sizeof (tree)` bytes.

On the other hand, several fields in this tuple need to be shared with the `gimple_statement_with_memory_ops` tuple. So, these common fields are placed in `gimple_statement_with_ops_base` which is then inherited from the other two tuples.

`gsbase`	256
`def_ops`	64
`use_ops`	64
`op`	`num_ops` * 64
Total size	48 + 8 * `num_ops` bytes

- `gsbase` Inherited from `struct gimple_statement_base`.
- `def_ops` Array of pointers into the operand array indicating all the slots that contain a variable written-to by the statement. This array is also used for immediate use chaining. Note that it would be possible to not rely on this array, but the changes required to implement this are pretty invasive.
- `use_ops` Similar to `def_ops` but for variables read by the statement.
- `op` Array of trees with `num_ops` slots.

11.1.3 `gimple_statement_with_memory_ops`

This tuple is essentially identical to `gimple_statement_with_ops`, except that it contains 4 additional fields to hold vectors related memory stores and loads. Similar to the pre-

vious case, the structure is split in two to accommodate for the operand vector (`gimple_statement_with_memory_ops_base` and `gimple_statement_with_memory_ops`).

Field	Size (bits)
`gsbase`	256
`def_ops`	64
`use_ops`	64
`vdef_ops`	64
`vuse_ops`	64
`stores`	64
`loads`	64
`op`	`num_ops` * 64
Total size	80 + 8 * `num_ops` bytes

- `vdef_ops` Similar to `def_ops` but for `VDEF` operators. There is one entry per memory symbol written by this statement. This is used to maintain the memory SSA use-def and def-def chains.
- `vuse_ops` Similar to `use_ops` but for `VUSE` operators. There is one entry per memory symbol loaded by this statement. This is used to maintain the memory SSA use-def chains.
- `stores` Bitset with all the UIDs for the symbols written-to by the statement. This is different than `vdef_ops` in that all the affected symbols are mentioned in this set. If memory partitioning is enabled, the `vdef_ops` vector will refer to memory partitions. Furthermore, no SSA information is stored in this set.
- `loads` Similar to `stores`, but for memory loads. (Note that there is some amount of redundancy here, it should be possible to reduce memory utilization further by removing these sets).

All the other tuples are defined in terms of these three basic ones. Each tuple will add some fields.

The following diagram shows the C++ inheritance hierarchy of statement kinds, along with their relationships to `GSS_` values (layouts) and `GIMPLE_` values (codes):

```
+- gimple_statement_base
     |    layout: GSS_BASE
     |    used for 4 codes: GIMPLE_ERROR_MARK
     |                      GIMPLE_NOP
     |                      GIMPLE_OMP_SECTIONS_SWITCH
     |                      GIMPLE_PREDICT
     |
     + gimple_statement_with_ops_base
     |   |    (no GSS layout)
     |   |
     |   + gimple_statement_with_ops
     |   |        layout: GSS_WITH_OPS
     |   |        Used for 5 codes: GIMPLE_COND
     |   |                          GIMPLE_DEBUG
     |   |                          GIMPLE_GOTO
     |   |                          GIMPLE_LABEL
     |   |                          GIMPLE_SWITCH
     |   |
     |   + gimple_statement_with_memory_ops_base
     |       |    layout: GSS_WITH_MEM_OPS_BASE
```

```
|       |
|       + gimple_statement_with_memory_ops
|       |        layout: GSS_WITH_MEM_OPS.
|       |        used for codes GIMPLE_ASSIGN and GIMPLE_RETURN.
|       |
|       + gimple_statement_call
|       |        layout: GSS_CALL, code: GIMPLE_CALL
|       |
|       + gimple_statement_asm
|       |        layout: GSS_ASM, code: GIMPLE_ASM
|       |
|       + gimple_statement_transaction
|                layout: GSS_TRANSACTION, code: GIMPLE_TRANSACTION
|
+ gimple_statement_omp
|   |    layout: GSS_OMP.  Used for code GIMPLE_OMP_SECTION
|   |
|   + gimple_statement_omp_critical
|   |        layout: GSS_OMP_CRITICAL, code: GIMPLE_OMP_CRITICAL
|   |
|   + gimple_statement_omp_for
|   |        layout: GSS_OMP_FOR, code: GIMPLE_OMP_FOR
|   |
|   + gimple_statement_omp_parallel_layout
|   |   |    layout: GSS_OMP_PARALLEL_LAYOUT
|   |   |
|   |   + gimple_statement_omp_taskreg
|   |   |   |
|   |   |   + gimple_statement_omp_parallel
|   |   |   |        code: GIMPLE_OMP_PARALLEL
|   |   |   |
|   |   |   + gimple_statement_omp_task
|   |   |            code: GIMPLE_OMP_TASK
|   |   |
|   |   + gimple_statement_omp_target
|   |            code: GIMPLE_OMP_TARGET
|   |
|   + gimple_statement_omp_sections
|   |        layout: GSS_OMP_SECTIONS, code: GIMPLE_OMP_SECTIONS
|   |
|   + gimple_statement_omp_single_layout
|       |    layout: GSS_OMP_SINGLE_LAYOUT
|       |
|       + gimple_statement_omp_single
|       |        code: GIMPLE_OMP_SINGLE
|       |
|       + gimple_statement_omp_teams
|                code: GIMPLE_OMP_TEAMS
|
+ gimple_statement_bind
|        layout: GSS_BIND, code: GIMPLE_BIND
|
+ gimple_statement_catch
|        layout: GSS_CATCH, code: GIMPLE_CATCH
|
+ gimple_statement_eh_filter
|        layout: GSS_EH_FILTER, code: GIMPLE_EH_FILTER
|
```

```
+ gimple_statement_eh_else
|        layout: GSS_EH_ELSE, code: GIMPLE_EH_ELSE
|
+ gimple_statement_eh_mnt
|        layout: GSS_EH_MNT, code: GIMPLE_EH_MUST_NOT_THROW
|
+ gimple_statement_phi
|        layout: GSS_PHI, code: GIMPLE_PHI
|
+ gimple_statement_eh_ctrl
|   |    layout: GSS_EH_CTRL
|   |
|   + gimple_statement_resx
|   |        code: GIMPLE_RESX
|   |
|   + gimple_statement_eh_dispatch
|            code: GIMPLE_EH_DISPATCH
|
+ gimple_statement_try
|        layout: GSS_TRY, code: GIMPLE_TRY
|
+ gimple_statement_wce
|        layout: GSS_WCE, code: GIMPLE_WITH_CLEANUP_EXPR
|
+ gimple_statement_omp_continue
|        layout: GSS_OMP_CONTINUE, code: GIMPLE_OMP_CONTINUE
|
+ gimple_statement_omp_atomic_load
|        layout: GSS_OMP_ATOMIC_LOAD, code: GIMPLE_OMP_ATOMIC_LOAD
|
+ gimple_statement_omp_atomic_store_layout
    |    layout: GSS_OMP_ATOMIC_STORE_LAYOUT,
    |    code: GIMPLE_OMP_ATOMIC_STORE
    |
    + gimple_statement_omp_atomic_store
    |        code: GIMPLE_OMP_ATOMIC_STORE
    |
    + gimple_statement_omp_return
             code: GIMPLE_OMP_RETURN
```

11.2 GIMPLE instruction set

The following table briefly describes the GIMPLE instruction set.

Instruction	High GIMPLE	Low GIMPLE
GIMPLE_ASM	x	x
GIMPLE_ASSIGN	x	x
GIMPLE_BIND	x	
GIMPLE_CALL	x	x
GIMPLE_CATCH	x	
GIMPLE_COND	x	x
GIMPLE_DEBUG	x	x
GIMPLE_EH_FILTER	x	
GIMPLE_GOTO	x	x
GIMPLE_LABEL	x	x
GIMPLE_NOP	x	x

GIMPLE_OMP_ATOMIC_LOAD	x	x
GIMPLE_OMP_ATOMIC_STORE	x	x
GIMPLE_OMP_CONTINUE	x	x
GIMPLE_OMP_CRITICAL	x	x
GIMPLE_OMP_FOR	x	x
GIMPLE_OMP_MASTER	x	x
GIMPLE_OMP_ORDERED	x	x
GIMPLE_OMP_PARALLEL	x	x
GIMPLE_OMP_RETURN	x	x
GIMPLE_OMP_SECTION	x	x
GIMPLE_OMP_SECTIONS	x	x
GIMPLE_OMP_SECTIONS_SWITCH	x	x
GIMPLE_OMP_SINGLE	x	x
GIMPLE_PHI		x
GIMPLE_RESX		x
GIMPLE_RETURN	x	x
GIMPLE_SWITCH	x	x
GIMPLE_TRY	x	

11.3 Exception Handling

Other exception handling constructs are represented using `GIMPLE_TRY_CATCH`. `GIMPLE_TRY_CATCH` has two operands. The first operand is a sequence of statements to execute. If executing these statements does not throw an exception, then the second operand is ignored. Otherwise, if an exception is thrown, then the second operand of the `GIMPLE_TRY_CATCH` is checked. The second operand may have the following forms:

1. A sequence of statements to execute. When an exception occurs, these statements are executed, and then the exception is rethrown.
2. A sequence of `GIMPLE_CATCH` statements. Each `GIMPLE_CATCH` has a list of applicable exception types and handler code. If the thrown exception matches one of the caught types, the associated handler code is executed. If the handler code falls off the bottom, execution continues after the original `GIMPLE_TRY_CATCH`.
3. A `GIMPLE_EH_FILTER` statement. This has a list of permitted exception types, and code to handle a match failure. If the thrown exception does not match one of the allowed types, the associated match failure code is executed. If the thrown exception does match, it continues unwinding the stack looking for the next handler.

Currently throwing an exception is not directly represented in GIMPLE, since it is implemented by calling a function. At some point in the future we will want to add some way to express that the call will throw an exception of a known type.

Just before running the optimizers, the compiler lowers the high-level EH constructs above into a set of '`goto`'s, magic labels, and EH regions. Continuing to unwind at the end of a cleanup is represented with a `GIMPLE_RESX`.

11.4 Temporaries

When gimplification encounters a subexpression that is too complex, it creates a new temporary variable to hold the value of the subexpression, and adds a new statement to initial-

ize it before the current statement. These special temporaries are known as '`expression temporaries`', and are allocated using `get_formal_tmp_var`. The compiler tries to always evaluate identical expressions into the same temporary, to simplify elimination of redundant calculations.

We can only use expression temporaries when we know that it will not be reevaluated before its value is used, and that it will not be otherwise modified[1]. Other temporaries can be allocated using `get_initialized_tmp_var` or `create_tmp_var`.

Currently, an expression like `a = b + 5` is not reduced any further. We tried converting it to something like

```
T1 = b + 5;
a = T1;
```

but this bloated the representation for minimal benefit. However, a variable which must live in memory cannot appear in an expression; its value is explicitly loaded into a temporary first. Similarly, storing the value of an expression to a memory variable goes through a temporary.

11.5 Operands

In general, expressions in GIMPLE consist of an operation and the appropriate number of simple operands; these operands must either be a GIMPLE rvalue (`is_gimple_val`), i.e. a constant or a register variable. More complex operands are factored out into temporaries, so that

```
a = b + c + d
```

becomes

```
T1 = b + c;
a = T1 + d;
```

The same rule holds for arguments to a `GIMPLE_CALL`.

The target of an assignment is usually a variable, but can also be a `MEM_REF` or a compound lvalue as described below.

11.5.1 Compound Expressions

The left-hand side of a C comma expression is simply moved into a separate statement.

11.5.2 Compound Lvalues

Currently compound lvalues involving array and structure field references are not broken down; an expression like `a.b[2] = 42` is not reduced any further (though complex array subscripts are). This restriction is a workaround for limitations in later optimizers; if we were to convert this to

```
T1 = &a.b;
T1[2] = 42;
```

alias analysis would not remember that the reference to `T1[2]` came by way of `a.b`, so it would think that the assignment could alias another member of `a`; this broke `struct-alias-1.c`. Future optimizer improvements may make this limitation unnecessary.

[1] These restrictions are derived from those in Morgan 4.8.

11.5.3 Conditional Expressions

A C `?:` expression is converted into an `if` statement with each branch assigning to the same temporary. So,

```
a = b ? c : d;
```

becomes

```
if (b == 1)
  T1 = c;
else
  T1 = d;
a = T1;
```

The GIMPLE level if-conversion pass re-introduces `?:` expression, if appropriate. It is used to vectorize loops with conditions using vector conditional operations.

Note that in GIMPLE, `if` statements are represented using `GIMPLE_COND`, as described below.

11.5.4 Logical Operators

Except when they appear in the condition operand of a `GIMPLE_COND`, logical 'and' and 'or' operators are simplified as follows: `a = b && c` becomes

```
T1 = (bool)b;
if (T1 == true)
  T1 = (bool)c;
a = T1;
```

Note that `T1` in this example cannot be an expression temporary, because it has two different assignments.

11.5.5 Manipulating operands

All gimple operands are of type `tree`. But only certain types of trees are allowed to be used as operand tuples. Basic validation is controlled by the function `get_gimple_rhs_class`, which given a tree code, returns an `enum` with the following values of type `enum gimple_rhs_class`

- `GIMPLE_INVALID_RHS` The tree cannot be used as a GIMPLE operand.
- `GIMPLE_TERNARY_RHS` The tree is a valid GIMPLE ternary operation.
- `GIMPLE_BINARY_RHS` The tree is a valid GIMPLE binary operation.
- `GIMPLE_UNARY_RHS` The tree is a valid GIMPLE unary operation.
- `GIMPLE_SINGLE_RHS` The tree is a single object, that cannot be split into simpler operands (for instance, `SSA_NAME`, `VAR_DECL`, `COMPONENT_REF`, etc).

  This operand class also acts as an escape hatch for tree nodes that may be flattened out into the operand vector, but would need more than two slots on the RHS. For instance, a `COND_EXPR` expression of the form `(a op b) ? x : y` could be flattened out on the operand vector using 4 slots, but it would also require additional processing to distinguish `c = a op b` from `c = a op b ? x : y`. Something similar occurs with `ASSERT_EXPR`. In time, these special case tree expressions should be flattened into the operand vector.

For tree nodes in the categories `GIMPLE_TERNARY_RHS`, `GIMPLE_BINARY_RHS` and `GIMPLE_UNARY_RHS`, they cannot be stored inside tuples directly. They first need to be flattened and separated into individual components. For instance, given the GENERIC expression

```
a = b + c
```

its tree representation is:

```
MODIFY_EXPR <VAR_DECL  <a>, PLUS_EXPR <VAR_DECL <b>, VAR_DECL <c>>>
```

In this case, the GIMPLE form for this statement is logically identical to its GENERIC form but in GIMPLE, the `PLUS_EXPR` on the RHS of the assignment is not represented as a tree, instead the two operands are taken out of the `PLUS_EXPR` sub-tree and flattened into the GIMPLE tuple as follows:

```
GIMPLE_ASSIGN <PLUS_EXPR, VAR_DECL <a>, VAR_DECL <b>, VAR_DECL <c>>
```

11.5.6 Operand vector allocation

The operand vector is stored at the bottom of the three tuple structures that accept operands. This means, that depending on the code of a given statement, its operand vector will be at different offsets from the base of the structure. To access tuple operands use the following accessors

`unsigned gimple_num_ops` (*gimple g*) [GIMPLE function]

Returns the number of operands in statement G.

`tree gimple_op` (*gimple g, unsigned i*) [GIMPLE function]

Returns operand `I` from statement `G`.

`tree * gimple_ops` (*gimple g*) [GIMPLE function]

Returns a pointer into the operand vector for statement `G`. This is computed using an internal table called `gimple_ops_offset_[]`. This table is indexed by the gimple code of `G`.

When the compiler is built, this table is filled-in using the sizes of the structures used by each statement code defined in gimple.def. Since the operand vector is at the bottom of the structure, for a gimple code `C` the offset is computed as sizeof (struct-of `C`) - sizeof (tree).

This mechanism adds one memory indirection to every access when using `gimple_op`(), if this becomes a bottleneck, a pass can choose to memoize the result from `gimple_ops`() and use that to access the operands.

11.5.7 Operand validation

When adding a new operand to a gimple statement, the operand will be validated according to what each tuple accepts in its operand vector. These predicates are called by the `gimple_`*`name`*`_set_...()`. Each tuple will use one of the following predicates (Note, this list is not exhaustive):

`bool is_gimple_val` (*tree t*) [GIMPLE function]

Returns true if t is a "GIMPLE value", which are all the non-addressable stack variables (variables for which `is_gimple_reg` returns true) and constants (expressions for which `is_gimple_min_invariant` returns true).

`bool is_gimple_addressable` (*tree t*) [GIMPLE function]

Returns true if t is a symbol or memory reference whose address can be taken.

`bool is_gimple_asm_val` (*tree t*) [GIMPLE function]
Similar to `is_gimple_val` but it also accepts hard registers.

`bool is_gimple_call_addr` (*tree t*) [GIMPLE function]
Return true if t is a valid expression to use as the function called by a `GIMPLE_CALL`.

`bool is_gimple_mem_ref_addr` (*tree t*) [GIMPLE function]
Return true if t is a valid expression to use as first operand of a `MEM_REF` expression.

`bool is_gimple_constant` (*tree t*) [GIMPLE function]
Return true if t is a valid gimple constant.

`bool is_gimple_min_invariant` (*tree t*) [GIMPLE function]
Return true if t is a valid minimal invariant. This is different from constants, in that the specific value of t may not be known at compile time, but it is known that it doesn't change (e.g., the address of a function local variable).

`bool is_gimple_ip_invariant` (*tree t*) [GIMPLE function]
Return true if t is an interprocedural invariant. This means that t is a valid invariant in all functions (e.g. it can be an address of a global variable but not of a local one).

`bool is_gimple_ip_invariant_address` (*tree t*) [GIMPLE function]
Return true if t is an `ADDR_EXPR` that does not change once the program is running (and which is valid in all functions).

11.5.8 Statement validation

`bool is_gimple_assign` (*gimple g*) [GIMPLE function]
Return true if the code of g is `GIMPLE_ASSIGN`.

`bool is_gimple_call` (*gimple g*) [GIMPLE function]
Return true if the code of g is `GIMPLE_CALL`.

`bool is_gimple_debug` (*gimple g*) [GIMPLE function]
Return true if the code of g is `GIMPLE_DEBUG`.

`bool gimple_assign_cast_p` (*const_gimple g*) [GIMPLE function]
Return true if g is a `GIMPLE_ASSIGN` that performs a type cast operation.

`bool gimple_debug_bind_p` (*gimple g*) [GIMPLE function]
Return true if g is a `GIMPLE_DEBUG` that binds the value of an expression to a variable.

`bool is_gimple_omp` (*gimple g*) [GIMPLE function]
Return true if g is any of the OpenMP codes.

11.6 Manipulating GIMPLE statements

This section documents all the functions available to handle each of the GIMPLE instructions.

11.6.1 Common accessors

The following are common accessors for gimple statements.

`enum gimple_code gimple_code` (*gimple g*) [GIMPLE function]
Return the code for statement `G`.

`basic_block gimple_bb` (*gimple g*) [GIMPLE function]
Return the basic block to which statement `G` belongs to.

`tree gimple_block` (*gimple g*) [GIMPLE function]
Return the lexical scope block holding statement `G`.

`tree gimple_expr_type` (*gimple stmt*) [GIMPLE function]
Return the type of the main expression computed by `STMT`. Return `void_type_node` if `STMT` computes nothing. This will only return something meaningful for `GIMPLE_ASSIGN`, `GIMPLE_COND` and `GIMPLE_CALL`. For all other tuple codes, it will return `void_type_node`.

`enum tree_code gimple_expr_code` (*gimple stmt*) [GIMPLE function]
Return the tree code for the expression computed by `STMT`. This is only meaningful for `GIMPLE_CALL`, `GIMPLE_ASSIGN` and `GIMPLE_COND`. If `STMT` is `GIMPLE_CALL`, it will return `CALL_EXPR`. For `GIMPLE_COND`, it returns the code of the comparison predicate. For `GIMPLE_ASSIGN` it returns the code of the operation performed by the `RHS` of the assignment.

`void gimple_set_block` (*gimple g, tree block*) [GIMPLE function]
Set the lexical scope block of `G` to `BLOCK`.

`location_t gimple_locus` (*gimple g*) [GIMPLE function]
Return locus information for statement `G`.

`void gimple_set_locus` (*gimple g, location_t locus*) [GIMPLE function]
Set locus information for statement `G`.

`bool gimple_locus_empty_p` (*gimple g*) [GIMPLE function]
Return true if `G` does not have locus information.

`bool gimple_no_warning_p` (*gimple stmt*) [GIMPLE function]
Return true if no warnings should be emitted for statement `STMT`.

`void gimple_set_visited` (*gimple stmt, bool visited_p*) [GIMPLE function]
Set the visited status on statement `STMT` to `VISITED_P`.

`bool gimple_visited_p` (*gimple stmt*) [GIMPLE function]
Return the visited status on statement `STMT`.

`void gimple_set_plf` (*gimple stmt, enum plf_mask plf, bool val_p*) [GIMPLE function]
Set pass local flag `PLF` on statement `STMT` to `VAL_P`.

`unsigned int gimple_plf` (*gimple stmt, enum plf_mask plf*) [GIMPLE function]
Return the value of pass local flag `PLF` on statement `STMT`.

`bool gimple_has_ops` (*gimple g*) [GIMPLE function]
Return true if statement `G` has register or memory operands.

`bool gimple_has_mem_ops` (*gimple g*) [GIMPLE function]
Return true if statement `G` has memory operands.

`unsigned gimple_num_ops` (*gimple g*) [GIMPLE function]
Return the number of operands for statement `G`.

`tree * gimple_ops` (*gimple g*) [GIMPLE function]
Return the array of operands for statement `G`.

`tree gimple_op` (*gimple g, unsigned i*) [GIMPLE function]
Return operand `I` for statement `G`.

`tree * gimple_op_ptr` (*gimple g, unsigned i*) [GIMPLE function]
Return a pointer to operand `I` for statement `G`.

`void gimple_set_op` (*gimple g, unsigned i, tree op*) [GIMPLE function]
Set operand `I` of statement `G` to `OP`.

`bitmap gimple_addresses_taken` (*gimple stmt*) [GIMPLE function]
Return the set of symbols that have had their address taken by `STMT`.

`struct def_optype_d * gimple_def_ops` (*gimple g*) [GIMPLE function]
Return the set of `DEF` operands for statement `G`.

`void gimple_set_def_ops` (*gimple g, struct def_optype_d *def*) [GIMPLE function]
Set `DEF` to be the set of `DEF` operands for statement `G`.

`struct use_optype_d * gimple_use_ops` (*gimple g*) [GIMPLE function]
Return the set of `USE` operands for statement `G`.

`void gimple_set_use_ops` (*gimple g, struct use_optype_d *use*) [GIMPLE function]
Set `USE` to be the set of `USE` operands for statement `G`.

`struct voptype_d * gimple_vuse_ops` (*gimple g*) [GIMPLE function]
Return the set of `VUSE` operands for statement `G`.

`void gimple_set_vuse_ops` (*gimple g, struct voptype_d *ops*) [GIMPLE function]
Set `OPS` to be the set of `VUSE` operands for statement `G`.

`struct voptype_d * gimple_vdef_ops` (*gimple g*) [GIMPLE function]
Return the set of `VDEF` operands for statement `G`.

`void gimple_set_vdef_ops` (*gimple g, struct voptype_d *ops*) [GIMPLE function]
Set `OPS` to be the set of `VDEF` operands for statement `G`.

`bitmap gimple_loaded_syms` (*gimple g*) [GIMPLE function]
Return the set of symbols loaded by statement `G`. Each element of the set is the `DECL_UID` of the corresponding symbol.

`bitmap gimple_stored_syms` (*gimple g*) [GIMPLE function]
Return the set of symbols stored by statement `G`. Each element of the set is the `DECL_UID` of the corresponding symbol.

`bool gimple_modified_p` (*gimple g*) [GIMPLE function]
Return true if statement `G` has operands and the modified field has been set.

`bool gimple_has_volatile_ops` (*gimple stmt*) [GIMPLE function]
Return true if statement `STMT` contains volatile operands.

`void gimple_set_has_volatile_ops` (*gimple stmt, bool volatilep*) [GIMPLE function]
Return true if statement `STMT` contains volatile operands.

`void update_stmt` (*gimple s*) [GIMPLE function]
Mark statement `S` as modified, and update it.

`void update_stmt_if_modified` (*gimple s*) [GIMPLE function]
Update statement `S` if it has been marked modified.

`gimple gimple_copy` (*gimple stmt*) [GIMPLE function]
Return a deep copy of statement `STMT`.

11.7 Tuple specific accessors

11.7.1 GIMPLE_ASM

`gimple gimple_build_asm` (*const char *string, ninputs, noutputs, nclobbers, ...*) [GIMPLE function]
Build a `GIMPLE_ASM` statement. This statement is used for building in-line assembly constructs. `STRING` is the assembly code. `NINPUT` is the number of register inputs. `NOUTPUT` is the number of register outputs. `NCLOBBERS` is the number of clobbered registers. The rest of the arguments trees for each input, output, and clobbered registers.

`gimple gimple_build_asm_vec` (*const char *, VEC(tree,gc) *, VEC(tree,gc) *, VEC(tree,gc) **) [GIMPLE function]
Identical to gimple_build_asm, but the arguments are passed in VECs.

`unsigned gimple_asm_ninputs` (*gimple g*) [GIMPLE function]
Return the number of input operands for `GIMPLE_ASM` `G`.

`unsigned gimple_asm_noutputs` (*gimple g*) [GIMPLE function]
Return the number of output operands for `GIMPLE_ASM` `G`.

`unsigned gimple_asm_nclobbers` (*gimple g*) [GIMPLE function]
Return the number of clobber operands for `GIMPLE_ASM` `G`.

`tree gimple_asm_input_op` (*gimple g, unsigned index*) [GIMPLE function]
Return input operand `INDEX` of `GIMPLE_ASM` `G`.

`void gimple_asm_set_input_op` (*gimple g, unsigned index, tree in_op*) [GIMPLE function]

Set `IN_OP` to be input operand `INDEX` in `GIMPLE_ASM` `G`.

`tree gimple_asm_output_op` (*gimple g, unsigned index*) [GIMPLE function]

Return output operand `INDEX` of `GIMPLE_ASM` `G`.

`void gimple_asm_set_output_op` (*gimple g, unsigned index, tree out_op*) [GIMPLE function]

Set `OUT_OP` to be output operand `INDEX` in `GIMPLE_ASM` `G`.

`tree gimple_asm_clobber_op` (*gimple g, unsigned index*) [GIMPLE function]

Return clobber operand `INDEX` of `GIMPLE_ASM` `G`.

`void gimple_asm_set_clobber_op` (*gimple g, unsigned index, tree clobber_op*) [GIMPLE function]

Set `CLOBBER_OP` to be clobber operand `INDEX` in `GIMPLE_ASM` `G`.

`const char * gimple_asm_string` (*gimple g*) [GIMPLE function]

Return the string representing the assembly instruction in `GIMPLE_ASM` `G`.

`bool gimple_asm_volatile_p` (*gimple g*) [GIMPLE function]

Return true if `G` is an asm statement marked volatile.

`void gimple_asm_set_volatile` (*gimple g*) [GIMPLE function]

Mark asm statement `G` as volatile.

11.7.2 GIMPLE_ASSIGN

`gimple gimple_build_assign` (*tree lhs, tree rhs*) [GIMPLE function]

Build a `GIMPLE_ASSIGN` statement. The left-hand side is an lvalue passed in lhs. The right-hand side can be either a unary or binary tree expression. The expression tree rhs will be flattened and its operands assigned to the corresponding operand slots in the new statement. This function is useful when you already have a tree expression that you want to convert into a tuple. However, try to avoid building expression trees for the sole purpose of calling this function. If you already have the operands in separate trees, it is better to use `gimple_build_assign_with_ops`.

`gimple gimplify_assign` (*tree dst, tree src, gimple_seq *seq_p*) [GIMPLE function]

Build a new `GIMPLE_ASSIGN` tuple and append it to the end of `*SEQ_P`.

`DST/SRC` are the destination and source respectively. You can pass ungimplified trees in `DST` or `SRC`, in which case they will be converted to a gimple operand if necessary.

This function returns the newly created `GIMPLE_ASSIGN` tuple.

`gimple gimple_build_assign_with_ops` (*enum tree_code subcode, tree lhs, tree op1, tree op2*) [GIMPLE function]

This function is similar to `gimple_build_assign`, but is used to build a `GIMPLE_ASSIGN` statement when the operands of the right-hand side of the assignment are already split into different operands.

The left-hand side is an lvalue passed in lhs. Subcode is the `tree_code` for the right-hand side of the assignment. Op1 and op2 are the operands. If op2 is null, subcode must be a `tree_code` for a unary expression.

`enum tree_code gimple_assign_rhs_code` (*gimple g*) [GIMPLE function]
Return the code of the expression computed on the `RHS` of assignment statement `G`.

`enum gimple_rhs_class gimple_assign_rhs_class` (*gimple g*) [GIMPLE function]
Return the gimple rhs class of the code for the expression computed on the rhs of assignment statement `G`. This will never return `GIMPLE_INVALID_RHS`.

`tree gimple_assign_lhs` (*gimple g*) [GIMPLE function]
Return the `LHS` of assignment statement `G`.

`tree * gimple_assign_lhs_ptr` (*gimple g*) [GIMPLE function]
Return a pointer to the `LHS` of assignment statement `G`.

`tree gimple_assign_rhs1` (*gimple g*) [GIMPLE function]
Return the first operand on the `RHS` of assignment statement `G`.

`tree * gimple_assign_rhs1_ptr` (*gimple g*) [GIMPLE function]
Return the address of the first operand on the `RHS` of assignment statement `G`.

`tree gimple_assign_rhs2` (*gimple g*) [GIMPLE function]
Return the second operand on the `RHS` of assignment statement `G`.

`tree * gimple_assign_rhs2_ptr` (*gimple g*) [GIMPLE function]
Return the address of the second operand on the `RHS` of assignment statement `G`.

`tree gimple_assign_rhs3` (*gimple g*) [GIMPLE function]
Return the third operand on the `RHS` of assignment statement `G`.

`tree * gimple_assign_rhs3_ptr` (*gimple g*) [GIMPLE function]
Return the address of the third operand on the `RHS` of assignment statement `G`.

`void gimple_assign_set_lhs` (*gimple g, tree lhs*) [GIMPLE function]
Set `LHS` to be the `LHS` operand of assignment statement `G`.

`void gimple_assign_set_rhs1` (*gimple g, tree rhs*) [GIMPLE function]
Set `RHS` to be the first operand on the `RHS` of assignment statement `G`.

`void gimple_assign_set_rhs2` (*gimple g, tree rhs*) [GIMPLE function]
Set `RHS` to be the second operand on the `RHS` of assignment statement `G`.

`void gimple_assign_set_rhs3` (*gimple g, tree rhs*) [GIMPLE function]
Set `RHS` to be the third operand on the `RHS` of assignment statement `G`.

`bool gimple_assign_cast_p` (*const_gimple s*) [GIMPLE function]
Return true if `S` is a type-cast assignment.

11.7.3 GIMPLE_BIND

`gimple gimple_build_bind` (*tree vars, gimple_seq body*) [GIMPLE function]
Build a `GIMPLE_BIND` statement with a list of variables in `VARS` and a body of statements in sequence `BODY`.

`tree gimple_bind_vars` (*gimple g*) [GIMPLE function]
Return the variables declared in the `GIMPLE_BIND` statement `G`.

`void gimple_bind_set_vars` (*gimple g, tree vars*) [GIMPLE function]
Set `VARS` to be the set of variables declared in the `GIMPLE_BIND` statement `G`.

`void gimple_bind_append_vars` (*gimple g, tree vars*) [GIMPLE function]
Append `VARS` to the set of variables declared in the `GIMPLE_BIND` statement `G`.

`gimple_seq gimple_bind_body` (*gimple g*) [GIMPLE function]
Return the GIMPLE sequence contained in the `GIMPLE_BIND` statement `G`.

`void gimple_bind_set_body` (*gimple g, gimple_seq seq*) [GIMPLE function]
Set `SEQ` to be sequence contained in the `GIMPLE_BIND` statement `G`.

`void gimple_bind_add_stmt` (*gimple gs, gimple stmt*) [GIMPLE function]
Append a statement to the end of a `GIMPLE_BIND`'s body.

`void gimple_bind_add_seq` (*gimple gs, gimple_seq seq*) [GIMPLE function]
Append a sequence of statements to the end of a `GIMPLE_BIND`'s body.

`tree gimple_bind_block` (*gimple g*) [GIMPLE function]
Return the `TREE_BLOCK` node associated with `GIMPLE_BIND` statement `G`. This is analogous to the `BIND_EXPR_BLOCK` field in trees.

`void gimple_bind_set_block` (*gimple g, tree block*) [GIMPLE function]
Set `BLOCK` to be the `TREE_BLOCK` node associated with `GIMPLE_BIND` statement `G`.

11.7.4 GIMPLE_CALL

`gimple gimple_build_call` (*tree fn, unsigned nargs, ...*) [GIMPLE function]
Build a `GIMPLE_CALL` statement to function `FN`. The argument `FN` must be either a `FUNCTION_DECL` or a gimple call address as determined by `is_gimple_call_addr`. `NARGS` are the number of arguments. The rest of the arguments follow the argument `NARGS`, and must be trees that are valid as rvalues in gimple (i.e., each operand is validated with `is_gimple_operand`).

`gimple gimple_build_call_from_tree` (*tree call_expr*) [GIMPLE function]
Build a `GIMPLE_CALL` from a `CALL_EXPR` node. The arguments and the function are taken from the expression directly. This routine assumes that `call_expr` is already in GIMPLE form. That is, its operands are GIMPLE values and the function call needs no further simplification. All the call flags in `call_expr` are copied over to the new `GIMPLE_CALL`.

`gimple gimple_build_call_vec` (*tree fn*, `VEC`(*tree*, *heap*) **args*) [GIMPLE function]

Identical to `gimple_build_call` but the arguments are stored in a `VEC`().

`tree gimple_call_lhs` (*gimple g*) [GIMPLE function]

Return the `LHS` of call statement `G`.

`tree * gimple_call_lhs_ptr` (*gimple g*) [GIMPLE function]

Return a pointer to the `LHS` of call statement `G`.

`void gimple_call_set_lhs` (*gimple g*, *tree lhs*) [GIMPLE function]

Set `LHS` to be the `LHS` operand of call statement `G`.

`tree gimple_call_fn` (*gimple g*) [GIMPLE function]

Return the tree node representing the function called by call statement `G`.

`void gimple_call_set_fn` (*gimple g*, *tree fn*) [GIMPLE function]

Set `FN` to be the function called by call statement `G`. This has to be a gimple value specifying the address of the called function.

`tree gimple_call_fndecl` (*gimple g*) [GIMPLE function]

If a given `GIMPLE_CALL`'s callee is a `FUNCTION_DECL`, return it. Otherwise return `NULL`. This function is analogous to `get_callee_fndecl` in `GENERIC`.

`tree gimple_call_set_fndecl` (*gimple g*, *tree fndecl*) [GIMPLE function]

Set the called function to `FNDECL`.

`tree gimple_call_return_type` (*gimple g*) [GIMPLE function]

Return the type returned by call statement `G`.

`tree gimple_call_chain` (*gimple g*) [GIMPLE function]

Return the static chain for call statement `G`.

`void gimple_call_set_chain` (*gimple g*, *tree chain*) [GIMPLE function]

Set `CHAIN` to be the static chain for call statement `G`.

`unsigned gimple_call_num_args` (*gimple g*) [GIMPLE function]

Return the number of arguments used by call statement `G`.

`tree gimple_call_arg` (*gimple g*, *unsigned index*) [GIMPLE function]

Return the argument at position `INDEX` for call statement `G`. The first argument is 0.

`tree * gimple_call_arg_ptr` (*gimple g*, *unsigned index*) [GIMPLE function]

Return a pointer to the argument at position `INDEX` for call statement `G`.

`void gimple_call_set_arg` (*gimple g*, *unsigned index*, *tree arg*) [GIMPLE function]

Set `ARG` to be the argument at position `INDEX` for call statement `G`.

`void gimple_call_set_tail` (*gimple s*) [GIMPLE function]

Mark call statement `S` as being a tail call (i.e., a call just before the exit of a function). These calls are candidate for tail call optimization.

`bool gimple_call_tail_p` (*gimple s*) [GIMPLE function]
Return true if `GIMPLE_CALL` `S` is marked as a tail call.

`void gimple_call_mark_uninlinable` (*gimple s*) [GIMPLE function]
Mark `GIMPLE_CALL` `S` as being uninlinable.

`bool gimple_call_cannot_inline_p` (*gimple s*) [GIMPLE function]
Return true if `GIMPLE_CALL` `S` cannot be inlined.

`bool gimple_call_noreturn_p` (*gimple s*) [GIMPLE function]
Return true if `S` is a noreturn call.

`gimple gimple_call_copy_skip_args` (*gimple stmt, bitmap args_to_skip*) [GIMPLE function]
Build a `GIMPLE_CALL` identical to `STMT` but skipping the arguments in the positions marked by the set `ARGS_TO_SKIP`.

11.7.5 GIMPLE_CATCH

`gimple gimple_build_catch` (*tree types, gimple_seq handler*) [GIMPLE function]
Build a `GIMPLE_CATCH` statement. `TYPES` are the tree types this catch handles. `HANDLER` is a sequence of statements with the code for the handler.

`tree gimple_catch_types` (*gimple g*) [GIMPLE function]
Return the types handled by `GIMPLE_CATCH` statement `G`.

`tree * gimple_catch_types_ptr` (*gimple g*) [GIMPLE function]
Return a pointer to the types handled by `GIMPLE_CATCH` statement `G`.

`gimple_seq gimple_catch_handler` (*gimple g*) [GIMPLE function]
Return the GIMPLE sequence representing the body of the handler of `GIMPLE_CATCH` statement `G`.

`void gimple_catch_set_types` (*gimple g, tree t*) [GIMPLE function]
Set `T` to be the set of types handled by `GIMPLE_CATCH` `G`.

`void gimple_catch_set_handler` (*gimple g, gimple_seq handler*) [GIMPLE function]
Set `HANDLER` to be the body of `GIMPLE_CATCH` `G`.

11.7.6 GIMPLE_COND

`gimple gimple_build_cond` (*enum tree_code pred_code, tree lhs, tree rhs, tree t_label, tree f_label*) [GIMPLE function]
Build a `GIMPLE_COND` statement. `A GIMPLE_COND` statement compares `LHS` and `RHS` and if the condition in `PRED_CODE` is true, jump to the label in `t_label`, otherwise jump to the label in `f_label`. `PRED_CODE` are relational operator tree codes like `EQ_EXPR`, `LT_EXPR`, `LE_EXPR`, `NE_EXPR`, etc.

`gimple gimple_build_cond_from_tree` (*tree cond, tree t_label, tree f_label*) [GIMPLE function]
Build a `GIMPLE_COND` statement from the conditional expression tree `COND`. `T_LABEL` and `F_LABEL` are as in `gimple_build_cond`.

`enum tree_code gimple_cond_code` (*gimple g*) [GIMPLE function]
Return the code of the predicate computed by conditional statement `G`.

`void gimple_cond_set_code` (*gimple g, enum tree_code code*) [GIMPLE function]
Set `CODE` to be the predicate code for the conditional statement `G`.

`tree gimple_cond_lhs` (*gimple g*) [GIMPLE function]
Return the `LHS` of the predicate computed by conditional statement `G`.

`void gimple_cond_set_lhs` (*gimple g, tree lhs*) [GIMPLE function]
Set `LHS` to be the `LHS` operand of the predicate computed by conditional statement `G`.

`tree gimple_cond_rhs` (*gimple g*) [GIMPLE function]
Return the `RHS` operand of the predicate computed by conditional `G`.

`void gimple_cond_set_rhs` (*gimple g, tree rhs*) [GIMPLE function]
Set `RHS` to be the `RHS` operand of the predicate computed by conditional statement `G`.

`tree gimple_cond_true_label` (*gimple g*) [GIMPLE function]
Return the label used by conditional statement `G` when its predicate evaluates to true.

`void gimple_cond_set_true_label` (*gimple g, tree label*) [GIMPLE function]
Set `LABEL` to be the label used by conditional statement `G` when its predicate evaluates to true.

`void gimple_cond_set_false_label` (*gimple g, tree label*) [GIMPLE function]
Set `LABEL` to be the label used by conditional statement `G` when its predicate evaluates to false.

`tree gimple_cond_false_label` (*gimple g*) [GIMPLE function]
Return the label used by conditional statement `G` when its predicate evaluates to false.

`void gimple_cond_make_false` (*gimple g*) [GIMPLE function]
Set the conditional `COND_STMT` to be of the form 'if (1 == 0)'.

`void gimple_cond_make_true` (*gimple g*) [GIMPLE function]
Set the conditional `COND_STMT` to be of the form 'if (1 == 1)'.

11.7.7 GIMPLE_DEBUG

`gimple gimple_build_debug_bind` (*tree var, tree value, gimple stmt*) [GIMPLE function]
Build a `GIMPLE_DEBUG` statement with `GIMPLE_DEBUG_BIND` of `subcode`. The effect of this statement is to tell debug information generation machinery that the value of user variable `var` is given by `value` at that point, and to remain with that value until `var` runs out of scope, a dynamically-subsequent debug bind statement overrides the binding, or conflicting values reach a control flow merge point. Even if components of the `value` expression change afterwards, the variable is supposed to retain the same value, though not necessarily the same location.

It is expected that `var` be most often a tree for automatic user variables (`VAR_DECL` or `PARM_DECL`) that satisfy the requirements for gimple registers, but it may also be

a tree for a scalarized component of a user variable (ARRAY_REF, COMPONENT_REF), or a debug temporary (DEBUG_EXPR_DECL).

As for value, it can be an arbitrary tree expression, but it is recommended that it be in a suitable form for a gimple assignment RHS. It is not expected that user variables that could appear as var ever appear in value, because in the latter we'd have their SSA_NAMEs instead, but even if they were not in SSA form, user variables appearing in value are to be regarded as part of the executable code space, whereas those in var are to be regarded as part of the source code space. There is no way to refer to the value bound to a user variable within a value expression.

If value is GIMPLE_DEBUG_BIND_NOVALUE, debug information generation machinery is informed that the variable var is unbound, i.e., that its value is indeterminate, which sometimes means it is really unavailable, and other times that the compiler could not keep track of it.

Block and location information for the newly-created stmt are taken from stmt, if given.

tree gimple_debug_bind_get_var (*gimple stmt*) [GIMPLE function]
Return the user variable *var* that is bound at stmt.

tree gimple_debug_bind_get_value (*gimple stmt*) [GIMPLE function]
Return the value expression that is bound to a user variable at stmt.

tree * gimple_debug_bind_get_value_ptr (*gimple stmt*) [GIMPLE function]
Return a pointer to the value expression that is bound to a user variable at stmt.

void gimple_debug_bind_set_var (*gimple stmt, tree var*) [GIMPLE function]
Modify the user variable bound at stmt to *var*.

void gimple_debug_bind_set_value (*gimple stmt, tree var*) [GIMPLE function]
Modify the value bound to the user variable bound at stmt to *value*.

void gimple_debug_bind_reset_value (*gimple stmt*) [GIMPLE function]
Modify the value bound to the user variable bound at stmt so that the variable becomes unbound.

bool gimple_debug_bind_has_value_p (*gimple stmt*) [GIMPLE function]
Return TRUE if stmt binds a user variable to a value, and FALSE if it unbinds the variable.

11.7.8 GIMPLE_EH_FILTER

gimple gimple_build_eh_filter (*tree types, gimple_seq failure*) [GIMPLE function]
Build a GIMPLE_EH_FILTER statement. TYPES are the filter's types. FAILURE is a sequence with the filter's failure action.

tree gimple_eh_filter_types (*gimple g*) [GIMPLE function]
Return the types handled by GIMPLE_EH_FILTER statement G.

`tree * gimple_eh_filter_types_ptr` (*gimple g*) [GIMPLE function]
Return a pointer to the types handled by `GIMPLE_EH_FILTER` statement `G`.

`gimple_seq gimple_eh_filter_failure` (*gimple g*) [GIMPLE function]
Return the sequence of statement to execute when `GIMPLE_EH_FILTER` statement fails.

`void gimple_eh_filter_set_types` (*gimple g, tree types*) [GIMPLE function]
Set `TYPES` to be the set of types handled by `GIMPLE_EH_FILTER` `G`.

`void gimple_eh_filter_set_failure` (*gimple g, gimple_seq failure*) [GIMPLE function]
Set `FAILURE` to be the sequence of statements to execute on failure for `GIMPLE_EH_FILTER` `G`.

`bool gimple_eh_filter_must_not_throw` (*gimple g*) [GIMPLE function]
Return the `EH_FILTER_MUST_NOT_THROW` flag.

`void gimple_eh_filter_set_must_not_throw` (*gimple g, bool mntp*) [GIMPLE function]
Set the `EH_FILTER_MUST_NOT_THROW` flag.

11.7.9 GIMPLE_LABEL

`gimple gimple_build_label` (*tree label*) [GIMPLE function]
Build a `GIMPLE_LABEL` statement with corresponding to the tree label, `LABEL`.

`tree gimple_label_label` (*gimple g*) [GIMPLE function]
Return the `LABEL_DECL` node used by `GIMPLE_LABEL` statement `G`.

`void gimple_label_set_label` (*gimple g, tree label*) [GIMPLE function]
Set `LABEL` to be the `LABEL_DECL` node used by `GIMPLE_LABEL` statement `G`.

`gimple gimple_build_goto` (*tree dest*) [GIMPLE function]
Build a `GIMPLE_GOTO` statement to label `DEST`.

`tree gimple_goto_dest` (*gimple g*) [GIMPLE function]
Return the destination of the unconditional jump `G`.

`void gimple_goto_set_dest` (*gimple g, tree dest*) [GIMPLE function]
Set `DEST` to be the destination of the unconditional jump `G`.

11.7.10 GIMPLE_NOP

`gimple gimple_build_nop` (*void*) [GIMPLE function]
Build a `GIMPLE_NOP` statement.

`bool gimple_nop_p` (*gimple g*) [GIMPLE function]
Returns `TRUE` if statement `G` is a `GIMPLE_NOP`.

11.7.11 GIMPLE_OMP_ATOMIC_LOAD

`gimple gimple_build_omp_atomic_load` (*tree lhs, tree rhs*) [GIMPLE function]
Build a `GIMPLE_OMP_ATOMIC_LOAD` statement. `LHS` is the left-hand side of the assignment. `RHS` is the right-hand side of the assignment.

`void gimple_omp_atomic_load_set_lhs` (*gimple g, tree lhs*) [GIMPLE function]
Set the `LHS` of an atomic load.

`tree gimple_omp_atomic_load_lhs` (*gimple g*) [GIMPLE function]
Get the `LHS` of an atomic load.

`void gimple_omp_atomic_load_set_rhs` (*gimple g, tree rhs*) [GIMPLE function]
Set the `RHS` of an atomic set.

`tree gimple_omp_atomic_load_rhs` (*gimple g*) [GIMPLE function]
Get the `RHS` of an atomic set.

11.7.12 GIMPLE_OMP_ATOMIC_STORE

`gimple gimple_build_omp_atomic_store` (*tree val*) [GIMPLE function]
Build a `GIMPLE_OMP_ATOMIC_STORE` statement. `VAL` is the value to be stored.

`void gimple_omp_atomic_store_set_val` (*gimple g, tree val*) [GIMPLE function]
Set the value being stored in an atomic store.

`tree gimple_omp_atomic_store_val` (*gimple g*) [GIMPLE function]
Return the value being stored in an atomic store.

11.7.13 GIMPLE_OMP_CONTINUE

`gimple gimple_build_omp_continue` (*tree control_def, tree control_use*) [GIMPLE function]
Build a `GIMPLE_OMP_CONTINUE` statement. `CONTROL_DEF` is the definition of the control variable. `CONTROL_USE` is the use of the control variable.

`tree gimple_omp_continue_control_def` (*gimple s*) [GIMPLE function]
Return the definition of the control variable on a `GIMPLE_OMP_CONTINUE` in `S`.

`tree gimple_omp_continue_control_def_ptr` (*gimple s*) [GIMPLE function]
Same as above, but return the pointer.

`tree gimple_omp_continue_set_control_def` (*gimple s*) [GIMPLE function]
Set the control variable definition for a `GIMPLE_OMP_CONTINUE` statement in `S`.

`tree gimple_omp_continue_control_use` (*gimple s*) [GIMPLE function]
Return the use of the control variable on a `GIMPLE_OMP_CONTINUE` in `S`.

`tree gimple_omp_continue_control_use_ptr` (*gimple s*) [GIMPLE function]
Same as above, but return the pointer.

`tree gimple_omp_continue_set_control_use` (*gimple s*) [GIMPLE function]
Set the control variable use for a `GIMPLE_OMP_CONTINUE` statement in `S`.

11.7.14 GIMPLE_OMP_CRITICAL

`gimple gimple_build_omp_critical` (*gimple_seq body, tree name*) [GIMPLE function]

Build a `GIMPLE_OMP_CRITICAL` statement. `BODY` is the sequence of statements for which only one thread can execute. `NAME` is an optional identifier for this critical block.

`tree gimple_omp_critical_name` (*gimple g*) [GIMPLE function]

Return the name associated with `OMP_CRITICAL` statement `G`.

`tree * gimple_omp_critical_name_ptr` (*gimple g*) [GIMPLE function]

Return a pointer to the name associated with `OMP` critical statement `G`.

`void gimple_omp_critical_set_name` (*gimple g, tree name*) [GIMPLE function]

Set `NAME` to be the name associated with `OMP` critical statement `G`.

11.7.15 GIMPLE_OMP_FOR

`gimple gimple_build_omp_for` (*gimple_seq body, tree clauses, tree index, tree initial, tree final, tree incr, gimple_seq pre_body, enum tree_code omp_for_cond*) [GIMPLE function]

Build a `GIMPLE_OMP_FOR` statement. `BODY` is sequence of statements inside the for loop. `CLAUSES`, are any of the `OMP` loop construct's clauses: private, firstprivate, lastprivate, reductions, ordered, schedule, and nowait. `PRE_BODY` is the sequence of statements that are loop invariant. `INDEX` is the index variable. `INITIAL` is the initial value of `INDEX`. `FINAL` is final value of `INDEX`. OMP_FOR_COND is the predicate used to compare `INDEX` and `FINAL`. `INCR` is the increment expression.

`tree gimple_omp_for_clauses` (*gimple g*) [GIMPLE function]

Return the clauses associated with `OMP_FOR` `G`.

`tree * gimple_omp_for_clauses_ptr` (*gimple g*) [GIMPLE function]

Return a pointer to the `OMP_FOR` `G`.

`void gimple_omp_for_set_clauses` (*gimple g, tree clauses*) [GIMPLE function]

Set `CLAUSES` to be the list of clauses associated with `OMP_FOR` `G`.

`tree gimple_omp_for_index` (*gimple g*) [GIMPLE function]

Return the index variable for `OMP_FOR` `G`.

`tree * gimple_omp_for_index_ptr` (*gimple g*) [GIMPLE function]

Return a pointer to the index variable for `OMP_FOR` `G`.

`void gimple_omp_for_set_index` (*gimple g, tree index*) [GIMPLE function]

Set `INDEX` to be the index variable for `OMP_FOR` `G`.

`tree gimple_omp_for_initial` (*gimple g*) [GIMPLE function]

Return the initial value for `OMP_FOR` `G`.

`tree * gimple_omp_for_initial_ptr` (*gimple g*) [GIMPLE function]

Return a pointer to the initial value for `OMP_FOR` `G`.

`void gimple_omp_for_set_initial` (*gimple g, tree initial*) [GIMPLE function]
Set `INITIAL` to be the initial value for `OMP_FOR` `G`.

`tree gimple_omp_for_final` (*gimple g*) [GIMPLE function]
Return the final value for `OMP_FOR` `G`.

`tree * gimple_omp_for_final_ptr` (*gimple g*) [GIMPLE function]
turn a pointer to the final value for `OMP_FOR` `G`.

`void gimple_omp_for_set_final` (*gimple g, tree final*) [GIMPLE function]
Set `FINAL` to be the final value for `OMP_FOR` `G`.

`tree gimple_omp_for_incr` (*gimple g*) [GIMPLE function]
Return the increment value for `OMP_FOR` `G`.

`tree * gimple_omp_for_incr_ptr` (*gimple g*) [GIMPLE function]
Return a pointer to the increment value for `OMP_FOR` `G`.

`void gimple_omp_for_set_incr` (*gimple g, tree incr*) [GIMPLE function]
Set `INCR` to be the increment value for `OMP_FOR` `G`.

`gimple_seq gimple_omp_for_pre_body` (*gimple g*) [GIMPLE function]
Return the sequence of statements to execute before the `OMP_FOR` statement `G` starts.

`void gimple_omp_for_set_pre_body` (*gimple g, gimple_seq pre_body*) [GIMPLE function]
Set `PRE_BODY` to be the sequence of statements to execute before the `OMP_FOR` statement `G` starts.

`void gimple_omp_for_set_cond` (*gimple g, enum tree_code cond*) [GIMPLE function]
Set `COND` to be the condition code for `OMP_FOR` `G`.

`enum tree_code gimple_omp_for_cond` (*gimple g*) [GIMPLE function]
Return the condition code associated with `OMP_FOR` `G`.

11.7.16 GIMPLE_OMP_MASTER

`gimple gimple_build_omp_master` (*gimple_seq body*) [GIMPLE function]
Build a `GIMPLE_OMP_MASTER` statement. `BODY` is the sequence of statements to be executed by just the master.

11.7.17 GIMPLE_OMP_ORDERED

`gimple gimple_build_omp_ordered` (*gimple_seq body*) [GIMPLE function]
Build a `GIMPLE_OMP_ORDERED` statement.

`BODY` is the sequence of statements inside a loop that will executed in sequence.

11.7.18 GIMPLE_OMP_PARALLEL

`gimple gimple_build_omp_parallel` (*gimple_seq body, tree clauses, tree child_fn, tree data_arg*) [GIMPLE function]

Build a `GIMPLE_OMP_PARALLEL` statement.

`BODY` is sequence of statements which are executed in parallel. `CLAUSES`, are the `OMP` parallel construct's clauses. `CHILD_FN` is the function created for the parallel threads to execute. `DATA_ARG` are the shared data argument(s).

`bool gimple_omp_parallel_combined_p` (*gimple g*) [GIMPLE function]

Return true if `OMP` parallel statement `G` has the `GF_OMP_PARALLEL_COMBINED` flag set.

`void gimple_omp_parallel_set_combined_p` (*gimple g*) [GIMPLE function]

Set the `GF_OMP_PARALLEL_COMBINED` field in `OMP` parallel statement `G`.

`gimple_seq gimple_omp_body` (*gimple g*) [GIMPLE function]

Return the body for the `OMP` statement `G`.

`void gimple_omp_set_body` (*gimple g, gimple_seq body*) [GIMPLE function]

Set `BODY` to be the body for the `OMP` statement `G`.

`tree gimple_omp_parallel_clauses` (*gimple g*) [GIMPLE function]

Return the clauses associated with `OMP_PARALLEL G`.

`tree * gimple_omp_parallel_clauses_ptr` (*gimple g*) [GIMPLE function]

Return a pointer to the clauses associated with `OMP_PARALLEL G`.

`void gimple_omp_parallel_set_clauses` (*gimple g, tree clauses*) [GIMPLE function]

Set `CLAUSES` to be the list of clauses associated with `OMP_PARALLEL G`.

`tree gimple_omp_parallel_child_fn` (*gimple g*) [GIMPLE function]

Return the child function used to hold the body of `OMP_PARALLEL G`.

`tree * gimple_omp_parallel_child_fn_ptr` (*gimple g*) [GIMPLE function]

Return a pointer to the child function used to hold the body of `OMP_PARALLEL G`.

`void gimple_omp_parallel_set_child_fn` (*gimple g, tree child_fn*) [GIMPLE function]

Set `CHILD_FN` to be the child function for `OMP_PARALLEL G`.

`tree gimple_omp_parallel_data_arg` (*gimple g*) [GIMPLE function]

Return the artificial argument used to send variables and values from the parent to the children threads in `OMP_PARALLEL G`.

`tree * gimple_omp_parallel_data_arg_ptr` (*gimple g*) [GIMPLE function]

Return a pointer to the data argument for `OMP_PARALLEL G`.

`void gimple_omp_parallel_set_data_arg` (*gimple g, tree data_arg*) [GIMPLE function]

Set `DATA_ARG` to be the data argument for `OMP_PARALLEL G`.

11.7.19 GIMPLE_OMP_RETURN

`gimple gimple_build_omp_return` (*bool wait_p*) [GIMPLE function]
Build a `GIMPLE_OMP_RETURN` statement. `WAIT_P` is true if this is a non-waiting return.

`void gimple_omp_return_set_nowait` (*gimple s*) [GIMPLE function]
Set the nowait flag on `GIMPLE_OMP_RETURN` statement `S`.

`bool gimple_omp_return_nowait_p` (*gimple g*) [GIMPLE function]
Return true if `OMP` return statement `G` has the `GF_OMP_RETURN_NOWAIT` flag set.

11.7.20 GIMPLE_OMP_SECTION

`gimple gimple_build_omp_section` (*gimple_seq body*) [GIMPLE function]
Build a `GIMPLE_OMP_SECTION` statement for a sections statement.

`BODY` is the sequence of statements in the section.

`bool gimple_omp_section_last_p` (*gimple g*) [GIMPLE function]
Return true if `OMP` section statement `G` has the `GF_OMP_SECTION_LAST` flag set.

`void gimple_omp_section_set_last` (*gimple g*) [GIMPLE function]
Set the `GF_OMP_SECTION_LAST` flag on `G`.

11.7.21 GIMPLE_OMP_SECTIONS

`gimple gimple_build_omp_sections` (*gimple_seq body, tree clauses*) [GIMPLE function]
Build a `GIMPLE_OMP_SECTIONS` statement. `BODY` is a sequence of section statements. `CLAUSES` are any of the `OMP` sections construct's clauses: private, firstprivate, lastprivate, reduction, and nowait.

`gimple gimple_build_omp_sections_switch` (*void*) [GIMPLE function]
Build a `GIMPLE_OMP_SECTIONS_SWITCH` statement.

`tree gimple_omp_sections_control` (*gimple g*) [GIMPLE function]
Return the control variable associated with the `GIMPLE_OMP_SECTIONS` in `G`.

`tree * gimple_omp_sections_control_ptr` (*gimple g*) [GIMPLE function]
Return a pointer to the clauses associated with the `GIMPLE_OMP_SECTIONS` in `G`.

`void gimple_omp_sections_set_control` (*gimple g, tree control*) [GIMPLE function]
Set `CONTROL` to be the set of clauses associated with the `GIMPLE_OMP_SECTIONS` in `G`.

`tree gimple_omp_sections_clauses` (*gimple g*) [GIMPLE function]
Return the clauses associated with `OMP_SECTIONS` `G`.

`tree * gimple_omp_sections_clauses_ptr` (*gimple g*) [GIMPLE function]
Return a pointer to the clauses associated with `OMP_SECTIONS` `G`.

`void gimple_omp_sections_set_clauses` (*gimple g, tree clauses*) [GIMPLE function]
Set `CLAUSES` to be the set of clauses associated with `OMP_SECTIONS` `G`.

11.7.22 GIMPLE_OMP_SINGLE

`gimple gimple_build_omp_single` (*gimple_seq body, tree clauses*) [GIMPLE function]

Build a `GIMPLE_OMP_SINGLE` statement. `BODY` is the sequence of statements that will be executed once. `CLAUSES` are any of the `OMP` single construct's clauses: private, firstprivate, copyprivate, nowait.

`tree gimple_omp_single_clauses` (*gimple g*) [GIMPLE function]

Return the clauses associated with `OMP_SINGLE G`.

`tree * gimple_omp_single_clauses_ptr` (*gimple g*) [GIMPLE function]

Return a pointer to the clauses associated with `OMP_SINGLE G`.

`void gimple_omp_single_set_clauses` (*gimple g, tree clauses*) [GIMPLE function]

Set `CLAUSES` to be the clauses associated with `OMP_SINGLE G`.

11.7.23 GIMPLE_PHI

`unsigned gimple_phi_capacity` (*gimple g*) [GIMPLE function]

Return the maximum number of arguments supported by `GIMPLE_PHI G`.

`unsigned gimple_phi_num_args` (*gimple g*) [GIMPLE function]

Return the number of arguments in `GIMPLE_PHI G`. This must always be exactly the number of incoming edges for the basic block holding `G`.

`tree gimple_phi_result` (*gimple g*) [GIMPLE function]

Return the `SSA` name created by `GIMPLE_PHI G`.

`tree * gimple_phi_result_ptr` (*gimple g*) [GIMPLE function]

Return a pointer to the `SSA` name created by `GIMPLE_PHI G`.

`void gimple_phi_set_result` (*gimple g, tree result*) [GIMPLE function]

Set `RESULT` to be the `SSA` name created by `GIMPLE_PHI G`.

`struct phi_arg_d * gimple_phi_arg` (*gimple g, index*) [GIMPLE function]

Return the `PHI` argument corresponding to incoming edge `INDEX` for `GIMPLE_PHI G`.

`void gimple_phi_set_arg` (*gimple g, index, struct phi_arg_d * phiarg*) [GIMPLE function]

Set `PHIARG` to be the argument corresponding to incoming edge `INDEX` for `GIMPLE_PHI G`.

11.7.24 GIMPLE_RESX

`gimple gimple_build_resx` (*int region*) [GIMPLE function]

Build a `GIMPLE_RESX` statement which is a statement. This statement is a placeholder for _Unwind_Resume before we know if a function call or a branch is needed. `REGION` is the exception region from which control is flowing.

`int gimple_resx_region` (*gimple g*) [GIMPLE function]
Return the region number for `GIMPLE_RESX` `G`.

`void gimple_resx_set_region` (*gimple g, int region*) [GIMPLE function]
Set `REGION` to be the region number for `GIMPLE_RESX` `G`.

11.7.25 GIMPLE_RETURN

`gimple gimple_build_return` (*tree retval*) [GIMPLE function]
Build a `GIMPLE_RETURN` statement whose return value is retval.

`tree gimple_return_retval` (*gimple g*) [GIMPLE function]
Return the return value for `GIMPLE_RETURN` `G`.

`void gimple_return_set_retval` (*gimple g, tree retval*) [GIMPLE function]
Set `RETVAL` to be the return value for `GIMPLE_RETURN` `G`.

11.7.26 GIMPLE_SWITCH

`gimple gimple_build_switch` (*tree index, tree default_label,* `VEC`(*tree,heap*) **args*) [GIMPLE function]
Build a `GIMPLE_SWITCH` statement. `INDEX` is the index variable to switch on, and `DEFAULT_LABEL` represents the default label. `ARGS` is a vector of `CASE_LABEL_EXPR` trees that contain the non-default case labels. Each label is a tree of code `CASE_LABEL_EXPR`.

`unsigned gimple_switch_num_labels` (*gimple g*) [GIMPLE function]
Return the number of labels associated with the switch statement `G`.

`void gimple_switch_set_num_labels` (*gimple g, unsigned nlabels*) [GIMPLE function]
Set `NLABELS` to be the number of labels for the switch statement `G`.

`tree gimple_switch_index` (*gimple g*) [GIMPLE function]
Return the index variable used by the switch statement `G`.

`void gimple_switch_set_index` (*gimple g, tree index*) [GIMPLE function]
Set `INDEX` to be the index variable for switch statement `G`.

`tree gimple_switch_label` (*gimple g, unsigned index*) [GIMPLE function]
Return the label numbered `INDEX`. The default label is 0, followed by any labels in a switch statement.

`void gimple_switch_set_label` (*gimple g, unsigned index, tree label*) [GIMPLE function]
Set the label number `INDEX` to `LABEL`. 0 is always the default label.

`tree gimple_switch_default_label` (*gimple g*) [GIMPLE function]
Return the default label for a switch statement.

`void gimple_switch_set_default_label` (*gimple g, tree label*) [GIMPLE function]
Set the default label for a switch statement.

11.7.27 GIMPLE_TRY

`gimple gimple_build_try` (*gimple_seq eval, gimple_seq cleanup, unsigned int kind*) [GIMPLE function]

Build a `GIMPLE_TRY` statement. `EVAL` is a sequence with the expression to evaluate. `CLEANUP` is a sequence of statements to run at clean-up time. `KIND` is the enumeration value `GIMPLE_TRY_CATCH` if this statement denotes a try/catch construct or `GIMPLE_TRY_FINALLY` if this statement denotes a try/finally construct.

`enum gimple_try_flags gimple_try_kind` (*gimple g*) [GIMPLE function]

Return the kind of try block represented by `GIMPLE_TRY G`. This is either `GIMPLE_TRY_CATCH` or `GIMPLE_TRY_FINALLY`.

`bool gimple_try_catch_is_cleanup` (*gimple g*) [GIMPLE function]

Return the `GIMPLE_TRY_CATCH_IS_CLEANUP` flag.

`gimple_seq gimple_try_eval` (*gimple g*) [GIMPLE function]

Return the sequence of statements used as the body for `GIMPLE_TRY G`.

`gimple_seq gimple_try_cleanup` (*gimple g*) [GIMPLE function]

Return the sequence of statements used as the cleanup body for `GIMPLE_TRY G`.

`void gimple_try_set_catch_is_cleanup` (*gimple g, bool catch_is_cleanup*) [GIMPLE function]

Set the `GIMPLE_TRY_CATCH_IS_CLEANUP` flag.

`void gimple_try_set_eval` (*gimple g, gimple_seq eval*) [GIMPLE function]

Set `EVAL` to be the sequence of statements to use as the body for `GIMPLE_TRY G`.

`void gimple_try_set_cleanup` (*gimple g, gimple_seq cleanup*) [GIMPLE function]

Set `CLEANUP` to be the sequence of statements to use as the cleanup body for `GIMPLE_TRY G`.

11.7.28 GIMPLE_WITH_CLEANUP_EXPR

`gimple gimple_build_wce` (*gimple_seq cleanup*) [GIMPLE function]

Build a `GIMPLE_WITH_CLEANUP_EXPR` statement. `CLEANUP` is the clean-up expression.

`gimple_seq gimple_wce_cleanup` (*gimple g*) [GIMPLE function]

Return the cleanup sequence for cleanup statement `G`.

`void gimple_wce_set_cleanup` (*gimple g, gimple_seq cleanup*) [GIMPLE function]

Set `CLEANUP` to be the cleanup sequence for `G`.

`bool gimple_wce_cleanup_eh_only` (*gimple g*) [GIMPLE function]

Return the `CLEANUP_EH_ONLY` flag for a `WCE` tuple.

`void gimple_wce_set_cleanup_eh_only` (*gimple g, bool eh_only_p*) [GIMPLE function]

Set the `CLEANUP_EH_ONLY` flag for a `WCE` tuple.

11.8 GIMPLE sequences

GIMPLE sequences are the tuple equivalent of `STATEMENT_LIST`'s used in `GENERIC`. They are used to chain statements together, and when used in conjunction with sequence iterators, provide a framework for iterating through statements.

GIMPLE sequences are of type struct `gimple_sequence`, but are more commonly passed by reference to functions dealing with sequences. The type for a sequence pointer is `gimple_seq` which is the same as struct `gimple_sequence` *. When declaring a local sequence, you can define a local variable of type struct `gimple_sequence`. When declaring a sequence allocated on the garbage collected heap, use the function `gimple_seq_alloc` documented below.

There are convenience functions for iterating through sequences in the section entitled Sequence Iterators.

Below is a list of functions to manipulate and query sequences.

`void gimple_seq_add_stmt` (*gimple_seq *seq, gimple g*) [GIMPLE function]
Link a gimple statement to the end of the sequence *`SEQ` if `G` is not `NULL`. If *`SEQ` is `NULL`, allocate a sequence before linking.

`void gimple_seq_add_seq` (*gimple_seq *dest, gimple_seq src*) [GIMPLE function]
Append sequence `SRC` to the end of sequence *`DEST` if `SRC` is not `NULL`. If *`DEST` is `NULL`, allocate a new sequence before appending.

`gimple_seq gimple_seq_deep_copy` (*gimple_seq src*) [GIMPLE function]
Perform a deep copy of sequence `SRC` and return the result.

`gimple_seq gimple_seq_reverse` (*gimple_seq seq*) [GIMPLE function]
Reverse the order of the statements in the sequence `SEQ`. Return `SEQ`.

`gimple gimple_seq_first` (*gimple_seq s*) [GIMPLE function]
Return the first statement in sequence `S`.

`gimple gimple_seq_last` (*gimple_seq s*) [GIMPLE function]
Return the last statement in sequence `S`.

`void gimple_seq_set_last` (*gimple_seq s, gimple last*) [GIMPLE function]
Set the last statement in sequence `S` to the statement in `LAST`.

`void gimple_seq_set_first` (*gimple_seq s, gimple first*) [GIMPLE function]
Set the first statement in sequence `S` to the statement in `FIRST`.

`void gimple_seq_init` (*gimple_seq s*) [GIMPLE function]
Initialize sequence `S` to an empty sequence.

`gimple_seq gimple_seq_alloc` (*void*) [GIMPLE function]
Allocate a new sequence in the garbage collected store and return it.

`void gimple_seq_copy` (*gimple_seq dest, gimple_seq src*) [GIMPLE function]
Copy the sequence `SRC` into the sequence `DEST`.

`bool gimple_seq_empty_p` (*gimple_seq s*) [GIMPLE function]
Return true if the sequence `S` is empty.

`gimple_seq bb_seq` (*basic_block bb*) [GIMPLE function]
Returns the sequence of statements in `BB`.

`void set_bb_seq` (*basic_block bb, gimple_seq seq*) [GIMPLE function]
Sets the sequence of statements in `BB` to `SEQ`.

`bool gimple_seq_singleton_p` (*gimple_seq seq*) [GIMPLE function]
Determine whether `SEQ` contains exactly one statement.

11.9 Sequence iterators

Sequence iterators are convenience constructs for iterating through statements in a sequence. Given a sequence `SEQ`, here is a typical use of gimple sequence iterators:

```
gimple_stmt_iterator gsi;

for (gsi = gsi_start (seq); !gsi_end_p (gsi); gsi_next (&gsi))
  {
    gimple g = gsi_stmt (gsi);
    /* Do something with gimple statement G.  */
  }
```

Backward iterations are possible:

```
for (gsi = gsi_last (seq); !gsi_end_p (gsi); gsi_prev (&gsi))
```

Forward and backward iterations on basic blocks are possible with `gsi_start_bb` and `gsi_last_bb`.

In the documentation below we sometimes refer to enum `gsi_iterator_update`. The valid options for this enumeration are:

- `GSI_NEW_STMT` Only valid when a single statement is added. Move the iterator to it.
- `GSI_SAME_STMT` Leave the iterator at the same statement.
- `GSI_CONTINUE_LINKING` Move iterator to whatever position is suitable for linking other statements in the same direction.

Below is a list of the functions used to manipulate and use statement iterators.

`gimple_stmt_iterator gsi_start` (*gimple_seq seq*) [GIMPLE function]
Return a new iterator pointing to the sequence `SEQ`'s first statement. If `SEQ` is empty, the iterator's basic block is `NULL`. Use `gsi_start_bb` instead when the iterator needs to always have the correct basic block set.

`gimple_stmt_iterator gsi_start_bb` (*basic_block bb*) [GIMPLE function]
Return a new iterator pointing to the first statement in basic block `BB`.

`gimple_stmt_iterator gsi_last` (*gimple_seq seq*) [GIMPLE function]
Return a new iterator initially pointing to the last statement of sequence `SEQ`. If `SEQ` is empty, the iterator's basic block is `NULL`. Use `gsi_last_bb` instead when the iterator needs to always have the correct basic block set.

`gimple_stmt_iterator gsi_last_bb` (*basic_block bb*) [GIMPLE function]
Return a new iterator pointing to the last statement in basic block `BB`.

`bool gsi_end_p` (*gimple_stmt_iterator i*) [GIMPLE function]
Return `TRUE` if at the end of `I`.

`bool gsi_one_before_end_p` (*gimple_stmt_iterator i*) [GIMPLE function]
Return `TRUE` if we're one statement before the end of `I`.

`void gsi_next` (*gimple_stmt_iterator *i*) [GIMPLE function]
Advance the iterator to the next gimple statement.

`void gsi_prev` (*gimple_stmt_iterator *i*) [GIMPLE function]
Advance the iterator to the previous gimple statement.

`gimple gsi_stmt` (*gimple_stmt_iterator i*) [GIMPLE function]
Return the current stmt.

`gimple_stmt_iterator gsi_after_labels` (*basic_block bb*) [GIMPLE function]
Return a block statement iterator that points to the first non-label statement in block `BB`.

`gimple * gsi_stmt_ptr` (*gimple_stmt_iterator *i*) [GIMPLE function]
Return a pointer to the current stmt.

`basic_block gsi_bb` (*gimple_stmt_iterator i*) [GIMPLE function]
Return the basic block associated with this iterator.

`gimple_seq gsi_seq` (*gimple_stmt_iterator i*) [GIMPLE function]
Return the sequence associated with this iterator.

`void gsi_remove` (*gimple_stmt_iterator *i, bool remove_eh_info*) [GIMPLE function]
Remove the current stmt from the sequence. The iterator is updated to point to the next statement. When `REMOVE_EH_INFO` is true we remove the statement pointed to by iterator `I` from the `EH` tables. Otherwise we do not modify the `EH` tables. Generally, `REMOVE_EH_INFO` should be true when the statement is going to be removed from the `IL` and not reinserted elsewhere.

`void gsi_link_seq_before` (*gimple_stmt_iterator *i, gimple_seq seq, enum gsi_iterator_update mode*) [GIMPLE function]
Links the sequence of statements `SEQ` before the statement pointed by iterator `I`. `MODE` indicates what to do with the iterator after insertion (see `enum gsi_iterator_update` above).

`void gsi_link_before` (*gimple_stmt_iterator *i, gimple g, enum gsi_iterator_update mode*) [GIMPLE function]
Links statement `G` before the statement pointed-to by iterator `I`. Updates iterator `I` according to `MODE`.

`void gsi_link_seq_after` (*gimple_stmt_iterator *i, gimple_seq seq, enum gsi_iterator_update mode*) [GIMPLE function]
Links sequence `SEQ` after the statement pointed-to by iterator `I`. `MODE` is as in `gsi_insert_after`.

`void gsi_link_after` (*gimple_stmt_iterator *i, gimple g, enum gsi_iterator_update mode*) [GIMPLE function]

Links statement `G` after the statement pointed-to by iterator `I`. `MODE` is as in `gsi_insert_after`.

`gimple_seq gsi_split_seq_after` (*gimple_stmt_iterator i*) [GIMPLE function]

Move all statements in the sequence after `I` to a new sequence. Return this new sequence.

`gimple_seq gsi_split_seq_before` (*gimple_stmt_iterator *i*) [GIMPLE function]

Move all statements in the sequence before `I` to a new sequence. Return this new sequence.

`void gsi_replace` (*gimple_stmt_iterator *i, gimple stmt, bool update_eh_info*) [GIMPLE function]

Replace the statement pointed-to by `I` to `STMT`. If `UPDATE_EH_INFO` is true, the exception handling information of the original statement is moved to the new statement.

`void gsi_insert_before` (*gimple_stmt_iterator *i, gimple stmt, enum gsi_iterator_update mode*) [GIMPLE function]

Insert statement `STMT` before the statement pointed-to by iterator `I`, update `STMT`'s basic block and scan it for new operands. `MODE` specifies how to update iterator `I` after insertion (see enum `gsi_iterator_update`).

`void gsi_insert_seq_before` (*gimple_stmt_iterator *i, gimple_seq seq, enum gsi_iterator_update mode*) [GIMPLE function]

Like `gsi_insert_before`, but for all the statements in `SEQ`.

`void gsi_insert_after` (*gimple_stmt_iterator *i, gimple stmt, enum gsi_iterator_update mode*) [GIMPLE function]

Insert statement `STMT` after the statement pointed-to by iterator `I`, update `STMT`'s basic block and scan it for new operands. `MODE` specifies how to update iterator `I` after insertion (see enum `gsi_iterator_update`).

`void gsi_insert_seq_after` (*gimple_stmt_iterator *i, gimple_seq seq, enum gsi_iterator_update mode*) [GIMPLE function]

Like `gsi_insert_after`, but for all the statements in `SEQ`.

`gimple_stmt_iterator gsi_for_stmt` (*gimple stmt*) [GIMPLE function]

Finds iterator for `STMT`.

`void gsi_move_after` (*gimple_stmt_iterator *from, gimple_stmt_iterator *to*) [GIMPLE function]

Move the statement at `FROM` so it comes right after the statement at `TO`.

`void gsi_move_before` (*gimple_stmt_iterator *from, gimple_stmt_iterator *to*) [GIMPLE function]

Move the statement at `FROM` so it comes right before the statement at `TO`.

`void gsi_move_to_bb_end` (*gimple_stmt_iterator *from, basic_block bb*) [GIMPLE function]

Move the statement at `FROM` to the end of basic block `BB`.

`void gsi_insert_on_edge` (*edge e, gimple stmt*) [GIMPLE function]

Add `STMT` to the pending list of edge `E`. No actual insertion is made until a call to `gsi_commit_edge_inserts`() is made.

`void gsi_insert_seq_on_edge` (*edge e, gimple_seq seq*) [GIMPLE function]

Add the sequence of statements in `SEQ` to the pending list of edge `E`. No actual insertion is made until a call to `gsi_commit_edge_inserts`() is made.

`basic_block gsi_insert_on_edge_immediate` (*edge e, gimple stmt*) [GIMPLE function]

Similar to `gsi_insert_on_edge+gsi_commit_edge_inserts`. If a new block has to be created, it is returned.

`void gsi_commit_one_edge_insert` (*edge e, basic_block *new_bb*) [GIMPLE function]

Commit insertions pending at edge `E`. If a new block is created, set `NEW_BB` to this block, otherwise set it to `NULL`.

`void gsi_commit_edge_inserts` (*void*) [GIMPLE function]

This routine will commit all pending edge insertions, creating any new basic blocks which are necessary.

11.10 Adding a new GIMPLE statement code

The first step in adding a new GIMPLE statement code, is modifying the file `gimple.def`, which contains all the GIMPLE codes. Then you must add a corresponding structure, and an entry in `union gimple_statement_d`, both of which are located in `gimple.h`. This in turn, will require you to add a corresponding `GTY` tag in `gsstruct.def`, and code to handle this tag in `gss_for_code` which is located in `gimple.c`.

In order for the garbage collector to know the size of the structure you created in `gimple.h`, you need to add a case to handle your new GIMPLE statement in `gimple_size` which is located in `gimple.c`.

You will probably want to create a function to build the new gimple statement in `gimple.c`. The function should be called `gimple_build_`*`new-tuple-name`*, and should return the new tuple of type gimple.

If your new statement requires accessors for any members or operands it may have, put simple inline accessors in `gimple.h` and any non-trivial accessors in `gimple.c` with a corresponding prototype in `gimple.h`.

11.11 Statement and operand traversals

There are two functions available for walking statements and sequences: `walk_gimple_stmt` and `walk_gimple_seq`, accordingly, and a third function for walking the operands in a statement: `walk_gimple_op`.

`tree walk_gimple_stmt` (*gimple_stmt_iterator *gsi, walk_stmt_fn callback_stmt, walk_tree_fn callback_op, struct walk_stmt_info *wi*) [GIMPLE function]

This function is used to walk the current statement in `GSI`, optionally using traversal state stored in `WI`. If `WI` is `NULL`, no state is kept during the traversal.

The callback `CALLBACK_STMT` is called. If `CALLBACK_STMT` returns true, it means that the callback function has handled all the operands of the statement and it is not necessary to walk its operands.

If `CALLBACK_STMT` is `NULL` or it returns false, `CALLBACK_OP` is called on each operand of the statement via `walk_gimple_op`. If `walk_gimple_op` returns non-`NULL` for any operand, the remaining operands are not scanned.

The return value is that returned by the last call to `walk_gimple_op`, or `NULL_TREE` if no `CALLBACK_OP` is specified.

`tree walk_gimple_op` (*gimple stmt, walk_tree_fn callback_op, struct walk_stmt_info *wi*) [GIMPLE function]

Use this function to walk the operands of statement `STMT`. Every operand is walked via `walk_tree` with optional state information in `WI`.

`CALLBACK_OP` is called on each operand of `STMT` via `walk_tree`. Additional parameters to `walk_tree` must be stored in `WI`. For each operand `OP`, `walk_tree` is called as:

```
walk_tree (&OP, CALLBACK_OP, WI, PSET)
```

If `CALLBACK_OP` returns non-`NULL` for an operand, the remaining operands are not scanned. The return value is that returned by the last call to `walk_tree`, or `NULL_TREE` if no `CALLBACK_OP` is specified.

`tree walk_gimple_seq` (*gimple_seq seq, walk_stmt_fn callback_stmt, walk_tree_fn callback_op, struct walk_stmt_info *wi*) [GIMPLE function]

This function walks all the statements in the sequence `SEQ` calling `walk_gimple_stmt` on each one. `WI` is as in `walk_gimple_stmt`. If `walk_gimple_stmt` returns non-`NULL`, the walk is stopped and the value returned. Otherwise, all the statements are walked and `NULL_TREE` returned.

12 Analysis and Optimization of GIMPLE tuples

GCC uses three main intermediate languages to represent the program during compilation: GENERIC, GIMPLE and RTL. GENERIC is a language-independent representation generated by each front end. It is used to serve as an interface between the parser and optimizer. GENERIC is a common representation that is able to represent programs written in all the languages supported by GCC.

GIMPLE and RTL are used to optimize the program. GIMPLE is used for target and language independent optimizations (e.g., inlining, constant propagation, tail call elimination, redundancy elimination, etc). Much like GENERIC, GIMPLE is a language independent, tree based representation. However, it differs from GENERIC in that the GIMPLE grammar is more restrictive: expressions contain no more than 3 operands (except function calls), it has no control flow structures and expressions with side-effects are only allowed on the right hand side of assignments. See the chapter describing GENERIC and GIMPLE for more details.

This chapter describes the data structures and functions used in the GIMPLE optimizers (also known as "tree optimizers" or "middle end"). In particular, it focuses on all the macros, data structures, functions and programming constructs needed to implement optimization passes for GIMPLE.

12.1 Annotations

The optimizers need to associate attributes with variables during the optimization process. For instance, we need to know whether a variable has aliases. All these attributes are stored in data structures called annotations which are then linked to the field `ann` in `struct tree_common`.

12.2 SSA Operands

Almost every GIMPLE statement will contain a reference to a variable or memory location. Since statements come in different shapes and sizes, their operands are going to be located at various spots inside the statement's tree. To facilitate access to the statement's operands, they are organized into lists associated inside each statement's annotation. Each element in an operand list is a pointer to a `VAR_DECL`, `PARM_DECL` or `SSA_NAME` tree node. This provides a very convenient way of examining and replacing operands.

Data flow analysis and optimization is done on all tree nodes representing variables. Any node for which `SSA_VAR_P` returns nonzero is considered when scanning statement operands. However, not all `SSA_VAR_P` variables are processed in the same way. For the purposes of optimization, we need to distinguish between references to local scalar variables and references to globals, statics, structures, arrays, aliased variables, etc. The reason is simple, the compiler can gather complete data flow information for a local scalar. On the other hand, a global variable may be modified by a function call, it may not be possible to keep track of all the elements of an array or the fields of a structure, etc.

The operand scanner gathers two kinds of operands: *real* and *virtual*. An operand for which `is_gimple_reg` returns true is considered real, otherwise it is a virtual operand. We also distinguish between uses and definitions. An operand is used if its value is loaded by the statement (e.g., the operand at the RHS of an assignment). If the statement assigns a

new value to the operand, the operand is considered a definition (e.g., the operand at the LHS of an assignment).

Virtual and real operands also have very different data flow properties. Real operands are unambiguous references to the full object that they represent. For instance, given

```
{
  int a, b;
  a = b
}
```

Since `a` and `b` are non-aliased locals, the statement `a = b` will have one real definition and one real use because variable `a` is completely modified with the contents of variable `b`. Real definition are also known as *killing definitions*. Similarly, the use of `b` reads all its bits.

In contrast, virtual operands are used with variables that can have a partial or ambiguous reference. This includes structures, arrays, globals, and aliased variables. In these cases, we have two types of definitions. For globals, structures, and arrays, we can determine from a statement whether a variable of these types has a killing definition. If the variable does, then the statement is marked as having a *must definition* of that variable. However, if a statement is only defining a part of the variable (i.e. a field in a structure), or if we know that a statement might define the variable but we cannot say for sure, then we mark that statement as having a *may definition*. For instance, given

```
{
  int a, b, *p;

  if (...)
    p = &a;
  else
    p = &b;
  *p = 5;
  return *p;
}
```

The assignment `*p = 5` may be a definition of `a` or `b`. If we cannot determine statically where `p` is pointing to at the time of the store operation, we create virtual definitions to mark that statement as a potential definition site for `a` and `b`. Memory loads are similarly marked with virtual use operands. Virtual operands are shown in tree dumps right before the statement that contains them. To request a tree dump with virtual operands, use the '`-vops`' option to '`-fdump-tree`':

```
{
  int a, b, *p;

  if (...)
    p = &a;
  else
    p = &b;
  # a = VDEF <a>
  # b = VDEF <b>
  *p = 5;

  # VUSE <a>
  # VUSE <b>
  return *p;
}
```

Notice that VDEF operands have two copies of the referenced variable. This indicates that this is not a killing definition of that variable. In this case we refer to it as a *may definition* or *aliased store*. The presence of the second copy of the variable in the VDEF operand will become important when the function is converted into SSA form. This will be used to link all the non-killing definitions to prevent optimizations from making incorrect assumptions about them.

Operands are updated as soon as the statement is finished via a call to update_stmt. If statement elements are changed via SET_USE or SET_DEF, then no further action is required (i.e., those macros take care of updating the statement). If changes are made by manipulating the statement's tree directly, then a call must be made to update_stmt when complete. Calling one of the bsi_insert routines or bsi_replace performs an implicit call to update_stmt.

12.2.1 Operand Iterators And Access Routines

Operands are collected by 'tree-ssa-operands.c'. They are stored inside each statement's annotation and can be accessed through either the operand iterators or an access routine.

The following access routines are available for examining operands:

1. SINGLE_SSA_{USE,DEF,TREE}_OPERAND: These accessors will return NULL unless there is exactly one operand matching the specified flags. If there is exactly one operand, the operand is returned as either a tree, def_operand_p, or use_operand_p.

```
tree t = SINGLE_SSA_TREE_OPERAND (stmt, flags);
use_operand_p u = SINGLE_SSA_USE_OPERAND (stmt, SSA_ALL_VIRTUAL_USES);
def_operand_p d = SINGLE_SSA_DEF_OPERAND (stmt, SSA_OP_ALL_DEFS);
```

2. ZERO_SSA_OPERANDS: This macro returns true if there are no operands matching the specified flags.

```
if (ZERO_SSA_OPERANDS (stmt, SSA_OP_ALL_VIRTUALS))
  return;
```

3. NUM_SSA_OPERANDS: This macro Returns the number of operands matching 'flags'. This actually executes a loop to perform the count, so only use this if it is really needed.

```
int count = NUM_SSA_OPERANDS (stmt, flags)
```

If you wish to iterate over some or all operands, use the FOR_EACH_SSA_{USE,DEF,TREE}_OPERAND iterator. For example, to print all the operands for a statement:

```
void
print_ops (tree stmt)
{
  ssa_op_iter;
  tree var;

  FOR_EACH_SSA_TREE_OPERAND (var, stmt, iter, SSA_OP_ALL_OPERANDS)
    print_generic_expr (stderr, var, TDF_SLIM);
}
```

How to choose the appropriate iterator:

1. Determine whether you are need to see the operand pointers, or just the trees, and choose the appropriate macro:

```
Need            Macro:
----            -------
use_operand_p   FOR_EACH_SSA_USE_OPERAND
```

```
def_operand_p   FOR_EACH_SSA_DEF_OPERAND
tree            FOR_EACH_SSA_TREE_OPERAND
```

2. You need to declare a variable of the type you are interested in, and an ssa_op_iter structure which serves as the loop controlling variable.
3. Determine which operands you wish to use, and specify the flags of those you are interested in. They are documented in '`tree-ssa-operands.h`':

```
#define SSA_OP_USE              0x01    /* Real USE operands.   */
#define SSA_OP_DEF              0x02    /* Real DEF operands.   */
#define SSA_OP_VUSE             0x04    /* VUSE operands.   */
#define SSA_OP_VDEF             0x08    /* VDEF operands.   */

/* These are commonly grouped operand flags.   */
#define SSA_OP_VIRTUAL_USES (SSA_OP_VUSE)
#define SSA_OP_VIRTUAL_DEFS (SSA_OP_VDEF)
#define SSA_OP_ALL_VIRTUALS     (SSA_OP_VIRTUAL_USES | SSA_OP_VIRTUAL_DEFS)
#define SSA_OP_ALL_USES (SSA_OP_VIRTUAL_USES | SSA_OP_USE)
#define SSA_OP_ALL_DEFS (SSA_OP_VIRTUAL_DEFS | SSA_OP_DEF)
#define SSA_OP_ALL_OPERANDS (SSA_OP_ALL_USES | SSA_OP_ALL_DEFS)
```

So if you want to look at the use pointers for all the `USE` and `VUSE` operands, you would do something like:

```
use_operand_p use_p;
ssa_op_iter iter;

FOR_EACH_SSA_USE_OPERAND (use_p, stmt, iter, (SSA_OP_USE | SSA_OP_VUSE))
  {
    process_use_ptr (use_p);
  }
```

The `TREE` macro is basically the same as the `USE` and `DEF` macros, only with the use or def dereferenced via `USE_FROM_PTR (use_p)` and `DEF_FROM_PTR (def_p)`. Since we aren't using operand pointers, use and defs flags can be mixed.

```
tree var;
ssa_op_iter iter;

FOR_EACH_SSA_TREE_OPERAND (var, stmt, iter, SSA_OP_VUSE)
  {
     print_generic_expr (stderr, var, TDF_SLIM);
  }
```

`VDEF`s are broken into two flags, one for the `DEF` portion (`SSA_OP_VDEF`) and one for the USE portion (`SSA_OP_VUSE`).

There are many examples in the code, in addition to the documentation in '`tree-ssa-operands.h`' and '`ssa-iterators.h`'.

There are also a couple of variants on the stmt iterators regarding PHI nodes.

`FOR_EACH_PHI_ARG` Works exactly like `FOR_EACH_SSA_USE_OPERAND`, except it works over `PHI` arguments instead of statement operands.

```
/* Look at every virtual PHI use.  */
FOR_EACH_PHI_ARG (use_p, phi_stmt, iter, SSA_OP_VIRTUAL_USES)
{
   my_code;
}

/* Look at every real PHI use.  */
```

```
FOR_EACH_PHI_ARG (use_p, phi_stmt, iter, SSA_OP_USES)
  my_code;

/* Look at every PHI use.  */
FOR_EACH_PHI_ARG (use_p, phi_stmt, iter, SSA_OP_ALL_USES)
  my_code;
```

FOR_EACH_PHI_OR_STMT_{USE,DEF} works exactly like FOR_EACH_SSA_{USE,DEF}_OPERAND, except it will function on either a statement or a PHI node. These should be used when it is appropriate but they are not quite as efficient as the individual FOR_EACH_PHI and FOR_EACH_SSA routines.

```
FOR_EACH_PHI_OR_STMT_USE (use_operand_p, stmt, iter, flags)
  {
     my_code;
  }

FOR_EACH_PHI_OR_STMT_DEF (def_operand_p, phi, iter, flags)
  {
     my_code;
  }
```

12.2.2 Immediate Uses

Immediate use information is now always available. Using the immediate use iterators, you may examine every use of any SSA_NAME. For instance, to change each use of ssa_var to ssa_var2 and call fold_stmt on each stmt after that is done:

```
use_operand_p imm_use_p;
imm_use_iterator iterator;
tree ssa_var, stmt;


FOR_EACH_IMM_USE_STMT (stmt, iterator, ssa_var)
  {
    FOR_EACH_IMM_USE_ON_STMT (imm_use_p, iterator)
      SET_USE (imm_use_p, ssa_var_2);
    fold_stmt (stmt);
  }
```

There are 2 iterators which can be used. FOR_EACH_IMM_USE_FAST is used when the immediate uses are not changed, i.e., you are looking at the uses, but not setting them.

If they do get changed, then care must be taken that things are not changed under the iterators, so use the FOR_EACH_IMM_USE_STMT and FOR_EACH_IMM_USE_ON_STMT iterators. They attempt to preserve the sanity of the use list by moving all the uses for a statement into a controlled position, and then iterating over those uses. Then the optimization can manipulate the stmt when all the uses have been processed. This is a little slower than the FAST version since it adds a placeholder element and must sort through the list a bit for each statement. This placeholder element must be also be removed if the loop is terminated early. The macro BREAK_FROM_IMM_USE_SAFE is provided to do this :

```
FOR_EACH_IMM_USE_STMT (stmt, iterator, ssa_var)
  {
    if (stmt == last_stmt)
      BREAK_FROM_SAFE_IMM_USE (iter);

    FOR_EACH_IMM_USE_ON_STMT (imm_use_p, iterator)
      SET_USE (imm_use_p, ssa_var_2);
```

```
    fold_stmt (stmt);
  }
```

There are checks in `verify_ssa` which verify that the immediate use list is up to date, as well as checking that an optimization didn't break from the loop without using this macro. It is safe to simply 'break'; from a `FOR_EACH_IMM_USE_FAST` traverse.

Some useful functions and macros:

1. `has_zero_uses (ssa_var)` : Returns true if there are no uses of `ssa_var`.
2. `has_single_use (ssa_var)` : Returns true if there is only a single use of `ssa_var`.
3. `single_imm_use (ssa_var, use_operand_p *ptr, tree *stmt)` : Returns true if there is only a single use of `ssa_var`, and also returns the use pointer and statement it occurs in, in the second and third parameters.
4. `num_imm_uses (ssa_var)` : Returns the number of immediate uses of `ssa_var`. It is better not to use this if possible since it simply utilizes a loop to count the uses.
5. `PHI_ARG_INDEX_FROM_USE (use_p)` : Given a use within a `PHI` node, return the index number for the use. An assert is triggered if the use isn't located in a `PHI` node.
6. `USE_STMT (use_p)` : Return the statement a use occurs in.

Note that uses are not put into an immediate use list until their statement is actually inserted into the instruction stream via a `bsi_*` routine.

It is also still possible to utilize lazy updating of statements, but this should be used only when absolutely required. Both alias analysis and the dominator optimizations currently do this.

When lazy updating is being used, the immediate use information is out of date and cannot be used reliably. Lazy updating is achieved by simply marking statements modified via calls to `mark_stmt_modified` instead of `update_stmt`. When lazy updating is no longer required, all the modified statements must have `update_stmt` called in order to bring them up to date. This must be done before the optimization is finished, or `verify_ssa` will trigger an abort.

This is done with a simple loop over the instruction stream:

```
block_stmt_iterator bsi;
basic_block bb;
FOR_EACH_BB (bb)
  {
    for (bsi = bsi_start (bb); !bsi_end_p (bsi); bsi_next (&bsi))
      update_stmt_if_modified (bsi_stmt (bsi));
  }
```

12.3 Static Single Assignment

Most of the tree optimizers rely on the data flow information provided by the Static Single Assignment (SSA) form. We implement the SSA form as described in *R. Cytron, J. Ferrante, B. Rosen, M. Wegman, and K. Zadeck. Efficiently Computing Static Single Assignment Form and the Control Dependence Graph. ACM Transactions on Programming Languages and Systems, 13(4):451-490, October 1991.*

The SSA form is based on the premise that program variables are assigned in exactly one location in the program. Multiple assignments to the same variable create new versions of that variable. Naturally, actual programs are seldom in SSA form initially because variables

tend to be assigned multiple times. The compiler modifies the program representation so that every time a variable is assigned in the code, a new version of the variable is created. Different versions of the same variable are distinguished by subscripting the variable name with its version number. Variables used in the right-hand side of expressions are renamed so that their version number matches that of the most recent assignment.

We represent variable versions using `SSA_NAME` nodes. The renaming process in '`tree-ssa.c`' wraps every real and virtual operand with an `SSA_NAME` node which contains the version number and the statement that created the `SSA_NAME`. Only definitions and virtual definitions may create new `SSA_NAME` nodes.

Sometimes, flow of control makes it impossible to determine the most recent version of a variable. In these cases, the compiler inserts an artificial definition for that variable called *PHI function* or *PHI node*. This new definition merges all the incoming versions of the variable to create a new name for it. For instance,

```
if (...)
  a_1 = 5;
else if (...)
  a_2 = 2;
else
  a_3 = 13;

# a_4 = PHI <a_1, a_2, a_3>
return a_4;
```

Since it is not possible to determine which of the three branches will be taken at runtime, we don't know which of `a_1`, `a_2` or `a_3` to use at the return statement. So, the SSA renamer creates a new version `a_4` which is assigned the result of "merging" `a_1`, `a_2` and `a_3`. Hence, PHI nodes mean "one of these operands. I don't know which".

The following functions can be used to examine PHI nodes

`gimple_phi_result` (*phi*) [Function]

Returns the `SSA_NAME` created by PHI node *phi* (i.e., *phi*'s LHS).

`gimple_phi_num_args` (*phi*) [Function]

Returns the number of arguments in *phi*. This number is exactly the number of incoming edges to the basic block holding *phi*.

`gimple_phi_arg` (*phi*, *i*) [Function]

Returns *i*th argument of *phi*.

`gimple_phi_arg_edge` (*phi*, *i*) [Function]

Returns the incoming edge for the *i*th argument of *phi*.

`gimple_phi_arg_def` (*phi*, *i*) [Function]

Returns the `SSA_NAME` for the *i*th argument of *phi*.

12.3.1 Preserving the SSA form

Some optimization passes make changes to the function that invalidate the SSA property. This can happen when a pass has added new symbols or changed the program so that variables that were previously aliased aren't anymore. Whenever something like this happens,

the affected symbols must be renamed into SSA form again. Transformations that emit new code or replicate existing statements will also need to update the SSA form.

Since GCC implements two different SSA forms for register and virtual variables, keeping the SSA form up to date depends on whether you are updating register or virtual names. In both cases, the general idea behind incremental SSA updates is similar: when new SSA names are created, they typically are meant to replace other existing names in the program.

For instance, given the following code:

```
1  L0:
2  x_1 = PHI (0, x_5)
3  if (x_1 < 10)
4    if (x_1 > 7)
5      y_2 = 0
6    else
7      y_3 = x_1 + x_7
8    endif
9    x_5 = x_1 + 1
10   goto L0;
11 endif
```

Suppose that we insert new names `x_10` and `x_11` (lines `4` and `8`).

```
1  L0:
2  x_1 = PHI (0, x_5)
3  if (x_1 < 10)
4    x_10 = ...
5    if (x_1 > 7)
6      y_2 = 0
7    else
8      x_11 = ...
9      y_3 = x_1 + x_7
10   endif
11   x_5 = x_1 + 1
12   goto L0;
13 endif
```

We want to replace all the uses of `x_1` with the new definitions of `x_10` and `x_11`. Note that the only uses that should be replaced are those at lines `5`, `9` and `11`. Also, the use of `x_7` at line `9` should *not* be replaced (this is why we cannot just mark symbol `x` for renaming).

Additionally, we may need to insert a PHI node at line `11` because that is a merge point for `x_10` and `x_11`. So the use of `x_1` at line `11` will be replaced with the new PHI node. The insertion of PHI nodes is optional. They are not strictly necessary to preserve the SSA form, and depending on what the caller inserted, they may not even be useful for the optimizers.

Updating the SSA form is a two step process. First, the pass has to identify which names need to be updated and/or which symbols need to be renamed into SSA form for the first time. When new names are introduced to replace existing names in the program, the mapping between the old and the new names are registered by calling `register_new_name_mapping` (note that if your pass creates new code by duplicating basic blocks, the call to `tree_duplicate_bb` will set up the necessary mappings automatically).

After the replacement mappings have been registered and new symbols marked for renaming, a call to `update_ssa` makes the registered changes. This can be done with an explicit call or by creating `TODO` flags in the `tree_opt_pass` structure for your pass. There are several `TODO` flags that control the behavior of `update_ssa`:

- `TODO_update_ssa`. Update the SSA form inserting PHI nodes for newly exposed symbols and virtual names marked for updating. When updating real names, only insert PHI nodes for a real name `O_j` in blocks reached by all the new and old definitions for `O_j`. If the iterated dominance frontier for `O_j` is not pruned, we may end up inserting PHI nodes in blocks that have one or more edges with no incoming definition for `O_j`. This would lead to uninitialized warnings for `O_j`'s symbol.
- `TODO_update_ssa_no_phi`. Update the SSA form without inserting any new PHI nodes at all. This is used by passes that have either inserted all the PHI nodes themselves or passes that need only to patch use-def and def-def chains for virtuals (e.g., DCE).
- `TODO_update_ssa_full_phi`. Insert PHI nodes everywhere they are needed. No pruning of the IDF is done. This is used by passes that need the PHI nodes for `O_j` even if it means that some arguments will come from the default definition of `O_j`'s symbol (e.g., `pass_linear_transform`).

  WARNING: If you need to use this flag, chances are that your pass may be doing something wrong. Inserting PHI nodes for an old name where not all edges carry a new replacement may lead to silent codegen errors or spurious uninitialized warnings.
- `TODO_update_ssa_only_virtuals`. Passes that update the SSA form on their own may want to delegate the updating of virtual names to the generic updater. Since FUD chains are easier to maintain, this simplifies the work they need to do. NOTE: If this flag is used, any OLD->NEW mappings for real names are explicitly destroyed and only the symbols marked for renaming are processed.

12.3.2 Preserving the virtual SSA form

The virtual SSA form is harder to preserve than the non-virtual SSA form mainly because the set of virtual operands for a statement may change at what some would consider unexpected times. In general, statement modifications should be bracketed between calls to `push_stmt_changes` and `pop_stmt_changes`. For example,

```
munge_stmt (tree stmt)
{
   push_stmt_changes (&stmt);
   ... rewrite STMT ...
   pop_stmt_changes (&stmt);
}
```

The call to `push_stmt_changes` saves the current state of the statement operands and the call to `pop_stmt_changes` compares the saved state with the current one and does the appropriate symbol marking for the SSA renamer.

It is possible to modify several statements at a time, provided that `push_stmt_changes` and `pop_stmt_changes` are called in LIFO order, as when processing a stack of statements.

Additionally, if the pass discovers that it did not need to make changes to the statement after calling `push_stmt_changes`, it can simply discard the topmost change buffer by calling `discard_stmt_changes`. This will avoid the expensive operand re-scan operation and the buffer comparison that determines if symbols need to be marked for renaming.

12.3.3 Examining `SSA_NAME` nodes

The following macros can be used to examine `SSA_NAME` nodes

`SSA_NAME_DEF_STMT (var)` [Macro]

Returns the statement *s* that creates the `SSA_NAME` *var*. If *s* is an empty statement (i.e., `IS_EMPTY_STMT (s)` returns `true`), it means that the first reference to this variable is a USE or a VUSE.

`SSA_NAME_VERSION (var)` [Macro]

Returns the version number of the `SSA_NAME` object *var*.

12.3.4 Walking the dominator tree

`void walk_dominator_tree (walk_data, bb)` [Tree SSA function]

This function walks the dominator tree for the current CFG calling a set of callback functions defined in *struct dom_walk_data* in '`domwalk.h`'. The call back functions you need to define give you hooks to execute custom code at various points during traversal:

1. Once to initialize any local data needed while processing *bb* and its children. This local data is pushed into an internal stack which is automatically pushed and popped as the walker traverses the dominator tree.
2. Once before traversing all the statements in the *bb*.
3. Once for every statement inside *bb*.
4. Once after traversing all the statements and before recursing into *bb*'s dominator children.
5. It then recurses into all the dominator children of *bb*.
6. After recursing into all the dominator children of *bb* it can, optionally, traverse every statement in *bb* again (i.e., repeating steps 2 and 3).
7. Once after walking the statements in *bb* and *bb*'s dominator children. At this stage, the block local data stack is popped.

12.4 Alias analysis

Alias analysis in GIMPLE SSA form consists of two pieces. First the virtual SSA web ties conflicting memory accesses and provides a SSA use-def chain and SSA immediate-use chains for walking possibly dependent memory accesses. Second an alias-oracle can be queried to disambiguate explicit and implicit memory references.

1. Memory SSA form.

   All statements that may use memory have exactly one accompanied use of a virtual SSA name that represents the state of memory at the given point in the IL.

   All statements that may define memory have exactly one accompanied definition of a virtual SSA name using the previous state of memory and defining the new state of memory after the given point in the IL.

```
int i;
int foo (void)
{
  # .MEM_3 = VDEF <.MEM_2(D)>
  i = 1;
  # VUSE <.MEM_3>
  return i;
```

```
}
```

The virtual SSA names in this case are `.MEM_2(D)` and `.MEM_3`. The store to the global variable `i` defines `.MEM_3` invalidating `.MEM_2(D)`. The load from `i` uses that new state `.MEM_3`.

The virtual SSA web serves as constraints to SSA optimizers preventing illegitimate code-motion and optimization. It also provides a way to walk related memory statements.

2. Points-to and escape analysis.

   Points-to analysis builds a set of constraints from the GIMPLE SSA IL representing all pointer operations and facts we do or do not know about pointers. Solving this set of constraints yields a conservatively correct solution for each pointer variable in the program (though we are only interested in SSA name pointers) as to what it may possibly point to.

   This points-to solution for a given SSA name pointer is stored in the `pt_solution` sub-structure of the `SSA_NAME_PTR_INFO` record. The following accessor functions are available:

   - `pt_solution_includes`
   - `pt_solutions_intersect`

   Points-to analysis also computes the solution for two special set of pointers, `ESCAPED` and `CALLUSED`. Those represent all memory that has escaped the scope of analysis or that is used by pure or nested const calls.

3. Type-based alias analysis

   Type-based alias analysis is frontend dependent though generic support is provided by the middle-end in `alias.c`. TBAA code is used by both tree optimizers and RTL optimizers.

   Every language that wishes to perform language-specific alias analysis should define a function that computes, given a `tree` node, an alias set for the node. Nodes in different alias sets are not allowed to alias. For an example, see the C front-end function `c_get_alias_set`.

4. Tree alias-oracle

   The tree alias-oracle provides means to disambiguate two memory references and memory references against statements. The following queries are available:

   - `refs_may_alias_p`
   - `ref_maybe_used_by_stmt_p`
   - `stmt_may_clobber_ref_p`

   In addition to those two kind of statement walkers are available walking statements related to a reference ref. `walk_non_aliased_vuses` walks over dominating memory defining statements and calls back if the statement does not clobber ref providing the non-aliased VUSE. The walk stops at the first clobbering statement or if asked to. `walk_aliased_vdefs` walks over dominating memory defining statements and calls back on each statement clobbering ref providing its aliasing VDEF. The walk stops if asked to.

12.5 Memory model

The memory model used by the middle-end models that of the C/C++ languages. The middle-end has the notion of an effective type of a memory region which is used for type-based alias analysis.

The following is a refinement of ISO C99 6.5/6, clarifying the block copy case to follow common sense and extending the concept of a dynamic effective type to objects with a declared type as required for C++.

```
The effective type of an object for an access to its stored value is
the declared type of the object or the effective type determined by
a previous store to it.  If a value is stored into an object through
an lvalue having a type that is not a character type, then the
type of the lvalue becomes the effective type of the object for that
access and for subsequent accesses that do not modify the stored value.
If a value is copied into an object using memcpy or memmove,
or is copied as an array of character type, then the effective type
of the modified object for that access and for subsequent accesses that
do not modify the value is undetermined.  For all other accesses to an
object, the effective type of the object is simply the type of the
lvalue used for the access.
```

13 RTL Representation

The last part of the compiler work is done on a low-level intermediate representation called Register Transfer Language. In this language, the instructions to be output are described, pretty much one by one, in an algebraic form that describes what the instruction does.

RTL is inspired by Lisp lists. It has both an internal form, made up of structures that point at other structures, and a textual form that is used in the machine description and in printed debugging dumps. The textual form uses nested parentheses to indicate the pointers in the internal form.

13.1 RTL Object Types

RTL uses five kinds of objects: expressions, integers, wide integers, strings and vectors. Expressions are the most important ones. An RTL expression ("RTX", for short) is a C structure, but it is usually referred to with a pointer; a type that is given the typedef name `rtx`.

An integer is simply an `int`; their written form uses decimal digits. A wide integer is an integral object whose type is `HOST_WIDE_INT`; their written form uses decimal digits.

A string is a sequence of characters. In core it is represented as a `char *` in usual C fashion, and it is written in C syntax as well. However, strings in RTL may never be null. If you write an empty string in a machine description, it is represented in core as a null pointer rather than as a pointer to a null character. In certain contexts, these null pointers instead of strings are valid. Within RTL code, strings are most commonly found inside `symbol_ref` expressions, but they appear in other contexts in the RTL expressions that make up machine descriptions.

In a machine description, strings are normally written with double quotes, as you would in C. However, strings in machine descriptions may extend over many lines, which is invalid C, and adjacent string constants are not concatenated as they are in C. Any string constant may be surrounded with a single set of parentheses. Sometimes this makes the machine description easier to read.

There is also a special syntax for strings, which can be useful when C code is embedded in a machine description. Wherever a string can appear, it is also valid to write a C-style brace block. The entire brace block, including the outermost pair of braces, is considered to be the string constant. Double quote characters inside the braces are not special. Therefore, if you write string constants in the C code, you need not escape each quote character with a backslash.

A vector contains an arbitrary number of pointers to expressions. The number of elements in the vector is explicitly present in the vector. The written form of a vector consists of square brackets ('`[...]`') surrounding the elements, in sequence and with whitespace separating them. Vectors of length zero are not created; null pointers are used instead.

Expressions are classified by *expression codes* (also called RTX codes). The expression code is a name defined in '`rtl.def`', which is also (in uppercase) a C enumeration constant. The possible expression codes and their meanings are machine-independent. The code of an RTX can be extracted with the macro `GET_CODE (`*x*`)` and altered with `PUT_CODE (`*x*`, `*newcode*`)`.

The expression code determines how many operands the expression contains, and what kinds of objects they are. In RTL, unlike Lisp, you cannot tell by looking at an operand what kind of object it is. Instead, you must know from its context—from the expression code of the containing expression. For example, in an expression of code `subreg`, the first operand is to be regarded as an expression and the second operand as an integer. In an expression of code `plus`, there are two operands, both of which are to be regarded as expressions. In a `symbol_ref` expression, there is one operand, which is to be regarded as a string.

Expressions are written as parentheses containing the name of the expression type, its flags and machine mode if any, and then the operands of the expression (separated by spaces).

Expression code names in the '`md`' file are written in lowercase, but when they appear in C code they are written in uppercase. In this manual, they are shown as follows: `const_int`.

In a few contexts a null pointer is valid where an expression is normally wanted. The written form of this is `(nil)`.

13.2 RTL Classes and Formats

The various expression codes are divided into several *classes*, which are represented by single characters. You can determine the class of an RTX code with the macro `GET_RTX_CLASS (code)`. Currently, '`rtl.def`' defines these classes:

`RTX_OBJ`
: An RTX code that represents an actual object, such as a register (`REG`) or a memory location (`MEM`, `SYMBOL_REF`). `LO_SUM`) is also included; instead, `SUBREG` and `STRICT_LOW_PART` are not in this class, but in class `x`.

`RTX_CONST_OBJ`
: An RTX code that represents a constant object. `HIGH` is also included in this class.

`RTX_COMPARE`
: An RTX code for a non-symmetric comparison, such as `GEU` or `LT`.

`RTX_COMM_COMPARE`
: An RTX code for a symmetric (commutative) comparison, such as `EQ` or `ORDERED`.

`RTX_UNARY`
: An RTX code for a unary arithmetic operation, such as `NEG`, `NOT`, or `ABS`. This category also includes value extension (sign or zero) and conversions between integer and floating point.

`RTX_COMM_ARITH`
: An RTX code for a commutative binary operation, such as `PLUS` or `AND`. `NE` and `EQ` are comparisons, so they have class `<`.

`RTX_BIN_ARITH`
: An RTX code for a non-commutative binary operation, such as `MINUS`, `DIV`, or `ASHIFTRT`.

`RTX_BITFIELD_OPS`
: An RTX code for a bit-field operation. Currently only `ZERO_EXTRACT` and `SIGN_EXTRACT`. These have three inputs and are lvalues (so they can be used for insertion as well). See Section 13.11 [Bit-Fields], page 254.

`RTX_TERNARY`
: An RTX code for other three input operations. Currently only `IF_THEN_ELSE`, `VEC_MERGE`, `SIGN_EXTRACT`, `ZERO_EXTRACT`, and `FMA`.

`RTX_INSN`
: An RTX code for an entire instruction: `INSN`, `JUMP_INSN`, and `CALL_INSN`. See Section 13.19 [Insns], page 265.

`RTX_MATCH`
: An RTX code for something that matches in insns, such as `MATCH_DUP`. These only occur in machine descriptions.

`RTX_AUTOINC`
: An RTX code for an auto-increment addressing mode, such as `POST_INC`.

`RTX_EXTRA`
: All other RTX codes. This category includes the remaining codes used only in machine descriptions (`DEFINE_*`, etc.). It also includes all the codes describing side effects (`SET`, `USE`, `CLOBBER`, etc.) and the non-insns that may appear on an insn chain, such as `NOTE`, `BARRIER`, and `CODE_LABEL`. `SUBREG` is also part of this class.

For each expression code, '`rtl.def`' specifies the number of contained objects and their kinds using a sequence of characters called the *format* of the expression code. For example, the format of `subreg` is '`ei`'.

These are the most commonly used format characters:

`e`
: An expression (actually a pointer to an expression).

`i`
: An integer.

`w`
: A wide integer.

`s`
: A string.

`E`
: A vector of expressions.

A few other format characters are used occasionally:

`u`
: '`u`' is equivalent to '`e`' except that it is printed differently in debugging dumps. It is used for pointers to insns.

`n`
: '`n`' is equivalent to '`i`' except that it is printed differently in debugging dumps. It is used for the line number or code number of a `note` insn.

`S`
: '`S`' indicates a string which is optional. In the RTL objects in core, '`S`' is equivalent to '`s`', but when the object is read, from an '`md`' file, the string value of this operand may be omitted. An omitted string is taken to be the null string.

`V` ‘`V`’ indicates a vector which is optional. In the RTL objects in core, ‘`V`’ is equivalent to ‘`E`’, but when the object is read from an ‘`md`’ file, the vector value of this operand may be omitted. An omitted vector is effectively the same as a vector of no elements.

`B` ‘`B`’ indicates a pointer to basic block structure.

`0` ‘`0`’ means a slot whose contents do not fit any normal category. ‘`0`’ slots are not printed at all in dumps, and are often used in special ways by small parts of the compiler.

There are macros to get the number of operands and the format of an expression code:

`GET_RTX_LENGTH (code)`
Number of operands of an RTX of code *code*.

`GET_RTX_FORMAT (code)`
The format of an RTX of code *code*, as a C string.

Some classes of RTX codes always have the same format. For example, it is safe to assume that all comparison operations have format `ee`.

`1` All codes of this class have format `e`.

`<`
`c`
`2` All codes of these classes have format `ee`.

`b`
`3` All codes of these classes have format `eee`.

`i` All codes of this class have formats that begin with `iuueiee`. See Section 13.19 [Insns], page 265. Note that not all RTL objects linked onto an insn chain are of class `i`.

`o`
`m`
`x` You can make no assumptions about the format of these codes.

13.3 Access to Operands

Operands of expressions are accessed using the macros `XEXP`, `XINT`, `XWINT` and `XSTR`. Each of these macros takes two arguments: an expression-pointer (RTX) and an operand number (counting from zero). Thus,

```
XEXP (x, 2)
```

accesses operand 2 of expression *x*, as an expression.

```
XINT (x, 2)
```

accesses the same operand as an integer. `XSTR`, used in the same fashion, would access it as a string.

Any operand can be accessed as an integer, as an expression or as a string. You must choose the correct method of access for the kind of value actually stored in the operand. You would do this based on the expression code of the containing expression. That is also how you would know how many operands there are.

For example, if *x* is a `subreg` expression, you know that it has two operands which can be correctly accessed as `XEXP (x, 0)` and `XINT (x, 1)`. If you did `XINT (x, 0)`, you would get the address of the expression operand but cast as an integer; that might occasionally be useful, but it would be cleaner to write `(int) XEXP (x, 0)`. `XEXP (x, 1)` would also compile without error, and would return the second, integer operand cast as an expression pointer, which would probably result in a crash when accessed. Nothing stops you from writing `XEXP (x, 28)` either, but this will access memory past the end of the expression with unpredictable results.

Access to operands which are vectors is more complicated. You can use the macro `XVEC` to get the vector-pointer itself, or the macros `XVECEXP` and `XVECLEN` to access the elements and length of a vector.

`XVEC (exp, idx)`
: Access the vector-pointer which is operand number *idx* in *exp*.

`XVECLEN (exp, idx)`
: Access the length (number of elements) in the vector which is in operand number *idx* in *exp*. This value is an `int`.

`XVECEXP (exp, idx, eltnum)`
: Access element number *eltnum* in the vector which is in operand number *idx* in *exp*. This value is an RTX.

  It is up to you to make sure that *eltnum* is not negative and is less than `XVECLEN (exp, idx)`.

All the macros defined in this section expand into lvalues and therefore can be used to assign the operands, lengths and vector elements as well as to access them.

13.4 Access to Special Operands

Some RTL nodes have special annotations associated with them.

`MEM`

`MEM_ALIAS_SET (x)`
: If 0, *x* is not in any alias set, and may alias anything. Otherwise, *x* can only alias `MEM`s in a conflicting alias set. This value is set in a language-dependent manner in the front-end, and should not be altered in the back-end. In some front-ends, these numbers may correspond in some way to types, or other language-level entities, but they need not, and the back-end makes no such assumptions. These set numbers are tested with `alias_sets_conflict_p`.

`MEM_EXPR (x)`
: If this register is known to hold the value of some user-level declaration, this is that tree node. It may also be a `COMPONENT_REF`, in which case this is some field reference, and `TREE_OPERAND (x, 0)` contains the declaration, or another `COMPONENT_REF`, or null if there is no compile-time object associated with the reference.

`MEM_OFFSET_KNOWN_P (x)`
: True if the offset of the memory reference from `MEM_EXPR` is known. '`MEM_OFFSET (x)`' provides the offset if so.

`MEM_OFFSET (x)`
: The offset from the start of `MEM_EXPR`. The value is only valid if '`MEM_OFFSET_KNOWN_P (x)`' is true.

`MEM_SIZE_KNOWN_P (x)`
: True if the size of the memory reference is known. '`MEM_SIZE (x)`' provides its size if so.

`MEM_SIZE (x)`
: The size in bytes of the memory reference. This is mostly relevant for `BLKmode` references as otherwise the size is implied by the mode. The value is only valid if '`MEM_SIZE_KNOWN_P (x)`' is true.

`MEM_ALIGN (x)`
: The known alignment in bits of the memory reference.

`MEM_ADDR_SPACE (x)`
: The address space of the memory reference. This will commonly be zero for the generic address space.

`REG`

`ORIGINAL_REGNO (x)`
: This field holds the number the register "originally" had; for a pseudo register turned into a hard reg this will hold the old pseudo register number.

`REG_EXPR (x)`
: If this register is known to hold the value of some user-level declaration, this is that tree node.

`REG_OFFSET (x)`
: If this register is known to hold the value of some user-level declaration, this is the offset into that logical storage.

`SYMBOL_REF`

`SYMBOL_REF_DECL (x)`
: If the `symbol_ref` x was created for a `VAR_DECL` or a `FUNCTION_DECL`, that tree is recorded here. If this value is null, then x was created by back end code generation routines, and there is no associated front end symbol table entry.

  `SYMBOL_REF_DECL` may also point to a tree of class `'c'`, that is, some sort of constant. In this case, the `symbol_ref` is an entry in the per-file constant pool; again, there is no associated front end symbol table entry.

`SYMBOL_REF_CONSTANT (x)`
: If '`CONSTANT_POOL_ADDRESS_P (x)`' is true, this is the constant pool entry for x. It is null otherwise.

SYMBOL_REF_DATA (*x*)
A field of opaque type used to store SYMBOL_REF_DECL or SYMBOL_REF_CONSTANT.

SYMBOL_REF_FLAGS (*x*)
In a symbol_ref, this is used to communicate various predicates about the symbol. Some of these are common enough to be computed by common code, some are specific to the target. The common bits are:

SYMBOL_FLAG_FUNCTION
Set if the symbol refers to a function.

SYMBOL_FLAG_LOCAL
Set if the symbol is local to this "module". See TARGET_BINDS_LOCAL_P.

SYMBOL_FLAG_EXTERNAL
Set if this symbol is not defined in this translation unit. Note that this is not the inverse of SYMBOL_FLAG_LOCAL.

SYMBOL_FLAG_SMALL
Set if the symbol is located in the small data section. See TARGET_IN_SMALL_DATA_P.

SYMBOL_REF_TLS_MODEL (*x*)
This is a multi-bit field accessor that returns the tls_model to be used for a thread-local storage symbol. It returns zero for non-thread-local symbols.

SYMBOL_FLAG_HAS_BLOCK_INFO
Set if the symbol has SYMBOL_REF_BLOCK and SYMBOL_REF_BLOCK_OFFSET fields.

SYMBOL_FLAG_ANCHOR
Set if the symbol is used as a section anchor. "Section anchors" are symbols that have a known position within an object_block and that can be used to access nearby members of that block. They are used to implement '-fsection-anchors'.

If this flag is set, then SYMBOL_FLAG_HAS_BLOCK_INFO will be too.

Bits beginning with SYMBOL_FLAG_MACH_DEP are available for the target's use.

SYMBOL_REF_BLOCK (*x*)
If 'SYMBOL_REF_HAS_BLOCK_INFO_P (*x*)', this is the 'object_block' structure to which the symbol belongs, or NULL if it has not been assigned a block.

SYMBOL_REF_BLOCK_OFFSET (*x*)
: If 'SYMBOL_REF_HAS_BLOCK_INFO_P (*x*)', this is the offset of *x* from the first object in 'SYMBOL_REF_BLOCK (*x*)'. The value is negative if *x* has not yet been assigned to a block, or it has not been given an offset within that block.

13.5 Flags in an RTL Expression

RTL expressions contain several flags (one-bit bit-fields) that are used in certain types of expression. Most often they are accessed with the following macros, which expand into lvalues.

CONSTANT_POOL_ADDRESS_P (*x*)
: Nonzero in a symbol_ref if it refers to part of the current function's constant pool. For most targets these addresses are in a .rodata section entirely separate from the function, but for some targets the addresses are close to the beginning of the function. In either case GCC assumes these addresses can be addressed directly, perhaps with the help of base registers. Stored in the unchanging field and printed as '/u'.

RTL_CONST_CALL_P (*x*)
: In a call_insn indicates that the insn represents a call to a const function. Stored in the unchanging field and printed as '/u'.

RTL_PURE_CALL_P (*x*)
: In a call_insn indicates that the insn represents a call to a pure function. Stored in the return_val field and printed as '/i'.

RTL_CONST_OR_PURE_CALL_P (*x*)
: In a call_insn, true if RTL_CONST_CALL_P or RTL_PURE_CALL_P is true.

RTL_LOOPING_CONST_OR_PURE_CALL_P (*x*)
: In a call_insn indicates that the insn represents a possibly infinite looping call to a const or pure function. Stored in the call field and printed as '/c'. Only true if one of RTL_CONST_CALL_P or RTL_PURE_CALL_P is true.

INSN_ANNULLED_BRANCH_P (*x*)
: In a jump_insn, call_insn, or insn indicates that the branch is an annulling one. See the discussion under sequence below. Stored in the unchanging field and printed as '/u'.

INSN_DELETED_P (*x*)
: In an insn, call_insn, jump_insn, code_label, jump_table_data, barrier, or note, nonzero if the insn has been deleted. Stored in the volatil field and printed as '/v'.

INSN_FROM_TARGET_P (*x*)
: In an insn or jump_insn or call_insn in a delay slot of a branch, indicates that the insn is from the target of the branch. If the branch insn has INSN_ANNULLED_BRANCH_P set, this insn will only be executed if the branch is taken. For annulled branches with INSN_FROM_TARGET_P clear, the insn will be executed only if the branch is not taken. When INSN_ANNULLED_BRANCH_P is not set, this insn will always be executed. Stored in the in_struct field and printed as '/s'.

`LABEL_PRESERVE_P (x)`

In a `code_label` or `note`, indicates that the label is referenced by code or data not visible to the RTL of a given function. Labels referenced by a non-local goto will have this bit set. Stored in the `in_struct` field and printed as '`/s`'.

`LABEL_REF_NONLOCAL_P (x)`

In `label_ref` and `reg_label` expressions, nonzero if this is a reference to a non-local label. Stored in the `volatil` field and printed as '`/v`'.

`MEM_KEEP_ALIAS_SET_P (x)`

In `mem` expressions, 1 if we should keep the alias set for this mem unchanged when we access a component. Set to 1, for example, when we are already in a non-addressable component of an aggregate. Stored in the `jump` field and printed as '`/j`'.

`MEM_VOLATILE_P (x)`

In `mem`, `asm_operands`, and `asm_input` expressions, nonzero for volatile memory references. Stored in the `volatil` field and printed as '`/v`'.

`MEM_NOTRAP_P (x)`

In `mem`, nonzero for memory references that will not trap. Stored in the `call` field and printed as '`/c`'.

`MEM_POINTER (x)`

Nonzero in a `mem` if the memory reference holds a pointer. Stored in the `frame_related` field and printed as '`/f`'.

`REG_FUNCTION_VALUE_P (x)`

Nonzero in a `reg` if it is the place in which this function's value is going to be returned. (This happens only in a hard register.) Stored in the `return_val` field and printed as '`/i`'.

`REG_POINTER (x)`

Nonzero in a `reg` if the register holds a pointer. Stored in the `frame_related` field and printed as '`/f`'.

`REG_USERVAR_P (x)`

In a `reg`, nonzero if it corresponds to a variable present in the user's source code. Zero for temporaries generated internally by the compiler. Stored in the `volatil` field and printed as '`/v`'.

The same hard register may be used also for collecting the values of functions called by this one, but `REG_FUNCTION_VALUE_P` is zero in this kind of use.

`RTX_FRAME_RELATED_P (x)`

Nonzero in an `insn`, `call_insn`, `jump_insn`, `barrier`, or `set` which is part of a function prologue and sets the stack pointer, sets the frame pointer, or saves a register. This flag should also be set on an instruction that sets up a temporary register to use in place of the frame pointer. Stored in the `frame_related` field and printed as '`/f`'.

In particular, on RISC targets where there are limits on the sizes of immediate constants, it is sometimes impossible to reach the register save area directly from

the stack pointer. In that case, a temporary register is used that is near enough to the register save area, and the Canonical Frame Address, i.e., DWARF2's logical frame pointer, register must (temporarily) be changed to be this temporary register. So, the instruction that sets this temporary register must be marked as `RTX_FRAME_RELATED_P`.

If the marked instruction is overly complex (defined in terms of what `dwarf2out_frame_debug_expr` can handle), you will also have to create a `REG_FRAME_RELATED_EXPR` note and attach it to the instruction. This note should contain a simple expression of the computation performed by this instruction, i.e., one that `dwarf2out_frame_debug_expr` can handle.

This flag is required for exception handling support on targets with RTL prologues.

`MEM_READONLY_P (x)`

Nonzero in a `mem`, if the memory is statically allocated and read-only.

Read-only in this context means never modified during the lifetime of the program, not necessarily in ROM or in write-disabled pages. A common example of the later is a shared library's global offset table. This table is initialized by the runtime loader, so the memory is technically writable, but after control is transferred from the runtime loader to the application, this memory will never be subsequently modified.

Stored in the `unchanging` field and printed as '`/u`'.

`SCHED_GROUP_P (x)`

During instruction scheduling, in an `insn`, `call_insn`, `jump_insn` or `jump_table_data`, indicates that the previous insn must be scheduled together with this insn. This is used to ensure that certain groups of instructions will not be split up by the instruction scheduling pass, for example, `use` insns before a `call_insn` may not be separated from the `call_insn`. Stored in the `in_struct` field and printed as '`/s`'.

`SET_IS_RETURN_P (x)`

For a `set`, nonzero if it is for a return. Stored in the `jump` field and printed as '`/j`'.

`SIBLING_CALL_P (x)`

For a `call_insn`, nonzero if the insn is a sibling call. Stored in the `jump` field and printed as '`/j`'.

`STRING_POOL_ADDRESS_P (x)`

For a `symbol_ref` expression, nonzero if it addresses this function's string constant pool. Stored in the `frame_related` field and printed as '`/f`'.

`SUBREG_PROMOTED_UNSIGNED_P (x)`

Returns a value greater then zero for a `subreg` that has `SUBREG_PROMOTED_VAR_P` nonzero if the object being referenced is kept zero-extended, zero if it is kept sign-extended, and less then zero if it is extended some other way via the `ptr_extend` instruction. Stored in the `unchanging` field and `volatil` field, printed as '`/u`' and '`/v`'. This macro may only be used to get the value it

may not be used to change the value. Use `SUBREG_PROMOTED_UNSIGNED_SET` to change the value.

`SUBREG_PROMOTED_UNSIGNED_SET (x)`
: Set the `unchanging` and `volatil` fields in a `subreg` to reflect zero, sign, or other extension. If `volatil` is zero, then `unchanging` as nonzero means zero extension and as zero means sign extension. If `volatil` is nonzero then some other type of extension was done via the `ptr_extend` instruction.

`SUBREG_PROMOTED_VAR_P (x)`
: Nonzero in a `subreg` if it was made when accessing an object that was promoted to a wider mode in accord with the `PROMOTED_MODE` machine description macro (see Section 17.5 [Storage Layout], page 432). In this case, the mode of the `subreg` is the declared mode of the object and the mode of `SUBREG_REG` is the mode of the register that holds the object. Promoted variables are always either sign- or zero-extended to the wider mode on every assignment. Stored in the `in_struct` field and printed as '`/s`'.

`SYMBOL_REF_USED (x)`
: In a `symbol_ref`, indicates that *x* has been used. This is normally only used to ensure that *x* is only declared external once. Stored in the `used` field.

`SYMBOL_REF_WEAK (x)`
: In a `symbol_ref`, indicates that *x* has been declared weak. Stored in the `return_val` field and printed as '`/i`'.

`SYMBOL_REF_FLAG (x)`
: In a `symbol_ref`, this is used as a flag for machine-specific purposes. Stored in the `volatil` field and printed as '`/v`'.

  Most uses of `SYMBOL_REF_FLAG` are historic and may be subsumed by `SYMBOL_REF_FLAGS`. Certainly use of `SYMBOL_REF_FLAGS` is mandatory if the target requires more than one bit of storage.

`PREFETCH_SCHEDULE_BARRIER_P (x)`
: In a `prefetch`, indicates that the prefetch is a scheduling barrier. No other INSNs will be moved over it. Stored in the `volatil` field and printed as '`/v`'.

These are the fields to which the above macros refer:

`call`
: In a `mem`, 1 means that the memory reference will not trap.

  In a `call`, 1 means that this pure or const call may possibly infinite loop.

  In an RTL dump, this flag is represented as '`/c`'.

`frame_related`
: In an `insn` or `set` expression, 1 means that it is part of a function prologue and sets the stack pointer, sets the frame pointer, saves a register, or sets up a temporary register to use in place of the frame pointer.

  In `reg` expressions, 1 means that the register holds a pointer.

  In `mem` expressions, 1 means that the memory reference holds a pointer.

  In `symbol_ref` expressions, 1 means that the reference addresses this function's string constant pool.

In an RTL dump, this flag is represented as '/f'.

`in_struct`

In `reg` expressions, it is 1 if the register has its entire life contained within the test expression of some loop.

In `subreg` expressions, 1 means that the `subreg` is accessing an object that has had its mode promoted from a wider mode.

In `label_ref` expressions, 1 means that the referenced label is outside the innermost loop containing the insn in which the `label_ref` was found.

In `code_label` expressions, it is 1 if the label may never be deleted. This is used for labels which are the target of non-local gotos. Such a label that would have been deleted is replaced with a `note` of type `NOTE_INSN_DELETED_LABEL`.

In an `insn` during dead-code elimination, 1 means that the insn is dead code.

In an `insn` or `jump_insn` during reorg for an insn in the delay slot of a branch, 1 means that this insn is from the target of the branch.

In an `insn` during instruction scheduling, 1 means that this insn must be scheduled as part of a group together with the previous insn.

In an RTL dump, this flag is represented as '/s'.

`return_val`

In `reg` expressions, 1 means the register contains the value to be returned by the current function. On machines that pass parameters in registers, the same register number may be used for parameters as well, but this flag is not set on such uses.

In `symbol_ref` expressions, 1 means the referenced symbol is weak.

In `call` expressions, 1 means the call is pure.

In an RTL dump, this flag is represented as '/i'.

`jump`

In a `mem` expression, 1 means we should keep the alias set for this mem unchanged when we access a component.

In a `set`, 1 means it is for a return.

In a `call_insn`, 1 means it is a sibling call.

In an RTL dump, this flag is represented as '/j'.

`unchanging`

In `reg` and `mem` expressions, 1 means that the value of the expression never changes.

In `subreg` expressions, it is 1 if the `subreg` references an unsigned object whose mode has been promoted to a wider mode.

In an `insn` or `jump_insn` in the delay slot of a branch instruction, 1 means an annulling branch should be used.

In a `symbol_ref` expression, 1 means that this symbol addresses something in the per-function constant pool.

In a `call_insn` 1 means that this instruction is a call to a const function.

In an RTL dump, this flag is represented as '/u'.

`used` This flag is used directly (without an access macro) at the end of RTL generation for a function, to count the number of times an expression appears in insns. Expressions that appear more than once are copied, according to the rules for shared structure (see Section 13.21 [Sharing], page 274).

For a `reg`, it is used directly (without an access macro) by the leaf register renumbering code to ensure that each register is only renumbered once.

In a `symbol_ref`, it indicates that an external declaration for the symbol has already been written.

`volatil` In a `mem`, `asm_operands`, or `asm_input` expression, it is 1 if the memory reference is volatile. Volatile memory references may not be deleted, reordered or combined.

In a `symbol_ref` expression, it is used for machine-specific purposes.

In a `reg` expression, it is 1 if the value is a user-level variable. 0 indicates an internal compiler temporary.

In an `insn`, 1 means the insn has been deleted.

In `label_ref` and `reg_label` expressions, 1 means a reference to a non-local label.

In `prefetch` expressions, 1 means that the containing insn is a scheduling barrier.

In an RTL dump, this flag is represented as '`/v`'.

13.6 Machine Modes

A machine mode describes a size of data object and the representation used for it. In the C code, machine modes are represented by an enumeration type, `enum machine_mode`, defined in '`machmode.def`'. Each RTL expression has room for a machine mode and so do certain kinds of tree expressions (declarations and types, to be precise).

In debugging dumps and machine descriptions, the machine mode of an RTL expression is written after the expression code with a colon to separate them. The letters '`mode`' which appear at the end of each machine mode name are omitted. For example, `(reg:SI 38)` is a `reg` expression with machine mode `SImode`. If the mode is `VOIDmode`, it is not written at all.

Here is a table of machine modes. The term "byte" below refers to an object of `BITS_PER_UNIT` bits (see Section 17.5 [Storage Layout], page 432).

`BImode` "Bit" mode represents a single bit, for predicate registers.

`QImode` "Quarter-Integer" mode represents a single byte treated as an integer.

`HImode` "Half-Integer" mode represents a two-byte integer.

`PSImode` "Partial Single Integer" mode represents an integer which occupies four bytes but which doesn't really use all four. On some machines, this is the right mode to use for pointers.

`SImode` "Single Integer" mode represents a four-byte integer.

`PDImode` "Partial Double Integer" mode represents an integer which occupies eight bytes but which doesn't really use all eight. On some machines, this is the right mode to use for certain pointers.

`DImode` "Double Integer" mode represents an eight-byte integer.

`TImode` "Tetra Integer" (?) mode represents a sixteen-byte integer.

`OImode` "Octa Integer" (?) mode represents a thirty-two-byte integer.

`XImode` "Hexadeca Integer" (?) mode represents a sixty-four-byte integer.

`QFmode` "Quarter-Floating" mode represents a quarter-precision (single byte) floating point number.

`HFmode` "Half-Floating" mode represents a half-precision (two byte) floating point number.

`TQFmode` "Three-Quarter-Floating" (?) mode represents a three-quarter-precision (three byte) floating point number.

`SFmode` "Single Floating" mode represents a four byte floating point number. In the common case, of a processor with IEEE arithmetic and 8-bit bytes, this is a single-precision IEEE floating point number; it can also be used for double-precision (on processors with 16-bit bytes) and single-precision VAX and IBM types.

`DFmode` "Double Floating" mode represents an eight byte floating point number. In the common case, of a processor with IEEE arithmetic and 8-bit bytes, this is a double-precision IEEE floating point number.

`XFmode` "Extended Floating" mode represents an IEEE extended floating point number. This mode only has 80 meaningful bits (ten bytes). Some processors require such numbers to be padded to twelve bytes, others to sixteen; this mode is used for either.

`SDmode` "Single Decimal Floating" mode represents a four byte decimal floating point number (as distinct from conventional binary floating point).

`DDmode` "Double Decimal Floating" mode represents an eight byte decimal floating point number.

`TDmode` "Tetra Decimal Floating" mode represents a sixteen byte decimal floating point number all 128 of whose bits are meaningful.

`TFmode` "Tetra Floating" mode represents a sixteen byte floating point number all 128 of whose bits are meaningful. One common use is the IEEE quad-precision format.

`QQmode` "Quarter-Fractional" mode represents a single byte treated as a signed fractional number. The default format is "s.7".

`HQmode` "Half-Fractional" mode represents a two-byte signed fractional number. The default format is "s.15".

`SQmode` "Single Fractional" mode represents a four-byte signed fractional number. The default format is "s.31".

`DQmode` "Double Fractional" mode represents an eight-byte signed fractional number. The default format is "s.63".

`TQmode` "Tetra Fractional" mode represents a sixteen-byte signed fractional number. The default format is "s.127".

`UQQmode` "Unsigned Quarter-Fractional" mode represents a single byte treated as an unsigned fractional number. The default format is ".8".

`UHQmode` "Unsigned Half-Fractional" mode represents a two-byte unsigned fractional number. The default format is ".16".

`USQmode` "Unsigned Single Fractional" mode represents a four-byte unsigned fractional number. The default format is ".32".

`UDQmode` "Unsigned Double Fractional" mode represents an eight-byte unsigned fractional number. The default format is ".64".

`UTQmode` "Unsigned Tetra Fractional" mode represents a sixteen-byte unsigned fractional number. The default format is ".128".

`HAmode` "Half-Accumulator" mode represents a two-byte signed accumulator. The default format is "s8.7".

`SAmode` "Single Accumulator" mode represents a four-byte signed accumulator. The default format is "s16.15".

`DAmode` "Double Accumulator" mode represents an eight-byte signed accumulator. The default format is "s32.31".

`TAmode` "Tetra Accumulator" mode represents a sixteen-byte signed accumulator. The default format is "s64.63".

`UHAmode` "Unsigned Half-Accumulator" mode represents a two-byte unsigned accumulator. The default format is "8.8".

`USAmode` "Unsigned Single Accumulator" mode represents a four-byte unsigned accumulator. The default format is "16.16".

`UDAmode` "Unsigned Double Accumulator" mode represents an eight-byte unsigned accumulator. The default format is "32.32".

`UTAmode` "Unsigned Tetra Accumulator" mode represents a sixteen-byte unsigned accumulator. The default format is "64.64".

`CCmode` "Condition Code" mode represents the value of a condition code, which is a machine-specific set of bits used to represent the result of a comparison operation. Other machine-specific modes may also be used for the condition code. These modes are not used on machines that use `cc0` (see Section 17.16 [Condition Code], page 506).

`BLKmode` "Block" mode represents values that are aggregates to which none of the other modes apply. In RTL, only memory references can have this mode, and only if they appear in string-move or vector instructions. On machines which have no such instructions, `BLKmode` will not appear in RTL.

`VOIDmode` Void mode means the absence of a mode or an unspecified mode. For example, RTL expressions of code `const_int` have mode `VOIDmode` because they can be taken to have whatever mode the context requires. In debugging dumps of RTL, `VOIDmode` is expressed by the absence of any mode.

`QCmode, HCmode, SCmode, DCmode, XCmode, TCmode`
These modes stand for a complex number represented as a pair of floating point values. The floating point values are in `QFmode`, `HFmode`, `SFmode`, `DFmode`, `XFmode`, and `TFmode`, respectively.

`CQImode, CHImode, CSImode, CDImode, CTImode, COImode`
These modes stand for a complex number represented as a pair of integer values. The integer values are in `QImode`, `HImode`, `SImode`, `DImode`, `TImode`, and `OImode`, respectively.

The machine description defines `Pmode` as a C macro which expands into the machine mode used for addresses. Normally this is the mode whose size is `BITS_PER_WORD`, `SImode` on 32-bit machines.

The only modes which a machine description *must* support are `QImode`, and the modes corresponding to `BITS_PER_WORD`, `FLOAT_TYPE_SIZE` and `DOUBLE_TYPE_SIZE`. The compiler will attempt to use `DImode` for 8-byte structures and unions, but this can be prevented by overriding the definition of `MAX_FIXED_MODE_SIZE`. Alternatively, you can have the compiler use `TImode` for 16-byte structures and unions. Likewise, you can arrange for the C type `short int` to avoid using `HImode`.

Very few explicit references to machine modes remain in the compiler and these few references will soon be removed. Instead, the machine modes are divided into mode classes. These are represented by the enumeration type `enum mode_class` defined in '`machmode.h`'. The possible mode classes are:

`MODE_INT` Integer modes. By default these are `BImode`, `QImode`, `HImode`, `SImode`, `DImode`, `TImode`, and `OImode`.

`MODE_PARTIAL_INT`
The "partial integer" modes, `PQImode`, `PHImode`, `PSImode` and `PDImode`.

`MODE_FLOAT`
Floating point modes. By default these are `QFmode`, `HFmode`, `TQFmode`, `SFmode`, `DFmode`, `XFmode` and `TFmode`.

`MODE_DECIMAL_FLOAT`
Decimal floating point modes. By default these are `SDmode`, `DDmode` and `TDmode`.

`MODE_FRACT`
Signed fractional modes. By default these are `QQmode`, `HQmode`, `SQmode`, `DQmode` and `TQmode`.

`MODE_UFRACT`
Unsigned fractional modes. By default these are `UQQmode`, `UHQmode`, `USQmode`, `UDQmode` and `UTQmode`.

`MODE_ACCUM`
Signed accumulator modes. By default these are `HAmode`, `SAmode`, `DAmode` and `TAmode`.

`MODE_UACCUM`
: Unsigned accumulator modes. By default these are `UHAmode`, `USAmode`, `UDAmode` and `UTAmode`.

`MODE_COMPLEX_INT`
: Complex integer modes. (These are not currently implemented).

`MODE_COMPLEX_FLOAT`
: Complex floating point modes. By default these are `QCmode`, `HCmode`, `SCmode`, `DCmode`, `XCmode`, and `TCmode`.

`MODE_FUNCTION`
: Algol or Pascal function variables including a static chain. (These are not currently implemented).

`MODE_CC` Modes representing condition code values. These are `CCmode` plus any `CC_MODE` modes listed in the '*machine*`-modes.def`'. See Section 16.12 [Jump Patterns], page 380, also see Section 17.16 [Condition Code], page 506.

`MODE_RANDOM`
: This is a catchall mode class for modes which don't fit into the above classes. Currently `VOIDmode` and `BLKmode` are in `MODE_RANDOM`.

Here are some C macros that relate to machine modes:

`GET_MODE (`*x*`)`
: Returns the machine mode of the RTX *x*.

`PUT_MODE (`*x*`, `*newmode*`)`
: Alters the machine mode of the RTX *x* to be *newmode*.

`NUM_MACHINE_MODES`
: Stands for the number of machine modes available on the target machine. This is one greater than the largest numeric value of any machine mode.

`GET_MODE_NAME (`*m*`)`
: Returns the name of mode *m* as a string.

`GET_MODE_CLASS (`*m*`)`
: Returns the mode class of mode *m*.

`GET_MODE_WIDER_MODE (`*m*`)`
: Returns the next wider natural mode. For example, the expression `GET_MODE_WIDER_MODE (QImode)` returns `HImode`.

`GET_MODE_SIZE (`*m*`)`
: Returns the size in bytes of a datum of mode *m*.

`GET_MODE_BITSIZE (`*m*`)`
: Returns the size in bits of a datum of mode *m*.

`GET_MODE_IBIT (`*m*`)`
: Returns the number of integral bits of a datum of fixed-point mode *m*.

`GET_MODE_FBIT (`*m*`)`
: Returns the number of fractional bits of a datum of fixed-point mode *m*.

`GET_MODE_MASK (m)`
: Returns a bitmask containing 1 for all bits in a word that fit within mode *m*. This macro can only be used for modes whose bitsize is less than or equal to `HOST_BITS_PER_INT`.

`GET_MODE_ALIGNMENT (m)`
: Return the required alignment, in bits, for an object of mode *m*.

`GET_MODE_UNIT_SIZE (m)`
: Returns the size in bytes of the subunits of a datum of mode *m*. This is the same as `GET_MODE_SIZE` except in the case of complex modes. For them, the unit size is the size of the real or imaginary part.

`GET_MODE_NUNITS (m)`
: Returns the number of units contained in a mode, i.e., `GET_MODE_SIZE` divided by `GET_MODE_UNIT_SIZE`.

`GET_CLASS_NARROWEST_MODE (c)`
: Returns the narrowest mode in mode class *c*.

The following 3 variables are defined on every target. They can be used to allocate buffers that are guaranteed to be large enough to hold any value that can be represented on the target. The first two can be overridden by defining them in the target's mode.def file, however, the value must be a constant that can determined very early in the compilation process. The third symbol cannot be overridden.

`BITS_PER_UNIT`
: The number of bits in an addressable storage unit (byte). If you do not define this, the default is 8.

`MAX_BITSIZE_MODE_ANY_INT`
: The maximum bitsize of any mode that is used in integer math. This should be overridden by the target if it uses large integers as containers for larger vectors but otherwise never uses the contents to compute integer values.

`MAX_BITSIZE_MODE_ANY_MODE`
: The bitsize of the largest mode on the target.

The global variables `byte_mode` and `word_mode` contain modes whose classes are `MODE_INT` and whose bitsizes are either `BITS_PER_UNIT` or `BITS_PER_WORD`, respectively. On 32-bit machines, these are `QImode` and `SImode`, respectively.

13.7 Constant Expression Types

The simplest RTL expressions are those that represent constant values.

`(const_int i)`
: This type of expression represents the integer value *i*. *i* is customarily accessed with the macro `INTVAL` as in `INTVAL (exp)`, which is equivalent to `XWINT (exp, 0)`.

  Constants generated for modes with fewer bits than in `HOST_WIDE_INT` must be sign extended to full width (e.g., with `gen_int_mode`). For constants for modes

with more bits than in HOST_WIDE_INT the implied high order bits of that constant are copies of the top bit. Note however that values are neither inherently signed nor inherently unsigned; where necessary, signedness is determined by the rtl operation instead.

There is only one expression object for the integer value zero; it is the value of the variable const0_rtx. Likewise, the only expression for integer value one is found in const1_rtx, the only expression for integer value two is found in const2_rtx, and the only expression for integer value negative one is found in constm1_rtx. Any attempt to create an expression of code const_int and value zero, one, two or negative one will return const0_rtx, const1_rtx, const2_rtx or constm1_rtx as appropriate.

Similarly, there is only one object for the integer whose value is STORE_FLAG_VALUE. It is found in const_true_rtx. If STORE_FLAG_VALUE is one, const_true_rtx and const1_rtx will point to the same object. If STORE_FLAG_VALUE is −1, const_true_rtx and constm1_rtx will point to the same object.

(const_double:*m* *i0* *i1* ...)

Represents either a floating-point constant of mode *m* or an integer constant too large to fit into HOST_BITS_PER_WIDE_INT bits but small enough to fit within twice that number of bits (GCC does not provide a mechanism to represent even larger constants). In the latter case, *m* will be VOIDmode. For integral values constants for modes with more bits than twice the number in HOST_WIDE_INT the implied high order bits of that constant are copies of the top bit of CONST_DOUBLE_HIGH. Note however that integral values are neither inherently signed nor inherently unsigned; where necessary, signedness is determined by the rtl operation instead.

If *m* is VOIDmode, the bits of the value are stored in *i0* and *i1*. *i0* is customarily accessed with the macro CONST_DOUBLE_LOW and *i1* with CONST_DOUBLE_HIGH.

If the constant is floating point (regardless of its precision), then the number of integers used to store the value depends on the size of REAL_VALUE_TYPE (see Section 17.23 [Floating Point], page 562). The integers represent a floating point number, but not precisely in the target machine's or host machine's floating point format. To convert them to the precise bit pattern used by the target machine, use the macro REAL_VALUE_TO_TARGET_DOUBLE and friends (see Section 17.21.2 [Data Output], page 531).

(const_fixed:*m* ...)

Represents a fixed-point constant of mode *m*. The operand is a data structure of type struct fixed_value and is accessed with the macro CONST_FIXED_VALUE. The high part of data is accessed with CONST_FIXED_VALUE_HIGH; the low part is accessed with CONST_FIXED_VALUE_LOW.

(const_vector:*m* [*x0* *x1* ...])

Represents a vector constant. The square brackets stand for the vector containing the constant elements. *x0*, *x1* and so on are the const_int, const_double or const_fixed elements.

The number of units in a const_vector is obtained with the macro CONST_VECTOR_NUNITS as in CONST_VECTOR_NUNITS (*v*).

Individual elements in a vector constant are accessed with the macro `CONST_VECTOR_ELT` as in `CONST_VECTOR_ELT (v, n)` where *v* is the vector constant and *n* is the element desired.

`(const_string str)`
Represents a constant string with value *str*. Currently this is used only for insn attributes (see Section 16.19 [Insn Attributes], page 394) since constant strings in C are placed in memory.

`(symbol_ref:mode symbol)`
Represents the value of an assembler label for data. *symbol* is a string that describes the name of the assembler label. If it starts with a '`*`', the label is the rest of *symbol* not including the '`*`'. Otherwise, the label is *symbol*, usually prefixed with '`_`'.

The `symbol_ref` contains a mode, which is usually `Pmode`. Usually that is the only mode for which a symbol is directly valid.

`(label_ref:mode label)`
Represents the value of an assembler label for code. It contains one operand, an expression, which must be a `code_label` or a `note` of type `NOTE_INSN_DELETED_LABEL` that appears in the instruction sequence to identify the place where the label should go.

The reason for using a distinct expression type for code label references is so that jump optimization can distinguish them.

The `label_ref` contains a mode, which is usually `Pmode`. Usually that is the only mode for which a label is directly valid.

`(const:m exp)`
Represents a constant that is the result of an assembly-time arithmetic computation. The operand, *exp*, is an expression that contains only constants (`const_int`, `symbol_ref` and `label_ref` expressions) combined with `plus` and `minus`. However, not all combinations are valid, since the assembler cannot do arbitrary arithmetic on relocatable symbols.

m should be `Pmode`.

`(high:m exp)`
Represents the high-order bits of *exp*, usually a `symbol_ref`. The number of bits is machine-dependent and is normally the number of bits specified in an instruction that initializes the high order bits of a register. It is used with `lo_sum` to represent the typical two-instruction sequence used in RISC machines to reference a global memory location.

m should be `Pmode`.

The macro `CONST0_RTX (mode)` refers to an expression with value 0 in mode *mode*. If mode *mode* is of mode class `MODE_INT`, it returns `const0_rtx`. If mode *mode* is of mode class `MODE_FLOAT`, it returns a `CONST_DOUBLE` expression in mode *mode*. Otherwise, it returns a `CONST_VECTOR` expression in mode *mode*. Similarly, the macro `CONST1_RTX (mode)` refers to an expression with value 1 in mode *mode* and similarly for `CONST2_RTX`. The `CONST1_RTX` and `CONST2_RTX` macros are undefined for vector modes.

13.8 Registers and Memory

Here are the RTL expression types for describing access to machine registers and to main memory.

`(reg:m n)` For small values of the integer *n* (those that are less than `FIRST_PSEUDO_REGISTER`), this stands for a reference to machine register number *n*: a *hard register*. For larger values of *n*, it stands for a temporary value or *pseudo register*. The compiler's strategy is to generate code assuming an unlimited number of such pseudo registers, and later convert them into hard registers or into memory references.

m is the machine mode of the reference. It is necessary because machines can generally refer to each register in more than one mode. For example, a register may contain a full word but there may be instructions to refer to it as a half word or as a single byte, as well as instructions to refer to it as a floating point number of various precisions.

Even for a register that the machine can access in only one mode, the mode must always be specified.

The symbol `FIRST_PSEUDO_REGISTER` is defined by the machine description, since the number of hard registers on the machine is an invariant characteristic of the machine. Note, however, that not all of the machine registers must be general registers. All the machine registers that can be used for storage of data are given hard register numbers, even those that can be used only in certain instructions or can hold only certain types of data.

A hard register may be accessed in various modes throughout one function, but each pseudo register is given a natural mode and is accessed only in that mode. When it is necessary to describe an access to a pseudo register using a nonnatural mode, a `subreg` expression is used.

A `reg` expression with a machine mode that specifies more than one word of data may actually stand for several consecutive registers. If in addition the register number specifies a hardware register, then it actually represents several consecutive hardware registers starting with the specified one.

Each pseudo register number used in a function's RTL code is represented by a unique `reg` expression.

Some pseudo register numbers, those within the range of `FIRST_VIRTUAL_REGISTER` to `LAST_VIRTUAL_REGISTER` only appear during the RTL generation phase and are eliminated before the optimization phases. These represent locations in the stack frame that cannot be determined until RTL generation for the function has been completed. The following virtual register numbers are defined:

`VIRTUAL_INCOMING_ARGS_REGNUM`
: This points to the first word of the incoming arguments passed on the stack. Normally these arguments are placed there by the caller, but the callee may have pushed some arguments that were previously passed in registers.

When RTL generation is complete, this virtual register is replaced by the sum of the register given by `ARG_POINTER_REGNUM` and the value of `FIRST_PARM_OFFSET`.

`VIRTUAL_STACK_VARS_REGNUM`
: If `FRAME_GROWS_DOWNWARD` is defined to a nonzero value, this points to immediately above the first variable on the stack. Otherwise, it points to the first variable on the stack.

  `VIRTUAL_STACK_VARS_REGNUM` is replaced with the sum of the register given by `FRAME_POINTER_REGNUM` and the value `STARTING_FRAME_OFFSET`.

`VIRTUAL_STACK_DYNAMIC_REGNUM`
: This points to the location of dynamically allocated memory on the stack immediately after the stack pointer has been adjusted by the amount of memory desired.

  This virtual register is replaced by the sum of the register given by `STACK_POINTER_REGNUM` and the value `STACK_DYNAMIC_OFFSET`.

`VIRTUAL_OUTGOING_ARGS_REGNUM`
: This points to the location in the stack at which outgoing arguments should be written when the stack is pre-pushed (arguments pushed using push insns should always use `STACK_POINTER_REGNUM`).

  This virtual register is replaced by the sum of the register given by `STACK_POINTER_REGNUM` and the value `STACK_POINTER_OFFSET`.

`(subreg:`*`m1 reg:m2 bytenum`*`)`
: `subreg` expressions are used to refer to a register in a machine mode other than its natural one, or to refer to one register of a multi-part `reg` that actually refers to several registers.

  Each pseudo register has a natural mode. If it is necessary to operate on it in a different mode, the register must be enclosed in a `subreg`.

  There are currently three supported types for the first operand of a `subreg`:

  - pseudo registers This is the most common case. Most `subreg`s have pseudo `reg`s as their first operand.
  - mem `subreg`s of `mem` were common in earlier versions of GCC and are still supported. During the reload pass these are replaced by plain `mem`s. On machines that do not do instruction scheduling, use of `subreg`s of `mem` are still used, but this is no longer recommended. Such `subreg`s are considered to be `register_operand`s rather than `memory_operand`s before and during reload. Because of this, the scheduling passes cannot properly schedule instructions with `subreg`s of `mem`, so for machines that do scheduling, `subreg`s of `mem` should never be used. To support this, the combine and recog passes have explicit code to inhibit the creation of `subreg`s of `mem` when `INSN_SCHEDULING` is defined.

    The use of `subreg`s of `mem` after the reload pass is an area that is not well understood and should be avoided. There is still some code in the compiler

to support this, but this code has possibly rotted. This use of `subreg`s is discouraged and will most likely not be supported in the future.

- hard registers It is seldom necessary to wrap hard registers in `subreg`s; such registers would normally reduce to a single `reg` rtx. This use of `subreg`s is discouraged and may not be supported in the future.

`subreg`s of `subreg`s are not supported. Using `simplify_gen_subreg` is the recommended way to avoid this problem.

`subreg`s come in two distinct flavors, each having its own usage and rules:

Paradoxical subregs

When *m1* is strictly wider than *m2*, the `subreg` expression is called *paradoxical*. The canonical test for this class of `subreg` is:

```
GET_MODE_SIZE (m1) > GET_MODE_SIZE (m2)
```

Paradoxical `subreg`s can be used as both lvalues and rvalues. When used as an lvalue, the low-order bits of the source value are stored in *reg* and the high-order bits are discarded. When used as an rvalue, the low-order bits of the `subreg` are taken from *reg* while the high-order bits may or may not be defined.

The high-order bits of rvalues are in the following circumstances:

- `subreg`s of `mem` When *m2* is smaller than a word, the macro `LOAD_EXTEND_OP`, can control how the high-order bits are defined.
- `subreg` of `reg`s The upper bits are defined when `SUBREG_PROMOTED_VAR_P` is true. `SUBREG_PROMOTED_UNSIGNED_P` describes what the upper bits hold. Such subregs usually represent local variables, register variables and parameter pseudo variables that have been promoted to a wider mode.

bytenum is always zero for a paradoxical `subreg`, even on big-endian targets.

For example, the paradoxical `subreg`:

```
(set (subreg:SI (reg:HI x) 0) y)
```

stores the lower 2 bytes of *y* in *x* and discards the upper 2 bytes. A subsequent:

```
(set z (subreg:SI (reg:HI x) 0))
```

would set the lower two bytes of *z* to *y* and set the upper two bytes to an unknown value assuming `SUBREG_PROMOTED_VAR_P` is false.

Normal subregs

When *m1* is at least as narrow as *m2* the `subreg` expression is called *normal*.

Normal `subreg`s restrict consideration to certain bits of *reg*. There are two cases. If *m1* is smaller than a word, the `subreg` refers to the least-significant part (or *lowpart*) of one word of *reg*. If *m1* is word-sized or greater, the `subreg` refers to one or more complete words.

When used as an lvalue, `subreg` is a word-based accessor. Storing to a `subreg` modifies all the words of *reg* that overlap the `subreg`, but it leaves the other words of *reg* alone.

When storing to a normal `subreg` that is smaller than a word, the other bits of the referenced word are usually left in an undefined state. This laxity makes it easier to generate efficient code for such instructions. To represent an instruction that preserves all the bits outside of those in the `subreg`, use `strict_low_part` or `zero_extract` around the `subreg`.

bytenum must identify the offset of the first byte of the `subreg` from the start of *reg*, assuming that *reg* is laid out in memory order. The memory order of bytes is defined by two target macros, `WORDS_BIG_ENDIAN` and `BYTES_BIG_ENDIAN`:

- `WORDS_BIG_ENDIAN`, if set to 1, says that byte number zero is part of the most significant word; otherwise, it is part of the least significant word.
- `BYTES_BIG_ENDIAN`, if set to 1, says that byte number zero is the most significant byte within a word; otherwise, it is the least significant byte within a word.

On a few targets, `FLOAT_WORDS_BIG_ENDIAN` disagrees with `WORDS_BIG_ENDIAN`. However, most parts of the compiler treat floating point values as if they had the same endianness as integer values. This works because they handle them solely as a collection of integer values, with no particular numerical value. Only real.c and the runtime libraries care about `FLOAT_WORDS_BIG_ENDIAN`.

Thus,

```
(subreg:HI (reg:SI x) 2)
```

on a `BYTES_BIG_ENDIAN`, '`UNITS_PER_WORD == 4`' target is the same as

```
(subreg:HI (reg:SI x) 0)
```

on a little-endian, '`UNITS_PER_WORD == 4`' target. Both `subreg`s access the lower two bytes of register *x*.

A `MODE_PARTIAL_INT` mode behaves as if it were as wide as the corresponding `MODE_INT` mode, except that it has an unknown number of undefined bits. For example:

```
(subreg:PSI (reg:SI 0) 0)
```

accesses the whole of '`(reg:SI 0)`', but the exact relationship between the `PSImode` value and the `SImode` value is not defined. If we assume '`UNITS_PER_WORD <= 4`', then the following two `subreg`s:

```
(subreg:PSI (reg:DI 0) 0)
(subreg:PSI (reg:DI 0) 4)
```

represent independent 4-byte accesses to the two halves of '`(reg:DI 0)`'. Both `subreg`s have an unknown number of undefined bits.

If '`UNITS_PER_WORD <= 2`' then these two `subreg`s:

```
(subreg:HI (reg:PSI 0) 0)
(subreg:HI (reg:PSI 0) 2)
```

represent independent 2-byte accesses that together span the whole of '`(reg:PSI 0)`'. Storing to the first `subreg` does not affect the value of the second, and vice versa. '`(reg:PSI 0)`' has an unknown number of undefined bits, so the assignment:

```
(set (subreg:HI (reg:PSI 0) 0) (reg:HI 4))
```

does not guarantee that '`(subreg:HI (reg:PSI 0) 0)`' has the value '`(reg:HI 4)`'.

The rules above apply to both pseudo *reg*s and hard *reg*s. If the semantics are not correct for particular combinations of *m1*, *m2* and hard *reg*, the target-specific code must ensure that those combinations are never used. For example:

```
CANNOT_CHANGE_MODE_CLASS (m2, m1, class)
```

must be true for every class *class* that includes *reg*.

The first operand of a `subreg` expression is customarily accessed with the `SUBREG_REG` macro and the second operand is customarily accessed with the `SUBREG_BYTE` macro.

It has been several years since a platform in which `BYTES_BIG_ENDIAN` not equal to `WORDS_BIG_ENDIAN` has been tested. Anyone wishing to support such a platform in the future may be confronted with code rot.

`(scratch:m)`

This represents a scratch register that will be required for the execution of a single instruction and not used subsequently. It is converted into a `reg` by either the local register allocator or the reload pass.

`scratch` is usually present inside a `clobber` operation (see Section 13.15 [Side Effects], page 257).

`(cc0)`

This refers to the machine's condition code register. It has no operands and may not have a machine mode. There are two ways to use it:

- To stand for a complete set of condition code flags. This is best on most machines, where each comparison sets the entire series of flags.

  With this technique, `(cc0)` may be validly used in only two contexts: as the destination of an assignment (in test and compare instructions) and in comparison operators comparing against zero (`const_int` with value zero; that is to say, `const0_rtx`).

- To stand for a single flag that is the result of a single condition. This is useful on machines that have only a single flag bit, and in which comparison instructions must specify the condition to test.

  With this technique, `(cc0)` may be validly used in only two contexts: as the destination of an assignment (in test and compare instructions) where the source is a comparison operator, and as the first operand of `if_then_else` (in a conditional branch).

There is only one expression object of code `cc0`; it is the value of the variable `cc0_rtx`. Any attempt to create an expression of code `cc0` will return `cc0_rtx`.

Instructions can set the condition code implicitly. On many machines, nearly all instructions set the condition code based on the value that they compute or store. It is not necessary to record these actions explicitly in the RTL because the machine description includes a prescription for recognizing the instructions that do so (by means of the macro `NOTICE_UPDATE_CC`). See Section 17.16 [Condition Code], page 506. Only instructions whose sole purpose is to set the condition code, and instructions that use the condition code, need mention `(cc0)`.

On some machines, the condition code register is given a register number and a `reg` is used instead of `(cc0)`. This is usually the preferable approach if only a small subset of instructions modify the condition code. Other machines store condition codes in general registers; in such cases a pseudo register should be used.

Some machines, such as the SPARC and RS/6000, have two sets of arithmetic instructions, one that sets and one that does not set the condition code. This is best handled by normally generating the instruction that does not set the condition code, and making a pattern that both performs the arithmetic and sets the condition code register (which would not be `(cc0)` in this case). For examples, search for '`addcc`' and '`andcc`' in '`sparc.md`'.

`(pc)` This represents the machine's program counter. It has no operands and may not have a machine mode. `(pc)` may be validly used only in certain specific contexts in jump instructions.

There is only one expression object of code `pc`; it is the value of the variable `pc_rtx`. Any attempt to create an expression of code `pc` will return `pc_rtx`.

All instructions that do not jump alter the program counter implicitly by incrementing it, but there is no need to mention this in the RTL.

`(mem:`*m addr alias*`)`

This RTX represents a reference to main memory at an address represented by the expression *addr*. *m* specifies how large a unit of memory is accessed. *alias* specifies an alias set for the reference. In general two items are in different alias sets if they cannot reference the same memory address.

The construct `(mem:BLK (scratch))` is considered to alias all other memories. Thus it may be used as a memory barrier in epilogue stack deallocation patterns.

`(concat`*m rtx rtx*`)`

This RTX represents the concatenation of two other RTXs. This is used for complex values. It should only appear in the RTL attached to declarations and during RTL generation. It should not appear in the ordinary insn chain.

`(concatn`*m* `[`*rtx* `...])`

This RTX represents the concatenation of all the *rtx* to make a single value. Like `concat`, this should only appear in declarations, and not in the insn chain.

13.9 RTL Expressions for Arithmetic

Unless otherwise specified, all the operands of arithmetic expressions must be valid for mode *m*. An operand is valid for mode *m* if it has mode *m*, or if it is a `const_int` or `const_double` and *m* is a mode of class `MODE_INT`.

For commutative binary operations, constants should be placed in the second operand.

`(plus:`*m x y*`)`
`(ss_plus:`*m x y*`)`
`(us_plus:`*m x y*`)`

These three expressions all represent the sum of the values represented by *x* and *y* carried out in machine mode *m*. They differ in their behavior on overflow of integer modes. `plus` wraps round modulo the width of *m*; `ss_plus` saturates at the maximum signed value representable in *m*; `us_plus` saturates at the maximum unsigned value.

`(lo_sum:`*m x y*`)`

This expression represents the sum of *x* and the low-order bits of *y*. It is used with `high` (see Section 13.7 [Constants], page 240) to represent the typical two-instruction sequence used in RISC machines to reference a global memory location.

The number of low order bits is machine-dependent but is normally the number of bits in a `Pmode` item minus the number of bits set by `high`.

m should be `Pmode`.

`(minus:`*m x y*`)`
`(ss_minus:`*m x y*`)`
`(us_minus:`*m x y*`)`

These three expressions represent the result of subtracting *y* from *x*, carried out in mode *M*. Behavior on overflow is the same as for the three variants of `plus` (see above).

`(compare:`*m x y*`)`

Represents the result of subtracting *y* from *x* for purposes of comparison. The result is computed without overflow, as if with infinite precision.

Of course, machines can't really subtract with infinite precision. However, they can pretend to do so when only the sign of the result will be used, which is the case when the result is stored in the condition code. And that is the *only* way this kind of expression may validly be used: as a value to be stored in the condition codes, either `(cc0)` or a register. See Section 13.10 [Comparisons], page 253.

The mode *m* is not related to the modes of *x* and *y*, but instead is the mode of the condition code value. If `(cc0)` is used, it is `VOIDmode`. Otherwise it is some mode in class `MODE_CC`, often `CCmode`. See Section 17.16 [Condition Code], page 506. If *m* is `VOIDmode` or `CCmode`, the operation returns sufficient information (in an unspecified format) so that any comparison operator can be applied to the result of the `COMPARE` operation. For other modes in class `MODE_CC`, the operation only returns a subset of this information.

Normally, *x* and *y* must have the same mode. Otherwise, `compare` is valid only if the mode of *x* is in class `MODE_INT` and *y* is a `const_int` or `const_double` with mode `VOIDmode`. The mode of *x* determines what mode the comparison is to be done in; thus it must not be `VOIDmode`.

If one of the operands is a constant, it should be placed in the second operand and the comparison code adjusted as appropriate.

A `compare` specifying two `VOIDmode` constants is not valid since there is no way to know in what mode the comparison is to be performed; the comparison must either be folded during the compilation or the first operand must be loaded into a register while its mode is still known.

`(neg:`*m* *x*`)`
`(ss_neg:`*m* *x*`)`
`(us_neg:`*m* *x*`)`

These two expressions represent the negation (subtraction from zero) of the value represented by *x*, carried out in mode *m*. They differ in the behavior on overflow of integer modes. In the case of `neg`, the negation of the operand may be a number not representable in mode *m*, in which case it is truncated to *m*. `ss_neg` and `us_neg` ensure that an out-of-bounds result saturates to the maximum or minimum signed or unsigned value.

`(mult:`*m* *x* *y*`)`
`(ss_mult:`*m* *x* *y*`)`
`(us_mult:`*m* *x* *y*`)`

Represents the signed product of the values represented by *x* and *y* carried out in machine mode *m*. `ss_mult` and `us_mult` ensure that an out-of-bounds result saturates to the maximum or minimum signed or unsigned value.

Some machines support a multiplication that generates a product wider than the operands. Write the pattern for this as

```
(mult:m (sign_extend:m x) (sign_extend:m y))
```

where *m* is wider than the modes of *x* and *y*, which need not be the same.

For unsigned widening multiplication, use the same idiom, but with `zero_extend` instead of `sign_extend`.

`(fma:`*m* *x* *y* *z*`)`

Represents the `fma`, `fmaf`, and `fmal` builtin functions that do a combined multiply of *x* and *y* and then adding to*z* without doing an intermediate rounding step.

`(div:`*m* *x* *y*`)`
`(ss_div:`*m* *x* *y*`)`

Represents the quotient in signed division of *x* by *y*, carried out in machine mode *m*. If *m* is a floating point mode, it represents the exact quotient; otherwise, the integerized quotient. `ss_div` ensures that an out-of-bounds result saturates to the maximum or minimum signed value.

Some machines have division instructions in which the operands and quotient widths are not all the same; you should represent such instructions using `truncate` and `sign_extend` as in,

```
(truncate:m1 (div:m2 x (sign_extend:m2 y)))
```

(udiv:*m* *x* *y*)
(us_div:*m* *x* *y*)
: Like `div` but represents unsigned division. `us_div` ensures that an out-of-bounds result saturates to the maximum or minimum unsigned value.

(mod:*m* *x* *y*)
(umod:*m* *x* *y*)
: Like `div` and `udiv` but represent the remainder instead of the quotient.

(smin:*m* *x* *y*)
(smax:*m* *x* *y*)
: Represents the smaller (for `smin`) or larger (for `smax`) of *x* and *y*, interpreted as signed values in mode *m*. When used with floating point, if both operands are zeros, or if either operand is `NaN`, then it is unspecified which of the two operands is returned as the result.

(umin:*m* *x* *y*)
(umax:*m* *x* *y*)
: Like `smin` and `smax`, but the values are interpreted as unsigned integers.

(not:*m* *x*)
: Represents the bitwise complement of the value represented by *x*, carried out in mode *m*, which must be a fixed-point machine mode.

(and:*m* *x* *y*)
: Represents the bitwise logical-and of the values represented by *x* and *y*, carried out in machine mode *m*, which must be a fixed-point machine mode.

(ior:*m* *x* *y*)
: Represents the bitwise inclusive-or of the values represented by *x* and *y*, carried out in machine mode *m*, which must be a fixed-point mode.

(xor:*m* *x* *y*)
: Represents the bitwise exclusive-or of the values represented by *x* and *y*, carried out in machine mode *m*, which must be a fixed-point mode.

(ashift:*m* *x* *c*)
(ss_ashift:*m* *x* *c*)
(us_ashift:*m* *x* *c*)
: These three expressions represent the result of arithmetically shifting *x* left by *c* places. They differ in their behavior on overflow of integer modes. An `ashift` operation is a plain shift with no special behavior in case of a change in the sign bit; `ss_ashift` and `us_ashift` saturates to the minimum or maximum representable value if any of the bits shifted out differs from the final sign bit.

  x have mode *m*, a fixed-point machine mode. *c* be a fixed-point mode or be a constant with mode `VOIDmode`; which mode is determined by the mode called for in the machine description entry for the left-shift instruction. For example, on the VAX, the mode of *c* is `QImode` regardless of *m*.

`(lshiftrt:m x c)`
`(ashiftrt:m x c)`
Like `ashift` but for right shift. Unlike the case for left shift, these two operations are distinct.

`(rotate:m x c)`
`(rotatert:m x c)`
Similar but represent left and right rotate. If c is a constant, use `rotate`.

`(abs:m x)`

`(ss_abs:m x)`
Represents the absolute value of x, computed in mode m. `ss_abs` ensures that an out-of-bounds result saturates to the maximum signed value.

`(sqrt:m x)`
Represents the square root of x, computed in mode m. Most often m will be a floating point mode.

`(ffs:m x)` Represents one plus the index of the least significant 1-bit in x, represented as an integer of mode m. (The value is zero if x is zero.) The mode of x must be m or `VOIDmode`.

`(clrsb:m x)`
Represents the number of redundant leading sign bits in x, represented as an integer of mode m, starting at the most significant bit position. This is one less than the number of leading sign bits (either 0 or 1), with no special cases. The mode of x must be m or `VOIDmode`.

`(clz:m x)` Represents the number of leading 0-bits in x, represented as an integer of mode m, starting at the most significant bit position. If x is zero, the value is determined by `CLZ_DEFINED_VALUE_AT_ZERO` (see Section 17.31 [Misc], page 573). Note that this is one of the few expressions that is not invariant under widening. The mode of x must be m or `VOIDmode`.

`(ctz:m x)` Represents the number of trailing 0-bits in x, represented as an integer of mode m, starting at the least significant bit position. If x is zero, the value is determined by `CTZ_DEFINED_VALUE_AT_ZERO` (see Section 17.31 [Misc], page 573). Except for this case, `ctz(x)` is equivalent to `ffs(x) - 1`. The mode of x must be m or `VOIDmode`.

`(popcount:m x)`
Represents the number of 1-bits in x, represented as an integer of mode m. The mode of x must be m or `VOIDmode`.

`(parity:m x)`
Represents the number of 1-bits modulo 2 in x, represented as an integer of mode m. The mode of x must be m or `VOIDmode`.

`(bswap:m x)`
Represents the value x with the order of bytes reversed, carried out in mode m, which must be a fixed-point machine mode. The mode of x must be m or `VOIDmode`.

13.10 Comparison Operations

Comparison operators test a relation on two operands and are considered to represent a machine-dependent nonzero value described by, but not necessarily equal to, `STORE_FLAG_VALUE` (see Section 17.31 [Misc], page 573) if the relation holds, or zero if it does not, for comparison operators whose results have a 'MODE_INT' mode, `FLOAT_STORE_FLAG_VALUE` (see Section 17.31 [Misc], page 573) if the relation holds, or zero if it does not, for comparison operators that return floating-point values, and a vector of either `VECTOR_STORE_FLAG_VALUE` (see Section 17.31 [Misc], page 573) if the relation holds, or of zeros if it does not, for comparison operators that return vector results. The mode of the comparison operation is independent of the mode of the data being compared. If the comparison operation is being tested (e.g., the first operand of an `if_then_else`), the mode must be `VOIDmode`.

There are two ways that comparison operations may be used. The comparison operators may be used to compare the condition codes `(cc0)` against zero, as in `(eq (cc0) (const_int 0))`. Such a construct actually refers to the result of the preceding instruction in which the condition codes were set. The instruction setting the condition code must be adjacent to the instruction using the condition code; only `note` insns may separate them.

Alternatively, a comparison operation may directly compare two data objects. The mode of the comparison is determined by the operands; they must both be valid for a common machine mode. A comparison with both operands constant would be invalid as the machine mode could not be deduced from it, but such a comparison should never exist in RTL due to constant folding.

In the example above, if `(cc0)` were last set to `(compare x y)`, the comparison operation is identical to `(eq x y)`. Usually only one style of comparisons is supported on a particular machine, but the combine pass will try to merge the operations to produce the `eq` shown in case it exists in the context of the particular insn involved.

Inequality comparisons come in two flavors, signed and unsigned. Thus, there are distinct expression codes `gt` and `gtu` for signed and unsigned greater-than. These can produce different results for the same pair of integer values: for example, 1 is signed greater-than −1 but not unsigned greater-than, because −1 when regarded as unsigned is actually `0xffffffff` which is greater than 1.

The signed comparisons are also used for floating point values. Floating point comparisons are distinguished by the machine modes of the operands.

`(eq:m x y)`
: `STORE_FLAG_VALUE` if the values represented by *x* and *y* are equal, otherwise 0.

`(ne:m x y)`
: `STORE_FLAG_VALUE` if the values represented by *x* and *y* are not equal, otherwise 0.

`(gt:m x y)`
: `STORE_FLAG_VALUE` if the *x* is greater than *y*. If they are fixed-point, the comparison is done in a signed sense.

`(gtu:m x y)`
: Like `gt` but does unsigned comparison, on fixed-point numbers only.

`(lt:m x y)`
`(ltu:m x y)`
Like `gt` and `gtu` but test for "less than".

`(ge:m x y)`
`(geu:m x y)`
Like `gt` and `gtu` but test for "greater than or equal".

`(le:m x y)`
`(leu:m x y)`
Like `gt` and `gtu` but test for "less than or equal".

`(if_then_else cond then else)`
This is not a comparison operation but is listed here because it is always used in conjunction with a comparison operation. To be precise, *cond* is a comparison expression. This expression represents a choice, according to *cond*, between the value represented by *then* and the one represented by *else*.

On most machines, `if_then_else` expressions are valid only to express conditional jumps.

`(cond [test1 value1 test2 value2 ...] default)`
Similar to `if_then_else`, but more general. Each of *test1*, *test2*, ... is performed in turn. The result of this expression is the *value* corresponding to the first nonzero test, or *default* if none of the tests are nonzero expressions.

This is currently not valid for instruction patterns and is supported only for insn attributes. See Section 16.19 [Insn Attributes], page 394.

13.11 Bit-Fields

Special expression codes exist to represent bit-field instructions.

`(sign_extract:m loc size pos)`
This represents a reference to a sign-extended bit-field contained or starting in *loc* (a memory or register reference). The bit-field is *size* bits wide and starts at bit *pos*. The compilation option `BITS_BIG_ENDIAN` says which end of the memory unit *pos* counts from.

If *loc* is in memory, its mode must be a single-byte integer mode. If *loc* is in a register, the mode to use is specified by the operand of the `insv` or `extv` pattern (see Section 16.9 [Standard Names], page 349) and is usually a full-word integer mode, which is the default if none is specified.

The mode of *pos* is machine-specific and is also specified in the `insv` or `extv` pattern.

The mode *m* is the same as the mode that would be used for *loc* if it were a register.

A `sign_extract` can not appear as an lvalue, or part thereof, in RTL.

`(zero_extract:m loc size pos)`
Like `sign_extract` but refers to an unsigned or zero-extended bit-field. The same sequence of bits are extracted, but they are filled to an entire word with zeros instead of by sign-extension.

Unlike `sign_extract`, this type of expressions can be lvalues in RTL; they may appear on the left side of an assignment, indicating insertion of a value into the specified bit-field.

13.12 Vector Operations

All normal RTL expressions can be used with vector modes; they are interpreted as operating on each part of the vector independently. Additionally, there are a few new expressions to describe specific vector operations.

`(vec_merge:`*m* *vec1* *vec2* *items*`)`

This describes a merge operation between two vectors. The result is a vector of mode *m*; its elements are selected from either *vec1* or *vec2*. Which elements are selected is described by *items*, which is a bit mask represented by a `const_int`; a zero bit indicates the corresponding element in the result vector is taken from *vec2* while a set bit indicates it is taken from *vec1*.

`(vec_select:`*m* *vec1* *selection*`)`

This describes an operation that selects parts of a vector. *vec1* is the source vector, and *selection* is a `parallel` that contains a `const_int` for each of the subparts of the result vector, giving the number of the source subpart that should be stored into it. The result mode *m* is either the submode for a single element of *vec1* (if only one subpart is selected), or another vector mode with that element submode (if multiple subparts are selected).

`(vec_concat:`*m* *x1* *x2*`)`

Describes a vector concat operation. The result is a concatenation of the vectors or scalars *x1* and *x2*; its length is the sum of the lengths of the two inputs.

`(vec_duplicate:`*m* *x*`)`

This operation converts a scalar into a vector or a small vector into a larger one by duplicating the input values. The output vector mode must have the same submodes as the input vector mode or the scalar modes, and the number of output parts must be an integer multiple of the number of input parts.

13.13 Conversions

All conversions between machine modes must be represented by explicit conversion operations. For example, an expression which is the sum of a byte and a full word cannot be written as `(plus:SI (reg:QI 34) (reg:SI 80))` because the `plus` operation requires two operands of the same machine mode. Therefore, the byte-sized operand is enclosed in a conversion operation, as in

```
(plus:SI (sign_extend:SI (reg:QI 34)) (reg:SI 80))
```

The conversion operation is not a mere placeholder, because there may be more than one way of converting from a given starting mode to the desired final mode. The conversion operation code says how to do it.

For all conversion operations, *x* must not be `VOIDmode` because the mode in which to do the conversion would not be known. The conversion must either be done at compile-time or *x* must be placed into a register.

`(sign_extend:m x)`
: Represents the result of sign-extending the value x to machine mode m. m must be a fixed-point mode and x a fixed-point value of a mode narrower than m.

`(zero_extend:m x)`
: Represents the result of zero-extending the value x to machine mode m. m must be a fixed-point mode and x a fixed-point value of a mode narrower than m.

`(float_extend:m x)`
: Represents the result of extending the value x to machine mode m. m must be a floating point mode and x a floating point value of a mode narrower than m.

`(truncate:m x)`
: Represents the result of truncating the value x to machine mode m. m must be a fixed-point mode and x a fixed-point value of a mode wider than m.

`(ss_truncate:m x)`
: Represents the result of truncating the value x to machine mode m, using signed saturation in the case of overflow. Both m and the mode of x must be fixed-point modes.

`(us_truncate:m x)`
: Represents the result of truncating the value x to machine mode m, using unsigned saturation in the case of overflow. Both m and the mode of x must be fixed-point modes.

`(float_truncate:m x)`
: Represents the result of truncating the value x to machine mode m. m must be a floating point mode and x a floating point value of a mode wider than m.

`(float:m x)`
: Represents the result of converting fixed point value x, regarded as signed, to floating point mode m.

`(unsigned_float:m x)`
: Represents the result of converting fixed point value x, regarded as unsigned, to floating point mode m.

`(fix:m x)`
: When m is a floating-point mode, represents the result of converting floating point value x (valid for mode m) to an integer, still represented in floating point mode m, by rounding towards zero.

  When m is a fixed-point mode, represents the result of converting floating point value x to mode m, regarded as signed. How rounding is done is not specified, so this operation may be used validly in compiling C code only for integer-valued operands.

`(unsigned_fix:m x)`
: Represents the result of converting floating point value x to fixed point mode m, regarded as unsigned. How rounding is done is not specified.

`(fract_convert:m x)`

Represents the result of converting fixed-point value *x* to fixed-point mode *m*, signed integer value *x* to fixed-point mode *m*, floating-point value *x* to fixed-point mode *m*, fixed-point value *x* to integer mode *m* regarded as signed, or fixed-point value *x* to floating-point mode *m*. When overflows or underflows happen, the results are undefined.

`(sat_fract:m x)`

Represents the result of converting fixed-point value *x* to fixed-point mode *m*, signed integer value *x* to fixed-point mode *m*, or floating-point value *x* to fixed-point mode *m*. When overflows or underflows happen, the results are saturated to the maximum or the minimum.

`(unsigned_fract_convert:m x)`

Represents the result of converting fixed-point value *x* to integer mode *m* regarded as unsigned, or unsigned integer value *x* to fixed-point mode *m*. When overflows or underflows happen, the results are undefined.

`(unsigned_sat_fract:m x)`

Represents the result of converting unsigned integer value *x* to fixed-point mode *m*. When overflows or underflows happen, the results are saturated to the maximum or the minimum.

13.14 Declarations

Declaration expression codes do not represent arithmetic operations but rather state assertions about their operands.

`(strict_low_part (subreg:m (reg:n r) 0))`

This expression code is used in only one context: as the destination operand of a `set` expression. In addition, the operand of this expression must be a non-paradoxical `subreg` expression.

The presence of `strict_low_part` says that the part of the register which is meaningful in mode *n*, but is not part of mode *m*, is not to be altered. Normally, an assignment to such a subreg is allowed to have undefined effects on the rest of the register when *m* is less than a word.

13.15 Side Effect Expressions

The expression codes described so far represent values, not actions. But machine instructions never produce values; they are meaningful only for their side effects on the state of the machine. Special expression codes are used to represent side effects.

The body of an instruction is always one of these side effect codes; the codes described above, which represent values, appear only as the operands of these.

`(set lval x)`

Represents the action of storing the value of *x* into the place represented by *lval*. *lval* must be an expression representing a place that can be stored in: `reg` (or `subreg`, `strict_low_part` or `zero_extract`), `mem`, `pc`, `parallel`, or `cc0`.

If *lval* is a `reg`, `subreg` or `mem`, it has a machine mode; then *x* must be valid for that mode.

If *lval* is a `reg` whose machine mode is less than the full width of the register, then it means that the part of the register specified by the machine mode is given the specified value and the rest of the register receives an undefined value. Likewise, if *lval* is a `subreg` whose machine mode is narrower than the mode of the register, the rest of the register can be changed in an undefined way.

If *lval* is a `strict_low_part` of a subreg, then the part of the register specified by the machine mode of the `subreg` is given the value *x* and the rest of the register is not changed.

If *lval* is a `zero_extract`, then the referenced part of the bit-field (a memory or register reference) specified by the `zero_extract` is given the value *x* and the rest of the bit-field is not changed. Note that `sign_extract` can not appear in *lval*.

If *lval* is `(cc0)`, it has no machine mode, and *x* may be either a `compare` expression or a value that may have any mode. The latter case represents a "test" instruction. The expression `(set (cc0) (reg:m n))` is equivalent to `(set (cc0) (compare (reg:m n) (const_int 0)))`. Use the former expression to save space during the compilation.

If *lval* is a `parallel`, it is used to represent the case of a function returning a structure in multiple registers. Each element of the `parallel` is an `expr_list` whose first operand is a `reg` and whose second operand is a `const_int` representing the offset (in bytes) into the structure at which the data in that register corresponds. The first element may be null to indicate that the structure is also passed partly in memory.

If *lval* is `(pc)`, we have a jump instruction, and the possibilities for *x* are very limited. It may be a `label_ref` expression (unconditional jump). It may be an `if_then_else` (conditional jump), in which case either the second or the third operand must be `(pc)` (for the case which does not jump) and the other of the two must be a `label_ref` (for the case which does jump). *x* may also be a `mem` or `(plus:SI (pc) y)`, where *y* may be a `reg` or a `mem`; these unusual patterns are used to represent jumps through branch tables.

If *lval* is neither `(cc0)` nor `(pc)`, the mode of *lval* must not be `VOIDmode` and the mode of *x* must be valid for the mode of *lval*.

lval is customarily accessed with the `SET_DEST` macro and *x* with the `SET_SRC` macro.

`(return)` As the sole expression in a pattern, represents a return from the current function, on machines where this can be done with one instruction, such as VAXen. On machines where a multi-instruction "epilogue" must be executed in order to return from the function, returning is done by jumping to a label which precedes the epilogue, and the `return` expression code is never used.

Inside an `if_then_else` expression, represents the value to be placed in `pc` to return to the caller.

Note that an insn pattern of `(return)` is logically equivalent to `(set (pc) (return))`, but the latter form is never used.

`(simple_return)`

Like `(return)`, but truly represents only a function return, while `(return)` may represent an insn that also performs other functions of the function epilogue. Like `(return)`, this may also occur in conditional jumps.

`(call` *function nargs*`)`

Represents a function call. *function* is a `mem` expression whose address is the address of the function to be called. *nargs* is an expression which can be used for two purposes: on some machines it represents the number of bytes of stack argument; on others, it represents the number of argument registers.

Each machine has a standard machine mode which *function* must have. The machine description defines macro `FUNCTION_MODE` to expand into the requisite mode name. The purpose of this mode is to specify what kind of addressing is allowed, on machines where the allowed kinds of addressing depend on the machine mode being addressed.

`(clobber` *x*`)`

Represents the storing or possible storing of an unpredictable, undescribed value into *x*, which must be a `reg`, `scratch`, `parallel` or `mem` expression.

One place this is used is in string instructions that store standard values into particular hard registers. It may not be worth the trouble to describe the values that are stored, but it is essential to inform the compiler that the registers will be altered, lest it attempt to keep data in them across the string instruction.

If *x* is `(mem:BLK (const_int 0))` or `(mem:BLK (scratch))`, it means that all memory locations must be presumed clobbered. If *x* is a `parallel`, it has the same meaning as a `parallel` in a `set` expression.

Note that the machine description classifies certain hard registers as "call-clobbered". All function call instructions are assumed by default to clobber these registers, so there is no need to use `clobber` expressions to indicate this fact. Also, each function call is assumed to have the potential to alter any memory location, unless the function is declared `const`.

If the last group of expressions in a `parallel` are each a `clobber` expression whose arguments are `reg` or `match_scratch` (see Section 16.4 [RTL Template], page 299) expressions, the combiner phase can add the appropriate `clobber` expressions to an insn it has constructed when doing so will cause a pattern to be matched.

This feature can be used, for example, on a machine that whose multiply and add instructions don't use an MQ register but which has an add-accumulate instruction that does clobber the MQ register. Similarly, a combined instruction might require a temporary register while the constituent instructions might not.

When a `clobber` expression for a register appears inside a `parallel` with other side effects, the register allocator guarantees that the register is unoccupied both before and after that insn if it is a hard register clobber. For pseudo-register clobber, the register allocator and the reload pass do not assign the same hard register to the clobber and the input operands if there is an insn alternative containing the '`&`' constraint (see Section 16.8.4 [Modifiers], page 315) for the clobber and the hard register is in register classes of the clobber in the

alternative. You can clobber either a specific hard register, a pseudo register, or a `scratch` expression; in the latter two cases, GCC will allocate a hard register that is available there for use as a temporary.

For instructions that require a temporary register, you should use `scratch` instead of a pseudo-register because this will allow the combiner phase to add the `clobber` when required. You do this by coding (`clobber` (`match_scratch` ...)). If you do clobber a pseudo register, use one which appears nowhere else—generate a new one each time. Otherwise, you may confuse CSE.

There is one other known use for clobbering a pseudo register in a `parallel`: when one of the input operands of the insn is also clobbered by the insn. In this case, using the same pseudo register in the clobber and elsewhere in the insn produces the expected results.

`(use x)` Represents the use of the value of *x*. It indicates that the value in *x* at this point in the program is needed, even though it may not be apparent why this is so. Therefore, the compiler will not attempt to delete previous instructions whose only effect is to store a value in *x*. *x* must be a `reg` expression.

In some situations, it may be tempting to add a `use` of a register in a `parallel` to describe a situation where the value of a special register will modify the behavior of the instruction. A hypothetical example might be a pattern for an addition that can either wrap around or use saturating addition depending on the value of a special control register:

```
(parallel [(set (reg:SI 2) (unspec:SI [(reg:SI 3)
                                        (reg:SI 4)] 0))
           (use (reg:SI 1))])
```

This will not work, several of the optimizers only look at expressions locally; it is very likely that if you have multiple insns with identical inputs to the `unspec`, they will be optimized away even if register 1 changes in between.

This means that `use` can *only* be used to describe that the register is live. You should think twice before adding `use` statements, more often you will want to use `unspec` instead. The `use` RTX is most commonly useful to describe that a fixed register is implicitly used in an insn. It is also safe to use in patterns where the compiler knows for other reasons that the result of the whole pattern is variable, such as '`movmem`*m*' or '`call`' patterns.

During the reload phase, an insn that has a `use` as pattern can carry a reg_equal note. These `use` insns will be deleted before the reload phase exits.

During the delayed branch scheduling phase, *x* may be an insn. This indicates that *x* previously was located at this place in the code and its data dependencies need to be taken into account. These `use` insns will be deleted before the delayed branch scheduling phase exits.

`(parallel [x0 x1 ...])`
Represents several side effects performed in parallel. The square brackets stand for a vector; the operand of `parallel` is a vector of expressions. *x0*, *x1* and so on are individual side effect expressions—expressions of code `set`, `call`, `return`, `simple_return`, `clobber` or `use`.

"In parallel" means that first all the values used in the individual side-effects are computed, and second all the actual side-effects are performed. For example,

```
(parallel [(set (reg:SI 1) (mem:SI (reg:SI 1)))
           (set (mem:SI (reg:SI 1)) (reg:SI 1))])
```

says unambiguously that the values of hard register 1 and the memory location addressed by it are interchanged. In both places where `(reg:SI 1)` appears as a memory address it refers to the value in register 1 *before* the execution of the insn.

It follows that it is *incorrect* to use `parallel` and expect the result of one `set` to be available for the next one. For example, people sometimes attempt to represent a jump-if-zero instruction this way:

```
(parallel [(set (cc0) (reg:SI 34))
           (set (pc) (if_then_else
                       (eq (cc0) (const_int 0))
                       (label_ref ...)
                       (pc)))])
```

But this is incorrect, because it says that the jump condition depends on the condition code value *before* this instruction, not on the new value that is set by this instruction.

Peephole optimization, which takes place together with final assembly code output, can produce insns whose patterns consist of a `parallel` whose elements are the operands needed to output the resulting assembler code—often `reg`, `mem` or constant expressions. This would not be well-formed RTL at any other stage in compilation, but it is OK then because no further optimization remains to be done. However, the definition of the macro `NOTICE_UPDATE_CC`, if any, must deal with such insns if you define any peephole optimizations.

`(cond_exec [`*cond expr*`])`

Represents a conditionally executed expression. The *expr* is executed only if the *cond* is nonzero. The *cond* expression must not have side-effects, but the *expr* may very well have side-effects.

`(sequence [`*insns* `...])`

Represents a sequence of insns. If a `sequence` appears in the chain of insns, then each of the *insns* that appears in the sequence must be suitable for appearing in the chain of insns, i.e. must satisfy the `INSN_P` predicate.

After delay-slot scheduling is completed, an insn and all the insns that reside in its delay slots are grouped together into a `sequence`. The insn requiring the delay slot is the first insn in the vector; subsequent insns are to be placed in the delay slot.

`INSN_ANNULLED_BRANCH_P` is set on an insn in a delay slot to indicate that a branch insn should be used that will conditionally annul the effect of the insns in the delay slots. In such a case, `INSN_FROM_TARGET_P` indicates that the insn is from the target of the branch and should be executed only if the branch is taken; otherwise the insn should be executed only if the branch is not taken. See Section 16.19.8 [Delay Slots], page 403.

Some back ends also use `sequence` objects for purposes other than delay-slot groups. This is not supported in the common parts of the compiler, which treat such sequences as delay-slot groups.

DWARF2 Call Frame Address (CFA) adjustments are sometimes also expressed using `sequence` objects as the value of a `RTX_FRAME_RELATED_P` note. This only happens if the CFA adjustments cannot be easily derived from the pattern of the instruction to which the note is attached. In such cases, the value of the note is used instead of best-guesing the semantics of the instruction. The back end can attach notes containing a `sequence` of `set` patterns that express the effect of the parent instruction.

These expression codes appear in place of a side effect, as the body of an insn, though strictly speaking they do not always describe side effects as such:

`(asm_input` *s*`)`
: Represents literal assembler code as described by the string *s*.

`(unspec [`*operands* `...] `*index*`)`
`(unspec_volatile [`*operands* `...] `*index*`)`
: Represents a machine-specific operation on *operands*. *index* selects between multiple machine-specific operations. `unspec_volatile` is used for volatile operations and operations that may trap; `unspec` is used for other operations.

These codes may appear inside a `pattern` of an insn, inside a `parallel`, or inside an expression.

`(addr_vec:`*m* `[`*lr0* *lr1* `...])`
: Represents a table of jump addresses. The vector elements *lr0*, etc., are `label_ref` expressions. The mode *m* specifies how much space is given to each address; normally *m* would be `Pmode`.

`(addr_diff_vec:`*m* *base* `[`*lr0* *lr1* `...] `*min* *max* *flags*`)`
: Represents a table of jump addresses expressed as offsets from *base*. The vector elements *lr0*, etc., are `label_ref` expressions and so is *base*. The mode *m* specifies how much space is given to each address-difference. *min* and *max* are set up by branch shortening and hold a label with a minimum and a maximum address, respectively. *flags* indicates the relative position of *base*, *min* and *max* to the containing insn and of *min* and *max* to *base*. See rtl.def for details.

`(prefetch:`*m* *addr* *rw* *locality*`)`
: Represents prefetch of memory at address *addr*. Operand *rw* is 1 if the prefetch is for data to be written, 0 otherwise; targets that do not support write prefetches should treat this as a normal prefetch. Operand *locality* specifies the amount of temporal locality; 0 if there is none or 1, 2, or 3 for increasing levels of temporal locality; targets that do not support locality hints should ignore this.

This insn is used to minimize cache-miss latency by moving data into a cache before it is accessed. It should use only non-faulting data prefetch instructions.

13.16 Embedded Side-Effects on Addresses

Six special side-effect expression codes appear as memory addresses.

`(pre_dec:m x)`

Represents the side effect of decrementing *x* by a standard amount and represents also the value that *x* has after being decremented. *x* must be a `reg` or `mem`, but most machines allow only a `reg`. *m* must be the machine mode for pointers on the machine in use. The amount *x* is decremented by is the length in bytes of the machine mode of the containing memory reference of which this expression serves as the address. Here is an example of its use:

```
(mem:DF (pre_dec:SI (reg:SI 39)))
```

This says to decrement pseudo register 39 by the length of a `DFmode` value and use the result to address a `DFmode` value.

`(pre_inc:m x)`

Similar, but specifies incrementing *x* instead of decrementing it.

`(post_dec:m x)`

Represents the same side effect as `pre_dec` but a different value. The value represented here is the value *x* has *before* being decremented.

`(post_inc:m x)`

Similar, but specifies incrementing *x* instead of decrementing it.

`(post_modify:m x y)`

Represents the side effect of setting *x* to *y* and represents *x* before *x* is modified. *x* must be a `reg` or `mem`, but most machines allow only a `reg`. *m* must be the machine mode for pointers on the machine in use.

The expression *y* must be one of three forms: `(plus:m x z)`, `(minus:m x z)`, or `(plus:m x i)`, where *z* is an index register and *i* is a constant.

Here is an example of its use:

```
(mem:SF (post_modify:SI (reg:SI 42) (plus (reg:SI 42)
                                          (reg:SI 48))))
```

This says to modify pseudo register 42 by adding the contents of pseudo register 48 to it, after the use of what ever 42 points to.

`(pre_modify:m x expr)`

Similar except side effects happen before the use.

These embedded side effect expressions must be used with care. Instruction patterns may not use them. Until the '`flow`' pass of the compiler, they may occur only to represent pushes onto the stack. The '`flow`' pass finds cases where registers are incremented or decremented in one instruction and used as an address shortly before or after; these cases are then transformed to use pre- or post-increment or -decrement.

If a register used as the operand of these expressions is used in another address in an insn, the original value of the register is used. Uses of the register outside of an address are not permitted within the same insn as a use in an embedded side effect expression because such insns behave differently on different machines and hence must be treated as ambiguous and disallowed.

An instruction that can be represented with an embedded side effect could also be represented using `parallel` containing an additional `set` to describe how the address register is altered. This is not done because machines that allow these operations at all typically allow them wherever a memory address is called for. Describing them as additional parallel stores would require doubling the number of entries in the machine description.

13.17 Assembler Instructions as Expressions

The RTX code `asm_operands` represents a value produced by a user-specified assembler instruction. It is used to represent an `asm` statement with arguments. An `asm` statement with a single output operand, like this:

```
asm ("foo %1,%2,%0" : "=a" (outputvar) : "g" (x + y), "di" (*z));
```

is represented using a single `asm_operands` RTX which represents the value that is stored in `outputvar`:

```
(set rtx-for-outputvar
     (asm_operands "foo %1,%2,%0" "a" 0
                   [rtx-for-addition-result rtx-for-*z]
                   [(asm_input:m1 "g")
                    (asm_input:m2 "di")]))
```

Here the operands of the `asm_operands` RTX are the assembler template string, the output-operand's constraint, the index-number of the output operand among the output operands specified, a vector of input operand RTX's, and a vector of input-operand modes and constraints. The mode *m1* is the mode of the sum `x+y`; *m2* is that of `*z`.

When an `asm` statement has multiple output values, its insn has several such `set` RTX's inside of a `parallel`. Each `set` contains an `asm_operands`; all of these share the same assembler template and vectors, but each contains the constraint for the respective output operand. They are also distinguished by the output-operand index number, which is 0, 1, . . . for successive output operands.

13.18 Variable Location Debug Information in RTL

Variable tracking relies on `MEM_EXPR` and `REG_EXPR` annotations to determine what user variables memory and register references refer to.

Variable tracking at assignments uses these notes only when they refer to variables that live at fixed locations (e.g., addressable variables, global non-automatic variables). For variables whose location may vary, it relies on the following types of notes.

`(var_location:`*mode var exp stat*`)`
: Binds variable `var`, a tree, to value *exp*, an RTL expression. It appears only in `NOTE_INSN_VAR_LOCATION` and `DEBUG_INSN`s, with slightly different meanings. *mode*, if present, represents the mode of *exp*, which is useful if it is a modeless expression. *stat* is only meaningful in notes, indicating whether the variable is known to be initialized or uninitialized.

`(debug_expr:`*mode decl*`)`
: Stands for the value bound to the `DEBUG_EXPR_DECL` *decl*, that points back to it, within value expressions in `VAR_LOCATION` nodes.

13.19 Insns

The RTL representation of the code for a function is a doubly-linked chain of objects called *insns*. Insns are expressions with special codes that are used for no other purpose. Some insns are actual instructions; others represent dispatch tables for `switch` statements; others represent labels to jump to or various sorts of declarative information.

In addition to its own specific data, each insn must have a unique id-number that distinguishes it from all other insns in the current function (after delayed branch scheduling, copies of an insn with the same id-number may be present in multiple places in a function, but these copies will always be identical and will only appear inside a `sequence`), and chain pointers to the preceding and following insns. These three fields occupy the same position in every insn, independent of the expression code of the insn. They could be accessed with `XEXP` and `XINT`, but instead three special macros are always used:

`INSN_UID (i)`
: Accesses the unique id of insn *i*.

`PREV_INSN (i)`
: Accesses the chain pointer to the insn preceding *i*. If *i* is the first insn, this is a null pointer.

`NEXT_INSN (i)`
: Accesses the chain pointer to the insn following *i*. If *i* is the last insn, this is a null pointer.

The first insn in the chain is obtained by calling `get_insns`; the last insn is the result of calling `get_last_insn`. Within the chain delimited by these insns, the `NEXT_INSN` and `PREV_INSN` pointers must always correspond: if *insn* is not the first insn,

```
NEXT_INSN (PREV_INSN (insn)) == insn
```

is always true and if *insn* is not the last insn,

```
PREV_INSN (NEXT_INSN (insn)) == insn
```

is always true.

After delay slot scheduling, some of the insns in the chain might be `sequence` expressions, which contain a vector of insns. The value of `NEXT_INSN` in all but the last of these insns is the next insn in the vector; the value of `NEXT_INSN` of the last insn in the vector is the same as the value of `NEXT_INSN` for the `sequence` in which it is contained. Similar rules apply for `PREV_INSN`.

This means that the above invariants are not necessarily true for insns inside `sequence` expressions. Specifically, if *insn* is the first insn in a `sequence`, `NEXT_INSN (PREV_INSN (insn))` is the insn containing the `sequence` expression, as is the value of `PREV_INSN (NEXT_INSN (insn))` if *insn* is the last insn in the `sequence` expression. You can use these expressions to find the containing `sequence` expression.

Every insn has one of the following expression codes:

`insn`
: The expression code `insn` is used for instructions that do not jump and do not do function calls. `sequence` expressions are always contained in insns with code `insn` even if one of those insns should jump or do function calls.

  Insns with code `insn` have four additional fields beyond the three mandatory ones listed above. These four are described in a table below.

`jump_insn`

The expression code `jump_insn` is used for instructions that may jump (or, more generally, may contain `label_ref` expressions to which `pc` can be set in that instruction). If there is an instruction to return from the current function, it is recorded as a `jump_insn`.

`jump_insn` insns have the same extra fields as `insn` insns, accessed in the same way and in addition contain a field `JUMP_LABEL` which is defined once jump optimization has completed.

For simple conditional and unconditional jumps, this field contains the `code_label` to which this insn will (possibly conditionally) branch. In a more complex jump, `JUMP_LABEL` records one of the labels that the insn refers to; other jump target labels are recorded as `REG_LABEL_TARGET` notes. The exception is `addr_vec` and `addr_diff_vec`, where `JUMP_LABEL` is `NULL_RTX` and the only way to find the labels is to scan the entire body of the insn.

Return insns count as jumps, but since they do not refer to any labels, their `JUMP_LABEL` is `NULL_RTX`.

`call_insn`

The expression code `call_insn` is used for instructions that may do function calls. It is important to distinguish these instructions because they imply that certain registers and memory locations may be altered unpredictably.

`call_insn` insns have the same extra fields as `insn` insns, accessed in the same way and in addition contain a field `CALL_INSN_FUNCTION_USAGE`, which contains a list (chain of `expr_list` expressions) containing `use`, `clobber` and sometimes `set` expressions that denote hard registers and `mem`s used or clobbered by the called function.

A `mem` generally points to a stack slot in which arguments passed to the libcall by reference (see Section 17.10.7 [Register Arguments], page 478) are stored. If the argument is caller-copied (see Section 17.10.7 [Register Arguments], page 478), the stack slot will be mentioned in `clobber` and `use` entries; if it's callee-copied, only a `use` will appear, and the `mem` may point to addresses that are not stack slots.

Registers occurring inside a `clobber` in this list augment registers specified in `CALL_USED_REGISTERS` (see Section 17.7.1 [Register Basics], page 447).

If the list contains a `set` involving two registers, it indicates that the function returns one of its arguments. Such a `set` may look like a no-op if the same register holds the argument and the return value.

`code_label`

A `code_label` insn represents a label that a jump insn can jump to. It contains two special fields of data in addition to the three standard ones. `CODE_LABEL_NUMBER` is used to hold the *label number*, a number that identifies this label uniquely among all the labels in the compilation (not just in the current function). Ultimately, the label is represented in the assembler output as an assembler label, usually of the form '`L`*n*' where *n* is the label number.

When a `code_label` appears in an RTL expression, it normally appears within a `label_ref` which represents the address of the label, as a number.

Besides as a `code_label`, a label can also be represented as a `note` of type `NOTE_INSN_DELETED_LABEL`.

The field `LABEL_NUSES` is only defined once the jump optimization phase is completed. It contains the number of times this label is referenced in the current function.

The field `LABEL_KIND` differentiates four different types of labels: `LABEL_NORMAL`, `LABEL_STATIC_ENTRY`, `LABEL_GLOBAL_ENTRY`, and `LABEL_WEAK_ENTRY`. The only labels that do not have type `LABEL_NORMAL` are *alternate entry points* to the current function. These may be static (visible only in the containing translation unit), global (exposed to all translation units), or weak (global, but can be overridden by another symbol with the same name).

Much of the compiler treats all four kinds of label identically. Some of it needs to know whether or not a label is an alternate entry point; for this purpose, the macro `LABEL_ALT_ENTRY_P` is provided. It is equivalent to testing whether '`LABEL_KIND (label) == LABEL_NORMAL`'. The only place that cares about the distinction between static, global, and weak alternate entry points, besides the front-end code that creates them, is the function `output_alternate_entry_point`, in '`final.c`'.

To set the kind of a label, use the `SET_LABEL_KIND` macro.

`jump_table_data`

A `jump_table_data` insn is a placeholder for the jump-table data of a `casesi` or `tablejump` insn. They are placed after a `tablejump_p` insn. A `jump_table_data` insn is not part o a basic blockm but it is associated with the basic block that ends with the `tablejump_p` insn. The `PATTERN` of a `jump_table_data` is always either an `addr_vec` or an `addr_diff_vec`, and a `jump_table_data` insn is always preceded by a `code_label`. The `tablejump_p` insn refers to that `code_label` via its `JUMP_LABEL`.

`barrier`

Barriers are placed in the instruction stream when control cannot flow past them. They are placed after unconditional jump instructions to indicate that the jumps are unconditional and after calls to `volatile` functions, which do not return (e.g., `exit`). They contain no information beyond the three standard fields.

`note`

`note` insns are used to represent additional debugging and declarative information. They contain two nonstandard fields, an integer which is accessed with the macro `NOTE_LINE_NUMBER` and a string accessed with `NOTE_SOURCE_FILE`.

If `NOTE_LINE_NUMBER` is positive, the note represents the position of a source line and `NOTE_SOURCE_FILE` is the source file name that the line came from. These notes control generation of line number data in the assembler output.

Otherwise, `NOTE_LINE_NUMBER` is not really a line number but a code with one of the following values (and `NOTE_SOURCE_FILE` must contain a null pointer):

`NOTE_INSN_DELETED`

Such a note is completely ignorable. Some passes of the compiler delete insns by altering them into notes of this kind.

`NOTE_INSN_DELETED_LABEL`
: This marks what used to be a `code_label`, but was not used for other purposes than taking its address and was transformed to mark that no code jumps to it.

`NOTE_INSN_BLOCK_BEG`
`NOTE_INSN_BLOCK_END`
: These types of notes indicate the position of the beginning and end of a level of scoping of variable names. They control the output of debugging information.

`NOTE_INSN_EH_REGION_BEG`
`NOTE_INSN_EH_REGION_END`
: These types of notes indicate the position of the beginning and end of a level of scoping for exception handling. `NOTE_EH_HANDLER` identifies which region is associated with these notes.

`NOTE_INSN_FUNCTION_BEG`
: Appears at the start of the function body, after the function prologue.

`NOTE_INSN_VAR_LOCATION`
: This note is used to generate variable location debugging information. It indicates that the user variable in its `VAR_LOCATION` operand is at the location given in the RTL expression, or holds a value that can be computed by evaluating the RTL expression from that static point in the program up to the next such note for the same user variable.

These codes are printed symbolically when they appear in debugging dumps.

`debug_insn`
: The expression code `debug_insn` is used for pseudo-instructions that hold debugging information for variable tracking at assignments (see '`-fvar-tracking-assignments`' option). They are the RTL representation of `GIMPLE_DEBUG` statements (Section 11.7.7 [`GIMPLE_DEBUG`], page 194), with a `VAR_LOCATION` operand that binds a user variable tree to an RTL representation of the `value` in the corresponding statement. A `DEBUG_EXPR` in it stands for the value bound to the corresponding `DEBUG_EXPR_DECL`.

Throughout optimization passes, binding information is kept in pseudo-instruction form, so that, unlike notes, it gets the same treatment and adjustments that regular instructions would. It is the variable tracking pass that turns these pseudo-instructions into var location notes, analyzing control flow, value equivalences and changes to registers and memory referenced in value expressions, propagating the values of debug temporaries and determining expressions that can be used to compute the value of each user variable at as many points (ranges, actually) in the program as possible.

Unlike `NOTE_INSN_VAR_LOCATION`, the value expression in an `INSN_VAR_LOCATION` denotes a value at that specific point in the program, rather than an expression that can be evaluated at any later point before an overriding

VAR_LOCATION is encountered. E.g., if a user variable is bound to a REG and then a subsequent insn modifies the REG, the note location would keep mapping the user variable to the register across the insn, whereas the insn location would keep the variable bound to the value, so that the variable tracking pass would emit another location note for the variable at the point in which the register is modified.

The machine mode of an insn is normally VOIDmode, but some phases use the mode for various purposes.

The common subexpression elimination pass sets the mode of an insn to QImode when it is the first insn in a block that has already been processed.

The second Haifa scheduling pass, for targets that can multiple issue, sets the mode of an insn to TImode when it is believed that the instruction begins an issue group. That is, when the instruction cannot issue simultaneously with the previous. This may be relied on by later passes, in particular machine-dependent reorg.

Here is a table of the extra fields of insn, jump_insn and call_insn insns:

PATTERN (*i*)

An expression for the side effect performed by this insn. This must be one of the following codes: set, call, use, clobber, return, simple_return, asm_input, asm_output, addr_vec, addr_diff_vec, trap_if, unspec, unspec_volatile, parallel, cond_exec, or sequence. If it is a parallel, each element of the parallel must be one these codes, except that parallel expressions cannot be nested and addr_vec and addr_diff_vec are not permitted inside a parallel expression.

INSN_CODE (*i*)

An integer that says which pattern in the machine description matches this insn, or −1 if the matching has not yet been attempted.

Such matching is never attempted and this field remains −1 on an insn whose pattern consists of a single use, clobber, asm_input, addr_vec or addr_diff_vec expression.

Matching is also never attempted on insns that result from an asm statement. These contain at least one asm_operands expression. The function asm_noperands returns a non-negative value for such insns.

In the debugging output, this field is printed as a number followed by a symbolic representation that locates the pattern in the 'md' file as some small positive or negative offset from a named pattern.

LOG_LINKS (*i*)

A list (chain of insn_list expressions) giving information about dependencies between instructions within a basic block. Neither a jump nor a label may come between the related insns. These are only used by the schedulers and by combine. This is a deprecated data structure. Def-use and use-def chains are now preferred.

`REG_NOTES (i)`
: A list (chain of `expr_list`, `insn_list` and `int_list` expressions) giving miscellaneous information about the insn. It is often information pertaining to the registers used in this insn.

The `LOG_LINKS` field of an insn is a chain of `insn_list` expressions. Each of these has two operands: the first is an insn, and the second is another `insn_list` expression (the next one in the chain). The last `insn_list` in the chain has a null pointer as second operand. The significant thing about the chain is which insns appear in it (as first operands of `insn_list` expressions). Their order is not significant.

This list is originally set up by the flow analysis pass; it is a null pointer until then. Flow only adds links for those data dependencies which can be used for instruction combination. For each insn, the flow analysis pass adds a link to insns which store into registers values that are used for the first time in this insn.

The `REG_NOTES` field of an insn is a chain similar to the `LOG_LINKS` field but it includes `expr_list` and `int_list` expressions in addition to `insn_list` expressions. There are several kinds of register notes, which are distinguished by the machine mode, which in a register note is really understood as being an `enum reg_note`. The first operand *op* of the note is data whose meaning depends on the kind of note.

The macro `REG_NOTE_KIND (x)` returns the kind of register note. Its counterpart, the macro `PUT_REG_NOTE_KIND (x, newkind)` sets the register note type of *x* to be *newkind*.

Register notes are of three classes: They may say something about an input to an insn, they may say something about an output of an insn, or they may create a linkage between two insns. There are also a set of values that are only used in `LOG_LINKS`.

These register notes annotate inputs to an insn:

`REG_DEAD`
: The value in *op* dies in this insn; that is to say, altering the value immediately after this insn would not affect the future behavior of the program.

It does not follow that the register *op* has no useful value after this insn since *op* is not necessarily modified by this insn. Rather, no subsequent instruction uses the contents of *op*.

`REG_UNUSED`
: The register *op* being set by this insn will not be used in a subsequent insn. This differs from a `REG_DEAD` note, which indicates that the value in an input will not be used subsequently. These two notes are independent; both may be present for the same register.

`REG_INC`
: The register *op* is incremented (or decremented; at this level there is no distinction) by an embedded side effect inside this insn. This means it appears in a `post_inc`, `pre_inc`, `post_dec` or `pre_dec` expression.

`REG_NONNEG`
: The register *op* is known to have a nonnegative value when this insn is reached. This is used so that decrement and branch until zero instructions, such as the m68k dbra, can be matched.

The `REG_NONNEG` note is added to insns only if the machine description has a '`decrement_and_branch_until_zero`' pattern.

`REG_LABEL_OPERAND`
This insn uses *op*, a `code_label` or a `note` of type `NOTE_INSN_DELETED_LABEL`, but is not a `jump_insn`, or it is a `jump_insn` that refers to the operand as an ordinary operand. The label may still eventually be a jump target, but if so in an indirect jump in a subsequent insn. The presence of this note allows jump optimization to be aware that *op* is, in fact, being used, and flow optimization to build an accurate flow graph.

`REG_LABEL_TARGET`
This insn is a `jump_insn` but not an `addr_vec` or `addr_diff_vec`. It uses *op*, a `code_label` as a direct or indirect jump target. Its purpose is similar to that of `REG_LABEL_OPERAND`. This note is only present if the insn has multiple targets; the last label in the insn (in the highest numbered insn-field) goes into the `JUMP_LABEL` field and does not have a `REG_LABEL_TARGET` note. See Section 13.19 [Insns], page 265.

`REG_CROSSING_JUMP`
This insn is a branching instruction (either an unconditional jump or an indirect jump) which crosses between hot and cold sections, which could potentially be very far apart in the executable. The presence of this note indicates to other optimizations that this branching instruction should not be "collapsed" into a simpler branching construct. It is used when the optimization to partition basic blocks into hot and cold sections is turned on.

`REG_SETJMP`
Appears attached to each `CALL_INSN` to `setjmp` or a related function.

The following notes describe attributes of outputs of an insn:

`REG_EQUIV`
`REG_EQUAL`
This note is only valid on an insn that sets only one register and indicates that that register will be equal to *op* at run time; the scope of this equivalence differs between the two types of notes. The value which the insn explicitly copies into the register may look different from *op*, but they will be equal at run time. If the output of the single `set` is a `strict_low_part` expression, the note refers to the register that is contained in `SUBREG_REG` of the `subreg` expression.

For `REG_EQUIV`, the register is equivalent to *op* throughout the entire function, and could validly be replaced in all its occurrences by *op*. ("Validly" here refers to the data flow of the program; simple replacement may make some insns invalid.) For example, when a constant is loaded into a register that is never assigned any other value, this kind of note is used.

When a parameter is copied into a pseudo-register at entry to a function, a note of this kind records that the register is equivalent to the stack slot where the parameter was passed. Although in this case the register may be set by other insns, it is still valid to replace the register by the stack slot throughout the function.

A `REG_EQUIV` note is also used on an instruction which copies a register parameter into a pseudo-register at entry to a function, if there is a stack slot where

that parameter could be stored. Although other insns may set the pseudo-register, it is valid for the compiler to replace the pseudo-register by stack slot throughout the function, provided the compiler ensures that the stack slot is properly initialized by making the replacement in the initial copy instruction as well. This is used on machines for which the calling convention allocates stack space for register parameters. See `REG_PARM_STACK_SPACE` in Section 17.10.6 [Stack Arguments], page 476.

In the case of `REG_EQUAL`, the register that is set by this insn will be equal to *op* at run time at the end of this insn but not necessarily elsewhere in the function. In this case, *op* is typically an arithmetic expression. For example, when a sequence of insns such as a library call is used to perform an arithmetic operation, this kind of note is attached to the insn that produces or copies the final value.

These two notes are used in different ways by the compiler passes. `REG_EQUAL` is used by passes prior to register allocation (such as common subexpression elimination and loop optimization) to tell them how to think of that value. `REG_EQUIV` notes are used by register allocation to indicate that there is an available substitute expression (either a constant or a `mem` expression for the location of a parameter on the stack) that may be used in place of a register if insufficient registers are available.

Except for stack homes for parameters, which are indicated by a `REG_EQUIV` note and are not useful to the early optimization passes and pseudo registers that are equivalent to a memory location throughout their entire life, which is not detected until later in the compilation, all equivalences are initially indicated by an attached `REG_EQUAL` note. In the early stages of register allocation, a `REG_EQUAL` note is changed into a `REG_EQUIV` note if *op* is a constant and the insn represents the only set of its destination register.

Thus, compiler passes prior to register allocation need only check for `REG_EQUAL` notes and passes subsequent to register allocation need only check for `REG_EQUIV` notes.

These notes describe linkages between insns. They occur in pairs: one insn has one of a pair of notes that points to a second insn, which has the inverse note pointing back to the first insn.

`REG_CC_SETTER`
`REG_CC_USER`

On machines that use `cc0`, the insns which set and use `cc0` set and use `cc0` are adjacent. However, when branch delay slot filling is done, this may no longer be true. In this case a `REG_CC_USER` note will be placed on the insn setting `cc0` to point to the insn using `cc0` and a `REG_CC_SETTER` note will be placed on the insn using `cc0` to point to the insn setting `cc0`.

These values are only used in the `LOG_LINKS` field, and indicate the type of dependency that each link represents. Links which indicate a data dependence (a read after write dependence) do not use any code, they simply have mode `VOIDmode`, and are printed without any descriptive text.

`REG_DEP_TRUE`
This indicates a true dependence (a read after write dependence).

`REG_DEP_OUTPUT`
This indicates an output dependence (a write after write dependence).

`REG_DEP_ANTI`
This indicates an anti dependence (a write after read dependence).

These notes describe information gathered from gcov profile data. They are stored in the `REG_NOTES` field of an insn.

`REG_BR_PROB`
This is used to specify the ratio of branches to non-branches of a branch insn according to the profile data. The note is represented as an `int_list` expression whose integer value is between 0 and REG_BR_PROB_BASE. Larger values indicate a higher probability that the branch will be taken.

`REG_BR_PRED`
These notes are found in JUMP insns after delayed branch scheduling has taken place. They indicate both the direction and the likelihood of the JUMP. The format is a bitmask of ATTR_FLAG_* values.

`REG_FRAME_RELATED_EXPR`
This is used on an RTX_FRAME_RELATED_P insn wherein the attached expression is used in place of the actual insn pattern. This is done in cases where the pattern is either complex or misleading.

For convenience, the machine mode in an `insn_list` or `expr_list` is printed using these symbolic codes in debugging dumps.

The only difference between the expression codes `insn_list` and `expr_list` is that the first operand of an `insn_list` is assumed to be an insn and is printed in debugging dumps as the insn's unique id; the first operand of an `expr_list` is printed in the ordinary way as an expression.

13.20 RTL Representation of Function-Call Insns

Insns that call subroutines have the RTL expression code `call_insn`. These insns must satisfy special rules, and their bodies must use a special RTL expression code, `call`.

A `call` expression has two operands, as follows:

```
(call (mem:fm addr) nbytes)
```

Here *nbytes* is an operand that represents the number of bytes of argument data being passed to the subroutine, *fm* is a machine mode (which must equal as the definition of the `FUNCTION_MODE` macro in the machine description) and *addr* represents the address of the subroutine.

For a subroutine that returns no value, the `call` expression as shown above is the entire body of the insn, except that the insn might also contain `use` or `clobber` expressions.

For a subroutine that returns a value whose mode is not `BLKmode`, the value is returned in a hard register. If this register's number is *r*, then the body of the call insn looks like this:

```
(set (reg:m r)
     (call (mem:fm addr) nbytes))
```

This RTL expression makes it clear (to the optimizer passes) that the appropriate register receives a useful value in this insn.

When a subroutine returns a `BLKmode` value, it is handled by passing to the subroutine the address of a place to store the value. So the call insn itself does not "return" any value, and it has the same RTL form as a call that returns nothing.

On some machines, the call instruction itself clobbers some register, for example to contain the return address. `call_insn` insns on these machines should have a body which is a `parallel` that contains both the `call` expression and `clobber` expressions that indicate which registers are destroyed. Similarly, if the call instruction requires some register other than the stack pointer that is not explicitly mentioned in its RTL, a `use` subexpression should mention that register.

Functions that are called are assumed to modify all registers listed in the configuration macro `CALL_USED_REGISTERS` (see Section 17.7.1 [Register Basics], page 447) and, with the exception of `const` functions and library calls, to modify all of memory.

Insns containing just `use` expressions directly precede the `call_insn` insn to indicate which registers contain inputs to the function. Similarly, if registers other than those in `CALL_USED_REGISTERS` are clobbered by the called function, insns containing a single `clobber` follow immediately after the call to indicate which registers.

13.21 Structure Sharing Assumptions

The compiler assumes that certain kinds of RTL expressions are unique; there do not exist two distinct objects representing the same value. In other cases, it makes an opposite assumption: that no RTL expression object of a certain kind appears in more than one place in the containing structure.

These assumptions refer to a single function; except for the RTL objects that describe global variables and external functions, and a few standard objects such as small integer constants, no RTL objects are common to two functions.

- Each pseudo-register has only a single `reg` object to represent it, and therefore only a single machine mode.
- For any symbolic label, there is only one `symbol_ref` object referring to it.
- All `const_int` expressions with equal values are shared.
- There is only one `pc` expression.
- There is only one `cc0` expression.
- There is only one `const_double` expression with value 0 for each floating point mode. Likewise for values 1 and 2.
- There is only one `const_vector` expression with value 0 for each vector mode, be it an integer or a double constant vector.
- No `label_ref` or `scratch` appears in more than one place in the RTL structure; in other words, it is safe to do a tree-walk of all the insns in the function and assume that each time a `label_ref` or `scratch` is seen it is distinct from all others that are seen.

- Only one `mem` object is normally created for each static variable or stack slot, so these objects are frequently shared in all the places they appear. However, separate but equal objects for these variables are occasionally made.
- When a single `asm` statement has multiple output operands, a distinct `asm_operands` expression is made for each output operand. However, these all share the vector which contains the sequence of input operands. This sharing is used later on to test whether two `asm_operands` expressions come from the same statement, so all optimizations must carefully preserve the sharing if they copy the vector at all.
- No RTL object appears in more than one place in the RTL structure except as described above. Many passes of the compiler rely on this by assuming that they can modify RTL objects in place without unwanted side-effects on other insns.
- During initial RTL generation, shared structure is freely introduced. After all the RTL for a function has been generated, all shared structure is copied by `unshare_all_rtl` in '`emit-rtl.c`', after which the above rules are guaranteed to be followed.
- During the combiner pass, shared structure within an insn can exist temporarily. However, the shared structure is copied before the combiner is finished with the insn. This is done by calling `copy_rtx_if_shared`, which is a subroutine of `unshare_all_rtl`.

13.22 Reading RTL

To read an RTL object from a file, call `read_rtx`. It takes one argument, a stdio stream, and returns a single RTL object. This routine is defined in '`read-rtl.c`'. It is not available in the compiler itself, only the various programs that generate the compiler back end from the machine description.

People frequently have the idea of using RTL stored as text in a file as an interface between a language front end and the bulk of GCC. This idea is not feasible.

GCC was designed to use RTL internally only. Correct RTL for a given program is very dependent on the particular target machine. And the RTL does not contain all the information about the program.

The proper way to interface GCC to a new language front end is with the "tree" data structure, described in the files '`tree.h`' and '`tree.def`'. The documentation for this structure (see Chapter 10 [GENERIC], page 129) is incomplete.

14 Control Flow Graph

A control flow graph (CFG) is a data structure built on top of the intermediate code representation (the RTL or GIMPLE instruction stream) abstracting the control flow behavior of a function that is being compiled. The CFG is a directed graph where the vertices represent basic blocks and edges represent possible transfer of control flow from one basic block to another. The data structures used to represent the control flow graph are defined in 'basic-block.h'.

In GCC, the representation of control flow is maintained throughout the compilation process, from constructing the CFG early in pass_build_cfg to pass_free_cfg (see 'passes.def'). The CFG takes various different modes and may undergo extensive manipulations, but the graph is always valid between its construction and its release. This way, transfer of information such as data flow, a measured profile, or the loop tree, can be propagated through the passes pipeline, and even from GIMPLE to RTL.

Often the CFG may be better viewed as integral part of instruction chain, than structure built on the top of it. Updating the compiler's intermediate representation for instructions can not be easily done without proper maintenance of the CFG simultaneously.

14.1 Basic Blocks

A basic block is a straight-line sequence of code with only one entry point and only one exit. In GCC, basic blocks are represented using the basic_block data type.

Special basic blocks represent possible entry and exit points of a function. These blocks are called ENTRY_BLOCK_PTR and EXIT_BLOCK_PTR. These blocks do not contain any code.

The BASIC_BLOCK array contains all basic blocks in an unspecified order. Each basic_block structure has a field that holds a unique integer identifier index that is the index of the block in the BASIC_BLOCK array. The total number of basic blocks in the function is n_basic_blocks. Both the basic block indices and the total number of basic blocks may vary during the compilation process, as passes reorder, create, duplicate, and destroy basic blocks. The index for any block should never be greater than last_basic_block. The indices 0 and 1 are special codes reserved for ENTRY_BLOCK and EXIT_BLOCK, the indices of ENTRY_BLOCK_PTR and EXIT_BLOCK_PTR.

Two pointer members of the basic_block structure are the pointers next_bb and prev_bb. These are used to keep doubly linked chain of basic blocks in the same order as the underlying instruction stream. The chain of basic blocks is updated transparently by the provided API for manipulating the CFG. The macro FOR_EACH_BB can be used to visit all the basic blocks in lexicographical order, except ENTRY_BLOCK and EXIT_BLOCK. The macro FOR_ALL_BB also visits all basic blocks in lexicographical order, including ENTRY_BLOCK and EXIT_BLOCK.

The functions post_order_compute and inverted_post_order_compute can be used to compute topological orders of the CFG. The orders are stored as vectors of basic block indices. The BASIC_BLOCK array can be used to iterate each basic block by index. Dominator traversals are also possible using walk_dominator_tree. Given two basic blocks A and B, block A dominates block B if A is *always* executed before B.

Each basic_block also contains pointers to the first instruction (the *head*) and the last instruction (the *tail*) or *end* of the instruction stream contained in a basic block. In fact,

since the `basic_block` data type is used to represent blocks in both major intermediate representations of GCC (`GIMPLE` and RTL), there are pointers to the head and end of a basic block for both representations, stored in intermediate representation specific data in the `il` field of `struct basic_block_def`.

For RTL, these pointers are `BB_HEAD` and `BB_END`.

In the RTL representation of a function, the instruction stream contains not only the "real" instructions, but also *notes* or *insn notes* (to distinguish them from *reg notes*). Any function that moves or duplicates the basic blocks needs to take care of updating of these notes. Many of these notes expect that the instruction stream consists of linear regions, so updating can sometimes be tedious. All types of insn notes are defined in '`insn-notes.def`'.

In the RTL function representation, the instructions contained in a basic block always follow a `NOTE_INSN_BASIC_BLOCK`, but zero or more `CODE_LABEL` nodes can precede the block note. A basic block ends with a control flow instruction or with the last instruction before the next `CODE_LABEL` or `NOTE_INSN_BASIC_BLOCK`. By definition, a `CODE_LABEL` cannot appear in the middle of the instruction stream of a basic block.

In addition to notes, the jump table vectors are also represented as "pseudo-instructions" inside the insn stream. These vectors never appear in the basic block and should always be placed just after the table jump instructions referencing them. After removing the table-jump it is often difficult to eliminate the code computing the address and referencing the vector, so cleaning up these vectors is postponed until after liveness analysis. Thus the jump table vectors may appear in the insn stream unreferenced and without any purpose. Before any edge is made *fall-thru*, the existence of such construct in the way needs to be checked by calling `can_fallthru` function.

For the `GIMPLE` representation, the PHI nodes and statements contained in a basic block are in a `gimple_seq` pointed to by the basic block intermediate language specific pointers. Abstract containers and iterators are used to access the PHI nodes and statements in a basic blocks. These iterators are called *GIMPLE statement iterators* (GSIs). Grep for `^gsi` in the various '`gimple-*`' and '`tree-*`' files. The following snippet will pretty-print all PHI nodes the statements of the current function in the GIMPLE representation.

```
basic_block bb;

FOR_EACH_BB (bb)
  {
   gimple_stmt_iterator si;

   for (si = gsi_start_phis (bb); !gsi_end_p (si); gsi_next (&si))
     {
       gimple phi = gsi_stmt (si);
       print_gimple_stmt (dump_file, phi, 0, TDF_SLIM);
     }
   for (si = gsi_start_bb (bb); !gsi_end_p (si); gsi_next (&si))
     {
       gimple stmt = gsi_stmt (si);
       print_gimple_stmt (dump_file, stmt, 0, TDF_SLIM);
     }
  }
```

14.2 Edges

Edges represent possible control flow transfers from the end of some basic block A to the head of another basic block B. We say that A is a predecessor of B, and B is a successor of A. Edges are represented in GCC with the `edge` data type. Each `edge` acts as a link between two basic blocks: The `src` member of an edge points to the predecessor basic block of the `dest` basic block. The members `preds` and `succs` of the `basic_block` data type point to type-safe vectors of edges to the predecessors and successors of the block.

When walking the edges in an edge vector, *edge iterators* should be used. Edge iterators are constructed using the `edge_iterator` data structure and several methods are available to operate on them:

`ei_start` This function initializes an `edge_iterator` that points to the first edge in a vector of edges.

`ei_last` This function initializes an `edge_iterator` that points to the last edge in a vector of edges.

`ei_end_p` This predicate is `true` if an `edge_iterator` represents the last edge in an edge vector.

`ei_one_before_end_p`
This predicate is `true` if an `edge_iterator` represents the second last edge in an edge vector.

`ei_next` This function takes a pointer to an `edge_iterator` and makes it point to the next edge in the sequence.

`ei_prev` This function takes a pointer to an `edge_iterator` and makes it point to the previous edge in the sequence.

`ei_edge` This function returns the `edge` currently pointed to by an `edge_iterator`.

`ei_safe_safe`
This function returns the `edge` currently pointed to by an `edge_iterator`, but returns `NULL` if the iterator is pointing at the end of the sequence. This function has been provided for existing code makes the assumption that a `NULL` edge indicates the end of the sequence.

The convenience macro `FOR_EACH_EDGE` can be used to visit all of the edges in a sequence of predecessor or successor edges. It must not be used when an element might be removed during the traversal, otherwise elements will be missed. Here is an example of how to use the macro:

```
edge e;
edge_iterator ei;

FOR_EACH_EDGE (e, ei, bb->succs)
  {
     if (e->flags & EDGE_FALLTHRU)
       break;
  }
```

There are various reasons why control flow may transfer from one block to another. One possibility is that some instruction, for example a `CODE_LABEL`, in a linearized instruction

stream just always starts a new basic block. In this case a *fall-thru* edge links the basic block to the first following basic block. But there are several other reasons why edges may be created. The `flags` field of the `edge` data type is used to store information about the type of edge we are dealing with. Each edge is of one of the following types:

jump
: No type flags are set for edges corresponding to jump instructions. These edges are used for unconditional or conditional jumps and in RTL also for table jumps. They are the easiest to manipulate as they may be freely redirected when the flow graph is not in SSA form.

fall-thru
: Fall-thru edges are present in case where the basic block may continue execution to the following one without branching. These edges have the `EDGE_FALLTHRU` flag set. Unlike other types of edges, these edges must come into the basic block immediately following in the instruction stream. The function `force_nonfallthru` is available to insert an unconditional jump in the case that redirection is needed. Note that this may require creation of a new basic block.

exception handling
: Exception handling edges represent possible control transfers from a trapping instruction to an exception handler. The definition of "trapping" varies. In C++, only function calls can throw, but for Java and Ada, exceptions like division by zero or segmentation fault are defined and thus each instruction possibly throwing this kind of exception needs to be handled as control flow instruction. Exception edges have the `EDGE_ABNORMAL` and `EDGE_EH` flags set.

  When updating the instruction stream it is easy to change possibly trapping instruction to non-trapping, by simply removing the exception edge. The opposite conversion is difficult, but should not happen anyway. The edges can be eliminated via `purge_dead_edges` call.

  In the RTL representation, the destination of an exception edge is specified by `REG_EH_REGION` note attached to the insn. In case of a trapping call the `EDGE_ABNORMAL_CALL` flag is set too. In the `GIMPLE` representation, this extra flag is not set.

  In the RTL representation, the predicate `may_trap_p` may be used to check whether instruction still may trap or not. For the tree representation, the `tree_could_trap_p` predicate is available, but this predicate only checks for possible memory traps, as in dereferencing an invalid pointer location.

sibling calls
: Sibling calls or tail calls terminate the function in a non-standard way and thus an edge to the exit must be present. `EDGE_SIBCALL` and `EDGE_ABNORMAL` are set in such case. These edges only exist in the RTL representation.

computed jumps
: Computed jumps contain edges to all labels in the function referenced from the code. All those edges have `EDGE_ABNORMAL` flag set. The edges used to represent computed jumps often cause compile time performance problems, since functions consisting of many taken labels and many computed jumps may have *very* dense flow graphs, so these edges need to be handled with special

care. During the earlier stages of the compilation process, GCC tries to avoid such dense flow graphs by factoring computed jumps. For example, given the following series of jumps,

```
goto *x;
[ ... ]

goto *x;
[ ... ]

goto *x;
[ ... ]
```

factoring the computed jumps results in the following code sequence which has a much simpler flow graph:

```
    goto y;
    [ ... ]

    goto y;
    [ ... ]

    goto y;
    [ ... ]

  y:
    goto *x;
```

However, the classic problem with this transformation is that it has a runtime cost in there resulting code: An extra jump. Therefore, the computed jumps are un-factored in the later passes of the compiler (in the pass called `pass_duplicate_computed_gotos`). Be aware of that when you work on passes in that area. There have been numerous examples already where the compile time for code with unfactored computed jumps caused some serious headaches.

nonlocal goto handlers

GCC allows nested functions to return into caller using a `goto` to a label passed to as an argument to the callee. The labels passed to nested functions contain special code to cleanup after function call. Such sections of code are referred to as "nonlocal goto receivers". If a function contains such nonlocal goto receivers, an edge from the call to the label is created with the `EDGE_ABNORMAL` and `EDGE_ABNORMAL_CALL` flags set.

function entry points

By definition, execution of function starts at basic block 0, so there is always an edge from the `ENTRY_BLOCK_PTR` to basic block 0. There is no `GIMPLE` representation for alternate entry points at this moment. In RTL, alternate entry points are specified by `CODE_LABEL` with `LABEL_ALTERNATE_NAME` defined. This feature is currently used for multiple entry point prologues and is limited to post-reload passes only. This can be used by back-ends to emit alternate prologues for functions called from different contexts. In future full support for multiple entry functions defined by Fortran 90 needs to be implemented.

function exits

In the pre-reload representation a function terminates after the last instruction in the insn chain and no explicit return instructions are used. This corresponds

to the fall-thru edge into exit block. After reload, optimal RTL epilogues are used that use explicit (conditional) return instructions that are represented by edges with no flags set.

14.3 Profile information

In many cases a compiler must make a choice whether to trade speed in one part of code for speed in another, or to trade code size for code speed. In such cases it is useful to know information about how often some given block will be executed. That is the purpose for maintaining profile within the flow graph. GCC can handle profile information obtained through *profile feedback*, but it can also estimate branch probabilities based on statics and heuristics.

The feedback based profile is produced by compiling the program with instrumentation, executing it on a train run and reading the numbers of executions of basic blocks and edges back to the compiler while re-compiling the program to produce the final executable. This method provides very accurate information about where a program spends most of its time on the train run. Whether it matches the average run of course depends on the choice of train data set, but several studies have shown that the behavior of a program usually changes just marginally over different data sets.

When profile feedback is not available, the compiler may be asked to attempt to predict the behavior of each branch in the program using a set of heuristics (see '`predict.def`' for details) and compute estimated frequencies of each basic block by propagating the probabilities over the graph.

Each `basic_block` contains two integer fields to represent profile information: `frequency` and `count`. The `frequency` is an estimation how often is basic block executed within a function. It is represented as an integer scaled in the range from 0 to `BB_FREQ_BASE`. The most frequently executed basic block in function is initially set to `BB_FREQ_BASE` and the rest of frequencies are scaled accordingly. During optimization, the frequency of the most frequent basic block can both decrease (for instance by loop unrolling) or grow (for instance by cross-jumping optimization), so scaling sometimes has to be performed multiple times.

The `count` contains hard-counted numbers of execution measured during training runs and is nonzero only when profile feedback is available. This value is represented as the host's widest integer (typically a 64 bit integer) of the special type `gcov_type`.

Most optimization passes can use only the frequency information of a basic block, but a few passes may want to know hard execution counts. The frequencies should always match the counts after scaling, however during updating of the profile information numerical error may accumulate into quite large errors.

Each edge also contains a branch probability field: an integer in the range from 0 to `REG_BR_PROB_BASE`. It represents probability of passing control from the end of the `src` basic block to the `dest` basic block, i.e. the probability that control will flow along this edge. The `EDGE_FREQUENCY` macro is available to compute how frequently a given edge is taken. There is a `count` field for each edge as well, representing same information as for a basic block.

The basic block frequencies are not represented in the instruction stream, but in the RTL representation the edge frequencies are represented for conditional jumps (via the `REG_BR_`

PROB macro) since they are used when instructions are output to the assembly file and the flow graph is no longer maintained.

The probability that control flow arrives via a given edge to its destination basic block is called *reverse probability* and is not directly represented, but it may be easily computed from frequencies of basic blocks.

Updating profile information is a delicate task that can unfortunately not be easily integrated with the CFG manipulation API. Many of the functions and hooks to modify the CFG, such as redirect_edge_and_branch, do not have enough information to easily update the profile, so updating it is in the majority of cases left up to the caller. It is difficult to uncover bugs in the profile updating code, because they manifest themselves only by producing worse code, and checking profile consistency is not possible because of numeric error accumulation. Hence special attention needs to be given to this issue in each pass that modifies the CFG.

It is important to point out that REG_BR_PROB_BASE and BB_FREQ_BASE are both set low enough to be possible to compute second power of any frequency or probability in the flow graph, it is not possible to even square the count field, as modern CPUs are fast enough to execute 2^32 operations quickly.

14.4 Maintaining the CFG

An important task of each compiler pass is to keep both the control flow graph and all profile information up-to-date. Reconstruction of the control flow graph after each pass is not an option, since it may be very expensive and lost profile information cannot be reconstructed at all.

GCC has two major intermediate representations, and both use the basic_block and edge data types to represent control flow. Both representations share as much of the CFG maintenance code as possible. For each representation, a set of *hooks* is defined so that each representation can provide its own implementation of CFG manipulation routines when necessary. These hooks are defined in 'cfghooks.h'. There are hooks for almost all common CFG manipulations, including block splitting and merging, edge redirection and creating and deleting basic blocks. These hooks should provide everything you need to maintain and manipulate the CFG in both the RTL and GIMPLE representation.

At the moment, the basic block boundaries are maintained transparently when modifying instructions, so there rarely is a need to move them manually (such as in case someone wants to output instruction outside basic block explicitly).

In the RTL representation, each instruction has a BLOCK_FOR_INSN value that represents pointer to the basic block that contains the instruction. In the GIMPLE representation, the function gimple_bb returns a pointer to the basic block containing the queried statement.

When changes need to be applied to a function in its GIMPLE representation, *GIMPLE statement iterators* should be used. These iterators provide an integrated abstraction of the flow graph and the instruction stream. Block statement iterators are constructed using the gimple_stmt_iterator data structure and several modifier are available, including the following:

gsi_start

This function initializes a gimple_stmt_iterator that points to the first non-empty statement in a basic block.

`gsi_last` This function initializes a `gimple_stmt_iterator` that points to the last statement in a basic block.

`gsi_end_p`
This predicate is `true` if a `gimple_stmt_iterator` represents the end of a basic block.

`gsi_next` This function takes a `gimple_stmt_iterator` and makes it point to its successor.

`gsi_prev` This function takes a `gimple_stmt_iterator` and makes it point to its predecessor.

`gsi_insert_after`
This function inserts a statement after the `gimple_stmt_iterator` passed in. The final parameter determines whether the statement iterator is updated to point to the newly inserted statement, or left pointing to the original statement.

`gsi_insert_before`
This function inserts a statement before the `gimple_stmt_iterator` passed in. The final parameter determines whether the statement iterator is updated to point to the newly inserted statement, or left pointing to the original statement.

`gsi_remove`
This function removes the `gimple_stmt_iterator` passed in and rechains the remaining statements in a basic block, if any.

In the RTL representation, the macros `BB_HEAD` and `BB_END` may be used to get the head and end `rtx` of a basic block. No abstract iterators are defined for traversing the insn chain, but you can just use `NEXT_INSN` and `PREV_INSN` instead. See Section 13.19 [Insns], page 265.

Usually a code manipulating pass simplifies the instruction stream and the flow of control, possibly eliminating some edges. This may for example happen when a conditional jump is replaced with an unconditional jump, but also when simplifying possibly trapping instruction to non-trapping while compiling Java. Updating of edges is not transparent and each optimization pass is required to do so manually. However only few cases occur in practice. The pass may call `purge_dead_edges` on a given basic block to remove superfluous edges, if any.

Another common scenario is redirection of branch instructions, but this is best modeled as redirection of edges in the control flow graph and thus use of `redirect_edge_and_branch` is preferred over more low level functions, such as `redirect_jump` that operate on RTL chain only. The CFG hooks defined in '`cfghooks.h`' should provide the complete API required for manipulating and maintaining the CFG.

It is also possible that a pass has to insert control flow instruction into the middle of a basic block, thus creating an entry point in the middle of the basic block, which is impossible by definition: The block must be split to make sure it only has one entry point, i.e. the head of the basic block. The CFG hook `split_block` may be used when an instruction in the middle of a basic block has to become the target of a jump or branch instruction.

For a global optimizer, a common operation is to split edges in the flow graph and insert instructions on them. In the RTL representation, this can be easily done using the `insert_insn_on_edge` function that emits an instruction "on the edge", caching it for a

later `commit_edge_insertions` call that will take care of moving the inserted instructions off the edge into the instruction stream contained in a basic block. This includes the creation of new basic blocks where needed. In the `GIMPLE` representation, the equivalent functions are `gsi_insert_on_edge` which inserts a block statement iterator on an edge, and `gsi_commit_edge_inserts` which flushes the instruction to actual instruction stream.

While debugging the optimization pass, the `verify_flow_info` function may be useful to find bugs in the control flow graph updating code.

14.5 Liveness information

Liveness information is useful to determine whether some register is "live" at given point of program, i.e. that it contains a value that may be used at a later point in the program. This information is used, for instance, during register allocation, as the pseudo registers only need to be assigned to a unique hard register or to a stack slot if they are live. The hard registers and stack slots may be freely reused for other values when a register is dead.

Liveness information is available in the back end starting with `pass_df_initialize` and ending with `pass_df_finish`. Three flavors of live analysis are available: With `LR`, it is possible to determine at any point `P` in the function if the register may be used on some path from `P` to the end of the function. With `UR`, it is possible to determine if there is a path from the beginning of the function to `P` that defines the variable. `LIVE` is the intersection of the `LR` and `UR` and a variable is live at `P` if there is both an assignment that reaches it from the beginning of the function and a use that can be reached on some path from `P` to the end of the function.

In general `LIVE` is the most useful of the three. The macros `DF_[LR,UR,LIVE]_[IN,OUT]` can be used to access this information. The macros take a basic block number and return a bitmap that is indexed by the register number. This information is only guaranteed to be up to date after calls are made to `df_analyze`. See the file `df-core.c` for details on using the dataflow.

The liveness information is stored partly in the RTL instruction stream and partly in the flow graph. Local information is stored in the instruction stream: Each instruction may contain `REG_DEAD` notes representing that the value of a given register is no longer needed, or `REG_UNUSED` notes representing that the value computed by the instruction is never used. The second is useful for instructions computing multiple values at once.

15 Analysis and Representation of Loops

GCC provides extensive infrastructure for work with natural loops, i.e., strongly connected components of CFG with only one entry block. This chapter describes representation of loops in GCC, both on GIMPLE and in RTL, as well as the interfaces to loop-related analyses (induction variable analysis and number of iterations analysis).

15.1 Loop representation

This chapter describes the representation of loops in GCC, and functions that can be used to build, modify and analyze this representation. Most of the interfaces and data structures are declared in '`cfgloop.h`'. Loop structures are analyzed and this information disposed or updated at the discretion of individual passes. Still most of the generic CFG manipulation routines are aware of loop structures and try to keep them up-to-date. By this means an increasing part of the compilation pipeline is setup to maintain loop structure across passes to allow attaching meta information to individual loops for consumption by later passes.

In general, a natural loop has one entry block (header) and possibly several back edges (latches) leading to the header from the inside of the loop. Loops with several latches may appear if several loops share a single header, or if there is a branching in the middle of the loop. The representation of loops in GCC however allows only loops with a single latch. During loop analysis, headers of such loops are split and forwarder blocks are created in order to disambiguate their structures. Heuristic based on profile information and structure of the induction variables in the loops is used to determine whether the latches correspond to sub-loops or to control flow in a single loop. This means that the analysis sometimes changes the CFG, and if you run it in the middle of an optimization pass, you must be able to deal with the new blocks. You may avoid CFG changes by passing `LOOPS_MAY_HAVE_MULTIPLE_LATCHES` flag to the loop discovery, note however that most other loop manipulation functions will not work correctly for loops with multiple latch edges (the functions that only query membership of blocks to loops and subloop relationships, or enumerate and test loop exits, can be expected to work).

Body of the loop is the set of blocks that are dominated by its header, and reachable from its latch against the direction of edges in CFG. The loops are organized in a containment hierarchy (tree) such that all the loops immediately contained inside loop L are the children of L in the tree. This tree is represented by the `struct loops` structure. The root of this tree is a fake loop that contains all blocks in the function. Each of the loops is represented in a `struct loop` structure. Each loop is assigned an index (`num` field of the `struct loop` structure), and the pointer to the loop is stored in the corresponding field of the `larray` vector in the loops structure. The indices do not have to be continuous, there may be empty (`NULL`) entries in the `larray` created by deleting loops. Also, there is no guarantee on the relative order of a loop and its subloops in the numbering. The index of a loop never changes.

The entries of the `larray` field should not be accessed directly. The function `get_loop` returns the loop description for a loop with the given index. `number_of_loops` function returns number of loops in the function. To traverse all loops, use `FOR_EACH_LOOP` macro. The `flags` argument of the macro is used to determine the direction of traversal and the set of loops visited. Each loop is guaranteed to be visited exactly once, regardless of the changes to the loop tree, and the loops may be removed during the traversal. The newly created

loops are never traversed, if they need to be visited, this must be done separately after their creation. The `FOR_EACH_LOOP` macro allocates temporary variables. If the `FOR_EACH_LOOP` loop were ended using break or goto, they would not be released; `FOR_EACH_LOOP_BREAK` macro must be used instead.

Each basic block contains the reference to the innermost loop it belongs to (`loop_father`). For this reason, it is only possible to have one `struct loops` structure initialized at the same time for each CFG. The global variable `current_loops` contains the `struct loops` structure. Many of the loop manipulation functions assume that dominance information is up-to-date.

The loops are analyzed through `loop_optimizer_init` function. The argument of this function is a set of flags represented in an integer bitmask. These flags specify what other properties of the loop structures should be calculated/enforced and preserved later:

- `LOOPS_MAY_HAVE_MULTIPLE_LATCHES`: If this flag is set, no changes to CFG will be performed in the loop analysis, in particular, loops with multiple latch edges will not be disambiguated. If a loop has multiple latches, its latch block is set to NULL. Most of the loop manipulation functions will not work for loops in this shape. No other flags that require CFG changes can be passed to loop_optimizer_init.
- `LOOPS_HAVE_PREHEADERS`: Forwarder blocks are created in such a way that each loop has only one entry edge, and additionally, the source block of this entry edge has only one successor. This creates a natural place where the code can be moved out of the loop, and ensures that the entry edge of the loop leads from its immediate super-loop.
- `LOOPS_HAVE_SIMPLE_LATCHES`: Forwarder blocks are created to force the latch block of each loop to have only one successor. This ensures that the latch of the loop does not belong to any of its sub-loops, and makes manipulation with the loops significantly easier. Most of the loop manipulation functions assume that the loops are in this shape. Note that with this flag, the "normal" loop without any control flow inside and with one exit consists of two basic blocks.
- `LOOPS_HAVE_MARKED_IRREDUCIBLE_REGIONS`: Basic blocks and edges in the strongly connected components that are not natural loops (have more than one entry block) are marked with `BB_IRREDUCIBLE_LOOP` and `EDGE_IRREDUCIBLE_LOOP` flags. The flag is not set for blocks and edges that belong to natural loops that are in such an irreducible region (but it is set for the entry and exit edges of such a loop, if they lead to/from this region).
- `LOOPS_HAVE_RECORDED_EXITS`: The lists of exits are recorded and updated for each loop. This makes some functions (e.g., `get_loop_exit_edges`) more efficient. Some functions (e.g., `single_exit`) can be used only if the lists of exits are recorded.

These properties may also be computed/enforced later, using functions `create_preheaders`, `force_single_succ_latches`, `mark_irreducible_loops` and `record_loop_exits`. The properties can be queried using `loops_state_satisfies_p`.

The memory occupied by the loops structures should be freed with `loop_optimizer_finalize` function. When loop structures are setup to be preserved across passes this function reduces the information to be kept up-to-date to a minimum (only `LOOPS_MAY_HAVE_MULTIPLE_LATCHES` set).

The CFG manipulation functions in general do not update loop structures. Specialized versions that additionally do so are provided for the most common tasks. On GIMPLE,

`cleanup_tree_cfg_loop` function can be used to cleanup CFG while updating the loops structures if `current_loops` is set.

At the moment loop structure is preserved from the start of GIMPLE loop optimizations until the end of RTL loop optimizations. During this time a loop can be tracked by its `struct loop` and number.

15.2 Loop querying

The functions to query the information about loops are declared in '`cfgloop.h`'. Some of the information can be taken directly from the structures. `loop_father` field of each basic block contains the innermost loop to that the block belongs. The most useful fields of loop structure (that are kept up-to-date at all times) are:

- `header`, `latch`: Header and latch basic blocks of the loop.
- `num_nodes`: Number of basic blocks in the loop (including the basic blocks of the sub-loops).
- `depth`: The depth of the loop in the loops tree, i.e., the number of super-loops of the loop.
- `outer`, `inner`, `next`: The super-loop, the first sub-loop, and the sibling of the loop in the loops tree.

There are other fields in the loop structures, many of them used only by some of the passes, or not updated during CFG changes; in general, they should not be accessed directly.

The most important functions to query loop structures are:

- `flow_loops_dump`: Dumps the information about loops to a file.
- `verify_loop_structure`: Checks consistency of the loop structures.
- `loop_latch_edge`: Returns the latch edge of a loop.
- `loop_preheader_edge`: If loops have preheaders, returns the preheader edge of a loop.
- `flow_loop_nested_p`: Tests whether loop is a sub-loop of another loop.
- `flow_bb_inside_loop_p`: Tests whether a basic block belongs to a loop (including its sub-loops).
- `find_common_loop`: Finds the common super-loop of two loops.
- `superloop_at_depth`: Returns the super-loop of a loop with the given depth.
- `tree_num_loop_insns`, `num_loop_insns`: Estimates the number of insns in the loop, on GIMPLE and on RTL.
- `loop_exit_edge_p`: Tests whether edge is an exit from a loop.
- `mark_loop_exit_edges`: Marks all exit edges of all loops with `EDGE_LOOP_EXIT` flag.
- `get_loop_body`, `get_loop_body_in_dom_order`, `get_loop_body_in_bfs_order`: Enumerates the basic blocks in the loop in depth-first search order in reversed CFG, ordered by dominance relation, and breath-first search order, respectively.
- `single_exit`: Returns the single exit edge of the loop, or `NULL` if the loop has more than one exit. You can only use this function if LOOPS_HAVE_MARKED_SINGLE_EXITS property is used.
- `get_loop_exit_edges`: Enumerates the exit edges of a loop.

- `just_once_each_iteration_p`: Returns true if the basic block is executed exactly once during each iteration of a loop (that is, it does not belong to a sub-loop, and it dominates the latch of the loop).

15.3 Loop manipulation

The loops tree can be manipulated using the following functions:

- `flow_loop_tree_node_add`: Adds a node to the tree.
- `flow_loop_tree_node_remove`: Removes a node from the tree.
- `add_bb_to_loop`: Adds a basic block to a loop.
- `remove_bb_from_loops`: Removes a basic block from loops.

Most low-level CFG functions update loops automatically. The following functions handle some more complicated cases of CFG manipulations:

- `remove_path`: Removes an edge and all blocks it dominates.
- `split_loop_exit_edge`: Splits exit edge of the loop, ensuring that PHI node arguments remain in the loop (this ensures that loop-closed SSA form is preserved). Only useful on GIMPLE.

Finally, there are some higher-level loop transformations implemented. While some of them are written so that they should work on non-innermost loops, they are mostly untested in that case, and at the moment, they are only reliable for the innermost loops:

- `create_iv`: Creates a new induction variable. Only works on GIMPLE. `standard_iv_increment_position` can be used to find a suitable place for the iv increment.
- `duplicate_loop_to_header_edge`, `tree_duplicate_loop_to_header_edge`: These functions (on RTL and on GIMPLE) duplicate the body of the loop prescribed number of times on one of the edges entering loop header, thus performing either loop unrolling or loop peeling. `can_duplicate_loop_p` (`can_unroll_loop_p` on GIMPLE) must be true for the duplicated loop.
- `loop_version`, `tree_ssa_loop_version`: These function create a copy of a loop, and a branch before them that selects one of them depending on the prescribed condition. This is useful for optimizations that need to verify some assumptions in runtime (one of the copies of the loop is usually left unchanged, while the other one is transformed in some way).
- `tree_unroll_loop`: Unrolls the loop, including peeling the extra iterations to make the number of iterations divisible by unroll factor, updating the exit condition, and removing the exits that now cannot be taken. Works only on GIMPLE.

15.4 Loop-closed SSA form

Throughout the loop optimizations on tree level, one extra condition is enforced on the SSA form: No SSA name is used outside of the loop in that it is defined. The SSA form satisfying this condition is called "loop-closed SSA form" – LCSSA. To enforce LCSSA, PHI nodes must be created at the exits of the loops for the SSA names that are used outside of them. Only the real operands (not virtual SSA names) are held in LCSSA, in order to save memory.

There are various benefits of LCSSA:

- Many optimizations (value range analysis, final value replacement) are interested in the values that are defined in the loop and used outside of it, i.e., exactly those for that we create new PHI nodes.
- In induction variable analysis, it is not necessary to specify the loop in that the analysis should be performed – the scalar evolution analysis always returns the results with respect to the loop in that the SSA name is defined.
- It makes updating of SSA form during loop transformations simpler. Without LCSSA, operations like loop unrolling may force creation of PHI nodes arbitrarily far from the loop, while in LCSSA, the SSA form can be updated locally. However, since we only keep real operands in LCSSA, we cannot use this advantage (we could have local updating of real operands, but it is not much more efficient than to use generic SSA form updating for it as well; the amount of changes to SSA is the same).

However, it also means LCSSA must be updated. This is usually straightforward, unless you create a new value in loop and use it outside, or unless you manipulate loop exit edges (functions are provided to make these manipulations simple). `rewrite_into_loop_closed_ssa` is used to rewrite SSA form to LCSSA, and `verify_loop_closed_ssa` to check that the invariant of LCSSA is preserved.

15.5 Scalar evolutions

Scalar evolutions (SCEV) are used to represent results of induction variable analysis on GIMPLE. They enable us to represent variables with complicated behavior in a simple and consistent way (we only use it to express values of polynomial induction variables, but it is possible to extend it). The interfaces to SCEV analysis are declared in '`tree-scalar-evolution.h`'. To use scalar evolutions analysis, `scev_initialize` must be used. To stop using SCEV, `scev_finalize` should be used. SCEV analysis caches results in order to save time and memory. This cache however is made invalid by most of the loop transformations, including removal of code. If such a transformation is performed, `scev_reset` must be called to clean the caches.

Given an SSA name, its behavior in loops can be analyzed using the `analyze_scalar_evolution` function. The returned SCEV however does not have to be fully analyzed and it may contain references to other SSA names defined in the loop. To resolve these (potentially recursive) references, `instantiate_parameters` or `resolve_mixers` functions must be used. `instantiate_parameters` is useful when you use the results of SCEV only for some analysis, and when you work with whole nest of loops at once. It will try replacing all SSA names by their SCEV in all loops, including the super-loops of the current loop, thus providing a complete information about the behavior of the variable in the loop nest. `resolve_mixers` is useful if you work with only one loop at a time, and if you possibly need to create code based on the value of the induction variable. It will only resolve the SSA names defined in the current loop, leaving the SSA names defined outside unchanged, even if their evolution in the outer loops is known.

The SCEV is a normal tree expression, except for the fact that it may contain several special tree nodes. One of them is `SCEV_NOT_KNOWN`, used for SSA names whose value cannot be expressed. The other one is `POLYNOMIAL_CHREC`. Polynomial chrec has three arguments – base, step and loop (both base and step may contain further polynomial chrecs). Type of the expression and of base and step must be the same. A variable has evolution `POLYNOMIAL_`

`CHREC(base, step, loop)` if it is (in the specified loop) equivalent to `x_1` in the following example

```
while (...)
  {
    x_1 = phi (base, x_2);
    x_2 = x_1 + step;
  }
```

Note that this includes the language restrictions on the operations. For example, if we compile C code and `x` has signed type, then the overflow in addition would cause undefined behavior, and we may assume that this does not happen. Hence, the value with this SCEV cannot overflow (which restricts the number of iterations of such a loop).

In many cases, one wants to restrict the attention just to affine induction variables. In this case, the extra expressive power of SCEV is not useful, and may complicate the optimizations. In this case, `simple_iv` function may be used to analyze a value – the result is a loop-invariant base and step.

15.6 IV analysis on RTL

The induction variable on RTL is simple and only allows analysis of affine induction variables, and only in one loop at once. The interface is declared in '`cfgloop.h`'. Before analyzing induction variables in a loop L, `iv_analysis_loop_init` function must be called on L. After the analysis (possibly calling `iv_analysis_loop_init` for several loops) is finished, `iv_analysis_done` should be called. The following functions can be used to access the results of the analysis:

- `iv_analyze`: Analyzes a single register used in the given insn. If no use of the register in this insn is found, the following insns are scanned, so that this function can be called on the insn returned by get_condition.
- `iv_analyze_result`: Analyzes result of the assignment in the given insn.
- `iv_analyze_expr`: Analyzes a more complicated expression. All its operands are analyzed by `iv_analyze`, and hence they must be used in the specified insn or one of the following insns.

The description of the induction variable is provided in `struct rtx_iv`. In order to handle subregs, the representation is a bit complicated; if the value of the `extend` field is not `UNKNOWN`, the value of the induction variable in the i-th iteration is

```
delta + mult * extend_{extend_mode} (subreg_{mode} (base + i * step)),
```

with the following exception: if `first_special` is true, then the value in the first iteration (when `i` is zero) is `delta + mult * base`. However, if `extend` is equal to `UNKNOWN`, then `first_special` must be false, `delta` 0, `mult` 1 and the value in the i-th iteration is

```
subreg_{mode} (base + i * step)
```

The function `get_iv_value` can be used to perform these calculations.

15.7 Number of iterations analysis

Both on GIMPLE and on RTL, there are functions available to determine the number of iterations of a loop, with a similar interface. The number of iterations of a loop in GCC is defined as the number of executions of the loop latch. In many cases, it is not possible

to determine the number of iterations unconditionally – the determined number is correct only if some assumptions are satisfied. The analysis tries to verify these conditions using the information contained in the program; if it fails, the conditions are returned together with the result. The following information and conditions are provided by the analysis:

- `assumptions`: If this condition is false, the rest of the information is invalid.
- `noloop_assumptions` on RTL, `may_be_zero` on GIMPLE: If this condition is true, the loop exits in the first iteration.
- `infinite`: If this condition is true, the loop is infinite. This condition is only available on RTL. On GIMPLE, conditions for finiteness of the loop are included in `assumptions`.
- `niter_expr` on RTL, `niter` on GIMPLE: The expression that gives number of iterations. The number of iterations is defined as the number of executions of the loop latch.

Both on GIMPLE and on RTL, it necessary for the induction variable analysis framework to be initialized (SCEV on GIMPLE, loop-iv on RTL). On GIMPLE, the results are stored to `struct tree_niter_desc` structure. Number of iterations before the loop is exited through a given exit can be determined using `number_of_iterations_exit` function. On RTL, the results are returned in `struct niter_desc` structure. The corresponding function is named `check_simple_exit`. There are also functions that pass through all the exits of a loop and try to find one with easy to determine number of iterations – `find_loop_niter` on GIMPLE and `find_simple_exit` on RTL. Finally, there are functions that provide the same information, but additionally cache it, so that repeated calls to number of iterations are not so costly – `number_of_latch_executions` on GIMPLE and `get_simple_loop_desc` on RTL.

Note that some of these functions may behave slightly differently than others – some of them return only the expression for the number of iterations, and fail if there are some assumptions. The function `number_of_latch_executions` works only for single-exit loops. The function `number_of_cond_exit_executions` can be used to determine number of executions of the exit condition of a single-exit loop (i.e., the `number_of_latch_executions` increased by one).

15.8 Data Dependency Analysis

The code for the data dependence analysis can be found in '`tree-data-ref.c`' and its interface and data structures are described in '`tree-data-ref.h`'. The function that computes the data dependences for all the array and pointer references for a given loop is `compute_data_dependences_for_loop`. This function is currently used by the linear loop transform and the vectorization passes. Before calling this function, one has to allocate two vectors: a first vector will contain the set of data references that are contained in the analyzed loop body, and the second vector will contain the dependence relations between the data references. Thus if the vector of data references is of size `n`, the vector containing the dependence relations will contain `n*n` elements. However if the analyzed loop contains side effects, such as calls that potentially can interfere with the data references in the current analyzed loop, the analysis stops while scanning the loop body for data references, and inserts a single `chrec_dont_know` in the dependence relation array.

The data references are discovered in a particular order during the scanning of the loop body: the loop body is analyzed in execution order, and the data references of each statement are pushed at the end of the data reference array. Two data references syntactically occur in the program in the same order as in the array of data references. This syntactic order is important in some classical data dependence tests, and mapping this order to the elements of this array avoids costly queries to the loop body representation.

Three types of data references are currently handled: ARRAY_REF, INDIRECT_REF and COMPONENT_REF. The data structure for the data reference is `data_reference`, where `data_reference_p` is a name of a pointer to the data reference structure. The structure contains the following elements:

- `base_object_info`: Provides information about the base object of the data reference and its access functions. These access functions represent the evolution of the data reference in the loop relative to its base, in keeping with the classical meaning of the data reference access function for the support of arrays. For example, for a reference `a.b[i][j]`, the base object is `a.b` and the access functions, one for each array subscript, are: `{i_init, + i_step}_1, {j_init, +, j_step}_2`.
- `first_location_in_loop`: Provides information about the first location accessed by the data reference in the loop and about the access function used to represent evolution relative to this location. This data is used to support pointers, and is not used for arrays (for which we have base objects). Pointer accesses are represented as a one-dimensional access that starts from the first location accessed in the loop. For example:

  ```
  for1 i
     for2 j
      *((int *)p + i + j) = a[i][j];
  ```

  The access function of the pointer access is `{0, + 4B}_for2` relative to `p + i`. The access functions of the array are `{i_init, + i_step}_for1` and `{j_init, +, j_step}_for2` relative to `a`.

  Usually, the object the pointer refers to is either unknown, or we can't prove that the access is confined to the boundaries of a certain object.

  Two data references can be compared only if at least one of these two representations has all its fields filled for both data references.

  The current strategy for data dependence tests is as follows: If both `a` and `b` are represented as arrays, compare `a.base_object` and `b.base_object`; if they are equal, apply dependence tests (use access functions based on base_objects). Else if both `a` and `b` are represented as pointers, compare `a.first_location` and `b.first_location`; if they are equal, apply dependence tests (use access functions based on first location). However, if `a` and `b` are represented differently, only try to prove that the bases are definitely different.
- Aliasing information.
- Alignment information.

The structure describing the relation between two data references is `data_dependence_relation` and the shorter name for a pointer to such a structure is `ddr_p`. This structure contains:

- a pointer to each data reference,

- a tree node `are_dependent` that is set to `chrec_known` if the analysis has proved that there is no dependence between these two data references, `chrec_dont_know` if the analysis was not able to determine any useful result and potentially there could exist a dependence between these data references, and `are_dependent` is set to `NULL_TREE` if there exist a dependence relation between the data references, and the description of this dependence relation is given in the `subscripts`, `dir_vects`, and `dist_vects` arrays,
- a boolean that determines whether the dependence relation can be represented by a classical distance vector,
- an array `subscripts` that contains a description of each subscript of the data references. Given two array accesses a subscript is the tuple composed of the access functions for a given dimension. For example, given `A[f1][f2][f3]` and `B[g1][g2][g3]`, there are three subscripts: `(f1, g1), (f2, g2), (f3, g3)`.
- two arrays `dir_vects` and `dist_vects` that contain classical representations of the data dependences under the form of direction and distance dependence vectors,
- an array of loops `loop_nest` that contains the loops to which the distance and direction vectors refer to.

Several functions for pretty printing the information extracted by the data dependence analysis are available: `dump_ddrs` prints with a maximum verbosity the details of a data dependence relations array, `dump_dist_dir_vectors` prints only the classical distance and direction vectors for a data dependence relations array, and `dump_data_references` prints the details of the data references contained in a data reference array.

15.9 Omega a solver for linear programming problems

The data dependence analysis contains several solvers triggered sequentially from the less complex ones to the more sophisticated. For ensuring the consistency of the results of these solvers, a data dependence check pass has been implemented based on two different solvers. The second method that has been integrated to GCC is based on the Omega dependence solver, written in the 1990's by William Pugh and David Wonnacott. Data dependence tests can be formulated using a subset of the Presburger arithmetics that can be translated to linear constraint systems. These linear constraint systems can then be solved using the Omega solver.

The Omega solver is using Fourier-Motzkin's algorithm for variable elimination: a linear constraint system containing `n` variables is reduced to a linear constraint system with `n-1` variables. The Omega solver can also be used for solving other problems that can be expressed under the form of a system of linear equalities and inequalities. The Omega solver is known to have an exponential worst case, also known under the name of "omega nightmare" in the literature, but in practice, the omega test is known to be efficient for the common data dependence tests.

The interface used by the Omega solver for describing the linear programming problems is described in '`omega.h`', and the solver is `omega_solve_problem`.

16 Machine Descriptions

A machine description has two parts: a file of instruction patterns ('`.md`' file) and a C header file of macro definitions.

The '`.md`' file for a target machine contains a pattern for each instruction that the target machine supports (or at least each instruction that is worth telling the compiler about). It may also contain comments. A semicolon causes the rest of the line to be a comment, unless the semicolon is inside a quoted string.

See the next chapter for information on the C header file.

16.1 Overview of How the Machine Description is Used

There are three main conversions that happen in the compiler:

1. The front end reads the source code and builds a parse tree.
2. The parse tree is used to generate an RTL insn list based on named instruction patterns.
3. The insn list is matched against the RTL templates to produce assembler code.

For the generate pass, only the names of the insns matter, from either a named `define_insn` or a `define_expand`. The compiler will choose the pattern with the right name and apply the operands according to the documentation later in this chapter, without regard for the RTL template or operand constraints. Note that the names the compiler looks for are hard-coded in the compiler—it will ignore unnamed patterns and patterns with names it doesn't know about, but if you don't provide a named pattern it needs, it will abort.

If a `define_insn` is used, the template given is inserted into the insn list. If a `define_expand` is used, one of three things happens, based on the condition logic. The condition logic may manually create new insns for the insn list, say via `emit_insn()`, and invoke `DONE`. For certain named patterns, it may invoke `FAIL` to tell the compiler to use an alternate way of performing that task. If it invokes neither `DONE` nor `FAIL`, the template given in the pattern is inserted, as if the `define_expand` were a `define_insn`.

Once the insn list is generated, various optimization passes convert, replace, and rearrange the insns in the insn list. This is where the `define_split` and `define_peephole` patterns get used, for example.

Finally, the insn list's RTL is matched up with the RTL templates in the `define_insn` patterns, and those patterns are used to emit the final assembly code. For this purpose, each named `define_insn` acts like it's unnamed, since the names are ignored.

16.2 Everything about Instruction Patterns

Each instruction pattern contains an incomplete RTL expression, with pieces to be filled in later, operand constraints that restrict how the pieces can be filled in, and an output pattern or C code to generate the assembler output, all wrapped up in a `define_insn` expression.

A `define_insn` is an RTL expression containing four or five operands:

1. An optional name. The presence of a name indicate that this instruction pattern can perform a certain standard job for the RTL-generation pass of the compiler. This pass knows certain names and will use the instruction patterns with those names, if the names are defined in the machine description.

The absence of a name is indicated by writing an empty string where the name should go. Nameless instruction patterns are never used for generating RTL code, but they may permit several simpler insns to be combined later on.

Names that are not thus known and used in RTL-generation have no effect; they are equivalent to no name at all.

For the purpose of debugging the compiler, you may also specify a name beginning with the '*' character. Such a name is used only for identifying the instruction in RTL dumps; it is entirely equivalent to having a nameless pattern for all other purposes.

2. The *RTL template* (see Section 16.4 [RTL Template], page 299) is a vector of incomplete RTL expressions which show what the instruction should look like. It is incomplete because it may contain `match_operand`, `match_operator`, and `match_dup` expressions that stand for operands of the instruction.

   If the vector has only one element, that element is the template for the instruction pattern. If the vector has multiple elements, then the instruction pattern is a `parallel` expression containing the elements described.

3. A condition. This is a string which contains a C expression that is the final test to decide whether an insn body matches this pattern.

   For a named pattern, the condition (if present) may not depend on the data in the insn being matched, but only the target-machine-type flags. The compiler needs to test these conditions during initialization in order to learn exactly which named instructions are available in a particular run.

   For nameless patterns, the condition is applied only when matching an individual insn, and only after the insn has matched the pattern's recognition template. The insn's operands may be found in the vector `operands`. For an insn where the condition has once matched, it can't be used to control register allocation, for example by excluding certain hard registers or hard register combinations.

4. The *output template*: a string that says how to output matching insns as assembler code. '%' in this string specifies where to substitute the value of an operand. See Section 16.5 [Output Template], page 303.

   When simple substitution isn't general enough, you can specify a piece of C code to compute the output. See Section 16.6 [Output Statement], page 304.

5. Optionally, a vector containing the values of attributes for insns matching this pattern. See Section 16.19 [Insn Attributes], page 394.

16.3 Example of `define_insn`

Here is an actual example of an instruction pattern, for the 68000/68020.

```
(define_insn "tstsi"
  [(set (cc0)
        (match_operand:SI 0 "general_operand" "rm"))]
  ""
  "*
{
  if (TARGET_68020 || ! ADDRESS_REG_P (operands[0]))
    return \"tstl %0\";
  return \"cmpl #0,%0\";
}")
```

This can also be written using braced strings:

```
(define_insn "tstsi"
  [(set (cc0)
        (match_operand:SI 0 "general_operand" "rm"))]
  ""
{
  if (TARGET_68020 || ! ADDRESS_REG_P (operands[0]))
    return "tstl %0";
  return "cmpl #0,%0";
})
```

This is an instruction that sets the condition codes based on the value of a general operand. It has no condition, so any insn whose RTL description has the form shown may be handled according to this pattern. The name '`tstsi`' means "test a `SImode` value" and tells the RTL generation pass that, when it is necessary to test such a value, an insn to do so can be constructed using this pattern.

The output control string is a piece of C code which chooses which output template to return based on the kind of operand and the specific type of CPU for which code is being generated.

'`"rm"`' is an operand constraint. Its meaning is explained below.

16.4 RTL Template

The RTL template is used to define which insns match the particular pattern and how to find their operands. For named patterns, the RTL template also says how to construct an insn from specified operands.

Construction involves substituting specified operands into a copy of the template. Matching involves determining the values that serve as the operands in the insn being matched. Both of these activities are controlled by special expression types that direct matching and substitution of the operands.

`(match_operand:`*`m`* *`n`* *`predicate`* *`constraint`*`)`

This expression is a placeholder for operand number *n* of the insn. When constructing an insn, operand number *n* will be substituted at this point. When matching an insn, whatever appears at this position in the insn will be taken as operand number *n*; but it must satisfy *predicate* or this instruction pattern will not match at all.

Operand numbers must be chosen consecutively counting from zero in each instruction pattern. There may be only one `match_operand` expression in the pattern for each operand number. Usually operands are numbered in the order of appearance in `match_operand` expressions. In the case of a `define_expand`, any operand numbers used only in `match_dup` expressions have higher values than all other operand numbers.

predicate is a string that is the name of a function that accepts two arguments, an expression and a machine mode. See Section 16.7 [Predicates], page 305. During matching, the function will be called with the putative operand as the expression and *m* as the mode argument (if *m* is not specified, `VOIDmode` will be used, which normally causes *predicate* to accept any mode). If it returns zero, this instruction pattern fails to match. *predicate* may be an empty string; then

it means no test is to be done on the operand, so anything which occurs in this position is valid.

Most of the time, *predicate* will reject modes other than *m*—but not always. For example, the predicate `address_operand` uses *m* as the mode of memory ref that the address should be valid for. Many predicates accept `const_int` nodes even though their mode is `VOIDmode`.

constraint controls reloading and the choice of the best register class to use for a value, as explained later (see Section 16.8 [Constraints], page 310). If the constraint would be an empty string, it can be omitted.

People are often unclear on the difference between the constraint and the predicate. The predicate helps decide whether a given insn matches the pattern. The constraint plays no role in this decision; instead, it controls various decisions in the case of an insn which does match.

`(match_scratch:`*m n constraint*`)`

This expression is also a placeholder for operand number *n* and indicates that operand must be a `scratch` or `reg` expression.

When matching patterns, this is equivalent to

```
(match_operand:m n "scratch_operand" pred)
```

but, when generating RTL, it produces a (`scratch`:*m*) expression.

If the last few expressions in a `parallel` are `clobber` expressions whose operands are either a hard register or `match_scratch`, the combiner can add or delete them when necessary. See Section 13.15 [Side Effects], page 257.

`(match_dup` *n*`)`

This expression is also a placeholder for operand number *n*. It is used when the operand needs to appear more than once in the insn.

In construction, `match_dup` acts just like `match_operand`: the operand is substituted into the insn being constructed. But in matching, `match_dup` behaves differently. It assumes that operand number *n* has already been determined by a `match_operand` appearing earlier in the recognition template, and it matches only an identical-looking expression.

Note that `match_dup` should not be used to tell the compiler that a particular register is being used for two operands (example: `add` that adds one register to another; the second register is both an input operand and the output operand). Use a matching constraint (see Section 16.8.1 [Simple Constraints], page 310) for those. `match_dup` is for the cases where one operand is used in two places in the template, such as an instruction that computes both a quotient and a remainder, where the opcode takes two input operands but the RTL template has to refer to each of those twice; once for the quotient pattern and once for the remainder pattern.

`(match_operator:`*m n predicate* `[`*operands*`...])`

This pattern is a kind of placeholder for a variable RTL expression code.

When constructing an insn, it stands for an RTL expression whose expression code is taken from that of operand *n*, and whose operands are constructed from the patterns *operands*.

When matching an expression, it matches an expression if the function *predicate* returns nonzero on that expression *and* the patterns *operands* match the operands of the expression.

Suppose that the function `commutative_operator` is defined as follows, to match any expression whose operator is one of the commutative arithmetic operators of RTL and whose mode is *mode*:

```
int
commutative_integer_operator (x, mode)
     rtx x;
     enum machine_mode mode;
{
  enum rtx_code code = GET_CODE (x);
  if (GET_MODE (x) != mode)
    return 0;
  return (GET_RTX_CLASS (code) == RTX_COMM_ARITH
          || code == EQ || code == NE);
}
```

Then the following pattern will match any RTL expression consisting of a commutative operator applied to two general operands:

```
(match_operator:SI 3 "commutative_operator"
  [(match_operand:SI 1 "general_operand" "g")
   (match_operand:SI 2 "general_operand" "g")])
```

Here the vector `[operands...]` contains two patterns because the expressions to be matched all contain two operands.

When this pattern does match, the two operands of the commutative operator are recorded as operands 1 and 2 of the insn. (This is done by the two instances of `match_operand`.) Operand 3 of the insn will be the entire commutative expression: use `GET_CODE (operands[3])` to see which commutative operator was used.

The machine mode *m* of `match_operator` works like that of `match_operand`: it is passed as the second argument to the predicate function, and that function is solely responsible for deciding whether the expression to be matched "has" that mode.

When constructing an insn, argument 3 of the gen-function will specify the operation (i.e. the expression code) for the expression to be made. It should be an RTL expression, whose expression code is copied into a new expression whose operands are arguments 1 and 2 of the gen-function. The subexpressions of argument 3 are not used; only its expression code matters.

When `match_operator` is used in a pattern for matching an insn, it usually best if the operand number of the `match_operator` is higher than that of the actual operands of the insn. This improves register allocation because the register allocator often looks at operands 1 and 2 of insns to see if it can do register tying.

There is no way to specify constraints in `match_operator`. The operand of the insn which corresponds to the `match_operator` never has any constraints because it is never reloaded as a whole. However, if parts of its *operands* are matched by `match_operand` patterns, those parts may have constraints of their own.

(match_op_dup:*m* *n*[*operands*...])

Like match_dup, except that it applies to operators instead of operands. When constructing an insn, operand number *n* will be substituted at this point. But in matching, match_op_dup behaves differently. It assumes that operand number *n* has already been determined by a match_operator appearing earlier in the recognition template, and it matches only an identical-looking expression.

(match_parallel *n* *predicate* [*subpat*...])

This pattern is a placeholder for an insn that consists of a parallel expression with a variable number of elements. This expression should only appear at the top level of an insn pattern.

When constructing an insn, operand number *n* will be substituted at this point. When matching an insn, it matches if the body of the insn is a parallel expression with at least as many elements as the vector of *subpat* expressions in the match_parallel, if each *subpat* matches the corresponding element of the parallel, *and* the function *predicate* returns nonzero on the parallel that is the body of the insn. It is the responsibility of the predicate to validate elements of the parallel beyond those listed in the match_parallel.

A typical use of match_parallel is to match load and store multiple expressions, which can contain a variable number of elements in a parallel. For example,

```
(define_insn ""
  [(match_parallel 0 "load_multiple_operation"
     [(set (match_operand:SI 1 "gpc_reg_operand" "=r")
           (match_operand:SI 2 "memory_operand" "m"))
      (use (reg:SI 179))
      (clobber (reg:SI 179))])]
  ""
  "loadm 0,0,%1,%2")
```

This example comes from 'a29k.md'. The function load_multiple_operation is defined in 'a29k.c' and checks that subsequent elements in the parallel are the same as the set in the pattern, except that they are referencing subsequent registers and memory locations.

An insn that matches this pattern might look like:

```
(parallel
 [(set (reg:SI 20) (mem:SI (reg:SI 100)))
  (use (reg:SI 179))
  (clobber (reg:SI 179))
  (set (reg:SI 21)
       (mem:SI (plus:SI (reg:SI 100)
                        (const_int 4))))
  (set (reg:SI 22)
       (mem:SI (plus:SI (reg:SI 100)
                        (const_int 8))))])
```

(match_par_dup *n* [*subpat*...])

Like match_op_dup, but for match_parallel instead of match_operator.

16.5 Output Templates and Operand Substitution

The *output template* is a string which specifies how to output the assembler code for an instruction pattern. Most of the template is a fixed string which is output literally. The character '%' is used to specify where to substitute an operand; it can also be used to identify places where different variants of the assembler require different syntax.

In the simplest case, a '%' followed by a digit *n* says to output operand *n* at that point in the string.

'%' followed by a letter and a digit says to output an operand in an alternate fashion. Four letters have standard, built-in meanings described below. The machine description macro `PRINT_OPERAND` can define additional letters with nonstandard meanings.

'%c*digit*' can be used to substitute an operand that is a constant value without the syntax that normally indicates an immediate operand.

'%n*digit*' is like '%c*digit*' except that the value of the constant is negated before printing.

'%a*digit*' can be used to substitute an operand as if it were a memory reference, with the actual operand treated as the address. This may be useful when outputting a "load address" instruction, because often the assembler syntax for such an instruction requires you to write the operand as if it were a memory reference.

'%l*digit*' is used to substitute a `label_ref` into a jump instruction.

'%=' outputs a number which is unique to each instruction in the entire compilation. This is useful for making local labels to be referred to more than once in a single template that generates multiple assembler instructions.

'%' followed by a punctuation character specifies a substitution that does not use an operand. Only one case is standard: '%%' outputs a '%' into the assembler code. Other nonstandard cases can be defined in the `PRINT_OPERAND` macro. You must also define which punctuation characters are valid with the `PRINT_OPERAND_PUNCT_VALID_P` macro.

The template may generate multiple assembler instructions. Write the text for the instructions, with '\;' between them.

When the RTL contains two operands which are required by constraint to match each other, the output template must refer only to the lower-numbered operand. Matching operands are not always identical, and the rest of the compiler arranges to put the proper RTL expression for printing into the lower-numbered operand.

One use of nonstandard letters or punctuation following '%' is to distinguish between different assembler languages for the same machine; for example, Motorola syntax versus MIT syntax for the 68000. Motorola syntax requires periods in most opcode names, while MIT syntax does not. For example, the opcode '`movel`' in MIT syntax is '`move.l`' in Motorola syntax. The same file of patterns is used for both kinds of output syntax, but the character sequence '`%.`' is used in each place where Motorola syntax wants a period. The `PRINT_OPERAND` macro for Motorola syntax defines the sequence to output a period; the macro for MIT syntax defines it to do nothing.

As a special case, a template consisting of the single character `#` instructs the compiler to first split the insn, and then output the resulting instructions separately. This helps eliminate redundancy in the output templates. If you have a `define_insn` that needs to emit multiple assembler instructions, and there is a matching `define_split` already

defined, then you can simply use `#` as the output template instead of writing an output template that emits the multiple assembler instructions.

If the macro `ASSEMBLER_DIALECT` is defined, you can use construct of the form '`{option0|option1|option2}`' in the templates. These describe multiple variants of assembler language syntax. See Section 17.21.7 [Instruction Output], page 546.

16.6 C Statements for Assembler Output

Often a single fixed template string cannot produce correct and efficient assembler code for all the cases that are recognized by a single instruction pattern. For example, the opcodes may depend on the kinds of operands; or some unfortunate combinations of operands may require extra machine instructions.

If the output control string starts with a '`@`', then it is actually a series of templates, each on a separate line. (Blank lines and leading spaces and tabs are ignored.) The templates correspond to the pattern's constraint alternatives (see Section 16.8.2 [Multi-Alternative], page 314). For example, if a target machine has a two-address add instruction '`addr`' to add into a register and another '`addm`' to add a register to memory, you might write this pattern:

```
(define_insn "addsi3"
  [(set (match_operand:SI 0 "general_operand" "=r,m")
        (plus:SI (match_operand:SI 1 "general_operand" "0,0")
                 (match_operand:SI 2 "general_operand" "g,r")))]
  ""
  "@
   addr %2,%0
   addm %2,%0")
```

If the output control string starts with a '`*`', then it is not an output template but rather a piece of C program that should compute a template. It should execute a `return` statement to return the template-string you want. Most such templates use C string literals, which require doublequote characters to delimit them. To include these doublequote characters in the string, prefix each one with '\'.

If the output control string is written as a brace block instead of a double-quoted string, it is automatically assumed to be C code. In that case, it is not necessary to put in a leading asterisk, or to escape the doublequotes surrounding C string literals.

The operands may be found in the array `operands`, whose C data type is `rtx []`.

It is very common to select different ways of generating assembler code based on whether an immediate operand is within a certain range. Be careful when doing this, because the result of `INTVAL` is an integer on the host machine. If the host machine has more bits in an `int` than the target machine has in the mode in which the constant will be used, then some of the bits you get from `INTVAL` will be superfluous. For proper results, you must carefully disregard the values of those bits.

It is possible to output an assembler instruction and then go on to output or compute more of them, using the subroutine `output_asm_insn`. This receives two arguments: a template-string and a vector of operands. The vector may be `operands`, or it may be another array of `rtx` that you declare locally and initialize yourself.

When an insn pattern has multiple alternatives in its constraints, often the appearance of the assembler code is determined mostly by which alternative was matched. When this

is so, the C code can test the variable `which_alternative`, which is the ordinal number of the alternative that was actually satisfied (0 for the first, 1 for the second alternative, etc.).

For example, suppose there are two opcodes for storing zero, '`clrreg`' for registers and '`clrmem`' for memory locations. Here is how a pattern could use `which_alternative` to choose between them:

```
(define_insn ""
  [(set (match_operand:SI 0 "general_operand" "=r,m")
        (const_int 0))]
  ""
  {
  return (which_alternative == 0
          ? "clrreg %0" : "clrmem %0");
  })
```

The example above, where the assembler code to generate was *solely* determined by the alternative, could also have been specified as follows, having the output control string start with a '`@`':

```
(define_insn ""
  [(set (match_operand:SI 0 "general_operand" "=r,m")
        (const_int 0))]
  ""
  "@
   clrreg %0
   clrmem %0")
```

If you just need a little bit of C code in one (or a few) alternatives, you can use '`*`' inside of a '`@`' multi-alternative template:

```
(define_insn ""
  [(set (match_operand:SI 0 "general_operand" "=r,<,m")
        (const_int 0))]
  ""
  "@
   clrreg %0
   * return stack_mem_p (operands[0]) ? \"push 0\" : \"clrmem %0\";
   clrmem %0")
```

16.7 Predicates

A predicate determines whether a `match_operand` or `match_operator` expression matches, and therefore whether the surrounding instruction pattern will be used for that combination of operands. GCC has a number of machine-independent predicates, and you can define machine-specific predicates as needed. By convention, predicates used with `match_operand` have names that end in '`_operand`', and those used with `match_operator` have names that end in '`_operator`'.

All predicates are Boolean functions (in the mathematical sense) of two arguments: the RTL expression that is being considered at that position in the instruction pattern, and the machine mode that the `match_operand` or `match_operator` specifies. In this section, the first argument is called *op* and the second argument *mode*. Predicates can be called from C as ordinary two-argument functions; this can be useful in output templates or other machine-specific code.

Operand predicates can allow operands that are not actually acceptable to the hardware, as long as the constraints give reload the ability to fix them up (see Section 16.8

[Constraints], page 310). However, GCC will usually generate better code if the predicates specify the requirements of the machine instructions as closely as possible. Reload cannot fix up operands that must be constants ("immediate operands"); you must use a predicate that allows only constants, or else enforce the requirement in the extra condition.

Most predicates handle their *mode* argument in a uniform manner. If *mode* is `VOIDmode` (unspecified), then *op* can have any mode. If *mode* is anything else, then *op* must have the same mode, unless *op* is a `CONST_INT` or integer `CONST_DOUBLE`. These RTL expressions always have `VOIDmode`, so it would be counterproductive to check that their mode matches. Instead, predicates that accept `CONST_INT` and/or integer `CONST_DOUBLE` check that the value stored in the constant will fit in the requested mode.

Predicates with this behavior are called *normal*. `genrecog` can optimize the instruction recognizer based on knowledge of how normal predicates treat modes. It can also diagnose certain kinds of common errors in the use of normal predicates; for instance, it is almost always an error to use a normal predicate without specifying a mode.

Predicates that do something different with their *mode* argument are called *special*. The generic predicates `address_operand` and `pmode_register_operand` are special predicates. `genrecog` does not do any optimizations or diagnosis when special predicates are used.

16.7.1 Machine-Independent Predicates

These are the generic predicates available to all back ends. They are defined in '`recog.c`'. The first category of predicates allow only constant, or *immediate*, operands.

`immediate_operand` [Function]

This predicate allows any sort of constant that fits in *mode*. It is an appropriate choice for instructions that take operands that must be constant.

`const_int_operand` [Function]

This predicate allows any `CONST_INT` expression that fits in *mode*. It is an appropriate choice for an immediate operand that does not allow a symbol or label.

`const_double_operand` [Function]

This predicate accepts any `CONST_DOUBLE` expression that has exactly *mode*. If *mode* is `VOIDmode`, it will also accept `CONST_INT`. It is intended for immediate floating point constants.

The second category of predicates allow only some kind of machine register.

`register_operand` [Function]

This predicate allows any `REG` or `SUBREG` expression that is valid for *mode*. It is often suitable for arithmetic instruction operands on a RISC machine.

`pmode_register_operand` [Function]

This is a slight variant on `register_operand` which works around a limitation in the machine-description reader.

```
(match_operand n "pmode_register_operand" constraint)
```

means exactly what

```
(match_operand:P n "register_operand" constraint)
```

would mean, if the machine-description reader accepted '`:P`' mode suffixes. Unfortunately, it cannot, because `Pmode` is an alias for some other mode, and might vary with machine-specific options. See Section 17.31 [Misc], page 573.

`scratch_operand` [Function]

This predicate allows hard registers and `SCRATCH` expressions, but not pseudo-registers. It is used internally by `match_scratch`; it should not be used directly.

The third category of predicates allow only some kind of memory reference.

`memory_operand` [Function]

This predicate allows any valid reference to a quantity of mode *mode* in memory, as determined by the weak form of `GO_IF_LEGITIMATE_ADDRESS` (see Section 17.14 [Addressing Modes], page 499).

`address_operand` [Function]

This predicate is a little unusual; it allows any operand that is a valid expression for the *address* of a quantity of mode *mode*, again determined by the weak form of `GO_IF_LEGITIMATE_ADDRESS`. To first order, if '`(mem:`*mode* `(`*exp*`))`' is acceptable to `memory_operand`, then *exp* is acceptable to `address_operand`. Note that *exp* does not necessarily have the mode *mode*.

`indirect_operand` [Function]

This is a stricter form of `memory_operand` which allows only memory references with a `general_operand` as the address expression. New uses of this predicate are discouraged, because `general_operand` is very permissive, so it's hard to tell what an `indirect_operand` does or does not allow. If a target has different requirements for memory operands for different instructions, it is better to define target-specific predicates which enforce the hardware's requirements explicitly.

`push_operand` [Function]

This predicate allows a memory reference suitable for pushing a value onto the stack. This will be a `MEM` which refers to `stack_pointer_rtx`, with a side-effect in its address expression (see Section 13.16 [Incdec], page 263); which one is determined by the `STACK_PUSH_CODE` macro (see Section 17.10.1 [Frame Layout], page 465).

`pop_operand` [Function]

This predicate allows a memory reference suitable for popping a value off the stack. Again, this will be a `MEM` referring to `stack_pointer_rtx`, with a side-effect in its address expression. However, this time `STACK_POP_CODE` is expected.

The fourth category of predicates allow some combination of the above operands.

`nonmemory_operand` [Function]

This predicate allows any immediate or register operand valid for *mode*.

`nonimmediate_operand` [Function]

This predicate allows any register or memory operand valid for *mode*.

`general_operand` [Function]

This predicate allows any immediate, register, or memory operand valid for *mode*.

Finally, there are two generic operator predicates.

`comparison_operator` [Function]

This predicate matches any expression which performs an arithmetic comparison in *mode*; that is, `COMPARISON_P` is true for the expression code.

`ordered_comparison_operator` [Function]

This predicate matches any expression which performs an arithmetic comparison in *mode* and whose expression code is valid for integer modes; that is, the expression code will be one of `eq`, `ne`, `lt`, `ltu`, `le`, `leu`, `gt`, `gtu`, `ge`, `geu`.

16.7.2 Defining Machine-Specific Predicates

Many machines have requirements for their operands that cannot be expressed precisely using the generic predicates. You can define additional predicates using `define_predicate` and `define_special_predicate` expressions. These expressions have three operands:

- The name of the predicate, as it will be referred to in `match_operand` or `match_operator` expressions.
- An RTL expression which evaluates to true if the predicate allows the operand *op*, false if it does not. This expression can only use the following RTL codes:

  `MATCH_OPERAND`

  When written inside a predicate expression, a `MATCH_OPERAND` expression evaluates to true if the predicate it names would allow *op*. The operand number and constraint are ignored. Due to limitations in `genrecog`, you can only refer to generic predicates and predicates that have already been defined.

  `MATCH_CODE`

  This expression evaluates to true if *op* or a specified subexpression of *op* has one of a given list of RTX codes.

  The first operand of this expression is a string constant containing a comma-separated list of RTX code names (in lower case). These are the codes for which the `MATCH_CODE` will be true.

  The second operand is a string constant which indicates what subexpression of *op* to examine. If it is absent or the empty string, *op* itself is examined. Otherwise, the string constant must be a sequence of digits and/or lowercase letters. Each character indicates a subexpression to extract from the current expression; for the first character this is *op*, for the second and subsequent characters it is the result of the previous character. A digit *n* extracts '`XEXP (e, n)`'; a letter *l* extracts '`XVECEXP (e, 0, n)`' where *n* is the alphabetic ordinal of *l* (0 for 'a', 1 for 'b', and so on). The `MATCH_CODE` then examines the RTX code of the subexpression extracted by the complete string. It is not possible to extract components of an `rtvec` that is not at position 0 within its RTX object.

`MATCH_TEST`
: This expression has one operand, a string constant containing a C expression. The predicate's arguments, *op* and *mode*, are available with those names in the C expression. The `MATCH_TEST` evaluates to true if the C expression evaluates to a nonzero value. `MATCH_TEST` expressions must not have side effects.

`AND`
`IOR`
`NOT`
`IF_THEN_ELSE`
: The basic '`MATCH_`' expressions can be combined using these logical operators, which have the semantics of the C operators '`&&`', '`||`', '`!`', and '`? :`' respectively. As in Common Lisp, you may give an `AND` or `IOR` expression an arbitrary number of arguments; this has exactly the same effect as writing a chain of two-argument `AND` or `IOR` expressions.

- An optional block of C code, which should execute '`return true`' if the predicate is found to match and '`return false`' if it does not. It must not have any side effects. The predicate arguments, *op* and *mode*, are available with those names.

  If a code block is present in a predicate definition, then the RTL expression must evaluate to true *and* the code block must execute '`return true`' for the predicate to allow the operand. The RTL expression is evaluated first; do not re-check anything in the code block that was checked in the RTL expression.

The program `genrecog` scans `define_predicate` and `define_special_predicate` expressions to determine which RTX codes are possibly allowed. You should always make this explicit in the RTL predicate expression, using `MATCH_OPERAND` and `MATCH_CODE`.

Here is an example of a simple predicate definition, from the IA64 machine description:

```
;; True if op is a SYMBOL_REF which refers to the sdata section.
(define_predicate "small_addr_symbolic_operand"
  (and (match_code "symbol_ref")
       (match_test "SYMBOL_REF_SMALL_ADDR_P (op)")))
```

And here is another, showing the use of the C block.

```
;; True if op is a register operand that is (or could be) a GR reg.
(define_predicate "gr_register_operand"
  (match_operand 0 "register_operand")
{
  unsigned int regno;
  if (GET_CODE (op) == SUBREG)
    op = SUBREG_REG (op);

  regno = REGNO (op);
  return (regno >= FIRST_PSEUDO_REGISTER || GENERAL_REGNO_P (regno));
})
```

Predicates written with `define_predicate` automatically include a test that *mode* is `VOIDmode`, or *op* has the same mode as *mode*, or *op* is a `CONST_INT` or `CONST_DOUBLE`. They do *not* check specifically for integer `CONST_DOUBLE`, nor do they test that the value of either kind of constant fits in the requested mode. This is because target-specific predicates that take constants usually have to do more stringent value checks anyway. If you need the

exact same treatment of `CONST_INT` or `CONST_DOUBLE` that the generic predicates provide, use a `MATCH_OPERAND` subexpression to call `const_int_operand`, `const_double_operand`, or `immediate_operand`.

Predicates written with `define_special_predicate` do not get any automatic mode checks, and are treated as having special mode handling by `genrecog`.

The program `genpreds` is responsible for generating code to test predicates. It also writes a header file containing function declarations for all machine-specific predicates. It is not necessary to declare these predicates in '*cpu*-`protos.h`'.

16.8 Operand Constraints

Each `match_operand` in an instruction pattern can specify constraints for the operands allowed. The constraints allow you to fine-tune matching within the set of operands allowed by the predicate.

Constraints can say whether an operand may be in a register, and which kinds of register; whether the operand can be a memory reference, and which kinds of address; whether the operand may be an immediate constant, and which possible values it may have. Constraints can also require two operands to match. Side-effects aren't allowed in operands of inline `asm`, unless '`<`' or '`>`' constraints are used, because there is no guarantee that the side-effects will happen exactly once in an instruction that can update the addressing register.

16.8.1 Simple Constraints

The simplest kind of constraint is a string full of letters, each of which describes one kind of operand that is permitted. Here are the letters that are allowed:

whitespace
: Whitespace characters are ignored and can be inserted at any position except the first. This enables each alternative for different operands to be visually aligned in the machine description even if they have different number of constraints and modifiers.

'`m`'
: A memory operand is allowed, with any kind of address that the machine supports in general. Note that the letter used for the general memory constraint can be re-defined by a back end using the `TARGET_MEM_CONSTRAINT` macro.

'`o`'
: A memory operand is allowed, but only if the address is *offsettable*. This means that adding a small integer (actually, the width in bytes of the operand, as determined by its machine mode) may be added to the address and the result is also a valid memory address.

  For example, an address which is constant is offsettable; so is an address that is the sum of a register and a constant (as long as a slightly larger constant is also within the range of address-offsets supported by the machine); but an autoincrement or autodecrement address is not offsettable. More complicated indirect/indexed addresses may or may not be offsettable depending on the other addressing modes that the machine supports.

  Note that in an output operand which can be matched by another operand, the constraint letter '`o`' is valid only when accompanied by both '`<`' (if the

target machine has predecrement addressing) and '>' (if the target machine has preincrement addressing).

'V' A memory operand that is not offsettable. In other words, anything that would fit the 'm' constraint but not the 'o' constraint.

'<' A memory operand with autodecrement addressing (either predecrement or postdecrement) is allowed. In inline `asm` this constraint is only allowed if the operand is used exactly once in an instruction that can handle the side-effects. Not using an operand with '<' in constraint string in the inline `asm` pattern at all or using it in multiple instructions isn't valid, because the side-effects wouldn't be performed or would be performed more than once. Furthermore, on some targets the operand with '<' in constraint string must be accompanied by special instruction suffixes like `%U0` instruction suffix on PowerPC or `%P0` on IA-64.

'>' A memory operand with autoincrement addressing (either preincrement or postincrement) is allowed. In inline `asm` the same restrictions as for '<' apply.

'r' A register operand is allowed provided that it is in a general register.

'i' An immediate integer operand (one with constant value) is allowed. This includes symbolic constants whose values will be known only at assembly time or later.

'n' An immediate integer operand with a known numeric value is allowed. Many systems cannot support assembly-time constants for operands less than a word wide. Constraints for these operands should use 'n' rather than 'i'.

'I', 'J', 'K', . . . 'P'
Other letters in the range 'I' through 'P' may be defined in a machine-dependent fashion to permit immediate integer operands with explicit integer values in specified ranges. For example, on the 68000, 'I' is defined to stand for the range of values 1 to 8. This is the range permitted as a shift count in the shift instructions.

'E' An immediate floating operand (expression code `const_double`) is allowed, but only if the target floating point format is the same as that of the host machine (on which the compiler is running).

'F' An immediate floating operand (expression code `const_double` or `const_vector`) is allowed.

'G', 'H' 'G' and 'H' may be defined in a machine-dependent fashion to permit immediate floating operands in particular ranges of values.

's' An immediate integer operand whose value is not an explicit integer is allowed.

This might appear strange; if an insn allows a constant operand with a value not known at compile time, it certainly must allow any known value. So why use 's' instead of 'i'? Sometimes it allows better code to be generated.

For example, on the 68000 in a fullword instruction it is possible to use an immediate operand; but if the immediate value is between −128 and 127, better

code results from loading the value into a register and using the register. This is because the load into the register can be done with a 'moveq' instruction. We arrange for this to happen by defining the letter 'K' to mean "any integer outside the range −128 to 127", and then specifying 'Ks' in the operand constraints.

'g' Any register, memory or immediate integer operand is allowed, except for registers that are not general registers.

'X' Any operand whatsoever is allowed, even if it does not satisfy `general_operand`. This is normally used in the constraint of a `match_scratch` when certain alternatives will not actually require a scratch register.

'0', '1', '2', . . . '9'

An operand that matches the specified operand number is allowed. If a digit is used together with letters within the same alternative, the digit should come last.

This number is allowed to be more than a single digit. If multiple digits are encountered consecutively, they are interpreted as a single decimal integer. There is scant chance for ambiguity, since to-date it has never been desirable that '10' be interpreted as matching either operand 1 *or* operand 0. Should this be desired, one can use multiple alternatives instead.

This is called a *matching constraint* and what it really means is that the assembler has only a single operand that fills two roles considered separate in the RTL insn. For example, an add insn has two input operands and one output operand in the RTL, but on most CISC machines an add instruction really has only two operands, one of them an input-output operand:

```
addl #35,r12
```

Matching constraints are used in these circumstances. More precisely, the two operands that match must include one input-only operand and one output-only operand. Moreover, the digit must be a smaller number than the number of the operand that uses it in the constraint.

For operands to match in a particular case usually means that they are identical-looking RTL expressions. But in a few special cases specific kinds of dissimilarity are allowed. For example, `*x` as an input operand will match `*x++` as an output operand. For proper results in such cases, the output template should always use the output-operand's number when printing the operand.

'p' An operand that is a valid memory address is allowed. This is for "load address" and "push address" instructions.

'p' in the constraint must be accompanied by `address_operand` as the predicate in the `match_operand`. This predicate interprets the mode specified in the `match_operand` as the mode of the memory reference for which the address would be valid.

other-letters

Other letters can be defined in machine-dependent fashion to stand for particular classes of registers or other arbitrary operand types. 'd', 'a' and 'f' are defined on the 68000/68020 to stand for data, address and floating point registers.

In order to have valid assembler code, each operand must satisfy its constraint. But a failure to do so does not prevent the pattern from applying to an insn. Instead, it directs the compiler to modify the code so that the constraint will be satisfied. Usually this is done by copying an operand into a register.

Contrast, therefore, the two instruction patterns that follow:

```
(define_insn ""
  [(set (match_operand:SI 0 "general_operand" "=r")
        (plus:SI (match_dup 0)
                 (match_operand:SI 1 "general_operand" "r")))]
  ""
  "...")
```

which has two operands, one of which must appear in two places, and

```
(define_insn ""
  [(set (match_operand:SI 0 "general_operand" "=r")
        (plus:SI (match_operand:SI 1 "general_operand" "0")
                 (match_operand:SI 2 "general_operand" "r")))]
  ""
  "...")
```

which has three operands, two of which are required by a constraint to be identical. If we are considering an insn of the form

```
(insn n prev next
  (set (reg:SI 3)
       (plus:SI (reg:SI 6) (reg:SI 109)))
  ...)
```

the first pattern would not apply at all, because this insn does not contain two identical subexpressions in the right place. The pattern would say, "That does not look like an add instruction; try other patterns". The second pattern would say, "Yes, that's an add instruction, but there is something wrong with it". It would direct the reload pass of the compiler to generate additional insns to make the constraint true. The results might look like this:

```
(insn n2 prev n
  (set (reg:SI 3) (reg:SI 6))
  ...)

(insn n n2 next
  (set (reg:SI 3)
       (plus:SI (reg:SI 3) (reg:SI 109)))
  ...)
```

It is up to you to make sure that each operand, in each pattern, has constraints that can handle any RTL expression that could be present for that operand. (When multiple alternatives are in use, each pattern must, for each possible combination of operand expressions, have at least one alternative which can handle that combination of operands.) The constraints don't need to *allow* any possible operand—when this is the case, they do not constrain—but they must at least point the way to reloading any possible operand so that it will fit.

- If the constraint accepts whatever operands the predicate permits, there is no problem: reloading is never necessary for this operand.

  For example, an operand whose constraints permit everything except registers is safe provided its predicate rejects registers.

An operand whose predicate accepts only constant values is safe provided its constraints include the letter 'i'. If any possible constant value is accepted, then nothing less than 'i' will do; if the predicate is more selective, then the constraints may also be more selective.

- Any operand expression can be reloaded by copying it into a register. So if an operand's constraints allow some kind of register, it is certain to be safe. It need not permit all classes of registers; the compiler knows how to copy a register into another register of the proper class in order to make an instruction valid.
- A nonoffsettable memory reference can be reloaded by copying the address into a register. So if the constraint uses the letter 'o', all memory references are taken care of.
- A constant operand can be reloaded by allocating space in memory to hold it as preinitialized data. Then the memory reference can be used in place of the constant. So if the constraint uses the letters 'o' or 'm', constant operands are not a problem.
- If the constraint permits a constant and a pseudo register used in an insn was not allocated to a hard register and is equivalent to a constant, the register will be replaced with the constant. If the predicate does not permit a constant and the insn is re-recognized for some reason, the compiler will crash. Thus the predicate must always recognize any objects allowed by the constraint.

If the operand's predicate can recognize registers, but the constraint does not permit them, it can make the compiler crash. When this operand happens to be a register, the reload pass will be stymied, because it does not know how to copy a register temporarily into memory.

If the predicate accepts a unary operator, the constraint applies to the operand. For example, the MIPS processor at ISA level 3 supports an instruction which adds two registers in `SImode` to produce a `DImode` result, but only if the registers are correctly sign extended. This predicate for the input operands accepts a `sign_extend` of an `SImode` register. Write the constraint to indicate the type of register that is required for the operand of the `sign_extend`.

16.8.2 Multiple Alternative Constraints

Sometimes a single instruction has multiple alternative sets of possible operands. For example, on the 68000, a logical-or instruction can combine register or an immediate value into memory, or it can combine any kind of operand into a register; but it cannot combine one memory location into another.

These constraints are represented as multiple alternatives. An alternative can be described by a series of letters for each operand. The overall constraint for an operand is made from the letters for this operand from the first alternative, a comma, the letters for this operand from the second alternative, a comma, and so on until the last alternative. Here is how it is done for fullword logical-or on the 68000:

```
(define_insn "iorsi3"
  [(set (match_operand:SI 0 "general_operand" "=m,d")
        (ior:SI (match_operand:SI 1 "general_operand" "%0,0")
                (match_operand:SI 2 "general_operand" "dKs,dmKs")))]
  ...)
```

The first alternative has '`m`' (memory) for operand 0, '`0`' for operand 1 (meaning it must match operand 0), and '`dKs`' for operand 2. The second alternative has '`d`' (data register) for operand 0, '`0`' for operand 1, and '`dmKs`' for operand 2. The '`=`' and '`%`' in the constraints apply to all the alternatives; their meaning is explained in the next section (see Section 16.8.3 [Class Preferences], page 315).

If all the operands fit any one alternative, the instruction is valid. Otherwise, for each alternative, the compiler counts how many instructions must be added to copy the operands so that that alternative applies. The alternative requiring the least copying is chosen. If two alternatives need the same amount of copying, the one that comes first is chosen. These choices can be altered with the '`?`' and '`!`' characters:

`?` Disparage slightly the alternative that the '`?`' appears in, as a choice when no alternative applies exactly. The compiler regards this alternative as one unit more costly for each '`?`' that appears in it.

`!` Disparage severely the alternative that the '`!`' appears in. This alternative can still be used if it fits without reloading, but if reloading is needed, some other alternative will be used.

When an insn pattern has multiple alternatives in its constraints, often the appearance of the assembler code is determined mostly by which alternative was matched. When this is so, the C code for writing the assembler code can use the variable `which_alternative`, which is the ordinal number of the alternative that was actually satisfied (0 for the first, 1 for the second alternative, etc.). See Section 16.6 [Output Statement], page 304.

16.8.3 Register Class Preferences

The operand constraints have another function: they enable the compiler to decide which kind of hardware register a pseudo register is best allocated to. The compiler examines the constraints that apply to the insns that use the pseudo register, looking for the machine-dependent letters such as '`d`' and '`a`' that specify classes of registers. The pseudo register is put in whichever class gets the most "votes". The constraint letters '`g`' and '`r`' also vote: they vote in favor of a general register. The machine description says which registers are considered general.

Of course, on some machines all registers are equivalent, and no register classes are defined. Then none of this complexity is relevant.

16.8.4 Constraint Modifier Characters

Here are constraint modifier characters.

'`=`' Means that this operand is write-only for this instruction: the previous value is discarded and replaced by output data.

'`+`' Means that this operand is both read and written by the instruction.

When the compiler fixes up the operands to satisfy the constraints, it needs to know which operands are inputs to the instruction and which are outputs from it. '`=`' identifies an output; '`+`' identifies an operand that is both input and output; all other operands are assumed to be input only.

If you specify '`=`' or '`+`' in a constraint, you put it in the first character of the constraint string.

'&' Means (in a particular alternative) that this operand is an *earlyclobber* operand, which is modified before the instruction is finished using the input operands. Therefore, this operand may not lie in a register that is used as an input operand or as part of any memory address.

'&' applies only to the alternative in which it is written. In constraints with multiple alternatives, sometimes one alternative requires '&' while others do not. See, for example, the 'movdf' insn of the 68000.

An input operand can be tied to an earlyclobber operand if its only use as an input occurs before the early result is written. Adding alternatives of this form often allows GCC to produce better code when only some of the inputs can be affected by the earlyclobber. See, for example, the 'mulsi3' insn of the ARM.

'&' does not obviate the need to write '='.

'%' Declares the instruction to be commutative for this operand and the following operand. This means that the compiler may interchange the two operands if that is the cheapest way to make all operands fit the constraints. This is often used in patterns for addition instructions that really have only two operands: the result must go in one of the arguments. Here for example, is how the 68000 halfword-add instruction is defined:

```
(define_insn "addhi3"
  [(set (match_operand:HI 0 "general_operand" "=m,r")
     (plus:HI (match_operand:HI 1 "general_operand" "%0,0")
              (match_operand:HI 2 "general_operand" "di,g")))]
  ...)
```

GCC can only handle one commutative pair in an asm; if you use more, the compiler may fail. Note that you need not use the modifier if the two alternatives are strictly identical; this would only waste time in the reload pass. The modifier is not operational after register allocation, so the result of define_peephole2 and define_splits performed after reload cannot rely on '%' to make the intended insn match.

'#' Says that all following characters, up to the next comma, are to be ignored as a constraint. They are significant only for choosing register preferences.

'*' Says that the following character should be ignored when choosing register preferences. '*' has no effect on the meaning of the constraint as a constraint, and no effect on reloading. For LRA '*' additionally disparages slightly the alternative if the following character matches the operand.

Here is an example: the 68000 has an instruction to sign-extend a halfword in a data register, and can also sign-extend a value by copying it into an address register. While either kind of register is acceptable, the constraints on an address-register destination are less strict, so it is best if register allocation makes an address register its goal. Therefore, '*' is used so that the 'd' constraint letter (for data register) is ignored when computing register preferences.

```
(define_insn "extendhisi2"
  [(set (match_operand:SI 0 "general_operand" "=*d,a")
        (sign_extend:SI
         (match_operand:HI 1 "general_operand" "0,g")))]
  ...)
```

16.8.5 Constraints for Particular Machines

Whenever possible, you should use the general-purpose constraint letters in `asm` arguments, since they will convey meaning more readily to people reading your code. Failing that, use the constraint letters that usually have very similar meanings across architectures. The most commonly used constraints are '`m`' and '`r`' (for memory and general-purpose registers respectively; see Section 16.8.1 [Simple Constraints], page 310), and '`I`', usually the letter indicating the most common immediate-constant format.

Each architecture defines additional constraints. These constraints are used by the compiler itself for instruction generation, as well as for `asm` statements; therefore, some of the constraints are not particularly useful for `asm`. Here is a summary of some of the machine-dependent constraints available on some particular machines; it includes both constraints that are useful for `asm` and constraints that aren't. The compiler source file mentioned in the table heading for each architecture is the definitive reference for the meanings of that architecture's constraints.

AArch64 family—'`config/aarch64/constraints.md`'

`k`	The stack pointer register (`SP`)
`w`	Floating point or SIMD vector register
`I`	Integer constant that is valid as an immediate operand in an `ADD` instruction
`J`	Integer constant that is valid as an immediate operand in a `SUB` instruction (once negated)
`K`	Integer constant that can be used with a 32-bit logical instruction
`L`	Integer constant that can be used with a 64-bit logical instruction
`M`	Integer constant that is valid as an immediate operand in a 32-bit `MOV` pseudo instruction. The `MOV` may be assembled to one of several different machine instructions depending on the value
`N`	Integer constant that is valid as an immediate operand in a 64-bit `MOV` pseudo instruction
`S`	An absolute symbolic address or a label reference
`Y`	Floating point constant zero
`Z`	Integer constant zero
`Ush`	The high part (bits 12 and upwards) of the pc-relative address of a symbol within 4GB of the instruction
`Q`	A memory address which uses a single base register with no offset
`Ump`	A memory address suitable for a load/store pair instruction in SI, DI, SF and DF modes

ARC —'`config/arc/constraints.md`'

`q`	Registers usable in ARCompact 16-bit instructions: `r0-r3`, `r12-r15`. This constraint can only match when the '`-mq`' option is in effect.

`e` Registers usable as base-regs of memory addresses in ARCompact 16-bit memory instructions: `r0-r3`, `r12-r15`, `sp`. This constraint can only match when the '`-mq`' option is in effect.

`D` ARC FPX (dpfp) 64-bit registers. `D0`, `D1`.

`I` A signed 12-bit integer constant.

`Cal` constant for arithmetic/logical operations. This might be any constant that can be put into a long immediate by the assmbler or linker without involving a PIC relocation.

`K` A 3-bit unsigned integer constant.

`L` A 6-bit unsigned integer constant.

`CnL` One's complement of a 6-bit unsigned integer constant.

`CmL` Two's complement of a 6-bit unsigned integer constant.

`M` A 5-bit unsigned integer constant.

`O` A 7-bit unsigned integer constant.

`P` A 8-bit unsigned integer constant.

`H` Any const_double value.

ARM family—'`config/arm/constraints.md`'

`w` VFP floating-point register

`G` The floating-point constant 0.0

`I` Integer that is valid as an immediate operand in a data processing instruction. That is, an integer in the range 0 to 255 rotated by a multiple of 2

`J` Integer in the range −4095 to 4095

`K` Integer that satisfies constraint '`I`' when inverted (ones complement)

`L` Integer that satisfies constraint '`I`' when negated (twos complement)

`M` Integer in the range 0 to 32

`Q` A memory reference where the exact address is in a single register (''`m`'' is preferable for `asm` statements)

`R` An item in the constant pool

`S` A symbol in the text segment of the current file

`Uv` A memory reference suitable for VFP load/store insns (reg+constant offset)

`Uy` A memory reference suitable for iWMMXt load/store instructions.

`Uq` A memory reference suitable for the ARMv4 ldrsb instruction.

AVR family—'`config/avr/constraints.md`'

`l`	Registers from r0 to r15
`a`	Registers from r16 to r23
`d`	Registers from r16 to r31
`w`	Registers from r24 to r31. These registers can be used in '`adiw`' command
`e`	Pointer register (r26–r31)
`b`	Base pointer register (r28–r31)
`q`	Stack pointer register (SPH:SPL)
`t`	Temporary register r0
`x`	Register pair X (r27:r26)
`y`	Register pair Y (r29:r28)
`z`	Register pair Z (r31:r30)
`I`	Constant greater than −1, less than 64
`J`	Constant greater than −64, less than 1
`K`	Constant integer 2
`L`	Constant integer 0
`M`	Constant that fits in 8 bits
`N`	Constant integer −1
`O`	Constant integer 8, 16, or 24
`P`	Constant integer 1
`G`	A floating point constant 0.0
`Q`	A memory address based on Y or Z pointer with displacement.

Epiphany—'`config/epiphany/constraints.md`'

`U16`	An unsigned 16-bit constant.
`K`	An unsigned 5-bit constant.
`L`	A signed 11-bit constant.
`Cm1`	A signed 11-bit constant added to −1. Can only match when the '`-m1reg-`*`reg`*' option is active.
`Cl1`	Left-shift of −1, i.e., a bit mask with a block of leading ones, the rest being a block of trailing zeroes. Can only match when the '`-m1reg-`*`reg`*' option is active.
`Cr1`	Right-shift of −1, i.e., a bit mask with a trailing block of ones, the rest being zeroes. Or to put it another way, one less than a power of two. Can only match when the '`-m1reg-`*`reg`*' option is active.

`Cal` Constant for arithmetic/logical operations. This is like `i`, except that for position independent code, no symbols / expressions needing relocations are allowed.

`Csy` Symbolic constant for call/jump instruction.

`Rcs` The register class usable in short insns. This is a register class constraint, and can thus drive register allocation. This constraint won't match unless '`-mprefer-short-insn-regs`' is in effect.

`Rsc` The the register class of registers that can be used to hold a sibcall call address. I.e., a caller-saved register.

`Rct` Core control register class.

`Rgs` The register group usable in short insns. This constraint does not use a register class, so that it only passively matches suitable registers, and doesn't drive register allocation.

`Car` Constant suitable for the addsi3_r pattern. This is a valid offset For byte, halfword, or word addressing.

`Rra` Matches the return address if it can be replaced with the link register.

`Rcc` Matches the integer condition code register.

`Sra` Matches the return address if it is in a stack slot.

`Cfm` Matches control register values to switch fp mode, which are encapsulated in `UNSPEC_FP_MODE`.

CR16 Architecture—'`config/cr16/cr16.h`'

`b` Registers from r0 to r14 (registers without stack pointer)

`t` Register from r0 to r11 (all 16-bit registers)

`p` Register from r12 to r15 (all 32-bit registers)

`I` Signed constant that fits in 4 bits

`J` Signed constant that fits in 5 bits

`K` Signed constant that fits in 6 bits

`L` Unsigned constant that fits in 4 bits

`M` Signed constant that fits in 32 bits

`N` Check for 64 bits wide constants for add/sub instructions

`G` Floating point constant that is legal for store immediate

Hewlett-Packard PA-RISC—'`config/pa/pa.h`'

`a` General register 1

`f` Floating point register

`q` Shift amount register

`x` Floating point register (deprecated)

`y` Upper floating point register (32-bit), floating point register (64-bit)

`Z` Any register

`I` Signed 11-bit integer constant

`J` Signed 14-bit integer constant

`K` Integer constant that can be deposited with a `zdepi` instruction

`L` Signed 5-bit integer constant

`M` Integer constant 0

`N` Integer constant that can be loaded with a `ldil` instruction

`O` Integer constant whose value plus one is a power of 2

`P` Integer constant that can be used for `and` operations in `depi` and `extru` instructions

`S` Integer constant 31

`U` Integer constant 63

`G` Floating-point constant 0.0

`A` A `lo_sum` data-linkage-table memory operand

`Q` A memory operand that can be used as the destination operand of an integer store instruction

`R` A scaled or unscaled indexed memory operand

`T` A memory operand for floating-point loads and stores

`W` A register indirect memory operand

picoChip family—'`picochip.h`'

`k` Stack register.

`f` Pointer register. A register which can be used to access memory without supplying an offset. Any other register can be used to access memory, but will need a constant offset. In the case of the offset being zero, it is more efficient to use a pointer register, since this reduces code size.

`t` A twin register. A register which may be paired with an adjacent register to create a 32-bit register.

`a` Any absolute memory address (e.g., symbolic constant, symbolic constant `+` offset).

`I` 4-bit signed integer.

`J` 4-bit unsigned integer.

`K` 8-bit signed integer.

`M` Any constant whose absolute value is no greater than 4-bits.

`N` 10-bit signed integer

`O` 16-bit signed integer.

PowerPC and IBM RS6000—'`config/rs6000/constraints.md`'

`b` Address base register

`d` Floating point register (containing 64-bit value)

`f` Floating point register (containing 32-bit value)

`v` Altivec vector register

`wa` Any VSX register if the -mvsx option was used or NO_REGS.

`wd` VSX vector register to hold vector double data or NO_REGS.

`wf` VSX vector register to hold vector float data or NO_REGS.

`wg` If '`-mmfpgpr`' was used, a floating point register or NO_REGS.

`wl` Floating point register if the LFIWAX instruction is enabled or NO_REGS.

`wm` VSX register if direct move instructions are enabled, or NO_REGS.

`wn` No register (NO_REGS).

`wr` General purpose register if 64-bit instructions are enabled or NO_REGS.

`ws` VSX vector register to hold scalar double values or NO_REGS.

`wt` VSX vector register to hold 128 bit integer or NO_REGS.

`wu` Altivec register to use for float/32-bit int loads/stores or NO_REGS.

`wv` Altivec register to use for double loads/stores or NO_REGS.

`ww` FP or VSX register to perform float operations under '`-mvsx`' or NO_REGS.

`wx` Floating point register if the STFIWX instruction is enabled or NO_REGS.

`wy` VSX vector register to hold scalar float values or NO_REGS.

`wz` Floating point register if the LFIWZX instruction is enabled or NO_REGS.

`wD` Int constant that is the element number of the 64-bit scalar in a vector.

`wQ` A memory address that will work with the `lq` and `stq` instructions.

`h` '`MQ`', '`CTR`', or '`LINK`' register

`q` '`MQ`' register

`c` ‘`CTR`’ register

`l` ‘`LINK`’ register

`x` ‘`CR`’ register (condition register) number 0

`y` ‘`CR`’ register (condition register)

`z` ‘`XER[CA]`’ carry bit (part of the XER register)

`I` Signed 16-bit constant

`J` Unsigned 16-bit constant shifted left 16 bits (use ‘`L`’ instead for `SImode` constants)

`K` Unsigned 16-bit constant

`L` Signed 16-bit constant shifted left 16 bits

`M` Constant larger than 31

`N` Exact power of 2

`O` Zero

`P` Constant whose negation is a signed 16-bit constant

`G` Floating point constant that can be loaded into a register with one instruction per word

`H` Integer/Floating point constant that can be loaded into a register using three instructions

`m` Memory operand. Normally, `m` does not allow addresses that update the base register. If ‘`<`’ or ‘`>`’ constraint is also used, they are allowed and therefore on PowerPC targets in that case it is only safe to use ‘`m<>`’ in an `asm` statement if that `asm` statement accesses the operand exactly once. The `asm` statement must also use ‘`%U<`*opno*`>`’ as a placeholder for the “update” flag in the corresponding load or store instruction. For example:

```
asm ("st%U0 %1,%0" : "=m<>" (mem) : "r" (val));
```

is correct but:

```
asm ("st %1,%0" : "=m<>" (mem) : "r" (val));
```

is not.

`es` A “stable” memory operand; that is, one which does not include any automodification of the base register. This used to be useful when ‘`m`’ allowed automodification of the base register, but as those are now only allowed when ‘`<`’ or ‘`>`’ is used, ‘`es`’ is basically the same as ‘`m`’ without ‘`<`’ and ‘`>`’.

`Q` Memory operand that is an offset from a register (it is usually better to use ‘`m`’ or ‘`es`’ in `asm` statements)

`Z` Memory operand that is an indexed or indirect from a register (it is usually better to use ‘`m`’ or ‘`es`’ in `asm` statements)

`R` AIX TOC entry

`a` Address operand that is an indexed or indirect from a register (‘`p`’ is preferable for `asm` statements)

`S` Constant suitable as a 64-bit mask operand

`T` Constant suitable as a 32-bit mask operand

`U` System V Release 4 small data area reference

`t` AND masks that can be performed by two rldic{l, r} instructions

`W` Vector constant that does not require memory

`j` Vector constant that is all zeros.

Intel 386—‘`config/i386/constraints.md`’

`R` Legacy register—the eight integer registers available on all i386 processors (`a`, `b`, `c`, `d`, `si`, `di`, `bp`, `sp`).

`q` Any register accessible as `rl`. In 32-bit mode, `a`, `b`, `c`, and `d`; in 64-bit mode, any integer register.

`Q` Any register accessible as `rh`: `a`, `b`, `c`, and `d`.

`l` Any register that can be used as the index in a base+index memory access: that is, any general register except the stack pointer.

`a` The `a` register.

`b` The `b` register.

`c` The `c` register.

`d` The `d` register.

`S` The `si` register.

`D` The `di` register.

`A` The `a` and `d` registers. This class is used for instructions that return double word results in the `ax:dx` register pair. Single word values will be allocated either in `ax` or `dx`. For example on i386 the following implements `rdtsc`:

```
unsigned long long rdtsc (void)
{
  unsigned long long tick;
  __asm__ __volatile__("rdtsc":"=A"(tick));
  return tick;
}
```

This is not correct on x86_64 as it would allocate tick in either `ax` or `dx`. You have to use the following variant instead:

```
unsigned long long rdtsc (void)
{
  unsigned int tickl, tickh;
  __asm__ __volatile__("rdtsc":"=a"(tickl),"=d"(tickh));
  return ((unsigned long long)tickh << 32)|tickl;
}
```

`f` Any 80387 floating-point (stack) register.

`t` Top of 80387 floating-point stack (`%st(0)`).

`u` Second from top of 80387 floating-point stack (`%st(1)`).

`y` Any MMX register.

`x` Any SSE register.

`Yz` First SSE register (`%xmm0`).

`Y2` Any SSE register, when SSE2 is enabled.

`Yi` Any SSE register, when SSE2 and inter-unit moves are enabled.

`Ym` Any MMX register, when inter-unit moves are enabled.

`I` Integer constant in the range 0 . . . 31, for 32-bit shifts.

`J` Integer constant in the range 0 . . . 63, for 64-bit shifts.

`K` Signed 8-bit integer constant.

`L` `0xFF` or `0xFFFF`, for andsi as a zero-extending move.

`M` 0, 1, 2, or 3 (shifts for the `lea` instruction).

`N` Unsigned 8-bit integer constant (for `in` and `out` instructions).

`O` Integer constant in the range 0 . . . 127, for 128-bit shifts.

`G` Standard 80387 floating point constant.

`C` Standard SSE floating point constant.

`e` 32-bit signed integer constant, or a symbolic reference known to fit that range (for immediate operands in sign-extending x86-64 instructions).

`Z` 32-bit unsigned integer constant, or a symbolic reference known to fit that range (for immediate operands in zero-extending x86-64 instructions).

Intel IA-64—'`config/ia64/ia64.h`'

`a` General register `r0` to `r3` for `addl` instruction

`b` Branch register

`c` Predicate register ('`c`' as in "conditional")

`d` Application register residing in M-unit

`e` Application register residing in I-unit

`f` Floating-point register

`m` Memory operand. If used together with '`<`' or '`>`', the operand can have postincrement and postdecrement which require printing with '`%Pn`' on IA-64.

`G` Floating-point constant 0.0 or 1.0

`I` 14-bit signed integer constant

`J` 22-bit signed integer constant

`K` 8-bit signed integer constant for logical instructions

`L` 8-bit adjusted signed integer constant for compare pseudo-ops

`M` 6-bit unsigned integer constant for shift counts

`N` 9-bit signed integer constant for load and store postincrements

`O` The constant zero

`P` 0 or −1 for `dep` instruction

`Q` Non-volatile memory for floating-point loads and stores

`R` Integer constant in the range 1 to 4 for `shladd` instruction

`S` Memory operand except postincrement and postdecrement. This is now roughly the same as '`m`' when not used together with '`<`' or '`>`'.

FRV—'`config/frv/frv.h`'

`a` Register in the class `ACC_REGS` (`acc0` to `acc7`).

`b` Register in the class `EVEN_ACC_REGS` (`acc0` to `acc7`).

`c` Register in the class `CC_REGS` (`fcc0` to `fcc3` and `icc0` to `icc3`).

`d` Register in the class `GPR_REGS` (`gr0` to `gr63`).

`e` Register in the class `EVEN_REGS` (`gr0` to `gr63`). Odd registers are excluded not in the class but through the use of a machine mode larger than 4 bytes.

`f` Register in the class `FPR_REGS` (`fr0` to `fr63`).

`h` Register in the class `FEVEN_REGS` (`fr0` to `fr63`). Odd registers are excluded not in the class but through the use of a machine mode larger than 4 bytes.

`l` Register in the class `LR_REG` (the `lr` register).

`q` Register in the class `QUAD_REGS` (`gr2` to `gr63`). Register numbers not divisible by 4 are excluded not in the class but through the use of a machine mode larger than 8 bytes.

`t` Register in the class `ICC_REGS` (`icc0` to `icc3`).

`u` Register in the class `FCC_REGS` (`fcc0` to `fcc3`).

`v` Register in the class `ICR_REGS` (`cc4` to `cc7`).

`w` Register in the class `FCR_REGS` (`cc0` to `cc3`).

`x` Register in the class `QUAD_FPR_REGS` (`fr0` to `fr63`). Register numbers not divisible by 4 are excluded not in the class but through the use of a machine mode larger than 8 bytes.

`z` Register in the class `SPR_REGS` (`lcr` and `lr`).

`A` Register in the class `QUAD_ACC_REGS` (`acc0` to `acc7`).

`B` Register in the class `ACCG_REGS` (`accg0` to `accg7`).

`C` Register in the class `CR_REGS` (`cc0` to `cc7`).

`G` Floating point constant zero

`I` 6-bit signed integer constant

`J` 10-bit signed integer constant

`L` 16-bit signed integer constant

`M` 16-bit unsigned integer constant

`N` 12-bit signed integer constant that is negative—i.e. in the range of −2048 to −1

`O` Constant zero

`P` 12-bit signed integer constant that is greater than zero—i.e. in the range of 1 to 2047.

Blackfin family—'`config/bfin/constraints.md`'

`a` P register

`d` D register

`z` A call clobbered P register.

`q`*n* A single register. If *n* is in the range 0 to 7, the corresponding D register. If it is `A`, then the register P0.

`D` Even-numbered D register

`W` Odd-numbered D register

`e` Accumulator register.

`A` Even-numbered accumulator register.

`B` Odd-numbered accumulator register.

`b` I register

`v` B register

`f` M register

`c` Registers used for circular buffering, i.e. I, B, or L registers.

`C` The CC register.

`t` LT0 or LT1.

`k` LC0 or LC1.

`u` LB0 or LB1.

`x` Any D, P, B, M, I or L register.

`y` Additional registers typically used only in prologues and epilogues: RETS, RETN, RETI, RETX, RETE, ASTAT, SEQSTAT and USP.

`w` Any register except accumulators or CC.

`Ksh` Signed 16 bit integer (in the range −32768 to 32767)

`Kuh` Unsigned 16 bit integer (in the range 0 to 65535)

`Ks7` Signed 7 bit integer (in the range −64 to 63)

`Ku7` Unsigned 7 bit integer (in the range 0 to 127)

`Ku5` Unsigned 5 bit integer (in the range 0 to 31)

`Ks4` Signed 4 bit integer (in the range −8 to 7)

`Ks3` Signed 3 bit integer (in the range −3 to 4)

`Ku3` Unsigned 3 bit integer (in the range 0 to 7)

`P`*n* Constant *n*, where *n* is a single-digit constant in the range 0 to 4.

`PA` An integer equal to one of the MACFLAG_XXX constants that is suitable for use with either accumulator.

`PB` An integer equal to one of the MACFLAG_XXX constants that is suitable for use only with accumulator A1.

`M1` Constant 255.

`M2` Constant 65535.

`J` An integer constant with exactly a single bit set.

`L` An integer constant with all bits set except exactly one.

`H`

`Q` Any SYMBOL_REF.

M32C—'`config/m32c/m32c.c`'

`Rsp`
`Rfb`
`Rsb` '`$sp`', '`$fb`', '`$sb`'.

`Rcr` Any control register, when they're 16 bits wide (nothing if control registers are 24 bits wide)

`Rcl` Any control register, when they're 24 bits wide.

`R0w`
`R1w`
`R2w`
`R3w` $r0, $r1, $r2, $r3.

`R02` $r0 or $r2, or $r2r0 for 32 bit values.

`R13` $r1 or $r3, or $r3r1 for 32 bit values.

`Rdi` A register that can hold a 64 bit value.

`Rhl`	$r0 or $r1 (registers with addressable high/low bytes)
`R23`	$r2 or $r3
`Raa`	Address registers
`Raw`	Address registers when they're 16 bits wide.
`Ral`	Address registers when they're 24 bits wide.
`Rqi`	Registers that can hold QI values.
`Rad`	Registers that can be used with displacements ($a0, $a1, $sb).
`Rsi`	Registers that can hold 32 bit values.
`Rhi`	Registers that can hold 16 bit values.
`Rhc`	Registers chat can hold 16 bit values, including all control registers.
`Rra`	$r0 through R1, plus $a0 and $a1.
`Rfl`	The flags register.
`Rmm`	The memory-based pseudo-registers $mem0 through $mem15.
`Rpi`	Registers that can hold pointers (16 bit registers for r8c, m16c; 24 bit registers for m32cm, m32c).
`Rpa`	Matches multiple registers in a PARALLEL to form a larger register. Used to match function return values.
`Is3`	$-8 \ldots 7$
`IS1`	$-128 \ldots 127$
`IS2`	$-32768 \ldots 32767$
`IU2`	$0 \ldots 65535$
`In4`	$-8 \ldots -1$ or $1 \ldots 8$
`In5`	$-16 \ldots -1$ or $1 \ldots 16$
`In6`	$-32 \ldots -1$ or $1 \ldots 32$
`IM2`	$-65536 \ldots -1$
`Ilb`	An 8 bit value with exactly one bit set.
`Ilw`	A 16 bit value with exactly one bit set.
`Sd`	The common src/dest memory addressing modes.
`Sa`	Memory addressed using $a0 or $a1.
`Si`	Memory addressed with immediate addresses.
`Ss`	Memory addressed using the stack pointer ($sp).
`Sf`	Memory addressed using the frame base register ($fb).
`Ss`	Memory addressed using the small base register ($sb).

`S1`	$r1h

MeP—'`config/mep/constraints.md`'

`a`	The $sp register.
`b`	The $tp register.
`c`	Any control register.
`d`	Either the $hi or the $lo register.
`em`	Coprocessor registers that can be directly loaded ($c0-$c15).
`ex`	Coprocessor registers that can be moved to each other.
`er`	Coprocessor registers that can be moved to core registers.
`h`	The $hi register.
`j`	The $rpc register.
`l`	The $lo register.
`t`	Registers which can be used in $tp-relative addressing.
`v`	The $gp register.
`x`	The coprocessor registers.
`y`	The coprocessor control registers.
`z`	The $0 register.
`A`	User-defined register set A.
`B`	User-defined register set B.
`C`	User-defined register set C.
`D`	User-defined register set D.
`I`	Offsets for $gp-rel addressing.
`J`	Constants that can be used directly with boolean insns.
`K`	Constants that can be moved directly to registers.
`L`	Small constants that can be added to registers.
`M`	Long shift counts.
`N`	Small constants that can be compared to registers.
`O`	Constants that can be loaded into the top half of registers.
`S`	Signed 8-bit immediates.
`T`	Symbols encoded for $tp-rel or $gp-rel addressing.
`U`	Non-constant addresses for loading/saving coprocessor registers.
`W`	The top half of a symbol's value.
`Y`	A register indirect address without offset.

`Z` Symbolic references to the control bus.

MicroBlaze—'`config/microblaze/constraints.md`'

`d` A general register (`r0` to `r31`).

`z` A status register (`rmsr`, `$fcc1` to `$fcc7`).

MIPS—'`config/mips/constraints.md`'

`d` An address register. This is equivalent to `r` unless generating MIPS16 code.

`f` A floating-point register (if available).

`h` Formerly the `hi` register. This constraint is no longer supported.

`l` The `lo` register. Use this register to store values that are no bigger than a word.

`x` The concatenated `hi` and `lo` registers. Use this register to store doubleword values.

`c` A register suitable for use in an indirect jump. This will always be `$25` for '`-mabicalls`'.

`v` Register `$3`. Do not use this constraint in new code; it is retained only for compatibility with glibc.

`y` Equivalent to `r`; retained for backwards compatibility.

`z` A floating-point condition code register.

`I` A signed 16-bit constant (for arithmetic instructions).

`J` Integer zero.

`K` An unsigned 16-bit constant (for logic instructions).

`L` A signed 32-bit constant in which the lower 16 bits are zero. Such constants can be loaded using `lui`.

`M` A constant that cannot be loaded using `lui`, `addiu` or `ori`.

`N` A constant in the range −65535 to −1 (inclusive).

`O` A signed 15-bit constant.

`P` A constant in the range 1 to 65535 (inclusive).

`G` Floating-point zero.

`R` An address that can be used in a non-macro load or store.

`ZC` When compiling microMIPS code, this constraint matches a memory operand whose address is formed from a base register and a 12-bit offset. These operands can be used for microMIPS instructions such as `ll` and `sc`. When not compiling for microMIPS code, `ZC` is equivalent to `R`.

`ZD` When compiling microMIPS code, this constraint matches an address operand that is formed from a base register and a 12-bit offset. These operands can be used for microMIPS instructions such as `prefetch`. When not compiling for microMIPS code, `ZD` is equivalent to `p`.

Motorola 680x0—'`config/m68k/constraints.md`'

`a` Address register

`d` Data register

`f` 68881 floating-point register, if available

`I` Integer in the range 1 to 8

`J` 16-bit signed number

`K` Signed number whose magnitude is greater than 0x80

`L` Integer in the range −8 to −1

`M` Signed number whose magnitude is greater than 0x100

`N` Range 24 to 31, rotatert:SI 8 to 1 expressed as rotate

`O` 16 (for rotate using swap)

`P` Range 8 to 15, rotatert:HI 8 to 1 expressed as rotate

`R` Numbers that mov3q can handle

`G` Floating point constant that is not a 68881 constant

`S` Operands that satisfy 'm' when -mpcrel is in effect

`T` Operands that satisfy 's' when -mpcrel is not in effect

`Q` Address register indirect addressing mode

`U` Register offset addressing

`W` const_call_operand

`Cs` symbol_ref or const

`Ci` const_int

`C0` const_int 0

`Cj` Range of signed numbers that don't fit in 16 bits

`Cmvq` Integers valid for mvq

`Capsw` Integers valid for a moveq followed by a swap

`Cmvz` Integers valid for mvz

`Cmvs` Integers valid for mvs

`Ap` push_operand

`Ac` Non-register operands allowed in clr

Moxie—'`config/moxie/constraints.md`'

`A`	An absolute address
`B`	An offset address
`W`	A register indirect memory operand
`I`	A constant in the range of 0 to 255.
`N`	A constant in the range of 0 to −255.

MSP430–'`config/msp430/constraints.md`'

`R12`	Register R12.
`R13`	Register R13.
`K`	Integer constant 1.
`L`	Integer constant -1^20..1^19.
`M`	Integer constant 1-4.
`Ya`	Memory references which do not require an extended MOVX instruction.
`Yl`	Memory reference, labels only.
`Ys`	Memory reference, stack only.

NDS32—'`config/nds32/constraints.md`'

`w`	LOW register class $r0 to $r7 constraint for V3/V3M ISA.
`l`	LOW register class $r0 to $r7.
`d`	MIDDLE register class $r0 to $r11, $r16 to $r19.
`h`	HIGH register class $r12 to $r14, $r20 to $r31.
`t`	Temporary assist register $ta (i.e. $r15).
`k`	Stack register $sp.
`Iu03`	Unsigned immediate 3-bit value.
`In03`	Negative immediate 3-bit value in the range of −7–0.
`Iu04`	Unsigned immediate 4-bit value.
`Is05`	Signed immediate 5-bit value.
`Iu05`	Unsigned immediate 5-bit value.
`In05`	Negative immediate 5-bit value in the range of −31–0.
`Ip05`	Unsigned immediate 5-bit value for movpi45 instruction with range 16–47.
`Iu06`	Unsigned immediate 6-bit value constraint for addri36.sp instruction.
`Iu08`	Unsigned immediate 8-bit value.

`Iu09` Unsigned immediate 9-bit value.

`Is10` Signed immediate 10-bit value.

`Is11` Signed immediate 11-bit value.

`Is15` Signed immediate 15-bit value.

`Iu15` Unsigned immediate 15-bit value.

`Ic15` A constant which is not in the range of imm15u but ok for bclr instruction.

`Ie15` A constant which is not in the range of imm15u but ok for bset instruction.

`It15` A constant which is not in the range of imm15u but ok for btgl instruction.

`Ii15` A constant whose compliment value is in the range of imm15u and ok for bitci instruction.

`Is16` Signed immediate 16-bit value.

`Is17` Signed immediate 17-bit value.

`Is19` Signed immediate 19-bit value.

`Is20` Signed immediate 20-bit value.

`Ihig` The immediate value that can be simply set high 20-bit.

`Izeb` The immediate value 0xff.

`Izeh` The immediate value 0xffff.

`Ixls` The immediate value 0x01.

`Ix11` The immediate value 0x7ff.

`Ibms` The immediate value with power of 2.

`Ifex` The immediate value with power of 2 minus 1.

`U33` Memory constraint for 333 format.

`U45` Memory constraint for 45 format.

`U37` Memory constraint for 37 format.

Nios II family—'`config/nios2/constraints.md`'

`I` Integer that is valid as an immediate operand in an instruction taking a signed 16-bit number. Range −32768 to 32767.

`J` Integer that is valid as an immediate operand in an instruction taking an unsigned 16-bit number. Range 0 to 65535.

`K` Integer that is valid as an immediate operand in an instruction taking only the upper 16-bits of a 32-bit number. Range 32-bit numbers with the lower 16-bits being 0.

`L` Integer that is valid as an immediate operand for a shift instruction. Range 0 to 31.

`M` Integer that is valid as an immediate operand for only the value 0. Can be used in conjunction with the format modifier `z` to use `r0` instead of `0` in the assembly output.

`N` Integer that is valid as an immediate operand for a custom instruction opcode. Range 0 to 255.

`S` Matches immediates which are addresses in the small data section and therefore can be added to `gp` as a 16-bit immediate to re-create their 32-bit value.

`T` A `const` wrapped `UNSPEC` expression, representing a supported PIC or TLS relocation.

PDP-11—'`config/pdp11/constraints.md`'

`a` Floating point registers AC0 through AC3. These can be loaded from/to memory with a single instruction.

`d` Odd numbered general registers (R1, R3, R5). These are used for 16-bit multiply operations.

`f` Any of the floating point registers (AC0 through AC5).

`G` Floating point constant 0.

`I` An integer constant that fits in 16 bits.

`J` An integer constant whose low order 16 bits are zero.

`K` An integer constant that does not meet the constraints for codes '`I`' or '`J`'.

`L` The integer constant 1.

`M` The integer constant −1.

`N` The integer constant 0.

`O` Integer constants −4 through −1 and 1 through 4; shifts by these amounts are handled as multiple single-bit shifts rather than a single variable-length shift.

`Q` A memory reference which requires an additional word (address or offset) after the opcode.

`R` A memory reference that is encoded within the opcode.

RL78—'`config/rl78/constraints.md`'

`Int3` An integer constant in the range 1 . . . 7.

`Int8` An integer constant in the range 0 . . . 255.

`J` An integer constant in the range −255 . . . 0

`K` The integer constant 1.

`L`	The integer constant -1.
`M`	The integer constant 0.
`N`	The integer constant 2.
`O`	The integer constant -2.
`P`	An integer constant in the range 1 . . . 15.
`Qbi`	The built-in compare types–eq, ne, gtu, ltu, geu, and leu.
`Qsc`	The synthetic compare types–gt, lt, ge, and le.
`Wab`	A memory reference with an absolute address.
`Wbc`	A memory reference using `BC` as a base register, with an optional offset.
`Wca`	A memory reference using `AX`, `BC`, `DE`, or `HL` for the address, for calls.
`Wcv`	A memory reference using any 16-bit register pair for the address, for calls.
`Wd2`	A memory reference using `DE` as a base register, with an optional offset.
`Wde`	A memory reference using `DE` as a base register, without any offset.
`Wfr`	Any memory reference to an address in the far address space.
`Wh1`	A memory reference using `HL` as a base register, with an optional one-byte offset.
`Whb`	A memory reference using `HL` as a base register, with `B` or `C` as the index register.
`Whl`	A memory reference using `HL` as a base register, without any offset.
`Ws1`	A memory reference using `SP` as a base register, with an optional one-byte offset.
`Y`	Any memory reference to an address in the near address space.
`A`	The `AX` register.
`B`	The `BC` register.
`D`	The `DE` register.
`R`	`A` through `L` registers.
`S`	The `SP` register.
`T`	The `HL` register.
`Z08W`	The 16-bit `R8` register.
`Z10W`	The 16-bit `R10` register.
`Zint`	The registers reserved for interrupts (`R24` to `R31`).

`a` The `A` register.

`b` The `B` register.

`c` The `C` register.

`d` The `D` register.

`e` The `E` register.

`h` The `H` register.

`l` The `L` register.

`v` The virtual registers.

`w` The `PSW` register.

`x` The `X` register.

RX—'`config/rx/constraints.md`'

`Q` An address which does not involve register indirect addressing or pre/post increment/decrement addressing.

`Symbol` A symbol reference.

`Int08` A constant in the range −256 to 255, inclusive.

`Sint08` A constant in the range −128 to 127, inclusive.

`Sint16` A constant in the range −32768 to 32767, inclusive.

`Sint24` A constant in the range −8388608 to 8388607, inclusive.

`Uint04` A constant in the range 0 to 15, inclusive.

SPARC—'`config/sparc/sparc.h`'

`f` Floating-point register on the SPARC-V8 architecture and lower floating-point register on the SPARC-V9 architecture.

`e` Floating-point register. It is equivalent to '`f`' on the SPARC-V8 architecture and contains both lower and upper floating-point registers on the SPARC-V9 architecture.

`c` Floating-point condition code register.

`d` Lower floating-point register. It is only valid on the SPARC-V9 architecture when the Visual Instruction Set is available.

`b` Floating-point register. It is only valid on the SPARC-V9 architecture when the Visual Instruction Set is available.

`h` 64-bit global or out register for the SPARC-V8+ architecture.

`C` The constant all-ones, for floating-point.

`A` Signed 5-bit constant

`D` A vector constant

`I` Signed 13-bit constant

`J` Zero

`K` 32-bit constant with the low 12 bits clear (a constant that can be loaded with the `sethi` instruction)

`L` A constant in the range supported by `movcc` instructions (11-bit signed immediate)

`M` A constant in the range supported by `movrcc` instructions (10-bit signed immediate)

`N` Same as '`K`', except that it verifies that bits that are not in the lower 32-bit range are all zero. Must be used instead of '`K`' for modes wider than `SImode`

`O` The constant 4096

`G` Floating-point zero

`H` Signed 13-bit constant, sign-extended to 32 or 64 bits

`P` The constant -1

`Q` Floating-point constant whose integral representation can be moved into an integer register using a single sethi instruction

`R` Floating-point constant whose integral representation can be moved into an integer register using a single mov instruction

`S` Floating-point constant whose integral representation can be moved into an integer register using a high/lo_sum instruction sequence

`T` Memory address aligned to an 8-byte boundary

`U` Even register

`W` Memory address for '`e`' constraint registers

`w` Memory address with only a base register

`Y` Vector zero

SPU—'`config/spu/spu.h`'

`a` An immediate which can be loaded with the il/ila/ilh/ilhu instructions. const_int is treated as a 64 bit value.

`c` An immediate for and/xor/or instructions. const_int is treated as a 64 bit value.

`d` An immediate for the `iohl` instruction. const_int is treated as a 64 bit value.

`f` An immediate which can be loaded with `fsmbi`.

`A` An immediate which can be loaded with the il/ila/ilh/ilhu instructions. const_int is treated as a 32 bit value.

`B` An immediate for most arithmetic instructions. const_int is treated as a 32 bit value.

`C` An immediate for and/xor/or instructions. const_int is treated as a 32 bit value.

`D` An immediate for the `iohl` instruction. const_int is treated as a 32 bit value.

`I` A constant in the range [−64, 63] for shift/rotate instructions.

`J` An unsigned 7-bit constant for conversion/nop/channel instructions.

`K` A signed 10-bit constant for most arithmetic instructions.

`M` A signed 16 bit immediate for `stop`.

`N` An unsigned 16-bit constant for `iohl` and `fsmbi`.

`O` An unsigned 7-bit constant whose 3 least significant bits are 0.

`P` An unsigned 3-bit constant for 16-byte rotates and shifts

`R` Call operand, reg, for indirect calls

`S` Call operand, symbol, for relative calls.

`T` Call operand, const_int, for absolute calls.

`U` An immediate which can be loaded with the il/ila/ilh/ilhu instructions. const_int is sign extended to 128 bit.

`W` An immediate for shift and rotate instructions. const_int is treated as a 32 bit value.

`Y` An immediate for and/xor/or instructions. const_int is sign extended as a 128 bit.

`Z` An immediate for the `iohl` instruction. const_int is sign extended to 128 bit.

S/390 and zSeries—'`config/s390/s390.h`'

`a` Address register (general purpose register except r0)

`c` Condition code register

`d` Data register (arbitrary general purpose register)

`f` Floating-point register

`I` Unsigned 8-bit constant (0–255)

`J` Unsigned 12-bit constant (0–4095)

`K` Signed 16-bit constant (−32768–32767)

`L` Value appropriate as displacement.

`(0..4095)`
for short displacement

`(−524288..524287)`
for long displacement

`M` Constant integer with a value of 0x7fffffff.

`N` Multiple letter constraint followed by 4 parameter letters.

- `0..9:` number of the part counting from most to least significant
- `H,Q:` mode of the part
- `D,S,H:` mode of the containing operand
- `0,F:` value of the other parts (F—all bits set)

The constraint matches if the specified part of a constant has a value different from its other parts.

`Q` Memory reference without index register and with short displacement.

`R` Memory reference with index register and short displacement.

`S` Memory reference without index register but with long displacement.

`T` Memory reference with index register and long displacement.

`U` Pointer with short displacement.

`W` Pointer with long displacement.

`Y` Shift count operand.

Score family—'`config/score/score.h`'

`d` Registers from r0 to r32.

`e` Registers from r0 to r16.

`t` r8—r11 or r22—r27 registers.

`h` hi register.

`l` lo register.

`x` hi + lo register.

`q` cnt register.

`y` lcb register.

`z` scb register.

`a` cnt + lcb + scb register.

`c` cr0—cr15 register.

`b` cp1 registers.

`f` cp2 registers.

`i` cp3 registers.

`j` cp1 + cp2 + cp3 registers.

`I` High 16-bit constant (32-bit constant with 16 LSBs zero).

`J` Unsigned 5 bit integer (in the range 0 to 31).

`K` Unsigned 16 bit integer (in the range 0 to 65535).

`L` Signed 16 bit integer (in the range −32768 to 32767).

`M` Unsigned 14 bit integer (in the range 0 to 16383).

`N` Signed 14 bit integer (in the range −8192 to 8191).

`Z` Any SYMBOL_REF.

Xstormy16—'`config/stormy16/stormy16.h`'

`a` Register r0.

`b` Register r1.

`c` Register r2.

`d` Register r8.

`e` Registers r0 through r7.

`t` Registers r0 and r1.

`y` The carry register.

`z` Registers r8 and r9.

`I` A constant between 0 and 3 inclusive.

`J` A constant that has exactly one bit set.

`K` A constant that has exactly one bit clear.

`L` A constant between 0 and 255 inclusive.

`M` A constant between −255 and 0 inclusive.

`N` A constant between −3 and 0 inclusive.

`O` A constant between 1 and 4 inclusive.

`P` A constant between −4 and −1 inclusive.

`Q` A memory reference that is a stack push.

`R` A memory reference that is a stack pop.

`S` A memory reference that refers to a constant address of known value.

`T` The register indicated by Rx (not implemented yet).

`U` A constant that is not between 2 and 15 inclusive.

`Z` The constant 0.

TI C6X family—'`config/c6x/constraints.md`'

`a` Register file A (A0–A31).

`b` Register file B (B0–B31).

`A` Predicate registers in register file A (A0–A2 on C64X and higher, A1 and A2 otherwise).

`B` Predicate registers in register file B (B0–B2).

`C` A call-used register in register file B (B0–B9, B16–B31).

`Da` Register file A, excluding predicate registers (A3–A31, plus A0 if not C64X or higher).

`Db` Register file B, excluding predicate registers (B3–B31).

`Iu4` Integer constant in the range 0 . . . 15.

`Iu5` Integer constant in the range 0 . . . 31.

`In5` Integer constant in the range −31 . . . 0.

`Is5` Integer constant in the range −16 . . . 15.

`I5x` Integer constant that can be the operand of an ADDA or a SUBA insn.

`IuB` Integer constant in the range 0 . . . 65535.

`IsB` Integer constant in the range −32768 . . . 32767.

`IsC` Integer constant in the range -2^{20} . . . $2^{20} - 1$.

`Jc` Integer constant that is a valid mask for the clr instruction.

`Js` Integer constant that is a valid mask for the set instruction.

`Q` Memory location with A base register.

`R` Memory location with B base register.

`S0` On C64x+ targets, a GP-relative small data reference.

`S1` Any kind of `SYMBOL_REF`, for use in a call address.

`Si` Any kind of immediate operand, unless it matches the S0 constraint.

`T` Memory location with B base register, but not using a long offset.

`W` A memory operand with an address that can't be used in an unaligned access.

`Z` Register B14 (aka DP).

TILE-Gx—'`config/tilegx/constraints.md`'

`R00`
`R01`
`R02`
`R03`
`R04`
`R05`
`R06`
`R07`
`R08`
`R09`
`R10` Each of these represents a register constraint for an individual register, from r0 to r10.

`I` Signed 8-bit integer constant.

`J` Signed 16-bit integer constant.

`K` Unsigned 16-bit integer constant.

`L` Integer constant that fits in one signed byte when incremented by one (−129 . . . 126).

`m` Memory operand. If used together with '`<`' or '`>`', the operand can have postincrement which requires printing with '`%In`' and '`%in`' on TILE-Gx. For example:

```
asm ("st_add %I0,%1,%i0" : "=m<>" (*mem) : "r" (val));
```

`M` A bit mask suitable for the BFINS instruction.

`N` Integer constant that is a byte tiled out eight times.

`O` The integer zero constant.

`P` Integer constant that is a sign-extended byte tiled out as four shorts.

`Q` Integer constant that fits in one signed byte when incremented (−129 . . . 126), but excluding -1.

`S` Integer constant that has all 1 bits consecutive and starting at bit 0.

`T` A 16-bit fragment of a got, tls, or pc-relative reference.

`U` Memory operand except postincrement. This is roughly the same as '`m`' when not used together with '`<`' or '`>`'.

`W` An 8-element vector constant with identical elements.

`Y` A 4-element vector constant with identical elements.

`Z0` The integer constant 0xffffffff.

`Z1` The integer constant 0xffffffff00000000.

TILEPro—'`config/tilepro/constraints.md`'

`R00`
`R01`
`R02`
`R03`
`R04`
`R05`
`R06`
`R07`
`R08`
`R09`
`R10` Each of these represents a register constraint for an individual register, from r0 to r10.

`I` Signed 8-bit integer constant.

`J` Signed 16-bit integer constant.

`K` Nonzero integer constant with low 16 bits zero.

`L` Integer constant that fits in one signed byte when incremented by one (−129 . . . 126).

`m` Memory operand. If used together with '`<`' or '`>`', the operand can have postincrement which requires printing with '`%In`' and '`%in`' on TILEPro. For example:

```
asm ("swadd %I0,%1,%i0" : "=m<>" (mem) : "r" (val));
```

`M` A bit mask suitable for the MM instruction.

`N` Integer constant that is a byte tiled out four times.

`O` The integer zero constant.

`P` Integer constant that is a sign-extended byte tiled out as two shorts.

`Q` Integer constant that fits in one signed byte when incremented (−129 . . . 126), but excluding -1.

`T` A symbolic operand, or a 16-bit fragment of a got, tls, or pc-relative reference.

`U` Memory operand except postincrement. This is roughly the same as '`m`' when not used together with '`<`' or '`>`'.

`W` A 4-element vector constant with identical elements.

`Y` A 2-element vector constant with identical elements.

Xtensa—'`config/xtensa/constraints.md`'

`a` General-purpose 32-bit register

`b` One-bit boolean register

`A` MAC16 40-bit accumulator register

`I` Signed 12-bit integer constant, for use in MOVI instructions

`J`	Signed 8-bit integer constant, for use in ADDI instructions
`K`	Integer constant valid for BccI instructions
`L`	Unsigned constant valid for BccUI instructions

16.8.6 Disable insn alternatives using the `enabled` attribute

The `enabled` insn attribute may be used to disable certain insn alternatives for machine-specific reasons. This is useful when adding new instructions to an existing pattern which are only available for certain cpu architecture levels as specified with the `-march=` option.

If an insn alternative is disabled, then it will never be used. The compiler treats the constraints for the disabled alternative as unsatisfiable.

In order to make use of the `enabled` attribute a back end has to add in the machine description files:

1. A definition of the `enabled` insn attribute. The attribute is defined as usual using the `define_attr` command. This definition should be based on other insn attributes and/or target flags. The `enabled` attribute is a numeric attribute and should evaluate to `(const_int 1)` for an enabled alternative and to `(const_int 0)` otherwise.
2. A definition of another insn attribute used to describe for what reason an insn alternative might be available or not. E.g. `cpu_facility` as in the example below.
3. An assignment for the second attribute to each insn definition combining instructions which are not all available under the same circumstances. (Note: It obviously only makes sense for definitions with more than one alternative. Otherwise the insn pattern should be disabled or enabled using the insn condition.)

E.g. the following two patterns could easily be merged using the `enabled` attribute:

```
(define_insn "*movdi_old"
  [(set (match_operand:DI 0 "register_operand" "=d")
        (match_operand:DI 1 "register_operand" " d"))]
  "!TARGET_NEW"
  "lgr %0,%1")

(define_insn "*movdi_new"
  [(set (match_operand:DI 0 "register_operand" "=d,f,d")
        (match_operand:DI 1 "register_operand" " d,d,f"))]
  "TARGET_NEW"
  "@
   lgr  %0,%1
   ldgr %0,%1
   lgdr %0,%1")
```

to:

```
(define_insn "*movdi_combined"
  [(set (match_operand:DI 0 "register_operand" "=d,f,d")
        (match_operand:DI 1 "register_operand" " d,d,f"))]
  ""
  "@
   lgr  %0,%1
   ldgr %0,%1
   lgdr %0,%1"
```

```
    [(set_attr "cpu_facility" "*,new,new")])
```

with the `enabled` attribute defined like this:

```
(define_attr "cpu_facility" "standard,new" (const_string "standard"))

(define_attr "enabled" ""
  (cond [(eq_attr "cpu_facility" "standard") (const_int 1)
         (and (eq_attr "cpu_facility" "new")
              (ne (symbol_ref "TARGET_NEW") (const_int 0)))
         (const_int 1)]
        (const_int 0)))
```

16.8.7 Defining Machine-Specific Constraints

Machine-specific constraints fall into two categories: register and non-register constraints. Within the latter category, constraints which allow subsets of all possible memory or address operands should be specially marked, to give `reload` more information.

Machine-specific constraints can be given names of arbitrary length, but they must be entirely composed of letters, digits, underscores ('`_`'), and angle brackets ('`< >`'). Like C identifiers, they must begin with a letter or underscore.

In order to avoid ambiguity in operand constraint strings, no constraint can have a name that begins with any other constraint's name. For example, if `x` is defined as a constraint name, `xy` may not be, and vice versa. As a consequence of this rule, no constraint may begin with one of the generic constraint letters: '`E F V X g i m n o p r s`'.

Register constraints correspond directly to register classes. See Section 17.8 [Register Classes], page 453. There is thus not much flexibility in their definitions.

`define_register_constraint` *name regclass docstring* [MD Expression]

All three arguments are string constants. *name* is the name of the constraint, as it will appear in `match_operand` expressions. If *name* is a multi-letter constraint its length shall be the same for all constraints starting with the same letter. *regclass* can be either the name of the corresponding register class (see Section 17.8 [Register Classes], page 453), or a C expression which evaluates to the appropriate register class. If it is an expression, it must have no side effects, and it cannot look at the operand. The usual use of expressions is to map some register constraints to `NO_REGS` when the register class is not available on a given subarchitecture.

docstring is a sentence documenting the meaning of the constraint. Docstrings are explained further below.

Non-register constraints are more like predicates: the constraint definition gives a Boolean expression which indicates whether the constraint matches.

`define_constraint` *name docstring exp* [MD Expression]

The *name* and *docstring* arguments are the same as for `define_register_constraint`, but note that the docstring comes immediately after the name for these expressions. *exp* is an RTL expression, obeying the same rules as the RTL expressions in predicate definitions. See Section 16.7.2 [Defining Predicates], page 308, for details. If it evaluates true, the constraint matches; if it evaluates false,

it doesn't. Constraint expressions should indicate which RTL codes they might match, just like predicate expressions.

`match_test` C expressions have access to the following variables:

op The RTL object defining the operand.

mode The machine mode of *op*.

ival '`INTVAL (op)`', if *op* is a `const_int`.

hval '`CONST_DOUBLE_HIGH (op)`', if *op* is an integer `const_double`.

lval '`CONST_DOUBLE_LOW (op)`', if *op* is an integer `const_double`.

rval '`CONST_DOUBLE_REAL_VALUE (op)`', if *op* is a floating-point `const_double`.

The **val* variables should only be used once another piece of the expression has verified that *op* is the appropriate kind of RTL object.

Most non-register constraints should be defined with `define_constraint`. The remaining two definition expressions are only appropriate for constraints that should be handled specially by `reload` if they fail to match.

`define_memory_constraint` *name docstring exp* [MD Expression]

Use this expression for constraints that match a subset of all memory operands: that is, `reload` can make them match by converting the operand to the form '`(mem (reg X))`', where *X* is a base register (from the register class specified by `BASE_REG_CLASS`, see Section 17.8 [Register Classes], page 453).

For example, on the S/390, some instructions do not accept arbitrary memory references, but only those that do not make use of an index register. The constraint letter '`Q`' is defined to represent a memory address of this type. If '`Q`' is defined with `define_memory_constraint`, a '`Q`' constraint can handle any memory operand, because `reload` knows it can simply copy the memory address into a base register if required. This is analogous to the way an '`o`' constraint can handle any memory operand.

The syntax and semantics are otherwise identical to `define_constraint`.

`define_address_constraint` *name docstring exp* [MD Expression]

Use this expression for constraints that match a subset of all address operands: that is, `reload` can make the constraint match by converting the operand to the form '`(reg X)`', again with *X* a base register.

Constraints defined with `define_address_constraint` can only be used with the `address_operand` predicate, or machine-specific predicates that work the same way. They are treated analogously to the generic '`p`' constraint.

The syntax and semantics are otherwise identical to `define_constraint`.

For historical reasons, names beginning with the letters '`G H`' are reserved for constraints that match only `const_double`s, and names beginning with the letters '`I J K L M N O P`' are reserved for constraints that match only `const_int`s. This may change in the future. For the time being, constraints with these names must be written in a stylized form, so that `genpreds` can tell you did it correctly:

```
(define_constraint "[GHIJKLMNOP]..."
  "doc..."
  (and (match_code "const_int")  ; const_double for G/H
       condition...))            ; usually a match_test
```

It is fine to use names beginning with other letters for constraints that match `const_double`s or `const_int`s.

Each docstring in a constraint definition should be one or more complete sentences, marked up in Texinfo format. *They are currently unused.* In the future they will be copied into the GCC manual, in Section 16.8.5 [Machine Constraints], page 317, replacing the hand-maintained tables currently found in that section. Also, in the future the compiler may use this to give more helpful diagnostics when poor choice of `asm` constraints causes a reload failure.

If you put the pseudo-Texinfo directive '`@internal`' at the beginning of a docstring, then (in the future) it will appear only in the internals manual's version of the machine-specific constraint tables. Use this for constraints that should not appear in `asm` statements.

16.8.8 Testing constraints from C

It is occasionally useful to test a constraint from C code rather than implicitly via the constraint string in a `match_operand`. The generated file '`tm_p.h`' declares a few interfaces for working with machine-specific constraints. None of these interfaces work with the generic constraints described in Section 16.8.1 [Simple Constraints], page 310. This may change in the future.

Warning: '`tm_p.h`' may declare other functions that operate on constraints, besides the ones documented here. Do not use those functions from machine-dependent code. They exist to implement the old constraint interface that machine-independent components of the compiler still expect. They will change or disappear in the future.

Some valid constraint names are not valid C identifiers, so there is a mangling scheme for referring to them from C. Constraint names that do not contain angle brackets or underscores are left unchanged. Underscores are doubled, each '`<`' is replaced with '`_l`', and each '`>`' with '`_g`'. Here are some examples:

Original	Mangled
`x`	`x`
`P42x`	`P42x`
`P4_x`	`P4__x`
`P4>x`	`P4_gx`
`P4>>`	`P4_g_g`
`P4_g>`	`P4__g_g`

Throughout this section, the variable *c* is either a constraint in the abstract sense, or a constant from `enum constraint_num`; the variable *m* is a mangled constraint name (usually as part of a larger identifier).

`constraint_num` [Enum]

For each machine-specific constraint, there is a corresponding enumeration constant: '`CONSTRAINT_`' plus the mangled name of the constraint. Functions that take an `enum constraint_num` as an argument expect one of these constants.

Machine-independent constraints do not have associated constants. This may change in the future.

`inline bool satisfies_constraint_m` (*rtx exp*) [Function]
For each machine-specific, non-register constraint *m*, there is one of these functions; it returns `true` if *exp* satisfies the constraint. These functions are only visible if '`rtl.h`' was included before '`tm_p.h`'.

`bool constraint_satisfied_p` (*rtx exp*, *enum constraint_num c*) [Function]
Like the `satisfies_constraint_m` functions, but the constraint to test is given as an argument, *c*. If *c* specifies a register constraint, this function will always return `false`.

`enum reg_class regclass_for_constraint` (*enum constraint_num c*) [Function]
Returns the register class associated with *c*. If *c* is not a register constraint, or those registers are not available for the currently selected subtarget, returns `NO_REGS`.

Here is an example use of `satisfies_constraint_m`. In peephole optimizations (see Section 16.18 [Peephole Definitions], page 390), operand constraint strings are ignored, so if there are relevant constraints, they must be tested in the C condition. In the example, the optimization is applied if operand 2 does *not* satisfy the '`K`' constraint. (This is a simplified version of a peephole definition from the i386 machine description.)

```
(define_peephole2
  [(match_scratch:SI 3 "r")
   (set (match_operand:SI 0 "register_operand" "")
        (mult:SI (match_operand:SI 1 "memory_operand" "")
                 (match_operand:SI 2 "immediate_operand" "")))]

  "!satisfies_constraint_K (operands[2])"

  [(set (match_dup 3) (match_dup 1))
   (set (match_dup 0) (mult:SI (match_dup 3) (match_dup 2)))]

  "")
```

16.9 Standard Pattern Names For Generation

Here is a table of the instruction names that are meaningful in the RTL generation pass of the compiler. Giving one of these names to an instruction pattern tells the RTL generation pass that it can use the pattern to accomplish a certain task.

'`mov`*m*' Here *m* stands for a two-letter machine mode name, in lowercase. This instruction pattern moves data with that machine mode from operand 1 to operand 0. For example, '`movsi`' moves full-word data.

If operand 0 is a `subreg` with mode *m* of a register whose own mode is wider than *m*, the effect of this instruction is to store the specified value in the part of the register that corresponds to mode *m*. Bits outside of *m*, but which are within the same target word as the `subreg` are undefined. Bits which are outside the target word are left unchanged.

This class of patterns is special in several ways. First of all, each of these names up to and including full word size *must* be defined, because there is no other

way to copy a datum from one place to another. If there are patterns accepting operands in larger modes, '`mov`*m*' must be defined for integer modes of those sizes.

Second, these patterns are not used solely in the RTL generation pass. Even the reload pass can generate move insns to copy values from stack slots into temporary registers. When it does so, one of the operands is a hard register and the other is an operand that can need to be reloaded into a register.

Therefore, when given such a pair of operands, the pattern must generate RTL which needs no reloading and needs no temporary registers—no registers other than the operands. For example, if you support the pattern with a `define_expand`, then in such a case the `define_expand` mustn't call `force_reg` or any other such function which might generate new pseudo registers.

This requirement exists even for subword modes on a RISC machine where fetching those modes from memory normally requires several insns and some temporary registers.

During reload a memory reference with an invalid address may be passed as an operand. Such an address will be replaced with a valid address later in the reload pass. In this case, nothing may be done with the address except to use it as it stands. If it is copied, it will not be replaced with a valid address. No attempt should be made to make such an address into a valid address and no routine (such as `change_address`) that will do so may be called. Note that `general_operand` will fail when applied to such an address.

The global variable `reload_in_progress` (which must be explicitly declared if required) can be used to determine whether such special handling is required.

The variety of operands that have reloads depends on the rest of the machine description, but typically on a RISC machine these can only be pseudo registers that did not get hard registers, while on other machines explicit memory references will get optional reloads.

If a scratch register is required to move an object to or from memory, it can be allocated using `gen_reg_rtx` prior to life analysis.

If there are cases which need scratch registers during or after reload, you must provide an appropriate secondary_reload target hook.

The macro `can_create_pseudo_p` can be used to determine if it is unsafe to create new pseudo registers. If this variable is nonzero, then it is unsafe to call `gen_reg_rtx` to allocate a new pseudo.

The constraints on a '`mov`*m*' must permit moving any hard register to any other hard register provided that `HARD_REGNO_MODE_OK` permits mode *m* in both registers and `TARGET_REGISTER_MOVE_COST` applied to their classes returns a value of 2.

It is obligatory to support floating point '`mov`*m*' instructions into and out of any registers that can hold fixed point values, because unions and structures (which have modes `SImode` or `DImode`) can be in those registers and they may have floating point members.

There may also be a need to support fixed point '`mov`*m*' instructions in and out of floating point registers. Unfortunately, I have forgotten why this was so, and

I don't know whether it is still true. If `HARD_REGNO_MODE_OK` rejects fixed point values in floating point registers, then the constraints of the fixed point '`mov`*m*' instructions must be designed to avoid ever trying to reload into a floating point register.

'`reload_in`*m*'
'`reload_out`*m*'

These named patterns have been obsoleted by the target hook `secondary_reload`.

Like '`mov`*m*', but used when a scratch register is required to move between operand 0 and operand 1. Operand 2 describes the scratch register. See the discussion of the `SECONDARY_RELOAD_CLASS` macro in see Section 17.8 [Register Classes], page 453.

There are special restrictions on the form of the `match_operand`s used in these patterns. First, only the predicate for the reload operand is examined, i.e., `reload_in` examines operand 1, but not the predicates for operand 0 or 2. Second, there may be only one alternative in the constraints. Third, only a single register class letter may be used for the constraint; subsequent constraint letters are ignored. As a special exception, an empty constraint string matches the `ALL_REGS` register class. This may relieve ports of the burden of defining an `ALL_REGS` constraint letter just for these patterns.

'`movstrict`*m*'

Like '`mov`*m*' except that if operand 0 is a `subreg` with mode *m* of a register whose natural mode is wider, the '`movstrict`*m*' instruction is guaranteed not to alter any of the register except the part which belongs to mode *m*.

'`movmisalign`*m*'

This variant of a move pattern is designed to load or store a value from a memory address that is not naturally aligned for its mode. For a store, the memory will be in operand 0; for a load, the memory will be in operand 1. The other operand is guaranteed not to be a memory, so that it's easy to tell whether this is a load or store.

This pattern is used by the autovectorizer, and when expanding a `MISALIGNED_INDIRECT_REF` expression.

'`load_multiple`'

Load several consecutive memory locations into consecutive registers. Operand 0 is the first of the consecutive registers, operand 1 is the first memory location, and operand 2 is a constant: the number of consecutive registers.

Define this only if the target machine really has such an instruction; do not define this if the most efficient way of loading consecutive registers from memory is to do them one at a time.

On some machines, there are restrictions as to which consecutive registers can be stored into memory, such as particular starting or ending register numbers or only a range of valid counts. For those machines, use a `define_expand` (see Section 16.15 [Expander Definitions], page 383) and make the pattern fail if the restrictions are not met.

Write the generated insn as a `parallel` with elements being a `set` of one register from the appropriate memory location (you may also need `use` or `clobber` elements). Use a `match_parallel` (see Section 16.4 [RTL Template], page 299) to recognize the insn. See '`rs6000.md`' for examples of the use of this insn pattern.

'`store_multiple`'
Similar to '`load_multiple`', but store several consecutive registers into consecutive memory locations. Operand 0 is the first of the consecutive memory locations, operand 1 is the first register, and operand 2 is a constant: the number of consecutive registers.

'`vec_load_lanes`*mn*'
Perform an interleaved load of several vectors from memory operand 1 into register operand 0. Both operands have mode *m*. The register operand is viewed as holding consecutive vectors of mode *n*, while the memory operand is a flat array that contains the same number of elements. The operation is equivalent to:

```
int c = GET_MODE_SIZE (m) / GET_MODE_SIZE (n);
for (j = 0; j < GET_MODE_NUNITS (n); j++)
  for (i = 0; i < c; i++)
    operand0[i][j] = operand1[j * c + i];
```

For example, '`vec_load_lanestiv4hi`' loads 8 16-bit values from memory into a register of mode '`TI`'. The register contains two consecutive vectors of mode '`V4HI`'.

This pattern can only be used if:

```
TARGET_ARRAY_MODE_SUPPORTED_P (n, c)
```

is true. GCC assumes that, if a target supports this kind of instruction for some mode *n*, it also supports unaligned loads for vectors of mode *n*.

'`vec_store_lanes`*mn*'
Equivalent to '`vec_load_lanes`*mn*', with the memory and register operands reversed. That is, the instruction is equivalent to:

```
int c = GET_MODE_SIZE (m) / GET_MODE_SIZE (n);
for (j = 0; j < GET_MODE_NUNITS (n); j++)
  for (i = 0; i < c; i++)
    operand0[j * c + i] = operand1[i][j];
```

for a memory operand 0 and register operand 1.

'`vec_set`*m*'
Set given field in the vector value. Operand 0 is the vector to modify, operand 1 is new value of field and operand 2 specify the field index.

'`vec_extract`*m*'
Extract given field from the vector value. Operand 1 is the vector, operand 2 specify field index and operand 0 place to store value into.

'`vec_init`*m*'
Initialize the vector to given values. Operand 0 is the vector to initialize and operand 1 is parallel containing values for individual fields.

'vcond*mn*' Output a conditional vector move. Operand 0 is the destination to receive a combination of operand 1 and operand 2, which are of mode *m*, dependent on the outcome of the predicate in operand 3 which is a vector comparison with operands of mode *n* in operands 4 and 5. The modes *m* and *n* should have the same size. Operand 0 will be set to the value *op1* & *msk* | *op2* & ~*msk* where *msk* is computed by element-wise evaluation of the vector comparison with a truth value of all-ones and a false value of all-zeros.

'vec_perm*m*'

Output a (variable) vector permutation. Operand 0 is the destination to receive elements from operand 1 and operand 2, which are of mode *m*. Operand 3 is the *selector*. It is an integral mode vector of the same width and number of elements as mode *m*.

The input elements are numbered from 0 in operand 1 through $2 * N - 1$ in operand 2. The elements of the selector must be computed modulo $2 * N$. Note that if `rtx_equal_p(operand1, operand2)`, this can be implemented with just operand 1 and selector elements modulo *N*.

In order to make things easy for a number of targets, if there is no 'vec_perm' pattern for mode *m*, but there is for mode *q* where *q* is a vector of `QImode` of the same width as *m*, the middle-end will lower the mode *m* `VEC_PERM_EXPR` to mode *q*.

'vec_perm_const*m*'

Like 'vec_perm' except that the permutation is a compile-time constant. That is, operand 3, the *selector*, is a `CONST_VECTOR`.

Some targets cannot perform a permutation with a variable selector, but can efficiently perform a constant permutation. Further, the target hook `vec_perm_ok` is queried to determine if the specific constant permutation is available efficiently; the named pattern is never expanded without `vec_perm_ok` returning true.

There is no need for a target to supply both 'vec_perm*m*' and 'vec_perm_const*m*' if the former can trivially implement the operation with, say, the vector constant loaded into a register.

'push*m*1' Output a push instruction. Operand 0 is value to push. Used only when `PUSH_ROUNDING` is defined. For historical reason, this pattern may be missing and in such case an `mov` expander is used instead, with a `MEM` expression forming the push operation. The `mov` expander method is deprecated.

'add*m*3' Add operand 2 and operand 1, storing the result in operand 0. All operands must have mode *m*. This can be used even on two-address machines, by means of constraints requiring operands 1 and 0 to be the same location.

'addptr*m*3'

Like `add*m*3` but is guaranteed to only be used for address calculations. The expanded code is not allowed to clobber the condition code. It only needs to be defined if `add*m*3` sets the condition code. If adds used for address calculations and normal adds are not compatible it is required to expand a distinct

pattern (e.g. using an unspec). The pattern is used by LRA to emit address calculations. `addm3` is used if `addptrm3` is not defined.

'`ssaddm3`', '`usaddm3`'
'`subm3`', '`sssubm3`', '`ussubm3`'
'`mulm3`', '`ssmulm3`', '`usmulm3`'
'`divm3`', '`ssdivm3`'
'`udivm3`', '`usdivm3`'
'`modm3`', '`umodm3`'
'`uminm3`', '`umaxm3`'
'`andm3`', '`iorm3`', '`xorm3`'
Similar, for other arithmetic operations.

'`fmam4`' Multiply operand 2 and operand 1, then add operand 3, storing the result in operand 0 without doing an intermediate rounding step. All operands must have mode *m*. This pattern is used to implement the `fma`, `fmaf`, and `fmal` builtin functions from the ISO C99 standard.

'`fmsm4`' Like `fmam4`, except operand 3 subtracted from the product instead of added to the product. This is represented in the rtl as

```
(fma:m op1 op2 (neg:m op3))
```

'`fnmam4`' Like `fmam4` except that the intermediate product is negated before being added to operand 3. This is represented in the rtl as

```
(fma:m (neg:m op1) op2 op3)
```

'`fnmsm4`' Like `fmsm4` except that the intermediate product is negated before subtracting operand 3. This is represented in the rtl as

```
(fma:m (neg:m op1) op2 (neg:m op3))
```

'`sminm3`', '`smaxm3`'
Signed minimum and maximum operations. When used with floating point, if both operands are zeros, or if either operand is `NaN`, then it is unspecified which of the two operands is returned as the result.

'`reduc_smin_m`', '`reduc_smax_m`'
Find the signed minimum/maximum of the elements of a vector. The vector is operand 1, and the scalar result is stored in the least significant bits of operand 0 (also a vector). The output and input vector should have the same modes.

'`reduc_umin_m`', '`reduc_umax_m`'
Find the unsigned minimum/maximum of the elements of a vector. The vector is operand 1, and the scalar result is stored in the least significant bits of operand 0 (also a vector). The output and input vector should have the same modes.

'`reduc_splus_m`'
Compute the sum of the signed elements of a vector. The vector is operand 1, and the scalar result is stored in the least significant bits of operand 0 (also a vector). The output and input vector should have the same modes.

'`reduc_uplus_m`'
Compute the sum of the unsigned elements of a vector. The vector is operand 1, and the scalar result is stored in the least significant bits of operand 0 (also a vector). The output and input vector should have the same modes.

'`sdot_prod`*m*'
'`udot_prod`*m*'
Compute the sum of the products of two signed/unsigned elements. Operand 1 and operand 2 are of the same mode. Their product, which is of a wider mode, is computed and added to operand 3. Operand 3 is of a mode equal or wider than the mode of the product. The result is placed in operand 0, which is of the same mode as operand 3.

'`ssum_widen`*m3*'
'`usum_widen`*m3*'
Operands 0 and 2 are of the same mode, which is wider than the mode of operand 1. Add operand 1 to operand 2 and place the widened result in operand 0. (This is used express accumulation of elements into an accumulator of a wider mode.)

'`vec_shl_`*m*', '`vec_shr_`*m*'
Whole vector left/right shift in bits. Operand 1 is a vector to be shifted. Operand 2 is an integer shift amount in bits. Operand 0 is where the resulting shifted vector is stored. The output and input vectors should have the same modes.

'`vec_pack_trunc_`*m*'
Narrow (demote) and merge the elements of two vectors. Operands 1 and 2 are vectors of the same mode having N integral or floating point elements of size S. Operand 0 is the resulting vector in which 2*N elements of size N/2 are concatenated after narrowing them down using truncation.

'`vec_pack_ssat_`*m*', '`vec_pack_usat_`*m*'
Narrow (demote) and merge the elements of two vectors. Operands 1 and 2 are vectors of the same mode having N integral elements of size S. Operand 0 is the resulting vector in which the elements of the two input vectors are concatenated after narrowing them down using signed/unsigned saturating arithmetic.

'`vec_pack_sfix_trunc_`*m*', '`vec_pack_ufix_trunc_`*m*'
Narrow, convert to signed/unsigned integral type and merge the elements of two vectors. Operands 1 and 2 are vectors of the same mode having N floating point elements of size S. Operand 0 is the resulting vector in which 2*N elements of size N/2 are concatenated.

'`vec_unpacks_hi_`*m*', '`vec_unpacks_lo_`*m*'
Extract and widen (promote) the high/low part of a vector of signed integral or floating point elements. The input vector (operand 1) has N elements of size S. Widen (promote) the high/low elements of the vector using signed or floating point extension and place the resulting N/2 values of size 2*S in the output vector (operand 0).

'`vec_unpacku_hi_`*m*', '`vec_unpacku_lo_`*m*'
Extract and widen (promote) the high/low part of a vector of unsigned integral elements. The input vector (operand 1) has N elements of size S. Widen (promote) the high/low elements of the vector using zero extension and place the resulting N/2 values of size 2*S in the output vector (operand 0).

'vec_unpacks_float_hi_*m*', 'vec_unpacks_float_lo_*m*'
'vec_unpacku_float_hi_*m*', 'vec_unpacku_float_lo_*m*'
Extract, convert to floating point type and widen the high/low part of a vector of signed/unsigned integral elements. The input vector (operand 1) has N elements of size S. Convert the high/low elements of the vector using floating point conversion and place the resulting N/2 values of size 2*S in the output vector (operand 0).

'vec_widen_umult_hi_*m*', 'vec_widen_umult_lo_*m*'
'vec_widen_smult_hi_*m*', 'vec_widen_smult_lo_*m*'
'vec_widen_umult_even_*m*', 'vec_widen_umult_odd_*m*'
'vec_widen_smult_even_*m*', 'vec_widen_smult_odd_*m*'
Signed/Unsigned widening multiplication. The two inputs (operands 1 and 2) are vectors with N signed/unsigned elements of size S. Multiply the high/low or even/odd elements of the two vectors, and put the N/2 products of size 2*S in the output vector (operand 0). A target shouldn't implement even/odd pattern pair if it is less efficient than lo/hi one.

'vec_widen_ushiftl_hi_*m*', 'vec_widen_ushiftl_lo_*m*'
'vec_widen_sshiftl_hi_*m*', 'vec_widen_sshiftl_lo_*m*'
Signed/Unsigned widening shift left. The first input (operand 1) is a vector with N signed/unsigned elements of size S. Operand 2 is a constant. Shift the high/low elements of operand 1, and put the N/2 results of size 2*S in the output vector (operand 0).

'mulhisi3'
Multiply operands 1 and 2, which have mode `HImode`, and store a `SImode` product in operand 0.

'mulqihi3', 'mulsidi3'
Similar widening-multiplication instructions of other widths.

'umulqihi3', 'umulhisi3', 'umulsidi3'
Similar widening-multiplication instructions that do unsigned multiplication.

'usmulqihi3', 'usmulhisi3', 'usmulsidi3'
Similar widening-multiplication instructions that interpret the first operand as unsigned and the second operand as signed, then do a signed multiplication.

'smul*m*3_highpart'
Perform a signed multiplication of operands 1 and 2, which have mode *m*, and store the most significant half of the product in operand 0. The least significant half of the product is discarded.

'umul*m*3_highpart'
Similar, but the multiplication is unsigned.

'madd*mn*4' Multiply operands 1 and 2, sign-extend them to mode *n*, add operand 3, and store the result in operand 0. Operands 1 and 2 have mode *m* and operands 0 and 3 have mode *n*. Both modes must be integer or fixed-point modes and *n* must be twice the size of *m*.

In other words, madd*mn*4 is like mul*mn*3 except that it also adds operand 3.

These instructions are not allowed to `FAIL`.

'`umadd`*mn*`4`'
Like `madd`*mn*`4`, but zero-extend the multiplication operands instead of sign-extending them.

'`ssmadd`*mn*`4`'
Like `madd`*mn*`4`, but all involved operations must be signed-saturating.

'`usmadd`*mn*`4`'
Like `umadd`*mn*`4`, but all involved operations must be unsigned-saturating.

'`msub`*mn*`4`' Multiply operands 1 and 2, sign-extend them to mode *n*, subtract the result from operand 3, and store the result in operand 0. Operands 1 and 2 have mode *m* and operands 0 and 3 have mode *n*. Both modes must be integer or fixed-point modes and *n* must be twice the size of *m*.

In other words, `msub`*mn*`4` is like `mul`*mn*`3` except that it also subtracts the result from operand 3.

These instructions are not allowed to `FAIL`.

'`umsub`*mn*`4`'
Like `msub`*mn*`4`, but zero-extend the multiplication operands instead of sign-extending them.

'`ssmsub`*mn*`4`'
Like `msub`*mn*`4`, but all involved operations must be signed-saturating.

'`usmsub`*mn*`4`'
Like `umsub`*mn*`4`, but all involved operations must be unsigned-saturating.

'`divmod`*m*`4`'
Signed division that produces both a quotient and a remainder. Operand 1 is divided by operand 2 to produce a quotient stored in operand 0 and a remainder stored in operand 3.

For machines with an instruction that produces both a quotient and a remainder, provide a pattern for '`divmod`*m*`4`' but do not provide patterns for '`div`*m*`3`' and '`mod`*m*`3`'. This allows optimization in the relatively common case when both the quotient and remainder are computed.

If an instruction that just produces a quotient or just a remainder exists and is more efficient than the instruction that produces both, write the output routine of '`divmod`*m*`4`' to call `find_reg_note` and look for a `REG_UNUSED` note on the quotient or remainder and generate the appropriate instruction.

'`udivmod`*m*`4`'
Similar, but does unsigned division.

'`ashl`*m*`3`', '`ssashl`*m*`3`', '`usashl`*m*`3`'
Arithmetic-shift operand 1 left by a number of bits specified by operand 2, and store the result in operand 0. Here *m* is the mode of operand 0 and operand 1; operand 2's mode is specified by the instruction pattern, and the compiler will

convert the operand to that mode before generating the instruction. The meaning of out-of-range shift counts can optionally be specified by `TARGET_SHIFT_TRUNCATION_MASK`. See [TARGET_SHIFT_TRUNCATION_MASK], page 575. Operand 2 is always a scalar type.

'`ashrm3`', '`lshrm3`', '`rotlm3`', '`rotrm3`'
Other shift and rotate instructions, analogous to the `ashlm3` instructions. Operand 2 is always a scalar type.

'`vashlm3`', '`vashrm3`', '`vlshrm3`', '`vrotlm3`', '`vrotrm3`'
Vector shift and rotate instructions that take vectors as operand 2 instead of a scalar type.

'`bswapm2`' Reverse the order of bytes of operand 1 and store the result in operand 0.

'`negm2`', '`ssnegm2`', '`usnegm2`'
Negate operand 1 and store the result in operand 0.

'`absm2`' Store the absolute value of operand 1 into operand 0.

'`sqrtm2`' Store the square root of operand 1 into operand 0.

The `sqrt` built-in function of C always uses the mode which corresponds to the C data type `double` and the `sqrtf` built-in function uses the mode which corresponds to the C data type `float`.

'`fmodm3`' Store the remainder of dividing operand 1 by operand 2 into operand 0, rounded towards zero to an integer.

The `fmod` built-in function of C always uses the mode which corresponds to the C data type `double` and the `fmodf` built-in function uses the mode which corresponds to the C data type `float`.

'`remainderm3`'
Store the remainder of dividing operand 1 by operand 2 into operand 0, rounded to the nearest integer.

The `remainder` built-in function of C always uses the mode which corresponds to the C data type `double` and the `remainderf` built-in function uses the mode which corresponds to the C data type `float`.

'`cosm2`' Store the cosine of operand 1 into operand 0.

The `cos` built-in function of C always uses the mode which corresponds to the C data type `double` and the `cosf` built-in function uses the mode which corresponds to the C data type `float`.

'`sinm2`' Store the sine of operand 1 into operand 0.

The `sin` built-in function of C always uses the mode which corresponds to the C data type `double` and the `sinf` built-in function uses the mode which corresponds to the C data type `float`.

'`sincosm3`'
Store the cosine of operand 2 into operand 0 and the sine of operand 2 into operand 1.

The `sin` and `cos` built-in functions of C always use the mode which corresponds to the C data type `double` and the `sinf` and `cosf` built-in function use the mode which corresponds to the C data type `float`. Targets that can calculate the sine and cosine simultaneously can implement this pattern as opposed to implementing individual `sin`*m*`2` and `cos`*m*`2` patterns. The `sin` and `cos` built-in functions will then be expanded to the `sincos`*m*`3` pattern, with one of the output values left unused.

'`exp`*m*`2`' Store the exponential of operand 1 into operand 0.

The `exp` built-in function of C always uses the mode which corresponds to the C data type `double` and the `expf` built-in function uses the mode which corresponds to the C data type `float`.

'`log`*m*`2`' Store the natural logarithm of operand 1 into operand 0.

The `log` built-in function of C always uses the mode which corresponds to the C data type `double` and the `logf` built-in function uses the mode which corresponds to the C data type `float`.

'`pow`*m*`3`' Store the value of operand 1 raised to the exponent operand 2 into operand 0.

The `pow` built-in function of C always uses the mode which corresponds to the C data type `double` and the `powf` built-in function uses the mode which corresponds to the C data type `float`.

'`atan2`*m*`3`' Store the arc tangent (inverse tangent) of operand 1 divided by operand 2 into operand 0, using the signs of both arguments to determine the quadrant of the result.

The `atan2` built-in function of C always uses the mode which corresponds to the C data type `double` and the `atan2f` built-in function uses the mode which corresponds to the C data type `float`.

'`floor`*m*`2`' Store the largest integral value not greater than argument.

The `floor` built-in function of C always uses the mode which corresponds to the C data type `double` and the `floorf` built-in function uses the mode which corresponds to the C data type `float`.

'`btrunc`*m*`2`'

Store the argument rounded to integer towards zero.

The `trunc` built-in function of C always uses the mode which corresponds to the C data type `double` and the `truncf` built-in function uses the mode which corresponds to the C data type `float`.

'`round`*m*`2`' Store the argument rounded to integer away from zero.

The `round` built-in function of C always uses the mode which corresponds to the C data type `double` and the `roundf` built-in function uses the mode which corresponds to the C data type `float`.

'`ceil`*m*`2`' Store the argument rounded to integer away from zero.

The `ceil` built-in function of C always uses the mode which corresponds to the C data type `double` and the `ceilf` built-in function uses the mode which corresponds to the C data type `float`.

'nearbyint*m*2'
: Store the argument rounded according to the default rounding mode

  The `nearbyint` built-in function of C always uses the mode which corresponds to the C data type `double` and the `nearbyintf` built-in function uses the mode which corresponds to the C data type `float`.

'rint*m*2'
: Store the argument rounded according to the default rounding mode and raise the inexact exception when the result differs in value from the argument

  The `rint` built-in function of C always uses the mode which corresponds to the C data type `double` and the `rintf` built-in function uses the mode which corresponds to the C data type `float`.

'lrint*mn*2'
: Convert operand 1 (valid for floating point mode *m*) to fixed point mode *n* as a signed number according to the current rounding mode and store in operand 0 (which has mode *n*).

'lround*mn*2'
: Convert operand 1 (valid for floating point mode *m*) to fixed point mode *n* as a signed number rounding to nearest and away from zero and store in operand 0 (which has mode *n*).

'lfloor*mn*2'
: Convert operand 1 (valid for floating point mode *m*) to fixed point mode *n* as a signed number rounding down and store in operand 0 (which has mode *n*).

'lceil*mn*2'
: Convert operand 1 (valid for floating point mode *m*) to fixed point mode *n* as a signed number rounding up and store in operand 0 (which has mode *n*).

'copysign*m*3'
: Store a value with the magnitude of operand 1 and the sign of operand 2 into operand 0.

  The `copysign` built-in function of C always uses the mode which corresponds to the C data type `double` and the `copysignf` built-in function uses the mode which corresponds to the C data type `float`.

'ffs*m*2'
: Store into operand 0 one plus the index of the least significant 1-bit of operand 1. If operand 1 is zero, store zero. *m* is the mode of operand 0; operand 1's mode is specified by the instruction pattern, and the compiler will convert the operand to that mode before generating the instruction.

  The `ffs` built-in function of C always uses the mode which corresponds to the C data type `int`.

'clz*m*2'
: Store into operand 0 the number of leading 0-bits in *x*, starting at the most significant bit position. If *x* is 0, the `CLZ_DEFINED_VALUE_AT_ZERO` (see Section 17.31 [Misc], page 573) macro defines if the result is undefined or has a useful value. *m* is the mode of operand 0; operand 1's mode is specified by the instruction pattern, and the compiler will convert the operand to that mode before generating the instruction.

'ctz*m*2' Store into operand 0 the number of trailing 0-bits in *x*, starting at the least significant bit position. If *x* is 0, the CTZ_DEFINED_VALUE_AT_ZERO (see Section 17.31 [Misc], page 573) macro defines if the result is undefined or has a useful value. *m* is the mode of operand 0; operand 1's mode is specified by the instruction pattern, and the compiler will convert the operand to that mode before generating the instruction.

'popcount*m*2'
Store into operand 0 the number of 1-bits in *x*. *m* is the mode of operand 0; operand 1's mode is specified by the instruction pattern, and the compiler will convert the operand to that mode before generating the instruction.

'parity*m*2'
Store into operand 0 the parity of *x*, i.e. the number of 1-bits in *x* modulo 2. *m* is the mode of operand 0; operand 1's mode is specified by the instruction pattern, and the compiler will convert the operand to that mode before generating the instruction.

'one_cmpl*m*2'
Store the bitwise-complement of operand 1 into operand 0.

'movmem*m*' Block move instruction. The destination and source blocks of memory are the first two operands, and both are mem:BLKs with an address in mode Pmode.

The number of bytes to move is the third operand, in mode *m*. Usually, you specify Pmode for *m*. However, if you can generate better code knowing the range of valid lengths is smaller than those representable in a full Pmode pointer, you should provide a pattern with a mode corresponding to the range of values you can handle efficiently (e.g., QImode for values in the range 0–127; note we avoid numbers that appear negative) and also a pattern with Pmode.

The fourth operand is the known shared alignment of the source and destination, in the form of a const_int rtx. Thus, if the compiler knows that both source and destination are word-aligned, it may provide the value 4 for this operand.

Optional operands 5 and 6 specify expected alignment and size of block respectively. The expected alignment differs from alignment in operand 4 in a way that the blocks are not required to be aligned according to it in all cases. This expected alignment is also in bytes, just like operand 4. Expected size, when unknown, is set to (const_int -1).

Descriptions of multiple movmem*m* patterns can only be beneficial if the patterns for smaller modes have fewer restrictions on their first, second and fourth operands. Note that the mode *m* in movmem*m* does not impose any restriction on the mode of individually moved data units in the block.

These patterns need not give special consideration to the possibility that the source and destination strings might overlap.

'movstr' String copy instruction, with stpcpy semantics. Operand 0 is an output operand in mode Pmode. The addresses of the destination and source strings are operands 1 and 2, and both are mem:BLKs with addresses in mode Pmode. The execution of the expansion of this pattern should store in operand 0 the address in which the NUL terminator was stored in the destination string.

This patern has also several optional operands that are same as in `setmem`.

'`setmem`*m*' Block set instruction. The destination string is the first operand, given as a `mem:BLK` whose address is in mode `Pmode`. The number of bytes to set is the second operand, in mode *m*. The value to initialize the memory with is the third operand. Targets that only support the clearing of memory should reject any value that is not the constant 0. See '`movmem`*m*' for a discussion of the choice of mode.

The fourth operand is the known alignment of the destination, in the form of a `const_int` rtx. Thus, if the compiler knows that the destination is word-aligned, it may provide the value 4 for this operand.

Optional operands 5 and 6 specify expected alignment and size of block respectively. The expected alignment differs from alignment in operand 4 in a way that the blocks are not required to be aligned according to it in all cases. This expected alignment is also in bytes, just like operand 4. Expected size, when unknown, is set to `(const_int -1)`. Operand 7 is the minimal size of the block and operand 8 is the maximal size of the block (NULL if it can not be represented as CONST_INT). Operand 9 is the probable maximal size (i.e. we can not rely on it for correctness, but it can be used for choosing proper code sequence for a given size).

The use for multiple `setmem`*m* is as for `movmem`*m*.

'`cmpstrn`*m*'

String compare instruction, with five operands. Operand 0 is the output; it has mode *m*. The remaining four operands are like the operands of '`movmem`*m*'. The two memory blocks specified are compared byte by byte in lexicographic order starting at the beginning of each string. The instruction is not allowed to prefetch more than one byte at a time since either string may end in the first byte and reading past that may access an invalid page or segment and cause a fault. The comparison terminates early if the fetched bytes are different or if they are equal to zero. The effect of the instruction is to store a value in operand 0 whose sign indicates the result of the comparison.

'`cmpstr`*m*' String compare instruction, without known maximum length. Operand 0 is the output; it has mode *m*. The second and third operand are the blocks of memory to be compared; both are `mem:BLK` with an address in mode `Pmode`.

The fourth operand is the known shared alignment of the source and destination, in the form of a `const_int` rtx. Thus, if the compiler knows that both source and destination are word-aligned, it may provide the value 4 for this operand.

The two memory blocks specified are compared byte by byte in lexicographic order starting at the beginning of each string. The instruction is not allowed to prefetch more than one byte at a time since either string may end in the first byte and reading past that may access an invalid page or segment and cause a fault. The comparison will terminate when the fetched bytes are different or if they are equal to zero. The effect of the instruction is to store a value in operand 0 whose sign indicates the result of the comparison.

'`cmpmem`*m*' Block compare instruction, with five operands like the operands of '`cmpstr`*m*'. The two memory blocks specified are compared byte by byte in lexicographic

order starting at the beginning of each block. Unlike '`cmpstrm`' the instruction can prefetch any bytes in the two memory blocks. Also unlike '`cmpstrm`' the comparison will not stop if both bytes are zero. The effect of the instruction is to store a value in operand 0 whose sign indicates the result of the comparison.

'`strlen`*m*' Compute the length of a string, with three operands. Operand 0 is the result (of mode *m*), operand 1 is a `mem` referring to the first character of the string, operand 2 is the character to search for (normally zero), and operand 3 is a constant describing the known alignment of the beginning of the string.

'`float`*mn*`2`'
Convert signed integer operand 1 (valid for fixed point mode *m*) to floating point mode *n* and store in operand 0 (which has mode *n*).

'`floatuns`*mn*`2`'
Convert unsigned integer operand 1 (valid for fixed point mode *m*) to floating point mode *n* and store in operand 0 (which has mode *n*).

'`fix`*mn*`2`' Convert operand 1 (valid for floating point mode *m*) to fixed point mode *n* as a signed number and store in operand 0 (which has mode *n*). This instruction's result is defined only when the value of operand 1 is an integer.

If the machine description defines this pattern, it also needs to define the `ftrunc` pattern.

'`fixuns`*mn*`2`'
Convert operand 1 (valid for floating point mode *m*) to fixed point mode *n* as an unsigned number and store in operand 0 (which has mode *n*). This instruction's result is defined only when the value of operand 1 is an integer.

'`ftrunc`*m*`2`'
Convert operand 1 (valid for floating point mode *m*) to an integer value, still represented in floating point mode *m*, and store it in operand 0 (valid for floating point mode *m*).

'`fix_trunc`*mn*`2`'
Like '`fix`*mn*`2`' but works for any floating point value of mode *m* by converting the value to an integer.

'`fixuns_trunc`*mn*`2`'
Like '`fixuns`*mn*`2`' but works for any floating point value of mode *m* by converting the value to an integer.

'`trunc`*mn*`2`'
Truncate operand 1 (valid for mode *m*) to mode *n* and store in operand 0 (which has mode *n*). Both modes must be fixed point or both floating point.

'`extend`*mn*`2`'
Sign-extend operand 1 (valid for mode *m*) to mode *n* and store in operand 0 (which has mode *n*). Both modes must be fixed point or both floating point.

'`zero_extend`*mn*`2`'
Zero-extend operand 1 (valid for mode *m*) to mode *n* and store in operand 0 (which has mode *n*). Both modes must be fixed point.

'fract*mn*2'
: Convert operand 1 of mode *m* to mode *n* and store in operand 0 (which has mode *n*). Mode *m* and mode *n* could be fixed-point to fixed-point, signed integer to fixed-point, fixed-point to signed integer, floating-point to fixed-point, or fixed-point to floating-point. When overflows or underflows happen, the results are undefined.

'satfract*mn*2'
: Convert operand 1 of mode *m* to mode *n* and store in operand 0 (which has mode *n*). Mode *m* and mode *n* could be fixed-point to fixed-point, signed integer to fixed-point, or floating-point to fixed-point. When overflows or underflows happen, the instruction saturates the results to the maximum or the minimum.

'fractuns*mn*2'
: Convert operand 1 of mode *m* to mode *n* and store in operand 0 (which has mode *n*). Mode *m* and mode *n* could be unsigned integer to fixed-point, or fixed-point to unsigned integer. When overflows or underflows happen, the results are undefined.

'satfractuns*mn*2'
: Convert unsigned integer operand 1 of mode *m* to fixed-point mode *n* and store in operand 0 (which has mode *n*). When overflows or underflows happen, the instruction saturates the results to the maximum or the minimum.

'extv*m*'
: Extract a bit-field from register operand 1, sign-extend it, and store it in operand 0. Operand 2 specifies the width of the field in bits and operand 3 the starting bit, which counts from the most significant bit if 'BITS_BIG_ENDIAN' is true and from the least significant bit otherwise.

  Operands 0 and 1 both have mode *m*. Operands 2 and 3 have a target-specific mode.

'extvmisalign*m*'
: Extract a bit-field from memory operand 1, sign extend it, and store it in operand 0. Operand 2 specifies the width in bits and operand 3 the starting bit. The starting bit is always somewhere in the first byte of operand 1; it counts from the most significant bit if 'BITS_BIG_ENDIAN' is true and from the least significant bit otherwise.

  Operand 0 has mode *m* while operand 1 has BLK mode. Operands 2 and 3 have a target-specific mode.

  The instruction must not read beyond the last byte of the bit-field.

'extzv*m*'
: Like 'extv*m*' except that the bit-field value is zero-extended.

'extzvmisalign*m*'
: Like 'extvmisalign*m*' except that the bit-field value is zero-extended.

'insv*m*'
: Insert operand 3 into a bit-field of register operand 0. Operand 1 specifies the width of the field in bits and operand 2 the starting bit, which counts from the most significant bit if 'BITS_BIG_ENDIAN' is true and from the least significant bit otherwise.

Operands 0 and 3 both have mode *m*. Operands 1 and 2 have a target-specific mode.

'`insvmisalignm`'
Insert operand 3 into a bit-field of memory operand 0. Operand 1 specifies the width of the field in bits and operand 2 the starting bit. The starting bit is always somewhere in the first byte of operand 0; it counts from the most significant bit if '`BITS_BIG_ENDIAN`' is true and from the least significant bit otherwise.

Operand 3 has mode *m* while operand 0 has `BLK` mode. Operands 1 and 2 have a target-specific mode.

The instruction must not read or write beyond the last byte of the bit-field.

'`extv`' Extract a bit-field from operand 1 (a register or memory operand), where operand 2 specifies the width in bits and operand 3 the starting bit, and store it in operand 0. Operand 0 must have mode `word_mode`. Operand 1 may have mode `byte_mode` or `word_mode`; often `word_mode` is allowed only for registers. Operands 2 and 3 must be valid for `word_mode`.

The RTL generation pass generates this instruction only with constants for operands 2 and 3 and the constant is never zero for operand 2.

The bit-field value is sign-extended to a full word integer before it is stored in operand 0.

This pattern is deprecated; please use '`extvm`' and `extvmisalignm` instead.

'`extzv`' Like '`extv`' except that the bit-field value is zero-extended.

This pattern is deprecated; please use '`extzvm`' and `extzvmisalignm` instead.

'`insv`' Store operand 3 (which must be valid for `word_mode`) into a bit-field in operand 0, where operand 1 specifies the width in bits and operand 2 the starting bit. Operand 0 may have mode `byte_mode` or `word_mode`; often `word_mode` is allowed only for registers. Operands 1 and 2 must be valid for `word_mode`.

The RTL generation pass generates this instruction only with constants for operands 1 and 2 and the constant is never zero for operand 1.

This pattern is deprecated; please use '`insvm`' and `insvmisalignm` instead.

'`mov`*`modecc`*'
Conditionally move operand 2 or operand 3 into operand 0 according to the comparison in operand 1. If the comparison is true, operand 2 is moved into operand 0, otherwise operand 3 is moved.

The mode of the operands being compared need not be the same as the operands being moved. Some machines, sparc64 for example, have instructions that conditionally move an integer value based on the floating point condition codes and vice versa.

If the machine does not have conditional move instructions, do not define these patterns.

'`add`*`modecc`*'
Similar to '`mov`*`modecc`*' but for conditional addition. Conditionally move operand 2 or (operands 2 `+` operand 3) into operand 0 according to the

comparison in operand 1. If the comparison is false, operand 2 is moved into operand 0, otherwise (operand 2 + operand 3) is moved.

'cstore*mode*4'

Store zero or nonzero in operand 0 according to whether a comparison is true. Operand 1 is a comparison operator. Operand 2 and operand 3 are the first and second operand of the comparison, respectively. You specify the mode that operand 0 must have when you write the `match_operand` expression. The compiler automatically sees which mode you have used and supplies an operand of that mode.

The value stored for a true condition must have 1 as its low bit, or else must be negative. Otherwise the instruction is not suitable and you should omit it from the machine description. You describe to the compiler exactly which value is stored by defining the macro `STORE_FLAG_VALUE` (see Section 17.31 [Misc], page 573). If a description cannot be found that can be used for all the possible comparison operators, you should pick one and use a `define_expand` to map all results onto the one you chose.

These operations may `FAIL`, but should do so only in relatively uncommon cases; if they would `FAIL` for common cases involving integer comparisons, it is best to restrict the predicates to not allow these operands. Likewise if a given comparison operator will always fail, independent of the operands (for floating-point modes, the `ordered_comparison_operator` predicate is often useful in this case).

If this pattern is omitted, the compiler will generate a conditional branch—for example, it may copy a constant one to the target and branching around an assignment of zero to the target—or a libcall. If the predicate for operand 1 only rejects some operators, it will also try reordering the operands and/or inverting the result value (e.g. by an exclusive OR). These possibilities could be cheaper or equivalent to the instructions used for the 'cstore*mode*4' pattern followed by those required to convert a positive result from `STORE_FLAG_VALUE` to 1; in this case, you can and should make operand 1's predicate reject some operators in the 'cstore*mode*4' pattern, or remove the pattern altogether from the machine description.

'cbranch*mode*4'

Conditional branch instruction combined with a compare instruction. Operand 0 is a comparison operator. Operand 1 and operand 2 are the first and second operands of the comparison, respectively. Operand 3 is a `label_ref` that refers to the label to jump to.

'jump' A jump inside a function; an unconditional branch. Operand 0 is the `label_ref` of the label to jump to. This pattern name is mandatory on all machines.

'call' Subroutine call instruction returning no value. Operand 0 is the function to call; operand 1 is the number of bytes of arguments pushed as a `const_int`; operand 2 is the number of registers used as operands.

On most machines, operand 2 is not actually stored into the RTL pattern. It is supplied for the sake of some RISC machines which need to put this information into the assembler code; they can put it in the RTL instead of operand 1.

Operand 0 should be a `mem` RTX whose address is the address of the function. Note, however, that this address can be a `symbol_ref` expression even if it would not be a legitimate memory address on the target machine. If it is also not a valid argument for a call instruction, the pattern for this operation should be a `define_expand` (see Section 16.15 [Expander Definitions], page 383) that places the address into a register and uses that register in the call instruction.

'`call_value`'
Subroutine call instruction returning a value. Operand 0 is the hard register in which the value is returned. There are three more operands, the same as the three operands of the '`call`' instruction (but with numbers increased by one).

Subroutines that return `BLKmode` objects use the '`call`' insn.

'`call_pop`', '`call_value_pop`'
Similar to '`call`' and '`call_value`', except used if defined and if `RETURN_POPS_ARGS` is nonzero. They should emit a `parallel` that contains both the function call and a `set` to indicate the adjustment made to the frame pointer.

For machines where `RETURN_POPS_ARGS` can be nonzero, the use of these patterns increases the number of functions for which the frame pointer can be eliminated, if desired.

'`untyped_call`'
Subroutine call instruction returning a value of any type. Operand 0 is the function to call; operand 1 is a memory location where the result of calling the function is to be stored; operand 2 is a `parallel` expression where each element is a `set` expression that indicates the saving of a function return value into the result block.

This instruction pattern should be defined to support `__builtin_apply` on machines where special instructions are needed to call a subroutine with arbitrary arguments or to save the value returned. This instruction pattern is required on machines that have multiple registers that can hold a return value (i.e. `FUNCTION_VALUE_REGNO_P` is true for more than one register).

'`return`' Subroutine return instruction. This instruction pattern name should be defined only if a single instruction can do all the work of returning from a function.

Like the '`movm`' patterns, this pattern is also used after the RTL generation phase. In this case it is to support machines where multiple instructions are usually needed to return from a function, but some class of functions only requires one instruction to implement a return. Normally, the applicable functions are those which do not need to save any registers or allocate stack space.

It is valid for this pattern to expand to an instruction using `simple_return` if no epilogue is required.

'`simple_return`'
Subroutine return instruction. This instruction pattern name should be defined only if a single instruction can do all the work of returning from a function on a path where no epilogue is required. This pattern is very similar to the `return` instruction pattern, but it is emitted only by the shrink-wrapping optimization on paths where the function prologue has not been executed, and a function

return should occur without any of the effects of the epilogue. Additional uses may be introduced on paths where both the prologue and the epilogue have executed.

For such machines, the condition specified in this pattern should only be true when `reload_completed` is nonzero and the function's epilogue would only be a single instruction. For machines with register windows, the routine `leaf_function_p` may be used to determine if a register window push is required.

Machines that have conditional return instructions should define patterns such as

```
(define_insn ""
  [(set (pc)
        (if_then_else (match_operator
                          0 "comparison_operator"
                          [(cc0) (const_int 0)])
                      (return)
                      (pc)))]
  "condition"
  "...")
```

where *condition* would normally be the same condition specified on the named '`return`' pattern.

'`untyped_return`'
: Untyped subroutine return instruction. This instruction pattern should be defined to support `__builtin_return` on machines where special instructions are needed to return a value of any type.

  Operand 0 is a memory location where the result of calling a function with `__builtin_apply` is stored; operand 1 is a `parallel` expression where each element is a `set` expression that indicates the restoring of a function return value from the result block.

'`nop`'
: No-op instruction. This instruction pattern name should always be defined to output a no-op in assembler code. `(const_int 0)` will do as an RTL pattern.

'`indirect_jump`'
: An instruction to jump to an address which is operand zero. This pattern name is mandatory on all machines.

'`casesi`'
: Instruction to jump through a dispatch table, including bounds checking. This instruction takes five operands:

  1. The index to dispatch on, which has mode `SImode`.
  2. The lower bound for indices in the table, an integer constant.
  3. The total range of indices in the table—the largest index minus the smallest one (both inclusive).
  4. A label that precedes the table itself.
  5. A label to jump to if the index has a value outside the bounds.

  The table is an `addr_vec` or `addr_diff_vec` inside of a `jump_table_data`. The number of elements in the table is one plus the difference between the upper bound and the lower bound.

'`tablejump`'

Instruction to jump to a variable address. This is a low-level capability which can be used to implement a dispatch table when there is no '`casesi`' pattern.

This pattern requires two operands: the address or offset, and a label which should immediately precede the jump table. If the macro `CASE_VECTOR_PC_RELATIVE` evaluates to a nonzero value then the first operand is an offset which counts from the address of the table; otherwise, it is an absolute address to jump to. In either case, the first operand has mode `Pmode`.

The '`tablejump`' insn is always the last insn before the jump table it uses. Its assembler code normally has no need to use the second operand, but you should incorporate it in the RTL pattern so that the jump optimizer will not delete the table as unreachable code.

'`decrement_and_branch_until_zero`'

Conditional branch instruction that decrements a register and jumps if the register is nonzero. Operand 0 is the register to decrement and test; operand 1 is the label to jump to if the register is nonzero. See Section 16.13 [Looping Patterns], page 380.

This optional instruction pattern is only used by the combiner, typically for loops reversed by the loop optimizer when strength reduction is enabled.

'`doloop_end`'

Conditional branch instruction that decrements a register and jumps if the register is nonzero. Operand 0 is the register to decrement and test; operand 1 is the label to jump to if the register is nonzero. See Section 16.13 [Looping Patterns], page 380.

This optional instruction pattern should be defined for machines with low-overhead looping instructions as the loop optimizer will try to modify suitable loops to utilize it. The target hook `TARGET_CAN_USE_DOLOOP_P` controls the conditions under which low-overhead loops can be used.

'`doloop_begin`'

Companion instruction to `doloop_end` required for machines that need to perform some initialization, such as loading a special counter register. Operand 1 is the associated `doloop_end` pattern and operand 0 is the register that it decrements.

If initialization insns do not always need to be emitted, use a `define_expand` (see Section 16.15 [Expander Definitions], page 383) and make it fail.

'`canonicalize_funcptr_for_compare`'

Canonicalize the function pointer in operand 1 and store the result into operand 0.

Operand 0 is always a `reg` and has mode `Pmode`; operand 1 may be a `reg`, `mem`, `symbol_ref`, `const_int`, etc and also has mode `Pmode`.

Canonicalization of a function pointer usually involves computing the address of the function which would be called if the function pointer were used in an indirect call.

Only define this pattern if function pointers on the target machine can have different values but still call the same function when used in an indirect call.

'save_stack_block'
'save_stack_function'
'save_stack_nonlocal'
'restore_stack_block'
'restore_stack_function'
'restore_stack_nonlocal'

Most machines save and restore the stack pointer by copying it to or from an object of mode Pmode. Do not define these patterns on such machines.

Some machines require special handling for stack pointer saves and restores. On those machines, define the patterns corresponding to the non-standard cases by using a define_expand (see Section 16.15 [Expander Definitions], page 383) that produces the required insns. The three types of saves and restores are:

1. 'save_stack_block' saves the stack pointer at the start of a block that allocates a variable-sized object, and 'restore_stack_block' restores the stack pointer when the block is exited.
2. 'save_stack_function' and 'restore_stack_function' do a similar job for the outermost block of a function and are used when the function allocates variable-sized objects or calls alloca. Only the epilogue uses the restored stack pointer, allowing a simpler save or restore sequence on some machines.
3. 'save_stack_nonlocal' is used in functions that contain labels branched to by nested functions. It saves the stack pointer in such a way that the inner function can use 'restore_stack_nonlocal' to restore the stack pointer. The compiler generates code to restore the frame and argument pointer registers, but some machines require saving and restoring additional data such as register window information or stack backchains. Place insns in these patterns to save and restore any such required data.

When saving the stack pointer, operand 0 is the save area and operand 1 is the stack pointer. The mode used to allocate the save area defaults to Pmode but you can override that choice by defining the STACK_SAVEAREA_MODE macro (see Section 17.5 [Storage Layout], page 432). You must specify an integral mode, or VOIDmode if no save area is needed for a particular type of save (either because no save is needed or because a machine-specific save area can be used). Operand 0 is the stack pointer and operand 1 is the save area for restore operations. If 'save_stack_block' is defined, operand 0 must not be VOIDmode since these saves can be arbitrarily nested.

A save area is a mem that is at a constant offset from virtual_stack_vars_rtx when the stack pointer is saved for use by nonlocal gotos and a reg in the other two cases.

'allocate_stack'

Subtract (or add if STACK_GROWS_DOWNWARD is undefined) operand 1 from the stack pointer to create space for dynamically allocated data.

Store the resultant pointer to this space into operand 0. If you are allocating space from the main stack, do this by emitting a move insn to copy `virtual_stack_dynamic_rtx` to operand 0. If you are allocating the space elsewhere, generate code to copy the location of the space to operand 0. In the latter case, you must ensure this space gets freed when the corresponding space on the main stack is free.

Do not define this pattern if all that must be done is the subtraction. Some machines require other operations such as stack probes or maintaining the back chain. Define this pattern to emit those operations in addition to updating the stack pointer.

'`check_stack`'
If stack checking (see Section 17.10.3 [Stack Checking], page 471) cannot be done on your system by probing the stack, define this pattern to perform the needed check and signal an error if the stack has overflowed. The single operand is the address in the stack farthest from the current stack pointer that you need to validate. Normally, on platforms where this pattern is needed, you would obtain the stack limit from a global or thread-specific variable or register.

'`probe_stack_address`'
If stack checking (see Section 17.10.3 [Stack Checking], page 471) can be done on your system by probing the stack but without the need to actually access it, define this pattern and signal an error if the stack has overflowed. The single operand is the memory address in the stack that needs to be probed.

'`probe_stack`'
If stack checking (see Section 17.10.3 [Stack Checking], page 471) can be done on your system by probing the stack but doing it with a "store zero" instruction is not valid or optimal, define this pattern to do the probing differently and signal an error if the stack has overflowed. The single operand is the memory reference in the stack that needs to be probed.

'`nonlocal_goto`'
Emit code to generate a non-local goto, e.g., a jump from one function to a label in an outer function. This pattern has four arguments, each representing a value to be used in the jump. The first argument is to be loaded into the frame pointer, the second is the address to branch to (code to dispatch to the actual label), the third is the address of a location where the stack is saved, and the last is the address of the label, to be placed in the location for the incoming static chain.

On most machines you need not define this pattern, since GCC will already generate the correct code, which is to load the frame pointer and static chain, restore the stack (using the '`restore_stack_nonlocal`' pattern, if defined), and jump indirectly to the dispatcher. You need only define this pattern if this code will not work on your machine.

'`nonlocal_goto_receiver`'
This pattern, if defined, contains code needed at the target of a nonlocal goto after the code already generated by GCC. You will not normally need to define

this pattern. A typical reason why you might need this pattern is if some value, such as a pointer to a global table, must be restored when the frame pointer is restored. Note that a nonlocal goto only occurs within a unit-of-translation, so a global table pointer that is shared by all functions of a given module need not be restored. There are no arguments.

'`exception_receiver`'
This pattern, if defined, contains code needed at the site of an exception handler that isn't needed at the site of a nonlocal goto. You will not normally need to define this pattern. A typical reason why you might need this pattern is if some value, such as a pointer to a global table, must be restored after control flow is branched to the handler of an exception. There are no arguments.

'`builtin_setjmp_setup`'
This pattern, if defined, contains additional code needed to initialize the `jmp_buf`. You will not normally need to define this pattern. A typical reason why you might need this pattern is if some value, such as a pointer to a global table, must be restored. Though it is preferred that the pointer value be recalculated if possible (given the address of a label for instance). The single argument is a pointer to the `jmp_buf`. Note that the buffer is five words long and that the first three are normally used by the generic mechanism.

'`builtin_setjmp_receiver`'
This pattern, if defined, contains code needed at the site of a built-in setjmp that isn't needed at the site of a nonlocal goto. You will not normally need to define this pattern. A typical reason why you might need this pattern is if some value, such as a pointer to a global table, must be restored. It takes one argument, which is the label to which builtin_longjmp transferred control; this pattern may be emitted at a small offset from that label.

'`builtin_longjmp`'
This pattern, if defined, performs the entire action of the longjmp. You will not normally need to define this pattern unless you also define `builtin_setjmp_setup`. The single argument is a pointer to the `jmp_buf`.

'`eh_return`'
This pattern, if defined, affects the way `__builtin_eh_return`, and thence the call frame exception handling library routines, are built. It is intended to handle non-trivial actions needed along the abnormal return path.

The address of the exception handler to which the function should return is passed as operand to this pattern. It will normally need to copied by the pattern to some special register or memory location. If the pattern needs to determine the location of the target call frame in order to do so, it may use `EH_RETURN_STACKADJ_RTX`, if defined; it will have already been assigned.

If this pattern is not defined, the default action will be to simply copy the return address to `EH_RETURN_HANDLER_RTX`. Either that macro or this pattern needs to be defined if call frame exception handling is to be used.

'prologue'

This pattern, if defined, emits RTL for entry to a function. The function entry is responsible for setting up the stack frame, initializing the frame pointer register, saving callee saved registers, etc.

Using a prologue pattern is generally preferred over defining TARGET_ASM_FUNCTION_PROLOGUE to emit assembly code for the prologue.

The prologue pattern is particularly useful for targets which perform instruction scheduling.

'window_save'

This pattern, if defined, emits RTL for a register window save. It should be defined if the target machine has register windows but the window events are decoupled from calls to subroutines. The canonical example is the SPARC architecture.

'epilogue'

This pattern emits RTL for exit from a function. The function exit is responsible for deallocating the stack frame, restoring callee saved registers and emitting the return instruction.

Using an epilogue pattern is generally preferred over defining TARGET_ASM_FUNCTION_EPILOGUE to emit assembly code for the epilogue.

The epilogue pattern is particularly useful for targets which perform instruction scheduling or which have delay slots for their return instruction.

'sibcall_epilogue'

This pattern, if defined, emits RTL for exit from a function without the final branch back to the calling function. This pattern will be emitted before any sibling call (aka tail call) sites.

The sibcall_epilogue pattern must not clobber any arguments used for parameter passing or any stack slots for arguments passed to the current function.

'trap' This pattern, if defined, signals an error, typically by causing some kind of signal to be raised. Among other places, it is used by the Java front end to signal 'invalid array index' exceptions.

'ctrap*MM*4'

Conditional trap instruction. Operand 0 is a piece of RTL which performs a comparison, and operands 1 and 2 are the arms of the comparison. Operand 3 is the trap code, an integer.

A typical ctrap pattern looks like

```
(define_insn "ctrapsi4"
  [(trap_if (match_operator 0 "trap_operator"
             [(match_operand 1 "register_operand")
              (match_operand 2 "immediate_operand")])
            (match_operand 3 "const_int_operand" "i"))]
  ""
  "...")
```

'prefetch'

This pattern, if defined, emits code for a non-faulting data prefetch instruction. Operand 0 is the address of the memory to prefetch. Operand 1 is a constant

1 if the prefetch is preparing for a write to the memory address, or a constant 0 otherwise. Operand 2 is the expected degree of temporal locality of the data and is a value between 0 and 3, inclusive; 0 means that the data has no temporal locality, so it need not be left in the cache after the access; 3 means that the data has a high degree of temporal locality and should be left in all levels of cache possible; 1 and 2 mean, respectively, a low or moderate degree of temporal locality.

Targets that do not support write prefetches or locality hints can ignore the values of operands 1 and 2.

'`blockage`'

This pattern defines a pseudo insn that prevents the instruction scheduler and other passes from moving instructions and using register equivalences across the boundary defined by the blockage insn. This needs to be an UNSPEC_VOLATILE pattern or a volatile ASM.

'`memory_barrier`'

If the target memory model is not fully synchronous, then this pattern should be defined to an instruction that orders both loads and stores before the instruction with respect to loads and stores after the instruction. This pattern has no operands.

'`sync_compare_and_swap`*mode*'

This pattern, if defined, emits code for an atomic compare-and-swap operation. Operand 1 is the memory on which the atomic operation is performed. Operand 2 is the "old" value to be compared against the current contents of the memory location. Operand 3 is the "new" value to store in the memory if the compare succeeds. Operand 0 is the result of the operation; it should contain the contents of the memory before the operation. If the compare succeeds, this should obviously be a copy of operand 2.

This pattern must show that both operand 0 and operand 1 are modified.

This pattern must issue any memory barrier instructions such that all memory operations before the atomic operation occur before the atomic operation and all memory operations after the atomic operation occur after the atomic operation.

For targets where the success or failure of the compare-and-swap operation is available via the status flags, it is possible to avoid a separate compare operation and issue the subsequent branch or store-flag operation immediately after the compare-and-swap. To this end, GCC will look for a `MODE_CC` set in the output of `sync_compare_and_swap`*mode*; if the machine description includes such a set, the target should also define special `cbranchcc4` and/or `cstorecc4` instructions. GCC will then be able to take the destination of the `MODE_CC` set and pass it to the `cbranchcc4` or `cstorecc4` pattern as the first operand of the comparison (the second will be `(const_int 0)`).

For targets where the operating system may provide support for this operation via library calls, the `sync_compare_and_swap_optab` may be initialized to a function with the same interface as the `__sync_val_compare_and_swap_`*n* built-in. If the entire set of *__sync* builtins are supported via library calls, the target can initialize all of the optabs at once with `init_sync_libfuncs`. For

the purposes of C++11 `std::atomic::is_lock_free`, it is assumed that these library calls do *not* use any kind of interruptable locking.

'`sync_add`*mode*', '`sync_sub`*mode*'
'`sync_ior`*mode*', '`sync_and`*mode*'
'`sync_xor`*mode*', '`sync_nand`*mode*'

These patterns emit code for an atomic operation on memory. Operand 0 is the memory on which the atomic operation is performed. Operand 1 is the second operand to the binary operator.

This pattern must issue any memory barrier instructions such that all memory operations before the atomic operation occur before the atomic operation and all memory operations after the atomic operation occur after the atomic operation.

If these patterns are not defined, the operation will be constructed from a compare-and-swap operation, if defined.

'`sync_old_add`*mode*', '`sync_old_sub`*mode*'
'`sync_old_ior`*mode*', '`sync_old_and`*mode*'
'`sync_old_xor`*mode*', '`sync_old_nand`*mode*'

These patterns emit code for an atomic operation on memory, and return the value that the memory contained before the operation. Operand 0 is the result value, operand 1 is the memory on which the atomic operation is performed, and operand 2 is the second operand to the binary operator.

This pattern must issue any memory barrier instructions such that all memory operations before the atomic operation occur before the atomic operation and all memory operations after the atomic operation occur after the atomic operation.

If these patterns are not defined, the operation will be constructed from a compare-and-swap operation, if defined.

'`sync_new_add`*mode*', '`sync_new_sub`*mode*'
'`sync_new_ior`*mode*', '`sync_new_and`*mode*'
'`sync_new_xor`*mode*', '`sync_new_nand`*mode*'

These patterns are like their `sync_old_`*op* counterparts, except that they return the value that exists in the memory location after the operation, rather than before the operation.

'`sync_lock_test_and_set`*mode*'

This pattern takes two forms, based on the capabilities of the target. In either case, operand 0 is the result of the operand, operand 1 is the memory on which the atomic operation is performed, and operand 2 is the value to set in the lock.

In the ideal case, this operation is an atomic exchange operation, in which the previous value in memory operand is copied into the result operand, and the value operand is stored in the memory operand.

For less capable targets, any value operand that is not the constant 1 should be rejected with `FAIL`. In this case the target may use an atomic test-and-set bit operation. The result operand should contain 1 if the bit was previously set and 0 if the bit was previously clear. The true contents of the memory operand are implementation defined.

This pattern must issue any memory barrier instructions such that the pattern as a whole acts as an acquire barrier, that is all memory operations after the pattern do not occur until the lock is acquired.

If this pattern is not defined, the operation will be constructed from a compare-and-swap operation, if defined.

'`sync_lock_release`*mode*'

This pattern, if defined, releases a lock set by `sync_lock_test_and_set`*mode*. Operand 0 is the memory that contains the lock; operand 1 is the value to store in the lock.

If the target doesn't implement full semantics for `sync_lock_test_and_set`*mode*, any value operand which is not the constant 0 should be rejected with `FAIL`, and the true contents of the memory operand are implementation defined.

This pattern must issue any memory barrier instructions such that the pattern as a whole acts as a release barrier, that is the lock is released only after all previous memory operations have completed.

If this pattern is not defined, then a `memory_barrier` pattern will be emitted, followed by a store of the value to the memory operand.

'`atomic_compare_and_swap`*mode*'

This pattern, if defined, emits code for an atomic compare-and-swap operation with memory model semantics. Operand 2 is the memory on which the atomic operation is performed. Operand 0 is an output operand which is set to true or false based on whether the operation succeeded. Operand 1 is an output operand which is set to the contents of the memory before the operation was attempted. Operand 3 is the value that is expected to be in memory. Operand 4 is the value to put in memory if the expected value is found there. Operand 5 is set to 1 if this compare and swap is to be treated as a weak operation. Operand 6 is the memory model to be used if the operation is a success. Operand 7 is the memory model to be used if the operation fails.

If memory referred to in operand 2 contains the value in operand 3, then operand 4 is stored in memory pointed to by operand 2 and fencing based on the memory model in operand 6 is issued.

If memory referred to in operand 2 does not contain the value in operand 3, then fencing based on the memory model in operand 7 is issued.

If a target does not support weak compare-and-swap operations, or the port elects not to implement weak operations, the argument in operand 5 can be ignored. Note a strong implementation must be provided.

If this pattern is not provided, the `__atomic_compare_exchange` built-in functions will utilize the legacy `sync_compare_and_swap` pattern with an `__ATOMIC_SEQ_CST` memory model.

'`atomic_load`*mode*'

This pattern implements an atomic load operation with memory model semantics. Operand 1 is the memory address being loaded from. Operand 0 is the

result of the load. Operand 2 is the memory model to be used for the load operation.

If not present, the `__atomic_load` built-in function will either resort to a normal load with memory barriers, or a compare-and-swap operation if a normal load would not be atomic.

'`atomic_store`*mode*'

This pattern implements an atomic store operation with memory model semantics. Operand 0 is the memory address being stored to. Operand 1 is the value to be written. Operand 2 is the memory model to be used for the operation.

If not present, the `__atomic_store` built-in function will attempt to perform a normal store and surround it with any required memory fences. If the store would not be atomic, then an `__atomic_exchange` is attempted with the result being ignored.

'`atomic_exchange`*mode*'

This pattern implements an atomic exchange operation with memory model semantics. Operand 1 is the memory location the operation is performed on. Operand 0 is an output operand which is set to the original value contained in the memory pointed to by operand 1. Operand 2 is the value to be stored. Operand 3 is the memory model to be used.

If this pattern is not present, the built-in function `__atomic_exchange` will attempt to preform the operation with a compare and swap loop.

'`atomic_add`*mode*', '`atomic_sub`*mode*'
'`atomic_or`*mode*', '`atomic_and`*mode*'
'`atomic_xor`*mode*', '`atomic_nand`*mode*'

These patterns emit code for an atomic operation on memory with memory model semantics. Operand 0 is the memory on which the atomic operation is performed. Operand 1 is the second operand to the binary operator. Operand 2 is the memory model to be used by the operation.

If these patterns are not defined, attempts will be made to use legacy `sync` patterns, or equivalent patterns which return a result. If none of these are available a compare-and-swap loop will be used.

'`atomic_fetch_add`*mode*', '`atomic_fetch_sub`*mode*'
'`atomic_fetch_or`*mode*', '`atomic_fetch_and`*mode*'
'`atomic_fetch_xor`*mode*', '`atomic_fetch_nand`*mode*'

These patterns emit code for an atomic operation on memory with memory model semantics, and return the original value. Operand 0 is an output operand which contains the value of the memory location before the operation was performed. Operand 1 is the memory on which the atomic operation is performed. Operand 2 is the second operand to the binary operator. Operand 3 is the memory model to be used by the operation.

If these patterns are not defined, attempts will be made to use legacy `sync` patterns. If none of these are available a compare-and-swap loop will be used.

'atomic_add_fetch*mode*', 'atomic_sub_fetch*mode*'
'atomic_or_fetch*mode*', 'atomic_and_fetch*mode*'
'atomic_xor_fetch*mode*', 'atomic_nand_fetch*mode*'

These patterns emit code for an atomic operation on memory with memory model semantics and return the result after the operation is performed. Operand 0 is an output operand which contains the value after the operation. Operand 1 is the memory on which the atomic operation is performed. Operand 2 is the second operand to the binary operator. Operand 3 is the memory model to be used by the operation.

If these patterns are not defined, attempts will be made to use legacy `sync` patterns, or equivalent patterns which return the result before the operation followed by the arithmetic operation required to produce the result. If none of these are available a compare-and-swap loop will be used.

'atomic_test_and_set'

This pattern emits code for `__builtin_atomic_test_and_set`. Operand 0 is an output operand which is set to true if the previous previous contents of the byte was "set", and false otherwise. Operand 1 is the `QImode` memory to be modified. Operand 2 is the memory model to be used.

The specific value that defines "set" is implementation defined, and is normally based on what is performed by the native atomic test and set instruction.

'mem_thread_fence*mode*'

This pattern emits code required to implement a thread fence with memory model semantics. Operand 0 is the memory model to be used.

If this pattern is not specified, all memory models except `__ATOMIC_RELAXED` will result in issuing a `sync_synchronize` barrier pattern.

'mem_signal_fence*mode*'

This pattern emits code required to implement a signal fence with memory model semantics. Operand 0 is the memory model to be used.

This pattern should impact the compiler optimizers the same way that mem_signal_fence does, but it does not need to issue any barrier instructions.

If this pattern is not specified, all memory models except `__ATOMIC_RELAXED` will result in issuing a `sync_synchronize` barrier pattern.

'get_thread_pointer*mode*'
'set_thread_pointer*mode*'

These patterns emit code that reads/sets the TLS thread pointer. Currently, these are only needed if the target needs to support the `__builtin_thread_pointer` and `__builtin_set_thread_pointer` builtins.

The get/set patterns have a single output/input operand respectively, with *mode* intended to be `Pmode`.

'stack_protect_set'

This pattern, if defined, moves a `ptr_mode` value from the memory in operand 1 to the memory in operand 0 without leaving the value in a register afterward. This is to avoid leaking the value some place that an attacker might use to rewrite the stack guard slot after having clobbered it.

If this pattern is not defined, then a plain move pattern is generated.

'`stack_protect_test`'
This pattern, if defined, compares a `ptr_mode` value from the memory in operand 1 with the memory in operand 0 without leaving the value in a register afterward and branches to operand 2 if the values were equal.

If this pattern is not defined, then a plain compare pattern and conditional branch pattern is used.

'`clear_cache`'
This pattern, if defined, flushes the instruction cache for a region of memory. The region is bounded to by the Pmode pointers in operand 0 inclusive and operand 1 exclusive.

If this pattern is not defined, a call to the library function `__clear_cache` is used.

16.10 When the Order of Patterns Matters

Sometimes an insn can match more than one instruction pattern. Then the pattern that appears first in the machine description is the one used. Therefore, more specific patterns (patterns that will match fewer things) and faster instructions (those that will produce better code when they do match) should usually go first in the description.

In some cases the effect of ordering the patterns can be used to hide a pattern when it is not valid. For example, the 68000 has an instruction for converting a fullword to floating point and another for converting a byte to floating point. An instruction converting an integer to floating point could match either one. We put the pattern to convert the fullword first to make sure that one will be used rather than the other. (Otherwise a large integer might be generated as a single-byte immediate quantity, which would not work.) Instead of using this pattern ordering it would be possible to make the pattern for convert-a-byte smart enough to deal properly with any constant value.

16.11 Interdependence of Patterns

In some cases machines support instructions identical except for the machine mode of one or more operands. For example, there may be "sign-extend halfword" and "sign-extend byte" instructions whose patterns are

```
(set (match_operand:SI 0 ...)
     (extend:SI (match_operand:HI 1 ...)))

(set (match_operand:SI 0 ...)
     (extend:SI (match_operand:QI 1 ...)))
```

Constant integers do not specify a machine mode, so an instruction to extend a constant value could match either pattern. The pattern it actually will match is the one that appears first in the file. For correct results, this must be the one for the widest possible mode (`HImode`, here). If the pattern matches the `QImode` instruction, the results will be incorrect if the constant value does not actually fit that mode.

Such instructions to extend constants are rarely generated because they are optimized away, but they do occasionally happen in nonoptimized compilations.

If a constraint in a pattern allows a constant, the reload pass may replace a register with a constant permitted by the constraint in some cases. Similarly for memory references. Because of this substitution, you should not provide separate patterns for increment and decrement instructions. Instead, they should be generated from the same pattern that supports register-register add insns by examining the operands and generating the appropriate machine instruction.

16.12 Defining Jump Instruction Patterns

GCC does not assume anything about how the machine realizes jumps. The machine description should define a single pattern, usually a `define_expand`, which expands to all the required insns.

Usually, this would be a comparison insn to set the condition code and a separate branch insn testing the condition code and branching or not according to its value. For many machines, however, separating compares and branches is limiting, which is why the more flexible approach with one `define_expand` is used in GCC. The machine description becomes clearer for architectures that have compare-and-branch instructions but no condition code. It also works better when different sets of comparison operators are supported by different kinds of conditional branches (e.g. integer vs. floating-point), or by conditional branches with respect to conditional stores.

Two separate insns are always used if the machine description represents a condition code register using the legacy RTL expression `(cc0)`, and on most machines that use a separate condition code register (see Section 17.16 [Condition Code], page 506). For machines that use `(cc0)`, in fact, the set and use of the condition code must be separate and adjacent[1], thus allowing flags in `cc_status` to be used (see Section 17.16 [Condition Code], page 506) and so that the comparison and branch insns could be located from each other by using the functions `prev_cc0_setter` and `next_cc0_user`.

Even in this case having a single entry point for conditional branches is advantageous, because it handles equally well the case where a single comparison instruction records the results of both signed and unsigned comparison of the given operands (with the branch insns coming in distinct signed and unsigned flavors) as in the x86 or SPARC, and the case where there are distinct signed and unsigned compare instructions and only one set of conditional branch instructions as in the PowerPC.

16.13 Defining Looping Instruction Patterns

Some machines have special jump instructions that can be utilized to make loops more efficient. A common example is the 68000 '`dbra`' instruction which performs a decrement of a register and a branch if the result was greater than zero. Other machines, in particular digital signal processors (DSPs), have special block repeat instructions to provide low-overhead loop support. For example, the TI TMS320C3x/C4x DSPs have a block repeat instruction that loads special registers to mark the top and end of a loop and to count the number of loop iterations. This avoids the need for fetching and executing a '`dbra`'-like instruction and avoids pipeline stalls associated with the jump.

[1] `note` insns can separate them, though.

GCC has three special named patterns to support low overhead looping. They are '`decrement_and_branch_until_zero`', '`doloop_begin`', and '`doloop_end`'. The first pattern, '`decrement_and_branch_until_zero`', is not emitted during RTL generation but may be emitted during the instruction combination phase. This requires the assistance of the loop optimizer, using information collected during strength reduction, to reverse a loop to count down to zero. Some targets also require the loop optimizer to add a `REG_NONNEG` note to indicate that the iteration count is always positive. This is needed if the target performs a signed loop termination test. For example, the 68000 uses a pattern similar to the following for its `dbra` instruction:

```
(define_insn "decrement_and_branch_until_zero"
  [(set (pc)
        (if_then_else
          (ge (plus:SI (match_operand:SI 0 "general_operand" "+d*am")
                       (const_int -1))
              (const_int 0))
          (label_ref (match_operand 1 "" ""))
          (pc)))
   (set (match_dup 0)
        (plus:SI (match_dup 0)
                 (const_int -1)))]
  "find_reg_note (insn, REG_NONNEG, 0)"
  "...")
```

Note that since the insn is both a jump insn and has an output, it must deal with its own reloads, hence the 'm' constraints. Also note that since this insn is generated by the instruction combination phase combining two sequential insns together into an implicit parallel insn, the iteration counter needs to be biased by the same amount as the decrement operation, in this case -1. Note that the following similar pattern will not be matched by the combiner.

```
(define_insn "decrement_and_branch_until_zero"
  [(set (pc)
        (if_then_else
          (ge (match_operand:SI 0 "general_operand" "+d*am")
              (const_int 1))
          (label_ref (match_operand 1 "" ""))
          (pc)))
   (set (match_dup 0)
        (plus:SI (match_dup 0)
                 (const_int -1)))]
  "find_reg_note (insn, REG_NONNEG, 0)"
  "...")
```

The other two special looping patterns, '`doloop_begin`' and '`doloop_end`', are emitted by the loop optimizer for certain well-behaved loops with a finite number of loop iterations using information collected during strength reduction.

The '`doloop_end`' pattern describes the actual looping instruction (or the implicit looping operation) and the '`doloop_begin`' pattern is an optional companion pattern that can be used for initialization needed for some low-overhead looping instructions.

Note that some machines require the actual looping instruction to be emitted at the top of the loop (e.g., the TMS320C3x/C4x DSPs). Emitting the true RTL for a looping instruction at the top of the loop can cause problems with flow analysis. So instead, a dummy `doloop` insn is emitted at the end of the loop. The machine dependent reorg pass checks for the presence of this `doloop` insn and then searches back to the top of the loop,

where it inserts the true looping insn (provided there are no instructions in the loop which would cause problems). Any additional labels can be emitted at this point. In addition, if the desired special iteration counter register was not allocated, this machine dependent reorg pass could emit a traditional compare and jump instruction pair.

The essential difference between the '`decrement_and_branch_until_zero`' and the '`doloop_end`' patterns is that the loop optimizer allocates an additional pseudo register for the latter as an iteration counter. This pseudo register cannot be used within the loop (i.e., general induction variables cannot be derived from it), however, in many cases the loop induction variable may become redundant and removed by the flow pass.

16.14 Canonicalization of Instructions

There are often cases where multiple RTL expressions could represent an operation performed by a single machine instruction. This situation is most commonly encountered with logical, branch, and multiply-accumulate instructions. In such cases, the compiler attempts to convert these multiple RTL expressions into a single canonical form to reduce the number of insn patterns required.

In addition to algebraic simplifications, following canonicalizations are performed:

- For commutative and comparison operators, a constant is always made the second operand. If a machine only supports a constant as the second operand, only patterns that match a constant in the second operand need be supplied.
- For associative operators, a sequence of operators will always chain to the left; for instance, only the left operand of an integer `plus` can itself be a `plus`. `and`, `ior`, `xor`, `plus`, `mult`, `smin`, `smax`, `umin`, and `umax` are associative when applied to integers, and sometimes to floating-point.
- For these operators, if only one operand is a `neg`, `not`, `mult`, `plus`, or `minus` expression, it will be the first operand.
- In combinations of `neg`, `mult`, `plus`, and `minus`, the `neg` operations (if any) will be moved inside the operations as far as possible. For instance, `(neg (mult A B))` is canonicalized as `(mult (neg A) B)`, but `(plus (mult (neg B) C) A)` is canonicalized as `(minus A (mult B C))`.
- For the `compare` operator, a constant is always the second operand if the first argument is a condition code register or `(cc0)`.
- An operand of `neg`, `not`, `mult`, `plus`, or `minus` is made the first operand under the same conditions as above.
- `(ltu (plus a b) b)` is converted to `(ltu (plus a b) a)`. Likewise with `geu` instead of `ltu`.
- `(minus x (const_int n))` is converted to `(plus x (const_int -n))`.
- Within address computations (i.e., inside `mem`), a left shift is converted into the appropriate multiplication by a power of two.
- De Morgan's Law is used to move bitwise negation inside a bitwise logical-and or logical-or operation. If this results in only one operand being a `not` expression, it will be the first one.

A machine that has an instruction that performs a bitwise logical-and of one operand with the bitwise negation of the other should specify the pattern for that instruction as

```
(define_insn ""
  [(set (match_operand:m 0 ...)
        (and:m (not:m (match_operand:m 1 ...))
                      (match_operand:m 2 ...)))]
  "..."
  "...")
```

Similarly, a pattern for a "NAND" instruction should be written

```
(define_insn ""
  [(set (match_operand:m 0 ...)
        (ior:m (not:m (match_operand:m 1 ...))
                      (not:m (match_operand:m 2 ...))))]
  "..."
  "...")
```

In both cases, it is not necessary to include patterns for the many logically equivalent RTL expressions.

- The only possible RTL expressions involving both bitwise exclusive-or and bitwise negation are `(xor:m x y)` and `(not:m (xor:m x y))`.
- The sum of three items, one of which is a constant, will only appear in the form

  `(plus:m (plus:m x y) constant)`
- Equality comparisons of a group of bits (usually a single bit) with zero will be written using `zero_extract` rather than the equivalent `and` or `sign_extract` operations.
- `(sign_extend:m1 (mult:m2 (sign_extend:m2 x) (sign_extend:m2 y)))` is converted to `(mult:m1 (sign_extend:m1 x) (sign_extend:m1 y))`, and likewise for `zero_extend`.
- `(sign_extend:m1 (mult:m2 (ashiftrt:m2 x s) (sign_extend:m2 y)))` is converted to `(mult:m1 (sign_extend:m1 (ashiftrt:m2 x s)) (sign_extend:m1 y))`, and likewise for patterns using `zero_extend` and `lshiftrt`. If the second operand of `mult` is also a shift, then that is extended also. This transformation is only applied when it can be proven that the original operation had sufficient precision to prevent overflow.

Further canonicalization rules are defined in the function `commutative_operand_precedence` in '`gcc/rtlanal.c`'.

16.15 Defining RTL Sequences for Code Generation

On some target machines, some standard pattern names for RTL generation cannot be handled with single insn, but a sequence of RTL insns can represent them. For these target machines, you can write a `define_expand` to specify how to generate the sequence of RTL.

A `define_expand` is an RTL expression that looks almost like a `define_insn`; but, unlike the latter, a `define_expand` is used only for RTL generation and it can produce more than one RTL insn.

A `define_expand` RTX has four operands:

- The name. Each `define_expand` must have a name, since the only use for it is to refer to it by name.

- The RTL template. This is a vector of RTL expressions representing a sequence of separate instructions. Unlike `define_insn`, there is no implicit surrounding `PARALLEL`.
- The condition, a string containing a C expression. This expression is used to express how the availability of this pattern depends on subclasses of target machine, selected by command-line options when GCC is run. This is just like the condition of a `define_insn` that has a standard name. Therefore, the condition (if present) may not depend on the data in the insn being matched, but only the target-machine-type flags. The compiler needs to test these conditions during initialization in order to learn exactly which named instructions are available in a particular run.
- The preparation statements, a string containing zero or more C statements which are to be executed before RTL code is generated from the RTL template.

  Usually these statements prepare temporary registers for use as internal operands in the RTL template, but they can also generate RTL insns directly by calling routines such as `emit_insn`, etc. Any such insns precede the ones that come from the RTL template.
- Optionally, a vector containing the values of attributes. See Section 16.19 [Insn Attributes], page 394.

Every RTL insn emitted by a `define_expand` must match some `define_insn` in the machine description. Otherwise, the compiler will crash when trying to generate code for the insn or trying to optimize it.

The RTL template, in addition to controlling generation of RTL insns, also describes the operands that need to be specified when this pattern is used. In particular, it gives a predicate for each operand.

A true operand, which needs to be specified in order to generate RTL from the pattern, should be described with a `match_operand` in its first occurrence in the RTL template. This enters information on the operand's predicate into the tables that record such things. GCC uses the information to preload the operand into a register if that is required for valid RTL code. If the operand is referred to more than once, subsequent references should use `match_dup`.

The RTL template may also refer to internal "operands" which are temporary registers or labels used only within the sequence made by the `define_expand`. Internal operands are substituted into the RTL template with `match_dup`, never with `match_operand`. The values of the internal operands are not passed in as arguments by the compiler when it requests use of this pattern. Instead, they are computed within the pattern, in the preparation statements. These statements compute the values and store them into the appropriate elements of `operands` so that `match_dup` can find them.

There are two special macros defined for use in the preparation statements: `DONE` and `FAIL`. Use them with a following semicolon, as a statement.

`DONE` Use the `DONE` macro to end RTL generation for the pattern. The only RTL insns resulting from the pattern on this occasion will be those already emitted by explicit calls to `emit_insn` within the preparation statements; the RTL template will not be generated.

`FAIL` Make the pattern fail on this occasion. When a pattern fails, it means that the pattern was not truly available. The calling routines in the compiler will try other strategies for code generation using other patterns.

Failure is currently supported only for binary (addition, multiplication, shifting, etc.) and bit-field (`extv`, `extzv`, and `insv`) operations.

If the preparation falls through (invokes neither `DONE` nor `FAIL`), then the `define_expand` acts like a `define_insn` in that the RTL template is used to generate the insn.

The RTL template is not used for matching, only for generating the initial insn list. If the preparation statement always invokes `DONE` or `FAIL`, the RTL template may be reduced to a simple list of operands, such as this example:

```
(define_expand "addsi3"
  [(match_operand:SI 0 "register_operand" "")
   (match_operand:SI 1 "register_operand" "")
   (match_operand:SI 2 "register_operand" "")]
  ""
  "
{
  handle_add (operands[0], operands[1], operands[2]);
  DONE;
}")
```

Here is an example, the definition of left-shift for the SPUR chip:

```
(define_expand "ashlsi3"
  [(set (match_operand:SI 0 "register_operand" "")
        (ashift:SI
          (match_operand:SI 1 "register_operand" "")
          (match_operand:SI 2 "nonmemory_operand" "")))]
  ""
  "

{
  if (GET_CODE (operands[2]) != CONST_INT
      || (unsigned) INTVAL (operands[2]) > 3)
    FAIL;
}")
```

This example uses `define_expand` so that it can generate an RTL insn for shifting when the shift-count is in the supported range of 0 to 3 but fail in other cases where machine insns aren't available. When it fails, the compiler tries another strategy using different patterns (such as, a library call).

If the compiler were able to handle nontrivial condition-strings in patterns with names, then it would be possible to use a `define_insn` in that case. Here is another case (zero-extension on the 68000) which makes more use of the power of `define_expand`:

```
(define_expand "zero_extendhisi2"
  [(set (match_operand:SI 0 "general_operand" "")
        (const_int 0))
   (set (strict_low_part
          (subreg:HI
            (match_dup 0)
            0))
        (match_operand:HI 1 "general_operand" ""))]
  ""
  "operands[1] = make_safe_from (operands[1], operands[0]);")
```

Here two RTL insns are generated, one to clear the entire output operand and the other to copy the input operand into its low half. This sequence is incorrect if the input operand refers to [the old value of] the output operand, so the preparation statement makes sure this isn't so. The function `make_safe_from` copies the `operands[1]` into a temporary register if it refers to `operands[0]`. It does this by emitting another RTL insn.

Finally, a third example shows the use of an internal operand. Zero-extension on the SPUR chip is done by `and`-ing the result against a halfword mask. But this mask cannot be represented by a `const_int` because the constant value is too large to be legitimate on this machine. So it must be copied into a register with `force_reg` and then the register used in the `and`.

```
(define_expand "zero_extendhisi2"
  [(set (match_operand:SI 0 "register_operand" "")
        (and:SI (subreg:SI
                  (match_operand:HI 1 "register_operand" "")
                  0)
                (match_dup 2)))]
  ""
  "operands[2]
     = force_reg (SImode, GEN_INT (65535)); ")
```

Note: If the `define_expand` is used to serve a standard binary or unary arithmetic operation or a bit-field operation, then the last insn it generates must not be a `code_label`, `barrier` or `note`. It must be an `insn`, `jump_insn` or `call_insn`. If you don't need a real insn at the end, emit an insn to copy the result of the operation into itself. Such an insn will generate no code, but it can avoid problems in the compiler.

16.16 Defining How to Split Instructions

There are two cases where you should specify how to split a pattern into multiple insns. On machines that have instructions requiring delay slots (see Section 16.19.8 [Delay Slots], page 403) or that have instructions whose output is not available for multiple cycles (see Section 16.19.9 [Processor pipeline description], page 404), the compiler phases that optimize these cases need to be able to move insns into one-instruction delay slots. However, some insns may generate more than one machine instruction. These insns cannot be placed into a delay slot.

Often you can rewrite the single insn as a list of individual insns, each corresponding to one machine instruction. The disadvantage of doing so is that it will cause the compilation to be slower and require more space. If the resulting insns are too complex, it may also suppress some optimizations. The compiler splits the insn if there is a reason to believe that it might improve instruction or delay slot scheduling.

The insn combiner phase also splits putative insns. If three insns are merged into one insn with a complex expression that cannot be matched by some `define_insn` pattern, the combiner phase attempts to split the complex pattern into two insns that are recognized. Usually it can break the complex pattern into two patterns by splitting out some subexpression. However, in some other cases, such as performing an addition of a large constant in two insns on a RISC machine, the way to split the addition into two insns is machine-dependent.

The `define_split` definition tells the compiler how to split a complex insn into several simpler insns. It looks like this:

```
(define_split
  [insn-pattern]
  "condition"
  [new-insn-pattern-1
   new-insn-pattern-2
   ...]
  "preparation-statements")
```

insn-pattern is a pattern that needs to be split and *condition* is the final condition to be tested, as in a `define_insn`. When an insn matching *insn-pattern* and satisfying *condition* is found, it is replaced in the insn list with the insns given by *new-insn-pattern-1*, *new-insn-pattern-2*, etc.

The *preparation-statements* are similar to those statements that are specified for `define_expand` (see Section 16.15 [Expander Definitions], page 383) and are executed before the new RTL is generated to prepare for the generated code or emit some insns whose pattern is not fixed. Unlike those in `define_expand`, however, these statements must not generate any new pseudo-registers. Once reload has completed, they also must not allocate any space in the stack frame.

Patterns are matched against *insn-pattern* in two different circumstances. If an insn needs to be split for delay slot scheduling or insn scheduling, the insn is already known to be valid, which means that it must have been matched by some `define_insn` and, if `reload_completed` is nonzero, is known to satisfy the constraints of that `define_insn`. In that case, the new insn patterns must also be insns that are matched by some `define_insn` and, if `reload_completed` is nonzero, must also satisfy the constraints of those definitions.

As an example of this usage of `define_split`, consider the following example from '`a29k.md`', which splits a `sign_extend` from `HImode` to `SImode` into a pair of shift insns:

```
(define_split
  [(set (match_operand:SI 0 "gen_reg_operand" "")
        (sign_extend:SI (match_operand:HI 1 "gen_reg_operand" "")))]
  ""
  [(set (match_dup 0)
        (ashift:SI (match_dup 1)
                   (const_int 16)))
   (set (match_dup 0)
        (ashiftrt:SI (match_dup 0)
                     (const_int 16)))]
  "
{ operands[1] = gen_lowpart (SImode, operands[1]); }")
```

When the combiner phase tries to split an insn pattern, it is always the case that the pattern is *not* matched by any `define_insn`. The combiner pass first tries to split a single `set` expression and then the same `set` expression inside a `parallel`, but followed by a `clobber` of a pseudo-reg to use as a scratch register. In these cases, the combiner expects exactly two new insn patterns to be generated. It will verify that these patterns match some `define_insn` definitions, so you need not do this test in the `define_split` (of course, there is no point in writing a `define_split` that will never produce insns that match).

Here is an example of this use of `define_split`, taken from '`rs6000.md`':

```
(define_split
  [(set (match_operand:SI 0 "gen_reg_operand" "")
        (plus:SI (match_operand:SI 1 "gen_reg_operand" "")
                 (match_operand:SI 2 "non_add_cint_operand" "")))]
  ""
```

```
  [(set (match_dup 0) (plus:SI (match_dup 1) (match_dup 3)))
   (set (match_dup 0) (plus:SI (match_dup 0) (match_dup 4)))]
"
{
  int low = INTVAL (operands[2]) & 0xffff;
  int high = (unsigned) INTVAL (operands[2]) >> 16;

  if (low & 0x8000)
    high++, low |= 0xffff0000;

  operands[3] = GEN_INT (high << 16);
  operands[4] = GEN_INT (low);
}")
```

Here the predicate `non_add_cint_operand` matches any `const_int` that is *not* a valid operand of a single add insn. The add with the smaller displacement is written so that it can be substituted into the address of a subsequent operation.

An example that uses a scratch register, from the same file, generates an equality comparison of a register and a large constant:

```
(define_split
  [(set (match_operand:CC 0 "cc_reg_operand" "")
        (compare:CC (match_operand:SI 1 "gen_reg_operand" "")
                    (match_operand:SI 2 "non_short_cint_operand" "")))
   (clobber (match_operand:SI 3 "gen_reg_operand" ""))]
  "find_single_use (operands[0], insn, 0)
   && (GET_CODE (*find_single_use (operands[0], insn, 0)) == EQ
       || GET_CODE (*find_single_use (operands[0], insn, 0)) == NE)"
  [(set (match_dup 3) (xor:SI (match_dup 1) (match_dup 4)))
   (set (match_dup 0) (compare:CC (match_dup 3) (match_dup 5)))]
  "
{
  /* Get the constant we are comparing against, C, and see what it
     looks like sign-extended to 16 bits. Then see what constant
     could be XOR'ed with C to get the sign-extended value.  */

  int c = INTVAL (operands[2]);
  int sextc = (c << 16) >> 16;
  int xorv = c ^ sextc;

  operands[4] = GEN_INT (xorv);
  operands[5] = GEN_INT (sextc);
}")
```

To avoid confusion, don't write a single `define_split` that accepts some insns that match some `define_insn` as well as some insns that don't. Instead, write two separate `define_split` definitions, one for the insns that are valid and one for the insns that are not valid.

The splitter is allowed to split jump instructions into sequence of jumps or create new jumps in while splitting non-jump instructions. As the central flowgraph and branch prediction information needs to be updated, several restriction apply.

Splitting of jump instruction into sequence that over by another jump instruction is always valid, as compiler expect identical behavior of new jump. When new sequence contains multiple jump instructions or new labels, more assistance is needed. Splitter is required to create only unconditional jumps, or simple conditional jump instructions. Additionally

it must attach a REG_BR_PROB note to each conditional jump. A global variable split_branch_probability holds the probability of the original branch in case it was a simple conditional jump, −1 otherwise. To simplify recomputing of edge frequencies, the new sequence is required to have only forward jumps to the newly created labels.

For the common case where the pattern of a define_split exactly matches the pattern of a define_insn, use define_insn_and_split. It looks like this:

```
(define_insn_and_split
  [insn-pattern]
  "condition"
  "output-template"
  "split-condition"
  [new-insn-pattern-1
   new-insn-pattern-2
   ...]
  "preparation-statements"
  [insn-attributes])
```

insn-pattern, *condition*, *output-template*, and *insn-attributes* are used as in define_insn. The *new-insn-pattern* vector and the *preparation-statements* are used as in a define_split. The *split-condition* is also used as in define_split, with the additional behavior that if the condition starts with '&&', the condition used for the split will be the constructed as a logical "and" of the split condition with the insn condition. For example, from i386.md:

```
(define_insn_and_split "zero_extendhisi2_and"
  [(set (match_operand:SI 0 "register_operand" "=r")
     (zero_extend:SI (match_operand:HI 1 "register_operand" "0")))
   (clobber (reg:CC 17))]
  "TARGET_ZERO_EXTEND_WITH_AND && !optimize_size"
  "#"
  "&& reload_completed"
  [(parallel [(set (match_dup 0)
                   (and:SI (match_dup 0) (const_int 65535)))
              (clobber (reg:CC 17))])]
  ""
  [(set_attr "type" "alu1")])
```

In this case, the actual split condition will be 'TARGET_ZERO_EXTEND_WITH_AND && !optimize_size && reload_completed'.

The define_insn_and_split construction provides exactly the same functionality as two separate define_insn and define_split patterns. It exists for compactness, and as a maintenance tool to prevent having to ensure the two patterns' templates match.

16.17 Including Patterns in Machine Descriptions.

The include pattern tells the compiler tools where to look for patterns that are in files other than in the file '.md'. This is used only at build time and there is no preprocessing allowed.

It looks like:

```
(include
  pathname)
```

For example:

```
(include "filestuff")
```

Where *pathname* is a string that specifies the location of the file, specifies the include file to be in '`gcc/config/target/filestuff`'. The directory '`gcc/config/target`' is regarded as the default directory.

Machine descriptions may be split up into smaller more manageable subsections and placed into subdirectories.

By specifying:

```
(include "BOGUS/filestuff")
```

the include file is specified to be in '`gcc/config/`*target*`/BOGUS/filestuff`'.

Specifying an absolute path for the include file such as;

```
(include "/u2/BOGUS/filestuff")
```

is permitted but is not encouraged.

16.17.1 RTL Generation Tool Options for Directory Search

The '`-I`*dir*' option specifies directories to search for machine descriptions. For example:

```
genrecog -I/p1/abc/proc1 -I/p2/abcd/pro2 target.md
```

Add the directory *dir* to the head of the list of directories to be searched for header files. This can be used to override a system machine definition file, substituting your own version, since these directories are searched before the default machine description file directories. If you use more than one '`-I`' option, the directories are scanned in left-to-right order; the standard default directory come after.

16.18 Machine-Specific Peephole Optimizers

In addition to instruction patterns the '`md`' file may contain definitions of machine-specific peephole optimizations.

The combiner does not notice certain peephole optimizations when the data flow in the program does not suggest that it should try them. For example, sometimes two consecutive insns related in purpose can be combined even though the second one does not appear to use a register computed in the first one. A machine-specific peephole optimizer can detect such opportunities.

There are two forms of peephole definitions that may be used. The original `define_peephole` is run at assembly output time to match insns and substitute assembly text. Use of `define_peephole` is deprecated.

A newer `define_peephole2` matches insns and substitutes new insns. The `peephole2` pass is run after register allocation but before scheduling, which may result in much better code for targets that do scheduling.

16.18.1 RTL to Text Peephole Optimizers

A definition looks like this:

```
(define_peephole
  [insn-pattern-1
   insn-pattern-2
   ...]
  "condition"
  "template"
  "optional-insn-attributes")
```

The last string operand may be omitted if you are not using any machine-specific information in this machine description. If present, it must obey the same rules as in a `define_insn`.

In this skeleton, *insn-pattern-1* and so on are patterns to match consecutive insns. The optimization applies to a sequence of insns when *insn-pattern-1* matches the first one, *insn-pattern-2* matches the next, and so on.

Each of the insns matched by a peephole must also match a `define_insn`. Peepholes are checked only at the last stage just before code generation, and only optionally. Therefore, any insn which would match a peephole but no `define_insn` will cause a crash in code generation in an unoptimized compilation, or at various optimization stages.

The operands of the insns are matched with `match_operands`, `match_operator`, and `match_dup`, as usual. What is not usual is that the operand numbers apply to all the insn patterns in the definition. So, you can check for identical operands in two insns by using `match_operand` in one insn and `match_dup` in the other.

The operand constraints used in `match_operand` patterns do not have any direct effect on the applicability of the peephole, but they will be validated afterward, so make sure your constraints are general enough to apply whenever the peephole matches. If the peephole matches but the constraints are not satisfied, the compiler will crash.

It is safe to omit constraints in all the operands of the peephole; or you can write constraints which serve as a double-check on the criteria previously tested.

Once a sequence of insns matches the patterns, the *condition* is checked. This is a C expression which makes the final decision whether to perform the optimization (we do so if the expression is nonzero). If *condition* is omitted (in other words, the string is empty) then the optimization is applied to every sequence of insns that matches the patterns.

The defined peephole optimizations are applied after register allocation is complete. Therefore, the peephole definition can check which operands have ended up in which kinds of registers, just by looking at the operands.

The way to refer to the operands in *condition* is to write `operands[i]` for operand number *i* (as matched by `(match_operand i ...)`). Use the variable `insn` to refer to the last of the insns being matched; use `prev_active_insn` to find the preceding insns.

When optimizing computations with intermediate results, you can use *condition* to match only when the intermediate results are not used elsewhere. Use the C expression `dead_or_set_p (insn, op)`, where *insn* is the insn in which you expect the value to be used for the last time (from the value of `insn`, together with use of `prev_nonnote_insn`), and *op* is the intermediate value (from `operands[i]`).

Applying the optimization means replacing the sequence of insns with one new insn. The *template* controls ultimate output of assembler code for this combined insn. It works exactly

like the template of a `define_insn`. Operand numbers in this template are the same ones used in matching the original sequence of insns.

The result of a defined peephole optimizer does not need to match any of the insn patterns in the machine description; it does not even have an opportunity to match them. The peephole optimizer definition itself serves as the insn pattern to control how the insn is output.

Defined peephole optimizers are run as assembler code is being output, so the insns they produce are never combined or rearranged in any way.

Here is an example, taken from the 68000 machine description:

```
(define_peephole
  [(set (reg:SI 15) (plus:SI (reg:SI 15) (const_int 4)))
   (set (match_operand:DF 0 "register_operand" "=f")
        (match_operand:DF 1 "register_operand" "ad"))]
  "FP_REG_P (operands[0]) && ! FP_REG_P (operands[1])"
{
  rtx xoperands[2];
  xoperands[1] = gen_rtx_REG (SImode, REGNO (operands[1]) + 1);
#ifdef MOTOROLA
  output_asm_insn ("move.l %1,(sp)", xoperands);
  output_asm_insn ("move.l %1,-(sp)", operands);
  return "fmove.d (sp)+,%0";
#else
  output_asm_insn ("movel %1,sp@", xoperands);
  output_asm_insn ("movel %1,sp@-", operands);
  return "fmoved sp@+,%0";
#endif
})
```

The effect of this optimization is to change

```
jbsr _foobar
addql #4,sp
movel d1,sp@-
movel d0,sp@-
fmoved sp@+,fp0
```

into

```
jbsr _foobar
movel d1,sp@
movel d0,sp@-
fmoved sp@+,fp0
```

insn-pattern-1 and so on look *almost* like the second operand of `define_insn`. There is one important difference: the second operand of `define_insn` consists of one or more RTX's enclosed in square brackets. Usually, there is only one: then the same action can be written as an element of a `define_peephole`. But when there are multiple actions in a `define_insn`, they are implicitly enclosed in a `parallel`. Then you must explicitly write the `parallel`, and the square brackets within it, in the `define_peephole`. Thus, if an insn pattern looks like this,

```
(define_insn "divmodsi4"
  [(set (match_operand:SI 0 "general_operand" "=d")
        (div:SI (match_operand:SI 1 "general_operand" "0")
                (match_operand:SI 2 "general_operand" "dmsK")))
   (set (match_operand:SI 3 "general_operand" "=d")
        (mod:SI (match_dup 1) (match_dup 2)))]
  "TARGET_68020"
```

```
  "divsl%.l %2,%3:%0")
```

then the way to mention this insn in a peephole is as follows:

```
(define_peephole
  [...
   (parallel
    [(set (match_operand:SI 0 "general_operand" "=d")
          (div:SI (match_operand:SI 1 "general_operand" "0")
                  (match_operand:SI 2 "general_operand" "dmsK")))
     (set (match_operand:SI 3 "general_operand" "=d")
          (mod:SI (match_dup 1) (match_dup 2)))])
   ...]
  ...)
```

16.18.2 RTL to RTL Peephole Optimizers

The `define_peephole2` definition tells the compiler how to substitute one sequence of instructions for another sequence, what additional scratch registers may be needed and what their lifetimes must be.

```
(define_peephole2
  [insn-pattern-1
   insn-pattern-2
   ...]
  "condition"
  [new-insn-pattern-1
   new-insn-pattern-2
   ...]
  "preparation-statements")
```

The definition is almost identical to `define_split` (see Section 16.16 [Insn Splitting], page 386) except that the pattern to match is not a single instruction, but a sequence of instructions.

It is possible to request additional scratch registers for use in the output template. If appropriate registers are not free, the pattern will simply not match.

Scratch registers are requested with a `match_scratch` pattern at the top level of the input pattern. The allocated register (initially) will be dead at the point requested within the original sequence. If the scratch is used at more than a single point, a `match_dup` pattern at the top level of the input pattern marks the last position in the input sequence at which the register must be available.

Here is an example from the IA-32 machine description:

```
(define_peephole2
  [(match_scratch:SI 2 "r")
   (parallel [(set (match_operand:SI 0 "register_operand" "")
                   (match_operator:SI 3 "arith_or_logical_operator"
                     [(match_dup 0)
                      (match_operand:SI 1 "memory_operand" "")]))
              (clobber (reg:CC 17))])]
  "! optimize_size && ! TARGET_READ_MODIFY"
  [(set (match_dup 2) (match_dup 1))
   (parallel [(set (match_dup 0)
                   (match_op_dup 3 [(match_dup 0) (match_dup 2)]))
              (clobber (reg:CC 17))])]
  "")
```

This pattern tries to split a load from its use in the hopes that we'll be able to schedule around the memory load latency. It allocates a single `SImode` register of class `GENERAL_REGS` (`"r"`) that needs to be live only at the point just before the arithmetic.

A real example requiring extended scratch lifetimes is harder to come by, so here's a silly made-up example:

```
(define_peephole2
  [(match_scratch:SI 4 "r")
   (set (match_operand:SI 0 "" "") (match_operand:SI 1 "" ""))
   (set (match_operand:SI 2 "" "") (match_dup 1))
   (match_dup 4)
   (set (match_operand:SI 3 "" "") (match_dup 1))]
  "/* determine 1 does not overlap 0 and 2 */"
  [(set (match_dup 4) (match_dup 1))
   (set (match_dup 0) (match_dup 4))
   (set (match_dup 2) (match_dup 4))
   (set (match_dup 3) (match_dup 4))]
  "")
```

If we had not added the `(match_dup 4)` in the middle of the input sequence, it might have been the case that the register we chose at the beginning of the sequence is killed by the first or second `set`.

16.19 Instruction Attributes

In addition to describing the instruction supported by the target machine, the '`md`' file also defines a group of *attributes* and a set of values for each. Every generated insn is assigned a value for each attribute. One possible attribute would be the effect that the insn has on the machine's condition code. This attribute can then be used by `NOTICE_UPDATE_CC` to track the condition codes.

16.19.1 Defining Attributes and their Values

The `define_attr` expression is used to define each attribute required by the target machine. It looks like:

```
(define_attr name list-of-values default)
```

name is a string specifying the name of the attribute being defined. Some attributes are used in a special way by the rest of the compiler. The `enabled` attribute can be used to conditionally enable or disable insn alternatives (see Section 16.8.6 [Disable Insn Alternatives], page 345). The `predicable` attribute, together with a suitable `define_cond_exec` (see Section 16.20 [Conditional Execution], page 409), can be used to automatically generate conditional variants of instruction patterns. The `mnemonic` attribute can be used to check for the instruction mnemonic (see Section 16.19.7 [Mnemonic Attribute], page 402). The compiler internally uses the names `ce_enabled` and `nonce_enabled`, so they should not be used elsewhere as alternative names.

list-of-values is either a string that specifies a comma-separated list of values that can be assigned to the attribute, or a null string to indicate that the attribute takes numeric values.

default is an attribute expression that gives the value of this attribute for insns that match patterns whose definition does not include an explicit value for this attribute. See Section 16.19.4 [Attr Example], page 400, for more information on the handling of defaults.

See Section 16.19.6 [Constant Attributes], page 402, for information on attributes that do not depend on any particular insn.

For each defined attribute, a number of definitions are written to the '`insn-attr.h`' file. For cases where an explicit set of values is specified for an attribute, the following are defined:

- A '`#define`' is written for the symbol '`HAVE_ATTR_name`'.
- An enumerated class is defined for '`attr_name`' with elements of the form '`upper-name_upper-value`' where the attribute name and value are first converted to uppercase.
- A function '`get_attr_name`' is defined that is passed an insn and returns the attribute value for that insn.

For example, if the following is present in the '`md`' file:

```
(define_attr "type" "branch,fp,load,store,arith" ...)
```

the following lines will be written to the file '`insn-attr.h`'.

```
#define HAVE_ATTR_type 1
enum attr_type {TYPE_BRANCH, TYPE_FP, TYPE_LOAD,
                TYPE_STORE, TYPE_ARITH};
extern enum attr_type get_attr_type ();
```

If the attribute takes numeric values, no `enum` type will be defined and the function to obtain the attribute's value will return `int`.

There are attributes which are tied to a specific meaning. These attributes are not free to use for other purposes:

`length` The `length` attribute is used to calculate the length of emitted code chunks. This is especially important when verifying branch distances. See Section 16.19.5 [Insn Lengths], page 401.

`enabled` The `enabled` attribute can be defined to prevent certain alternatives of an insn definition from being used during code generation. See Section 16.8.6 [Disable Insn Alternatives], page 345.

`mnemonic` The `mnemonic` attribute can be defined to implement instruction specific checks in e.g. the pipeline description. See Section 16.19.7 [Mnemonic Attribute], page 402.

For each of these special attributes, the corresponding '`HAVE_ATTR_name`' '`#define`' is also written when the attribute is not defined; in that case, it is defined as '`0`'.

Another way of defining an attribute is to use:

```
(define_enum_attr "attr" "enum" default)
```

This works in just the same way as `define_attr`, except that the list of values is taken from a separate enumeration called *enum* (see [define_enum], page 415). This form allows you to use the same list of values for several attributes without having to repeat the list each time. For example:

```
(define_enum "processor" [
  model_a
  model_b
  ...
])
```

```
(define_enum_attr "arch" "processor"
  (const (symbol_ref "target_arch")))
(define_enum_attr "tune" "processor"
  (const (symbol_ref "target_tune")))
```

defines the same attributes as:

```
(define_attr "arch" "model_a,model_b,..."
  (const (symbol_ref "target_arch")))
(define_attr "tune" "model_a,model_b,..."
  (const (symbol_ref "target_tune")))
```

but without duplicating the processor list. The second example defines two separate C enums (`attr_arch` and `attr_tune`) whereas the first defines a single C enum (`processor`).

16.19.2 Attribute Expressions

RTL expressions used to define attributes use the codes described above plus a few specific to attribute definitions, to be discussed below. Attribute value expressions must have one of the following forms:

`(const_int i)`

The integer *i* specifies the value of a numeric attribute. *i* must be non-negative.

The value of a numeric attribute can be specified either with a `const_int`, or as an integer represented as a string in `const_string`, `eq_attr` (see below), `attr`, `symbol_ref`, simple arithmetic expressions, and `set_attr` overrides on specific instructions (see Section 16.19.3 [Tagging Insns], page 398).

`(const_string value)`

The string *value* specifies a constant attribute value. If *value* is specified as '`"*"`', it means that the default value of the attribute is to be used for the insn containing this expression. '`"*"`' obviously cannot be used in the *default* expression of a `define_attr`.

If the attribute whose value is being specified is numeric, *value* must be a string containing a non-negative integer (normally `const_int` would be used in this case). Otherwise, it must contain one of the valid values for the attribute.

`(if_then_else test true-value false-value)`

test specifies an attribute test, whose format is defined below. The value of this expression is *true-value* if *test* is true, otherwise it is *false-value*.

`(cond [test1 value1 ...] default)`

The first operand of this expression is a vector containing an even number of expressions and consisting of pairs of *test* and *value* expressions. The value of the `cond` expression is that of the *value* corresponding to the first true *test* expression. If none of the *test* expressions are true, the value of the `cond` expression is that of the *default* expression.

test expressions can have one of the following forms:

`(const_int i)`

This test is true if *i* is nonzero and false otherwise.

(not *test*)
(ior *test1 test2*)
(and *test1 test2*)

These tests are true if the indicated logical function is true.

(match_operand:*m n pred constraints*)

This test is true if operand *n* of the insn whose attribute value is being determined has mode *m* (this part of the test is ignored if *m* is `VOIDmode`) and the function specified by the string *pred* returns a nonzero value when passed operand *n* and mode *m* (this part of the test is ignored if *pred* is the null string).

The *constraints* operand is ignored and should be the null string.

(match_test *c-expr*)

The test is true if C expression *c-expr* is true. In non-constant attributes, *c-expr* has access to the following variables:

insn The rtl instruction under test.

which_alternative
The `define_insn` alternative that *insn* matches. See Section 16.6 [Output Statement], page 304.

operands An array of *insn*'s rtl operands.

c-expr behaves like the condition in a C `if` statement, so there is no need to explicitly convert the expression into a boolean 0 or 1 value. For example, the following two tests are equivalent:

```
(match_test "x & 2")
(match_test "(x & 2) != 0")
```

(le *arith1 arith2*)
(leu *arith1 arith2*)
(lt *arith1 arith2*)
(ltu *arith1 arith2*)
(gt *arith1 arith2*)
(gtu *arith1 arith2*)
(ge *arith1 arith2*)
(geu *arith1 arith2*)
(ne *arith1 arith2*)
(eq *arith1 arith2*)

These tests are true if the indicated comparison of the two arithmetic expressions is true. Arithmetic expressions are formed with `plus`, `minus`, `mult`, `div`, `mod`, `abs`, `neg`, `and`, `ior`, `xor`, `not`, `ashift`, `lshiftrt`, and `ashiftrt` expressions.

`const_int` and `symbol_ref` are always valid terms (see Section 16.19.5 [Insn Lengths], page 401,for additional forms). `symbol_ref` is a string denoting a C expression that yields an `int` when evaluated by the '`get_attr_...`' routine. It should normally be a global variable.

(eq_attr *name value*)

name is a string specifying the name of an attribute.

value is a string that is either a valid value for attribute *name*, a comma-separated list of values, or '`!`' followed by a value or list. If *value* does not begin with a '`!`', this test is true if the value of the *name* attribute of the current insn is in the list specified by *value*. If *value* begins with a '`!`', this test is true if the attribute's value is *not* in the specified list.

For example,

```
(eq_attr "type" "load,store")
```

is equivalent to

```
(ior (eq_attr "type" "load") (eq_attr "type" "store"))
```

If *name* specifies an attribute of '`alternative`', it refers to the value of the compiler variable `which_alternative` (see Section 16.6 [Output Statement], page 304) and the values must be small integers. For example,

```
(eq_attr "alternative" "2,3")
```

is equivalent to

```
(ior (eq (symbol_ref "which_alternative") (const_int 2))
     (eq (symbol_ref "which_alternative") (const_int 3)))
```

Note that, for most attributes, an `eq_attr` test is simplified in cases where the value of the attribute being tested is known for all insns matching a particular pattern. This is by far the most common case.

`(attr_flag` *name*`)`

The value of an `attr_flag` expression is true if the flag specified by *name* is true for the `insn` currently being scheduled.

name is a string specifying one of a fixed set of flags to test. Test the flags `forward` and `backward` to determine the direction of a conditional branch.

This example describes a conditional branch delay slot which can be nullified for forward branches that are taken (annul-true) or for backward branches which are not taken (annul-false).

```
(define_delay (eq_attr "type" "cbranch")
  [(eq_attr "in_branch_delay" "true")
   (and (eq_attr "in_branch_delay" "true")
        (attr_flag "forward"))
   (and (eq_attr "in_branch_delay" "true")
        (attr_flag "backward"))])
```

The `forward` and `backward` flags are false if the current `insn` being scheduled is not a conditional branch.

`attr_flag` is only used during delay slot scheduling and has no meaning to other passes of the compiler.

`(attr` *name*`)`

The value of another attribute is returned. This is most useful for numeric attributes, as `eq_attr` and `attr_flag` produce more efficient code for non-numeric attributes.

16.19.3 Assigning Attribute Values to Insns

The value assigned to an attribute of an insn is primarily determined by which pattern is matched by that insn (or which `define_peephole` generated it). Every `define_insn` and

`define_peephole` can have an optional last argument to specify the values of attributes for matching insns. The value of any attribute not specified in a particular insn is set to the default value for that attribute, as specified in its `define_attr`. Extensive use of default values for attributes permits the specification of the values for only one or two attributes in the definition of most insn patterns, as seen in the example in the next section.

The optional last argument of `define_insn` and `define_peephole` is a vector of expressions, each of which defines the value for a single attribute. The most general way of assigning an attribute's value is to use a `set` expression whose first operand is an `attr` expression giving the name of the attribute being set. The second operand of the `set` is an attribute expression (see Section 16.19.2 [Expressions], page 396) giving the value of the attribute.

When the attribute value depends on the '`alternative`' attribute (i.e., which is the applicable alternative in the constraint of the insn), the `set_attr_alternative` expression can be used. It allows the specification of a vector of attribute expressions, one for each alternative.

When the generality of arbitrary attribute expressions is not required, the simpler `set_attr` expression can be used, which allows specifying a string giving either a single attribute value or a list of attribute values, one for each alternative.

The form of each of the above specifications is shown below. In each case, *name* is a string specifying the attribute to be set.

`(set_attr` *`name value-string`*`)`

value-string is either a string giving the desired attribute value, or a string containing a comma-separated list giving the values for succeeding alternatives. The number of elements must match the number of alternatives in the constraint of the insn pattern.

Note that it may be useful to specify '`*`' for some alternative, in which case the attribute will assume its default value for insns matching that alternative.

`(set_attr_alternative` *`name`* `[`*`value1 value2 ...`*`])`

Depending on the alternative of the insn, the value will be one of the specified values. This is a shorthand for using a `cond` with tests on the '`alternative`' attribute.

`(set (attr` *`name`*`)` *`value`*`)`

The first operand of this `set` must be the special RTL expression `attr`, whose sole operand is a string giving the name of the attribute being set. *value* is the value of the attribute.

The following shows three different ways of representing the same attribute value specification:

```
(set_attr "type" "load,store,arith")

(set_attr_alternative "type"
                      [(const_string "load") (const_string "store")
                       (const_string "arith")])

(set (attr "type")
     (cond [(eq_attr "alternative" "1") (const_string "load")
```

```
                (eq_attr "alternative" "2") (const_string "store")]
               (const_string "arith")))
```

The `define_asm_attributes` expression provides a mechanism to specify the attributes assigned to insns produced from an `asm` statement. It has the form:

```
(define_asm_attributes [attr-sets])
```

where *attr-sets* is specified the same as for both the `define_insn` and the `define_peephole` expressions.

These values will typically be the "worst case" attribute values. For example, they might indicate that the condition code will be clobbered.

A specification for a `length` attribute is handled specially. The way to compute the length of an `asm` insn is to multiply the length specified in the expression `define_asm_attributes` by the number of machine instructions specified in the `asm` statement, determined by counting the number of semicolons and newlines in the string. Therefore, the value of the `length` attribute specified in a `define_asm_attributes` should be the maximum possible length of a single machine instruction.

16.19.4 Example of Attribute Specifications

The judicious use of defaulting is important in the efficient use of insn attributes. Typically, insns are divided into *types* and an attribute, customarily called `type`, is used to represent this value. This attribute is normally used only to define the default value for other attributes. An example will clarify this usage.

Assume we have a RISC machine with a condition code and in which only full-word operations are performed in registers. Let us assume that we can divide all insns into loads, stores, (integer) arithmetic operations, floating point operations, and branches.

Here we will concern ourselves with determining the effect of an insn on the condition code and will limit ourselves to the following possible effects: The condition code can be set unpredictably (clobbered), not be changed, be set to agree with the results of the operation, or only changed if the item previously set into the condition code has been modified.

Here is part of a sample '`md`' file for such a machine:

```
(define_attr "type" "load,store,arith,fp,branch" (const_string "arith"))

(define_attr "cc" "clobber,unchanged,set,change0"
             (cond [(eq_attr "type" "load")
                        (const_string "change0")
                    (eq_attr "type" "store,branch")
                        (const_string "unchanged")
                    (eq_attr "type" "arith")
                        (if_then_else (match_operand:SI 0 "" "")
                                      (const_string "set")
                                      (const_string "clobber"))]
                   (const_string "clobber")))

(define_insn ""
  [(set (match_operand:SI 0 "general_operand" "=r,r,m")
        (match_operand:SI 1 "general_operand" "r,m,r"))]
  ""
  "@
   move %0,%1
   load %0,%1
```

```
 store %0,%1"
[(set_attr "type" "arith,load,store")])
```

Note that we assume in the above example that arithmetic operations performed on quantities smaller than a machine word clobber the condition code since they will set the condition code to a value corresponding to the full-word result.

16.19.5 Computing the Length of an Insn

For many machines, multiple types of branch instructions are provided, each for different length branch displacements. In most cases, the assembler will choose the correct instruction to use. However, when the assembler cannot do so, GCC can when a special attribute, the `length` attribute, is defined. This attribute must be defined to have numeric values by specifying a null string in its `define_attr`.

In the case of the `length` attribute, two additional forms of arithmetic terms are allowed in test expressions:

`(match_dup` *n*`)`
: This refers to the address of operand *n* of the current insn, which must be a `label_ref`.

`(pc)`
: This refers to the address of the *current* insn. It might have been more consistent with other usage to make this the address of the *next* insn but this would be confusing because the length of the current insn is to be computed.

For normal insns, the length will be determined by value of the `length` attribute. In the case of `addr_vec` and `addr_diff_vec` insn patterns, the length is computed as the number of vectors multiplied by the size of each vector.

Lengths are measured in addressable storage units (bytes).

The following macros can be used to refine the length computation:

`ADJUST_INSN_LENGTH (`*insn*`, `*length*`)`
: If defined, modifies the length assigned to instruction *insn* as a function of the context in which it is used. *length* is an lvalue that contains the initially computed length of the insn and should be updated with the correct length of the insn.

  This macro will normally not be required. A case in which it is required is the ROMP. On this machine, the size of an `addr_vec` insn must be increased by two to compensate for the fact that alignment may be required.

The routine that returns `get_attr_length` (the value of the `length` attribute) can be used by the output routine to determine the form of the branch instruction to be written, as the example below illustrates.

As an example of the specification of variable-length branches, consider the IBM 360. If we adopt the convention that a register will be set to the starting address of a function, we can jump to labels within 4k of the start using a four-byte instruction. Otherwise, we need a six-byte sequence to load the address from memory and then branch to it.

On such a machine, a pattern for a branch instruction might be specified as follows:

```
(define_insn "jump"
  [(set (pc)
```

```
        (label_ref (match_operand 0 "" "")))]
  ""
{
   return (get_attr_length (insn) == 4
           ? "b %l0" : "l r15,=a(%l0); br r15");
}
  [(set (attr "length")
        (if_then_else (lt (match_dup 0) (const_int 4096))
                      (const_int 4)
                      (const_int 6)))])
```

16.19.6 Constant Attributes

A special form of `define_attr`, where the expression for the default value is a `const` expression, indicates an attribute that is constant for a given run of the compiler. Constant attributes may be used to specify which variety of processor is used. For example,

```
(define_attr "cpu" "m88100,m88110,m88000"
 (const
  (cond [(symbol_ref "TARGET_88100") (const_string "m88100")
         (symbol_ref "TARGET_88110") (const_string "m88110")]
        (const_string "m88000"))))

(define_attr "memory" "fast,slow"
 (const
  (if_then_else (symbol_ref "TARGET_FAST_MEM")
                (const_string "fast")
                (const_string "slow"))))
```

The routine generated for constant attributes has no parameters as it does not depend on any particular insn. RTL expressions used to define the value of a constant attribute may use the `symbol_ref` form, but may not use either the `match_operand` form or `eq_attr` forms involving insn attributes.

16.19.7 Mnemonic Attribute

The `mnemonic` attribute is a string type attribute holding the instruction mnemonic for an insn alternative. The attribute values will automatically be generated by the machine description parser if there is an attribute definition in the md file:

```
(define_attr "mnemonic" "unknown" (const_string "unknown"))
```

The default value can be freely chosen as long as it does not collide with any of the instruction mnemonics. This value will be used whenever the machine description parser is not able to determine the mnemonic string. This might be the case for output templates containing more than a single instruction as in `"mvcle\t%0,%1,0\;jo\t.-4"`.

The `mnemonic` attribute set is not generated automatically if the instruction string is generated via C code.

An existing `mnemonic` attribute set in an insn definition will not be overriden by the md file parser. That way it is possible to manually set the instruction mnemonics for the cases where the md file parser fails to determine it automatically.

The `mnemonic` attribute is useful for dealing with instruction specific properties in the pipeline description without defining additional insn attributes.

```
(define_attr "ooo_expanded" ""
  (cond [(eq_attr "mnemonic" "dlr,dsgr,d,dsgf,stam,dsgfr,dlgr")
         (const_int 1)]
```

```
            (const_int 0)))
```

16.19.8 Delay Slot Scheduling

The insn attribute mechanism can be used to specify the requirements for delay slots, if any, on a target machine. An instruction is said to require a *delay slot* if some instructions that are physically after the instruction are executed as if they were located before it. Classic examples are branch and call instructions, which often execute the following instruction before the branch or call is performed.

On some machines, conditional branch instructions can optionally *annul* instructions in the delay slot. This means that the instruction will not be executed for certain branch outcomes. Both instructions that annul if the branch is true and instructions that annul if the branch is false are supported.

Delay slot scheduling differs from instruction scheduling in that determining whether an instruction needs a delay slot is dependent only on the type of instruction being generated, not on data flow between the instructions. See the next section for a discussion of data-dependent instruction scheduling.

The requirement of an insn needing one or more delay slots is indicated via the `define_delay` expression. It has the following form:

```
(define_delay test
              [delay-1 annul-true-1 annul-false-1
               delay-2 annul-true-2 annul-false-2
               ...])
```

test is an attribute test that indicates whether this `define_delay` applies to a particular insn. If so, the number of required delay slots is determined by the length of the vector specified as the second argument. An insn placed in delay slot *n* must satisfy attribute test *delay-n*. *annul-true-n* is an attribute test that specifies which insns may be annulled if the branch is true. Similarly, *annul-false-n* specifies which insns in the delay slot may be annulled if the branch is false. If annulling is not supported for that delay slot, `(nil)` should be coded.

For example, in the common case where branch and call insns require a single delay slot, which may contain any insn other than a branch or call, the following would be placed in the '`md`' file:

```
(define_delay (eq_attr "type" "branch,call")
              [(eq_attr "type" "!branch,call") (nil) (nil)])
```

Multiple `define_delay` expressions may be specified. In this case, each such expression specifies different delay slot requirements and there must be no insn for which tests in two `define_delay` expressions are both true.

For example, if we have a machine that requires one delay slot for branches but two for calls, no delay slot can contain a branch or call insn, and any valid insn in the delay slot for the branch can be annulled if the branch is true, we might represent this as follows:

```
(define_delay (eq_attr "type" "branch")
   [(eq_attr "type" "!branch,call")
    (eq_attr "type" "!branch,call")
    (nil)])

(define_delay (eq_attr "type" "call")
              [(eq_attr "type" "!branch,call") (nil) (nil)
               (eq_attr "type" "!branch,call") (nil) (nil)])
```

16.19.9 Specifying processor pipeline description

To achieve better performance, most modern processors (super-pipelined, superscalar RISC, and VLIW processors) have many *functional units* on which several instructions can be executed simultaneously. An instruction starts execution if its issue conditions are satisfied. If not, the instruction is stalled until its conditions are satisfied. Such *interlock (pipeline) delay* causes interruption of the fetching of successor instructions (or demands nop instructions, e.g. for some MIPS processors).

There are two major kinds of interlock delays in modern processors. The first one is a data dependence delay determining *instruction latency time*. The instruction execution is not started until all source data have been evaluated by prior instructions (there are more complex cases when the instruction execution starts even when the data are not available but will be ready in given time after the instruction execution start). Taking the data dependence delays into account is simple. The data dependence (true, output, and anti-dependence) delay between two instructions is given by a constant. In most cases this approach is adequate. The second kind of interlock delays is a reservation delay. The reservation delay means that two instructions under execution will be in need of shared processors resources, i.e. buses, internal registers, and/or functional units, which are reserved for some time. Taking this kind of delay into account is complex especially for modern RISC processors.

The task of exploiting more processor parallelism is solved by an instruction scheduler. For a better solution to this problem, the instruction scheduler has to have an adequate description of the processor parallelism (or *pipeline description*). GCC machine descriptions describe processor parallelism and functional unit reservations for groups of instructions with the aid of *regular expressions*.

The GCC instruction scheduler uses a *pipeline hazard recognizer* to figure out the possibility of the instruction issue by the processor on a given simulated processor cycle. The pipeline hazard recognizer is automatically generated from the processor pipeline description. The pipeline hazard recognizer generated from the machine description is based on a deterministic finite state automaton (DFA): the instruction issue is possible if there is a transition from one automaton state to another one. This algorithm is very fast, and furthermore, its speed is not dependent on processor complexity[2].

The rest of this section describes the directives that constitute an automaton-based processor pipeline description. The order of these constructions within the machine description file is not important.

The following optional construction describes names of automata generated and used for the pipeline hazards recognition. Sometimes the generated finite state automaton used by the pipeline hazard recognizer is large. If we use more than one automaton and bind functional units to the automata, the total size of the automata is usually less than the size of the single automaton. If there is no one such construction, only one finite state automaton is generated.

```
(define_automaton automata-names)
```

[2] However, the size of the automaton depends on processor complexity. To limit this effect, machine descriptions can split orthogonal parts of the machine description among several automata: but then, since each of these must be stepped independently, this does cause a small decrease in the algorithm's performance.

automata-names is a string giving names of the automata. The names are separated by commas. All the automata should have unique names. The automaton name is used in the constructions `define_cpu_unit` and `define_query_cpu_unit`.

Each processor functional unit used in the description of instruction reservations should be described by the following construction.

```
(define_cpu_unit unit-names [automaton-name])
```

unit-names is a string giving the names of the functional units separated by commas. Don't use name '`nothing`', it is reserved for other goals.

automaton-name is a string giving the name of the automaton with which the unit is bound. The automaton should be described in construction `define_automaton`. You should give *automaton-name*, if there is a defined automaton.

The assignment of units to automata are constrained by the uses of the units in insn reservations. The most important constraint is: if a unit reservation is present on a particular cycle of an alternative for an insn reservation, then some unit from the same automaton must be present on the same cycle for the other alternatives of the insn reservation. The rest of the constraints are mentioned in the description of the subsequent constructions.

The following construction describes CPU functional units analogously to `define_cpu_unit`. The reservation of such units can be queried for an automaton state. The instruction scheduler never queries reservation of functional units for given automaton state. So as a rule, you don't need this construction. This construction could be used for future code generation goals (e.g. to generate VLIW insn templates).

```
(define_query_cpu_unit unit-names [automaton-name])
```

unit-names is a string giving names of the functional units separated by commas.

automaton-name is a string giving the name of the automaton with which the unit is bound.

The following construction is the major one to describe pipeline characteristics of an instruction.

```
(define_insn_reservation insn-name default_latency
                         condition regexp)
```

default_latency is a number giving latency time of the instruction. There is an important difference between the old description and the automaton based pipeline description. The latency time is used for all dependencies when we use the old description. In the automaton based pipeline description, the given latency time is only used for true dependencies. The cost of anti-dependencies is always zero and the cost of output dependencies is the difference between latency times of the producing and consuming insns (if the difference is negative, the cost is considered to be zero). You can always change the default costs for any description by using the target hook `TARGET_SCHED_ADJUST_COST` (see Section 17.18 [Scheduling], page 515).

insn-name is a string giving the internal name of the insn. The internal names are used in constructions `define_bypass` and in the automaton description file generated for debugging. The internal name has nothing in common with the names in `define_insn`. It is a good practice to use insn classes described in the processor manual.

condition defines what RTL insns are described by this construction. You should remember that you will be in trouble if *condition* for two or more different `define_insn_reservation` constructions is TRUE for an insn. In this case what reservation will be used

for the insn is not defined. Such cases are not checked during generation of the pipeline hazards recognizer because in general recognizing that two conditions may have the same value is quite difficult (especially if the conditions contain `symbol_ref`). It is also not checked during the pipeline hazard recognizer work because it would slow down the recognizer considerably.

regexp is a string describing the reservation of the cpu's functional units by the instruction. The reservations are described by a regular expression according to the following syntax:

```
regexp = regexp "," oneof
       | oneof

oneof = oneof "|" allof
      | allof

allof = allof "+" repeat
      | repeat

repeat = element "*" number
       | element

element = cpu_function_unit_name
        | reservation_name
        | result_name
        | "nothing"
        | "(" regexp ")"
```

- '`,`' is used for describing the start of the next cycle in the reservation.
- '`|`' is used for describing a reservation described by the first regular expression **or** a reservation described by the second regular expression **or** etc.
- '`+`' is used for describing a reservation described by the first regular expression **and** a reservation described by the second regular expression **and** etc.
- '`*`' is used for convenience and simply means a sequence in which the regular expression are repeated *number* times with cycle advancing (see '`,`').
- '`cpu_function_unit_name`' denotes reservation of the named functional unit.
- '`reservation_name`' — see description of construction '`define_reservation`'.
- '`nothing`' denotes no unit reservations.

Sometimes unit reservations for different insns contain common parts. In such case, you can simplify the pipeline description by describing the common part by the following construction

```
(define_reservation reservation-name regexp)
```

reservation-name is a string giving name of *regexp*. Functional unit names and reservation names are in the same name space. So the reservation names should be different from the functional unit names and can not be the reserved name '`nothing`'.

The following construction is used to describe exceptions in the latency time for given instruction pair. This is so called bypasses.

```
(define_bypass number out_insn_names in_insn_names
               [guard])
```

number defines when the result generated by the instructions given in string *out_insn_names* will be ready for the instructions given in string *in_insn_names*. Each of

these strings is a comma-separated list of filename-style globs and they refer to the names of `define_insn_reservation`s. For example:

```
(define_bypass 1 "cpu1_load_*, cpu1_store_*" "cpu1_load_*")
```

defines a bypass between instructions that start with '`cpu1_load_`' or '`cpu1_store_`' and those that start with '`cpu1_load_`'.

guard is an optional string giving the name of a C function which defines an additional guard for the bypass. The function will get the two insns as parameters. If the function returns zero the bypass will be ignored for this case. The additional guard is necessary to recognize complicated bypasses, e.g. when the consumer is only an address of insn '`store`' (not a stored value).

If there are more one bypass with the same output and input insns, the chosen bypass is the first bypass with a guard in description whose guard function returns nonzero. If there is no such bypass, then bypass without the guard function is chosen.

The following five constructions are usually used to describe VLIW processors, or more precisely, to describe a placement of small instructions into VLIW instruction slots. They can be used for RISC processors, too.

```
(exclusion_set unit-names unit-names)
(presence_set unit-names patterns)
(final_presence_set unit-names patterns)
(absence_set unit-names patterns)
(final_absence_set unit-names patterns)
```

unit-names is a string giving names of functional units separated by commas.

patterns is a string giving patterns of functional units separated by comma. Currently pattern is one unit or units separated by white-spaces.

The first construction ('`exclusion_set`') means that each functional unit in the first string can not be reserved simultaneously with a unit whose name is in the second string and vice versa. For example, the construction is useful for describing processors (e.g. some SPARC processors) with a fully pipelined floating point functional unit which can execute simultaneously only single floating point insns or only double floating point insns.

The second construction ('`presence_set`') means that each functional unit in the first string can not be reserved unless at least one of pattern of units whose names are in the second string is reserved. This is an asymmetric relation. For example, it is useful for description that VLIW '`slot1`' is reserved after '`slot0`' reservation. We could describe it by the following construction

```
(presence_set "slot1" "slot0")
```

Or '`slot1`' is reserved only after '`slot0`' and unit '`b0`' reservation. In this case we could write

```
(presence_set "slot1" "slot0 b0")
```

The third construction ('`final_presence_set`') is analogous to '`presence_set`'. The difference between them is when checking is done. When an instruction is issued in given automaton state reflecting all current and planned unit reservations, the automaton state is changed. The first state is a source state, the second one is a result state. Checking for '`presence_set`' is done on the source state reservation, checking for '`final_presence_set`' is done on the result reservation. This construction is useful to describe a reservation which is actually two subsequent reservations. For example, if we use

```
(presence_set "slot1" "slot0")
```

the following insn will be never issued (because '`slot1`' requires '`slot0`' which is absent in the source state).

```
(define_reservation "insn_and_nop" "slot0 + slot1")
```

but it can be issued if we use analogous '`final_presence_set`'.

The forth construction ('`absence_set`') means that each functional unit in the first string can be reserved only if each pattern of units whose names are in the second string is not reserved. This is an asymmetric relation (actually '`exclusion_set`' is analogous to this one but it is symmetric). For example it might be useful in a VLIW description to say that '`slot0`' cannot be reserved after either '`slot1`' or '`slot2`' have been reserved. This can be described as:

```
(absence_set "slot0" "slot1, slot2")
```

Or '`slot2`' can not be reserved if '`slot0`' and unit '`b0`' are reserved or '`slot1`' and unit '`b1`' are reserved. In this case we could write

```
(absence_set "slot2" "slot0 b0, slot1 b1")
```

All functional units mentioned in a set should belong to the same automaton.

The last construction ('`final_absence_set`') is analogous to '`absence_set`' but checking is done on the result (state) reservation. See comments for '`final_presence_set`'.

You can control the generator of the pipeline hazard recognizer with the following construction.

```
(automata_option options)
```

options is a string giving options which affect the generated code. Currently there are the following options:

- *no-minimization* makes no minimization of the automaton. This is only worth to do when we are debugging the description and need to look more accurately at reservations of states.
- *time* means printing time statistics about the generation of automata.
- *stats* means printing statistics about the generated automata such as the number of DFA states, NDFA states and arcs.
- *v* means a generation of the file describing the result automata. The file has suffix '`.dfa`' and can be used for the description verification and debugging.
- *w* means a generation of warning instead of error for non-critical errors.
- *no-comb-vect* prevents the automaton generator from generating two data structures and comparing them for space efficiency. Using a comb vector to represent transitions may be better, but it can be very expensive to construct. This option is useful if the build process spends an unacceptably long time in genautomata.
- *ndfa* makes nondeterministic finite state automata. This affects the treatment of operator '`|`' in the regular expressions. The usual treatment of the operator is to try the first alternative and, if the reservation is not possible, the second alternative. The nondeterministic treatment means trying all alternatives, some of them may be rejected by reservations in the subsequent insns.
- *collapse-ndfa* modifies the behaviour of the generator when producing an automaton. An additional state transition to collapse a nondeterministic NDFA state to a

deterministic DFA state is generated. It can be triggered by passing `const0_rtx` to state_transition. In such an automaton, cycle advance transitions are available only for these collapsed states. This option is useful for ports that want to use the `ndfa` option, but also want to use `define_query_cpu_unit` to assign units to insns issued in a cycle.

- *progress* means output of a progress bar showing how many states were generated so far for automaton being processed. This is useful during debugging a DFA description. If you see too many generated states, you could interrupt the generator of the pipeline hazard recognizer and try to figure out a reason for generation of the huge automaton.

As an example, consider a superscalar RISC machine which can issue three insns (two integer insns and one floating point insn) on the cycle but can finish only two insns. To describe this, we define the following functional units.

```
(define_cpu_unit "i0_pipeline, i1_pipeline, f_pipeline")
(define_cpu_unit "port0, port1")
```

All simple integer insns can be executed in any integer pipeline and their result is ready in two cycles. The simple integer insns are issued into the first pipeline unless it is reserved, otherwise they are issued into the second pipeline. Integer division and multiplication insns can be executed only in the second integer pipeline and their results are ready correspondingly in 8 and 4 cycles. The integer division is not pipelined, i.e. the subsequent integer division insn can not be issued until the current division insn finished. Floating point insns are fully pipelined and their results are ready in 3 cycles. Where the result of a floating point insn is used by an integer insn, an additional delay of one cycle is incurred. To describe all of this we could specify

```
(define_cpu_unit "div")

(define_insn_reservation "simple" 2 (eq_attr "type" "int")
                         "(i0_pipeline | i1_pipeline), (port0 | port1)")

(define_insn_reservation "mult" 4 (eq_attr "type" "mult")
                         "i1_pipeline, nothing*2, (port0 | port1)")

(define_insn_reservation "div" 8 (eq_attr "type" "div")
                         "i1_pipeline, div*7, div + (port0 | port1)")

(define_insn_reservation "float" 3 (eq_attr "type" "float")
                         "f_pipeline, nothing, (port0 | port1))

(define_bypass 4 "float" "simple,mult,div")
```

To simplify the description we could describe the following reservation

```
(define_reservation "finish" "port0|port1")
```

and use it in all `define_insn_reservation` as in the following construction

```
(define_insn_reservation "simple" 2 (eq_attr "type" "int")
                         "(i0_pipeline | i1_pipeline), finish")
```

16.20 Conditional Execution

A number of architectures provide for some form of conditional execution, or predication. The hallmark of this feature is the ability to nullify most of the instructions in the instruction set. When the instruction set is large and not entirely symmetric, it can be quite tedious

to describe these forms directly in the '.md' file. An alternative is the define_cond_exec template.

```
(define_cond_exec
  [predicate-pattern]
  "condition"
  "output-template"
  "optional-insn-attribues")
```

predicate-pattern is the condition that must be true for the insn to be executed at runtime and should match a relational operator. One can use match_operator to match several relational operators at once. Any match_operand operands must have no more than one alternative.

condition is a C expression that must be true for the generated pattern to match.

output-template is a string similar to the define_insn output template (see Section 16.5 [Output Template], page 303), except that the '*' and '@' special cases do not apply. This is only useful if the assembly text for the predicate is a simple prefix to the main insn. In order to handle the general case, there is a global variable current_insn_predicate that will contain the entire predicate if the current insn is predicated, and will otherwise be NULL.

optional-insn-attributes is an optional vector of attributes that gets appended to the insn attributes of the produced cond_exec rtx. It can be used to add some distinguishing attribute to cond_exec rtxs produced that way. An example usage would be to use this attribute in conjunction with attributes on the main pattern to disable particular alternatives under certain conditions.

When define_cond_exec is used, an implicit reference to the predicable instruction attribute is made. See Section 16.19 [Insn Attributes], page 394. This attribute must be a boolean (i.e. have exactly two elements in its *list-of-values*), with the possible values being no and yes. The default and all uses in the insns must be a simple constant, not a complex expressions. It may, however, depend on the alternative, by using a comma-separated list of values. If that is the case, the port should also define an enabled attribute (see Section 16.8.6 [Disable Insn Alternatives], page 345), which should also allow only no and yes as its values.

For each define_insn for which the predicable attribute is true, a new define_insn pattern will be generated that matches a predicated version of the instruction. For example,

```
(define_insn "addsi"
  [(set (match_operand:SI 0 "register_operand" "r")
        (plus:SI (match_operand:SI 1 "register_operand" "r")
                 (match_operand:SI 2 "register_operand" "r")))]
  "test1"
  "add %2,%1,%0")

(define_cond_exec
  [(ne (match_operand:CC 0 "register_operand" "c")
       (const_int 0))]
  "test2"
  "(%0)")
```

generates a new pattern

```
(define_insn ""
  [(cond_exec
     (ne (match_operand:CC 3 "register_operand" "c") (const_int 0))
     (set (match_operand:SI 0 "register_operand" "r")
```

```
            (plus:SI (match_operand:SI 1 "register_operand" "r")
                     (match_operand:SI 2 "register_operand" "r"))))]
    "(test2) && (test1)"
    "(%3) add %2,%1,%0")
```

16.21 RTL Templates Transformations

For some hardware architectures there are common cases when the RTL templates for the instructions can be derived from the other RTL templates using simple transformations. E.g., '`i386.md`' contains an RTL template for the ordinary `sub` instruction— `*subsi_1`, and for the `sub` instruction with subsequent zero-extension—`*subsi_1_zext`. Such cases can be easily implemented by a single meta-template capable of generating a modified case based on the initial one:

```
(define_subst "name"
  [input-template]
  "condition"
  [output-template])
```

input-template is a pattern describing the source RTL template, which will be transformed.

condition is a C expression that is conjunct with the condition from the input-template to generate a condition to be used in the output-template.

output-template is a pattern that will be used in the resulting template.

`define_subst` mechanism is tightly coupled with the notion of the subst attribute (see Section 16.23.4 [Subst Iterators], page 420). The use of `define_subst` is triggered by a reference to a subst attribute in the transforming RTL template. This reference initiates duplication of the source RTL template and substitution of the attributes with their values. The source RTL template is left unchanged, while the copy is transformed by `define_subst`. This transformation can fail in the case when the source RTL template is not matched against the input-template of the `define_subst`. In such case the copy is deleted.

`define_subst` can be used only in `define_insn` and `define_expand`, it cannot be used in other expressions (e.g. in `define_insn_and_split`).

16.21.1 `define_subst` Example

To illustrate how `define_subst` works, let us examine a simple template transformation.

Suppose there are two kinds of instructions: one that touches flags and the other that does not. The instructions of the second type could be generated with the following `define_subst`:

```
(define_subst "add_clobber_subst"
  [(set (match_operand:SI 0 "" "")
        (match_operand:SI 1 "" ""))]
  ""
  [(set (match_dup 0)
        (match_dup 1))
   (clobber (reg:CC FLAGS_REG))]
```

This `define_subst` can be applied to any RTL pattern containing `set` of mode SI and generates a copy with clobber when it is applied.

Assume there is an RTL template for a `max` instruction to be used in `define_subst` mentioned above:

```
(define_insn "maxsi"
  [(set (match_operand:SI 0 "register_operand" "=r")
        (max:SI
          (match_operand:SI 1 "register_operand" "r")
          (match_operand:SI 2 "register_operand" "r")))]
  ""
  "max\t{%2, %1, %0|%0, %1, %2}"
 [...])
```

To mark the RTL template for `define_subst` application, subst-attributes are used. They should be declared in advance:

```
(define_subst_attr "add_clobber_name" "add_clobber_subst" "_noclobber" "_clobber")
```

Here '`add_clobber_name`' is the attribute name, '`add_clobber_subst`' is the name of the corresponding `define_subst`, the third argument ('`_noclobber`') is the attribute value that would be substituted into the unchanged version of the source RTL template, and the last argument ('`_clobber`') is the value that would be substituted into the second, transformed, version of the RTL template.

Once the subst-attribute has been defined, it should be used in RTL templates which need to be processed by the `define_subst`. So, the original RTL template should be changed:

```
(define_insn "maxsi<add_clobber_name>"
  [(set (match_operand:SI 0 "register_operand" "=r")
        (max:SI
          (match_operand:SI 1 "register_operand" "r")
          (match_operand:SI 2 "register_operand" "r")))]
  ""
  "max\t{%2, %1, %0|%0, %1, %2}"
 [...])
```

The result of the `define_subst` usage would look like the following:

```
(define_insn "maxsi_noclobber"
  [(set (match_operand:SI 0 "register_operand" "=r")
        (max:SI
          (match_operand:SI 1 "register_operand" "r")
          (match_operand:SI 2 "register_operand" "r")))]
  ""
  "max\t{%2, %1, %0|%0, %1, %2}"
 [...])
(define_insn "maxsi_clobber"
  [(set (match_operand:SI 0 "register_operand" "=r")
        (max:SI
          (match_operand:SI 1 "register_operand" "r")
          (match_operand:SI 2 "register_operand" "r")))
   (clobber (reg:CC FLAGS_REG))]
  ""
  "max\t{%2, %1, %0|%0, %1, %2}"
 [...])
```

16.21.2 Pattern Matching in `define_subst`

All expressions, allowed in `define_insn` or `define_expand`, are allowed in the input-template of `define_subst`, except `match_par_dup`, `match_scratch`, `match_parallel`. The meanings of expressions in the input-template were changed:

`match_operand` matches any expression (possibly, a subtree in RTL-template), if modes of the `match_operand` and this expression are the same, or mode of the `match_operand`

is VOIDmode, or this expression is match_dup, match_op_dup. If the expression is match_operand too, and predicate of match_operand from the input pattern is not empty, then the predicates are compared. That can be used for more accurate filtering of accepted RTL-templates.

match_operator matches common operators (like plus, minus), unspec, unspec_volatile operators and match_operators from the original pattern if the modes match and match_operator from the input pattern has the same number of operands as the operator from the original pattern.

16.21.3 Generation of output template in define_subst

If all necessary checks for define_subst application pass, a new RTL-pattern, based on the output-template, is created to replace the old template. Like in input-patterns, meanings of some RTL expressions are changed when they are used in output-patterns of a define_subst. Thus, match_dup is used for copying the whole expression from the original pattern, which matched corresponding match_operand from the input pattern.

match_dup N is used in the output template to be replaced with the expression from the original pattern, which matched match_operand N from the input pattern. As a consequence, match_dup cannot be used to point to match_operands from the output pattern, it should always refer to a match_operand from the input pattern.

In the output template one can refer to the expressions from the original pattern and create new ones. For instance, some operands could be added by means of standard match_operand.

After replacing match_dup with some RTL-subtree from the original pattern, it could happen that several match_operands in the output pattern have the same indexes. It is unknown, how many and what indexes would be used in the expression which would replace match_dup, so such conflicts in indexes are inevitable. To overcome this issue, match_operands and match_operators, which were introduced into the output pattern, are renumerated when all match_dups are replaced.

Number of alternatives in match_operands introduced into the output template M could differ from the number of alternatives in the original pattern N, so in the resultant pattern there would be N*M alternatives. Thus, constraints from the original pattern would be duplicated N times, constraints from the output pattern would be duplicated M times, producing all possible combinations.

16.22 Constant Definitions

Using literal constants inside instruction patterns reduces legibility and can be a maintenance problem.

To overcome this problem, you may use the define_constants expression. It contains a vector of name-value pairs. From that point on, wherever any of the names appears in the MD file, it is as if the corresponding value had been written instead. You may use define_constants multiple times; each appearance adds more constants to the table. It is an error to redefine a constant with a different value.

To come back to the a29k load multiple example, instead of

```
(define_insn ""
  [(match_parallel 0 "load_multiple_operation"
```

```
        [(set (match_operand:SI 1 "gpc_reg_operand" "=r")
              (match_operand:SI 2 "memory_operand" "m"))
         (use (reg:SI 179))
         (clobber (reg:SI 179))])]
    ""
    "loadm 0,0,%1,%2")
```

You could write:

```
(define_constants [
    (R_BP 177)
    (R_FC 178)
    (R_CR 179)
    (R_Q  180)
])

(define_insn ""
  [(match_parallel 0 "load_multiple_operation"
     [(set (match_operand:SI 1 "gpc_reg_operand" "=r")
           (match_operand:SI 2 "memory_operand" "m"))
      (use (reg:SI R_CR))
      (clobber (reg:SI R_CR))])]
  ""
  "loadm 0,0,%1,%2")
```

The constants that are defined with a define_constant are also output in the insn-codes.h header file as #defines.

You can also use the machine description file to define enumerations. Like the constants defined by `define_constant`, these enumerations are visible to both the machine description file and the main C code.

The syntax is as follows:

```
(define_c_enum "name" [
  value0
  value1
  ...
  valuen
])
```

This definition causes the equivalent of the following C code to appear in '`insn-constants.h`':

```
enum name {
  value0 = 0,
  value1 = 1,
  ...
  valuen = n
};
#define NUM_cname_VALUES (n + 1)
```

where *cname* is the capitalized form of *name*. It also makes each *valuei* available in the machine description file, just as if it had been declared with:

```
(define_constants [(valuei i)])
```

Each *valuei* is usually an upper-case identifier and usually begins with *cname*.

You can split the enumeration definition into as many statements as you like. The above example is directly equivalent to:

```
(define_c_enum "name" [value0])
(define_c_enum "name" [value1])
```

```
...
(define_c_enum "name" [valuen])
```

Splitting the enumeration helps to improve the modularity of each individual `.md` file. For example, if a port defines its synchronization instructions in a separate '`sync.md`' file, it is convenient to define all synchronization-specific enumeration values in '`sync.md`' rather than in the main '`.md`' file.

Some enumeration names have special significance to GCC:

`unspecv` If an enumeration called `unspecv` is defined, GCC will use it when printing out `unspec_volatile` expressions. For example:

```
(define_c_enum "unspecv" [
  UNSPECV_BLOCKAGE
])
```

causes GCC to print '`(unspec_volatile ... 0)`' as:

```
(unspec_volatile ... UNSPECV_BLOCKAGE)
```

`unspec` If an enumeration called `unspec` is defined, GCC will use it when printing out `unspec` expressions. GCC will also use it when printing out `unspec_volatile` expressions unless an `unspecv` enumeration is also defined. You can therefore decide whether to keep separate enumerations for volatile and non-volatile expressions or whether to use the same enumeration for both.

Another way of defining an enumeration is to use `define_enum`:

```
(define_enum "name" [
  value0
  value1
  ...
  valuen
])
```

This directive implies:

```
(define_c_enum "name" [
  cname_cvalue0
  cname_cvalue1
  ...
  cname_cvaluen
])
```

where *cvaluei* is the capitalized form of *valuei*. However, unlike `define_c_enum`, the enumerations defined by `define_enum` can be used in attribute specifications (see [define_enum_attr], page 395).

16.23 Iterators

Ports often need to define similar patterns for more than one machine mode or for more than one rtx code. GCC provides some simple iterator facilities to make this process easier.

16.23.1 Mode Iterators

Ports often need to define similar patterns for two or more different modes. For example:

- If a processor has hardware support for both single and double floating-point arithmetic, the `SFmode` patterns tend to be very similar to the `DFmode` ones.

- If a port uses `SImode` pointers in one configuration and `DImode` pointers in another, it will usually have very similar `SImode` and `DImode` patterns for manipulating pointers.

Mode iterators allow several patterns to be instantiated from one '`.md`' file template. They can be used with any type of rtx-based construct, such as a `define_insn`, `define_split`, or `define_peephole2`.

16.23.1.1 Defining Mode Iterators

The syntax for defining a mode iterator is:

```
(define_mode_iterator name [(mode1 "cond1") ... (moden "condn")])
```

This allows subsequent '`.md`' file constructs to use the mode suffix `:name`. Every construct that does so will be expanded *n* times, once with every use of `:name` replaced by `:mode1`, once with every use replaced by `:mode2`, and so on. In the expansion for a particular *modei*, every C condition will also require that *condi* be true.

For example:

```
(define_mode_iterator P [(SI "Pmode == SImode") (DI "Pmode == DImode")])
```

defines a new mode suffix `:P`. Every construct that uses `:P` will be expanded twice, once with every `:P` replaced by `:SI` and once with every `:P` replaced by `:DI`. The `:SI` version will only apply if `Pmode == SImode` and the `:DI` version will only apply if `Pmode == DImode`.

As with other '`.md`' conditions, an empty string is treated as "always true". `(mode "")` can also be abbreviated to `mode`. For example:

```
(define_mode_iterator GPR [SI (DI "TARGET_64BIT")])
```

means that the `:DI` expansion only applies if `TARGET_64BIT` but that the `:SI` expansion has no such constraint.

Iterators are applied in the order they are defined. This can be significant if two iterators are used in a construct that requires substitutions. See Section 16.23.1.2 [Substitutions], page 416.

16.23.1.2 Substitution in Mode Iterators

If an '`.md`' file construct uses mode iterators, each version of the construct will often need slightly different strings or modes. For example:

- When a `define_expand` defines several `add`*m*`3` patterns (see Section 16.9 [Standard Names], page 349), each expander will need to use the appropriate mode name for *m*.
- When a `define_insn` defines several instruction patterns, each instruction will often use a different assembler mnemonic.
- When a `define_insn` requires operands with different modes, using an iterator for one of the operand modes usually requires a specific mode for the other operand(s).

GCC supports such variations through a system of "mode attributes". There are two standard attributes: `mode`, which is the name of the mode in lower case, and `MODE`, which is the same thing in upper case. You can define other attributes using:

```
(define_mode_attr name [(mode1 "value1") ... (moden "valuen")])
```

where *name* is the name of the attribute and *valuei* is the value associated with *modei*.

When GCC replaces some *:iterator* with *:mode*, it will scan each string and mode in the pattern for sequences of the form `<iterator:attr>`, where *attr* is the name of a mode

attribute. If the attribute is defined for *mode*, the whole `<...>` sequence will be replaced by the appropriate attribute value.

For example, suppose an '`.md`' file has:

```
(define_mode_iterator P [(SI "Pmode == SImode") (DI "Pmode == DImode")])
(define_mode_attr load [(SI "lw") (DI "ld")])
```

If one of the patterns that uses `:P` contains the string `"<P:load>\t%0,%1"`, the `SI` version of that pattern will use `"lw\t%0,%1"` and the `DI` version will use `"ld\t%0,%1"`.

Here is an example of using an attribute for a mode:

```
(define_mode_iterator LONG [SI DI])
(define_mode_attr SHORT [(SI "HI") (DI "SI")])
(define_insn ...
  (sign_extend:LONG (match_operand:<LONG:SHORT> ...)) ...)
```

The *`iterator`*`:` prefix may be omitted, in which case the substitution will be attempted for every iterator expansion.

16.23.1.3 Mode Iterator Examples

Here is an example from the MIPS port. It defines the following modes and attributes (among others):

```
(define_mode_iterator GPR [SI (DI "TARGET_64BIT")])
(define_mode_attr d [(SI "") (DI "d")])
```

and uses the following template to define both `subsi3` and `subdi3`:

```
(define_insn "sub<mode>3"
  [(set (match_operand:GPR 0 "register_operand" "=d")
        (minus:GPR (match_operand:GPR 1 "register_operand" "d")
                   (match_operand:GPR 2 "register_operand" "d")))]
  ""
  "<d>subu\t%0,%1,%2"
  [(set_attr "type" "arith")
   (set_attr "mode" "<MODE>")])
```

This is exactly equivalent to:

```
(define_insn "subsi3"
  [(set (match_operand:SI 0 "register_operand" "=d")
        (minus:SI (match_operand:SI 1 "register_operand" "d")
                  (match_operand:SI 2 "register_operand" "d")))]
  ""
  "subu\t%0,%1,%2"
  [(set_attr "type" "arith")
   (set_attr "mode" "SI")])

(define_insn "subdi3"
  [(set (match_operand:DI 0 "register_operand" "=d")
        (minus:DI (match_operand:DI 1 "register_operand" "d")
                  (match_operand:DI 2 "register_operand" "d")))]
  ""
  "dsubu\t%0,%1,%2"
  [(set_attr "type" "arith")
   (set_attr "mode" "DI")])
```

16.23.2 Code Iterators

Code iterators operate in a similar way to mode iterators. See Section 16.23.1 [Mode Iterators], page 415.

The construct:

```
(define_code_iterator name [(code1 "cond1") ... (coden "condn")])
```

defines a pseudo rtx code *name* that can be instantiated as *codei* if condition *condi* is true. Each *codei* must have the same rtx format. See Section 13.2 [RTL Classes], page 224.

As with mode iterators, each pattern that uses *name* will be expanded *n* times, once with all uses of *name* replaced by *code1*, once with all uses replaced by *code2*, and so on. See Section 16.23.1.1 [Defining Mode Iterators], page 416.

It is possible to define attributes for codes as well as for modes. There are two standard code attributes: `code`, the name of the code in lower case, and `CODE`, the name of the code in upper case. Other attributes are defined using:

```
(define_code_attr name [(code1 "value1") ... (coden "valuen")])
```

Here's an example of code iterators in action, taken from the MIPS port:

```
(define_code_iterator any_cond [unordered ordered unlt unge uneq ltgt unle ungt
                                eq ne gt ge lt le gtu geu ltu leu])

(define_expand "b<code>"
  [(set (pc)
        (if_then_else (any_cond:CC (cc0)
                                   (const_int 0))
                      (label_ref (match_operand 0 ""))
                      (pc)))]
  ""
{
  gen_conditional_branch (operands, <CODE>);
  DONE;
})
```

This is equivalent to:

```
(define_expand "bunordered"
  [(set (pc)
        (if_then_else (unordered:CC (cc0)
                                    (const_int 0))
                      (label_ref (match_operand 0 ""))
                      (pc)))]
  ""
{
  gen_conditional_branch (operands, UNORDERED);
  DONE;
})

(define_expand "bordered"
  [(set (pc)
        (if_then_else (ordered:CC (cc0)
                                  (const_int 0))
                      (label_ref (match_operand 0 ""))
                      (pc)))]
  ""
{
  gen_conditional_branch (operands, ORDERED);
  DONE;
})

...
```

16.23.3 Int Iterators

Int iterators operate in a similar way to code iterators. See Section 16.23.2 [Code Iterators], page 417.

The construct:

```
(define_int_iterator name [(int1 "cond1") ... (intn "condn")])
```

defines a pseudo integer constant *name* that can be instantiated as *inti* if condition *condi* is true. Each *int* must have the same rtx format. See Section 13.2 [RTL Classes], page 224. Int iterators can appear in only those rtx fields that have 'i' as the specifier. This means that each *int* has to be a constant defined using define_constant or define_c_enum.

As with mode and code iterators, each pattern that uses *name* will be expanded *n* times, once with all uses of *name* replaced by *int1*, once with all uses replaced by *int2*, and so on. See Section 16.23.1.1 [Defining Mode Iterators], page 416.

It is possible to define attributes for ints as well as for codes and modes. Attributes are defined using:

```
(define_int_attr name [(int1 "value1") ... (intn "valuen")])
```

Here's an example of int iterators in action, taken from the ARM port:

```
(define_int_iterator QABSNEG [UNSPEC_VQABS UNSPEC_VQNEG])

(define_int_attr absneg [(UNSPEC_VQABS "abs") (UNSPEC_VQNEG "neg")])

(define_insn "neon_vq<absneg><mode>"
  [(set (match_operand:VDQIW 0 "s_register_operand" "=w")
(unspec:VDQIW [(match_operand:VDQIW 1 "s_register_operand" "w")
       (match_operand:SI 2 "immediate_operand" "i")]
      QABSNEG))]
  "TARGET_NEON"
  "vq<absneg>.<V_s_elem>\t%<V_reg>0, %<V_reg>1"
  [(set_attr "type" "neon_vqneg_vqabs")]
)
```

This is equivalent to:

```
(define_insn "neon_vqabs<mode>"
  [(set (match_operand:VDQIW 0 "s_register_operand" "=w")
(unspec:VDQIW [(match_operand:VDQIW 1 "s_register_operand" "w")
       (match_operand:SI 2 "immediate_operand" "i")]
      UNSPEC_VQABS))]
  "TARGET_NEON"
  "vqabs.<V_s_elem>\t%<V_reg>0, %<V_reg>1"
  [(set_attr "type" "neon_vqneg_vqabs")]
)

(define_insn "neon_vqneg<mode>"
  [(set (match_operand:VDQIW 0 "s_register_operand" "=w")
(unspec:VDQIW [(match_operand:VDQIW 1 "s_register_operand" "w")
       (match_operand:SI 2 "immediate_operand" "i")]
      UNSPEC_VQNEG))]
  "TARGET_NEON"
  "vqneg.<V_s_elem>\t%<V_reg>0, %<V_reg>1"
  [(set_attr "type" "neon_vqneg_vqabs")]
)
```

16.23.4 Subst Iterators

Subst iterators are special type of iterators with the following restrictions: they could not be declared explicitly, they always have only two values, and they do not have explicit dedicated name. Subst-iterators are triggered only when corresponding subst-attribute is used in RTL-pattern.

Subst iterators transform templates in the following way: the templates are duplicated, the subst-attributes in these templates are replaced with the corresponding values, and a new attribute is implicitly added to the given `define_insn`/`define_expand`. The name of the added attribute matches the name of `define_subst`. Such attributes are declared implicitly, and it is not allowed to have a `define_attr` named as a `define_subst`.

Each subst iterator is linked to a `define_subst`. It is declared implicitly by the first appearance of the corresponding `define_subst_attr`, and it is not allowed to define it explicitly.

Declarations of subst-attributes have the following syntax:

```
(define_subst_attr "name"
  "subst-name"
  "no-subst-value"
  "subst-applied-value")
```

name is a string with which the given subst-attribute could be referred to.

subst-name shows which `define_subst` should be applied to an RTL-template if the given subst-attribute is present in the RTL-template.

no-subst-value is a value with which subst-attribute would be replaced in the first copy of the original RTL-template.

subst-applied-value is a value with which subst-attribute would be replaced in the second copy of the original RTL-template.

17 Target Description Macros and Functions

In addition to the file '*machine*.md', a machine description includes a C header file conventionally given the name '*machine*.h' and a C source file named '*machine*.c'. The header file defines numerous macros that convey the information about the target machine that does not fit into the scheme of the '.md' file. The file 'tm.h' should be a link to '*machine*.h'. The header file 'config.h' includes 'tm.h' and most compiler source files include 'config.h'. The source file defines a variable targetm, which is a structure containing pointers to functions and data relating to the target machine. '*machine*.c' should also contain their definitions, if they are not defined elsewhere in GCC, and other functions called through the macros defined in the '.h' file.

17.1 The Global targetm Variable

struct gcc_target targetm [Variable]

The target '.c' file must define the global targetm variable which contains pointers to functions and data relating to the target machine. The variable is declared in 'target.h'; 'target-def.h' defines the macro TARGET_INITIALIZER which is used to initialize the variable, and macros for the default initializers for elements of the structure. The '.c' file should override those macros for which the default definition is inappropriate. For example:

```
#include "target.h"
#include "target-def.h"

/* Initialize the GCC target structure.  */

#undef TARGET_COMP_TYPE_ATTRIBUTES
#define TARGET_COMP_TYPE_ATTRIBUTES machine_comp_type_attributes

struct gcc_target targetm = TARGET_INITIALIZER;
```

Where a macro should be defined in the '.c' file in this manner to form part of the targetm structure, it is documented below as a "Target Hook" with a prototype. Many macros will change in future from being defined in the '.h' file to being part of the targetm structure.

Similarly, there is a targetcm variable for hooks that are specific to front ends for C-family languages, documented as "C Target Hook". This is declared in 'c-family/c-target.h', the initializer TARGETCM_INITIALIZER in 'c-family/c-target-def.h'. If targets initialize targetcm themselves, they should set target_has_targetcm=yes in 'config.gcc'; otherwise a default definition is used.

Similarly, there is a targetm_common variable for hooks that are shared between the compiler driver and the compilers proper, documented as "Common Target Hook". This is declared in 'common/common-target.h', the initializer TARGETM_COMMON_INITIALIZER in 'common/common-target-def.h'. If targets initialize targetm_common themselves, they should set target_has_targetm_common=yes in 'config.gcc'; otherwise a default definition is used.

17.2 Controlling the Compilation Driver, 'gcc'

You can control the compilation driver.

DRIVER_SELF_SPECS [Macro]

A list of specs for the driver itself. It should be a suitable initializer for an array of strings, with no surrounding braces.

The driver applies these specs to its own command line between loading default 'specs' files (but not command-line specified ones) and choosing the multilib directory or running any subcommands. It applies them in the order given, so each spec can depend on the options added by earlier ones. It is also possible to remove options using '%<*option*' in the usual way.

This macro can be useful when a port has several interdependent target options. It provides a way of standardizing the command line so that the other specs are easier to write.

Do not define this macro if it does not need to do anything.

OPTION_DEFAULT_SPECS [Macro]

A list of specs used to support configure-time default options (i.e. '--with' options) in the driver. It should be a suitable initializer for an array of structures, each containing two strings, without the outermost pair of surrounding braces.

The first item in the pair is the name of the default. This must match the code in 'config.gcc' for the target. The second item is a spec to apply if a default with this name was specified. The string '%(VALUE)' in the spec will be replaced by the value of the default everywhere it occurs.

The driver will apply these specs to its own command line between loading default 'specs' files and processing DRIVER_SELF_SPECS, using the same mechanism as DRIVER_SELF_SPECS.

Do not define this macro if it does not need to do anything.

CPP_SPEC [Macro]

A C string constant that tells the GCC driver program options to pass to CPP. It can also specify how to translate options you give to GCC into options for GCC to pass to the CPP.

Do not define this macro if it does not need to do anything.

CPLUSPLUS_CPP_SPEC [Macro]

This macro is just like CPP_SPEC, but is used for C++, rather than C. If you do not define this macro, then the value of CPP_SPEC (if any) will be used instead.

CC1_SPEC [Macro]

A C string constant that tells the GCC driver program options to pass to cc1, cc1plus, f771, and the other language front ends. It can also specify how to translate options you give to GCC into options for GCC to pass to front ends.

Do not define this macro if it does not need to do anything.

`CC1PLUS_SPEC` [Macro]

A C string constant that tells the GCC driver program options to pass to `cc1plus`. It can also specify how to translate options you give to GCC into options for GCC to pass to the `cc1plus`.

Do not define this macro if it does not need to do anything. Note that everything defined in CC1_SPEC is already passed to `cc1plus` so there is no need to duplicate the contents of CC1_SPEC in CC1PLUS_SPEC.

`ASM_SPEC` [Macro]

A C string constant that tells the GCC driver program options to pass to the assembler. It can also specify how to translate options you give to GCC into options for GCC to pass to the assembler. See the file '`sun3.h`' for an example of this.

Do not define this macro if it does not need to do anything.

`ASM_FINAL_SPEC` [Macro]

A C string constant that tells the GCC driver program how to run any programs which cleanup after the normal assembler. Normally, this is not needed. See the file '`mips.h`' for an example of this.

Do not define this macro if it does not need to do anything.

`AS_NEEDS_DASH_FOR_PIPED_INPUT` [Macro]

Define this macro, with no value, if the driver should give the assembler an argument consisting of a single dash, '`-`', to instruct it to read from its standard input (which will be a pipe connected to the output of the compiler proper). This argument is given after any '`-o`' option specifying the name of the output file.

If you do not define this macro, the assembler is assumed to read its standard input if given no non-option arguments. If your assembler cannot read standard input at all, use a '`%{pipe:%e}`' construct; see '`mips.h`' for instance.

`LINK_SPEC` [Macro]

A C string constant that tells the GCC driver program options to pass to the linker. It can also specify how to translate options you give to GCC into options for GCC to pass to the linker.

Do not define this macro if it does not need to do anything.

`LIB_SPEC` [Macro]

Another C string constant used much like `LINK_SPEC`. The difference between the two is that `LIB_SPEC` is used at the end of the command given to the linker.

If this macro is not defined, a default is provided that loads the standard C library from the usual place. See '`gcc.c`'.

`LIBGCC_SPEC` [Macro]

Another C string constant that tells the GCC driver program how and when to place a reference to '`libgcc.a`' into the linker command line. This constant is placed both before and after the value of `LIB_SPEC`.

If this macro is not defined, the GCC driver provides a default that passes the string '`-lgcc`' to the linker.

REAL_LIBGCC_SPEC [Macro]

By default, if ENABLE_SHARED_LIBGCC is defined, the LIBGCC_SPEC is not directly used by the driver program but is instead modified to refer to different versions of 'libgcc.a' depending on the values of the command line flags '-static', '-shared', '-static-libgcc', and '-shared-libgcc'. On targets where these modifications are inappropriate, define REAL_LIBGCC_SPEC instead. REAL_LIBGCC_SPEC tells the driver how to place a reference to 'libgcc' on the link command line, but, unlike LIBGCC_SPEC, it is used unmodified.

USE_LD_AS_NEEDED [Macro]

A macro that controls the modifications to LIBGCC_SPEC mentioned in REAL_LIBGCC_SPEC. If nonzero, a spec will be generated that uses '--as-needed' or equivalent options and the shared 'libgcc' in place of the static exception handler library, when linking without any of -static, -static-libgcc, or -shared-libgcc.

LINK_EH_SPEC [Macro]

If defined, this C string constant is added to LINK_SPEC. When USE_LD_AS_NEEDED is zero or undefined, it also affects the modifications to LIBGCC_SPEC mentioned in REAL_LIBGCC_SPEC.

STARTFILE_SPEC [Macro]

Another C string constant used much like LINK_SPEC. The difference between the two is that STARTFILE_SPEC is used at the very beginning of the command given to the linker.

If this macro is not defined, a default is provided that loads the standard C startup file from the usual place. See 'gcc.c'.

ENDFILE_SPEC [Macro]

Another C string constant used much like LINK_SPEC. The difference between the two is that ENDFILE_SPEC is used at the very end of the command given to the linker.

Do not define this macro if it does not need to do anything.

THREAD_MODEL_SPEC [Macro]

GCC -v will print the thread model GCC was configured to use. However, this doesn't work on platforms that are multilibbed on thread models, such as AIX 4.3. On such platforms, define THREAD_MODEL_SPEC such that it evaluates to a string without blanks that names one of the recognized thread models. %*, the default value of this macro, will expand to the value of thread_file set in 'config.gcc'.

SYSROOT_SUFFIX_SPEC [Macro]

Define this macro to add a suffix to the target sysroot when GCC is configured with a sysroot. This will cause GCC to search for usr/lib, et al, within sysroot+suffix.

SYSROOT_HEADERS_SUFFIX_SPEC [Macro]

Define this macro to add a headers_suffix to the target sysroot when GCC is configured with a sysroot. This will cause GCC to pass the updated sysroot+headers_suffix to CPP, causing it to search for usr/include, et al, within sysroot+headers_suffix.

EXTRA_SPECS [Macro]

Define this macro to provide additional specifications to put in the 'specs' file that can be used in various specifications like CC1_SPEC.

The definition should be an initializer for an array of structures, containing a string constant, that defines the specification name, and a string constant that provides the specification.

Do not define this macro if it does not need to do anything.

EXTRA_SPECS is useful when an architecture contains several related targets, which have various ..._SPECS which are similar to each other, and the maintainer would like one central place to keep these definitions.

For example, the PowerPC System V.4 targets use EXTRA_SPECS to define either _CALL_SYSV when the System V calling sequence is used or _CALL_AIX when the older AIX-based calling sequence is used.

The 'config/rs6000/rs6000.h' target file defines:

```
#define EXTRA_SPECS \
  { "cpp_sysv_default", CPP_SYSV_DEFAULT },

#define CPP_SYS_DEFAULT ""
```

The 'config/rs6000/sysv.h' target file defines:

```
#undef CPP_SPEC
#define CPP_SPEC \
"%{posix: -D_POSIX_SOURCE } \
%{mcall-sysv: -D_CALL_SYSV } \
%{!mcall-sysv: %(cpp_sysv_default) } \
%{msoft-float: -D_SOFT_FLOAT} %{mcpu=403: -D_SOFT_FLOAT}"

#undef CPP_SYSV_DEFAULT
#define CPP_SYSV_DEFAULT "-D_CALL_SYSV"
```

while the 'config/rs6000/eabiaix.h' target file defines CPP_SYSV_DEFAULT as:

```
#undef CPP_SYSV_DEFAULT
#define CPP_SYSV_DEFAULT "-D_CALL_AIX"
```

LINK_LIBGCC_SPECIAL_1 [Macro]

Define this macro if the driver program should find the library 'libgcc.a'. If you do not define this macro, the driver program will pass the argument '-lgcc' to tell the linker to do the search.

LINK_GCC_C_SEQUENCE_SPEC [Macro]

The sequence in which libgcc and libc are specified to the linker. By default this is %G %L %G.

LINK_COMMAND_SPEC [Macro]

A C string constant giving the complete command line need to execute the linker. When you do this, you will need to update your port each time a change is made to the link command line within 'gcc.c'. Therefore, define this macro only if you need to completely redefine the command line for invoking the linker and there is no other way to accomplish the effect you need. Overriding this macro may be avoidable by overriding LINK_GCC_C_SEQUENCE_SPEC instead.

`bool TARGET_ALWAYS_STRIP_DOTDOT` [Common Target Hook]

True if '`..`' components should always be removed from directory names computed relative to GCC's internal directories, false (default) if such components should be preserved and directory names containing them passed to other tools such as the linker.

`MULTILIB_DEFAULTS` [Macro]

Define this macro as a C expression for the initializer of an array of string to tell the driver program which options are defaults for this target and thus do not need to be handled specially when using `MULTILIB_OPTIONS`.

Do not define this macro if `MULTILIB_OPTIONS` is not defined in the target makefile fragment or if none of the options listed in `MULTILIB_OPTIONS` are set by default. See Section 19.1 [Target Fragment], page 595.

`RELATIVE_PREFIX_NOT_LINKDIR` [Macro]

Define this macro to tell `gcc` that it should only translate a '`-B`' prefix into a '`-L`' linker option if the prefix indicates an absolute file name.

`MD_EXEC_PREFIX` [Macro]

If defined, this macro is an additional prefix to try after `STANDARD_EXEC_PREFIX`. `MD_EXEC_PREFIX` is not searched when the compiler is built as a cross compiler. If you define `MD_EXEC_PREFIX`, then be sure to add it to the list of directories used to find the assembler in '`configure.in`'.

`STANDARD_STARTFILE_PREFIX` [Macro]

Define this macro as a C string constant if you wish to override the standard choice of `libdir` as the default prefix to try when searching for startup files such as '`crt0.o`'. `STANDARD_STARTFILE_PREFIX` is not searched when the compiler is built as a cross compiler.

`STANDARD_STARTFILE_PREFIX_1` [Macro]

Define this macro as a C string constant if you wish to override the standard choice of `/lib` as a prefix to try after the default prefix when searching for startup files such as '`crt0.o`'. `STANDARD_STARTFILE_PREFIX_1` is not searched when the compiler is built as a cross compiler.

`STANDARD_STARTFILE_PREFIX_2` [Macro]

Define this macro as a C string constant if you wish to override the standard choice of `/lib` as yet another prefix to try after the default prefix when searching for startup files such as '`crt0.o`'. `STANDARD_STARTFILE_PREFIX_2` is not searched when the compiler is built as a cross compiler.

`MD_STARTFILE_PREFIX` [Macro]

If defined, this macro supplies an additional prefix to try after the standard prefixes. `MD_EXEC_PREFIX` is not searched when the compiler is built as a cross compiler.

`MD_STARTFILE_PREFIX_1` [Macro]

If defined, this macro supplies yet another prefix to try after the standard prefixes. It is not searched when the compiler is built as a cross compiler.

INIT_ENVIRONMENT [Macro]

Define this macro as a C string constant if you wish to set environment variables for programs called by the driver, such as the assembler and loader. The driver passes the value of this macro to `putenv` to initialize the necessary environment variables.

LOCAL_INCLUDE_DIR [Macro]

Define this macro as a C string constant if you wish to override the standard choice of '`/usr/local/include`' as the default prefix to try when searching for local header files. `LOCAL_INCLUDE_DIR` comes before `NATIVE_SYSTEM_HEADER_DIR` (set in '`config.gcc`', normally '`/usr/include`') in the search order.

Cross compilers do not search either '`/usr/local/include`' or its replacement.

NATIVE_SYSTEM_HEADER_COMPONENT [Macro]

The "component" corresponding to `NATIVE_SYSTEM_HEADER_DIR`. See `INCLUDE_DEFAULTS`, below, for the description of components. If you do not define this macro, no component is used.

INCLUDE_DEFAULTS [Macro]

Define this macro if you wish to override the entire default search path for include files. For a native compiler, the default search path usually consists of `GCC_INCLUDE_DIR`, `LOCAL_INCLUDE_DIR`, `GPLUSPLUS_INCLUDE_DIR`, and `NATIVE_SYSTEM_HEADER_DIR`. In addition, `GPLUSPLUS_INCLUDE_DIR` and `GCC_INCLUDE_DIR` are defined automatically by '`Makefile`', and specify private search areas for GCC. The directory `GPLUSPLUS_INCLUDE_DIR` is used only for C++ programs.

The definition should be an initializer for an array of structures. Each array element should have four elements: the directory name (a string constant), the component name (also a string constant), a flag for C++-only directories, and a flag showing that the includes in the directory don't need to be wrapped in `extern 'C'` when compiling C++. Mark the end of the array with a null element.

The component name denotes what GNU package the include file is part of, if any, in all uppercase letters. For example, it might be '`GCC`' or '`BINUTILS`'. If the package is part of a vendor-supplied operating system, code the component name as '`0`'.

For example, here is the definition used for VAX/VMS:

```
#define INCLUDE_DEFAULTS \
{                                       \
  { "GNU_GXX_INCLUDE:", "G++", 1, 1},   \
  { "GNU_CC_INCLUDE:", "GCC", 0, 0},    \
  { "SYS$SYSROOT:[SYSLIB.]", 0, 0, 0},  \
  { ".", 0, 0, 0},                      \
  { 0, 0, 0, 0}                         \
}
```

Here is the order of prefixes tried for exec files:

1. Any prefixes specified by the user with '`-B`'.
2. The environment variable `GCC_EXEC_PREFIX` or, if `GCC_EXEC_PREFIX` is not set and the compiler has not been installed in the configure-time *prefix*, the location in which the compiler has actually been installed.
3. The directories specified by the environment variable `COMPILER_PATH`.

4. The macro STANDARD_EXEC_PREFIX, if the compiler has been installed in the configured-time *prefix*.
5. The location '/usr/libexec/gcc/', but only if this is a native compiler.
6. The location '/usr/lib/gcc/', but only if this is a native compiler.
7. The macro MD_EXEC_PREFIX, if defined, but only if this is a native compiler.

Here is the order of prefixes tried for startfiles:

1. Any prefixes specified by the user with '-B'.
2. The environment variable GCC_EXEC_PREFIX or its automatically determined value based on the installed toolchain location.
3. The directories specified by the environment variable LIBRARY_PATH (or port-specific name; native only, cross compilers do not use this).
4. The macro STANDARD_EXEC_PREFIX, but only if the toolchain is installed in the configured *prefix* or this is a native compiler.
5. The location '/usr/lib/gcc/', but only if this is a native compiler.
6. The macro MD_EXEC_PREFIX, if defined, but only if this is a native compiler.
7. The macro MD_STARTFILE_PREFIX, if defined, but only if this is a native compiler, or we have a target system root.
8. The macro MD_STARTFILE_PREFIX_1, if defined, but only if this is a native compiler, or we have a target system root.
9. The macro STANDARD_STARTFILE_PREFIX, with any sysroot modifications. If this path is relative it will be prefixed by GCC_EXEC_PREFIX and the machine suffix or STANDARD_EXEC_PREFIX and the machine suffix.
10. The macro STANDARD_STARTFILE_PREFIX_1, but only if this is a native compiler, or we have a target system root. The default for this macro is '/lib/'.
11. The macro STANDARD_STARTFILE_PREFIX_2, but only if this is a native compiler, or we have a target system root. The default for this macro is '/usr/lib/'.

17.3 Run-time Target Specification

Here are run-time target specifications.

TARGET_CPU_CPP_BUILTINS () [Macro]

This function-like macro expands to a block of code that defines built-in preprocessor macros and assertions for the target CPU, using the functions builtin_define, builtin_define_std and builtin_assert. When the front end calls this macro it provides a trailing semicolon, and since it has finished command line option processing your code can use those results freely.

builtin_assert takes a string in the form you pass to the command-line option '-A', such as cpu=mips, and creates the assertion. builtin_define takes a string in the form accepted by option '-D' and unconditionally defines the macro.

builtin_define_std takes a string representing the name of an object-like macro. If it doesn't lie in the user's namespace, builtin_define_std defines it unconditionally. Otherwise, it defines a version with two leading underscores, and another version with two leading and trailing underscores, and defines the original only if an ISO standard

was not requested on the command line. For example, passing `unix` defines `__unix`, `__unix__` and possibly `unix`; passing `_mips` defines `__mips`, `__mips__` and possibly `_mips`, and passing `_ABI64` defines only `_ABI64`.

You can also test for the C dialect being compiled. The variable `c_language` is set to one of `clk_c`, `clk_cplusplus` or `clk_objective_c`. Note that if we are preprocessing assembler, this variable will be `clk_c` but the function-like macro `preprocessing_asm_p()` will return true, so you might want to check for that first. If you need to check for strict ANSI, the variable `flag_iso` can be used. The function-like macro `preprocessing_trad_p()` can be used to check for traditional preprocessing.

`TARGET_OS_CPP_BUILTINS ()` [Macro]

Similarly to `TARGET_CPU_CPP_BUILTINS` but this macro is optional and is used for the target operating system instead.

`TARGET_OBJFMT_CPP_BUILTINS ()` [Macro]

Similarly to `TARGET_CPU_CPP_BUILTINS` but this macro is optional and is used for the target object format. '`elfos.h`' uses this macro to define `__ELF__`, so you probably do not need to define it yourself.

`extern int target_flags` [Variable]

This variable is declared in '`options.h`', which is included before any target-specific headers.

`int TARGET_DEFAULT_TARGET_FLAGS` [Common Target Hook]

This variable specifies the initial value of `target_flags`. Its default setting is 0.

`bool TARGET_HANDLE_OPTION` (*struct gcc_options* ***opts***, *struct gcc_options* ***opts_set***, *const struct cl_decoded_option* ***decoded***, *location_t* ***loc***) [Common Target Hook]

This hook is called whenever the user specifies one of the target-specific options described by the '`.opt`' definition files (see Chapter 8 [Options], page 105). It has the opportunity to do some option-specific processing and should return true if the option is valid. The default definition does nothing but return true.

decoded specifies the option and its arguments. *opts* and *opts_set* are the `gcc_options` structures to be used for storing option state, and *loc* is the location at which the option was passed (`UNKNOWN_LOCATION` except for options passed via attributes).

`bool TARGET_HANDLE_C_OPTION` (*size_t* ***code***, *const char* ***arg***, *int* ***value***) [C Target Hook]

This target hook is called whenever the user specifies one of the target-specific C language family options described by the '`.opt`' definition files(see Chapter 8 [Options], page 105). It has the opportunity to do some option-specific processing and should return true if the option is valid. The arguments are like for `TARGET_HANDLE_OPTION`. The default definition does nothing but return false.

In general, you should use `TARGET_HANDLE_OPTION` to handle options. However, if processing an option requires routines that are only available in the C (and related language) front ends, then you should use `TARGET_HANDLE_C_OPTION` instead.

`tree TARGET_OBJC_CONSTRUCT_STRING_OBJECT` (*tree* ***string***) [C Target Hook]

Targets may provide a string object type that can be used within and between C, C++ and their respective Objective-C dialects. A string object might, for example, embed encoding and length information. These objects are considered opaque to the compiler and handled as references. An ideal implementation makes the composition of the string object match that of the Objective-C `NSString` (`NXString` for GNUStep), allowing efficient interworking between C-only and Objective-C code. If a target implements string objects then this hook should return a reference to such an object constructed from the normal 'C' string representation provided in *string*. At present, the hook is used by Objective-C only, to obtain a common-format string object when the target provides one.

`void TARGET_OBJC_DECLARE_UNRESOLVED_CLASS_REFERENCE` (*const char* ****classname***) [C Target Hook]

Declare that Objective C class *classname* is referenced by the current TU.

`void TARGET_OBJC_DECLARE_CLASS_DEFINITION` (*const char* ****classname***) [C Target Hook]

Declare that Objective C class *classname* is defined by the current TU.

`bool TARGET_STRING_OBJECT_REF_TYPE_P` (*const_tree* ***stringref***) [C Target Hook]

If a target implements string objects then this hook should return `true` if *stringref* is a valid reference to such an object.

`void TARGET_CHECK_STRING_OBJECT_FORMAT_ARG` (*tree* ***format_arg***, *tree* ***args_list***) [C Target Hook]

If a target implements string objects then this hook should should provide a facility to check the function arguments in *args_list* against the format specifiers in *format_arg* where the type of *format_arg* is one recognized as a valid string reference type.

`void TARGET_OVERRIDE_OPTIONS_AFTER_CHANGE` (*void*) [Target Hook]

This target function is similar to the hook `TARGET_OPTION_OVERRIDE` but is called when the optimize level is changed via an attribute or pragma or when it is reset at the end of the code affected by the attribute or pragma. It is not called at the beginning of compilation when `TARGET_OPTION_OVERRIDE` is called so if you want to perform these actions then, you should have `TARGET_OPTION_OVERRIDE` call `TARGET_OVERRIDE_OPTIONS_AFTER_CHANGE`.

`C_COMMON_OVERRIDE_OPTIONS` [Macro]

This is similar to the `TARGET_OPTION_OVERRIDE` hook but is only used in the C language frontends (C, Objective-C, C++, Objective-C++) and so can be used to alter option flag variables which only exist in those frontends.

`const struct default_options * TARGET_OPTION_OPTIMIZATION_TABLE` [Common Target Hook]

Some machines may desire to change what optimizations are performed for various optimization levels. This variable, if defined, describes options to enable at particular

sets of optimization levels. These options are processed once just after the optimization level is determined and before the remainder of the command options have been parsed, so may be overridden by other options passed explicitly.

This processing is run once at program startup and when the optimization options are changed via `#pragma GCC optimize` or by using the `optimize` attribute.

`void TARGET_OPTION_INIT_STRUCT` (*struct gcc_options *opts*) [Common Target Hook]

Set target-dependent initial values of fields in *opts*.

`void TARGET_OPTION_DEFAULT_PARAMS` (*void*) [Common Target Hook]

Set target-dependent default values for '`--param`' settings, using calls to `set_default_param_value`.

`SWITCHABLE_TARGET` [Macro]

Some targets need to switch between substantially different subtargets during compilation. For example, the MIPS target has one subtarget for the traditional MIPS architecture and another for MIPS16. Source code can switch between these two subarchitectures using the `mips16` and `nomips16` attributes.

Such subtargets can differ in things like the set of available registers, the set of available instructions, the costs of various operations, and so on. GCC caches a lot of this type of information in global variables, and recomputing them for each subtarget takes a significant amount of time. The compiler therefore provides a facility for maintaining several versions of the global variables and quickly switching between them; see '`target-globals.h`' for details.

Define this macro to 1 if your target needs this facility. The default is 0.

`bool TARGET_FLOAT_EXCEPTIONS_ROUNDING_SUPPORTED_P` (*void*) [Target Hook]

Returns true if the target supports IEEE 754 floating-point exceptions and rounding modes, false otherwise. This is intended to relate to the `float` and `double` types, but not necessarily `long double`. By default, returns true if the `adddf3` instruction pattern is available and false otherwise, on the assumption that hardware floating point supports exceptions and rounding modes but software floating point does not.

17.4 Defining data structures for per-function information.

If the target needs to store information on a per-function basis, GCC provides a macro and a couple of variables to allow this. Note, just using statics to store the information is a bad idea, since GCC supports nested functions, so you can be halfway through encoding one function when another one comes along.

GCC defines a data structure called `struct function` which contains all of the data specific to an individual function. This structure contains a field called `machine` whose type is `struct machine_function *`, which can be used by targets to point to their own specific data.

If a target needs per-function specific data it should define the type `struct machine_function` and also the macro `INIT_EXPANDERS`. This macro should be used to initialize the function pointer `init_machine_status`. This pointer is explained below.

One typical use of per-function, target specific data is to create an RTX to hold the register containing the function's return address. This RTX can then be used to implement the `__builtin_return_address` function, for level 0.

Note—earlier implementations of GCC used a single data area to hold all of the per-function information. Thus when processing of a nested function began the old per-function data had to be pushed onto a stack, and when the processing was finished, it had to be popped off the stack. GCC used to provide function pointers called `save_machine_status` and `restore_machine_status` to handle the saving and restoring of the target specific information. Since the single data area approach is no longer used, these pointers are no longer supported.

`INIT_EXPANDERS` [Macro]

Macro called to initialize any target specific information. This macro is called once per function, before generation of any RTL has begun. The intention of this macro is to allow the initialization of the function pointer `init_machine_status`.

`void (*)(struct function *) init_machine_status` [Variable]

If this function pointer is non-`NULL` it will be called once per function, before function compilation starts, in order to allow the target to perform any target specific initialization of the `struct function` structure. It is intended that this would be used to initialize the `machine` of that structure.

`struct machine_function` structures are expected to be freed by GC. Generally, any memory that they reference must be allocated by using GC allocation, including the structure itself.

17.5 Storage Layout

Note that the definitions of the macros in this table which are sizes or alignments measured in bits do not need to be constant. They can be C expressions that refer to static variables, such as the `target_flags`. See Section 17.3 [Run-time Target], page 428.

`BITS_BIG_ENDIAN` [Macro]

Define this macro to have the value 1 if the most significant bit in a byte has the lowest number; otherwise define it to have the value zero. This means that bit-field instructions count from the most significant bit. If the machine has no bit-field instructions, then this must still be defined, but it doesn't matter which value it is defined to. This macro need not be a constant.

This macro does not affect the way structure fields are packed into bytes or words; that is controlled by `BYTES_BIG_ENDIAN`.

`BYTES_BIG_ENDIAN` [Macro]

Define this macro to have the value 1 if the most significant byte in a word has the lowest number. This macro need not be a constant.

`WORDS_BIG_ENDIAN` [Macro]

Define this macro to have the value 1 if, in a multiword object, the most significant word has the lowest number. This applies to both memory locations and registers; see `REG_WORDS_BIG_ENDIAN` if the order of words in memory is not the same as the order in registers. This macro need not be a constant.

`REG_WORDS_BIG_ENDIAN` [Macro]

On some machines, the order of words in a multiword object differs between registers in memory. In such a situation, define this macro to describe the order of words in a register. The macro `WORDS_BIG_ENDIAN` controls the order of words in memory.

`FLOAT_WORDS_BIG_ENDIAN` [Macro]

Define this macro to have the value 1 if `DFmode`, `XFmode` or `TFmode` floating point numbers are stored in memory with the word containing the sign bit at the lowest address; otherwise define it to have the value 0. This macro need not be a constant.

You need not define this macro if the ordering is the same as for multi-word integers.

`BITS_PER_WORD` [Macro]

Number of bits in a word. If you do not define this macro, the default is `BITS_PER_UNIT * UNITS_PER_WORD`.

`MAX_BITS_PER_WORD` [Macro]

Maximum number of bits in a word. If this is undefined, the default is `BITS_PER_WORD`. Otherwise, it is the constant value that is the largest value that `BITS_PER_WORD` can have at run-time.

`UNITS_PER_WORD` [Macro]

Number of storage units in a word; normally the size of a general-purpose register, a power of two from 1 or 8.

`MIN_UNITS_PER_WORD` [Macro]

Minimum number of units in a word. If this is undefined, the default is `UNITS_PER_WORD`. Otherwise, it is the constant value that is the smallest value that `UNITS_PER_WORD` can have at run-time.

`POINTER_SIZE` [Macro]

Width of a pointer, in bits. You must specify a value no wider than the width of `Pmode`. If it is not equal to the width of `Pmode`, you must define `POINTERS_EXTEND_UNSIGNED`. If you do not specify a value the default is `BITS_PER_WORD`.

`POINTERS_EXTEND_UNSIGNED` [Macro]

A C expression that determines how pointers should be extended from `ptr_mode` to either `Pmode` or `word_mode`. It is greater than zero if pointers should be zero-extended, zero if they should be sign-extended, and negative if some other sort of conversion is needed. In the last case, the extension is done by the target's `ptr_extend` instruction.

You need not define this macro if the `ptr_mode`, `Pmode` and `word_mode` are all the same width.

`PROMOTE_MODE` (*m*, *unsignedp*, *type*) [Macro]

A macro to update *m* and *unsignedp* when an object whose type is *type* and which has the specified mode and signedness is to be stored in a register. This macro is only called when *type* is a scalar type.

On most RISC machines, which only have operations that operate on a full register, define this macro to set *m* to `word_mode` if *m* is an integer mode narrower than

BITS_PER_WORD. In most cases, only integer modes should be widened because wider-precision floating-point operations are usually more expensive than their narrower counterparts.

For most machines, the macro definition does not change *unsignedp*. However, some machines, have instructions that preferentially handle either signed or unsigned quantities of certain modes. For example, on the DEC Alpha, 32-bit loads from memory and 32-bit add instructions sign-extend the result to 64 bits. On such machines, set *unsignedp* according to which kind of extension is more efficient.

Do not define this macro if it would never modify *m*.

enum machine_mode TARGET_PROMOTE_FUNCTION_MODE (*const_tree* ***type***, *enum machine_mode* ***mode***, *int* ****punsignedp***, *const_tree* ***funtype***, *int* ***for_return***) [Target Hook]

Like PROMOTE_MODE, but it is applied to outgoing function arguments or function return values. The target hook should return the new mode and possibly change ****punsignedp*** if the promotion should change signedness. This function is called only for scalar *or pointer* types.

for_return allows to distinguish the promotion of arguments and return values. If it is 1, a return value is being promoted and TARGET_FUNCTION_VALUE must perform the same promotions done here. If it is 2, the returned mode should be that of the register in which an incoming parameter is copied, or the outgoing result is computed; then the hook should return the same mode as promote_mode, though the signedness may be different.

type can be NULL when promoting function arguments of libcalls.

The default is to not promote arguments and return values. You can also define the hook to default_promote_function_mode_always_promote if you would like to apply the same rules given by PROMOTE_MODE.

PARM_BOUNDARY [Macro]

Normal alignment required for function parameters on the stack, in bits. All stack parameters receive at least this much alignment regardless of data type. On most machines, this is the same as the size of an integer.

STACK_BOUNDARY [Macro]

Define this macro to the minimum alignment enforced by hardware for the stack pointer on this machine. The definition is a C expression for the desired alignment (measured in bits). This value is used as a default if PREFERRED_STACK_BOUNDARY is not defined. On most machines, this should be the same as PARM_BOUNDARY.

PREFERRED_STACK_BOUNDARY [Macro]

Define this macro if you wish to preserve a certain alignment for the stack pointer, greater than what the hardware enforces. The definition is a C expression for the desired alignment (measured in bits). This macro must evaluate to a value equal to or larger than STACK_BOUNDARY.

`INCOMING_STACK_BOUNDARY` [Macro]

Define this macro if the incoming stack boundary may be different from `PREFERRED_STACK_BOUNDARY`. This macro must evaluate to a value equal to or larger than `STACK_BOUNDARY`.

`FUNCTION_BOUNDARY` [Macro]

Alignment required for a function entry point, in bits.

`BIGGEST_ALIGNMENT` [Macro]

Biggest alignment that any data type can require on this machine, in bits. Note that this is not the biggest alignment that is supported, just the biggest alignment that, when violated, may cause a fault.

`MALLOC_ABI_ALIGNMENT` [Macro]

Alignment, in bits, a C conformant malloc implementation has to provide. If not defined, the default value is `BITS_PER_WORD`.

`ATTRIBUTE_ALIGNED_VALUE` [Macro]

Alignment used by the `__attribute__ ((aligned))` construct. If not defined, the default value is `BIGGEST_ALIGNMENT`.

`MINIMUM_ATOMIC_ALIGNMENT` [Macro]

If defined, the smallest alignment, in bits, that can be given to an object that can be referenced in one operation, without disturbing any nearby object. Normally, this is `BITS_PER_UNIT`, but may be larger on machines that don't have byte or half-word store operations.

`BIGGEST_FIELD_ALIGNMENT` [Macro]

Biggest alignment that any structure or union field can require on this machine, in bits. If defined, this overrides `BIGGEST_ALIGNMENT` for structure and union fields only, unless the field alignment has been set by the `__attribute__ ((aligned (n)))` construct.

`ADJUST_FIELD_ALIGN` (*field*, *computed*) [Macro]

An expression for the alignment of a structure field *field* if the alignment computed in the usual way (including applying of `BIGGEST_ALIGNMENT` and `BIGGEST_FIELD_ALIGNMENT` to the alignment) is *computed*. It overrides alignment only if the field alignment has not been set by the `__attribute__ ((aligned (n)))` construct.

`MAX_STACK_ALIGNMENT` [Macro]

Biggest stack alignment guaranteed by the backend. Use this macro to specify the maximum alignment of a variable on stack.

If not defined, the default value is `STACK_BOUNDARY`.

`MAX_OFILE_ALIGNMENT` [Macro]

Biggest alignment supported by the object file format of this machine. Use this macro to limit the alignment which can be specified using the `__attribute__ ((aligned (n)))` construct. If not defined, the default value is `BIGGEST_ALIGNMENT`.

On systems that use ELF, the default (in '`config/elfos.h`') is the largest supported 32-bit ELF section alignment representable on a 32-bit host e.g. '`(((unsigned`

`HOST_WIDEST_INT) 1 << 28) * 8)`'. On 32-bit ELF the largest supported section alignment in bits is '`(0x80000000 * 8)`', but this is not representable on 32-bit hosts.

`DATA_ALIGNMENT (type, basic-align)` [Macro]

If defined, a C expression to compute the alignment for a variable in the static store. *type* is the data type, and *basic-align* is the alignment that the object would ordinarily have. The value of this macro is used instead of that alignment to align the object.

If this macro is not defined, then *basic-align* is used.

One use of this macro is to increase alignment of medium-size data to make it all fit in fewer cache lines. Another is to cause character arrays to be word-aligned so that `strcpy` calls that copy constants to character arrays can be done inline.

`DATA_ABI_ALIGNMENT (type, basic-align)` [Macro]

Similar to `DATA_ALIGNMENT`, but for the cases where the ABI mandates some alignment increase, instead of optimization only purposes. E.g. AMD x86-64 psABI says that variables with array type larger than 15 bytes must be aligned to 16 byte boundaries.

If this macro is not defined, then *basic-align* is used.

`CONSTANT_ALIGNMENT (constant, basic-align)` [Macro]

If defined, a C expression to compute the alignment given to a constant that is being placed in memory. *constant* is the constant and *basic-align* is the alignment that the object would ordinarily have. The value of this macro is used instead of that alignment to align the object.

If this macro is not defined, then *basic-align* is used.

The typical use of this macro is to increase alignment for string constants to be word aligned so that `strcpy` calls that copy constants can be done inline.

`LOCAL_ALIGNMENT (type, basic-align)` [Macro]

If defined, a C expression to compute the alignment for a variable in the local store. *type* is the data type, and *basic-align* is the alignment that the object would ordinarily have. The value of this macro is used instead of that alignment to align the object.

If this macro is not defined, then *basic-align* is used.

One use of this macro is to increase alignment of medium-size data to make it all fit in fewer cache lines.

If the value of this macro has a type, it should be an unsigned type.

`HOST_WIDE_INT TARGET_VECTOR_ALIGNMENT (const_tree type)` [Target Hook]

This hook can be used to define the alignment for a vector of type *type*, in order to comply with a platform ABI. The default is to require natural alignment for vector types. The alignment returned by this hook must be a power-of-two multiple of the default alignment of the vector element type.

`STACK_SLOT_ALIGNMENT (type, mode, basic-align)` [Macro]

If defined, a C expression to compute the alignment for stack slot. *type* is the data type, *mode* is the widest mode available, and *basic-align* is the alignment that the

slot would ordinarily have. The value of this macro is used instead of that alignment to align the slot.

If this macro is not defined, then *basic-align* is used when *type* is `NULL`. Otherwise, `LOCAL_ALIGNMENT` will be used.

This macro is to set alignment of stack slot to the maximum alignment of all possible modes which the slot may have.

If the value of this macro has a type, it should be an unsigned type.

`LOCAL_DECL_ALIGNMENT (decl)` [Macro]

If defined, a C expression to compute the alignment for a local variable *decl*.

If this macro is not defined, then `LOCAL_ALIGNMENT (TREE_TYPE (decl), DECL_ALIGN (decl))` is used.

One use of this macro is to increase alignment of medium-size data to make it all fit in fewer cache lines.

If the value of this macro has a type, it should be an unsigned type.

`MINIMUM_ALIGNMENT (exp, mode, align)` [Macro]

If defined, a C expression to compute the minimum required alignment for dynamic stack realignment purposes for *exp* (a type or decl), *mode*, assuming normal alignment *align*.

If this macro is not defined, then *align* will be used.

`EMPTY_FIELD_BOUNDARY` [Macro]

Alignment in bits to be given to a structure bit-field that follows an empty field such as `int : 0;`.

If `PCC_BITFIELD_TYPE_MATTERS` is true, it overrides this macro.

`STRUCTURE_SIZE_BOUNDARY` [Macro]

Number of bits which any structure or union's size must be a multiple of. Each structure or union's size is rounded up to a multiple of this.

If you do not define this macro, the default is the same as `BITS_PER_UNIT`.

`STRICT_ALIGNMENT` [Macro]

Define this macro to be the value 1 if instructions will fail to work if given data not on the nominal alignment. If instructions will merely go slower in that case, define this macro as 0.

`PCC_BITFIELD_TYPE_MATTERS` [Macro]

Define this if you wish to imitate the way many other C compilers handle alignment of bit-fields and the structures that contain them.

The behavior is that the type written for a named bit-field (`int`, `short`, or other integer type) imposes an alignment for the entire structure, as if the structure really did contain an ordinary field of that type. In addition, the bit-field is placed within the structure so that it would fit within such a field, not crossing a boundary for it.

Thus, on most machines, a named bit-field whose type is written as `int` would not cross a four-byte boundary, and would force four-byte alignment for the whole structure. (The alignment used may not be four bytes; it is controlled by the other alignment parameters.)

An unnamed bit-field will not affect the alignment of the containing structure.

If the macro is defined, its definition should be a C expression; a nonzero value for the expression enables this behavior.

Note that if this macro is not defined, or its value is zero, some bit-fields may cross more than one alignment boundary. The compiler can support such references if there are '`insv`', '`extv`', and '`extzv`' insns that can directly reference memory.

The other known way of making bit-fields work is to define `STRUCTURE_SIZE_BOUNDARY` as large as `BIGGEST_ALIGNMENT`. Then every structure can be accessed with fullwords.

Unless the machine has bit-field instructions or you define `STRUCTURE_SIZE_BOUNDARY` that way, you must define `PCC_BITFIELD_TYPE_MATTERS` to have a nonzero value.

If your aim is to make GCC use the same conventions for laying out bit-fields as are used by another compiler, here is how to investigate what the other compiler does. Compile and run this program:

```
struct foo1
{
  char x;
  char :0;
  char y;
};

struct foo2
{
  char x;
  int :0;
  char y;
};

main ()
{
  printf ("Size of foo1 is %d\n",
          sizeof (struct foo1));
  printf ("Size of foo2 is %d\n",
          sizeof (struct foo2));
  exit (0);
}
```

If this prints 2 and 5, then the compiler's behavior is what you would get from `PCC_BITFIELD_TYPE_MATTERS`.

`BITFIELD_NBYTES_LIMITED` [Macro]

Like `PCC_BITFIELD_TYPE_MATTERS` except that its effect is limited to aligning a bit-field within the structure.

`bool TARGET_ALIGN_ANON_BITFIELD` (*void*) [Target Hook]

When `PCC_BITFIELD_TYPE_MATTERS` is true this hook will determine whether unnamed bitfields affect the alignment of the containing structure. The hook should return true if the structure should inherit the alignment requirements of an unnamed bitfield's type.

`bool TARGET_NARROW_VOLATILE_BITFIELD (void)` [Target Hook]

This target hook should return `true` if accesses to volatile bitfields should use the narrowest mode possible. It should return `false` if these accesses should use the bitfield container type.

The default is `false`.

`bool TARGET_MEMBER_TYPE_FORCES_BLK (const_tree field, enum machine_mode mode)` [Target Hook]

Return true if a structure, union or array containing *field* should be accessed using `BLKMODE`.

If *field* is the only field in the structure, *mode* is its mode, otherwise *mode* is VOIDmode. *mode* is provided in the case where structures of one field would require the structure's mode to retain the field's mode.

Normally, this is not needed.

`ROUND_TYPE_ALIGN (type, computed, specified)` [Macro]

Define this macro as an expression for the alignment of a type (given by *type* as a tree node) if the alignment computed in the usual way is *computed* and the alignment explicitly specified was *specified*.

The default is to use *specified* if it is larger; otherwise, use the smaller of *computed* and `BIGGEST_ALIGNMENT`

`MAX_FIXED_MODE_SIZE` [Macro]

An integer expression for the size in bits of the largest integer machine mode that should actually be used. All integer machine modes of this size or smaller can be used for structures and unions with the appropriate sizes. If this macro is undefined, `GET_MODE_BITSIZE (DImode)` is assumed.

`STACK_SAVEAREA_MODE (save_level)` [Macro]

If defined, an expression of type `enum machine_mode` that specifies the mode of the save area operand of a `save_stack_level` named pattern (see Section 16.9 [Standard Names], page 349). *save_level* is one of `SAVE_BLOCK`, `SAVE_FUNCTION`, or `SAVE_NONLOCAL` and selects which of the three named patterns is having its mode specified.

You need not define this macro if it always returns `Pmode`. You would most commonly define this macro if the `save_stack_level` patterns need to support both a 32- and a 64-bit mode.

`STACK_SIZE_MODE` [Macro]

If defined, an expression of type `enum machine_mode` that specifies the mode of the size increment operand of an `allocate_stack` named pattern (see Section 16.9 [Standard Names], page 349).

You need not define this macro if it always returns `word_mode`. You would most commonly define this macro if the `allocate_stack` pattern needs to support both a 32- and a 64-bit mode.

`enum machine_mode TARGET_LIBGCC_CMP_RETURN_MODE (void)` [Target Hook]

This target hook should return the mode to be used for the return value of compare instructions expanded to libgcc calls. If not defined `word_mode` is returned which is the right choice for a majority of targets.

`enum machine_mode TARGET_LIBGCC_SHIFT_COUNT_MODE (void)` [Target Hook]

This target hook should return the mode to be used for the shift count operand of shift instructions expanded to libgcc calls. If not defined `word_mode` is returned which is the right choice for a majority of targets.

`enum machine_mode TARGET_UNWIND_WORD_MODE (void)` [Target Hook]

Return machine mode to be used for `_Unwind_Word` type. The default is to use `word_mode`.

`ROUND_TOWARDS_ZERO` [Macro]

If defined, this macro should be true if the prevailing rounding mode is towards zero.

Defining this macro only affects the way '`libgcc.a`' emulates floating-point arithmetic.

Not defining this macro is equivalent to returning zero.

`LARGEST_EXPONENT_IS_NORMAL (size)` [Macro]

This macro should return true if floats with *size* bits do not have a NaN or infinity representation, but use the largest exponent for normal numbers instead.

Defining this macro only affects the way '`libgcc.a`' emulates floating-point arithmetic.

The default definition of this macro returns false for all sizes.

`bool TARGET_MS_BITFIELD_LAYOUT_P (const_tree record_type)` [Target Hook]

This target hook returns `true` if bit-fields in the given *record_type* are to be laid out following the rules of Microsoft Visual C/C++, namely: (i) a bit-field won't share the same storage unit with the previous bit-field if their underlying types have different sizes, and the bit-field will be aligned to the highest alignment of the underlying types of itself and of the previous bit-field; (ii) a zero-sized bit-field will affect the alignment of the whole enclosing structure, even if it is unnamed; except that (iii) a zero-sized bit-field will be disregarded unless it follows another bit-field of nonzero size. If this hook returns `true`, other macros that control bit-field layout are ignored.

When a bit-field is inserted into a packed record, the whole size of the underlying type is used by one or more same-size adjacent bit-fields (that is, if its long:3, 32 bits is used in the record, and any additional adjacent long bit-fields are packed into the same chunk of 32 bits. However, if the size changes, a new field of that size is allocated). In an unpacked record, this is the same as using alignment, but not equivalent when packing.

If both MS bit-fields and '`__attribute__((packed))`' are used, the latter will take precedence. If '`__attribute__((packed))`' is used on a single field when MS bit-fields are in use, it will take precedence for that field, but the alignment of the rest of the structure may affect its placement.

`bool TARGET_DECIMAL_FLOAT_SUPPORTED_P (void)` [Target Hook]

Returns true if the target supports decimal floating point.

`bool TARGET_FIXED_POINT_SUPPORTED_P (void)` [Target Hook]

Returns true if the target supports fixed-point arithmetic.

`void TARGET_EXPAND_TO_RTL_HOOK (void)` [Target Hook]

This hook is called just before expansion into rtl, allowing the target to perform additional initializations or analysis before the expansion. For example, the rs6000 port uses it to allocate a scratch stack slot for use in copying SDmode values between memory and floating point registers whenever the function being expanded has any SDmode usage.

`void TARGET_INSTANTIATE_DECLS (void)` [Target Hook]

This hook allows the backend to perform additional instantiations on rtl that are not actually in any insns yet, but will be later.

`const char * TARGET_MANGLE_TYPE (const_tree type)` [Target Hook]

If your target defines any fundamental types, or any types your target uses should be mangled differently from the default, define this hook to return the appropriate encoding for these types as part of a C++ mangled name. The *type* argument is the tree structure representing the type to be mangled. The hook may be applied to trees which are not target-specific fundamental types; it should return `NULL` for all such types, as well as arguments it does not recognize. If the return value is not `NULL`, it must point to a statically-allocated string constant.

Target-specific fundamental types might be new fundamental types or qualified versions of ordinary fundamental types. Encode new fundamental types as '`u` *n name*', where *name* is the name used for the type in source code, and *n* is the length of *name* in decimal. Encode qualified versions of ordinary types as '`U` *n name code*', where *name* is the name used for the type qualifier in source code, *n* is the length of *name* as above, and *code* is the code used to represent the unqualified version of this type. (See `write_builtin_type` in '`cp/mangle.c`' for the list of codes.) In both cases the spaces are for clarity; do not include any spaces in your string.

This hook is applied to types prior to typedef resolution. If the mangled name for a particular type depends only on that type's main variant, you can perform typedef resolution yourself using `TYPE_MAIN_VARIANT` before mangling.

The default version of this hook always returns `NULL`, which is appropriate for a target that does not define any new fundamental types.

17.6 Layout of Source Language Data Types

These macros define the sizes and other characteristics of the standard basic data types used in programs being compiled. Unlike the macros in the previous section, these apply to specific features of C and related languages, rather than to fundamental aspects of storage layout.

`INT_TYPE_SIZE` [Macro]

A C expression for the size in bits of the type `int` on the target machine. If you don't define this, the default is one word.

`SHORT_TYPE_SIZE` [Macro]

A C expression for the size in bits of the type `short` on the target machine. If you don't define this, the default is half a word. (If this would be less than one storage unit, it is rounded up to one unit.)

`LONG_TYPE_SIZE` [Macro]

A C expression for the size in bits of the type `long` on the target machine. If you don't define this, the default is one word.

`ADA_LONG_TYPE_SIZE` [Macro]

On some machines, the size used for the Ada equivalent of the type `long` by a native Ada compiler differs from that used by C. In that situation, define this macro to be a C expression to be used for the size of that type. If you don't define this, the default is the value of `LONG_TYPE_SIZE`.

`LONG_LONG_TYPE_SIZE` [Macro]

A C expression for the size in bits of the type `long long` on the target machine. If you don't define this, the default is two words. If you want to support GNU Ada on your machine, the value of this macro must be at least 64.

`CHAR_TYPE_SIZE` [Macro]

A C expression for the size in bits of the type `char` on the target machine. If you don't define this, the default is `BITS_PER_UNIT`.

`BOOL_TYPE_SIZE` [Macro]

A C expression for the size in bits of the C++ type `bool` and C99 type `_Bool` on the target machine. If you don't define this, and you probably shouldn't, the default is `CHAR_TYPE_SIZE`.

`FLOAT_TYPE_SIZE` [Macro]

A C expression for the size in bits of the type `float` on the target machine. If you don't define this, the default is one word.

`DOUBLE_TYPE_SIZE` [Macro]

A C expression for the size in bits of the type `double` on the target machine. If you don't define this, the default is two words.

`LONG_DOUBLE_TYPE_SIZE` [Macro]

A C expression for the size in bits of the type `long double` on the target machine. If you don't define this, the default is two words.

`SHORT_FRACT_TYPE_SIZE` [Macro]

A C expression for the size in bits of the type `short _Fract` on the target machine. If you don't define this, the default is `BITS_PER_UNIT`.

`FRACT_TYPE_SIZE` [Macro]

A C expression for the size in bits of the type `_Fract` on the target machine. If you don't define this, the default is `BITS_PER_UNIT * 2`.

`LONG_FRACT_TYPE_SIZE` [Macro]

A C expression for the size in bits of the type `long _Fract` on the target machine. If you don't define this, the default is `BITS_PER_UNIT * 4`.

`LONG_LONG_FRACT_TYPE_SIZE` [Macro]

A C expression for the size in bits of the type `long long _Fract` on the target machine. If you don't define this, the default is `BITS_PER_UNIT * 8`.

SHORT_ACCUM_TYPE_SIZE [Macro]

A C expression for the size in bits of the type `short _Accum` on the target machine. If you don't define this, the default is `BITS_PER_UNIT * 2`.

ACCUM_TYPE_SIZE [Macro]

A C expression for the size in bits of the type `_Accum` on the target machine. If you don't define this, the default is `BITS_PER_UNIT * 4`.

LONG_ACCUM_TYPE_SIZE [Macro]

A C expression for the size in bits of the type `long _Accum` on the target machine. If you don't define this, the default is `BITS_PER_UNIT * 8`.

LONG_LONG_ACCUM_TYPE_SIZE [Macro]

A C expression for the size in bits of the type `long long _Accum` on the target machine. If you don't define this, the default is `BITS_PER_UNIT * 16`.

LIBGCC2_LONG_DOUBLE_TYPE_SIZE [Macro]

Define this macro if `LONG_DOUBLE_TYPE_SIZE` is not constant or if you want routines in '`libgcc2.a`' for a size other than `LONG_DOUBLE_TYPE_SIZE`. If you don't define this, the default is `LONG_DOUBLE_TYPE_SIZE`.

LIBGCC2_HAS_DF_MODE [Macro]

Define this macro if neither `DOUBLE_TYPE_SIZE` nor `LIBGCC2_LONG_DOUBLE_TYPE_SIZE` is `DFmode` but you want `DFmode` routines in '`libgcc2.a`' anyway. If you don't define this and either `DOUBLE_TYPE_SIZE` or `LIBGCC2_LONG_DOUBLE_TYPE_SIZE` is 64 then the default is 1, otherwise it is 0.

LIBGCC2_HAS_XF_MODE [Macro]

Define this macro if `LIBGCC2_LONG_DOUBLE_TYPE_SIZE` is not `XFmode` but you want `XFmode` routines in '`libgcc2.a`' anyway. If you don't define this and `LIBGCC2_LONG_DOUBLE_TYPE_SIZE` is 80 then the default is 1, otherwise it is 0.

LIBGCC2_HAS_TF_MODE [Macro]

Define this macro if `LIBGCC2_LONG_DOUBLE_TYPE_SIZE` is not `TFmode` but you want `TFmode` routines in '`libgcc2.a`' anyway. If you don't define this and `LIBGCC2_LONG_DOUBLE_TYPE_SIZE` is 128 then the default is 1, otherwise it is 0.

LIBGCC2_GNU_PREFIX [Macro]

This macro corresponds to the `TARGET_LIBFUNC_GNU_PREFIX` target hook and should be defined if that hook is overriden to be true. It causes function names in libgcc to be changed to use a `__gnu_` prefix for their name rather than the default `__`. A port which uses this macro should also arrange to use '`t-gnu-prefix`' in the libgcc '`config.host`'.

SF_SIZE [Macro]
DF_SIZE [Macro]
XF_SIZE [Macro]
TF_SIZE [Macro]

Define these macros to be the size in bits of the mantissa of `SFmode`, `DFmode`, `XFmode` and `TFmode` values, if the defaults in '`libgcc2.h`' are inappropriate. By default,

FLT_MANT_DIG is used for SF_SIZE, LDBL_MANT_DIG for XF_SIZE and TF_SIZE, and DBL_MANT_DIG or LDBL_MANT_DIG for DF_SIZE according to whether DOUBLE_TYPE_SIZE or LIBGCC2_LONG_DOUBLE_TYPE_SIZE is 64.

TARGET_FLT_EVAL_METHOD [Macro]

A C expression for the value for FLT_EVAL_METHOD in 'float.h', assuming, if applicable, that the floating-point control word is in its default state. If you do not define this macro the value of FLT_EVAL_METHOD will be zero.

WIDEST_HARDWARE_FP_SIZE [Macro]

A C expression for the size in bits of the widest floating-point format supported by the hardware. If you define this macro, you must specify a value less than or equal to the value of LONG_DOUBLE_TYPE_SIZE. If you do not define this macro, the value of LONG_DOUBLE_TYPE_SIZE is the default.

DEFAULT_SIGNED_CHAR [Macro]

An expression whose value is 1 or 0, according to whether the type char should be signed or unsigned by default. The user can always override this default with the options '-fsigned-char' and '-funsigned-char'.

bool TARGET_DEFAULT_SHORT_ENUMS (*void*) [Target Hook]

This target hook should return true if the compiler should give an enum type only as many bytes as it takes to represent the range of possible values of that type. It should return false if all enum types should be allocated like int.

The default is to return false.

SIZE_TYPE [Macro]

A C expression for a string describing the name of the data type to use for size values. The typedef name size_t is defined using the contents of the string.

The string can contain more than one keyword. If so, separate them with spaces, and write first any length keyword, then unsigned if appropriate, and finally int. The string must exactly match one of the data type names defined in the function c_common_nodes_and_builtins in the file 'c-family/c-common.c'. You may not omit int or change the order—that would cause the compiler to crash on startup.

If you don't define this macro, the default is "long unsigned int".

SIZETYPE [Macro]

GCC defines internal types (sizetype, ssizetype, bitsizetype and sbitsizetype) for expressions dealing with size. This macro is a C expression for a string describing the name of the data type from which the precision of sizetype is extracted.

The string has the same restrictions as SIZE_TYPE string.

If you don't define this macro, the default is SIZE_TYPE.

PTRDIFF_TYPE [Macro]

A C expression for a string describing the name of the data type to use for the result of subtracting two pointers. The typedef name ptrdiff_t is defined using the contents of the string. See SIZE_TYPE above for more information.

If you don't define this macro, the default is "long int".

`WCHAR_TYPE` [Macro]

A C expression for a string describing the name of the data type to use for wide characters. The typedef name `wchar_t` is defined using the contents of the string. See `SIZE_TYPE` above for more information.

If you don't define this macro, the default is `"int"`.

`WCHAR_TYPE_SIZE` [Macro]

A C expression for the size in bits of the data type for wide characters. This is used in `cpp`, which cannot make use of `WCHAR_TYPE`.

`WINT_TYPE` [Macro]

A C expression for a string describing the name of the data type to use for wide characters passed to `printf` and returned from `getwc`. The typedef name `wint_t` is defined using the contents of the string. See `SIZE_TYPE` above for more information.

If you don't define this macro, the default is `"unsigned int"`.

`INTMAX_TYPE` [Macro]

A C expression for a string describing the name of the data type that can represent any value of any standard or extended signed integer type. The typedef name `intmax_t` is defined using the contents of the string. See `SIZE_TYPE` above for more information.

If you don't define this macro, the default is the first of `"int"`, `"long int"`, or `"long long int"` that has as much precision as `long long int`.

`UINTMAX_TYPE` [Macro]

A C expression for a string describing the name of the data type that can represent any value of any standard or extended unsigned integer type. The typedef name `uintmax_t` is defined using the contents of the string. See `SIZE_TYPE` above for more information.

If you don't define this macro, the default is the first of `"unsigned int"`, `"long unsigned int"`, or `"long long unsigned int"` that has as much precision as `long long unsigned int`.

`SIG_ATOMIC_TYPE` [Macro]
`INT8_TYPE` [Macro]
`INT16_TYPE` [Macro]
`INT32_TYPE` [Macro]
`INT64_TYPE` [Macro]
`UINT8_TYPE` [Macro]
`UINT16_TYPE` [Macro]
`UINT32_TYPE` [Macro]
`UINT64_TYPE` [Macro]
`INT_LEAST8_TYPE` [Macro]
`INT_LEAST16_TYPE` [Macro]
`INT_LEAST32_TYPE` [Macro]
`INT_LEAST64_TYPE` [Macro]
`UINT_LEAST8_TYPE` [Macro]
`UINT_LEAST16_TYPE` [Macro]
`UINT_LEAST32_TYPE` [Macro]

UINT_LEAST64_TYPE [Macro]
INT_FAST8_TYPE [Macro]
INT_FAST16_TYPE [Macro]
INT_FAST32_TYPE [Macro]
INT_FAST64_TYPE [Macro]
UINT_FAST8_TYPE [Macro]
UINT_FAST16_TYPE [Macro]
UINT_FAST32_TYPE [Macro]
UINT_FAST64_TYPE [Macro]
INTPTR_TYPE [Macro]
UINTPTR_TYPE [Macro]

C expressions for the standard types `sig_atomic_t`, `int8_t`, `int16_t`, `int32_t`, `int64_t`, `uint8_t`, `uint16_t`, `uint32_t`, `uint64_t`, `int_least8_t`, `int_least16_t`, `int_least32_t`, `int_least64_t`, `uint_least8_t`, `uint_least16_t`, `uint_least32_t`, `uint_least64_t`, `int_fast8_t`, `int_fast16_t`, `int_fast32_t`, `int_fast64_t`, `uint_fast8_t`, `uint_fast16_t`, `uint_fast32_t`, `uint_fast64_t`, `intptr_t`, and `uintptr_t`. See `SIZE_TYPE` above for more information.

If any of these macros evaluates to a null pointer, the corresponding type is not supported; if GCC is configured to provide `<stdint.h>` in such a case, the header provided may not conform to C99, depending on the type in question. The defaults for all of these macros are null pointers.

TARGET_PTRMEMFUNC_VBIT_LOCATION [Macro]

The C++ compiler represents a pointer-to-member-function with a struct that looks like:

```
struct {
  union {
    void (*fn)();
    ptrdiff_t vtable_index;
  };
  ptrdiff_t delta;
};
```

The C++ compiler must use one bit to indicate whether the function that will be called through a pointer-to-member-function is virtual. Normally, we assume that the low-order bit of a function pointer must always be zero. Then, by ensuring that the vtable_index is odd, we can distinguish which variant of the union is in use. But, on some platforms function pointers can be odd, and so this doesn't work. In that case, we use the low-order bit of the `delta` field, and shift the remainder of the `delta` field to the left.

GCC will automatically make the right selection about where to store this bit using the `FUNCTION_BOUNDARY` setting for your platform. However, some platforms such as ARM/Thumb have `FUNCTION_BOUNDARY` set such that functions always start at even addresses, but the lowest bit of pointers to functions indicate whether the function at that address is in ARM or Thumb mode. If this is the case of your architecture, you should define this macro to `ptrmemfunc_vbit_in_delta`.

In general, you should not have to define this macro. On architectures in which function addresses are always even, according to `FUNCTION_BOUNDARY`, GCC will automatically define this macro to `ptrmemfunc_vbit_in_pfn`.

`TARGET_VTABLE_USES_DESCRIPTORS` [Macro]

Normally, the C++ compiler uses function pointers in vtables. This macro allows the target to change to use "function descriptors" instead. Function descriptors are found on targets for whom a function pointer is actually a small data structure. Normally the data structure consists of the actual code address plus a data pointer to which the function's data is relative.

If vtables are used, the value of this macro should be the number of words that the function descriptor occupies.

`TARGET_VTABLE_ENTRY_ALIGN` [Macro]

By default, the vtable entries are void pointers, the so the alignment is the same as pointer alignment. The value of this macro specifies the alignment of the vtable entry in bits. It should be defined only when special alignment is necessary. */

`TARGET_VTABLE_DATA_ENTRY_DISTANCE` [Macro]

There are a few non-descriptor entries in the vtable at offsets below zero. If these entries must be padded (say, to preserve the alignment specified by `TARGET_VTABLE_ENTRY_ALIGN`), set this to the number of words in each data entry.

17.7 Register Usage

This section explains how to describe what registers the target machine has, and how (in general) they can be used.

The description of which registers a specific instruction can use is done with register classes; see Section 17.8 [Register Classes], page 453. For information on using registers to access a stack frame, see Section 17.10.4 [Frame Registers], page 472. For passing values in registers, see Section 17.10.7 [Register Arguments], page 478. For returning values in registers, see Section 17.10.8 [Scalar Return], page 484.

17.7.1 Basic Characteristics of Registers

Registers have various characteristics.

`FIRST_PSEUDO_REGISTER` [Macro]

Number of hardware registers known to the compiler. They receive numbers 0 through `FIRST_PSEUDO_REGISTER-1`; thus, the first pseudo register's number really is assigned the number `FIRST_PSEUDO_REGISTER`.

`FIXED_REGISTERS` [Macro]

An initializer that says which registers are used for fixed purposes all throughout the compiled code and are therefore not available for general allocation. These would include the stack pointer, the frame pointer (except on machines where that can be used as a general register when no frame pointer is needed), the program counter on machines where that is considered one of the addressable registers, and any other numbered register with a standard use.

This information is expressed as a sequence of numbers, separated by commas and surrounded by braces. The *n*th number is 1 if register *n* is fixed, 0 otherwise.

The table initialized from this macro, and the table initialized by the following one, may be overridden at run time either automatically, by the actions of the

macro CONDITIONAL_REGISTER_USAGE, or by the user with the command options '-ffixed-*reg*', '-fcall-used-*reg*' and '-fcall-saved-*reg*'.

CALL_USED_REGISTERS [Macro]

Like FIXED_REGISTERS but has 1 for each register that is clobbered (in general) by function calls as well as for fixed registers. This macro therefore identifies the registers that are not available for general allocation of values that must live across function calls.

If a register has 0 in CALL_USED_REGISTERS, the compiler automatically saves it on function entry and restores it on function exit, if the register is used within the function.

CALL_REALLY_USED_REGISTERS [Macro]

Like CALL_USED_REGISTERS except this macro doesn't require that the entire set of FIXED_REGISTERS be included. (CALL_USED_REGISTERS must be a superset of FIXED_REGISTERS). This macro is optional. If not specified, it defaults to the value of CALL_USED_REGISTERS.

HARD_REGNO_CALL_PART_CLOBBERED (*regno*, *mode*) [Macro]

A C expression that is nonzero if it is not permissible to store a value of mode *mode* in hard register number *regno* across a call without some part of it being clobbered. For most machines this macro need not be defined. It is only required for machines that do not preserve the entire contents of a register across a call.

void TARGET_CONDITIONAL_REGISTER_USAGE (*void*) [Target Hook]

This hook may conditionally modify five variables fixed_regs, call_used_regs, global_regs, reg_names, and reg_class_contents, to take into account any dependence of these register sets on target flags. The first three of these are of type char [] (interpreted as Boolean vectors). global_regs is a const char *[], and reg_class_contents is a HARD_REG_SET. Before the macro is called, fixed_regs, call_used_regs, reg_class_contents, and reg_names have been initialized from FIXED_REGISTERS, CALL_USED_REGISTERS, REG_CLASS_CONTENTS, and REGISTER_NAMES, respectively. global_regs has been cleared, and any '-ffixed-*reg*', '-fcall-used-*reg*' and '-fcall-saved-*reg*' command options have been applied.

If the usage of an entire class of registers depends on the target flags, you may indicate this to GCC by using this macro to modify fixed_regs and call_used_regs to 1 for each of the registers in the classes which should not be used by GCC. Also define the macro REG_CLASS_FROM_LETTER / REG_CLASS_FROM_CONSTRAINT to return NO_REGS if it is called with a letter for a class that shouldn't be used.

(However, if this class is not included in GENERAL_REGS and all of the insn patterns whose constraints permit this class are controlled by target switches, then GCC will automatically avoid using these registers when the target switches are opposed to them.)

INCOMING_REGNO (*out*) [Macro]

Define this macro if the target machine has register windows. This C expression returns the register number as seen by the called function corresponding to the register

number *out* as seen by the calling function. Return *out* if register number *out* is not an outbound register.

`OUTGOING_REGNO (in)` [Macro]

Define this macro if the target machine has register windows. This C expression returns the register number as seen by the calling function corresponding to the register number *in* as seen by the called function. Return *in* if register number *in* is not an inbound register.

`LOCAL_REGNO (regno)` [Macro]

Define this macro if the target machine has register windows. This C expression returns true if the register is call-saved but is in the register window. Unlike most call-saved registers, such registers need not be explicitly restored on function exit or during non-local gotos.

`PC_REGNUM` [Macro]

If the program counter has a register number, define this as that register number. Otherwise, do not define it.

17.7.2 Order of Allocation of Registers

Registers are allocated in order.

`REG_ALLOC_ORDER` [Macro]

If defined, an initializer for a vector of integers, containing the numbers of hard registers in the order in which GCC should prefer to use them (from most preferred to least).

If this macro is not defined, registers are used lowest numbered first (all else being equal).

One use of this macro is on machines where the highest numbered registers must always be saved and the save-multiple-registers instruction supports only sequences of consecutive registers. On such machines, define `REG_ALLOC_ORDER` to be an initializer that lists the highest numbered allocable register first.

`ADJUST_REG_ALLOC_ORDER` [Macro]

A C statement (sans semicolon) to choose the order in which to allocate hard registers for pseudo-registers local to a basic block.

Store the desired register order in the array `reg_alloc_order`. Element 0 should be the register to allocate first; element 1, the next register; and so on.

The macro body should not assume anything about the contents of `reg_alloc_order` before execution of the macro.

On most machines, it is not necessary to define this macro.

`HONOR_REG_ALLOC_ORDER` [Macro]

Normally, IRA tries to estimate the costs for saving a register in the prologue and restoring it in the epilogue. This discourages it from using call-saved registers. If a machine wants to ensure that IRA allocates registers in the order given by REG_ALLOC_ORDER even if some call-saved registers appear earlier than call-used ones, this macro should be defined.

`IRA_HARD_REGNO_ADD_COST_MULTIPLIER` (*regno*) [Macro]

In some case register allocation order is not enough for the Integrated Register Allocator (IRA) to generate a good code. If this macro is defined, it should return a floating point value based on *regno*. The cost of using *regno* for a pseudo will be increased by approximately the pseudo's usage frequency times the value returned by this macro. Not defining this macro is equivalent to having it always return `0.0`.

On most machines, it is not necessary to define this macro.

17.7.3 How Values Fit in Registers

This section discusses the macros that describe which kinds of values (specifically, which machine modes) each register can hold, and how many consecutive registers are needed for a given mode.

`HARD_REGNO_NREGS` (*regno*, *mode*) [Macro]

A C expression for the number of consecutive hard registers, starting at register number *regno*, required to hold a value of mode *mode*. This macro must never return zero, even if a register cannot hold the requested mode - indicate that with HARD_REGNO_MODE_OK and/or CANNOT_CHANGE_MODE_CLASS instead.

On a machine where all registers are exactly one word, a suitable definition of this macro is

```
#define HARD_REGNO_NREGS(REGNO, MODE)            \
   ((GET_MODE_SIZE (MODE) + UNITS_PER_WORD - 1)  \
    / UNITS_PER_WORD)
```

`HARD_REGNO_NREGS_HAS_PADDING` (*regno*, *mode*) [Macro]

A C expression that is nonzero if a value of mode *mode*, stored in memory, ends with padding that causes it to take up more space than in registers starting at register number *regno* (as determined by multiplying GCC's notion of the size of the register when containing this mode by the number of registers returned by `HARD_REGNO_NREGS`). By default this is zero.

For example, if a floating-point value is stored in three 32-bit registers but takes up 128 bits in memory, then this would be nonzero.

This macros only needs to be defined if there are cases where `subreg_get_info` would otherwise wrongly determine that a `subreg` can be represented by an offset to the register number, when in fact such a `subreg` would contain some of the padding not stored in registers and so not be representable.

`HARD_REGNO_NREGS_WITH_PADDING` (*regno*, *mode*) [Macro]

For values of *regno* and *mode* for which `HARD_REGNO_NREGS_HAS_PADDING` returns nonzero, a C expression returning the greater number of registers required to hold the value including any padding. In the example above, the value would be four.

`REGMODE_NATURAL_SIZE` (*mode*) [Macro]

Define this macro if the natural size of registers that hold values of mode *mode* is not the word size. It is a C expression that should give the natural size in bytes for the specified mode. It is used by the register allocator to try to optimize its results. This happens for example on SPARC 64-bit where the natural size of floating-point registers is still 32-bit.

`HARD_REGNO_MODE_OK` (*regno*, *mode*) [Macro]

A C expression that is nonzero if it is permissible to store a value of mode *mode* in hard register number *regno* (or in several registers starting with that one). For a machine where all registers are equivalent, a suitable definition is

```
#define HARD_REGNO_MODE_OK(REGNO, MODE) 1
```

You need not include code to check for the numbers of fixed registers, because the allocation mechanism considers them to be always occupied.

On some machines, double-precision values must be kept in even/odd register pairs. You can implement that by defining this macro to reject odd register numbers for such modes.

The minimum requirement for a mode to be OK in a register is that the '`mov`*mode*' instruction pattern support moves between the register and other hard register in the same class and that moving a value into the register and back out not alter it.

Since the same instruction used to move `word_mode` will work for all narrower integer modes, it is not necessary on any machine for `HARD_REGNO_MODE_OK` to distinguish between these modes, provided you define patterns '`movhi`', etc., to take advantage of this. This is useful because of the interaction between `HARD_REGNO_MODE_OK` and `MODES_TIEABLE_P`; it is very desirable for all integer modes to be tieable.

Many machines have special registers for floating point arithmetic. Often people assume that floating point machine modes are allowed only in floating point registers. This is not true. Any registers that can hold integers can safely *hold* a floating point machine mode, whether or not floating arithmetic can be done on it in those registers. Integer move instructions can be used to move the values.

On some machines, though, the converse is true: fixed-point machine modes may not go in floating registers. This is true if the floating registers normalize any value stored in them, because storing a non-floating value there would garble it. In this case, `HARD_REGNO_MODE_OK` should reject fixed-point machine modes in floating registers. But if the floating registers do not automatically normalize, if you can store any bit pattern in one and retrieve it unchanged without a trap, then any machine mode may go in a floating register, so you can define this macro to say so.

The primary significance of special floating registers is rather that they are the registers acceptable in floating point arithmetic instructions. However, this is of no concern to `HARD_REGNO_MODE_OK`. You handle it by writing the proper constraints for those instructions.

On some machines, the floating registers are especially slow to access, so that it is better to store a value in a stack frame than in such a register if floating point arithmetic is not being done. As long as the floating registers are not in class `GENERAL_REGS`, they will not be used unless some pattern's constraint asks for one.

`HARD_REGNO_RENAME_OK` (*from*, *to*) [Macro]

A C expression that is nonzero if it is OK to rename a hard register *from* to another hard register *to*.

One common use of this macro is to prevent renaming of a register to another register that is not saved by a prologue in an interrupt handler.

The default is always nonzero.

`MODES_TIEABLE_P (mode1, mode2)` [Macro]

A C expression that is nonzero if a value of mode *mode1* is accessible in mode *mode2* without copying.

If `HARD_REGNO_MODE_OK (r, mode1)` and `HARD_REGNO_MODE_OK (r, mode2)` are always the same for any *r*, then `MODES_TIEABLE_P (mode1, mode2)` should be nonzero. If they differ for any *r*, you should define this macro to return zero unless some other mechanism ensures the accessibility of the value in a narrower mode.

You should define this macro to return nonzero in as many cases as possible since doing so will allow GCC to perform better register allocation.

`bool TARGET_HARD_REGNO_SCRATCH_OK (unsigned int regno)` [Target Hook]

This target hook should return `true` if it is OK to use a hard register *regno* as scratch reg in peephole2.

One common use of this macro is to prevent using of a register that is not saved by a prologue in an interrupt handler.

The default version of this hook always returns `true`.

`AVOID_CCMODE_COPIES` [Macro]

Define this macro if the compiler should avoid copies to/from `CCmode` registers. You should only define this macro if support for copying to/from `CCmode` is incomplete.

17.7.4 Handling Leaf Functions

On some machines, a leaf function (i.e., one which makes no calls) can run more efficiently if it does not make its own register window. Often this means it is required to receive its arguments in the registers where they are passed by the caller, instead of the registers where they would normally arrive.

The special treatment for leaf functions generally applies only when other conditions are met; for example, often they may use only those registers for its own variables and temporaries. We use the term "leaf function" to mean a function that is suitable for this special handling, so that functions with no calls are not necessarily "leaf functions".

GCC assigns register numbers before it knows whether the function is suitable for leaf function treatment. So it needs to renumber the registers in order to output a leaf function. The following macros accomplish this.

`LEAF_REGISTERS` [Macro]

Name of a char vector, indexed by hard register number, which contains 1 for a register that is allowable in a candidate for leaf function treatment.

If leaf function treatment involves renumbering the registers, then the registers marked here should be the ones before renumbering—those that GCC would ordinarily allocate. The registers which will actually be used in the assembler code, after renumbering, should not be marked with 1 in this vector.

Define this macro only if the target machine offers a way to optimize the treatment of leaf functions.

`LEAF_REG_REMAP (regno)` [Macro]

A C expression whose value is the register number to which *regno* should be renumbered, when a function is treated as a leaf function.

If *regno* is a register number which should not appear in a leaf function before renumbering, then the expression should yield −1, which will cause the compiler to abort.

Define this macro only if the target machine offers a way to optimize the treatment of leaf functions, and registers need to be renumbered to do this.

`TARGET_ASM_FUNCTION_PROLOGUE` and `TARGET_ASM_FUNCTION_EPILOGUE` must usually treat leaf functions specially. They can test the C variable `current_function_is_leaf` which is nonzero for leaf functions. `current_function_is_leaf` is set prior to local register allocation and is valid for the remaining compiler passes. They can also test the C variable `current_function_uses_only_leaf_regs` which is nonzero for leaf functions which only use leaf registers. `current_function_uses_only_leaf_regs` is valid after all passes that modify the instructions have been run and is only useful if `LEAF_REGISTERS` is defined.

17.7.5 Registers That Form a Stack

There are special features to handle computers where some of the "registers" form a stack. Stack registers are normally written by pushing onto the stack, and are numbered relative to the top of the stack.

Currently, GCC can only handle one group of stack-like registers, and they must be consecutively numbered. Furthermore, the existing support for stack-like registers is specific to the 80387 floating point coprocessor. If you have a new architecture that uses stack-like registers, you will need to do substantial work on '`reg-stack.c`' and write your machine description to cooperate with it, as well as defining these macros.

`STACK_REGS` [Macro]

Define this if the machine has any stack-like registers.

`STACK_REG_COVER_CLASS` [Macro]

This is a cover class containing the stack registers. Define this if the machine has any stack-like registers.

`FIRST_STACK_REG` [Macro]

The number of the first stack-like register. This one is the top of the stack.

`LAST_STACK_REG` [Macro]

The number of the last stack-like register. This one is the bottom of the stack.

17.8 Register Classes

On many machines, the numbered registers are not all equivalent. For example, certain registers may not be allowed for indexed addressing; certain registers may not be allowed in some instructions. These machine restrictions are described to the compiler using *register classes*.

You define a number of register classes, giving each one a name and saying which of the registers belong to it. Then you can specify register classes that are allowed as operands to particular instruction patterns.

In general, each register will belong to several classes. In fact, one class must be named `ALL_REGS` and contain all the registers. Another class must be named `NO_REGS` and contain

no registers. Often the union of two classes will be another class; however, this is not required.

One of the classes must be named GENERAL_REGS. There is nothing terribly special about the name, but the operand constraint letters 'r' and 'g' specify this class. If GENERAL_REGS is the same as ALL_REGS, just define it as a macro which expands to ALL_REGS.

Order the classes so that if class *x* is contained in class *y* then *x* has a lower class number than *y*.

The way classes other than GENERAL_REGS are specified in operand constraints is through machine-dependent operand constraint letters. You can define such letters to correspond to various classes, then use them in operand constraints.

You must define the narrowest register classes for allocatable registers, so that each class either has no subclasses, or that for some mode, the move cost between registers within the class is cheaper than moving a register in the class to or from memory (see Section 17.17 [Costs], page 510).

You should define a class for the union of two classes whenever some instruction allows both classes. For example, if an instruction allows either a floating point (coprocessor) register or a general register for a certain operand, you should define a class FLOAT_OR_GENERAL_REGS which includes both of them. Otherwise you will get suboptimal code, or even internal compiler errors when reload cannot find a register in the class computed via reg_class_subunion.

You must also specify certain redundant information about the register classes: for each class, which classes contain it and which ones are contained in it; for each pair of classes, the largest class contained in their union.

When a value occupying several consecutive registers is expected in a certain class, all the registers used must belong to that class. Therefore, register classes cannot be used to enforce a requirement for a register pair to start with an even-numbered register. The way to specify this requirement is with HARD_REGNO_MODE_OK.

Register classes used for input-operands of bitwise-and or shift instructions have a special requirement: each such class must have, for each fixed-point machine mode, a subclass whose registers can transfer that mode to or from memory. For example, on some machines, the operations for single-byte values (QImode) are limited to certain registers. When this is so, each register class that is used in a bitwise-and or shift instruction must have a subclass consisting of registers from which single-byte values can be loaded or stored. This is so that PREFERRED_RELOAD_CLASS can always have a possible value to return.

`enum reg_class` [Data type]

An enumerated type that must be defined with all the register class names as enumerated values. NO_REGS must be first. ALL_REGS must be the last register class, followed by one more enumerated value, LIM_REG_CLASSES, which is not a register class but rather tells how many classes there are.

Each register class has a number, which is the value of casting the class name to type int. The number serves as an index in many of the tables described below.

`N_REG_CLASSES` [Macro]

The number of distinct register classes, defined as follows:

```
#define N_REG_CLASSES (int) LIM_REG_CLASSES
```

`REG_CLASS_NAMES` [Macro]

An initializer containing the names of the register classes as C string constants. These names are used in writing some of the debugging dumps.

`REG_CLASS_CONTENTS` [Macro]

An initializer containing the contents of the register classes, as integers which are bit masks. The *n*th integer specifies the contents of class *n*. The way the integer *mask* is interpreted is that register *r* is in the class if `mask & (1 << r)` is 1.

When the machine has more than 32 registers, an integer does not suffice. Then the integers are replaced by sub-initializers, braced groupings containing several integers. Each sub-initializer must be suitable as an initializer for the type `HARD_REG_SET` which is defined in '`hard-reg-set.h`'. In this situation, the first integer in each sub-initializer corresponds to registers 0 through 31, the second integer to registers 32 through 63, and so on.

`REGNO_REG_CLASS (regno)` [Macro]

A C expression whose value is a register class containing hard register *regno*. In general there is more than one such class; choose a class which is *minimal*, meaning that no smaller class also contains the register.

`BASE_REG_CLASS` [Macro]

A macro whose definition is the name of the class to which a valid base register must belong. A base register is one used in an address which is the register value plus a displacement.

`MODE_BASE_REG_CLASS (mode)` [Macro]

This is a variation of the `BASE_REG_CLASS` macro which allows the selection of a base register in a mode dependent manner. If *mode* is VOIDmode then it should return the same value as `BASE_REG_CLASS`.

`MODE_BASE_REG_REG_CLASS (mode)` [Macro]

A C expression whose value is the register class to which a valid base register must belong in order to be used in a base plus index register address. You should define this macro if base plus index addresses have different requirements than other base register uses.

`MODE_CODE_BASE_REG_CLASS (mode, address_space, outer_code, index_code)` [Macro]

A C expression whose value is the register class to which a valid base register for a memory reference in mode *mode* to address space *address_space* must belong. *outer_code* and *index_code* define the context in which the base register occurs. *outer_code* is the code of the immediately enclosing expression (`MEM` for the top level of an address, `ADDRESS` for something that occurs in an `address_operand`). *index_code* is the code of the corresponding index expression if *outer_code* is `PLUS`; `SCRATCH` otherwise.

`INDEX_REG_CLASS` [Macro]

A macro whose definition is the name of the class to which a valid index register must belong. An index register is one used in an address where its value is either multiplied by a scale factor or added to another register (as well as added to a displacement).

`REGNO_OK_FOR_BASE_P (num)` [Macro]

A C expression which is nonzero if register number *num* is suitable for use as a base register in operand addresses.

`REGNO_MODE_OK_FOR_BASE_P (num, mode)` [Macro]

A C expression that is just like `REGNO_OK_FOR_BASE_P`, except that that expression may examine the mode of the memory reference in *mode*. You should define this macro if the mode of the memory reference affects whether a register may be used as a base register. If you define this macro, the compiler will use it instead of `REGNO_OK_FOR_BASE_P`. The mode may be `VOIDmode` for addresses that appear outside a `MEM`, i.e., as an `address_operand`.

`REGNO_MODE_OK_FOR_REG_BASE_P (num, mode)` [Macro]

A C expression which is nonzero if register number *num* is suitable for use as a base register in base plus index operand addresses, accessing memory in mode *mode*. It may be either a suitable hard register or a pseudo register that has been allocated such a hard register. You should define this macro if base plus index addresses have different requirements than other base register uses.

Use of this macro is deprecated; please use the more general `REGNO_MODE_CODE_OK_FOR_BASE_P`.

`REGNO_MODE_CODE_OK_FOR_BASE_P (num, mode, address_space, outer_code, index_code)` [Macro]

A C expression which is nonzero if register number *num* is suitable for use as a base register in operand addresses, accessing memory in mode *mode* in address space *address_space*. This is similar to `REGNO_MODE_OK_FOR_BASE_P`, except that that expression may examine the context in which the register appears in the memory reference. *outer_code* is the code of the immediately enclosing expression (`MEM` if at the top level of the address, `ADDRESS` for something that occurs in an `address_operand`). *index_code* is the code of the corresponding index expression if *outer_code* is `PLUS`; `SCRATCH` otherwise. The mode may be `VOIDmode` for addresses that appear outside a `MEM`, i.e., as an `address_operand`.

`REGNO_OK_FOR_INDEX_P (num)` [Macro]

A C expression which is nonzero if register number *num* is suitable for use as an index register in operand addresses. It may be either a suitable hard register or a pseudo register that has been allocated such a hard register.

The difference between an index register and a base register is that the index register may be scaled. If an address involves the sum of two registers, neither one of them scaled, then either one may be labeled the "base" and the other the "index"; but whichever labeling is used must fit the machine's constraints of which registers may serve in each capacity. The compiler will try both labelings, looking for one that is valid, and will reload one or both registers only if neither labeling works.

`reg_class_t TARGET_PREFERRED_RENAME_CLASS (reg_class_t rclass)` [Target Hook]

A target hook that places additional preference on the register class to use when it is necessary to rename a register in class *rclass* to another class, or perhaps *NO_REGS*,

if no preferred register class is found or hook `preferred_rename_class` is not implemented. Sometimes returning a more restrictive class makes better code. For example, on ARM, thumb-2 instructions using `LO_REGS` may be smaller than instructions using `GENERIC_REGS`. By returning `LO_REGS` from `preferred_rename_class`, code size can be reduced.

`reg_class_t TARGET_PREFERRED_RELOAD_CLASS` (*rtx* `x`, *reg_class_t* *`rclass`*) [Target Hook]

A target hook that places additional restrictions on the register class to use when it is necessary to copy value *x* into a register in class *rclass*. The value is a register class; perhaps *rclass*, or perhaps another, smaller class.

The default version of this hook always returns value of `rclass` argument.

Sometimes returning a more restrictive class makes better code. For example, on the 68000, when *x* is an integer constant that is in range for a '`moveq`' instruction, the value of this macro is always `DATA_REGS` as long as *rclass* includes the data registers. Requiring a data register guarantees that a '`moveq`' will be used.

One case where `TARGET_PREFERRED_RELOAD_CLASS` must not return *rclass* is if *x* is a legitimate constant which cannot be loaded into some register class. By returning `NO_REGS` you can force *x* into a memory location. For example, rs6000 can load immediate values into general-purpose registers, but does not have an instruction for loading an immediate value into a floating-point register, so `TARGET_PREFERRED_RELOAD_CLASS` returns `NO_REGS` when *x* is a floating-point constant. If the constant can't be loaded into any kind of register, code generation will be better if `TARGET_LEGITIMATE_CONSTANT_P` makes the constant illegitimate instead of using `TARGET_PREFERRED_RELOAD_CLASS`.

If an insn has pseudos in it after register allocation, reload will go through the alternatives and call repeatedly `TARGET_PREFERRED_RELOAD_CLASS` to find the best one. Returning `NO_REGS`, in this case, makes reload add a `!` in front of the constraint: the x86 back-end uses this feature to discourage usage of 387 registers when math is done in the SSE registers (and vice versa).

`PREFERRED_RELOAD_CLASS` (`x`, *`class`*) [Macro]

A C expression that places additional restrictions on the register class to use when it is necessary to copy value *x* into a register in class *class*. The value is a register class; perhaps *class*, or perhaps another, smaller class. On many machines, the following definition is safe:

```
#define PREFERRED_RELOAD_CLASS(X,CLASS) CLASS
```

Sometimes returning a more restrictive class makes better code. For example, on the 68000, when *x* is an integer constant that is in range for a '`moveq`' instruction, the value of this macro is always `DATA_REGS` as long as *class* includes the data registers. Requiring a data register guarantees that a '`moveq`' will be used.

One case where `PREFERRED_RELOAD_CLASS` must not return *class* is if *x* is a legitimate constant which cannot be loaded into some register class. By returning `NO_REGS` you can force *x* into a memory location. For example, rs6000 can load immediate values into general-purpose registers, but does not have an instruction for loading an immediate value into a floating-point register, so `PREFERRED_RELOAD_CLASS` returns

NO_REGS when *x* is a floating-point constant. If the constant can't be loaded into any kind of register, code generation will be better if TARGET_LEGITIMATE_CONSTANT_P makes the constant illegitimate instead of using TARGET_PREFERRED_RELOAD_CLASS.

If an insn has pseudos in it after register allocation, reload will go through the alternatives and call repeatedly PREFERRED_RELOAD_CLASS to find the best one. Returning NO_REGS, in this case, makes reload add a ! in front of the constraint: the x86 backend uses this feature to discourage usage of 387 registers when math is done in the SSE registers (and vice versa).

reg_class_t TARGET_PREFERRED_OUTPUT_RELOAD_CLASS (*rtx* x, *reg_class_t* rclass) [Target Hook]

Like TARGET_PREFERRED_RELOAD_CLASS, but for output reloads instead of input reloads.

The default version of this hook always returns value of rclass argument.

You can also use TARGET_PREFERRED_OUTPUT_RELOAD_CLASS to discourage reload from using some alternatives, like TARGET_PREFERRED_RELOAD_CLASS.

LIMIT_RELOAD_CLASS (*mode*, *class*) [Macro]

A C expression that places additional restrictions on the register class to use when it is necessary to be able to hold a value of mode *mode* in a reload register for which class *class* would ordinarily be used.

Unlike PREFERRED_RELOAD_CLASS, this macro should be used when there are certain modes that simply can't go in certain reload classes.

The value is a register class; perhaps *class*, or perhaps another, smaller class.

Don't define this macro unless the target machine has limitations which require the macro to do something nontrivial.

reg_class_t TARGET_SECONDARY_RELOAD (*bool* in_p, *rtx* x, *reg_class_t* reload_class, *enum machine_mode* reload_mode, *secondary_reload_info* *sri) [Target Hook]

Many machines have some registers that cannot be copied directly to or from memory or even from other types of registers. An example is the 'MQ' register, which on most machines, can only be copied to or from general registers, but not memory. Below, we shall be using the term 'intermediate register' when a move operation cannot be performed directly, but has to be done by copying the source into the intermediate register first, and then copying the intermediate register to the destination. An intermediate register always has the same mode as source and destination. Since it holds the actual value being copied, reload might apply optimizations to re-use an intermediate register and eliding the copy from the source when it can determine that the intermediate register still holds the required value.

Another kind of secondary reload is required on some machines which allow copying all registers to and from memory, but require a scratch register for stores to some memory locations (e.g., those with symbolic address on the RT, and those with certain symbolic address on the SPARC when compiling PIC). Scratch registers need not have the same mode as the value being copied, and usually hold a different value than that being copied. Special patterns in the md file are needed to describe how the copy

is performed with the help of the scratch register; these patterns also describe the number, register class(es) and mode(s) of the scratch register(s).

In some cases, both an intermediate and a scratch register are required.

For input reloads, this target hook is called with nonzero *in_p*, and *x* is an rtx that needs to be copied to a register of class *reload_class* in *reload_mode*. For output reloads, this target hook is called with zero *in_p*, and a register of class *reload_class* needs to be copied to rtx *x* in *reload_mode*.

If copying a register of *reload_class* from/to *x* requires an intermediate register, the hook `secondary_reload` should return the register class required for this intermediate register. If no intermediate register is required, it should return NO_REGS. If more than one intermediate register is required, describe the one that is closest in the copy chain to the reload register.

If scratch registers are needed, you also have to describe how to perform the copy from/to the reload register to/from this closest intermediate register. Or if no intermediate register is required, but still a scratch register is needed, describe the copy from/to the reload register to/from the reload operand *x*.

You do this by setting `sri->icode` to the instruction code of a pattern in the md file which performs the move. Operands 0 and 1 are the output and input of this copy, respectively. Operands from operand 2 onward are for scratch operands. These scratch operands must have a mode, and a single-register-class output constraint.

When an intermediate register is used, the `secondary_reload` hook will be called again to determine how to copy the intermediate register to/from the reload operand *x*, so your hook must also have code to handle the register class of the intermediate operand.

x might be a pseudo-register or a `subreg` of a pseudo-register, which could either be in a hard register or in memory. Use `true_regnum` to find out; it will return −1 if the pseudo is in memory and the hard register number if it is in a register.

Scratch operands in memory (constraint `"=m"` / `"=&m"`) are currently not supported. For the time being, you will have to continue to use `SECONDARY_MEMORY_NEEDED` for that purpose.

`copy_cost` also uses this target hook to find out how values are copied. If you want it to include some extra cost for the need to allocate (a) scratch register(s), set `sri->extra_cost` to the additional cost. Or if two dependent moves are supposed to have a lower cost than the sum of the individual moves due to expected fortuitous scheduling and/or special forwarding logic, you can set `sri->extra_cost` to a negative amount.

`SECONDARY_RELOAD_CLASS` (*class*, *mode*, *x*) [Macro]
`SECONDARY_INPUT_RELOAD_CLASS` (*class*, *mode*, *x*) [Macro]
`SECONDARY_OUTPUT_RELOAD_CLASS` (*class*, *mode*, *x*) [Macro]

These macros are obsolete, new ports should use the target hook `TARGET_SECONDARY_RELOAD` instead.

These are obsolete macros, replaced by the `TARGET_SECONDARY_RELOAD` target hook. Older ports still define these macros to indicate to the reload phase that it may need to allocate at least one register for a reload in addition to the register to contain the data. Specifically, if copying *x* to a register *class* in *mode* requires an intermediate

register, you were supposed to define `SECONDARY_INPUT_RELOAD_CLASS` to return the largest register class all of whose registers can be used as intermediate registers or scratch registers.

If copying a register *class* in *mode* to *x* requires an intermediate or scratch register, `SECONDARY_OUTPUT_RELOAD_CLASS` was supposed to be defined be defined to return the largest register class required. If the requirements for input and output reloads were the same, the macro `SECONDARY_RELOAD_CLASS` should have been used instead of defining both macros identically.

The values returned by these macros are often `GENERAL_REGS`. Return `NO_REGS` if no spare register is needed; i.e., if *x* can be directly copied to or from a register of *class* in *mode* without requiring a scratch register. Do not define this macro if it would always return `NO_REGS`.

If a scratch register is required (either with or without an intermediate register), you were supposed to define patterns for '`reload_in`*m*' or '`reload_out`*m*', as required (see Section 16.9 [Standard Names], page 349. These patterns, which were normally implemented with a `define_expand`, should be similar to the '`mov`*m*' patterns, except that operand 2 is the scratch register.

These patterns need constraints for the reload register and scratch register that contain a single register class. If the original reload register (whose class is *class*) can meet the constraint given in the pattern, the value returned by these macros is used for the class of the scratch register. Otherwise, two additional reload registers are required. Their classes are obtained from the constraints in the insn pattern.

x might be a pseudo-register or a `subreg` of a pseudo-register, which could either be in a hard register or in memory. Use `true_regnum` to find out; it will return −1 if the pseudo is in memory and the hard register number if it is in a register.

These macros should not be used in the case where a particular class of registers can only be copied to memory and not to another class of registers. In that case, secondary reload registers are not needed and would not be helpful. Instead, a stack location must be used to perform the copy and the `mov`*m* pattern should use memory as an intermediate storage. This case often occurs between floating-point and general registers.

`SECONDARY_MEMORY_NEEDED` (*class1*, *class2*, *m*) [Macro]

Certain machines have the property that some registers cannot be copied to some other registers without using memory. Define this macro on those machines to be a C expression that is nonzero if objects of mode *m* in registers of *class1* can only be copied to registers of class *class2* by storing a register of *class1* into memory and loading that memory location into a register of *class2*.

Do not define this macro if its value would always be zero.

`SECONDARY_MEMORY_NEEDED_RTX` (*mode*) [Macro]

Normally when `SECONDARY_MEMORY_NEEDED` is defined, the compiler allocates a stack slot for a memory location needed for register copies. If this macro is defined, the compiler instead uses the memory location defined by this macro.

Do not define this macro if you do not define `SECONDARY_MEMORY_NEEDED`.

`SECONDARY_MEMORY_NEEDED_MODE (mode)` [Macro]

When the compiler needs a secondary memory location to copy between two registers of mode *mode*, it normally allocates sufficient memory to hold a quantity of `BITS_PER_WORD` bits and performs the store and load operations in a mode that many bits wide and whose class is the same as that of *mode*.

This is right thing to do on most machines because it ensures that all bits of the register are copied and prevents accesses to the registers in a narrower mode, which some machines prohibit for floating-point registers.

However, this default behavior is not correct on some machines, such as the DEC Alpha, that store short integers in floating-point registers differently than in integer registers. On those machines, the default widening will not work correctly and you must define this macro to suppress that widening in some cases. See the file '`alpha.h`' for details.

Do not define this macro if you do not define `SECONDARY_MEMORY_NEEDED` or if widening *mode* to a mode that is `BITS_PER_WORD` bits wide is correct for your machine.

`bool TARGET_CLASS_LIKELY_SPILLED_P (`*reg_class_t* `rclass)` [Target Hook]

A target hook which returns `true` if pseudos that have been assigned to registers of class *rclass* would likely be spilled because registers of *rclass* are needed for spill registers.

The default version of this target hook returns `true` if *rclass* has exactly one register and `false` otherwise. On most machines, this default should be used. For generally register-starved machines, such as i386, or machines with right register constraints, such as SH, this hook can be used to avoid excessive spilling.

This hook is also used by some of the global intra-procedural code transformations to throtle code motion, to avoid increasing register pressure.

`unsigned char TARGET_CLASS_MAX_NREGS (`*reg_class_t* `rclass,` *enum machine_mode* `mode)` [Target Hook]

A target hook returns the maximum number of consecutive registers of class *rclass* needed to hold a value of mode *mode*.

This is closely related to the macro `HARD_REGNO_NREGS`. In fact, the value returned by `TARGET_CLASS_MAX_NREGS (rclass, mode)` target hook should be the maximum value of `HARD_REGNO_NREGS (regno, mode)` for all *regno* values in the class *rclass*.

This target hook helps control the handling of multiple-word values in the reload pass.

The default version of this target hook returns the size of *mode* in words.

`CLASS_MAX_NREGS (class, mode)` [Macro]

A C expression for the maximum number of consecutive registers of class *class* needed to hold a value of mode *mode*.

This is closely related to the macro `HARD_REGNO_NREGS`. In fact, the value of the macro `CLASS_MAX_NREGS (class, mode)` should be the maximum value of `HARD_REGNO_NREGS (regno, mode)` for all *regno* values in the class *class*.

This macro helps control the handling of multiple-word values in the reload pass.

`CANNOT_CHANGE_MODE_CLASS` (*from*, *to*, *class*) [Macro]

If defined, a C expression that returns nonzero for a *class* for which a change from mode *from* to mode *to* is invalid.

For the example, loading 32-bit integer or floating-point objects into floating-point registers on the Alpha extends them to 64 bits. Therefore loading a 64-bit object and then storing it as a 32-bit object does not store the low-order 32 bits, as would be the case for a normal register. Therefore, '`alpha.h`' defines `CANNOT_CHANGE_MODE_CLASS` as below:

```
#define CANNOT_CHANGE_MODE_CLASS(FROM, TO, CLASS) \
  (GET_MODE_SIZE (FROM) != GET_MODE_SIZE (TO) \
   ? reg_classes_intersect_p (FLOAT_REGS, (CLASS)) : 0)
```

`bool TARGET_LRA_P` (*void*) [Target Hook]

A target hook which returns true if we use LRA instead of reload pass. It means that LRA was ported to the target. The default version of this target hook returns always false.

`int TARGET_REGISTER_PRIORITY` (*int*) [Target Hook]

A target hook which returns the register priority number to which the register *hard_regno* belongs to. The bigger the number, the more preferable the hard register usage (when all other conditions are the same). This hook can be used to prefer some hard register over others in LRA. For example, some x86-64 register usage needs additional prefix which makes instructions longer. The hook can return lower priority number for such registers make them less favorable and as result making the generated code smaller. The default version of this target hook returns always zero.

`bool TARGET_REGISTER_USAGE_LEVELING_P` (*void*) [Target Hook]

A target hook which returns true if we need register usage leveling. That means if a few hard registers are equally good for the assignment, we choose the least used hard register. The register usage leveling may be profitable for some targets. Don't use the usage leveling for targets with conditional execution or targets with big register files as it hurts if-conversion and cross-jumping optimizations. The default version of this target hook returns always false.

`bool TARGET_DIFFERENT_ADDR_DISPLACEMENT_P` (*void*) [Target Hook]

A target hook which returns true if an address with the same structure can have different maximal legitimate displacement. For example, the displacement can depend on memory mode or on operand combinations in the insn. The default version of this target hook returns always false.

`reg_class_t TARGET_SPILL_CLASS` (*reg_class_t*, *enum machine_mode*) [Target Hook]

This hook defines a class of registers which could be used for spilling pseudos of the given mode and class, or `NO_REGS` if only memory should be used. Not defining this hook is equivalent to returning `NO_REGS` for all inputs.

`enum machine_mode TARGET_CSTORE_MODE` (*enum insn_code icode*) [Target Hook]

This hook defines the machine mode to use for the boolean result of conditional store patterns. The ICODE argument is the instruction code for the cstore being

performed. Not definiting this hook is the same as accepting the mode encoded into operand 0 of the cstore expander patterns.

17.9 Obsolete Macros for Defining Constraints

Machine-specific constraints can be defined with these macros instead of the machine description constructs described in Section 16.8.7 [Define Constraints], page 346. This mechanism is obsolete. New ports should not use it; old ports should convert to the new mechanism.

`CONSTRAINT_LEN` (*char*, *str*) [Macro]

For the constraint at the start of *str*, which starts with the letter *c*, return the length. This allows you to have register class / constant / extra constraints that are longer than a single letter; you don't need to define this macro if you can do with single-letter constraints only. The definition of this macro should use DEFAULT_CONSTRAINT_LEN for all the characters that you don't want to handle specially. There are some sanity checks in genoutput.c that check the constraint lengths for the md file, so you can also use this macro to help you while you are transitioning from a byzantine single-letter-constraint scheme: when you return a negative length for a constraint you want to re-use, genoutput will complain about every instance where it is used in the md file.

`REG_CLASS_FROM_LETTER` (*char*) [Macro]

A C expression which defines the machine-dependent operand constraint letters for register classes. If *char* is such a letter, the value should be the register class corresponding to it. Otherwise, the value should be `NO_REGS`. The register letter '`r`', corresponding to class `GENERAL_REGS`, will not be passed to this macro; you do not need to handle it.

`REG_CLASS_FROM_CONSTRAINT` (*char*, *str*) [Macro]

Like `REG_CLASS_FROM_LETTER`, but you also get the constraint string passed in *str*, so that you can use suffixes to distinguish between different variants.

`CONST_OK_FOR_LETTER_P` (*value*, *c*) [Macro]

A C expression that defines the machine-dependent operand constraint letters ('`I`', '`J`', '`K`', . . . '`P`') that specify particular ranges of integer values. If *c* is one of those letters, the expression should check that *value*, an integer, is in the appropriate range and return 1 if so, 0 otherwise. If *c* is not one of those letters, the value should be 0 regardless of *value*.

`CONST_OK_FOR_CONSTRAINT_P` (*value*, *c*, *str*) [Macro]

Like `CONST_OK_FOR_LETTER_P`, but you also get the constraint string passed in *str*, so that you can use suffixes to distinguish between different variants.

`CONST_DOUBLE_OK_FOR_LETTER_P` (*value*, *c*) [Macro]

A C expression that defines the machine-dependent operand constraint letters that specify particular ranges of `const_double` values ('`G`' or '`H`').

If *c* is one of those letters, the expression should check that *value*, an RTX of code `const_double`, is in the appropriate range and return 1 if so, 0 otherwise. If *c* is not one of those letters, the value should be 0 regardless of *value*.

`const_double` is used for all floating-point constants and for `DImode` fixed-point constants. A given letter can accept either or both kinds of values. It can use `GET_MODE` to distinguish between these kinds.

`CONST_DOUBLE_OK_FOR_CONSTRAINT_P` (*value*, *c*, *str*) [Macro]

Like `CONST_DOUBLE_OK_FOR_LETTER_P`, but you also get the constraint string passed in *str*, so that you can use suffixes to distinguish between different variants.

`EXTRA_CONSTRAINT` (*value*, *c*) [Macro]

A C expression that defines the optional machine-dependent constraint letters that can be used to segregate specific types of operands, usually memory references, for the target machine. Any letter that is not elsewhere defined and not matched by `REG_CLASS_FROM_LETTER` / `REG_CLASS_FROM_CONSTRAINT` may be used. Normally this macro will not be defined.

If it is required for a particular target machine, it should return 1 if *value* corresponds to the operand type represented by the constraint letter *c*. If *c* is not defined as an extra constraint, the value returned should be 0 regardless of *value*.

For example, on the ROMP, load instructions cannot have their output in r0 if the memory reference contains a symbolic address. Constraint letter '`Q`' is defined as representing a memory address that does *not* contain a symbolic address. An alternative is specified with a '`Q`' constraint on the input and '`r`' on the output. The next alternative specifies '`m`' on the input and a register class that does not include r0 on the output.

`EXTRA_CONSTRAINT_STR` (*value*, *c*, *str*) [Macro]

Like `EXTRA_CONSTRAINT`, but you also get the constraint string passed in *str*, so that you can use suffixes to distinguish between different variants.

`EXTRA_MEMORY_CONSTRAINT` (*c*, *str*) [Macro]

A C expression that defines the optional machine-dependent constraint letters, amongst those accepted by `EXTRA_CONSTRAINT`, that should be treated like memory constraints by the reload pass.

It should return 1 if the operand type represented by the constraint at the start of *str*, the first letter of which is the letter *c*, comprises a subset of all memory references including all those whose address is simply a base register. This allows the reload pass to reload an operand, if it does not directly correspond to the operand type of *c*, by copying its address into a base register.

For example, on the S/390, some instructions do not accept arbitrary memory references, but only those that do not make use of an index register. The constraint letter '`Q`' is defined via `EXTRA_CONSTRAINT` as representing a memory address of this type. If the letter '`Q`' is marked as `EXTRA_MEMORY_CONSTRAINT`, a '`Q`' constraint can handle any memory operand, because the reload pass knows it can be reloaded by copying the memory address into a base register if required. This is analogous to the way an '`o`' constraint can handle any memory operand.

`EXTRA_ADDRESS_CONSTRAINT` (*c*, *str*) [Macro]

A C expression that defines the optional machine-dependent constraint letters, amongst those accepted by `EXTRA_CONSTRAINT` / `EXTRA_CONSTRAINT_STR`, that should be treated like address constraints by the reload pass.

It should return 1 if the operand type represented by the constraint at the start of *str*, which starts with the letter *c*, comprises a subset of all memory addresses including all those that consist of just a base register. This allows the reload pass to reload an operand, if it does not directly correspond to the operand type of *str*, by copying it into a base register.

Any constraint marked as `EXTRA_ADDRESS_CONSTRAINT` can only be used with the `address_operand` predicate. It is treated analogously to the '`p`' constraint.

17.10 Stack Layout and Calling Conventions

This describes the stack layout and calling conventions.

17.10.1 Basic Stack Layout

Here is the basic stack layout.

`STACK_GROWS_DOWNWARD` [Macro]

Define this macro if pushing a word onto the stack moves the stack pointer to a smaller address.

When we say, "define this macro if . . .", it means that the compiler checks this macro only with `#ifdef` so the precise definition used does not matter.

`STACK_PUSH_CODE` [Macro]

This macro defines the operation used when something is pushed on the stack. In RTL, a push operation will be `(set (mem (STACK_PUSH_CODE (reg sp))) ...)`

The choices are `PRE_DEC`, `POST_DEC`, `PRE_INC`, and `POST_INC`. Which of these is correct depends on the stack direction and on whether the stack pointer points to the last item on the stack or whether it points to the space for the next item on the stack.

The default is `PRE_DEC` when `STACK_GROWS_DOWNWARD` is defined, which is almost always right, and `PRE_INC` otherwise, which is often wrong.

`FRAME_GROWS_DOWNWARD` [Macro]

Define this macro to nonzero value if the addresses of local variable slots are at negative offsets from the frame pointer.

`ARGS_GROW_DOWNWARD` [Macro]

Define this macro if successive arguments to a function occupy decreasing addresses on the stack.

`STARTING_FRAME_OFFSET` [Macro]

Offset from the frame pointer to the first local variable slot to be allocated.

If `FRAME_GROWS_DOWNWARD`, find the next slot's offset by subtracting the first slot's length from `STARTING_FRAME_OFFSET`. Otherwise, it is found by adding the length of the first slot to the value `STARTING_FRAME_OFFSET`.

`STACK_ALIGNMENT_NEEDED` [Macro]

Define to zero to disable final alignment of the stack during reload. The nonzero default for this macro is suitable for most ports.

On ports where STARTING_FRAME_OFFSET is nonzero or where there is a register save block following the local block that doesn't require alignment to STACK_BOUNDARY, it may be beneficial to disable stack alignment and do it in the backend.

STACK_POINTER_OFFSET [Macro]

Offset from the stack pointer register to the first location at which outgoing arguments are placed. If not specified, the default value of zero is used. This is the proper value for most machines.

If ARGS_GROW_DOWNWARD, this is the offset to the location above the first location at which outgoing arguments are placed.

FIRST_PARM_OFFSET (*fundecl*) [Macro]

Offset from the argument pointer register to the first argument's address. On some machines it may depend on the data type of the function.

If ARGS_GROW_DOWNWARD, this is the offset to the location above the first argument's address.

STACK_DYNAMIC_OFFSET (*fundecl*) [Macro]

Offset from the stack pointer register to an item dynamically allocated on the stack, e.g., by alloca.

The default value for this macro is STACK_POINTER_OFFSET plus the length of the outgoing arguments. The default is correct for most machines. See 'function.c' for details.

INITIAL_FRAME_ADDRESS_RTX [Macro]

A C expression whose value is RTL representing the address of the initial stack frame. This address is passed to RETURN_ADDR_RTX and DYNAMIC_CHAIN_ADDRESS. If you don't define this macro, a reasonable default value will be used. Define this macro in order to make frame pointer elimination work in the presence of __builtin_frame_address (count) and __builtin_return_address (count) for count not equal to zero.

DYNAMIC_CHAIN_ADDRESS (*frameaddr*) [Macro]

A C expression whose value is RTL representing the address in a stack frame where the pointer to the caller's frame is stored. Assume that *frameaddr* is an RTL expression for the address of the stack frame itself.

If you don't define this macro, the default is to return the value of *frameaddr*—that is, the stack frame address is also the address of the stack word that points to the previous frame.

SETUP_FRAME_ADDRESSES [Macro]

If defined, a C expression that produces the machine-specific code to setup the stack so that arbitrary frames can be accessed. For example, on the SPARC, we must flush all of the register windows to the stack before we can access arbitrary stack frames. You will seldom need to define this macro.

rtx TARGET_BUILTIN_SETJMP_FRAME_VALUE (*void*) [Target Hook]

This target hook should return an rtx that is used to store the address of the current frame into the built in setjmp buffer. The default value, virtual_stack_vars_rtx,

is correct for most machines. One reason you may need to define this target hook is if `hard_frame_pointer_rtx` is the appropriate value on your machine.

`FRAME_ADDR_RTX (frameaddr)` [Macro]

A C expression whose value is RTL representing the value of the frame address for the current frame. *frameaddr* is the frame pointer of the current frame. This is used for __builtin_frame_address. You need only define this macro if the frame address is not the same as the frame pointer. Most machines do not need to define it.

`RETURN_ADDR_RTX (count, frameaddr)` [Macro]

A C expression whose value is RTL representing the value of the return address for the frame *count* steps up from the current frame, after the prologue. *frameaddr* is the frame pointer of the *count* frame, or the frame pointer of the *count* − 1 frame if `RETURN_ADDR_IN_PREVIOUS_FRAME` is defined.

The value of the expression must always be the correct address when *count* is zero, but may be `NULL_RTX` if there is no way to determine the return address of other frames.

`RETURN_ADDR_IN_PREVIOUS_FRAME` [Macro]

Define this if the return address of a particular stack frame is accessed from the frame pointer of the previous stack frame.

`INCOMING_RETURN_ADDR_RTX` [Macro]

A C expression whose value is RTL representing the location of the incoming return address at the beginning of any function, before the prologue. This RTL is either a `REG`, indicating that the return value is saved in '`REG`', or a `MEM` representing a location in the stack.

You only need to define this macro if you want to support call frame debugging information like that provided by DWARF 2.

If this RTL is a `REG`, you should also define `DWARF_FRAME_RETURN_COLUMN` to `DWARF_FRAME_REGNUM (REGNO)`.

`DWARF_ALT_FRAME_RETURN_COLUMN` [Macro]

A C expression whose value is an integer giving a DWARF 2 column number that may be used as an alternative return column. The column must not correspond to any gcc hard register (that is, it must not be in the range of `DWARF_FRAME_REGNUM`).

This macro can be useful if `DWARF_FRAME_RETURN_COLUMN` is set to a general register, but an alternative column needs to be used for signal frames. Some targets have also used different frame return columns over time.

`DWARF_ZERO_REG` [Macro]

A C expression whose value is an integer giving a DWARF 2 register number that is considered to always have the value zero. This should only be defined if the target has an architected zero register, and someone decided it was a good idea to use that register number to terminate the stack backtrace. New ports should avoid this.

void TARGET_DWARF_HANDLE_FRAME_UNSPEC (*const char* **label*, *rtx* *pattern*, *int* *index*) [Target Hook]

This target hook allows the backend to emit frame-related insns that contain UNSPECs or UNSPEC_VOLATILEs. The DWARF 2 call frame debugging info engine will invoke it on insns of the form

```
(set (reg) (unspec [...] UNSPEC_INDEX))
```

and

```
(set (reg) (unspec_volatile [...] UNSPECV_INDEX)).
```

to let the backend emit the call frame instructions. *label* is the CFI label attached to the insn, *pattern* is the pattern of the insn and *index* is `UNSPEC_INDEX` or `UNSPECV_INDEX`.

INCOMING_FRAME_SP_OFFSET [Macro]

A C expression whose value is an integer giving the offset, in bytes, from the value of the stack pointer register to the top of the stack frame at the beginning of any function, before the prologue. The top of the frame is defined to be the value of the stack pointer in the previous frame, just before the call instruction.

You only need to define this macro if you want to support call frame debugging information like that provided by DWARF 2.

ARG_POINTER_CFA_OFFSET (*fundecl*) [Macro]

A C expression whose value is an integer giving the offset, in bytes, from the argument pointer to the canonical frame address (cfa). The final value should coincide with that calculated by `INCOMING_FRAME_SP_OFFSET`. Which is unfortunately not usable during virtual register instantiation.

The default value for this macro is `FIRST_PARM_OFFSET (fundecl) + crtl->args.pretend_args_size`, which is correct for most machines; in general, the arguments are found immediately before the stack frame. Note that this is not the case on some targets that save registers into the caller's frame, such as SPARC and rs6000, and so such targets need to define this macro.

You only need to define this macro if the default is incorrect, and you want to support call frame debugging information like that provided by DWARF 2.

FRAME_POINTER_CFA_OFFSET (*fundecl*) [Macro]

If defined, a C expression whose value is an integer giving the offset in bytes from the frame pointer to the canonical frame address (cfa). The final value should coincide with that calculated by `INCOMING_FRAME_SP_OFFSET`.

Normally the CFA is calculated as an offset from the argument pointer, via `ARG_POINTER_CFA_OFFSET`, but if the argument pointer is variable due to the ABI, this may not be possible. If this macro is defined, it implies that the virtual register instantiation should be based on the frame pointer instead of the argument pointer. Only one of `FRAME_POINTER_CFA_OFFSET` and `ARG_POINTER_CFA_OFFSET` should be defined.

CFA_FRAME_BASE_OFFSET (*fundecl*) [Macro]

If defined, a C expression whose value is an integer giving the offset in bytes from the canonical frame address (cfa) to the frame base used in DWARF 2 debug information.

The default is zero. A different value may reduce the size of debug information on some ports.

17.10.2 Exception Handling Support

`EH_RETURN_DATA_REGNO (N)` [Macro]

A C expression whose value is the Nth register number used for data by exception handlers, or `INVALID_REGNUM` if fewer than N registers are usable.

The exception handling library routines communicate with the exception handlers via a set of agreed upon registers. Ideally these registers should be call-clobbered; it is possible to use call-saved registers, but may negatively impact code size. The target must support at least 2 data registers, but should define 4 if there are enough free registers.

You must define this macro if you want to support call frame exception handling like that provided by DWARF 2.

`EH_RETURN_STACKADJ_RTX` [Macro]

A C expression whose value is RTL representing a location in which to store a stack adjustment to be applied before function return. This is used to unwind the stack to an exception handler's call frame. It will be assigned zero on code paths that return normally.

Typically this is a call-clobbered hard register that is otherwise untouched by the epilogue, but could also be a stack slot.

Do not define this macro if the stack pointer is saved and restored by the regular prolog and epilog code in the call frame itself; in this case, the exception handling library routines will update the stack location to be restored in place. Otherwise, you must define this macro if you want to support call frame exception handling like that provided by DWARF 2.

`EH_RETURN_HANDLER_RTX` [Macro]

A C expression whose value is RTL representing a location in which to store the address of an exception handler to which we should return. It will not be assigned on code paths that return normally.

Typically this is the location in the call frame at which the normal return address is stored. For targets that return by popping an address off the stack, this might be a memory address just below the *target* call frame rather than inside the current call frame. If defined, `EH_RETURN_STACKADJ_RTX` will have already been assigned, so it may be used to calculate the location of the target call frame.

Some targets have more complex requirements than storing to an address calculable during initial code generation. In that case the `eh_return` instruction pattern should be used instead.

If you want to support call frame exception handling, you must define either this macro or the `eh_return` instruction pattern.

`RETURN_ADDR_OFFSET` [Macro]

If defined, an integer-valued C expression for which rtl will be generated to add it to the exception handler address before it is searched in the exception handling tables,

and to subtract it again from the address before using it to return to the exception handler.

`ASM_PREFERRED_EH_DATA_FORMAT` (*code*, *global*) [Macro]

This macro chooses the encoding of pointers embedded in the exception handling sections. If at all possible, this should be defined such that the exception handling section will not require dynamic relocations, and so may be read-only.

code is 0 for data, 1 for code labels, 2 for function pointers. *global* is true if the symbol may be affected by dynamic relocations. The macro should return a combination of the `DW_EH_PE_*` defines as found in '`dwarf2.h`'.

If this macro is not defined, pointers will not be encoded but represented directly.

`ASM_MAYBE_OUTPUT_ENCODED_ADDR_RTX` (*file*, *encoding*, *size*, *addr*, *done*) [Macro]

This macro allows the target to emit whatever special magic is required to represent the encoding chosen by `ASM_PREFERRED_EH_DATA_FORMAT`. Generic code takes care of pc-relative and indirect encodings; this must be defined if the target uses text-relative or data-relative encodings.

This is a C statement that branches to *done* if the format was handled. *encoding* is the format chosen, *size* is the number of bytes that the format occupies, *addr* is the `SYMBOL_REF` to be emitted.

`MD_FALLBACK_FRAME_STATE_FOR` (*context*, *fs*) [Macro]

This macro allows the target to add CPU and operating system specific code to the call-frame unwinder for use when there is no unwind data available. The most common reason to implement this macro is to unwind through signal frames.

This macro is called from `uw_frame_state_for` in '`unwind-dw2.c`', '`unwind-dw2-xtensa.c`' and '`unwind-ia64.c`'. *context* is an `_Unwind_Context`; *fs* is an `_Unwind_FrameState`. Examine `context->ra` for the address of the code being executed and `context->cfa` for the stack pointer value. If the frame can be decoded, the register save addresses should be updated in *fs* and the macro should evaluate to `_URC_NO_REASON`. If the frame cannot be decoded, the macro should evaluate to `_URC_END_OF_STACK`.

For proper signal handling in Java this macro is accompanied by `MAKE_THROW_FRAME`, defined in '`libjava/include/*-signal.h`' headers.

`MD_HANDLE_UNWABI` (*context*, *fs*) [Macro]

This macro allows the target to add operating system specific code to the call-frame unwinder to handle the IA-64 `.unwabi` unwinding directive, usually used for signal or interrupt frames.

This macro is called from `uw_update_context` in libgcc's '`unwind-ia64.c`'. *context* is an `_Unwind_Context`; *fs* is an `_Unwind_FrameState`. Examine `fs->unwabi` for the abi and context in the `.unwabi` directive. If the `.unwabi` directive can be handled, the register save addresses should be updated in *fs*.

`TARGET_USES_WEAK_UNWIND_INFO` [Macro]

A C expression that evaluates to true if the target requires unwind info to be given comdat linkage. Define it to be `1` if comdat linkage is necessary. The default is `0`.

17.10.3 Specifying How Stack Checking is Done

GCC will check that stack references are within the boundaries of the stack, if the option '`-fstack-check`' is specified, in one of three ways:

1. If the value of the `STACK_CHECK_BUILTIN` macro is nonzero, GCC will assume that you have arranged for full stack checking to be done at appropriate places in the configuration files. GCC will not do other special processing.
2. If `STACK_CHECK_BUILTIN` is zero and the value of the `STACK_CHECK_STATIC_BUILTIN` macro is nonzero, GCC will assume that you have arranged for static stack checking (checking of the static stack frame of functions) to be done at appropriate places in the configuration files. GCC will only emit code to do dynamic stack checking (checking on dynamic stack allocations) using the third approach below.
3. If neither of the above are true, GCC will generate code to periodically "probe" the stack pointer using the values of the macros defined below.

If neither STACK_CHECK_BUILTIN nor STACK_CHECK_STATIC_BUILTIN is defined, GCC will change its allocation strategy for large objects if the option '`-fstack-check`' is specified: they will always be allocated dynamically if their size exceeds `STACK_CHECK_MAX_VAR_SIZE` bytes.

`STACK_CHECK_BUILTIN` [Macro]

A nonzero value if stack checking is done by the configuration files in a machine-dependent manner. You should define this macro if stack checking is required by the ABI of your machine or if you would like to do stack checking in some more efficient way than the generic approach. The default value of this macro is zero.

`STACK_CHECK_STATIC_BUILTIN` [Macro]

A nonzero value if static stack checking is done by the configuration files in a machine-dependent manner. You should define this macro if you would like to do static stack checking in some more efficient way than the generic approach. The default value of this macro is zero.

`STACK_CHECK_PROBE_INTERVAL_EXP` [Macro]

An integer specifying the interval at which GCC must generate stack probe instructions, defined as 2 raised to this integer. You will normally define this macro so that the interval be no larger than the size of the "guard pages" at the end of a stack area. The default value of 12 (4096-byte interval) is suitable for most systems.

`STACK_CHECK_MOVING_SP` [Macro]

An integer which is nonzero if GCC should move the stack pointer page by page when doing probes. This can be necessary on systems where the stack pointer contains the bottom address of the memory area accessible to the executing thread at any point in time. In this situation an alternate signal stack is required in order to be able to recover from a stack overflow. The default value of this macro is zero.

`STACK_CHECK_PROTECT` [Macro]

The number of bytes of stack needed to recover from a stack overflow, for languages where such a recovery is supported. The default value of 75 words with the `setjmp/longjmp`-based exception handling mechanism and 8192 bytes with other exception handling mechanisms should be adequate for most machines.

The following macros are relevant only if neither STACK_CHECK_BUILTIN nor STACK_CHECK_STATIC_BUILTIN is defined; you can omit them altogether in the opposite case.

`STACK_CHECK_MAX_FRAME_SIZE` [Macro]

The maximum size of a stack frame, in bytes. GCC will generate probe instructions in non-leaf functions to ensure at least this many bytes of stack are available. If a stack frame is larger than this size, stack checking will not be reliable and GCC will issue a warning. The default is chosen so that GCC only generates one instruction on most systems. You should normally not change the default value of this macro.

`STACK_CHECK_FIXED_FRAME_SIZE` [Macro]

GCC uses this value to generate the above warning message. It represents the amount of fixed frame used by a function, not including space for any callee-saved registers, temporaries and user variables. You need only specify an upper bound for this amount and will normally use the default of four words.

`STACK_CHECK_MAX_VAR_SIZE` [Macro]

The maximum size, in bytes, of an object that GCC will place in the fixed area of the stack frame when the user specifies '`-fstack-check`'. GCC computed the default from the values of the above macros and you will normally not need to override that default.

17.10.4 Registers That Address the Stack Frame

This discusses registers that address the stack frame.

`STACK_POINTER_REGNUM` [Macro]

The register number of the stack pointer register, which must also be a fixed register according to `FIXED_REGISTERS`. On most machines, the hardware determines which register this is.

`FRAME_POINTER_REGNUM` [Macro]

The register number of the frame pointer register, which is used to access automatic variables in the stack frame. On some machines, the hardware determines which register this is. On other machines, you can choose any register you wish for this purpose.

`HARD_FRAME_POINTER_REGNUM` [Macro]

On some machines the offset between the frame pointer and starting offset of the automatic variables is not known until after register allocation has been done (for example, because the saved registers are between these two locations). On those machines, define `FRAME_POINTER_REGNUM` the number of a special, fixed register to be used internally until the offset is known, and define `HARD_FRAME_POINTER_REGNUM` to be the actual hard register number used for the frame pointer.

You should define this macro only in the very rare circumstances when it is not possible to calculate the offset between the frame pointer and the automatic variables until after register allocation has been completed. When this macro is defined, you must also indicate in your definition of `ELIMINABLE_REGS` how to eliminate `FRAME_POINTER_REGNUM` into either `HARD_FRAME_POINTER_REGNUM` or `STACK_POINTER_REGNUM`.

Do not define this macro if it would be the same as FRAME_POINTER_REGNUM.

ARG_POINTER_REGNUM [Macro]

The register number of the arg pointer register, which is used to access the function's argument list. On some machines, this is the same as the frame pointer register. On some machines, the hardware determines which register this is. On other machines, you can choose any register you wish for this purpose. If this is not the same register as the frame pointer register, then you must mark it as a fixed register according to FIXED_REGISTERS, or arrange to be able to eliminate it (see Section 17.10.5 [Elimination], page 475).

HARD_FRAME_POINTER_IS_FRAME_POINTER [Macro]

Define this to a preprocessor constant that is nonzero if hard_frame_pointer_rtx and frame_pointer_rtx should be the same. The default definition is '(HARD_FRAME_POINTER_REGNUM == FRAME_POINTER_REGNUM)'; you only need to define this macro if that definition is not suitable for use in preprocessor conditionals.

HARD_FRAME_POINTER_IS_ARG_POINTER [Macro]

Define this to a preprocessor constant that is nonzero if hard_frame_pointer_rtx and arg_pointer_rtx should be the same. The default definition is '(HARD_FRAME_POINTER_REGNUM == ARG_POINTER_REGNUM)'; you only need to define this macro if that definition is not suitable for use in preprocessor conditionals.

RETURN_ADDRESS_POINTER_REGNUM [Macro]

The register number of the return address pointer register, which is used to access the current function's return address from the stack. On some machines, the return address is not at a fixed offset from the frame pointer or stack pointer or argument pointer. This register can be defined to point to the return address on the stack, and then be converted by ELIMINABLE_REGS into either the frame pointer or stack pointer.

Do not define this macro unless there is no other way to get the return address from the stack.

STATIC_CHAIN_REGNUM [Macro]
STATIC_CHAIN_INCOMING_REGNUM [Macro]

Register numbers used for passing a function's static chain pointer. If register windows are used, the register number as seen by the called function is STATIC_CHAIN_INCOMING_REGNUM, while the register number as seen by the calling function is STATIC_CHAIN_REGNUM. If these registers are the same, STATIC_CHAIN_INCOMING_REGNUM need not be defined.

The static chain register need not be a fixed register.

If the static chain is passed in memory, these macros should not be defined; instead, the TARGET_STATIC_CHAIN hook should be used.

rtx TARGET_STATIC_CHAIN (*const_tree* ***fndecl***, *bool* ***incoming_p***) [Target Hook]

This hook replaces the use of STATIC_CHAIN_REGNUM et al for targets that may use different static chain locations for different nested functions. This may be required if the target has function attributes that affect the calling conventions of the function and those calling conventions use different static chain locations.

The default version of this hook uses `STATIC_CHAIN_REGNUM` et al.

If the static chain is passed in memory, this hook should be used to provide rtx giving `mem` expressions that denote where they are stored. Often the `mem` expression as seen by the caller will be at an offset from the stack pointer and the `mem` expression as seen by the callee will be at an offset from the frame pointer. The variables `stack_pointer_rtx`, `frame_pointer_rtx`, and `arg_pointer_rtx` will have been initialized and should be used to refer to those items.

`DWARF_FRAME_REGISTERS` [Macro]

This macro specifies the maximum number of hard registers that can be saved in a call frame. This is used to size data structures used in DWARF2 exception handling.

Prior to GCC 3.0, this macro was needed in order to establish a stable exception handling ABI in the face of adding new hard registers for ISA extensions. In GCC 3.0 and later, the EH ABI is insulated from changes in the number of hard registers. Nevertheless, this macro can still be used to reduce the runtime memory requirements of the exception handling routines, which can be substantial if the ISA contains a lot of registers that are not call-saved.

If this macro is not defined, it defaults to `FIRST_PSEUDO_REGISTER`.

`PRE_GCC3_DWARF_FRAME_REGISTERS` [Macro]

This macro is similar to `DWARF_FRAME_REGISTERS`, but is provided for backward compatibility in pre GCC 3.0 compiled code.

If this macro is not defined, it defaults to `DWARF_FRAME_REGISTERS`.

`DWARF_REG_TO_UNWIND_COLUMN (`*`regno`*`)` [Macro]

Define this macro if the target's representation for dwarf registers is different than the internal representation for unwind column. Given a dwarf register, this macro should return the internal unwind column number to use instead.

See the PowerPC's SPE target for an example.

`DWARF_FRAME_REGNUM (`*`regno`*`)` [Macro]

Define this macro if the target's representation for dwarf registers used in .eh_frame or .debug_frame is different from that used in other debug info sections. Given a GCC hard register number, this macro should return the .eh_frame register number. The default is `DBX_REGISTER_NUMBER (`*`regno`*`)`.

`DWARF2_FRAME_REG_OUT (`*`regno`*`, `*`for_eh`*`)` [Macro]

Define this macro to map register numbers held in the call frame info that GCC has collected using `DWARF_FRAME_REGNUM` to those that should be output in .debug_frame (*`for_eh`* is zero) and .eh_frame (*`for_eh`* is nonzero). The default is to return *`regno`*.

`REG_VALUE_IN_UNWIND_CONTEXT` [Macro]

Define this macro if the target stores register values as `_Unwind_Word` type in unwind context. It should be defined if target register size is larger than the size of `void *`. The default is to store register values as `void *` type.

`ASSUME_EXTENDED_UNWIND_CONTEXT` [Macro]

Define this macro to be 1 if the target always uses extended unwind context with version, args_size and by_value fields. If it is undefined, it will be defined to 1 when `REG_VALUE_IN_UNWIND_CONTEXT` is defined and 0 otherwise.

17.10.5 Eliminating Frame Pointer and Arg Pointer

This is about eliminating the frame pointer and arg pointer.

`bool TARGET_FRAME_POINTER_REQUIRED (void)` [Target Hook]

This target hook should return `true` if a function must have and use a frame pointer. This target hook is called in the reload pass. If its return value is `true` the function will have a frame pointer.

This target hook can in principle examine the current function and decide according to the facts, but on most machines the constant `false` or the constant `true` suffices. Use `false` when the machine allows code to be generated with no frame pointer, and doing so saves some time or space. Use `true` when there is no possible advantage to avoiding a frame pointer.

In certain cases, the compiler does not know how to produce valid code without a frame pointer. The compiler recognizes those cases and automatically gives the function a frame pointer regardless of what `TARGET_FRAME_POINTER_REQUIRED` returns. You don't need to worry about them.

In a function that does not require a frame pointer, the frame pointer register can be allocated for ordinary usage, unless you mark it as a fixed register. See `FIXED_REGISTERS` for more information.

Default return value is `false`.

`INITIAL_FRAME_POINTER_OFFSET (depth-var)` [Macro]

A C statement to store in the variable *depth-var* the difference between the frame pointer and the stack pointer values immediately after the function prologue. The value would be computed from information such as the result of `get_frame_size ()` and the tables of registers `regs_ever_live` and `call_used_regs`.

If `ELIMINABLE_REGS` is defined, this macro will be not be used and need not be defined. Otherwise, it must be defined even if `TARGET_FRAME_POINTER_REQUIRED` always returns true; in that case, you may set *depth-var* to anything.

`ELIMINABLE_REGS` [Macro]

If defined, this macro specifies a table of register pairs used to eliminate unneeded registers that point into the stack frame. If it is not defined, the only elimination attempted by the compiler is to replace references to the frame pointer with references to the stack pointer.

The definition of this macro is a list of structure initializations, each of which specifies an original and replacement register.

On some machines, the position of the argument pointer is not known until the compilation is completed. In such a case, a separate hard register must be used for the argument pointer. This register can be eliminated by replacing it with either the frame pointer or the argument pointer, depending on whether or not the frame pointer has been eliminated.

In this case, you might specify:

```
#define ELIMINABLE_REGS  \
{{ARG_POINTER_REGNUM, STACK_POINTER_REGNUM}, \
 {ARG_POINTER_REGNUM, FRAME_POINTER_REGNUM}, \
```

```
{FRAME_POINTER_REGNUM, STACK_POINTER_REGNUM}}
```

Note that the elimination of the argument pointer with the stack pointer is specified first since that is the preferred elimination.

`bool TARGET_CAN_ELIMINATE` (*const int* ***from_reg***, *const int* ***to_reg***) [Target Hook]

This target hook should returns `true` if the compiler is allowed to try to replace register number *from_reg* with register number *to_reg*. This target hook need only be defined if `ELIMINABLE_REGS` is defined, and will usually be `true`, since most of the cases preventing register elimination are things that the compiler already knows about.

Default return value is `true`.

`INITIAL_ELIMINATION_OFFSET` (***from-reg***, ***to-reg***, ***offset-var***) [Macro]

This macro is similar to `INITIAL_FRAME_POINTER_OFFSET`. It specifies the initial difference between the specified pair of registers. This macro must be defined if `ELIMINABLE_REGS` is defined.

17.10.6 Passing Function Arguments on the Stack

The macros in this section control how arguments are passed on the stack. See the following section for other macros that control passing certain arguments in registers.

`bool TARGET_PROMOTE_PROTOTYPES` (*const_tree* ***fntype***) [Target Hook]

This target hook returns `true` if an argument declared in a prototype as an integral type smaller than `int` should actually be passed as an `int`. In addition to avoiding errors in certain cases of mismatch, it also makes for better code on certain machines. The default is to not promote prototypes.

`PUSH_ARGS` [Macro]

A C expression. If nonzero, push insns will be used to pass outgoing arguments. If the target machine does not have a push instruction, set it to zero. That directs GCC to use an alternate strategy: to allocate the entire argument block and then store the arguments into it. When `PUSH_ARGS` is nonzero, `PUSH_ROUNDING` must be defined too.

`PUSH_ARGS_REVERSED` [Macro]

A C expression. If nonzero, function arguments will be evaluated from last to first, rather than from first to last. If this macro is not defined, it defaults to `PUSH_ARGS` on targets where the stack and args grow in opposite directions, and 0 otherwise.

`PUSH_ROUNDING` (***npushed***) [Macro]

A C expression that is the number of bytes actually pushed onto the stack when an instruction attempts to push *npushed* bytes.

On some machines, the definition

```
#define PUSH_ROUNDING(BYTES) (BYTES)
```

will suffice. But on other machines, instructions that appear to push one byte actually push two bytes in an attempt to maintain alignment. Then the definition should be

```
#define PUSH_ROUNDING(BYTES) (((BYTES) + 1) & ~1)
```

If the value of this macro has a type, it should be an unsigned type.

`ACCUMULATE_OUTGOING_ARGS` [Macro]

A C expression. If nonzero, the maximum amount of space required for outgoing arguments will be computed and placed into `crtl->outgoing_args_size`. No space will be pushed onto the stack for each call; instead, the function prologue should increase the stack frame size by this amount.

Setting both `PUSH_ARGS` and `ACCUMULATE_OUTGOING_ARGS` is not proper.

`REG_PARM_STACK_SPACE (fndecl)` [Macro]

Define this macro if functions should assume that stack space has been allocated for arguments even when their values are passed in registers.

The value of this macro is the size, in bytes, of the area reserved for arguments passed in registers for the function represented by *fndecl*, which can be zero if GCC is calling a library function. The argument *fndecl* can be the FUNCTION_DECL, or the type itself of the function.

This space can be allocated by the caller, or be a part of the machine-dependent stack frame: `OUTGOING_REG_PARM_STACK_SPACE` says which.

`OUTGOING_REG_PARM_STACK_SPACE (fntype)` [Macro]

Define this to a nonzero value if it is the responsibility of the caller to allocate the area reserved for arguments passed in registers when calling a function of *fntype*. *fntype* may be NULL if the function called is a library function.

If `ACCUMULATE_OUTGOING_ARGS` is defined, this macro controls whether the space for these arguments counts in the value of `crtl->outgoing_args_size`.

`STACK_PARMS_IN_REG_PARM_AREA` [Macro]

Define this macro if `REG_PARM_STACK_SPACE` is defined, but the stack parameters don't skip the area specified by it.

Normally, when a parameter is not passed in registers, it is placed on the stack beyond the `REG_PARM_STACK_SPACE` area. Defining this macro suppresses this behavior and causes the parameter to be passed on the stack in its natural location.

`int TARGET_RETURN_POPS_ARGS (`*tree* `fundecl`*, tree* `funtype`*, int* `size``)` [Target Hook]

This target hook returns the number of bytes of its own arguments that a function pops on returning, or 0 if the function pops no arguments and the caller must therefore pop them all after the function returns.

fundecl is a C variable whose value is a tree node that describes the function in question. Normally it is a node of type `FUNCTION_DECL` that describes the declaration of the function. From this you can obtain the `DECL_ATTRIBUTES` of the function.

funtype is a C variable whose value is a tree node that describes the function in question. Normally it is a node of type `FUNCTION_TYPE` that describes the data type of the function. From this it is possible to obtain the data types of the value and arguments (if known).

When a call to a library function is being considered, *fundecl* will contain an identifier node for the library function. Thus, if you need to distinguish among various library functions, you can do so by their names. Note that "library function" in this context

means a function used to perform arithmetic, whose name is known specially in the compiler and was not mentioned in the C code being compiled.

size is the number of bytes of arguments passed on the stack. If a variable number of bytes is passed, it is zero, and argument popping will always be the responsibility of the calling function.

On the VAX, all functions always pop their arguments, so the definition of this macro is *size*. On the 68000, using the standard calling convention, no functions pop their arguments, so the value of the macro is always 0 in this case. But an alternative calling convention is available in which functions that take a fixed number of arguments pop them but other functions (such as `printf`) pop nothing (the caller pops all). When this convention is in use, *funtype* is examined to determine whether a function takes a fixed number of arguments.

`CALL_POPS_ARGS (cum)` [Macro]

A C expression that should indicate the number of bytes a call sequence pops off the stack. It is added to the value of `RETURN_POPS_ARGS` when compiling a function call.

cum is the variable in which all arguments to the called function have been accumulated.

On certain architectures, such as the SH5, a call trampoline is used that pops certain registers off the stack, depending on the arguments that have been passed to the function. Since this is a property of the call site, not of the called function, `RETURN_POPS_ARGS` is not appropriate.

17.10.7 Passing Arguments in Registers

This section describes the macros which let you control how various types of arguments are passed in registers or how they are arranged in the stack.

`rtx TARGET_FUNCTION_ARG (cumulative_args_t ca, enum machine_mode mode, const_tree type, bool named)` [Target Hook]

Return an RTX indicating whether a function argument is passed in a register and if so, which register.

The arguments are *ca*, which summarizes all the previous arguments; *mode*, the machine mode of the argument; *type*, the data type of the argument as a tree node or 0 if that is not known (which happens for C support library functions); and *named*, which is `true` for an ordinary argument and `false` for nameless arguments that correspond to '`...`' in the called function's prototype. *type* can be an incomplete type if a syntax error has previously occurred.

The return value is usually either a `reg` RTX for the hard register in which to pass the argument, or zero to pass the argument on the stack.

The value of the expression can also be a `parallel` RTX. This is used when an argument is passed in multiple locations. The mode of the `parallel` should be the mode of the entire argument. The `parallel` holds any number of `expr_list` pairs; each one describes where part of the argument is passed. In each `expr_list` the first operand must be a `reg` RTX for the hard register in which to pass this part of the argument, and the mode of the register RTX indicates how large this part of the argument is. The second operand of the `expr_list` is a `const_int` which gives

the offset in bytes into the entire argument of where this part starts. As a special exception the first `expr_list` in the `parallel` RTX may have a first operand of zero. This indicates that the entire argument is also stored on the stack.

The last time this hook is called, it is called with `MODE == VOIDmode`, and its result is passed to the `call` or `call_value` pattern as operands 2 and 3 respectively.

The usual way to make the ISO library '`stdarg.h`' work on a machine where some arguments are usually passed in registers, is to cause nameless arguments to be passed on the stack instead. This is done by making `TARGET_FUNCTION_ARG` return 0 whenever *named* is `false`.

You may use the hook `targetm.calls.must_pass_in_stack` in the definition of this macro to determine if this argument is of a type that must be passed in the stack. If `REG_PARM_STACK_SPACE` is not defined and `TARGET_FUNCTION_ARG` returns nonzero for such an argument, the compiler will abort. If `REG_PARM_STACK_SPACE` is defined, the argument will be computed in the stack and then loaded into a register.

`bool TARGET_MUST_PASS_IN_STACK` (*enum machine_mode* `mode`, *const_tree* `type`) [Target Hook]

This target hook should return `true` if we should not pass *type* solely in registers. The file '`expr.h`' defines a definition that is usually appropriate, refer to '`expr.h`' for additional documentation.

`rtx TARGET_FUNCTION_INCOMING_ARG` (*cumulative_args_t* `ca`, *enum machine_mode* `mode`, *const_tree* `type`, *bool* `named`) [Target Hook]

Define this hook if the target machine has "register windows", so that the register in which a function sees an arguments is not necessarily the same as the one in which the caller passed the argument.

For such machines, `TARGET_FUNCTION_ARG` computes the register in which the caller passes the value, and `TARGET_FUNCTION_INCOMING_ARG` should be defined in a similar fashion to tell the function being called where the arguments will arrive.

If `TARGET_FUNCTION_INCOMING_ARG` is not defined, `TARGET_FUNCTION_ARG` serves both purposes.

`int TARGET_ARG_PARTIAL_BYTES` (*cumulative_args_t* `cum`, *enum machine_mode* `mode`, *tree* `type`, *bool* `named`) [Target Hook]

This target hook returns the number of bytes at the beginning of an argument that must be put in registers. The value must be zero for arguments that are passed entirely in registers or that are entirely pushed on the stack.

On some machines, certain arguments must be passed partially in registers and partially in memory. On these machines, typically the first few words of arguments are passed in registers, and the rest on the stack. If a multi-word argument (a `double` or a structure) crosses that boundary, its first few words must be passed in registers and the rest must be pushed. This macro tells the compiler when this occurs, and how many bytes should go in registers.

`TARGET_FUNCTION_ARG` for these arguments should return the first register to be used by the caller for this argument; likewise `TARGET_FUNCTION_INCOMING_ARG`, for the called function.

`bool TARGET_PASS_BY_REFERENCE (cumulative_args_t cum, enum machine_mode mode, const_tree type, bool named)` [Target Hook]

This target hook should return `true` if an argument at the position indicated by *cum* should be passed by reference. This predicate is queried after target independent reasons for being passed by reference, such as `TREE_ADDRESSABLE (type)`.

If the hook returns true, a copy of that argument is made in memory and a pointer to the argument is passed instead of the argument itself. The pointer is passed in whatever way is appropriate for passing a pointer to that type.

`bool TARGET_CALLEE_COPIES (cumulative_args_t cum, enum machine_mode mode, const_tree type, bool named)` [Target Hook]

The function argument described by the parameters to this hook is known to be passed by reference. The hook should return true if the function argument should be copied by the callee instead of copied by the caller.

For any argument for which the hook returns true, if it can be determined that the argument is not modified, then a copy need not be generated.

The default version of this hook always returns false.

`CUMULATIVE_ARGS` [Macro]

A C type for declaring a variable that is used as the first argument of `TARGET_FUNCTION_ARG` and other related values. For some target machines, the type `int` suffices and can hold the number of bytes of argument so far.

There is no need to record in `CUMULATIVE_ARGS` anything about the arguments that have been passed on the stack. The compiler has other variables to keep track of that. For target machines on which all arguments are passed on the stack, there is no need to store anything in `CUMULATIVE_ARGS`; however, the data structure must exist and should not be empty, so use `int`.

`OVERRIDE_ABI_FORMAT (fndecl)` [Macro]

If defined, this macro is called before generating any code for a function, but after the *cfun* descriptor for the function has been created. The back end may use this macro to update *cfun* to reflect an ABI other than that which would normally be used by default. If the compiler is generating code for a compiler-generated function, *fndecl* may be `NULL`.

`INIT_CUMULATIVE_ARGS (cum, fntype, libname, fndecl, n_named_args)` [Macro]

A C statement (sans semicolon) for initializing the variable *cum* for the state at the beginning of the argument list. The variable has type `CUMULATIVE_ARGS`. The value of *fntype* is the tree node for the data type of the function which will receive the args, or 0 if the args are to a compiler support library function. For direct calls that are not libcalls, *fndecl* contain the declaration node of the function. *fndecl* is also set when `INIT_CUMULATIVE_ARGS` is used to find arguments for the function being compiled. *n_named_args* is set to the number of named arguments, including a structure return address if it is passed as a parameter, when making a call. When processing incoming arguments, *n_named_args* is set to -1.

When processing a call to a compiler support library function, *libname* identifies which one. It is a `symbol_ref` rtx which contains the name of the function, as a

string. *libname* is 0 when an ordinary C function call is being processed. Thus, each time this macro is called, either *libname* or *fntype* is nonzero, but never both of them at once.

`INIT_CUMULATIVE_LIBCALL_ARGS` (*cum*, *mode*, *libname*) [Macro]

Like `INIT_CUMULATIVE_ARGS` but only used for outgoing libcalls, it gets a `MODE` argument instead of *fntype*, that would be `NULL`. *indirect* would always be zero, too. If this macro is not defined, `INIT_CUMULATIVE_ARGS (cum, NULL_RTX, libname, 0)` is used instead.

`INIT_CUMULATIVE_INCOMING_ARGS` (*cum*, *fntype*, *libname*) [Macro]

Like `INIT_CUMULATIVE_ARGS` but overrides it for the purposes of finding the arguments for the function being compiled. If this macro is undefined, `INIT_CUMULATIVE_ARGS` is used instead.

The value passed for *libname* is always 0, since library routines with special calling conventions are never compiled with GCC. The argument *libname* exists for symmetry with `INIT_CUMULATIVE_ARGS`.

`void TARGET_FUNCTION_ARG_ADVANCE` (*cumulative_args_t* **ca**, *enum machine_mode* **mode**, *const_tree* **type**, *bool* **named**) [Target Hook]

This hook updates the summarizer variable pointed to by *ca* to advance past an argument in the argument list. The values *mode*, *type* and *named* describe that argument. Once this is done, the variable *cum* is suitable for analyzing the *following* argument with `TARGET_FUNCTION_ARG`, etc.

This hook need not do anything if the argument in question was passed on the stack. The compiler knows how to track the amount of stack space used for arguments without any special help.

`FUNCTION_ARG_OFFSET` (*mode*, *type*) [Macro]

If defined, a C expression that is the number of bytes to add to the offset of the argument passed in memory. This is needed for the SPU, which passes `char` and `short` arguments in the preferred slot that is in the middle of the quad word instead of starting at the top.

`FUNCTION_ARG_PADDING` (*mode*, *type*) [Macro]

If defined, a C expression which determines whether, and in which direction, to pad out an argument with extra space. The value should be of type `enum direction`: either `upward` to pad above the argument, `downward` to pad below, or `none` to inhibit padding.

The *amount* of padding is not controlled by this macro, but by the target hook `TARGET_FUNCTION_ARG_ROUND_BOUNDARY`. It is always just enough to reach the next multiple of that boundary.

This macro has a default definition which is right for most systems. For little-endian machines, the default is to pad upward. For big-endian machines, the default is to pad downward for an argument of constant size shorter than an `int`, and upward otherwise.

`PAD_VARARGS_DOWN` [Macro]

If defined, a C expression which determines whether the default implementation of va_arg will attempt to pad down before reading the next argument, if that argument is smaller than its aligned space as controlled by `PARM_BOUNDARY`. If this macro is not defined, all such arguments are padded down if `BYTES_BIG_ENDIAN` is true.

`BLOCK_REG_PADDING` (*mode*, *type*, *first*) [Macro]

Specify padding for the last element of a block move between registers and memory. *first* is nonzero if this is the only element. Defining this macro allows better control of register function parameters on big-endian machines, without using `PARALLEL` rtl. In particular, `MUST_PASS_IN_STACK` need not test padding and mode of types in registers, as there is no longer a "wrong" part of a register; For example, a three byte aggregate may be passed in the high part of a register if so required.

`unsigned int TARGET_FUNCTION_ARG_BOUNDARY` (*enum machine_mode* **mode**, *const_tree* **type**) [Target Hook]

This hook returns the alignment boundary, in bits, of an argument with the specified mode and type. The default hook returns `PARM_BOUNDARY` for all arguments.

`unsigned int TARGET_FUNCTION_ARG_ROUND_BOUNDARY` (*enum machine_mode* **mode**, *const_tree* **type**) [Target Hook]

Normally, the size of an argument is rounded up to `PARM_BOUNDARY`, which is the default value for this hook. You can define this hook to return a different value if an argument size must be rounded to a larger value.

`FUNCTION_ARG_REGNO_P` (*regno*) [Macro]

A C expression that is nonzero if *regno* is the number of a hard register in which function arguments are sometimes passed. This does *not* include implicit arguments such as the static chain and the structure-value address. On many machines, no registers can be used for this purpose since all function arguments are pushed on the stack.

`bool TARGET_SPLIT_COMPLEX_ARG` (*const_tree* **type**) [Target Hook]

This hook should return true if parameter of type *type* are passed as two scalar parameters. By default, GCC will attempt to pack complex arguments into the target's word size. Some ABIs require complex arguments to be split and treated as their individual components. For example, on AIX64, complex floats should be passed in a pair of floating point registers, even though a complex float would fit in one 64-bit floating point register.

The default value of this hook is `NULL`, which is treated as always false.

`tree TARGET_BUILD_BUILTIN_VA_LIST` (*void*) [Target Hook]

This hook returns a type node for `va_list` for the target. The default version of the hook returns `void*`.

`int TARGET_ENUM_VA_LIST_P` (*int* **idx**, *const char* ***pname**, *tree* ***ptree**) [Target Hook]

This target hook is used in function `c_common_nodes_and_builtins` to iterate through the target specific builtin types for va_list. The variable *idx* is used as

iterator. *pname* has to be a pointer to a `const char *` and *ptree* a pointer to a `tree` typed variable. The arguments *pname* and *ptree* are used to store the result of this macro and are set to the name of the va_list builtin type and its internal type. If the return value of this macro is zero, then there is no more element. Otherwise the *IDX* should be increased for the next call of this macro to iterate through all types.

`tree TARGET_FN_ABI_VA_LIST` (*tree* ***fndecl***) [Target Hook]

This hook returns the va_list type of the calling convention specified by *fndecl*. The default version of this hook returns `va_list_type_node`.

`tree TARGET_CANONICAL_VA_LIST_TYPE` (*tree* ***type***) [Target Hook]

This hook returns the va_list type of the calling convention specified by the type of *type*. If *type* is not a valid va_list type, it returns `NULL_TREE`.

`tree TARGET_GIMPLIFY_VA_ARG_EXPR` (*tree* ***valist***, *tree* ***type***, *gimple_seq* ****pre_p***, *gimple_seq* ****post_p***) [Target Hook]

This hook performs target-specific gimplification of `VA_ARG_EXPR`. The first two parameters correspond to the arguments to `va_arg`; the latter two are as in `gimplify.c:gimplify_expr`.

`bool TARGET_VALID_POINTER_MODE` (*enum machine_mode* ***mode***) [Target Hook]

Define this to return nonzero if the port can handle pointers with machine mode *mode*. The default version of this hook returns true for both `ptr_mode` and `Pmode`.

`bool TARGET_REF_MAY_ALIAS_ERRNO` (*struct ao_ref* ****ref***) [Target Hook]

Define this to return nonzero if the memory reference *ref* may alias with the system C library errno location. The default version of this hook assumes the system C library errno location is either a declaration of type int or accessed by dereferencing a pointer to int.

`bool TARGET_SCALAR_MODE_SUPPORTED_P` (*enum machine_mode* ***mode***) [Target Hook]

Define this to return nonzero if the port is prepared to handle insns involving scalar mode *mode*. For a scalar mode to be considered supported, all the basic arithmetic and comparisons must work.

The default version of this hook returns true for any mode required to handle the basic C types (as defined by the port). Included here are the double-word arithmetic supported by the code in '`optabs.c`'.

`bool TARGET_VECTOR_MODE_SUPPORTED_P` (*enum machine_mode* ***mode***) [Target Hook]

Define this to return nonzero if the port is prepared to handle insns involving vector mode *mode*. At the very least, it must have move patterns for this mode.

`bool TARGET_ARRAY_MODE_SUPPORTED_P` (*enum machine_mode* ***mode***, *unsigned HOST_WIDE_INT* ***nelems***) [Target Hook]

Return true if GCC should try to use a scalar mode to store an array of *nelems* elements, given that each element has mode *mode*. Returning true here overrides the usual `MAX_FIXED_MODE` limit and allows GCC to use any defined integer mode.

One use of this hook is to support vector load and store operations that operate on several homogeneous vectors. For example, ARM NEON has operations like:

```
int8x8x3_t vld3_s8 (const int8_t *)
```

where the return type is defined as:

```
typedef struct int8x8x3_t
{
  int8x8_t val[3];
} int8x8x3_t;
```

If this hook allows `val` to have a scalar mode, then `int8x8x3_t` can have the same mode. GCC can then store `int8x8x3_t`s in registers rather than forcing them onto the stack.

`bool TARGET_SMALL_REGISTER_CLASSES_FOR_MODE_P (`*enum machine_mode* `mode``)` [Target Hook]

Define this to return nonzero for machine modes for which the port has small register classes. If this target hook returns nonzero for a given *mode*, the compiler will try to minimize the lifetime of registers in *mode*. The hook may be called with `VOIDmode` as argument. In this case, the hook is expected to return nonzero if it returns nonzero for any mode.

On some machines, it is risky to let hard registers live across arbitrary insns. Typically, these machines have instructions that require values to be in specific registers (like an accumulator), and reload will fail if the required hard register is used for another purpose across such an insn.

Passes before reload do not know which hard registers will be used in an instruction, but the machine modes of the registers set or used in the instruction are already known. And for some machines, register classes are small for, say, integer registers but not for floating point registers. For example, the AMD x86-64 architecture requires specific registers for the legacy x86 integer instructions, but there are many SSE registers for floating point operations. On such targets, a good strategy may be to return nonzero from this hook for `INTEGRAL_MODE_P` machine modes but zero for the SSE register classes.

The default version of this hook returns false for any mode. It is always safe to redefine this hook to return with a nonzero value. But if you unnecessarily define it, you will reduce the amount of optimizations that can be performed in some cases. If you do not define this hook to return a nonzero value when it is required, the compiler will run out of spill registers and print a fatal error message.

`unsigned int TARGET_FLAGS_REGNUM` [Target Hook]

If the target has a dedicated flags register, and it needs to use the post-reload comparison elimination pass, then this value should be set appropriately.

17.10.8 How Scalar Function Values Are Returned

This section discusses the macros that control returning scalars as values—values that can fit in registers.

`rtx TARGET_FUNCTION_VALUE` (*const_tree* `ret_type`, *const_tree* `fn_decl_or_type`, *bool* `outgoing`) [Target Hook]

Define this to return an RTX representing the place where a function returns or receives a value of data type *ret_type*, a tree node representing a data type. *fn_decl_or_type* is a tree node representing `FUNCTION_DECL` or `FUNCTION_TYPE` of a function being called. If *outgoing* is false, the hook should compute the register in which the caller will see the return value. Otherwise, the hook should return an RTX representing the place where a function returns a value.

On many machines, only `TYPE_MODE (ret_type)` is relevant. (Actually, on most machines, scalar values are returned in the same place regardless of mode.) The value of the expression is usually a `reg` RTX for the hard register where the return value is stored. The value can also be a `parallel` RTX, if the return value is in multiple places. See `TARGET_FUNCTION_ARG` for an explanation of the `parallel` form. Note that the callee will populate every location specified in the `parallel`, but if the first element of the `parallel` contains the whole return value, callers will use that element as the canonical location and ignore the others. The m68k port uses this type of `parallel` to return pointers in both '`%a0`' (the canonical location) and '`%d0`'.

If `TARGET_PROMOTE_FUNCTION_RETURN` returns true, you must apply the same promotion rules specified in `PROMOTE_MODE` if *valtype* is a scalar type.

If the precise function being called is known, *func* is a tree node (`FUNCTION_DECL`) for it; otherwise, *func* is a null pointer. This makes it possible to use a different value-returning convention for specific functions when all their calls are known.

Some target machines have "register windows" so that the register in which a function returns its value is not the same as the one in which the caller sees the value. For such machines, you should return different RTX depending on *outgoing*.

`TARGET_FUNCTION_VALUE` is not used for return values with aggregate data types, because these are returned in another way. See `TARGET_STRUCT_VALUE_RTX` and related macros, below.

`FUNCTION_VALUE` (`valtype`, `func`) [Macro]

This macro has been deprecated. Use `TARGET_FUNCTION_VALUE` for a new target instead.

`LIBCALL_VALUE` (`mode`) [Macro]

A C expression to create an RTX representing the place where a library function returns a value of mode *mode*.

Note that "library function" in this context means a compiler support routine, used to perform arithmetic, whose name is known specially by the compiler and was not mentioned in the C code being compiled.

`rtx TARGET_LIBCALL_VALUE` (*enum machine_mode* `mode`, *const_rtx* `fun`) [Target Hook]

Define this hook if the back-end needs to know the name of the libcall function in order to determine where the result should be returned.

The mode of the result is given by *mode* and the name of the called library function is given by *fun*. The hook should return an RTX representing the place where the library function result will be returned.

If this hook is not defined, then LIBCALL_VALUE will be used.

`FUNCTION_VALUE_REGNO_P` (*regno*) [Macro]

A C expression that is nonzero if *regno* is the number of a hard register in which the values of called function may come back.

A register whose use for returning values is limited to serving as the second of a pair (for a value of type `double`, say) need not be recognized by this macro. So for most machines, this definition suffices:

```
#define FUNCTION_VALUE_REGNO_P(N) ((N) == 0)
```

If the machine has register windows, so that the caller and the called function use different registers for the return value, this macro should recognize only the caller's register numbers.

This macro has been deprecated. Use `TARGET_FUNCTION_VALUE_REGNO_P` for a new target instead.

`bool TARGET_FUNCTION_VALUE_REGNO_P` (*const unsigned int regno*) [Target Hook]

A target hook that return `true` if *regno* is the number of a hard register in which the values of called function may come back.

A register whose use for returning values is limited to serving as the second of a pair (for a value of type `double`, say) need not be recognized by this target hook.

If the machine has register windows, so that the caller and the called function use different registers for the return value, this target hook should recognize only the caller's register numbers.

If this hook is not defined, then FUNCTION_VALUE_REGNO_P will be used.

`APPLY_RESULT_SIZE` [Macro]

Define this macro if '`untyped_call`' and '`untyped_return`' need more space than is implied by `FUNCTION_VALUE_REGNO_P` for saving and restoring an arbitrary return value.

`bool TARGET_RETURN_IN_MSB` (*const_tree type*) [Target Hook]

This hook should return true if values of type *type* are returned at the most significant end of a register (in other words, if they are padded at the least significant end). You can assume that *type* is returned in a register; the caller is required to check this.

Note that the register provided by `TARGET_FUNCTION_VALUE` must be able to hold the complete return value. For example, if a 1-, 2- or 3-byte structure is returned at the most significant end of a 4-byte register, `TARGET_FUNCTION_VALUE` should provide an `SImode` rtx.

17.10.9 How Large Values Are Returned

When a function value's mode is `BLKmode` (and in some other cases), the value is not returned according to `TARGET_FUNCTION_VALUE` (see Section 17.10.8 [Scalar Return], page 484). Instead, the caller passes the address of a block of memory in which the value should be stored. This address is called the *structure value address*.

This section describes how to control returning structure values in memory.

`bool TARGET_RETURN_IN_MEMORY` (*const_tree* `type`, *const_tree* `fntype`) [Target Hook]

This target hook should return a nonzero value to say to return the function value in memory, just as large structures are always returned. Here *type* will be the data type of the value, and *fntype* will be the type of the function doing the returning, or `NULL` for libcalls.

Note that values of mode `BLKmode` must be explicitly handled by this function. Also, the option '`-fpcc-struct-return`' takes effect regardless of this macro. On most systems, it is possible to leave the hook undefined; this causes a default definition to be used, whose value is the constant 1 for `BLKmode` values, and 0 otherwise.

Do not use this hook to indicate that structures and unions should always be returned in memory. You should instead use `DEFAULT_PCC_STRUCT_RETURN` to indicate this.

`DEFAULT_PCC_STRUCT_RETURN` [Macro]

Define this macro to be 1 if all structure and union return values must be in memory. Since this results in slower code, this should be defined only if needed for compatibility with other compilers or with an ABI. If you define this macro to be 0, then the conventions used for structure and union return values are decided by the `TARGET_RETURN_IN_MEMORY` target hook.

If not defined, this defaults to the value 1.

`rtx TARGET_STRUCT_VALUE_RTX` (*tree* `fndecl`, *int* `incoming`) [Target Hook]

This target hook should return the location of the structure value address (normally a `mem` or `reg`), or 0 if the address is passed as an "invisible" first argument. Note that *fndecl* may be `NULL`, for libcalls. You do not need to define this target hook if the address is always passed as an "invisible" first argument.

On some architectures the place where the structure value address is found by the called function is not the same place that the caller put it. This can be due to register windows, or it could be because the function prologue moves it to a different place. *incoming* is `1` or `2` when the location is needed in the context of the called function, and `0` in the context of the caller.

If *incoming* is nonzero and the address is to be found on the stack, return a `mem` which refers to the frame pointer. If *incoming* is `2`, the result is being used to fetch the structure value address at the beginning of a function. If you need to emit adjusting code, you should do it at this point.

`PCC_STATIC_STRUCT_RETURN` [Macro]

Define this macro if the usual system convention on the target machine for returning structures and unions is for the called function to return the address of a static variable containing the value.

Do not define this if the usual system convention is for the caller to pass an address to the subroutine.

This macro has effect in '`-fpcc-struct-return`' mode, but it does nothing when you use '`-freg-struct-return`' mode.

`enum machine_mode TARGET_GET_RAW_RESULT_MODE` (*int* `regno`) [Target Hook]

This target hook returns the mode to be used when accessing raw return registers in `__builtin_return`. Define this macro if the value in *reg_raw_mode* is not correct.

`enum machine_mode TARGET_GET_RAW_ARG_MODE (int regno)` [Target Hook]

This target hook returns the mode to be used when accessing raw argument registers in `__builtin_apply_args`. Define this macro if the value in *reg_raw_mode* is not correct.

17.10.10 Caller-Saves Register Allocation

If you enable it, GCC can save registers around function calls. This makes it possible to use call-clobbered registers to hold variables that must live across calls.

`CALLER_SAVE_PROFITABLE (refs, calls)` [Macro]

A C expression to determine whether it is worthwhile to consider placing a pseudo-register in a call-clobbered hard register and saving and restoring it around each function call. The expression should be 1 when this is worth doing, and 0 otherwise.

If you don't define this macro, a default is used which is good on most machines: `4 * calls < refs`.

`HARD_REGNO_CALLER_SAVE_MODE (regno, nregs)` [Macro]

A C expression specifying which mode is required for saving *nregs* of a pseudo-register in call-clobbered hard register *regno*. If *regno* is unsuitable for caller save, `VOIDmode` should be returned. For most machines this macro need not be defined since GCC will select the smallest suitable mode.

17.10.11 Function Entry and Exit

This section describes the macros that output function entry (*prologue*) and exit (*epilogue*) code.

`void TARGET_ASM_FUNCTION_PROLOGUE (FILE *file, HOST_WIDE_INT size)` [Target Hook]

If defined, a function that outputs the assembler code for entry to a function. The prologue is responsible for setting up the stack frame, initializing the frame pointer register, saving registers that must be saved, and allocating *size* additional bytes of storage for the local variables. *size* is an integer. *file* is a stdio stream to which the assembler code should be output.

The label for the beginning of the function need not be output by this macro. That has already been done when the macro is run.

To determine which registers to save, the macro can refer to the array `regs_ever_live`: element *r* is nonzero if hard register *r* is used anywhere within the function. This implies the function prologue should save register *r*, provided it is not one of the call-used registers. (`TARGET_ASM_FUNCTION_EPILOGUE` must likewise use `regs_ever_live`.)

On machines that have "register windows", the function entry code does not save on the stack the registers that are in the windows, even if they are supposed to be preserved by function calls; instead it takes appropriate steps to "push" the register stack, if any non-call-used registers are used in the function.

On machines where functions may or may not have frame-pointers, the function entry code must vary accordingly; it must set up the frame pointer if one is wanted, and not

otherwise. To determine whether a frame pointer is in wanted, the macro can refer to the variable `frame_pointer_needed`. The variable's value will be 1 at run time in a function that needs a frame pointer. See Section 17.10.5 [Elimination], page 475.

The function entry code is responsible for allocating any stack space required for the function. This stack space consists of the regions listed below. In most cases, these regions are allocated in the order listed, with the last listed region closest to the top of the stack (the lowest address if `STACK_GROWS_DOWNWARD` is defined, and the highest address if it is not defined). You can use a different order for a machine if doing so is more convenient or required for compatibility reasons. Except in cases where required by standard or by a debugger, there is no reason why the stack layout used by GCC need agree with that used by other compilers for a machine.

`void TARGET_ASM_FUNCTION_END_PROLOGUE (FILE *file)` [Target Hook]

If defined, a function that outputs assembler code at the end of a prologue. This should be used when the function prologue is being emitted as RTL, and you have some extra assembler that needs to be emitted. See [prologue instruction pattern], page 372.

`void TARGET_ASM_FUNCTION_BEGIN_EPILOGUE (FILE *file)` [Target Hook]

If defined, a function that outputs assembler code at the start of an epilogue. This should be used when the function epilogue is being emitted as RTL, and you have some extra assembler that needs to be emitted. See [epilogue instruction pattern], page 373.

`void TARGET_ASM_FUNCTION_EPILOGUE (FILE *file, HOST_WIDE_INT size)` [Target Hook]

If defined, a function that outputs the assembler code for exit from a function. The epilogue is responsible for restoring the saved registers and stack pointer to their values when the function was called, and returning control to the caller. This macro takes the same arguments as the macro `TARGET_ASM_FUNCTION_PROLOGUE`, and the registers to restore are determined from `regs_ever_live` and `CALL_USED_REGISTERS` in the same way.

On some machines, there is a single instruction that does all the work of returning from the function. On these machines, give that instruction the name '`return`' and do not define the macro `TARGET_ASM_FUNCTION_EPILOGUE` at all.

Do not define a pattern named '`return`' if you want the `TARGET_ASM_FUNCTION_EPILOGUE` to be used. If you want the target switches to control whether return instructions or epilogues are used, define a '`return`' pattern with a validity condition that tests the target switches appropriately. If the '`return`' pattern's validity condition is false, epilogues will be used.

On machines where functions may or may not have frame-pointers, the function exit code must vary accordingly. Sometimes the code for these two cases is completely different. To determine whether a frame pointer is wanted, the macro can refer to the variable `frame_pointer_needed`. The variable's value will be 1 when compiling a function that needs a frame pointer.

Normally, TARGET_ASM_FUNCTION_PROLOGUE and TARGET_ASM_FUNCTION_EPILOGUE must treat leaf functions specially. The C variable current_function_is_leaf is nonzero for such a function. See Section 17.7.4 [Leaf Functions], page 452.

On some machines, some functions pop their arguments on exit while others leave that for the caller to do. For example, the 68020 when given '-mrtd' pops arguments in functions that take a fixed number of arguments.

Your definition of the macro RETURN_POPS_ARGS decides which functions pop their own arguments. TARGET_ASM_FUNCTION_EPILOGUE needs to know what was decided. The number of bytes of the current function's arguments that this function should pop is available in crtl->args.pops_args. See Section 17.10.8 [Scalar Return], page 484.

- A region of crtl->args.pretend_args_size bytes of uninitialized space just underneath the first argument arriving on the stack. (This may not be at the very start of the allocated stack region if the calling sequence has pushed anything else since pushing the stack arguments. But usually, on such machines, nothing else has been pushed yet, because the function prologue itself does all the pushing.) This region is used on machines where an argument may be passed partly in registers and partly in memory, and, in some cases to support the features in <stdarg.h>.
- An area of memory used to save certain registers used by the function. The size of this area, which may also include space for such things as the return address and pointers to previous stack frames, is machine-specific and usually depends on which registers have been used in the function. Machines with register windows often do not require a save area.
- A region of at least *size* bytes, possibly rounded up to an allocation boundary, to contain the local variables of the function. On some machines, this region and the save area may occur in the opposite order, with the save area closer to the top of the stack.
- Optionally, when ACCUMULATE_OUTGOING_ARGS is defined, a region of crtl->outgoing_args_size bytes to be used for outgoing argument lists of the function. See Section 17.10.6 [Stack Arguments], page 476.

EXIT_IGNORE_STACK [Macro]

Define this macro as a C expression that is nonzero if the return instruction or the function epilogue ignores the value of the stack pointer; in other words, if it is safe to delete an instruction to adjust the stack pointer before a return from the function. The default is 0.

Note that this macro's value is relevant only for functions for which frame pointers are maintained. It is never safe to delete a final stack adjustment in a function that has no frame pointer, and the compiler knows this regardless of EXIT_IGNORE_STACK.

EPILOGUE_USES (*regno*) [Macro]

Define this macro as a C expression that is nonzero for registers that are used by the epilogue or the 'return' pattern. The stack and frame pointer registers are already assumed to be used as needed.

EH_USES (*regno*) [Macro]

Define this macro as a C expression that is nonzero for registers that are used by the exception handling mechanism, and so should be considered live on entry to an exception edge.

`void TARGET_ASM_OUTPUT_MI_THUNK (FILE *file, tree thunk_fndecl, HOST_WIDE_INT delta, HOST_WIDE_INT vcall_offset, tree function)` [Target Hook]

A function that outputs the assembler code for a thunk function, used to implement C++ virtual function calls with multiple inheritance. The thunk acts as a wrapper around a virtual function, adjusting the implicit object parameter before handing control off to the real function.

First, emit code to add the integer *delta* to the location that contains the incoming first argument. Assume that this argument contains a pointer, and is the one used to pass the `this` pointer in C++. This is the incoming argument *before* the function prologue, e.g. '`%o0`' on a sparc. The addition must preserve the values of all other incoming arguments.

Then, if *vcall_offset* is nonzero, an additional adjustment should be made after adding `delta`. In particular, if *p* is the adjusted pointer, the following adjustment should be made:

```
p += (*((ptrdiff_t **)p))[vcall_offset/sizeof(ptrdiff_t)]
```

After the additions, emit code to jump to *function*, which is a `FUNCTION_DECL`. This is a direct pure jump, not a call, and does not touch the return address. Hence returning from *FUNCTION* will return to whoever called the current '`thunk`'.

The effect must be as if *function* had been called directly with the adjusted first argument. This macro is responsible for emitting all of the code for a thunk function; `TARGET_ASM_FUNCTION_PROLOGUE` and `TARGET_ASM_FUNCTION_EPILOGUE` are not invoked.

The *thunk_fndecl* is redundant. (*delta* and *function* have already been extracted from it.) It might possibly be useful on some targets, but probably not.

If you do not define this macro, the target-independent code in the C++ front end will generate a less efficient heavyweight thunk that calls *function* instead of jumping to it. The generic approach does not support varargs.

`bool TARGET_ASM_CAN_OUTPUT_MI_THUNK (const_tree thunk_fndecl, HOST_WIDE_INT delta, HOST_WIDE_INT vcall_offset, const_tree function)` [Target Hook]

A function that returns true if TARGET_ASM_OUTPUT_MI_THUNK would be able to output the assembler code for the thunk function specified by the arguments it is passed, and false otherwise. In the latter case, the generic approach will be used by the C++ front end, with the limitations previously exposed.

17.10.12 Generating Code for Profiling

These macros will help you generate code for profiling.

`FUNCTION_PROFILER (file, labelno)` [Macro]

A C statement or compound statement to output to *file* some assembler code to call the profiling subroutine `mcount`.

The details of how `mcount` expects to be called are determined by your operating system environment, not by GCC. To figure them out, compile a small program for

profiling using the system's installed C compiler and look at the assembler code that results.

Older implementations of `mcount` expect the address of a counter variable to be loaded into some register. The name of this variable is '`LP`' followed by the number *labelno*, so you would generate the name using '`LP%d`' in a `fprintf`.

`PROFILE_HOOK` [Macro]

A C statement or compound statement to output to *file* some assembly code to call the profiling subroutine `mcount` even the target does not support profiling.

`NO_PROFILE_COUNTERS` [Macro]

Define this macro to be an expression with a nonzero value if the `mcount` subroutine on your system does not need a counter variable allocated for each function. This is true for almost all modern implementations. If you define this macro, you must not use the *labelno* argument to `FUNCTION_PROFILER`.

`PROFILE_BEFORE_PROLOGUE` [Macro]

Define this macro if the code for function profiling should come before the function prologue. Normally, the profiling code comes after.

17.10.13 Permitting tail calls

`bool TARGET_FUNCTION_OK_FOR_SIBCALL` (*tree* `decl`, *tree* `exp`) [Target Hook]

True if it is OK to do sibling call optimization for the specified call expression *exp*. *decl* will be the called function, or `NULL` if this is an indirect call.

It is not uncommon for limitations of calling conventions to prevent tail calls to functions outside the current unit of translation, or during PIC compilation. The hook is used to enforce these restrictions, as the `sibcall` md pattern can not fail, or fall over to a "normal" call. The criteria for successful sibling call optimization may vary greatly between different architectures.

`void TARGET_EXTRA_LIVE_ON_ENTRY` (*bitmap* `regs`) [Target Hook]

Add any hard registers to *regs* that are live on entry to the function. This hook only needs to be defined to provide registers that cannot be found by examination of FUNCTION_ARG_REGNO_P, the callee saved registers, STATIC_CHAIN_INCOMING_REGNUM, STATIC_CHAIN_REGNUM, TARGET_STRUCT_VALUE_RTX, FRAME_POINTER_REGNUM, EH_USES, FRAME_POINTER_REGNUM, ARG_POINTER_REGNUM, and the PIC_OFFSET_TABLE_REGNUM.

`void TARGET_SET_UP_BY_PROLOGUE` (*struct hard_reg_set_container* *) [Target Hook]

This hook should add additional registers that are computed by the prologue to the hard regset for shrink-wrapping optimization purposes.

`bool TARGET_WARN_FUNC_RETURN` (*tree*) [Target Hook]

True if a function's return statements should be checked for matching the function's return type. This includes checking for falling off the end of a non-void function. Return false if no such check should be made.

17.10.14 Stack smashing protection

`tree TARGET_STACK_PROTECT_GUARD` (*void*) [Target Hook]

This hook returns a `DECL` node for the external variable to use for the stack protection guard. This variable is initialized by the runtime to some random value and is used to initialize the guard value that is placed at the top of the local stack frame. The type of this variable must be `ptr_type_node`.

The default version of this hook creates a variable called '`__stack_chk_guard`', which is normally defined in '`libgcc2.c`'.

`tree TARGET_STACK_PROTECT_FAIL` (*void*) [Target Hook]

This hook returns a `CALL_EXPR` that alerts the runtime that the stack protect guard variable has been modified. This expression should involve a call to a `noreturn` function.

The default version of this hook invokes a function called '`__stack_chk_fail`', taking no arguments. This function is normally defined in '`libgcc2.c`'.

`bool TARGET_SUPPORTS_SPLIT_STACK` (*bool* ***report***, *struct gcc_options* ****opts***) [Common Target Hook]

Whether this target supports splitting the stack when the options described in *opts* have been passed. This is called after options have been parsed, so the target may reject splitting the stack in some configurations. The default version of this hook returns false. If *report* is true, this function may issue a warning or error; if *report* is false, it must simply return a value

17.11 Implementing the Varargs Macros

GCC comes with an implementation of `<varargs.h>` and `<stdarg.h>` that work without change on machines that pass arguments on the stack. Other machines require their own implementations of varargs, and the two machine independent header files must have conditionals to include it.

ISO `<stdarg.h>` differs from traditional `<varargs.h>` mainly in the calling convention for `va_start`. The traditional implementation takes just one argument, which is the variable in which to store the argument pointer. The ISO implementation of `va_start` takes an additional second argument. The user is supposed to write the last named argument of the function here.

However, `va_start` should not use this argument. The way to find the end of the named arguments is with the built-in functions described below.

`__builtin_saveregs` () [Macro]

Use this built-in function to save the argument registers in memory so that the varargs mechanism can access them. Both ISO and traditional versions of `va_start` must use `__builtin_saveregs`, unless you use `TARGET_SETUP_INCOMING_VARARGS` (see below) instead.

On some machines, `__builtin_saveregs` is open-coded under the control of the target hook `TARGET_EXPAND_BUILTIN_SAVEREGS`. On other machines, it calls a routine written in assembler language, found in '`libgcc2.c`'.

Code generated for the call to `__builtin_saveregs` appears at the beginning of the function, as opposed to where the call to `__builtin_saveregs` is written, regardless of what the code is. This is because the registers must be saved before the function starts to use them for its own purposes.

`__builtin_next_arg` (*lastarg*) [Macro]

This builtin returns the address of the first anonymous stack argument, as type `void *`. If `ARGS_GROW_DOWNWARD`, it returns the address of the location above the first anonymous stack argument. Use it in `va_start` to initialize the pointer for fetching arguments from the stack. Also use it in `va_start` to verify that the second parameter *lastarg* is the last named argument of the current function.

`__builtin_classify_type` (*object*) [Macro]

Since each machine has its own conventions for which data types are passed in which kind of register, your implementation of `va_arg` has to embody these conventions. The easiest way to categorize the specified data type is to use `__builtin_classify_type` together with `sizeof` and `__alignof__`.

`__builtin_classify_type` ignores the value of *object*, considering only its data type. It returns an integer describing what kind of type that is—integer, floating, pointer, structure, and so on.

The file '`typeclass.h`' defines an enumeration that you can use to interpret the values of `__builtin_classify_type`.

These machine description macros help implement varargs:

`rtx TARGET_EXPAND_BUILTIN_SAVEREGS` (*void*) [Target Hook]

If defined, this hook produces the machine-specific code for a call to `__builtin_saveregs`. This code will be moved to the very beginning of the function, before any parameter access are made. The return value of this function should be an RTX that contains the value to use as the return of `__builtin_saveregs`.

`void TARGET_SETUP_INCOMING_VARARGS` (*cumulative_args_t* ***args_so_far***, *enum machine_mode* ***mode***, *tree* ***type***, *int* *****pretend_args_size***, *int* ***second_time***) [Target Hook]

This target hook offers an alternative to using `__builtin_saveregs` and defining the hook `TARGET_EXPAND_BUILTIN_SAVEREGS`. Use it to store the anonymous register arguments into the stack so that all the arguments appear to have been passed consecutively on the stack. Once this is done, you can use the standard implementation of varargs that works for machines that pass all their arguments on the stack.

The argument *args_so_far* points to the `CUMULATIVE_ARGS` data structure, containing the values that are obtained after processing the named arguments. The arguments *mode* and *type* describe the last named argument—its machine mode and its data type as a tree node.

The target hook should do two things: first, push onto the stack all the argument registers *not* used for the named arguments, and second, store the size of the data thus pushed into the `int`-valued variable pointed to by *pretend_args_size*. The value that you store here will serve as additional offset for setting up the stack frame.

Because you must generate code to push the anonymous arguments at compile time without knowing their data types, `TARGET_SETUP_INCOMING_VARARGS` is only useful on machines that have just a single category of argument register and use it uniformly for all data types.

If the argument *second_time* is nonzero, it means that the arguments of the function are being analyzed for the second time. This happens for an inline function, which is not actually compiled until the end of the source file. The hook `TARGET_SETUP_INCOMING_VARARGS` should not generate any instructions in this case.

`bool TARGET_STRICT_ARGUMENT_NAMING` (*cumulative_args_t* `ca`) [Target Hook]

Define this hook to return `true` if the location where a function argument is passed depends on whether or not it is a named argument.

This hook controls how the *named* argument to `TARGET_FUNCTION_ARG` is set for varargs and stdarg functions. If this hook returns `true`, the *named* argument is always true for named arguments, and false for unnamed arguments. If it returns `false`, but `TARGET_PRETEND_OUTGOING_VARARGS_NAMED` returns `true`, then all arguments are treated as named. Otherwise, all named arguments except the last are treated as named.

You need not define this hook if it always returns `false`.

`bool TARGET_PRETEND_OUTGOING_VARARGS_NAMED` (*cumulative_args_t* `ca`) [Target Hook]

If you need to conditionally change ABIs so that one works with `TARGET_SETUP_INCOMING_VARARGS`, but the other works like neither `TARGET_SETUP_INCOMING_VARARGS` nor `TARGET_STRICT_ARGUMENT_NAMING` was defined, then define this hook to return `true` if `TARGET_SETUP_INCOMING_VARARGS` is used, `false` otherwise. Otherwise, you should not define this hook.

17.12 Trampolines for Nested Functions

A *trampoline* is a small piece of code that is created at run time when the address of a nested function is taken. It normally resides on the stack, in the stack frame of the containing function. These macros tell GCC how to generate code to allocate and initialize a trampoline.

The instructions in the trampoline must do two things: load a constant address into the static chain register, and jump to the real address of the nested function. On CISC machines such as the m68k, this requires two instructions, a move immediate and a jump. Then the two addresses exist in the trampoline as word-long immediate operands. On RISC machines, it is often necessary to load each address into a register in two parts. Then pieces of each address form separate immediate operands.

The code generated to initialize the trampoline must store the variable parts—the static chain value and the function address—into the immediate operands of the instructions. On a CISC machine, this is simply a matter of copying each address to a memory reference at the proper offset from the start of the trampoline. On a RISC machine, it may be necessary to take out pieces of the address and store them separately.

`void TARGET_ASM_TRAMPOLINE_TEMPLATE (FILE *f)` [Target Hook]

This hook is called by `assemble_trampoline_template` to output, on the stream *f*, assembler code for a block of data that contains the constant parts of a trampoline. This code should not include a label—the label is taken care of automatically.

If you do not define this hook, it means no template is needed for the target. Do not define this hook on systems where the block move code to copy the trampoline into place would be larger than the code to generate it on the spot.

`TRAMPOLINE_SECTION` [Macro]

Return the section into which the trampoline template is to be placed (see Section 17.19 [Sections], page 521). The default value is `readonly_data_section`.

`TRAMPOLINE_SIZE` [Macro]

A C expression for the size in bytes of the trampoline, as an integer.

`TRAMPOLINE_ALIGNMENT` [Macro]

Alignment required for trampolines, in bits.

If you don't define this macro, the value of `FUNCTION_ALIGNMENT` is used for aligning trampolines.

`void TARGET_TRAMPOLINE_INIT (rtx m_tramp, tree fndecl, rtx static_chain)` [Target Hook]

This hook is called to initialize a trampoline. *m_tramp* is an RTX for the memory block for the trampoline; *fndecl* is the `FUNCTION_DECL` for the nested function; *static_chain* is an RTX for the static chain value that should be passed to the function when it is called.

If the target defines `TARGET_ASM_TRAMPOLINE_TEMPLATE`, then the first thing this hook should do is emit a block move into *m_tramp* from the memory block returned by `assemble_trampoline_template`. Note that the block move need only cover the constant parts of the trampoline. If the target isolates the variable parts of the trampoline to the end, not all `TRAMPOLINE_SIZE` bytes need be copied.

If the target requires any other actions, such as flushing caches or enabling stack execution, these actions should be performed after initializing the trampoline proper.

`rtx TARGET_TRAMPOLINE_ADJUST_ADDRESS (rtx addr)` [Target Hook]

This hook should perform any machine-specific adjustment in the address of the trampoline. Its argument contains the address of the memory block that was passed to `TARGET_TRAMPOLINE_INIT`. In case the address to be used for a function call should be different from the address at which the template was stored, the different address should be returned; otherwise *addr* should be returned unchanged. If this hook is not defined, *addr* will be used for function calls.

Implementing trampolines is difficult on many machines because they have separate instruction and data caches. Writing into a stack location fails to clear the memory in the instruction cache, so when the program jumps to that location, it executes the old contents.

Here are two possible solutions. One is to clear the relevant parts of the instruction cache whenever a trampoline is set up. The other is to make all trampolines identical, by having

them jump to a standard subroutine. The former technique makes trampoline execution faster; the latter makes initialization faster.

To clear the instruction cache when a trampoline is initialized, define the following macro.

`CLEAR_INSN_CACHE` (*beg*, *end*) [Macro]

If defined, expands to a C expression clearing the *instruction cache* in the specified interval. The definition of this macro would typically be a series of `asm` statements. Both *beg* and *end* are both pointer expressions.

To use a standard subroutine, define the following macro. In addition, you must make sure that the instructions in a trampoline fill an entire cache line with identical instructions, or else ensure that the beginning of the trampoline code is always aligned at the same point in its cache line. Look in '`m68k.h`' as a guide.

`TRANSFER_FROM_TRAMPOLINE` [Macro]

Define this macro if trampolines need a special subroutine to do their work. The macro should expand to a series of `asm` statements which will be compiled with GCC. They go in a library function named `__transfer_from_trampoline`.

If you need to avoid executing the ordinary prologue code of a compiled C function when you jump to the subroutine, you can do so by placing a special label of your own in the assembler code. Use one `asm` statement to generate an assembler label, and another to make the label global. Then trampolines can use that label to jump directly to your special assembler code.

17.13 Implicit Calls to Library Routines

Here is an explanation of implicit calls to library routines.

`DECLARE_LIBRARY_RENAMES` [Macro]

This macro, if defined, should expand to a piece of C code that will get expanded when compiling functions for libgcc.a. It can be used to provide alternate names for GCC's internal library functions if there are ABI-mandated names that the compiler should provide.

`void TARGET_INIT_LIBFUNCS` (*void*) [Target Hook]

This hook should declare additional library routines or rename existing ones, using the functions `set_optab_libfunc` and `init_one_libfunc` defined in '`optabs.c`'. `init_optabs` calls this macro after initializing all the normal library routines.

The default is to do nothing. Most ports don't need to define this hook.

`bool TARGET_LIBFUNC_GNU_PREFIX` [Target Hook]

If false (the default), internal library routines start with two underscores. If set to true, these routines start with `__gnu_` instead. E.g., `__muldi3` changes to `__gnu_muldi3`. This currently only affects functions defined in '`libgcc2.c`'. If this is set to true, the '`tm.h`' file must also `#define LIBGCC2_GNU_PREFIX`.

`FLOAT_LIB_COMPARE_RETURNS_BOOL` (*mode*, *comparison*) [Macro]

This macro should return `true` if the library routine that implements the floating point comparison operator *comparison* in mode *mode* will return a boolean, and *false* if it will return a tristate.

GCC's own floating point libraries return tristates from the comparison operators, so the default returns false always. Most ports don't need to define this macro.

`TARGET_LIB_INT_CMP_BIASED` [Macro]

This macro should evaluate to `true` if the integer comparison functions (like `__cmpdi2`) return 0 to indicate that the first operand is smaller than the second, 1 to indicate that they are equal, and 2 to indicate that the first operand is greater than the second. If this macro evaluates to `false` the comparison functions return −1, 0, and 1 instead of 0, 1, and 2. If the target uses the routines in '`libgcc.a`', you do not need to define this macro.

`TARGET_HAS_NO_HW_DIVIDE` [Macro]

This macro should be defined if the target has no hardware divide instructions. If this macro is defined, GCC will use an algorithm which make use of simple logical and arithmetic operations for 64-bit division. If the macro is not defined, GCC will use an algorithm which make use of a 64-bit by 32-bit divide primitive.

`TARGET_EDOM` [Macro]

The value of `EDOM` on the target machine, as a C integer constant expression. If you don't define this macro, GCC does not attempt to deposit the value of `EDOM` into `errno` directly. Look in '`/usr/include/errno.h`' to find the value of `EDOM` on your system.

If you do not define `TARGET_EDOM`, then compiled code reports domain errors by calling the library function and letting it report the error. If mathematical functions on your system use `matherr` when there is an error, then you should leave `TARGET_EDOM` undefined so that `matherr` is used normally.

`GEN_ERRNO_RTX` [Macro]

Define this macro as a C expression to create an rtl expression that refers to the global "variable" `errno`. (On certain systems, `errno` may not actually be a variable.) If you don't define this macro, a reasonable default is used.

`bool TARGET_LIBC_HAS_FUNCTION` (*enum function_class* ***fn_class***) [Target Hook]

This hook determines whether a function from a class of functions *fn_class* is present at the runtime.

`NEXT_OBJC_RUNTIME` [Macro]

Set this macro to 1 to use the "NeXT" Objective-C message sending conventions by default. This calling convention involves passing the object, the selector and the method arguments all at once to the method-lookup library function. This is the usual setting when targeting Darwin/Mac OS X systems, which have the NeXT runtime installed.

If the macro is set to 0, the "GNU" Objective-C message sending convention will be used by default. This convention passes just the object and the selector to the method-lookup function, which returns a pointer to the method.

In either case, it remains possible to select code-generation for the alternate scheme, by means of compiler command line switches.

17.14 Addressing Modes

This is about addressing modes.

`HAVE_PRE_INCREMENT` [Macro]
`HAVE_PRE_DECREMENT` [Macro]
`HAVE_POST_INCREMENT` [Macro]
`HAVE_POST_DECREMENT` [Macro]

A C expression that is nonzero if the machine supports pre-increment, pre-decrement, post-increment, or post-decrement addressing respectively.

`HAVE_PRE_MODIFY_DISP` [Macro]
`HAVE_POST_MODIFY_DISP` [Macro]

A C expression that is nonzero if the machine supports pre- or post-address side-effect generation involving constants other than the size of the memory operand.

`HAVE_PRE_MODIFY_REG` [Macro]
`HAVE_POST_MODIFY_REG` [Macro]

A C expression that is nonzero if the machine supports pre- or post-address side-effect generation involving a register displacement.

`CONSTANT_ADDRESS_P (x)` [Macro]

A C expression that is 1 if the RTX *x* is a constant which is a valid address. On most machines the default definition of `(CONSTANT_P (x) && GET_CODE (x) != CONST_DOUBLE)` is acceptable, but a few machines are more restrictive as to which constant addresses are supported.

`CONSTANT_P (x)` [Macro]

`CONSTANT_P`, which is defined by target-independent code, accepts integer-values expressions whose values are not explicitly known, such as `symbol_ref`, `label_ref`, and `high` expressions and `const` arithmetic expressions, in addition to `const_int` and `const_double` expressions.

`MAX_REGS_PER_ADDRESS` [Macro]

A number, the maximum number of registers that can appear in a valid memory address. Note that it is up to you to specify a value equal to the maximum number that `TARGET_LEGITIMATE_ADDRESS_P` would ever accept.

`bool TARGET_LEGITIMATE_ADDRESS_P (`*enum machine_mode* `mode`, *rtx* `x`, *bool* `strict``)` [Target Hook]

A function that returns whether *x* (an RTX) is a legitimate memory address on the target machine for a memory operand of mode *mode*.

Legitimate addresses are defined in two variants: a strict variant and a non-strict one. The *strict* parameter chooses which variant is desired by the caller.

The strict variant is used in the reload pass. It must be defined so that any pseudo-register that has not been allocated a hard register is considered a memory reference. This is because in contexts where some kind of register is required, a pseudo-register with no hard register must be rejected. For non-hard registers, the strict variant should look up the `reg_renumber` array; it should then proceed using the hard register number in the array, or treat the pseudo as a memory reference if the array holds `-1`.

The non-strict variant is used in other passes. It must be defined to accept all pseudo-registers in every context where some kind of register is required.

Normally, constant addresses which are the sum of a `symbol_ref` and an integer are stored inside a `const` RTX to mark them as constant. Therefore, there is no need to recognize such sums specifically as legitimate addresses. Normally you would simply recognize any `const` as legitimate.

Usually `PRINT_OPERAND_ADDRESS` is not prepared to handle constant sums that are not marked with `const`. It assumes that a naked `plus` indicates indexing. If so, then you *must* reject such naked constant sums as illegitimate addresses, so that none of them will be given to `PRINT_OPERAND_ADDRESS`.

On some machines, whether a symbolic address is legitimate depends on the section that the address refers to. On these machines, define the target hook `TARGET_ENCODE_SECTION_INFO` to store the information into the `symbol_ref`, and then check for it here. When you see a `const`, you will have to look inside it to find the `symbol_ref` in order to determine the section. See Section 17.21 [Assembler Format], page 527.

Some ports are still using a deprecated legacy substitute for this hook, the `GO_IF_LEGITIMATE_ADDRESS` macro. This macro has this syntax:

```
#define GO_IF_LEGITIMATE_ADDRESS (mode, x, label)
```

and should `goto` *`label`* if the address *x* is a valid address on the target machine for a memory operand of mode *mode*.

Compiler source files that want to use the strict variant of this macro define the macro `REG_OK_STRICT`. You should use an `#ifdef REG_OK_STRICT` conditional to define the strict variant in that case and the non-strict variant otherwise.

Using the hook is usually simpler because it limits the number of files that are recompiled when changes are made.

`TARGET_MEM_CONSTRAINT` [Macro]

A single character to be used instead of the default `'m'` character for general memory addresses. This defines the constraint letter which matches the memory addresses accepted by `TARGET_LEGITIMATE_ADDRESS_P`. Define this macro if you want to support new address formats in your back end without changing the semantics of the `'m'` constraint. This is necessary in order to preserve functionality of inline assembly constructs using the `'m'` constraint.

`FIND_BASE_TERM (x)` [Macro]

A C expression to determine the base term of address *x*, or to provide a simplified version of *x* from which '`alias.c`' can easily find the base term. This macro is used in only two places: `find_base_value` and `find_base_term` in '`alias.c`'.

It is always safe for this macro to not be defined. It exists so that alias analysis can understand machine-dependent addresses.

The typical use of this macro is to handle addresses containing a label_ref or symbol_ref within an UNSPEC.

`rtx TARGET_LEGITIMIZE_ADDRESS (`*rtx* `x`, *rtx* `oldx`, *enum machine_mode* `mode``)` [Target Hook]

This hook is given an invalid memory address *x* for an operand of mode *mode* and should try to return a valid memory address.

x will always be the result of a call to `break_out_memory_refs`, and *oldx* will be the operand that was given to that function to produce *x*.

The code of the hook should not alter the substructure of *x*. If it transforms *x* into a more legitimate form, it should return the new *x*.

It is not necessary for this hook to come up with a legitimate address, with the exception of native TLS addresses (see Section 17.26 [Emulated TLS], page 567). The compiler has standard ways of doing so in all cases. In fact, if the target supports only emulated TLS, it is safe to omit this hook or make it return *x* if it cannot find a valid way to legitimize the address. But often a machine-dependent strategy can generate better code.

`LEGITIMIZE_RELOAD_ADDRESS` (*x*, *mode*, *opnum*, *type*, *ind_levels*, *win*) [Macro]

A C compound statement that attempts to replace *x*, which is an address that needs reloading, with a valid memory address for an operand of mode *mode*. *win* will be a C statement label elsewhere in the code. It is not necessary to define this macro, but it might be useful for performance reasons.

For example, on the i386, it is sometimes possible to use a single reload register instead of two by reloading a sum of two pseudo registers into a register. On the other hand, for number of RISC processors offsets are limited so that often an intermediate address needs to be generated in order to address a stack slot. By defining `LEGITIMIZE_RELOAD_ADDRESS` appropriately, the intermediate addresses generated for adjacent some stack slots can be made identical, and thus be shared.

Note: This macro should be used with caution. It is necessary to know something of how reload works in order to effectively use this, and it is quite easy to produce macros that build in too much knowledge of reload internals.

Note: This macro must be able to reload an address created by a previous invocation of this macro. If it fails to handle such addresses then the compiler may generate incorrect code or abort.

The macro definition should use `push_reload` to indicate parts that need reloading; *opnum*, *type* and *ind_levels* are usually suitable to be passed unaltered to `push_reload`.

The code generated by this macro must not alter the substructure of *x*. If it transforms *x* into a more legitimate form, it should assign *x* (which will always be a C variable) a new value. This also applies to parts that you change indirectly by calling `push_reload`.

The macro definition may use `strict_memory_address_p` to test if the address has become legitimate.

If you want to change only a part of *x*, one standard way of doing this is to use `copy_rtx`. Note, however, that it unshares only a single level of rtl. Thus, if the part to be changed is not at the top level, you'll need to replace first the top level. It is not necessary for this macro to come up with a legitimate address; but often a machine-dependent strategy can generate better code.

`bool TARGET_MODE_DEPENDENT_ADDRESS_P (const_rtx addr, addr_space_t addrspace)` [Target Hook]

This hook returns `true` if memory address *addr* in address space *addrspace* can have different meanings depending on the machine mode of the memory reference it is used for or if the address is valid for some modes but not others.

Autoincrement and autodecrement addresses typically have mode-dependent effects because the amount of the increment or decrement is the size of the operand being addressed. Some machines have other mode-dependent addresses. Many RISC machines have no mode-dependent addresses.

You may assume that *addr* is a valid address for the machine.

The default version of this hook returns `false`.

`bool TARGET_LEGITIMATE_CONSTANT_P (enum machine_mode mode, rtx x)` [Target Hook]

This hook returns true if *x* is a legitimate constant for a *mode*-mode immediate operand on the target machine. You can assume that *x* satisfies `CONSTANT_P`, so you need not check this.

The default definition returns true.

`rtx TARGET_DELEGITIMIZE_ADDRESS (rtx x)` [Target Hook]

This hook is used to undo the possibly obfuscating effects of the `LEGITIMIZE_ADDRESS` and `LEGITIMIZE_RELOAD_ADDRESS` target macros. Some backend implementations of these macros wrap symbol references inside an `UNSPEC` rtx to represent PIC or similar addressing modes. This target hook allows GCC's optimizers to understand the semantics of these opaque `UNSPEC`s by converting them back into their original form.

`bool TARGET_CONST_NOT_OK_FOR_DEBUG_P (rtx x)` [Target Hook]

This hook should return true if *x* should not be emitted into debug sections.

`bool TARGET_CANNOT_FORCE_CONST_MEM (enum machine_mode mode, rtx x)` [Target Hook]

This hook should return true if *x* is of a form that cannot (or should not) be spilled to the constant pool. *mode* is the mode of *x*.

The default version of this hook returns false.

The primary reason to define this hook is to prevent reload from deciding that a non-legitimate constant would be better reloaded from the constant pool instead of spilling and reloading a register holding the constant. This restriction is often true of addresses of TLS symbols for various targets.

`bool TARGET_USE_BLOCKS_FOR_CONSTANT_P (enum machine_mode mode, const_rtx x)` [Target Hook]

This hook should return true if pool entries for constant *x* can be placed in an `object_block` structure. *mode* is the mode of *x*.

The default version returns false for all constants.

`bool TARGET_USE_BLOCKS_FOR_DECL_P` (*const_tree* `decl`) [Target Hook]

This hook should return true if pool entries for *decl* should be placed in an `object_block` structure.

The default version returns true for all decls.

`tree TARGET_BUILTIN_RECIPROCAL` (*unsigned* `fn`, *bool* `md_fn`, *bool* `sqrt`) [Target Hook]

This hook should return the DECL of a function that implements reciprocal of the builtin function with builtin function code *fn*, or `NULL_TREE` if such a function is not available. *md_fn* is true when *fn* is a code of a machine-dependent builtin function. When *sqrt* is true, additional optimizations that apply only to the reciprocal of a square root function are performed, and only reciprocals of `sqrt` function are valid.

`tree TARGET_VECTORIZE_BUILTIN_MASK_FOR_LOAD` (*void*) [Target Hook]

This hook should return the DECL of a function *f* that given an address *addr* as an argument returns a mask *m* that can be used to extract from two vectors the relevant data that resides in *addr* in case *addr* is not properly aligned.

The autovectorizer, when vectorizing a load operation from an address *addr* that may be unaligned, will generate two vector loads from the two aligned addresses around *addr*. It then generates a `REALIGN_LOAD` operation to extract the relevant data from the two loaded vectors. The first two arguments to `REALIGN_LOAD`, *v1* and *v2*, are the two vectors, each of size *VS*, and the third argument, *OFF*, defines how the data will be extracted from these two vectors: if *OFF* is 0, then the returned vector is *v2*; otherwise, the returned vector is composed from the last *VS-OFF* elements of *v1* concatenated to the first *OFF* elements of *v2*.

If this hook is defined, the autovectorizer will generate a call to *f* (using the DECL tree that this hook returns) and will use the return value of *f* as the argument *OFF* to `REALIGN_LOAD`. Therefore, the mask *m* returned by *f* should comply with the semantics expected by `REALIGN_LOAD` described above. If this hook is not defined, then *addr* will be used as the argument *OFF* to `REALIGN_LOAD`, in which case the low $\log2(VS) - 1$ bits of *addr* will be considered.

`int TARGET_VECTORIZE_BUILTIN_VECTORIZATION_COST` (*enum vect_cost_for_stmt* `type_of_cost`, *tree* `vectype`, *int* `misalign`) [Target Hook]

Returns cost of different scalar or vector statements for vectorization cost model. For vector memory operations the cost may depend on type (*vectype*) and misalignment value (*misalign*).

`bool TARGET_VECTORIZE_VECTOR_ALIGNMENT_REACHABLE` (*const_tree* `type`, *bool* `is_packed`) [Target Hook]

Return true if vector alignment is reachable (by peeling N iterations) for the given type.

`bool TARGET_VECTORIZE_VEC_PERM_CONST_OK` (*enum* `machine_mode`, *const unsigned char* `*sel`) [Target Hook]

Return true if a vector created for `vec_perm_const` is valid.

`tree TARGET_VECTORIZE_BUILTIN_CONVERSION` (*unsigned* `code`, *tree* `dest_type`, *tree* `src_type`) [Target Hook]

This hook should return the DECL of a function that implements conversion of the input vector of type *src_type* to type *dest_type*. The value of *code* is one of the enumerators in `enum tree_code` and specifies how the conversion is to be applied (truncation, rounding, etc.).

If this hook is defined, the autovectorizer will use the `TARGET_VECTORIZE_BUILTIN_CONVERSION` target hook when vectorizing conversion. Otherwise, it will return `NULL_TREE`.

`tree TARGET_VECTORIZE_BUILTIN_VECTORIZED_FUNCTION` (*tree* `fndecl`, *tree* `vec_type_out`, *tree* `vec_type_in`) [Target Hook]

This hook should return the decl of a function that implements the vectorized variant of the builtin function with builtin function code *code* or `NULL_TREE` if such a function is not available. The value of *fndecl* is the builtin function declaration. The return type of the vectorized function shall be of vector type *vec_type_out* and the argument types should be *vec_type_in*.

`bool TARGET_VECTORIZE_SUPPORT_VECTOR_MISALIGNMENT` (*enum machine_mode* `mode`, *const_tree* `type`, *int* `misalignment`, *bool* `is_packed`) [Target Hook]

This hook should return true if the target supports misaligned vector store/load of a specific factor denoted in the *misalignment* parameter. The vector store/load should be of machine mode *mode* and the elements in the vectors should be of type *type*. *is_packed* parameter is true if the memory access is defined in a packed struct.

`enum machine_mode TARGET_VECTORIZE_PREFERRED_SIMD_MODE` (*enum machine_mode* `mode`) [Target Hook]

This hook should return the preferred mode for vectorizing scalar mode *mode*. The default is equal to `word_mode`, because the vectorizer can do some transformations even in absence of specialized SIMD hardware.

`unsigned int TARGET_VECTORIZE_AUTOVECTORIZE_VECTOR_SIZES` (*void*) [Target Hook]

This hook should return a mask of sizes that should be iterated over after trying to autovectorize using the vector size derived from the mode returned by `TARGET_VECTORIZE_PREFERRED_SIMD_MODE`. The default is zero which means to not iterate over other vector sizes.

`void * TARGET_VECTORIZE_INIT_COST` (*struct loop* `*loop_info`) [Target Hook]

This hook should initialize target-specific data structures in preparation for modeling the costs of vectorizing a loop or basic block. The default allocates three unsigned integers for accumulating costs for the prologue, body, and epilogue of the loop or basic block. If *loop_info* is non-NULL, it identifies the loop being vectorized; otherwise a single block is being vectorized.

`unsigned TARGET_VECTORIZE_ADD_STMT_COST` (*void* `*data`, *int* `count`, *enum vect_cost_for_stmt* `kind`, *struct _stmt_vec_info* `*stmt_info`, *int* `misalign`, *enum vect_cost_model_location* `where`) [Target Hook]

This hook should update the target-specific *data* in response to adding *count* copies of the given *kind* of statement to a loop or basic block. The default adds the builtin

vectorizer cost for the copies of the statement to the accumulator specified by *where*, (the prologue, body, or epilogue) and returns the amount added. The return value should be viewed as a tentative cost that may later be revised.

`void TARGET_VECTORIZE_FINISH_COST` (*void* *`data`, *unsigned* *`prologue_cost`, *unsigned* *`body_cost`, *unsigned* *`epilogue_cost`) [Target Hook]

This hook should complete calculations of the cost of vectorizing a loop or basic block based on *data*, and return the prologue, body, and epilogue costs as unsigned integers. The default returns the value of the three accumulators.

`void TARGET_VECTORIZE_DESTROY_COST_DATA` (*void* *`data`) [Target Hook]

This hook should release *data* and any related data structures allocated by TARGET_VECTORIZE_INIT_COST. The default releases the accumulator.

`tree TARGET_VECTORIZE_BUILTIN_TM_LOAD` (*tree*) [Target Hook]

This hook should return the built-in decl needed to load a vector of the given type within a transaction.

`tree TARGET_VECTORIZE_BUILTIN_TM_STORE` (*tree*) [Target Hook]

This hook should return the built-in decl needed to store a vector of the given type within a transaction.

`tree TARGET_VECTORIZE_BUILTIN_GATHER` (*const_tree* `mem_vectype`, *const_tree* `index_type`, *int* `scale`) [Target Hook]

Target builtin that implements vector gather operation. *mem_vectype* is the vector type of the load and *index_type* is scalar type of the index, scaled by *scale*. The default is `NULL_TREE` which means to not vectorize gather loads.

`int TARGET_SIMD_CLONE_COMPUTE_VECSIZE_AND_SIMDLEN` (*struct cgraph_node *, struct cgraph_simd_clone **, `tree`, `int`) [Target Hook]

This hook should set *vecsize_mangle*, *vecsize_int*, *vecsize_float* fields in *simd_clone* structure pointed by *clone_info* argument and also *simdlen* field if it was previously 0. The hook should return 0 if SIMD clones shouldn't be emitted, or number of *vecsize_mangle* variants that should be emitted.

`void TARGET_SIMD_CLONE_ADJUST` (*struct cgraph_node **) [Target Hook]

This hook should add implicit `attribute(target("..."))` attribute to SIMD clone *node* if needed.

`int TARGET_SIMD_CLONE_USABLE` (*struct cgraph_node **) [Target Hook]

This hook should return -1 if SIMD clone *node* shouldn't be used in vectorized loops in current function, or non-negative number if it is usable. In that case, the smaller the number is, the more desirable it is to use it.

17.15 Anchored Addresses

GCC usually addresses every static object as a separate entity. For example, if we have:

```
static int a, b, c;
int foo (void) { return a + b + c; }
```

the code for `foo` will usually calculate three separate symbolic addresses: those of `a`, `b` and `c`. On some targets, it would be better to calculate just one symbolic address and access the three variables relative to it. The equivalent pseudocode would be something like:

```
int foo (void)
{
  register int *xr = &x;
  return xr[&a - &x] + xr[&b - &x] + xr[&c - &x];
}
```

(which isn't valid C). We refer to shared addresses like `x` as "section anchors". Their use is controlled by '`-fsection-anchors`'.

The hooks below describe the target properties that GCC needs to know in order to make effective use of section anchors. It won't use section anchors at all unless either `TARGET_MIN_ANCHOR_OFFSET` or `TARGET_MAX_ANCHOR_OFFSET` is set to a nonzero value.

`HOST_WIDE_INT TARGET_MIN_ANCHOR_OFFSET` [Target Hook]

The minimum offset that should be applied to a section anchor. On most targets, it should be the smallest offset that can be applied to a base register while still giving a legitimate address for every mode. The default value is 0.

`HOST_WIDE_INT TARGET_MAX_ANCHOR_OFFSET` [Target Hook]

Like `TARGET_MIN_ANCHOR_OFFSET`, but the maximum (inclusive) offset that should be applied to section anchors. The default value is 0.

`void TARGET_ASM_OUTPUT_ANCHOR (`*rtx* `x)` [Target Hook]

Write the assembly code to define section anchor *x*, which is a `SYMBOL_REF` for which '`SYMBOL_REF_ANCHOR_P (x)`' is true. The hook is called with the assembly output position set to the beginning of `SYMBOL_REF_BLOCK (x)`.

If `ASM_OUTPUT_DEF` is available, the hook's default definition uses it to define the symbol as '`. + SYMBOL_REF_BLOCK_OFFSET (x)`'. If `ASM_OUTPUT_DEF` is not available, the hook's default definition is `NULL`, which disables the use of section anchors altogether.

`bool TARGET_USE_ANCHORS_FOR_SYMBOL_P (`*const_rtx* `x)` [Target Hook]

Return true if GCC should attempt to use anchors to access `SYMBOL_REF` *x*. You can assume '`SYMBOL_REF_HAS_BLOCK_INFO_P (x)`' and '`!SYMBOL_REF_ANCHOR_P (x)`'.

The default version is correct for most targets, but you might need to intercept this hook to handle things like target-specific attributes or target-specific sections.

17.16 Condition Code Status

The macros in this section can be split in two families, according to the two ways of representing condition codes in GCC.

The first representation is the so called `(cc0)` representation (see Section 16.12 [Jump Patterns], page 380), where all instructions can have an implicit clobber of the condition codes. The second is the condition code register representation, which provides better schedulability for architectures that do have a condition code register, but on which most instructions do not affect it. The latter category includes most RISC machines.

The implicit clobbering poses a strong restriction on the placement of the definition and use of the condition code. In the past the definition and use were always adjacent.

However, recent changes to support trapping arithmatic may result in the definition and user being in different blocks. Thus, there may be a `NOTE_INSN_BASIC_BLOCK` between them. Additionally, the definition may be the source of exception handling edges.

These restrictions can prevent important optimizations on some machines. For example, on the IBM RS/6000, there is a delay for taken branches unless the condition code register is set three instructions earlier than the conditional branch. The instruction scheduler cannot perform this optimization if it is not permitted to separate the definition and use of the condition code register.

For this reason, it is possible and suggested to use a register to represent the condition code for new ports. If there is a specific condition code register in the machine, use a hard register. If the condition code or comparison result can be placed in any general register, or if there are multiple condition registers, use a pseudo register. Registers used to store the condition code value will usually have a mode that is in class `MODE_CC`.

Alternatively, you can use `BImode` if the comparison operator is specified already in the compare instruction. In this case, you are not interested in most macros in this section.

17.16.1 Representation of condition codes using (cc0)

The file '`conditions.h`' defines a variable `cc_status` to describe how the condition code was computed (in case the interpretation of the condition code depends on the instruction that it was set by). This variable contains the RTL expressions on which the condition code is currently based, and several standard flags.

Sometimes additional machine-specific flags must be defined in the machine description header file. It can also add additional machine-specific information by defining `CC_STATUS_MDEP`.

`CC_STATUS_MDEP` [Macro]

C code for a data type which is used for declaring the `mdep` component of `cc_status`. It defaults to `int`.

This macro is not used on machines that do not use `cc0`.

`CC_STATUS_MDEP_INIT` [Macro]

A C expression to initialize the `mdep` field to "empty". The default definition does nothing, since most machines don't use the field anyway. If you want to use the field, you should probably define this macro to initialize it.

This macro is not used on machines that do not use `cc0`.

`NOTICE_UPDATE_CC` (*exp*, *insn*) [Macro]

A C compound statement to set the components of `cc_status` appropriately for an insn *insn* whose body is *exp*. It is this macro's responsibility to recognize insns that set the condition code as a byproduct of other activity as well as those that explicitly set `(cc0)`.

This macro is not used on machines that do not use `cc0`.

If there are insns that do not set the condition code but do alter other machine registers, this macro must check to see whether they invalidate the expressions that the condition code is recorded as reflecting. For example, on the 68000, insns that store in address registers do not set the condition code, which means that usually

NOTICE_UPDATE_CC can leave cc_status unaltered for such insns. But suppose that the previous insn set the condition code based on location 'a4@(102)' and the current insn stores a new value in 'a4'. Although the condition code is not changed by this, it will no longer be true that it reflects the contents of 'a4@(102)'. Therefore, NOTICE_UPDATE_CC must alter cc_status in this case to say that nothing is known about the condition code value.

The definition of NOTICE_UPDATE_CC must be prepared to deal with the results of peephole optimization: insns whose patterns are parallel RTXs containing various reg, mem or constants which are just the operands. The RTL structure of these insns is not sufficient to indicate what the insns actually do. What NOTICE_UPDATE_CC should do when it sees one is just to run CC_STATUS_INIT.

A possible definition of NOTICE_UPDATE_CC is to call a function that looks at an attribute (see Section 16.19 [Insn Attributes], page 394) named, for example, 'cc'. This avoids having detailed information about patterns in two places, the 'md' file and in NOTICE_UPDATE_CC.

17.16.2 Representation of condition codes using registers

SELECT_CC_MODE (*op*, *x*, *y*) [Macro]

On many machines, the condition code may be produced by other instructions than compares, for example the branch can use directly the condition code set by a subtract instruction. However, on some machines when the condition code is set this way some bits (such as the overflow bit) are not set in the same way as a test instruction, so that a different branch instruction must be used for some conditional branches. When this happens, use the machine mode of the condition code register to record different formats of the condition code register. Modes can also be used to record which compare instruction (e.g. a signed or an unsigned comparison) produced the condition codes.

If other modes than CCmode are required, add them to '*machine*-modes.def' and define SELECT_CC_MODE to choose a mode given an operand of a compare. This is needed because the modes have to be chosen not only during RTL generation but also, for example, by instruction combination. The result of SELECT_CC_MODE should be consistent with the mode used in the patterns; for example to support the case of the add on the SPARC discussed above, we have the pattern

```
(define_insn ""
  [(set (reg:CC_NOOV 0)
        (compare:CC_NOOV
          (plus:SI (match_operand:SI 0 "register_operand" "%r")
                   (match_operand:SI 1 "arith_operand" "rI"))
          (const_int 0)))]
  ""
  "...")
```

together with a SELECT_CC_MODE that returns CC_NOOVmode for comparisons whose argument is a plus:

```
#define SELECT_CC_MODE(OP,X,Y) \
  (GET_MODE_CLASS (GET_MODE (X)) == MODE_FLOAT          \
   ? ((OP == EQ || OP == NE) ? CCFPmode : CCFPEmode)    \
   : ((GET_CODE (X) == PLUS || GET_CODE (X) == MINUS    \
```

```
          || GET_CODE (X) == NEG) \
         ? CC_NOOVmode : CCmode))
```

Another reason to use modes is to retain information on which operands were used by the comparison; see `REVERSIBLE_CC_MODE` later in this section.

You should define this macro if and only if you define extra CC modes in '*machine*-`modes.def`'.

`void TARGET_CANONICALIZE_COMPARISON (int *code, rtx *op0, rtx *op1, bool op0_preserve_value)` [Target Hook]

On some machines not all possible comparisons are defined, but you can convert an invalid comparison into a valid one. For example, the Alpha does not have a `GT` comparison, but you can use an `LT` comparison instead and swap the order of the operands.

On such machines, implement this hook to do any required conversions. *code* is the initial comparison code and *op0* and *op1* are the left and right operands of the comparison, respectively. If *op0_preserve_value* is `true` the implementation is not allowed to change the value of *op0* since the value might be used in RTXs which aren't comparisons. E.g. the implementation is not allowed to swap operands in that case.

GCC will not assume that the comparison resulting from this macro is valid but will see if the resulting insn matches a pattern in the '`md`' file.

You need not to implement this hook if it would never change the comparison code or operands.

`REVERSIBLE_CC_MODE (mode)` [Macro]

A C expression whose value is one if it is always safe to reverse a comparison whose mode is *mode*. If `SELECT_CC_MODE` can ever return *mode* for a floating-point inequality comparison, then `REVERSIBLE_CC_MODE (mode)` must be zero.

You need not define this macro if it would always returns zero or if the floating-point format is anything other than `IEEE_FLOAT_FORMAT`. For example, here is the definition used on the SPARC, where floating-point inequality comparisons are always given `CCFPEmode`:

```
#define REVERSIBLE_CC_MODE(MODE)  ((MODE) != CCFPEmode)
```

`REVERSE_CONDITION (code, mode)` [Macro]

A C expression whose value is reversed condition code of the *code* for comparison done in CC_MODE *mode*. The macro is used only in case `REVERSIBLE_CC_MODE (mode)` is nonzero. Define this macro in case machine has some non-standard way how to reverse certain conditionals. For instance in case all floating point conditions are non-trapping, compiler may freely convert unordered compares to ordered one. Then definition may look like:

```
#define REVERSE_CONDITION(CODE, MODE) \
   ((MODE) != CCFPmode ? reverse_condition (CODE) \
    : reverse_condition_maybe_unordered (CODE))
```

`bool TARGET_FIXED_CONDITION_CODE_REGS` (*unsigned int *p1, unsigned int *p2*) [Target Hook]

On targets which do not use `(cc0)`, and which use a hard register rather than a pseudo-register to hold condition codes, the regular CSE passes are often not able to identify cases in which the hard register is set to a common value. Use this hook to enable a small pass which optimizes such cases. This hook should return true to enable this pass, and it should set the integers to which its arguments point to the hard register numbers used for condition codes. When there is only one such register, as is true on most systems, the integer pointed to by *p2* should be set to `INVALID_REGNUM`.

The default version of this hook returns false.

`enum machine_mode TARGET_CC_MODES_COMPATIBLE` (*enum machine_mode m1, enum machine_mode m2*) [Target Hook]

On targets which use multiple condition code modes in class `MODE_CC`, it is sometimes the case that a comparison can be validly done in more than one mode. On such a system, define this target hook to take two mode arguments and to return a mode in which both comparisons may be validly done. If there is no such mode, return `VOIDmode`.

The default version of this hook checks whether the modes are the same. If they are, it returns that mode. If they are different, it returns `VOIDmode`.

17.17 Describing Relative Costs of Operations

These macros let you describe the relative speed of various operations on the target machine.

`REGISTER_MOVE_COST` (*mode, from, to*) [Macro]

A C expression for the cost of moving data of mode *mode* from a register in class *from* to one in class *to*. The classes are expressed using the enumeration values such as `GENERAL_REGS`. A value of 2 is the default; other values are interpreted relative to that.

It is not required that the cost always equal 2 when *from* is the same as *to*; on some machines it is expensive to move between registers if they are not general registers.

If reload sees an insn consisting of a single `set` between two hard registers, and if `REGISTER_MOVE_COST` applied to their classes returns a value of 2, reload does not check to ensure that the constraints of the insn are met. Setting a cost of other than 2 will allow reload to verify that the constraints are met. You should do this if the '`movm`' pattern's constraints do not allow such copying.

These macros are obsolete, new ports should use the target hook `TARGET_REGISTER_MOVE_COST` instead.

`int TARGET_REGISTER_MOVE_COST` (*enum machine_mode mode, reg_class_t from, reg_class_t to*) [Target Hook]

This target hook should return the cost of moving data of mode *mode* from a register in class *from* to one in class *to*. The classes are expressed using the enumeration values such as `GENERAL_REGS`. A value of 2 is the default; other values are interpreted relative to that.

It is not required that the cost always equal 2 when *from* is the same as *to*; on some machines it is expensive to move between registers if they are not general registers.

If reload sees an insn consisting of a single `set` between two hard registers, and if `TARGET_REGISTER_MOVE_COST` applied to their classes returns a value of 2, reload does not check to ensure that the constraints of the insn are met. Setting a cost of other than 2 will allow reload to verify that the constraints are met. You should do this if the '`mov`*m*' pattern's constraints do not allow such copying.

The default version of this function returns 2.

`MEMORY_MOVE_COST` (*`mode`*, *`class`*, *`in`*) [Macro]

A C expression for the cost of moving data of mode *mode* between a register of class *class* and memory; *in* is zero if the value is to be written to memory, nonzero if it is to be read in. This cost is relative to those in `REGISTER_MOVE_COST`. If moving between registers and memory is more expensive than between two registers, you should define this macro to express the relative cost.

If you do not define this macro, GCC uses a default cost of 4 plus the cost of copying via a secondary reload register, if one is needed. If your machine requires a secondary reload register to copy between memory and a register of *class* but the reload mechanism is more complex than copying via an intermediate, define this macro to reflect the actual cost of the move.

GCC defines the function `memory_move_secondary_cost` if secondary reloads are needed. It computes the costs due to copying via a secondary register. If your machine copies from memory using a secondary register in the conventional way but the default base value of 4 is not correct for your machine, define this macro to add some other value to the result of that function. The arguments to that function are the same as to this macro.

These macros are obsolete, new ports should use the target hook `TARGET_MEMORY_MOVE_COST` instead.

`int TARGET_MEMORY_MOVE_COST` (*enum machine_mode* *`mode`*, *reg_class_t* *`rclass`*, *bool* *`in`*) [Target Hook]

This target hook should return the cost of moving data of mode *mode* between a register of class *rclass* and memory; *in* is `false` if the value is to be written to memory, `true` if it is to be read in. This cost is relative to those in `TARGET_REGISTER_MOVE_COST`. If moving between registers and memory is more expensive than between two registers, you should add this target hook to express the relative cost.

If you do not add this target hook, GCC uses a default cost of 4 plus the cost of copying via a secondary reload register, if one is needed. If your machine requires a secondary reload register to copy between memory and a register of *rclass* but the reload mechanism is more complex than copying via an intermediate, use this target hook to reflect the actual cost of the move.

GCC defines the function `memory_move_secondary_cost` if secondary reloads are needed. It computes the costs due to copying via a secondary register. If your machine copies from memory using a secondary register in the conventional way but the default base value of 4 is not correct for your machine, use this target hook to add some other value to the result of that function. The arguments to that function are the same as to this target hook.

`BRANCH_COST` (*speed_p*, *predictable_p*) [Macro]

A C expression for the cost of a branch instruction. A value of 1 is the default; other values are interpreted relative to that. Parameter *speed_p* is true when the branch in question should be optimized for speed. When it is false, `BRANCH_COST` should return a value optimal for code size rather than performance. *predictable_p* is true for well-predicted branches. On many architectures the `BRANCH_COST` can be reduced then.

Here are additional macros which do not specify precise relative costs, but only that certain actions are more expensive than GCC would ordinarily expect.

`SLOW_BYTE_ACCESS` [Macro]

Define this macro as a C expression which is nonzero if accessing less than a word of memory (i.e. a `char` or a `short`) is no faster than accessing a word of memory, i.e., if such access require more than one instruction or if there is no difference in cost between byte and (aligned) word loads.

When this macro is not defined, the compiler will access a field by finding the smallest containing object; when it is defined, a fullword load will be used if alignment permits. Unless bytes accesses are faster than word accesses, using word accesses is preferable since it may eliminate subsequent memory access if subsequent accesses occur to other fields in the same word of the structure, but to different bytes.

`SLOW_UNALIGNED_ACCESS` (*mode*, *alignment*) [Macro]

Define this macro to be the value 1 if memory accesses described by the *mode* and *alignment* parameters have a cost many times greater than aligned accesses, for example if they are emulated in a trap handler.

When this macro is nonzero, the compiler will act as if `STRICT_ALIGNMENT` were nonzero when generating code for block moves. This can cause significantly more instructions to be produced. Therefore, do not set this macro nonzero if unaligned accesses only add a cycle or two to the time for a memory access.

If the value of this macro is always zero, it need not be defined. If this macro is defined, it should produce a nonzero value when `STRICT_ALIGNMENT` is nonzero.

`MOVE_RATIO` (*speed*) [Macro]

The threshold of number of scalar memory-to-memory move insns, *below* which a sequence of insns should be generated instead of a string move insn or a library call. Increasing the value will always make code faster, but eventually incurs high cost in increased code size.

Note that on machines where the corresponding move insn is a `define_expand` that emits a sequence of insns, this macro counts the number of such sequences.

The parameter *speed* is true if the code is currently being optimized for speed rather than size.

If you don't define this, a reasonable default is used.

`MOVE_BY_PIECES_P` (*size*, *alignment*) [Macro]

A C expression used to determine whether `move_by_pieces` will be used to copy a chunk of memory, or whether some other block move mechanism will be used. Defaults to 1 if `move_by_pieces_ninsns` returns less than `MOVE_RATIO`.

`MOVE_MAX_PIECES` [Macro]

A C expression used by `move_by_pieces` to determine the largest unit a load or store used to copy memory is. Defaults to `MOVE_MAX`.

`CLEAR_RATIO (speed)` [Macro]

The threshold of number of scalar move insns, *below* which a sequence of insns should be generated to clear memory instead of a string clear insn or a library call. Increasing the value will always make code faster, but eventually incurs high cost in increased code size.

The parameter *speed* is true if the code is currently being optimized for speed rather than size.

If you don't define this, a reasonable default is used.

`CLEAR_BY_PIECES_P (size, alignment)` [Macro]

A C expression used to determine whether `clear_by_pieces` will be used to clear a chunk of memory, or whether some other block clear mechanism will be used. Defaults to 1 if `move_by_pieces_ninsns` returns less than `CLEAR_RATIO`.

`SET_RATIO (speed)` [Macro]

The threshold of number of scalar move insns, *below* which a sequence of insns should be generated to set memory to a constant value, instead of a block set insn or a library call. Increasing the value will always make code faster, but eventually incurs high cost in increased code size.

The parameter *speed* is true if the code is currently being optimized for speed rather than size.

If you don't define this, it defaults to the value of `MOVE_RATIO`.

`SET_BY_PIECES_P (size, alignment)` [Macro]

A C expression used to determine whether `store_by_pieces` will be used to set a chunk of memory to a constant value, or whether some other mechanism will be used. Used by `__builtin_memset` when storing values other than constant zero. Defaults to 1 if `move_by_pieces_ninsns` returns less than `SET_RATIO`.

`STORE_BY_PIECES_P (size, alignment)` [Macro]

A C expression used to determine whether `store_by_pieces` will be used to set a chunk of memory to a constant string value, or whether some other mechanism will be used. Used by `__builtin_strcpy` when called with a constant source string. Defaults to 1 if `move_by_pieces_ninsns` returns less than `MOVE_RATIO`.

`USE_LOAD_POST_INCREMENT (mode)` [Macro]

A C expression used to determine whether a load postincrement is a good thing to use for a given mode. Defaults to the value of `HAVE_POST_INCREMENT`.

`USE_LOAD_POST_DECREMENT (mode)` [Macro]

A C expression used to determine whether a load postdecrement is a good thing to use for a given mode. Defaults to the value of `HAVE_POST_DECREMENT`.

`USE_LOAD_PRE_INCREMENT (mode)` [Macro]

A C expression used to determine whether a load preincrement is a good thing to use for a given mode. Defaults to the value of `HAVE_PRE_INCREMENT`.

`USE_LOAD_PRE_DECREMENT (mode)` [Macro]

A C expression used to determine whether a load predecrement is a good thing to use for a given mode. Defaults to the value of `HAVE_PRE_DECREMENT`.

`USE_STORE_POST_INCREMENT (mode)` [Macro]

A C expression used to determine whether a store postincrement is a good thing to use for a given mode. Defaults to the value of `HAVE_POST_INCREMENT`.

`USE_STORE_POST_DECREMENT (mode)` [Macro]

A C expression used to determine whether a store postdecrement is a good thing to use for a given mode. Defaults to the value of `HAVE_POST_DECREMENT`.

`USE_STORE_PRE_INCREMENT (mode)` [Macro]

This macro is used to determine whether a store preincrement is a good thing to use for a given mode. Defaults to the value of `HAVE_PRE_INCREMENT`.

`USE_STORE_PRE_DECREMENT (mode)` [Macro]

This macro is used to determine whether a store predecrement is a good thing to use for a given mode. Defaults to the value of `HAVE_PRE_DECREMENT`.

`NO_FUNCTION_CSE` [Macro]

Define this macro if it is as good or better to call a constant function address than to call an address kept in a register.

`LOGICAL_OP_NON_SHORT_CIRCUIT` [Macro]

Define this macro if a non-short-circuit operation produced by '`fold_range_test ()`' is optimal. This macro defaults to true if `BRANCH_COST` is greater than or equal to the value 2.

`bool TARGET_RTX_COSTS (rtx x, int code, int outer_code, int opno, int *total, bool speed)` [Target Hook]

This target hook describes the relative costs of RTL expressions.

The cost may depend on the precise form of the expression, which is available for examination in *x*, and the fact that *x* appears as operand *opno* of an expression with rtx code *outer_code*. That is, the hook can assume that there is some rtx *y* such that '`GET_CODE (y) == outer_code`' and such that either (a) '`XEXP (y, opno) == x`' or (b) '`XVEC (y, opno)`' contains *x*.

code is *x*'s expression code—redundant, since it can be obtained with `GET_CODE (x)`.

In implementing this hook, you can use the construct `COSTS_N_INSNS (n)` to specify a cost equal to *n* fast instructions.

On entry to the hook, `*total` contains a default estimate for the cost of the expression. The hook should modify this value as necessary. Traditionally, the default costs are `COSTS_N_INSNS (5)` for multiplications, `COSTS_N_INSNS (7)` for division and modulus operations, and `COSTS_N_INSNS (1)` for all other operations.

When optimizing for code size, i.e. when `speed` is false, this target hook should be used to estimate the relative size cost of an expression, again relative to `COSTS_N_INSNS`.

The hook returns true when all subexpressions of *x* have been processed, and false when `rtx_cost` should recurse.

`int TARGET_ADDRESS_COST` (*rtx* `address`, *enum machine_mode* `mode`, *addr_space_t* `as`, *bool* `speed`) [Target Hook]

This hook computes the cost of an addressing mode that contains *address*. If not defined, the cost is computed from the *address* expression and the `TARGET_RTX_COST` hook.

For most CISC machines, the default cost is a good approximation of the true cost of the addressing mode. However, on RISC machines, all instructions normally have the same length and execution time. Hence all addresses will have equal costs.

In cases where more than one form of an address is known, the form with the lowest cost will be used. If multiple forms have the same, lowest, cost, the one that is the most complex will be used.

For example, suppose an address that is equal to the sum of a register and a constant is used twice in the same basic block. When this macro is not defined, the address will be computed in a register and memory references will be indirect through that register. On machines where the cost of the addressing mode containing the sum is no higher than that of a simple indirect reference, this will produce an additional instruction and possibly require an additional register. Proper specification of this macro eliminates this overhead for such machines.

This hook is never called with an invalid address.

On machines where an address involving more than one register is as cheap as an address computation involving only one register, defining `TARGET_ADDRESS_COST` to reflect this can cause two registers to be live over a region of code where only one would have been if `TARGET_ADDRESS_COST` were not defined in that manner. This effect should be considered in the definition of this macro. Equivalent costs should probably only be given to addresses with different numbers of registers on machines with lots of registers.

17.18 Adjusting the Instruction Scheduler

The instruction scheduler may need a fair amount of machine-specific adjustment in order to produce good code. GCC provides several target hooks for this purpose. It is usually enough to define just a few of them: try the first ones in this list first.

`int TARGET_SCHED_ISSUE_RATE` (*void*) [Target Hook]

This hook returns the maximum number of instructions that can ever issue at the same time on the target machine. The default is one. Although the insn scheduler can define itself the possibility of issue an insn on the same cycle, the value can serve as an additional constraint to issue insns on the same simulated processor cycle (see hooks '`TARGET_SCHED_REORDER`' and '`TARGET_SCHED_REORDER2`'). This value must be constant over the entire compilation. If you need it to vary depending on what the instructions are, you must use '`TARGET_SCHED_VARIABLE_ISSUE`'.

`int TARGET_SCHED_VARIABLE_ISSUE` (*FILE* `*file`, *int* `verbose`, *rtx* `insn`, *int* `more`) [Target Hook]

This hook is executed by the scheduler after it has scheduled an insn from the ready list. It should return the number of insns which can still be issued in the current cycle. The default is '`more - 1`' for insns other than `CLOBBER` and `USE`, which normally are

not counted against the issue rate. You should define this hook if some insns take more machine resources than others, so that fewer insns can follow them in the same cycle. *file* is either a null pointer, or a stdio stream to write any debug output to. *verbose* is the verbose level provided by '`-fsched-verbose-n`'. *insn* is the instruction that was scheduled.

`int TARGET_SCHED_ADJUST_COST (rtx insn, rtx link, rtx dep_insn, int cost)` [Target Hook]

This function corrects the value of *cost* based on the relationship between *insn* and *dep_insn* through the dependence *link*. It should return the new value. The default is to make no adjustment to *cost*. This can be used for example to specify to the scheduler using the traditional pipeline description that an output- or anti-dependence does not incur the same cost as a data-dependence. If the scheduler using the automaton based pipeline description, the cost of anti-dependence is zero and the cost of output-dependence is maximum of one and the difference of latency times of the first and the second insns. If these values are not acceptable, you could use the hook to modify them too. See also see Section 16.19.9 [Processor pipeline description], page 404.

`int TARGET_SCHED_ADJUST_PRIORITY (rtx insn, int priority)` [Target Hook]

This hook adjusts the integer scheduling priority *priority* of *insn*. It should return the new priority. Increase the priority to execute *insn* earlier, reduce the priority to execute *insn* later. Do not define this hook if you do not need to adjust the scheduling priorities of insns.

`int TARGET_SCHED_REORDER (FILE *file, int verbose, rtx *ready, int *n_readyp, int clock)` [Target Hook]

This hook is executed by the scheduler after it has scheduled the ready list, to allow the machine description to reorder it (for example to combine two small instructions together on '`VLIW`' machines). *file* is either a null pointer, or a stdio stream to write any debug output to. *verbose* is the verbose level provided by '`-fsched-verbose-n`'. *ready* is a pointer to the ready list of instructions that are ready to be scheduled. *n_readyp* is a pointer to the number of elements in the ready list. The scheduler reads the ready list in reverse order, starting with *ready*[**n_readyp* − 1] and going to *ready*[0]. *clock* is the timer tick of the scheduler. You may modify the ready list and the number of ready insns. The return value is the number of insns that can issue this cycle; normally this is just `issue_rate`. See also '`TARGET_SCHED_REORDER2`'.

`int TARGET_SCHED_REORDER2 (FILE *file, int verbose, rtx *ready, int *n_readyp, int clock)` [Target Hook]

Like '`TARGET_SCHED_REORDER`', but called at a different time. That function is called whenever the scheduler starts a new cycle. This one is called once per iteration over a cycle, immediately after '`TARGET_SCHED_VARIABLE_ISSUE`'; it can reorder the ready list and return the number of insns to be scheduled in the same cycle. Defining this hook can be useful if there are frequent situations where scheduling one insn causes other insns to become ready in the same cycle. These other insns can then be taken into account properly.

`bool TARGET_SCHED_MACRO_FUSION_P (void)` [Target Hook]

This hook is used to check whether target platform supports macro fusion.

`bool TARGET_SCHED_MACRO_FUSION_PAIR_P (rtx condgen, rtx condjmp)` [Target Hook]

This hook is used to check whether two insns could be macro fused for target microarchitecture. If this hook returns true for the given insn pair (*condgen* and *condjmp*), scheduler will put them into a sched group, and they will not be scheduled apart.

`void TARGET_SCHED_DEPENDENCIES_EVALUATION_HOOK (rtx head, rtx tail)` [Target Hook]

This hook is called after evaluation forward dependencies of insns in chain given by two parameter values (*head* and *tail* correspondingly) but before insns scheduling of the insn chain. For example, it can be used for better insn classification if it requires analysis of dependencies. This hook can use backward and forward dependencies of the insn scheduler because they are already calculated.

`void TARGET_SCHED_INIT (FILE *file, int verbose, int max_ready)` [Target Hook]

This hook is executed by the scheduler at the beginning of each block of instructions that are to be scheduled. *file* is either a null pointer, or a stdio stream to write any debug output to. *verbose* is the verbose level provided by '`-fsched-verbose-n`'. *max_ready* is the maximum number of insns in the current scheduling region that can be live at the same time. This can be used to allocate scratch space if it is needed, e.g. by '`TARGET_SCHED_REORDER`'.

`void TARGET_SCHED_FINISH (FILE *file, int verbose)` [Target Hook]

This hook is executed by the scheduler at the end of each block of instructions that are to be scheduled. It can be used to perform cleanup of any actions done by the other scheduling hooks. *file* is either a null pointer, or a stdio stream to write any debug output to. *verbose* is the verbose level provided by '`-fsched-verbose-n`'.

`void TARGET_SCHED_INIT_GLOBAL (FILE *file, int verbose, int old_max_uid)` [Target Hook]

This hook is executed by the scheduler after function level initializations. *file* is either a null pointer, or a stdio stream to write any debug output to. *verbose* is the verbose level provided by '`-fsched-verbose-n`'. *old_max_uid* is the maximum insn uid when scheduling begins.

`void TARGET_SCHED_FINISH_GLOBAL (FILE *file, int verbose)` [Target Hook]

This is the cleanup hook corresponding to `TARGET_SCHED_INIT_GLOBAL`. *file* is either a null pointer, or a stdio stream to write any debug output to. *verbose* is the verbose level provided by '`-fsched-verbose-n`'.

`rtx TARGET_SCHED_DFA_PRE_CYCLE_INSN (void)` [Target Hook]

The hook returns an RTL insn. The automaton state used in the pipeline hazard recognizer is changed as if the insn were scheduled when the new simulated processor cycle starts. Usage of the hook may simplify the automaton pipeline description for some VLIW processors. If the hook is defined, it is used only for the automaton based pipeline description. The default is not to change the state when the new simulated processor cycle starts.

`void TARGET_SCHED_INIT_DFA_PRE_CYCLE_INSN (void)` [Target Hook]

The hook can be used to initialize data used by the previous hook.

`rtx TARGET_SCHED_DFA_POST_CYCLE_INSN (void)` [Target Hook]

The hook is analogous to '`TARGET_SCHED_DFA_PRE_CYCLE_INSN`' but used to changed the state as if the insn were scheduled when the new simulated processor cycle finishes.

`void TARGET_SCHED_INIT_DFA_POST_CYCLE_INSN (void)` [Target Hook]

The hook is analogous to '`TARGET_SCHED_INIT_DFA_PRE_CYCLE_INSN`' but used to initialize data used by the previous hook.

`void TARGET_SCHED_DFA_PRE_ADVANCE_CYCLE (void)` [Target Hook]

The hook to notify target that the current simulated cycle is about to finish. The hook is analogous to '`TARGET_SCHED_DFA_PRE_CYCLE_INSN`' but used to change the state in more complicated situations - e.g., when advancing state on a single insn is not enough.

`void TARGET_SCHED_DFA_POST_ADVANCE_CYCLE (void)` [Target Hook]

The hook to notify target that new simulated cycle has just started. The hook is analogous to '`TARGET_SCHED_DFA_POST_CYCLE_INSN`' but used to change the state in more complicated situations - e.g., when advancing state on a single insn is not enough.

`int TARGET_SCHED_FIRST_CYCLE_MULTIPASS_DFA_LOOKAHEAD (void)` [Target Hook]

This hook controls better choosing an insn from the ready insn queue for the DFA-based insn scheduler. Usually the scheduler chooses the first insn from the queue. If the hook returns a positive value, an additional scheduler code tries all permutations of '`TARGET_SCHED_FIRST_CYCLE_MULTIPASS_DFA_LOOKAHEAD ()`' subsequent ready insns to choose an insn whose issue will result in maximal number of issued insns on the same cycle. For the VLIW processor, the code could actually solve the problem of packing simple insns into the VLIW insn. Of course, if the rules of VLIW packing are described in the automaton.

This code also could be used for superscalar RISC processors. Let us consider a superscalar RISC processor with 3 pipelines. Some insns can be executed in pipelines *A* or *B*, some insns can be executed only in pipelines *B* or *C*, and one insn can be executed in pipeline *B*. The processor may issue the 1st insn into *A* and the 2nd one into *B*. In this case, the 3rd insn will wait for freeing *B* until the next cycle. If the scheduler issues the 3rd insn the first, the processor could issue all 3 insns per cycle.

Actually this code demonstrates advantages of the automaton based pipeline hazard recognizer. We try quickly and easy many insn schedules to choose the best one.

The default is no multipass scheduling.

`int TARGET_SCHED_FIRST_CYCLE_MULTIPASS_DFA_LOOKAHEAD_GUARD (rtx insn)` [Target Hook]

This hook controls what insns from the ready insn queue will be considered for the multipass insn scheduling. If the hook returns zero for *insn*, the insn will be not chosen to be issued.

The default is that any ready insns can be chosen to be issued.

`void TARGET_SCHED_FIRST_CYCLE_MULTIPASS_BEGIN` (*void* *`data`, *char* *`ready_try`, *int* `n_ready`, *bool* `first_cycle_insn_p`) [Target Hook]

This hook prepares the target backend for a new round of multipass scheduling.

`void TARGET_SCHED_FIRST_CYCLE_MULTIPASS_ISSUE` (*void* *`data`, *char* *`ready_try`, *int* `n_ready`, *rtx* `insn`, *const void* *`prev_data`) [Target Hook]

This hook is called when multipass scheduling evaluates instruction INSN.

`void TARGET_SCHED_FIRST_CYCLE_MULTIPASS_BACKTRACK` (*const void* *`data`, *char* *`ready_try`, *int* `n_ready`) [Target Hook]

This is called when multipass scheduling backtracks from evaluation of an instruction.

`void TARGET_SCHED_FIRST_CYCLE_MULTIPASS_END` (*const void* *`data`) [Target Hook]

This hook notifies the target about the result of the concluded current round of multipass scheduling.

`void TARGET_SCHED_FIRST_CYCLE_MULTIPASS_INIT` (*void* *`data`) [Target Hook]

This hook initializes target-specific data used in multipass scheduling.

`void TARGET_SCHED_FIRST_CYCLE_MULTIPASS_FINI` (*void* *`data`) [Target Hook]

This hook finalizes target-specific data used in multipass scheduling.

`int TARGET_SCHED_DFA_NEW_CYCLE` (*FILE* *`dump`, *int* `verbose`, *rtx* `insn`, *int* `last_clock`, *int* `clock`, *int* *`sort_p`) [Target Hook]

This hook is called by the insn scheduler before issuing *insn* on cycle *clock*. If the hook returns nonzero, *insn* is not issued on this processor cycle. Instead, the processor cycle is advanced. If **sort_p* is zero, the insn ready queue is not sorted on the new cycle start as usually. *dump* and *verbose* specify the file and verbosity level to use for debugging output. *last_clock* and *clock* are, respectively, the processor cycle on which the previous insn has been issued, and the current processor cycle.

`bool TARGET_SCHED_IS_COSTLY_DEPENDENCE` (*struct _dep* *`_dep`, *int* `cost`, *int* `distance`) [Target Hook]

This hook is used to define which dependences are considered costly by the target, so costly that it is not advisable to schedule the insns that are involved in the dependence too close to one another. The parameters to this hook are as follows: The first parameter *_dep* is the dependence being evaluated. The second parameter *cost* is the cost of the dependence as estimated by the scheduler, and the third parameter *distance* is the distance in cycles between the two insns. The hook returns `true` if considering the distance between the two insns the dependence between them is considered costly by the target, and `false` otherwise.

Defining this hook can be useful in multiple-issue out-of-order machines, where (a) it's practically hopeless to predict the actual data/resource delays, however: (b) there's a better chance to predict the actual grouping that will be formed, and (c) correctly emulating the grouping can be very important. In such targets one may want to allow issuing dependent insns closer to one another—i.e., closer than the dependence distance; however, not in cases of "costly dependences", which this hooks allows to define.

`void TARGET_SCHED_H_I_D_EXTENDED (void)` [Target Hook]

This hook is called by the insn scheduler after emitting a new instruction to the instruction stream. The hook notifies a target backend to extend its per instruction data structures.

`void * TARGET_SCHED_ALLOC_SCHED_CONTEXT (void)` [Target Hook]

Return a pointer to a store large enough to hold target scheduling context.

`void TARGET_SCHED_INIT_SCHED_CONTEXT (void *tc, bool clean_p)` [Target Hook]

Initialize store pointed to by *tc* to hold target scheduling context. It *clean_p* is true then initialize *tc* as if scheduler is at the beginning of the block. Otherwise, copy the current context into *tc*.

`void TARGET_SCHED_SET_SCHED_CONTEXT (void *tc)` [Target Hook]

Copy target scheduling context pointed to by *tc* to the current context.

`void TARGET_SCHED_CLEAR_SCHED_CONTEXT (void *tc)` [Target Hook]

Deallocate internal data in target scheduling context pointed to by *tc*.

`void TARGET_SCHED_FREE_SCHED_CONTEXT (void *tc)` [Target Hook]

Deallocate a store for target scheduling context pointed to by *tc*.

`int TARGET_SCHED_SPECULATE_INSN (rtx insn, unsigned int dep_status, rtx *new_pat)` [Target Hook]

This hook is called by the insn scheduler when *insn* has only speculative dependencies and therefore can be scheduled speculatively. The hook is used to check if the pattern of *insn* has a speculative version and, in case of successful check, to generate that speculative pattern. The hook should return 1, if the instruction has a speculative form, or -1, if it doesn't. *request* describes the type of requested speculation. If the return value equals 1 then *new_pat* is assigned the generated speculative pattern.

`bool TARGET_SCHED_NEEDS_BLOCK_P (unsigned int dep_status)` [Target Hook]

This hook is called by the insn scheduler during generation of recovery code for *insn*. It should return `true`, if the corresponding check instruction should branch to recovery code, or `false` otherwise.

`rtx TARGET_SCHED_GEN_SPEC_CHECK (rtx insn, rtx label, unsigned int ds)` [Target Hook]

This hook is called by the insn scheduler to generate a pattern for recovery check instruction. If *mutate_p* is zero, then *insn* is a speculative instruction for which the check should be generated. *label* is either a label of a basic block, where recovery code should be emitted, or a null pointer, when requested check doesn't branch to recovery code (a simple check). If *mutate_p* is nonzero, then a pattern for a branchy check corresponding to a simple check denoted by *insn* should be generated. In this case *label* can't be null.

bool TARGET_SCHED_FIRST_CYCLE_MULTIPASS_DFA_LOOKAHEAD_GUARD_SPEC (*const_rtx* insn) [Target Hook]

This hook is used as a workaround for 'TARGET_SCHED_FIRST_CYCLE_MULTIPASS_DFA_LOOKAHEAD_GUARD' not being called on the first instruction of the ready list. The hook is used to discard speculative instructions that stand first in the ready list from being scheduled on the current cycle. If the hook returns false, *insn* will not be chosen to be issued. For non-speculative instructions, the hook should always return true. For example, in the ia64 backend the hook is used to cancel data speculative insns when the ALAT table is nearly full.

void TARGET_SCHED_SET_SCHED_FLAGS (*struct spec_info_def* *spec_info) [Target Hook]

This hook is used by the insn scheduler to find out what features should be enabled/used. The structure **spec_info* should be filled in by the target. The structure describes speculation types that can be used in the scheduler.

int TARGET_SCHED_SMS_RES_MII (*struct ddg* *g) [Target Hook]

This hook is called by the swing modulo scheduler to calculate a resource-based lower bound which is based on the resources available in the machine and the resources required by each instruction. The target backend can use *g* to calculate such bound. A very simple lower bound will be used in case this hook is not implemented: the total number of instructions divided by the issue rate.

bool TARGET_SCHED_DISPATCH (*rtx* insn, *int* x) [Target Hook]

This hook is called by Haifa Scheduler. It returns true if dispatch scheduling is supported in hardware and the condition specified in the parameter is true.

void TARGET_SCHED_DISPATCH_DO (*rtx* insn, *int* x) [Target Hook]

This hook is called by Haifa Scheduler. It performs the operation specified in its second parameter.

bool TARGET_SCHED_EXPOSED_PIPELINE [Target Hook]

True if the processor has an exposed pipeline, which means that not just the order of instructions is important for correctness when scheduling, but also the latencies of operations.

int TARGET_SCHED_REASSOCIATION_WIDTH (*unsigned int* opc, *enum machine_mode* mode) [Target Hook]

This hook is called by tree reassociator to determine a level of parallelism required in output calculations chain.

17.19 Dividing the Output into Sections (Texts, Data, . . .)

An object file is divided into sections containing different types of data. In the most common case, there are three sections: the *text section*, which holds instructions and read-only data; the *data section*, which holds initialized writable data; and the *bss section*, which holds uninitialized data. Some systems have other kinds of sections.

'varasm.c' provides several well-known sections, such as text_section, data_section and bss_section. The normal way of controlling a *foo*_section variable is to define the

associated *FOO*_SECTION_ASM_OP macro, as described below. The macros are only read once, when 'varasm.c' initializes itself, so their values must be run-time constants. They may however depend on command-line flags.

Note: Some run-time files, such 'crtstuff.c', also make use of the *FOO*_SECTION_ASM_OP macros, and expect them to be string literals.

Some assemblers require a different string to be written every time a section is selected. If your assembler falls into this category, you should define the TARGET_ASM_INIT_SECTIONS hook and use get_unnamed_section to set up the sections.

You must always create a text_section, either by defining TEXT_SECTION_ASM_OP or by initializing text_section in TARGET_ASM_INIT_SECTIONS. The same is true of data_section and DATA_SECTION_ASM_OP. If you do not create a distinct readonly_data_section, the default is to reuse text_section.

All the other 'varasm.c' sections are optional, and are null if the target does not provide them.

TEXT_SECTION_ASM_OP [Macro]

A C expression whose value is a string, including spacing, containing the assembler operation that should precede instructions and read-only data. Normally "\t.text" is right.

HOT_TEXT_SECTION_NAME [Macro]

If defined, a C string constant for the name of the section containing most frequently executed functions of the program. If not defined, GCC will provide a default definition if the target supports named sections.

UNLIKELY_EXECUTED_TEXT_SECTION_NAME [Macro]

If defined, a C string constant for the name of the section containing unlikely executed functions in the program.

DATA_SECTION_ASM_OP [Macro]

A C expression whose value is a string, including spacing, containing the assembler operation to identify the following data as writable initialized data. Normally "\t.data" is right.

SDATA_SECTION_ASM_OP [Macro]

If defined, a C expression whose value is a string, including spacing, containing the assembler operation to identify the following data as initialized, writable small data.

READONLY_DATA_SECTION_ASM_OP [Macro]

A C expression whose value is a string, including spacing, containing the assembler operation to identify the following data as read-only initialized data.

BSS_SECTION_ASM_OP [Macro]

If defined, a C expression whose value is a string, including spacing, containing the assembler operation to identify the following data as uninitialized global data. If not defined, and ASM_OUTPUT_ALIGNED_BSS not defined, uninitialized global data will be output in the data section if '-fno-common' is passed, otherwise ASM_OUTPUT_COMMON will be used.

`SBSS_SECTION_ASM_OP` [Macro]

If defined, a C expression whose value is a string, including spacing, containing the assembler operation to identify the following data as uninitialized, writable small data.

`TLS_COMMON_ASM_OP` [Macro]

If defined, a C expression whose value is a string containing the assembler operation to identify the following data as thread-local common data. The default is `".tls_common"`.

`TLS_SECTION_ASM_FLAG` [Macro]

If defined, a C expression whose value is a character constant containing the flag used to mark a section as a TLS section. The default is `'T'`.

`INIT_SECTION_ASM_OP` [Macro]

If defined, a C expression whose value is a string, including spacing, containing the assembler operation to identify the following data as initialization code. If not defined, GCC will assume such a section does not exist. This section has no corresponding `init_section` variable; it is used entirely in runtime code.

`FINI_SECTION_ASM_OP` [Macro]

If defined, a C expression whose value is a string, including spacing, containing the assembler operation to identify the following data as finalization code. If not defined, GCC will assume such a section does not exist. This section has no corresponding `fini_section` variable; it is used entirely in runtime code.

`INIT_ARRAY_SECTION_ASM_OP` [Macro]

If defined, a C expression whose value is a string, including spacing, containing the assembler operation to identify the following data as part of the `.init_array` (or equivalent) section. If not defined, GCC will assume such a section does not exist. Do not define both this macro and `INIT_SECTION_ASM_OP`.

`FINI_ARRAY_SECTION_ASM_OP` [Macro]

If defined, a C expression whose value is a string, including spacing, containing the assembler operation to identify the following data as part of the `.fini_array` (or equivalent) section. If not defined, GCC will assume such a section does not exist. Do not define both this macro and `FINI_SECTION_ASM_OP`.

`CRT_CALL_STATIC_FUNCTION` (*section_op*, *function*) [Macro]

If defined, an ASM statement that switches to a different section via *section_op*, calls *function*, and switches back to the text section. This is used in '`crtstuff.c`' if `INIT_SECTION_ASM_OP` or `FINI_SECTION_ASM_OP` to calls to initialization and finalization functions from the init and fini sections. By default, this macro uses a simple function call. Some ports need hand-crafted assembly code to avoid dependencies on registers initialized in the function prologue or to ensure that constant pools don't end up too far way in the text section.

`TARGET_LIBGCC_SDATA_SECTION` [Macro]

If defined, a string which names the section into which small variables defined in crtstuff and libgcc should go. This is useful when the target has options for optimizing

access to small data, and you want the crtstuff and libgcc routines to be conservative in what they expect of your application yet liberal in what your application expects. For example, for targets with a `.sdata` section (like MIPS), you could compile crtstuff with `-G 0` so that it doesn't require small data support from your application, but use this macro to put small data into `.sdata` so that your application can access these variables whether it uses small data or not.

`FORCE_CODE_SECTION_ALIGN` [Macro]

If defined, an ASM statement that aligns a code section to some arbitrary boundary. This is used to force all fragments of the `.init` and `.fini` sections to have to same alignment and thus prevent the linker from having to add any padding.

`JUMP_TABLES_IN_TEXT_SECTION` [Macro]

Define this macro to be an expression with a nonzero value if jump tables (for `tablejump` insns) should be output in the text section, along with the assembler instructions. Otherwise, the readonly data section is used.

This macro is irrelevant if there is no separate readonly data section.

`void TARGET_ASM_INIT_SECTIONS` (*void*) [Target Hook]

Define this hook if you need to do something special to set up the '`varasm.c`' sections, or if your target has some special sections of its own that you need to create.

GCC calls this hook after processing the command line, but before writing any assembly code, and before calling any of the section-returning hooks described below.

`int TARGET_ASM_RELOC_RW_MASK` (*void*) [Target Hook]

Return a mask describing how relocations should be treated when selecting sections. Bit 1 should be set if global relocations should be placed in a read-write section; bit 0 should be set if local relocations should be placed in a read-write section.

The default version of this function returns 3 when '`-fpic`' is in effect, and 0 otherwise. The hook is typically redefined when the target cannot support (some kinds of) dynamic relocations in read-only sections even in executables.

`section * TARGET_ASM_SELECT_SECTION` (*tree* `exp`, *int* `reloc`, *unsigned HOST_WIDE_INT* `align`) [Target Hook]

Return the section into which *exp* should be placed. You can assume that *exp* is either a `VAR_DECL` node or a constant of some sort. *reloc* indicates whether the initial value of *exp* requires link-time relocations. Bit 0 is set when variable contains local relocations only, while bit 1 is set for global relocations. *align* is the constant alignment in bits.

The default version of this function takes care of putting read-only variables in `readonly_data_section`.

See also *USE_SELECT_SECTION_FOR_FUNCTIONS*.

`USE_SELECT_SECTION_FOR_FUNCTIONS` [Macro]

Define this macro if you wish TARGET_ASM_SELECT_SECTION to be called for `FUNCTION_DECL`s as well as for variables and constants.

In the case of a `FUNCTION_DECL`, *reloc* will be zero if the function has been determined to be likely to be called, and nonzero if it is unlikely to be called.

void TARGET_ASM_UNIQUE_SECTION (*tree* *decl*, *int* *reloc*) [Target Hook]

Build up a unique section name, expressed as a STRING_CST node, and assign it to 'DECL_SECTION_NAME (*decl*)'. As with TARGET_ASM_SELECT_SECTION, *reloc* indicates whether the initial value of *exp* requires link-time relocations.

The default version of this function appends the symbol name to the ELF section name that would normally be used for the symbol. For example, the function foo would be placed in .text.foo. Whatever the actual target object format, this is often good enough.

section * TARGET_ASM_FUNCTION_RODATA_SECTION (*tree* *decl*) [Target Hook]

Return the readonly data section associated with 'DECL_SECTION_NAME (*decl*)'. The default version of this function selects .gnu.linkonce.r.name if the function's section is .gnu.linkonce.t.name, .rodata.name if function is in .text.name, and the normal readonly-data section otherwise.

const char * TARGET_ASM_MERGEABLE_RODATA_PREFIX [Target Hook]

Usually, the compiler uses the prefix ".rodata" to construct section names for mergeable constant data. Define this macro to override the string if a different section name should be used.

section * TARGET_ASM_TM_CLONE_TABLE_SECTION (*void*) [Target Hook]

Return the section that should be used for transactional memory clone tables.

section * TARGET_ASM_SELECT_RTX_SECTION (*enum machine_mode* *mode*, *rtx* *x*, *unsigned HOST_WIDE_INT* *align*) [Target Hook]

Return the section into which a constant *x*, of mode *mode*, should be placed. You can assume that *x* is some kind of constant in RTL. The argument *mode* is redundant except in the case of a const_int rtx. *align* is the constant alignment in bits.

The default version of this function takes care of putting symbolic constants in flag_pic mode in data_section and everything else in readonly_data_section.

tree TARGET_MANGLE_DECL_ASSEMBLER_NAME (*tree* *decl*, *tree* *id*) [Target Hook]

Define this hook if you need to postprocess the assembler name generated by target-independent code. The *id* provided to this hook will be the computed name (e.g., the macro DECL_NAME of the *decl* in C, or the mangled name of the *decl* in C++). The return value of the hook is an IDENTIFIER_NODE for the appropriate mangled name on your target system. The default implementation of this hook just returns the *id* provided.

void TARGET_ENCODE_SECTION_INFO (*tree* *decl*, *rtx* *rtl*, *int* *new_decl_p*) [Target Hook]

Define this hook if references to a symbol or a constant must be treated differently depending on something about the variable or function named by the symbol (such as what section it is in).

The hook is executed immediately after rtl has been created for *decl*, which may be a variable or function declaration or an entry in the constant pool. In either case, *rtl* is the rtl in question. Do *not* use DECL_RTL (*decl*) in this hook; that field may not have been initialized yet.

In the case of a constant, it is safe to assume that the rtl is a `mem` whose address is a `symbol_ref`. Most decls will also have this form, but that is not guaranteed. Global register variables, for instance, will have a `reg` for their rtl. (Normally the right thing to do with such unusual rtl is leave it alone.)

The *new_decl_p* argument will be true if this is the first time that `TARGET_ENCODE_SECTION_INFO` has been invoked on this decl. It will be false for subsequent invocations, which will happen for duplicate declarations. Whether or not anything must be done for the duplicate declaration depends on whether the hook examines `DECL_ATTRIBUTES`. *new_decl_p* is always true when the hook is called for a constant.

The usual thing for this hook to do is to record flags in the `symbol_ref`, using `SYMBOL_REF_FLAG` or `SYMBOL_REF_FLAGS`. Historically, the name string was modified if it was necessary to encode more than one bit of information, but this practice is now discouraged; use `SYMBOL_REF_FLAGS`.

The default definition of this hook, `default_encode_section_info` in '`varasm.c`', sets a number of commonly-useful bits in `SYMBOL_REF_FLAGS`. Check whether the default does what you need before overriding it.

`const char * TARGET_STRIP_NAME_ENCODING` (*const char *name*) [Target Hook]

Decode *name* and return the real name part, sans the characters that `TARGET_ENCODE_SECTION_INFO` may have added.

`bool TARGET_IN_SMALL_DATA_P` (*const_tree exp*) [Target Hook]

Returns true if *exp* should be placed into a "small data" section. The default version of this hook always returns false.

`bool TARGET_HAVE_SRODATA_SECTION` [Target Hook]

Contains the value true if the target places read-only "small data" into a separate section. The default value is false.

`bool TARGET_PROFILE_BEFORE_PROLOGUE` (*void*) [Target Hook]

It returns true if target wants profile code emitted before prologue.

The default version of this hook use the target macro `PROFILE_BEFORE_PROLOGUE`.

`bool TARGET_BINDS_LOCAL_P` (*const_tree exp*) [Target Hook]

Returns true if *exp* names an object for which name resolution rules must resolve to the current "module" (dynamic shared library or executable image).

The default version of this hook implements the name resolution rules for ELF, which has a looser model of global name binding than other currently supported object file formats.

`bool TARGET_HAVE_TLS` [Target Hook]

Contains the value true if the target supports thread-local storage. The default value is false.

17.20 Position Independent Code

This section describes macros that help implement generation of position independent code. Simply defining these macros is not enough to generate valid PIC; you must also add support to the hook `TARGET_LEGITIMATE_ADDRESS_P` and to the macro `PRINT_OPERAND_ADDRESS`, as well as `LEGITIMIZE_ADDRESS`. You must modify the definition of '`movsi`' to do something appropriate when the source operand contains a symbolic address. You may also need to alter the handling of switch statements so that they use relative addresses.

`PIC_OFFSET_TABLE_REGNUM` [Macro]

The register number of the register used to address a table of static data addresses in memory. In some cases this register is defined by a processor's "application binary interface" (ABI). When this macro is defined, RTL is generated for this register once, as with the stack pointer and frame pointer registers. If this macro is not defined, it is up to the machine-dependent files to allocate such a register (if necessary). Note that this register must be fixed when in use (e.g. when `flag_pic` is true).

`PIC_OFFSET_TABLE_REG_CALL_CLOBBERED` [Macro]

A C expression that is nonzero if the register defined by `PIC_OFFSET_TABLE_REGNUM` is clobbered by calls. If not defined, the default is zero. Do not define this macro if `PIC_OFFSET_TABLE_REGNUM` is not defined.

`LEGITIMATE_PIC_OPERAND_P (x)` [Macro]

A C expression that is nonzero if *x* is a legitimate immediate operand on the target machine when generating position independent code. You can assume that *x* satisfies `CONSTANT_P`, so you need not check this. You can also assume *flag_pic* is true, so you need not check it either. You need not define this macro if all constants (including `SYMBOL_REF`) can be immediate operands when generating position independent code.

17.21 Defining the Output Assembler Language

This section describes macros whose principal purpose is to describe how to write instructions in assembler language—rather than what the instructions do.

17.21.1 The Overall Framework of an Assembler File

This describes the overall framework of an assembly file.

`void TARGET_ASM_FILE_START (void)` [Target Hook]

Output to `asm_out_file` any text which the assembler expects to find at the beginning of a file. The default behavior is controlled by two flags, documented below. Unless your target's assembler is quite unusual, if you override the default, you should call `default_file_start` at some point in your target hook. This lets other target files rely on these variables.

`bool TARGET_ASM_FILE_START_APP_OFF` [Target Hook]

If this flag is true, the text of the macro `ASM_APP_OFF` will be printed as the very first line in the assembly file, unless '`-fverbose-asm`' is in effect. (If that macro has been defined to the empty string, this variable has no effect.) With the normal definition of `ASM_APP_OFF`, the effect is to notify the GNU assembler that it need not bother

stripping comments or extra whitespace from its input. This allows it to work a bit faster.

The default is false. You should not set it to true unless you have verified that your port does not generate any extra whitespace or comments that will cause GAS to issue errors in NO_APP mode.

`bool TARGET_ASM_FILE_START_FILE_DIRECTIVE` [Target Hook]

If this flag is true, `output_file_directive` will be called for the primary source file, immediately after printing `ASM_APP_OFF` (if that is enabled). Most ELF assemblers expect this to be done. The default is false.

`void TARGET_ASM_FILE_END (void)` [Target Hook]

Output to `asm_out_file` any text which the assembler expects to find at the end of a file. The default is to output nothing.

`void file_end_indicate_exec_stack ()` [Function]

Some systems use a common convention, the '`.note.GNU-stack`' special section, to indicate whether or not an object file relies on the stack being executable. If your system uses this convention, you should define `TARGET_ASM_FILE_END` to this function. If you need to do other things in that hook, have your hook function call this function.

`void TARGET_ASM_LTO_START (void)` [Target Hook]

Output to `asm_out_file` any text which the assembler expects to find at the start of an LTO section. The default is to output nothing.

`void TARGET_ASM_LTO_END (void)` [Target Hook]

Output to `asm_out_file` any text which the assembler expects to find at the end of an LTO section. The default is to output nothing.

`void TARGET_ASM_CODE_END (void)` [Target Hook]

Output to `asm_out_file` any text which is needed before emitting unwind info and debug info at the end of a file. Some targets emit here PIC setup thunks that cannot be emitted at the end of file, because they couldn't have unwind info then. The default is to output nothing.

`ASM_COMMENT_START` [Macro]

A C string constant describing how to begin a comment in the target assembler language. The compiler assumes that the comment will end at the end of the line.

`ASM_APP_ON` [Macro]

A C string constant for text to be output before each `asm` statement or group of consecutive ones. Normally this is `"#APP"`, which is a comment that has no effect on most assemblers but tells the GNU assembler that it must check the lines that follow for all valid assembler constructs.

`ASM_APP_OFF` [Macro]

A C string constant for text to be output after each `asm` statement or group of consecutive ones. Normally this is `"#NO_APP"`, which tells the GNU assembler to resume making the time-saving assumptions that are valid for ordinary compiler output.

`ASM_OUTPUT_SOURCE_FILENAME` (*stream*, *name*) [Macro]

A C statement to output COFF information or DWARF debugging information which indicates that filename *name* is the current source file to the stdio stream *stream*.

This macro need not be defined if the standard form of output for the file format in use is appropriate.

`void TARGET_ASM_OUTPUT_SOURCE_FILENAME` (*FILE *file*, *const char *name*) [Target Hook]

Output COFF information or DWARF debugging information which indicates that filename *name* is the current source file to the stdio stream *file*.

This target hook need not be defined if the standard form of output for the file format in use is appropriate.

`void TARGET_ASM_OUTPUT_IDENT` (*const char *name*) [Target Hook]

Output a string based on *name*, suitable for the '`#ident`' directive, or the equivalent directive or pragma in non-C-family languages. If this hook is not defined, nothing is output for the '`#ident`' directive.

`OUTPUT_QUOTED_STRING` (*stream*, *string*) [Macro]

A C statement to output the string *string* to the stdio stream *stream*. If you do not call the function `output_quoted_string` in your config files, GCC will only call it to output filenames to the assembler source. So you can use it to canonicalize the format of the filename using this macro.

`void TARGET_ASM_NAMED_SECTION` (*const char *name*, *unsigned int flags*, *tree decl*) [Target Hook]

Output assembly directives to switch to section *name*. The section should have attributes as specified by *flags*, which is a bit mask of the `SECTION_*` flags defined in '`output.h`'. If *decl* is non-NULL, it is the `VAR_DECL` or `FUNCTION_DECL` with which this section is associated.

`section * TARGET_ASM_FUNCTION_SECTION` (*tree decl*, *enum node_frequency freq*, *bool startup*, *bool exit*) [Target Hook]

Return preferred text (sub)section for function *decl*. Main purpose of this function is to separate cold, normal and hot functions. *startup* is true when function is known to be used only at startup (from static constructors or it is `main()`). *exit* is true when function is known to be used only at exit (from static destructors). Return NULL if function should go to default text section.

`void TARGET_ASM_FUNCTION_SWITCHED_TEXT_SECTIONS` (*FILE *file*, *tree decl*, *bool new_is_cold*) [Target Hook]

Used by the target to emit any assembler directives or additional labels needed when a function is partitioned between different sections. Output should be written to *file*. The function decl is available as *decl* and the new section is 'cold' if *new_is_cold* is `true`.

`bool TARGET_HAVE_NAMED_SECTIONS` [Common Target Hook]

This flag is true if the target supports `TARGET_ASM_NAMED_SECTION`. It must not be modified by command-line option processing.

`bool TARGET_HAVE_SWITCHABLE_BSS_SECTIONS` [Target Hook]

This flag is true if we can create zeroed data by switching to a BSS section and then using `ASM_OUTPUT_SKIP` to allocate the space. This is true on most ELF targets.

`unsigned int TARGET_SECTION_TYPE_FLAGS` (*tree* `decl`, *const char* *`name`, *int* `reloc`) [Target Hook]

Choose a set of section attributes for use by `TARGET_ASM_NAMED_SECTION` based on a variable or function decl, a section name, and whether or not the declaration's initializer may contain runtime relocations. *decl* may be null, in which case read-write data should be assumed.

The default version of this function handles choosing code vs data, read-only vs read-write data, and `flag_pic`. You should only need to override this if your target has special flags that might be set via `__attribute__`.

`int TARGET_ASM_RECORD_GCC_SWITCHES` (*print_switch_type* `type`, *const char* *`text`) [Target Hook]

Provides the target with the ability to record the gcc command line switches that have been passed to the compiler, and options that are enabled. The *type* argument specifies what is being recorded. It can take the following values:

`SWITCH_TYPE_PASSED`
: *text* is a command line switch that has been set by the user.

`SWITCH_TYPE_ENABLED`
: *text* is an option which has been enabled. This might be as a direct result of a command line switch, or because it is enabled by default or because it has been enabled as a side effect of a different command line switch. For example, the '`-O2`' switch enables various different individual optimization passes.

`SWITCH_TYPE_DESCRIPTIVE`
: *text* is either NULL or some descriptive text which should be ignored. If *text* is NULL then it is being used to warn the target hook that either recording is starting or ending. The first time *type* is SWITCH_TYPE_DESCRIPTIVE and *text* is NULL, the warning is for start up and the second time the warning is for wind down. This feature is to allow the target hook to make any necessary preparations before it starts to record switches and to perform any necessary tidying up after it has finished recording switches.

`SWITCH_TYPE_LINE_START`
: This option can be ignored by this target hook.

`SWITCH_TYPE_LINE_END`
: This option can be ignored by this target hook.

The hook's return value must be zero. Other return values may be supported in the future.

By default this hook is set to NULL, but an example implementation is provided for ELF based targets. Called *elf_record_gcc_switches*, it records the switches as ASCII

text inside a new, string mergeable section in the assembler output file. The name of the new section is provided by the `TARGET_ASM_RECORD_GCC_SWITCHES_SECTION` target hook.

`const char * TARGET_ASM_RECORD_GCC_SWITCHES_SECTION` [Target Hook]

This is the name of the section that will be created by the example ELF implementation of the `TARGET_ASM_RECORD_GCC_SWITCHES` target hook.

17.21.2 Output of Data

`const char * TARGET_ASM_BYTE_OP` [Target Hook]
`const char * TARGET_ASM_ALIGNED_HI_OP` [Target Hook]
`const char * TARGET_ASM_ALIGNED_SI_OP` [Target Hook]
`const char * TARGET_ASM_ALIGNED_DI_OP` [Target Hook]
`const char * TARGET_ASM_ALIGNED_TI_OP` [Target Hook]
`const char * TARGET_ASM_UNALIGNED_HI_OP` [Target Hook]
`const char * TARGET_ASM_UNALIGNED_SI_OP` [Target Hook]
`const char * TARGET_ASM_UNALIGNED_DI_OP` [Target Hook]
`const char * TARGET_ASM_UNALIGNED_TI_OP` [Target Hook]

These hooks specify assembly directives for creating certain kinds of integer object. The `TARGET_ASM_BYTE_OP` directive creates a byte-sized object, the `TARGET_ASM_ALIGNED_HI_OP` one creates an aligned two-byte object, and so on. Any of the hooks may be `NULL`, indicating that no suitable directive is available.

The compiler will print these strings at the start of a new line, followed immediately by the object's initial value. In most cases, the string should contain a tab, a pseudo-op, and then another tab.

`bool TARGET_ASM_INTEGER` (*rtx* `x`, *unsigned int* `size`, *int* `aligned_p`) [Target Hook]

The `assemble_integer` function uses this hook to output an integer object. *x* is the object's value, *size* is its size in bytes and *aligned_p* indicates whether it is aligned. The function should return `true` if it was able to output the object. If it returns false, `assemble_integer` will try to split the object into smaller parts.

The default implementation of this hook will use the `TARGET_ASM_BYTE_OP` family of strings, returning `false` when the relevant string is `NULL`.

`bool TARGET_ASM_OUTPUT_ADDR_CONST_EXTRA` (*FILE* `*file`, *rtx* `x`) [Target Hook]

A target hook to recognize *rtx* patterns that `output_addr_const` can't deal with, and output assembly code to *file* corresponding to the pattern *x*. This may be used to allow machine-dependent `UNSPEC`s to appear within constants.

If target hook fails to recognize a pattern, it must return `false`, so that a standard error message is printed. If it prints an error message itself, by calling, for example, `output_operand_lossage`, it may just return `true`.

`ASM_OUTPUT_ASCII` (`stream`, `ptr`, `len`) [Macro]

A C statement to output to the stdio stream *stream* an assembler instruction to assemble a string constant containing the *len* bytes at *ptr*. *ptr* will be a C expression of type `char *` and *len* a C expression of type `int`.

If the assembler has a `.ascii` pseudo-op as found in the Berkeley Unix assembler, do not define the macro `ASM_OUTPUT_ASCII`.

`ASM_OUTPUT_FDESC (stream, decl, n)` [Macro]

A C statement to output word *n* of a function descriptor for *decl*. This must be defined if `TARGET_VTABLE_USES_DESCRIPTORS` is defined, and is otherwise unused.

`CONSTANT_POOL_BEFORE_FUNCTION` [Macro]

You may define this macro as a C expression. You should define the expression to have a nonzero value if GCC should output the constant pool for a function before the code for the function, or a zero value if GCC should output the constant pool after the function. If you do not define this macro, the usual case, GCC will output the constant pool before the function.

`ASM_OUTPUT_POOL_PROLOGUE (file, funname, fundecl, size)` [Macro]

A C statement to output assembler commands to define the start of the constant pool for a function. *funname* is a string giving the name of the function. Should the return type of the function be required, it can be obtained via *fundecl*. *size* is the size, in bytes, of the constant pool that will be written immediately after this call.

If no constant-pool prefix is required, the usual case, this macro need not be defined.

`ASM_OUTPUT_SPECIAL_POOL_ENTRY (file, x, mode, align, labelno, jumpto)` [Macro]

A C statement (with or without semicolon) to output a constant in the constant pool, if it needs special treatment. (This macro need not do anything for RTL expressions that can be output normally.)

The argument *file* is the standard I/O stream to output the assembler code on. *x* is the RTL expression for the constant to output, and *mode* is the machine mode (in case *x* is a '`const_int`'). *align* is the required alignment for the value *x*; you should output an assembler directive to force this much alignment.

The argument *labelno* is a number to use in an internal label for the address of this pool entry. The definition of this macro is responsible for outputting the label definition at the proper place. Here is how to do this:

```
(*targetm.asm_out.internal_label) (file, "LC", labelno);
```

When you output a pool entry specially, you should end with a `goto` to the label *jumpto*. This will prevent the same pool entry from being output a second time in the usual manner.

You need not define this macro if it would do nothing.

`ASM_OUTPUT_POOL_EPILOGUE (file funname fundecl size)` [Macro]

A C statement to output assembler commands to at the end of the constant pool for a function. *funname* is a string giving the name of the function. Should the return type of the function be required, you can obtain it via *fundecl*. *size* is the size, in bytes, of the constant pool that GCC wrote immediately before this call.

If no constant-pool epilogue is required, the usual case, you need not define this macro.

`IS_ASM_LOGICAL_LINE_SEPARATOR (C, STR)` [Macro]

Define this macro as a C expression which is nonzero if *C* is used as a logical line separator by the assembler. *STR* points to the position in the string where *C* was found; this can be used if a line separator uses multiple characters.

If you do not define this macro, the default is that only the character '`;`' is treated as a logical line separator.

`const char * TARGET_ASM_OPEN_PAREN` [Target Hook]
`const char * TARGET_ASM_CLOSE_PAREN` [Target Hook]

These target hooks are C string constants, describing the syntax in the assembler for grouping arithmetic expressions. If not overridden, they default to normal parentheses, which is correct for most assemblers.

These macros are provided by '`real.h`' for writing the definitions of `ASM_OUTPUT_DOUBLE` and the like:

`REAL_VALUE_TO_TARGET_SINGLE (x, l)` [Macro]
`REAL_VALUE_TO_TARGET_DOUBLE (x, l)` [Macro]
`REAL_VALUE_TO_TARGET_LONG_DOUBLE (x, l)` [Macro]
`REAL_VALUE_TO_TARGET_DECIMAL32 (x, l)` [Macro]
`REAL_VALUE_TO_TARGET_DECIMAL64 (x, l)` [Macro]
`REAL_VALUE_TO_TARGET_DECIMAL128 (x, l)` [Macro]

These translate *x*, of type `REAL_VALUE_TYPE`, to the target's floating point representation, and store its bit pattern in the variable *l*. For `REAL_VALUE_TO_TARGET_SINGLE` and `REAL_VALUE_TO_TARGET_DECIMAL32`, this variable should be a simple `long int`. For the others, it should be an array of `long int`. The number of elements in this array is determined by the size of the desired target floating point data type: 32 bits of it go in each `long int` array element. Each array element holds 32 bits of the result, even if `long int` is wider than 32 bits on the host machine.

The array element values are designed so that you can print them out using `fprintf` in the order they should appear in the target machine's memory.

17.21.3 Output of Uninitialized Variables

Each of the macros in this section is used to do the whole job of outputting a single uninitialized variable.

`ASM_OUTPUT_COMMON (stream, name, size, rounded)` [Macro]

A C statement (sans semicolon) to output to the stdio stream *stream* the assembler definition of a common-label named *name* whose size is *size* bytes. The variable *rounded* is the size rounded up to whatever alignment the caller wants. It is possible that *size* may be zero, for instance if a struct with no other member than a zero-length array is defined. In this case, the backend must output a symbol definition that allocates at least one byte, both so that the address of the resulting object does not compare equal to any other, and because some object formats cannot even express the concept of a zero-sized common symbol, as that is how they represent an ordinary undefined external.

Use the expression `assemble_name (stream, name)` to output the name itself; before and after that, output the additional assembler syntax for defining the name, and a newline.

This macro controls how the assembler definitions of uninitialized common global variables are output.

`ASM_OUTPUT_ALIGNED_COMMON (stream, name, size, alignment)` [Macro]

Like `ASM_OUTPUT_COMMON` except takes the required alignment as a separate, explicit argument. If you define this macro, it is used in place of `ASM_OUTPUT_COMMON`, and gives you more flexibility in handling the required alignment of the variable. The alignment is specified as the number of bits.

`ASM_OUTPUT_ALIGNED_DECL_COMMON (stream, decl, name, size, alignment)` [Macro]

Like `ASM_OUTPUT_ALIGNED_COMMON` except that *decl* of the variable to be output, if there is one, or `NULL_TREE` if there is no corresponding variable. If you define this macro, GCC will use it in place of both `ASM_OUTPUT_COMMON` and `ASM_OUTPUT_ALIGNED_COMMON`. Define this macro when you need to see the variable's decl in order to chose what to output.

`ASM_OUTPUT_ALIGNED_BSS (stream, decl, name, size, alignment)` [Macro]

A C statement (sans semicolon) to output to the stdio stream *stream* the assembler definition of uninitialized global *decl* named *name* whose size is *size* bytes. The variable *alignment* is the alignment specified as the number of bits.

Try to use function `asm_output_aligned_bss` defined in file '`varasm.c`' when defining this macro. If unable, use the expression `assemble_name (stream, name)` to output the name itself; before and after that, output the additional assembler syntax for defining the name, and a newline.

There are two ways of handling global BSS. One is to define this macro. The other is to have `TARGET_ASM_SELECT_SECTION` return a switchable BSS section (see [TARGET_HAVE_SWITCHABLE_BSS_SECTIONS], page 530). You do not need to do both.

Some languages do not have `common` data, and require a non-common form of global BSS in order to handle uninitialized globals efficiently. C++ is one example of this. However, if the target does not support global BSS, the front end may choose to make globals common in order to save space in the object file.

`ASM_OUTPUT_LOCAL (stream, name, size, rounded)` [Macro]

A C statement (sans semicolon) to output to the stdio stream *stream* the assembler definition of a local-common-label named *name* whose size is *size* bytes. The variable *rounded* is the size rounded up to whatever alignment the caller wants.

Use the expression `assemble_name (stream, name)` to output the name itself; before and after that, output the additional assembler syntax for defining the name, and a newline.

This macro controls how the assembler definitions of uninitialized static variables are output.

`ASM_OUTPUT_ALIGNED_LOCAL (stream, name, size, alignment)` [Macro]

Like `ASM_OUTPUT_LOCAL` except takes the required alignment as a separate, explicit argument. If you define this macro, it is used in place of `ASM_OUTPUT_LOCAL`, and gives you more flexibility in handling the required alignment of the variable. The alignment is specified as the number of bits.

`ASM_OUTPUT_ALIGNED_DECL_LOCAL (stream, decl, name, size, alignment)` [Macro]

Like `ASM_OUTPUT_ALIGNED_DECL` except that *decl* of the variable to be output, if there is one, or `NULL_TREE` if there is no corresponding variable. If you define this macro, GCC will use it in place of both `ASM_OUTPUT_DECL` and `ASM_OUTPUT_ALIGNED_DECL`. Define this macro when you need to see the variable's decl in order to chose what to output.

17.21.4 Output and Generation of Labels

This is about outputting labels.

`ASM_OUTPUT_LABEL (stream, name)` [Macro]

A C statement (sans semicolon) to output to the stdio stream *stream* the assembler definition of a label named *name*. Use the expression `assemble_name (stream, name)` to output the name itself; before and after that, output the additional assembler syntax for defining the name, and a newline. A default definition of this macro is provided which is correct for most systems.

`ASM_OUTPUT_FUNCTION_LABEL (stream, name, decl)` [Macro]

A C statement (sans semicolon) to output to the stdio stream *stream* the assembler definition of a label named *name* of a function. Use the expression `assemble_name (stream, name)` to output the name itself; before and after that, output the additional assembler syntax for defining the name, and a newline. A default definition of this macro is provided which is correct for most systems.

If this macro is not defined, then the function name is defined in the usual manner as a label (by means of `ASM_OUTPUT_LABEL`).

`ASM_OUTPUT_INTERNAL_LABEL (stream, name)` [Macro]

Identical to `ASM_OUTPUT_LABEL`, except that *name* is known to refer to a compiler-generated label. The default definition uses `assemble_name_raw`, which is like `assemble_name` except that it is more efficient.

`SIZE_ASM_OP` [Macro]

A C string containing the appropriate assembler directive to specify the size of a symbol, without any arguments. On systems that use ELF, the default (in '`config/elfos.h`') is '`"\t.size\t"`'; on other systems, the default is not to define this macro.

Define this macro only if it is correct to use the default definitions of `ASM_OUTPUT_SIZE_DIRECTIVE` and `ASM_OUTPUT_MEASURED_SIZE` for your system. If you need your own custom definitions of those macros, or if you do not need explicit symbol sizes at all, do not define this macro.

`ASM_OUTPUT_SIZE_DIRECTIVE (stream, name, size)` [Macro]

A C statement (sans semicolon) to output to the stdio stream *stream* a directive telling the assembler that the size of the symbol *name* is *size*. *size* is a `HOST_WIDE_INT`. If you define `SIZE_ASM_OP`, a default definition of this macro is provided.

`ASM_OUTPUT_MEASURED_SIZE (stream, name)` [Macro]

A C statement (sans semicolon) to output to the stdio stream *stream* a directive telling the assembler to calculate the size of the symbol *name* by subtracting its address from the current address.

If you define `SIZE_ASM_OP`, a default definition of this macro is provided. The default assumes that the assembler recognizes a special '`.`' symbol as referring to the current address, and can calculate the difference between this and another symbol. If your assembler does not recognize '`.`' or cannot do calculations with it, you will need to redefine `ASM_OUTPUT_MEASURED_SIZE` to use some other technique.

`NO_DOLLAR_IN_LABEL` [Macro]

Define this macro if the assembler does not accept the character '`$`' in label names. By default constructors and destructors in G++ have '`$`' in the identifiers. If this macro is defined, '`.`' is used instead.

`NO_DOT_IN_LABEL` [Macro]

Define this macro if the assembler does not accept the character '`.`' in label names. By default constructors and destructors in G++ have names that use '`.`'. If this macro is defined, these names are rewritten to avoid '`.`'.

`TYPE_ASM_OP` [Macro]

A C string containing the appropriate assembler directive to specify the type of a symbol, without any arguments. On systems that use ELF, the default (in '`config/elfos.h`') is '`"\t.type\t"`'; on other systems, the default is not to define this macro.

Define this macro only if it is correct to use the default definition of `ASM_OUTPUT_TYPE_DIRECTIVE` for your system. If you need your own custom definition of this macro, or if you do not need explicit symbol types at all, do not define this macro.

`TYPE_OPERAND_FMT` [Macro]

A C string which specifies (using `printf` syntax) the format of the second operand to `TYPE_ASM_OP`. On systems that use ELF, the default (in '`config/elfos.h`') is '`"@%s"`'; on other systems, the default is not to define this macro.

Define this macro only if it is correct to use the default definition of `ASM_OUTPUT_TYPE_DIRECTIVE` for your system. If you need your own custom definition of this macro, or if you do not need explicit symbol types at all, do not define this macro.

`ASM_OUTPUT_TYPE_DIRECTIVE (stream, type)` [Macro]

A C statement (sans semicolon) to output to the stdio stream *stream* a directive telling the assembler that the type of the symbol *name* is *type*. *type* is a C string; currently, that string is always either '`"function"`' or '`"object"`', but you should not count on this.

If you define `TYPE_ASM_OP` and `TYPE_OPERAND_FMT`, a default definition of this macro is provided.

`ASM_DECLARE_FUNCTION_NAME` (*stream*, *name*, *decl*) [Macro]

A C statement (sans semicolon) to output to the stdio stream *stream* any text necessary for declaring the name *name* of a function which is being defined. This macro is responsible for outputting the label definition (perhaps using `ASM_OUTPUT_FUNCTION_LABEL`). The argument *decl* is the `FUNCTION_DECL` tree node representing the function.

If this macro is not defined, then the function name is defined in the usual manner as a label (by means of `ASM_OUTPUT_FUNCTION_LABEL`).

You may wish to use `ASM_OUTPUT_TYPE_DIRECTIVE` in the definition of this macro.

`ASM_DECLARE_FUNCTION_SIZE` (*stream*, *name*, *decl*) [Macro]

A C statement (sans semicolon) to output to the stdio stream *stream* any text necessary for declaring the size of a function which is being defined. The argument *name* is the name of the function. The argument *decl* is the `FUNCTION_DECL` tree node representing the function.

If this macro is not defined, then the function size is not defined.

You may wish to use `ASM_OUTPUT_MEASURED_SIZE` in the definition of this macro.

`ASM_DECLARE_OBJECT_NAME` (*stream*, *name*, *decl*) [Macro]

A C statement (sans semicolon) to output to the stdio stream *stream* any text necessary for declaring the name *name* of an initialized variable which is being defined. This macro must output the label definition (perhaps using `ASM_OUTPUT_LABEL`). The argument *decl* is the `VAR_DECL` tree node representing the variable.

If this macro is not defined, then the variable name is defined in the usual manner as a label (by means of `ASM_OUTPUT_LABEL`).

You may wish to use `ASM_OUTPUT_TYPE_DIRECTIVE` and/or `ASM_OUTPUT_SIZE_DIRECTIVE` in the definition of this macro.

`void TARGET_ASM_DECLARE_CONSTANT_NAME` (*FILE *file*, *const char *name*, *const_tree expr*, *HOST_WIDE_INT size*) [Target Hook]

A target hook to output to the stdio stream *file* any text necessary for declaring the name *name* of a constant which is being defined. This target hook is responsible for outputting the label definition (perhaps using `assemble_label`). The argument *exp* is the value of the constant, and *size* is the size of the constant in bytes. The *name* will be an internal label.

The default version of this target hook, define the *name* in the usual manner as a label (by means of `assemble_label`).

You may wish to use `ASM_OUTPUT_TYPE_DIRECTIVE` in this target hook.

`ASM_DECLARE_REGISTER_GLOBAL` (*stream*, *decl*, *regno*, *name*) [Macro]

A C statement (sans semicolon) to output to the stdio stream *stream* any text necessary for claiming a register *regno* for a global variable *decl* with name *name*.

If you don't define this macro, that is equivalent to defining it to do nothing.

`ASM_FINISH_DECLARE_OBJECT` (*stream*, *decl*, *toplevel*, *atend*) [Macro]

A C statement (sans semicolon) to finish up declaring a variable name once the compiler has processed its initializer fully and thus has had a chance to determine the

size of an array when controlled by an initializer. This is used on systems where it's necessary to declare something about the size of the object.

If you don't define this macro, that is equivalent to defining it to do nothing.

You may wish to use `ASM_OUTPUT_SIZE_DIRECTIVE` and/or `ASM_OUTPUT_MEASURED_SIZE` in the definition of this macro.

`void TARGET_ASM_GLOBALIZE_LABEL (FILE *stream, const char *name)` [Target Hook]

This target hook is a function to output to the stdio stream *stream* some commands that will make the label *name* global; that is, available for reference from other files.

The default implementation relies on a proper definition of `GLOBAL_ASM_OP`.

`void TARGET_ASM_GLOBALIZE_DECL_NAME (FILE *stream, tree decl)` [Target Hook]

This target hook is a function to output to the stdio stream *stream* some commands that will make the name associated with *decl* global; that is, available for reference from other files.

The default implementation uses the TARGET_ASM_GLOBALIZE_LABEL target hook.

`ASM_WEAKEN_LABEL (stream, name)` [Macro]

A C statement (sans semicolon) to output to the stdio stream *stream* some commands that will make the label *name* weak; that is, available for reference from other files but only used if no other definition is available. Use the expression `assemble_name (stream, name)` to output the name itself; before and after that, output the additional assembler syntax for making that name weak, and a newline.

If you don't define this macro or `ASM_WEAKEN_DECL`, GCC will not support weak symbols and you should not define the `SUPPORTS_WEAK` macro.

`ASM_WEAKEN_DECL (stream, decl, name, value)` [Macro]

Combines (and replaces) the function of `ASM_WEAKEN_LABEL` and `ASM_OUTPUT_WEAK_ALIAS`, allowing access to the associated function or variable decl. If *value* is not `NULL`, this C statement should output to the stdio stream *stream* assembler code which defines (equates) the weak symbol *name* to have the value *value*. If *value* is `NULL`, it should output commands to make *name* weak.

`ASM_OUTPUT_WEAKREF (stream, decl, name, value)` [Macro]

Outputs a directive that enables *name* to be used to refer to symbol *value* with weak-symbol semantics. `decl` is the declaration of `name`.

`SUPPORTS_WEAK` [Macro]

A preprocessor constant expression which evaluates to true if the target supports weak symbols.

If you don't define this macro, '`defaults.h`' provides a default definition. If either `ASM_WEAKEN_LABEL` or `ASM_WEAKEN_DECL` is defined, the default definition is '`1`'; otherwise, it is '`0`'.

`TARGET_SUPPORTS_WEAK` [Macro]

A C expression which evaluates to true if the target supports weak symbols.

If you don't define this macro, '`defaults.h`' provides a default definition. The default definition is '`(SUPPORTS_WEAK)`'. Define this macro if you want to control weak symbol support with a compiler flag such as '`-melf`'.

`MAKE_DECL_ONE_ONLY (decl)` [Macro]

A C statement (sans semicolon) to mark *decl* to be emitted as a public symbol such that extra copies in multiple translation units will be discarded by the linker. Define this macro if your object file format provides support for this concept, such as the '`COMDAT`' section flags in the Microsoft Windows PE/COFF format, and this support requires changes to *decl*, such as putting it in a separate section.

`SUPPORTS_ONE_ONLY` [Macro]

A C expression which evaluates to true if the target supports one-only semantics.

If you don't define this macro, '`varasm.c`' provides a default definition. If `MAKE_DECL_ONE_ONLY` is defined, the default definition is '`1`'; otherwise, it is '`0`'. Define this macro if you want to control one-only symbol support with a compiler flag, or if setting the `DECL_ONE_ONLY` flag is enough to mark a declaration to be emitted as one-only.

`void TARGET_ASM_ASSEMBLE_VISIBILITY (tree decl, int visibility)` [Target Hook]

This target hook is a function to output to *asm_out_file* some commands that will make the symbol(s) associated with *decl* have hidden, protected or internal visibility as specified by *visibility*.

`TARGET_WEAK_NOT_IN_ARCHIVE_TOC` [Macro]

A C expression that evaluates to true if the target's linker expects that weak symbols do not appear in a static archive's table of contents. The default is `0`.

Leaving weak symbols out of an archive's table of contents means that, if a symbol will only have a definition in one translation unit and will have undefined references from other translation units, that symbol should not be weak. Defining this macro to be nonzero will thus have the effect that certain symbols that would normally be weak (explicit template instantiations, and vtables for polymorphic classes with noninline key methods) will instead be nonweak.

The C++ ABI requires this macro to be zero. Define this macro for targets where full C++ ABI compliance is impossible and where linker restrictions require weak symbols to be left out of a static archive's table of contents.

`ASM_OUTPUT_EXTERNAL (stream, decl, name)` [Macro]

A C statement (sans semicolon) to output to the stdio stream *stream* any text necessary for declaring the name of an external symbol named *name* which is referenced in this compilation but not defined. The value of *decl* is the tree node for the declaration.

This macro need not be defined if it does not need to output anything. The GNU assembler and most Unix assemblers don't require anything.

void TARGET_ASM_EXTERNAL_LIBCALL (*rtx* *symref*) [Target Hook]

This target hook is a function to output to *asm_out_file* an assembler pseudo-op to declare a library function name external. The name of the library function is given by *symref*, which is a `symbol_ref`.

void TARGET_ASM_MARK_DECL_PRESERVED (*const char* **symbol*) [Target Hook]

This target hook is a function to output to *asm_out_file* an assembler directive to annotate *symbol* as used. The Darwin target uses the .no_dead_code_strip directive.

ASM_OUTPUT_LABELREF (*stream*, *name*) [Macro]

A C statement (sans semicolon) to output to the stdio stream *stream* a reference in assembler syntax to a label named *name*. This should add '_' to the front of the name, if that is customary on your operating system, as it is in most Berkeley Unix systems. This macro is used in `assemble_name`.

tree TARGET_MANGLE_ASSEMBLER_NAME (*const char* **name*) [Target Hook]

Given a symbol *name*, perform same mangling as `varasm.c`'s `assemble_name`, but in memory rather than to a file stream, returning result as an `IDENTIFIER_NODE`. Required for correct LTO symtabs. The default implementation calls the `TARGET_STRIP_NAME_ENCODING` hook and then prepends the `USER_LABEL_PREFIX`, if any.

ASM_OUTPUT_SYMBOL_REF (*stream*, *sym*) [Macro]

A C statement (sans semicolon) to output a reference to `SYMBOL_REF` *sym*. If not defined, `assemble_name` will be used to output the name of the symbol. This macro may be used to modify the way a symbol is referenced depending on information encoded by `TARGET_ENCODE_SECTION_INFO`.

ASM_OUTPUT_LABEL_REF (*stream*, *buf*) [Macro]

A C statement (sans semicolon) to output a reference to *buf*, the result of `ASM_GENERATE_INTERNAL_LABEL`. If not defined, `assemble_name` will be used to output the name of the symbol. This macro is not used by `output_asm_label`, or the `%l` specifier that calls it; the intention is that this macro should be set when it is necessary to output a label differently when its address is being taken.

void TARGET_ASM_INTERNAL_LABEL (*FILE* **stream*, *const char* **prefix*, *unsigned long* *labelno*) [Target Hook]

A function to output to the stdio stream *stream* a label whose name is made from the string *prefix* and the number *labelno*.

It is absolutely essential that these labels be distinct from the labels used for user-level functions and variables. Otherwise, certain programs will have name conflicts with internal labels.

It is desirable to exclude internal labels from the symbol table of the object file. Most assemblers have a naming convention for labels that should be excluded; on many systems, the letter 'L' at the beginning of a label has this effect. You should find out what convention your system uses, and follow it.

The default version of this function utilizes `ASM_GENERATE_INTERNAL_LABEL`.

`ASM_OUTPUT_DEBUG_LABEL (stream, prefix, num)` [Macro]

A C statement to output to the stdio stream *stream* a debug info label whose name is made from the string *prefix* and the number *num*. This is useful for VLIW targets, where debug info labels may need to be treated differently than branch target labels. On some systems, branch target labels must be at the beginning of instruction bundles, but debug info labels can occur in the middle of instruction bundles.

If this macro is not defined, then `(*targetm.asm_out.internal_label)` will be used.

`ASM_GENERATE_INTERNAL_LABEL (string, prefix, num)` [Macro]

A C statement to store into the string *string* a label whose name is made from the string *prefix* and the number *num*.

This string, when output subsequently by `assemble_name`, should produce the output that `(*targetm.asm_out.internal_label)` would produce with the same *prefix* and *num*.

If the string begins with '`*`', then `assemble_name` will output the rest of the string unchanged. It is often convenient for `ASM_GENERATE_INTERNAL_LABEL` to use '`*`' in this way. If the string doesn't start with '`*`', then `ASM_OUTPUT_LABELREF` gets to output the string, and may change it. (Of course, `ASM_OUTPUT_LABELREF` is also part of your machine description, so you should know what it does on your machine.)

`ASM_FORMAT_PRIVATE_NAME (outvar, name, number)` [Macro]

A C expression to assign to *outvar* (which is a variable of type `char *`) a newly allocated string made from the string *name* and the number *number*, with some suitable punctuation added. Use `alloca` to get space for the string.

The string will be used as an argument to `ASM_OUTPUT_LABELREF` to produce an assembler label for an internal static variable whose name is *name*. Therefore, the string must be such as to result in valid assembler code. The argument *number* is different each time this macro is executed; it prevents conflicts between similarly-named internal static variables in different scopes.

Ideally this string should not be a valid C identifier, to prevent any conflict with the user's own symbols. Most assemblers allow periods or percent signs in assembler symbols; putting at least one of these between the name and the number will suffice.

If this macro is not defined, a default definition will be provided which is correct for most systems.

`ASM_OUTPUT_DEF (stream, name, value)` [Macro]

A C statement to output to the stdio stream *stream* assembler code which defines (equates) the symbol *name* to have the value *value*.

If `SET_ASM_OP` is defined, a default definition is provided which is correct for most systems.

`ASM_OUTPUT_DEF_FROM_DECLS (stream, decl_of_name, decl_of_value)` [Macro]

A C statement to output to the stdio stream *stream* assembler code which defines (equates) the symbol whose tree node is *decl_of_name* to have the value of the tree node *decl_of_value*. This macro will be used in preference to '`ASM_OUTPUT_DEF`' if it is defined and if the tree nodes are available.

If `SET_ASM_OP` is defined, a default definition is provided which is correct for most systems.

`TARGET_DEFERRED_OUTPUT_DEFS` (*decl_of_name*, *decl_of_value*) [Macro]

A C statement that evaluates to true if the assembler code which defines (equates) the symbol whose tree node is *decl_of_name* to have the value of the tree node *decl_of_value* should be emitted near the end of the current compilation unit. The default is to not defer output of defines. This macro affects defines output by '`ASM_OUTPUT_DEF`' and '`ASM_OUTPUT_DEF_FROM_DECLS`'.

`ASM_OUTPUT_WEAK_ALIAS` (*stream*, *name*, *value*) [Macro]

A C statement to output to the stdio stream *stream* assembler code which defines (equates) the weak symbol *name* to have the value *value*. If *value* is `NULL`, it defines *name* as an undefined weak symbol.

Define this macro if the target only supports weak aliases; define `ASM_OUTPUT_DEF` instead if possible.

`OBJC_GEN_METHOD_LABEL` (*buf*, *is_inst*, *class_name*, *cat_name*, *sel_name*) [Macro]

Define this macro to override the default assembler names used for Objective-C methods.

The default name is a unique method number followed by the name of the class (e.g. '`_1_Foo`'). For methods in categories, the name of the category is also included in the assembler name (e.g. '`_1_Foo_Bar`').

These names are safe on most systems, but make debugging difficult since the method's selector is not present in the name. Therefore, particular systems define other ways of computing names.

buf is an expression of type `char *` which gives you a buffer in which to store the name; its length is as long as *class_name*, *cat_name* and *sel_name* put together, plus 50 characters extra.

The argument *is_inst* specifies whether the method is an instance method or a class method; *class_name* is the name of the class; *cat_name* is the name of the category (or `NULL` if the method is not in a category); and *sel_name* is the name of the selector.

On systems where the assembler can handle quoted names, you can use this macro to provide more human-readable names.

17.21.5 How Initialization Functions Are Handled

The compiled code for certain languages includes *constructors* (also called *initialization routines*)—functions to initialize data in the program when the program is started. These functions need to be called before the program is "started"—that is to say, before `main` is called.

Compiling some languages generates *destructors* (also called *termination routines*) that should be called when the program terminates.

To make the initialization and termination functions work, the compiler must output something in the assembler code to cause those functions to be called at the appropriate time. When you port the compiler to a new system, you need to specify how to do this.

There are two major ways that GCC currently supports the execution of initialization and termination functions. Each way has two variants. Much of the structure is common to all four variations.

The linker must build two lists of these functions—a list of initialization functions, called `__CTOR_LIST__`, and a list of termination functions, called `__DTOR_LIST__`.

Each list always begins with an ignored function pointer (which may hold 0, −1, or a count of the function pointers after it, depending on the environment). This is followed by a series of zero or more function pointers to constructors (or destructors), followed by a function pointer containing zero.

Depending on the operating system and its executable file format, either '`crtstuff.c`' or '`libgcc2.c`' traverses these lists at startup time and exit time. Constructors are called in reverse order of the list; destructors in forward order.

The best way to handle static constructors works only for object file formats which provide arbitrarily-named sections. A section is set aside for a list of constructors, and another for a list of destructors. Traditionally these are called '`.ctors`' and '`.dtors`'. Each object file that defines an initialization function also puts a word in the constructor section to point to that function. The linker accumulates all these words into one contiguous '`.ctors`' section. Termination functions are handled similarly.

This method will be chosen as the default by '`target-def.h`' if `TARGET_ASM_NAMED_SECTION` is defined. A target that does not support arbitrary sections, but does support special designated constructor and destructor sections may define `CTORS_SECTION_ASM_OP` and `DTORS_SECTION_ASM_OP` to achieve the same effect.

When arbitrary sections are available, there are two variants, depending upon how the code in '`crtstuff.c`' is called. On systems that support a *.init* section which is executed at program startup, parts of '`crtstuff.c`' are compiled into that section. The program is linked by the `gcc` driver like this:

```
ld -o output_file crti.o crtbegin.o ... -lgcc crtend.o crtn.o
```

The prologue of a function (`__init`) appears in the `.init` section of '`crti.o`'; the epilogue appears in '`crtn.o`'. Likewise for the function `__fini` in the *.fini* section. Normally these files are provided by the operating system or by the GNU C library, but are provided by GCC for a few targets.

The objects '`crtbegin.o`' and '`crtend.o`' are (for most targets) compiled from '`crtstuff.c`'. They contain, among other things, code fragments within the `.init` and `.fini` sections that branch to routines in the `.text` section. The linker will pull all parts of a section together, which results in a complete `__init` function that invokes the routines we need at startup.

To use this variant, you must define the `INIT_SECTION_ASM_OP` macro properly.

If no init section is available, when GCC compiles any function called `main` (or more accurately, any function designated as a program entry point by the language front end calling `expand_main_function`), it inserts a procedure call to `__main` as the first executable code after the function prologue. The `__main` function is defined in '`libgcc2.c`' and runs the global constructors.

In file formats that don't support arbitrary sections, there are again two variants. In the simplest variant, the GNU linker (GNU `ld`) and an 'a.out' format must be used. In

this case, TARGET_ASM_CONSTRUCTOR is defined to produce a .stabs entry of type 'N_SETT', referencing the name __CTOR_LIST__, and with the address of the void function containing the initialization code as its value. The GNU linker recognizes this as a request to add the value to a *set*; the values are accumulated, and are eventually placed in the executable as a vector in the format described above, with a leading (ignored) count and a trailing zero element. TARGET_ASM_DESTRUCTOR is handled similarly. Since no init section is available, the absence of INIT_SECTION_ASM_OP causes the compilation of main to call __main as above, starting the initialization process.

The last variant uses neither arbitrary sections nor the GNU linker. This is preferable when you want to do dynamic linking and when using file formats which the GNU linker does not support, such as 'ECOFF'. In this case, TARGET_HAVE_CTORS_DTORS is false, initialization and termination functions are recognized simply by their names. This requires an extra program in the linkage step, called collect2. This program pretends to be the linker, for use with GCC; it does its job by running the ordinary linker, but also arranges to include the vectors of initialization and termination functions. These functions are called via __main as described above. In order to use this method, use_collect2 must be defined in the target in 'config.gcc'.

17.21.6 Macros Controlling Initialization Routines

Here are the macros that control how the compiler handles initialization and termination functions:

INIT_SECTION_ASM_OP [Macro]

If defined, a C string constant, including spacing, for the assembler operation to identify the following data as initialization code. If not defined, GCC will assume such a section does not exist. When you are using special sections for initialization and termination functions, this macro also controls how 'crtstuff.c' and 'libgcc2.c' arrange to run the initialization functions.

HAS_INIT_SECTION [Macro]

If defined, main will not call __main as described above. This macro should be defined for systems that control start-up code on a symbol-by-symbol basis, such as OSF/1, and should not be defined explicitly for systems that support INIT_SECTION_ASM_OP.

LD_INIT_SWITCH [Macro]

If defined, a C string constant for a switch that tells the linker that the following symbol is an initialization routine.

LD_FINI_SWITCH [Macro]

If defined, a C string constant for a switch that tells the linker that the following symbol is a finalization routine.

COLLECT_SHARED_INIT_FUNC (*stream*, *func*) [Macro]

If defined, a C statement that will write a function that can be automatically called when a shared library is loaded. The function should call *func*, which takes no arguments. If not defined, and the object format requires an explicit initialization function, then a function called _GLOBAL__DI will be generated.

This function and the following one are used by collect2 when linking a shared library that needs constructors or destructors, or has DWARF2 exception tables embedded in the code.

`COLLECT_SHARED_FINI_FUNC` (*stream*, *func*) [Macro]

If defined, a C statement that will write a function that can be automatically called when a shared library is unloaded. The function should call *func*, which takes no arguments. If not defined, and the object format requires an explicit finalization function, then a function called `_GLOBAL__DD` will be generated.

`INVOKE__main` [Macro]

If defined, `main` will call `__main` despite the presence of `INIT_SECTION_ASM_OP`. This macro should be defined for systems where the init section is not actually run automatically, but is still useful for collecting the lists of constructors and destructors.

`SUPPORTS_INIT_PRIORITY` [Macro]

If nonzero, the C++ `init_priority` attribute is supported and the compiler should emit instructions to control the order of initialization of objects. If zero, the compiler will issue an error message upon encountering an `init_priority` attribute.

`bool TARGET_HAVE_CTORS_DTORS` [Target Hook]

This value is true if the target supports some "native" method of collecting constructors and destructors to be run at startup and exit. It is false if we must use `collect2`.

`void TARGET_ASM_CONSTRUCTOR` (*rtx* *symbol*, *int* *priority*) [Target Hook]

If defined, a function that outputs assembler code to arrange to call the function referenced by *symbol* at initialization time.

Assume that *symbol* is a `SYMBOL_REF` for a function taking no arguments and with no return value. If the target supports initialization priorities, *priority* is a value between 0 and `MAX_INIT_PRIORITY`; otherwise it must be `DEFAULT_INIT_PRIORITY`.

If this macro is not defined by the target, a suitable default will be chosen if (1) the target supports arbitrary section names, (2) the target defines `CTORS_SECTION_ASM_OP`, or (3) `USE_COLLECT2` is not defined.

`void TARGET_ASM_DESTRUCTOR` (*rtx* *symbol*, *int* *priority*) [Target Hook]

This is like `TARGET_ASM_CONSTRUCTOR` but used for termination functions rather than initialization functions.

If `TARGET_HAVE_CTORS_DTORS` is true, the initialization routine generated for the generated object file will have static linkage.

If your system uses `collect2` as the means of processing constructors, then that program normally uses `nm` to scan an object file for constructor functions to be called.

On certain kinds of systems, you can define this macro to make `collect2` work faster (and, in some cases, make it work at all):

`OBJECT_FORMAT_COFF` [Macro]

Define this macro if the system uses COFF (Common Object File Format) object files, so that `collect2` can assume this format and scan object files directly for dynamic constructor/destructor functions.

This macro is effective only in a native compiler; `collect2` as part of a cross compiler always uses `nm` for the target machine.

`REAL_NM_FILE_NAME` [Macro]

Define this macro as a C string constant containing the file name to use to execute `nm`. The default is to search the path normally for `nm`.

`NM_FLAGS` [Macro]

`collect2` calls `nm` to scan object files for static constructors and destructors and LTO info. By default, '`-n`' is passed. Define `NM_FLAGS` to a C string constant if other options are needed to get the same output format as GNU `nm -n` produces.

If your system supports shared libraries and has a program to list the dynamic dependencies of a given library or executable, you can define these macros to enable support for running initialization and termination functions in shared libraries:

`LDD_SUFFIX` [Macro]

Define this macro to a C string constant containing the name of the program which lists dynamic dependencies, like `ldd` under SunOS 4.

`PARSE_LDD_OUTPUT` (*ptr*) [Macro]

Define this macro to be C code that extracts filenames from the output of the program denoted by `LDD_SUFFIX`. *ptr* is a variable of type `char *` that points to the beginning of a line of output from `LDD_SUFFIX`. If the line lists a dynamic dependency, the code must advance *ptr* to the beginning of the filename on that line. Otherwise, it must set *ptr* to `NULL`.

`SHLIB_SUFFIX` [Macro]

Define this macro to a C string constant containing the default shared library extension of the target (e.g., '`".so"`'). `collect2` strips version information after this suffix when generating global constructor and destructor names. This define is only needed on targets that use `collect2` to process constructors and destructors.

17.21.7 Output of Assembler Instructions

This describes assembler instruction output.

`REGISTER_NAMES` [Macro]

A C initializer containing the assembler's names for the machine registers, each one as a C string constant. This is what translates register numbers in the compiler into assembler language.

`ADDITIONAL_REGISTER_NAMES` [Macro]

If defined, a C initializer for an array of structures containing a name and a register number. This macro defines additional names for hard registers, thus allowing the `asm` option in declarations to refer to registers using alternate names.

`OVERLAPPING_REGISTER_NAMES` [Macro]

If defined, a C initializer for an array of structures containing a name, a register number and a count of the number of consecutive machine registers the name overlaps. This macro defines additional names for hard registers, thus allowing the `asm`

option in declarations to refer to registers using alternate names. Unlike `ADDITIONAL_REGISTER_NAMES`, this macro should be used when the register name implies multiple underlying registers.

This macro should be used when it is important that a clobber in an `asm` statement clobbers all the underlying values implied by the register name. For example, on ARM, clobbering the double-precision VFP register "d0" implies clobbering both single-precision registers "s0" and "s1".

`ASM_OUTPUT_OPCODE (stream, ptr)` [Macro]

Define this macro if you are using an unusual assembler that requires different names for the machine instructions.

The definition is a C statement or statements which output an assembler instruction opcode to the stdio stream *stream*. The macro-operand *ptr* is a variable of type `char *` which points to the opcode name in its "internal" form—the form that is written in the machine description. The definition should output the opcode name to *stream*, performing any translation you desire, and increment the variable *ptr* to point at the end of the opcode so that it will not be output twice.

In fact, your macro definition may process less than the entire opcode name, or more than the opcode name; but if you want to process text that includes '`%`'-sequences to substitute operands, you must take care of the substitution yourself. Just be sure to increment *ptr* over whatever text should not be output normally.

If you need to look at the operand values, they can be found as the elements of `recog_data.operand`.

If the macro definition does nothing, the instruction is output in the usual way.

`FINAL_PRESCAN_INSN (insn, opvec, noperands)` [Macro]

If defined, a C statement to be executed just prior to the output of assembler code for *insn*, to modify the extracted operands so they will be output differently.

Here the argument *opvec* is the vector containing the operands extracted from *insn*, and *noperands* is the number of elements of the vector which contain meaningful data for this insn. The contents of this vector are what will be used to convert the insn template into assembler code, so you can change the assembler output by changing the contents of the vector.

This macro is useful when various assembler syntaxes share a single file of instruction patterns; by defining this macro differently, you can cause a large class of instructions to be output differently (such as with rearranged operands). Naturally, variations in assembler syntax affecting individual insn patterns ought to be handled by writing conditional output routines in those patterns.

If this macro is not defined, it is equivalent to a null statement.

`void TARGET_ASM_FINAL_POSTSCAN_INSN (FILE *file, rtx insn, rtx *opvec, int noperands)` [Target Hook]

If defined, this target hook is a function which is executed just after the output of assembler code for *insn*, to change the mode of the assembler if necessary.

Here the argument *opvec* is the vector containing the operands extracted from *insn*, and *noperands* is the number of elements of the vector which contain meaningful

data for this insn. The contents of this vector are what was used to convert the insn template into assembler code, so you can change the assembler mode by checking the contents of the vector.

`PRINT_OPERAND (stream, x, code)` [Macro]

A C compound statement to output to stdio stream *stream* the assembler syntax for an instruction operand *x*. *x* is an RTL expression.

code is a value that can be used to specify one of several ways of printing the operand. It is used when identical operands must be printed differently depending on the context. *code* comes from the '`%`' specification that was used to request printing of the operand. If the specification was just '`%digit`' then *code* is 0; if the specification was '`%ltr digit`' then *code* is the ASCII code for *ltr*.

If *x* is a register, this macro should print the register's name. The names can be found in an array `reg_names` whose type is `char *[]`. `reg_names` is initialized from `REGISTER_NAMES`.

When the machine description has a specification '`%punct`' (a '`%`' followed by a punctuation character), this macro is called with a null pointer for *x* and the punctuation character for *code*.

`PRINT_OPERAND_PUNCT_VALID_P (code)` [Macro]

A C expression which evaluates to true if *code* is a valid punctuation character for use in the `PRINT_OPERAND` macro. If `PRINT_OPERAND_PUNCT_VALID_P` is not defined, it means that no punctuation characters (except for the standard one, '`%`') are used in this way.

`PRINT_OPERAND_ADDRESS (stream, x)` [Macro]

A C compound statement to output to stdio stream *stream* the assembler syntax for an instruction operand that is a memory reference whose address is *x*. *x* is an RTL expression.

On some machines, the syntax for a symbolic address depends on the section that the address refers to. On these machines, define the hook `TARGET_ENCODE_SECTION_INFO` to store the information into the `symbol_ref`, and then check for it here. See Section 17.21 [Assembler Format], page 527.

`DBR_OUTPUT_SEQEND (file)` [Macro]

A C statement, to be executed after all slot-filler instructions have been output. If necessary, call `dbr_sequence_length` to determine the number of slots filled in a sequence (zero if not currently outputting a sequence), to decide how many no-ops to output, or whatever.

Don't define this macro if it has nothing to do, but it is helpful in reading assembly output if the extent of the delay sequence is made explicit (e.g. with white space).

Note that output routines for instructions with delay slots must be prepared to deal with not being output as part of a sequence (i.e. when the scheduling pass is not run, or when no slot fillers could be found.) The variable `final_sequence` is null when not processing a sequence, otherwise it contains the `sequence` rtx being output.

`REGISTER_PREFIX` [Macro]
`LOCAL_LABEL_PREFIX` [Macro]
`USER_LABEL_PREFIX` [Macro]
`IMMEDIATE_PREFIX` [Macro]

If defined, C string expressions to be used for the '`%R`', '`%L`', '`%U`', and '`%I`' options of `asm_fprintf` (see '`final.c`'). These are useful when a single '`md`' file must support multiple assembler formats. In that case, the various '`tm.h`' files can define these macros differently.

`ASM_FPRINTF_EXTENSIONS` (*file*, *argptr*, *format*) [Macro]

If defined this macro should expand to a series of `case` statements which will be parsed inside the `switch` statement of the `asm_fprintf` function. This allows targets to define extra printf formats which may useful when generating their assembler statements. Note that uppercase letters are reserved for future generic extensions to asm_fprintf, and so are not available to target specific code. The output file is given by the parameter *file*. The varargs input pointer is *argptr* and the rest of the format string, starting the character after the one that is being switched upon, is pointed to by *format*.

`ASSEMBLER_DIALECT` [Macro]

If your target supports multiple dialects of assembler language (such as different opcodes), define this macro as a C expression that gives the numeric index of the assembler language dialect to use, with zero as the first variant.

If this macro is defined, you may use constructs of the form

```
'{option0|option1|option2...}'
```

in the output templates of patterns (see Section 16.5 [Output Template], page 303) or in the first argument of `asm_fprintf`. This construct outputs '`option0`', '`option1`', '`option2`', etc., if the value of `ASSEMBLER_DIALECT` is zero, one, two, etc. Any special characters within these strings retain their usual meaning. If there are fewer alternatives within the braces than the value of `ASSEMBLER_DIALECT`, the construct outputs nothing. If it's needed to print curly braces or '`|`' character in assembler output directly, '`%{`', '`%}`' and '`%|`' can be used.

If you do not define this macro, the characters '`{`', '`|`' and '`}`' do not have any special meaning when used in templates or operands to `asm_fprintf`.

Define the macros `REGISTER_PREFIX`, `LOCAL_LABEL_PREFIX`, `USER_LABEL_PREFIX` and `IMMEDIATE_PREFIX` if you can express the variations in assembler language syntax with that mechanism. Define `ASSEMBLER_DIALECT` and use the '`{option0|option1}`' syntax if the syntax variant are larger and involve such things as different opcodes or operand order.

`ASM_OUTPUT_REG_PUSH` (*stream*, *regno*) [Macro]

A C expression to output to *stream* some assembler code which will push hard register number *regno* onto the stack. The code need not be optimal, since this macro is used only when profiling.

`ASM_OUTPUT_REG_POP` (*stream*, *regno*) [Macro]

A C expression to output to *stream* some assembler code which will pop hard register number *regno* off of the stack. The code need not be optimal, since this macro is used only when profiling.

17.21.8 Output of Dispatch Tables

This concerns dispatch tables.

`ASM_OUTPUT_ADDR_DIFF_ELT` (*stream*, *body*, *value*, *rel*) [Macro]

A C statement to output to the stdio stream *stream* an assembler pseudo-instruction to generate a difference between two labels. *value* and *rel* are the numbers of two internal labels. The definitions of these labels are output using `(*targetm.asm_out.internal_label)`, and they must be printed in the same way here. For example,

```
fprintf (stream, "\t.word L%d-L%d\n",
         value, rel)
```

You must provide this macro on machines where the addresses in a dispatch table are relative to the table's own address. If defined, GCC will also use this macro on all machines when producing PIC. *body* is the body of the `ADDR_DIFF_VEC`; it is provided so that the mode and flags can be read.

`ASM_OUTPUT_ADDR_VEC_ELT` (*stream*, *value*) [Macro]

This macro should be provided on machines where the addresses in a dispatch table are absolute.

The definition should be a C statement to output to the stdio stream *stream* an assembler pseudo-instruction to generate a reference to a label. *value* is the number of an internal label whose definition is output using `(*targetm.asm_out.internal_label)`. For example,

```
fprintf (stream, "\t.word L%d\n", value)
```

`ASM_OUTPUT_CASE_LABEL` (*stream*, *prefix*, *num*, *table*) [Macro]

Define this if the label before a jump-table needs to be output specially. The first three arguments are the same as for `(*targetm.asm_out.internal_label)`; the fourth argument is the jump-table which follows (a `jump_table_data` containing an `addr_vec` or `addr_diff_vec`).

This feature is used on system V to output a `swbeg` statement for the table.

If this macro is not defined, these labels are output with `(*targetm.asm_out.internal_label)`.

`ASM_OUTPUT_CASE_END` (*stream*, *num*, *table*) [Macro]

Define this if something special must be output at the end of a jump-table. The definition should be a C statement to be executed after the assembler code for the table is written. It should write the appropriate code to stdio stream *stream*. The argument *table* is the jump-table insn, and *num* is the label-number of the preceding label.

If this macro is not defined, nothing special is output at the end of the jump-table.

void TARGET_ASM_EMIT_UNWIND_LABEL (*FILE* *stream, *tree* decl, *int* for_eh, *int* empty) [Target Hook]

This target hook emits a label at the beginning of each FDE. It should be defined on targets where FDEs need special labels, and it should write the appropriate label, for the FDE associated with the function declaration *decl*, to the stdio stream *stream*. The third argument, *for_eh*, is a boolean: true if this is for an exception table. The fourth argument, *empty*, is a boolean: true if this is a placeholder label for an omitted FDE.

The default is that FDEs are not given nonlocal labels.

void TARGET_ASM_EMIT_EXCEPT_TABLE_LABEL (*FILE* *stream) [Target Hook]

This target hook emits a label at the beginning of the exception table. It should be defined on targets where it is desirable for the table to be broken up according to function.

The default is that no label is emitted.

void TARGET_ASM_EMIT_EXCEPT_PERSONALITY (*rtx* personality) [Target Hook]

If the target implements TARGET_ASM_UNWIND_EMIT, this hook may be used to emit a directive to install a personality hook into the unwind info. This hook should not be used if dwarf2 unwind info is used.

void TARGET_ASM_UNWIND_EMIT (*FILE* *stream, *rtx* insn) [Target Hook]

This target hook emits assembly directives required to unwind the given instruction. This is only used when TARGET_EXCEPT_UNWIND_INFO returns UI_TARGET.

bool TARGET_ASM_UNWIND_EMIT_BEFORE_INSN [Target Hook]

True if the TARGET_ASM_UNWIND_EMIT hook should be called before the assembly for *insn* has been emitted, false if the hook should be called afterward.

17.21.9 Assembler Commands for Exception Regions

This describes commands marking the start and the end of an exception region.

EH_FRAME_SECTION_NAME [Macro]

If defined, a C string constant for the name of the section containing exception handling frame unwind information. If not defined, GCC will provide a default definition if the target supports named sections. 'crtstuff.c' uses this macro to switch to the appropriate section.

You should define this symbol if your target supports DWARF 2 frame unwind information and the default definition does not work.

EH_FRAME_IN_DATA_SECTION [Macro]

If defined, DWARF 2 frame unwind information will be placed in the data section even though the target supports named sections. This might be necessary, for instance, if the system linker does garbage collection and sections cannot be marked as not to be collected.

Do not define this macro unless TARGET_ASM_NAMED_SECTION is also defined.

`EH_TABLES_CAN_BE_READ_ONLY` [Macro]

Define this macro to 1 if your target is such that no frame unwind information encoding used with non-PIC code will ever require a runtime relocation, but the linker may not support merging read-only and read-write sections into a single read-write section.

`MASK_RETURN_ADDR` [Macro]

An rtx used to mask the return address found via `RETURN_ADDR_RTX`, so that it does not contain any extraneous set bits in it.

`DWARF2_UNWIND_INFO` [Macro]

Define this macro to 0 if your target supports DWARF 2 frame unwind information, but it does not yet work with exception handling. Otherwise, if your target supports this information (if it defines `INCOMING_RETURN_ADDR_RTX` and `OBJECT_FORMAT_ELF`), GCC will provide a default definition of 1.

`enum unwind_info_type TARGET_EXCEPT_UNWIND_INFO` [Common Target Hook]
(*struct gcc_options* ***opts**)

This hook defines the mechanism that will be used for exception handling by the target. If the target has ABI specified unwind tables, the hook should return `UI_TARGET`. If the target is to use the `setjmp/longjmp`-based exception handling scheme, the hook should return `UI_SJLJ`. If the target supports DWARF 2 frame unwind information, the hook should return `UI_DWARF2`.

A target may, if exceptions are disabled, choose to return `UI_NONE`. This may end up simplifying other parts of target-specific code. The default implementation of this hook never returns `UI_NONE`.

Note that the value returned by this hook should be constant. It should not depend on anything except the command-line switches described by *opts*. In particular, the setting `UI_SJLJ` must be fixed at compiler start-up as C pre-processor macros and builtin functions related to exception handling are set up depending on this setting.

The default implementation of the hook first honors the '`--enable-sjlj-exceptions`' configure option, then `DWARF2_UNWIND_INFO`, and finally defaults to `UI_SJLJ`. If `DWARF2_UNWIND_INFO` depends on command-line options, the target must define this hook so that *opts* is used correctly.

`bool TARGET_UNWIND_TABLES_DEFAULT` [Common Target Hook]

This variable should be set to `true` if the target ABI requires unwinding tables even when exceptions are not used. It must not be modified by command-line option processing.

`DONT_USE_BUILTIN_SETJMP` [Macro]

Define this macro to 1 if the `setjmp/longjmp`-based scheme should use the `setjmp/longjmp` functions from the C library instead of the `__builtin_setjmp/__builtin_longjmp` machinery.

`JMP_BUF_SIZE` [Macro]

This macro has no effect unless `DONT_USE_BUILTIN_SETJMP` is also defined. Define this macro if the default size of `jmp_buf` buffer for the `setjmp/longjmp`-based exception

handling mechanism is not large enough, or if it is much too large. The default size is `FIRST_PSEUDO_REGISTER * sizeof(void *)`.

`DWARF_CIE_DATA_ALIGNMENT` [Macro]

This macro need only be defined if the target might save registers in the function prologue at an offset to the stack pointer that is not aligned to `UNITS_PER_WORD`. The definition should be the negative minimum alignment if `STACK_GROWS_DOWNWARD` is defined, and the positive minimum alignment otherwise. See Section 17.22.5 [SDB and DWARF], page 559. Only applicable if the target supports DWARF 2 frame unwind information.

`bool TARGET_TERMINATE_DW2_EH_FRAME_INFO` [Target Hook]

Contains the value true if the target should add a zero word onto the end of a Dwarf-2 frame info section when used for exception handling. Default value is false if `EH_FRAME_SECTION_NAME` is defined, and true otherwise.

`rtx TARGET_DWARF_REGISTER_SPAN` (*rtx* ***reg***) [Target Hook]

Given a register, this hook should return a parallel of registers to represent where to find the register pieces. Define this hook if the register and its mode are represented in Dwarf in non-contiguous locations, or if the register should be represented in more than one register in Dwarf. Otherwise, this hook should return `NULL_RTX`. If not defined, the default is to return `NULL_RTX`.

`void TARGET_INIT_DWARF_REG_SIZES_EXTRA` (*tree* ***address***) [Target Hook]

If some registers are represented in Dwarf-2 unwind information in multiple pieces, define this hook to fill in information about the sizes of those pieces in the table used by the unwinder at runtime. It will be called by `expand_builtin_init_dwarf_reg_sizes` after filling in a single size corresponding to each hard register; *address* is the address of the table.

`bool TARGET_ASM_TTYPE` (*rtx* ***sym***) [Target Hook]

This hook is used to output a reference from a frame unwinding table to the type_info object identified by *sym*. It should return `true` if the reference was output. Returning `false` will cause the reference to be output using the normal Dwarf2 routines.

`bool TARGET_ARM_EABI_UNWINDER` [Target Hook]

This flag should be set to `true` on targets that use an ARM EABI based unwinding library, and `false` on other targets. This effects the format of unwinding tables, and how the unwinder in entered after running a cleanup. The default is `false`.

17.21.10 Assembler Commands for Alignment

This describes commands for alignment.

`JUMP_ALIGN` (*label*) [Macro]

The alignment (log base 2) to put in front of *label*, which is a common destination of jumps and has no fallthru incoming edge.

This macro need not be defined if you don't want any special alignment to be done at such a time. Most machine descriptions do not currently define the macro.

Unless it's necessary to inspect the *label* parameter, it is better to set the variable *align_jumps* in the target's `TARGET_OPTION_OVERRIDE`. Otherwise, you should try to honor the user's selection in *align_jumps* in a `JUMP_ALIGN` implementation.

`int TARGET_ASM_JUMP_ALIGN_MAX_SKIP (rtx label)` [Target Hook]

The maximum number of bytes to skip before *label* when applying `JUMP_ALIGN`. This works only if `ASM_OUTPUT_MAX_SKIP_ALIGN` is defined.

`LABEL_ALIGN_AFTER_BARRIER (label)` [Macro]

The alignment (log base 2) to put in front of *label*, which follows a `BARRIER`.

This macro need not be defined if you don't want any special alignment to be done at such a time. Most machine descriptions do not currently define the macro.

`int TARGET_ASM_LABEL_ALIGN_AFTER_BARRIER_MAX_SKIP (rtx label)` [Target Hook]

The maximum number of bytes to skip before *label* when applying `LABEL_ALIGN_AFTER_BARRIER`. This works only if `ASM_OUTPUT_MAX_SKIP_ALIGN` is defined.

`LOOP_ALIGN (label)` [Macro]

The alignment (log base 2) to put in front of *label* that heads a frequently executed basic block (usually the header of a loop).

This macro need not be defined if you don't want any special alignment to be done at such a time. Most machine descriptions do not currently define the macro.

Unless it's necessary to inspect the *label* parameter, it is better to set the variable `align_loops` in the target's `TARGET_OPTION_OVERRIDE`. Otherwise, you should try to honor the user's selection in `align_loops` in a `LOOP_ALIGN` implementation.

`int TARGET_ASM_LOOP_ALIGN_MAX_SKIP (rtx label)` [Target Hook]

The maximum number of bytes to skip when applying `LOOP_ALIGN` to *label*. This works only if `ASM_OUTPUT_MAX_SKIP_ALIGN` is defined.

`LABEL_ALIGN (label)` [Macro]

The alignment (log base 2) to put in front of *label*. If `LABEL_ALIGN_AFTER_BARRIER` / `LOOP_ALIGN` specify a different alignment, the maximum of the specified values is used.

Unless it's necessary to inspect the *label* parameter, it is better to set the variable `align_labels` in the target's `TARGET_OPTION_OVERRIDE`. Otherwise, you should try to honor the user's selection in `align_labels` in a `LABEL_ALIGN` implementation.

`int TARGET_ASM_LABEL_ALIGN_MAX_SKIP (rtx label)` [Target Hook]

The maximum number of bytes to skip when applying `LABEL_ALIGN` to *label*. This works only if `ASM_OUTPUT_MAX_SKIP_ALIGN` is defined.

`ASM_OUTPUT_SKIP (stream, nbytes)` [Macro]

A C statement to output to the stdio stream *stream* an assembler instruction to advance the location counter by *nbytes* bytes. Those bytes should be zero when loaded. *nbytes* will be a C expression of type `unsigned HOST_WIDE_INT`.

`ASM_NO_SKIP_IN_TEXT` [Macro]

Define this macro if `ASM_OUTPUT_SKIP` should not be used in the text section because it fails to put zeros in the bytes that are skipped. This is true on many Unix systems, where the pseudo–op to skip bytes produces no-op instructions rather than zeros when used in the text section.

`ASM_OUTPUT_ALIGN (stream, power)` [Macro]

A C statement to output to the stdio stream *stream* an assembler command to advance the location counter to a multiple of 2 to the *power* bytes. *power* will be a C expression of type `int`.

`ASM_OUTPUT_ALIGN_WITH_NOP (stream, power)` [Macro]

Like `ASM_OUTPUT_ALIGN`, except that the "nop" instruction is used for padding, if necessary.

`ASM_OUTPUT_MAX_SKIP_ALIGN (stream, power, max_skip)` [Macro]

A C statement to output to the stdio stream *stream* an assembler command to advance the location counter to a multiple of 2 to the *power* bytes, but only if *max_skip* or fewer bytes are needed to satisfy the alignment request. *power* and *max_skip* will be a C expression of type `int`.

17.22 Controlling Debugging Information Format

This describes how to specify debugging information.

17.22.1 Macros Affecting All Debugging Formats

These macros affect all debugging formats.

`DBX_REGISTER_NUMBER (regno)` [Macro]

A C expression that returns the DBX register number for the compiler register number *regno*. In the default macro provided, the value of this expression will be *regno* itself. But sometimes there are some registers that the compiler knows about and DBX does not, or vice versa. In such cases, some register may need to have one number in the compiler and another for DBX.

If two registers have consecutive numbers inside GCC, and they can be used as a pair to hold a multiword value, then they *must* have consecutive numbers after renumbering with `DBX_REGISTER_NUMBER`. Otherwise, debuggers will be unable to access such a pair, because they expect register pairs to be consecutive in their own numbering scheme.

If you find yourself defining `DBX_REGISTER_NUMBER` in way that does not preserve register pairs, then what you must do instead is redefine the actual register numbering scheme.

`DEBUGGER_AUTO_OFFSET (x)` [Macro]

A C expression that returns the integer offset value for an automatic variable having address *x* (an RTL expression). The default computation assumes that *x* is based on the frame-pointer and gives the offset from the frame-pointer. This is required for targets that produce debugging output for DBX or COFF-style debugging output for SDB and allow the frame-pointer to be eliminated when the '`-g`' options is used.

DEBUGGER_ARG_OFFSET (*offset*, *x*) [Macro]

A C expression that returns the integer offset value for an argument having address *x* (an RTL expression). The nominal offset is *offset*.

PREFERRED_DEBUGGING_TYPE [Macro]

A C expression that returns the type of debugging output GCC should produce when the user specifies just '-g'. Define this if you have arranged for GCC to support more than one format of debugging output. Currently, the allowable values are DBX_DEBUG, SDB_DEBUG, DWARF_DEBUG, DWARF2_DEBUG, XCOFF_DEBUG, VMS_DEBUG, and VMS_AND_DWARF2_DEBUG.

When the user specifies '-ggdb', GCC normally also uses the value of this macro to select the debugging output format, but with two exceptions. If DWARF2_DEBUGGING_INFO is defined, GCC uses the value DWARF2_DEBUG. Otherwise, if DBX_DEBUGGING_INFO is defined, GCC uses DBX_DEBUG.

The value of this macro only affects the default debugging output; the user can always get a specific type of output by using '-gstabs', '-gcoff', '-gdwarf-2', '-gxcoff', or '-gvms'.

17.22.2 Specific Options for DBX Output

These are specific options for DBX output.

DBX_DEBUGGING_INFO [Macro]

Define this macro if GCC should produce debugging output for DBX in response to the '-g' option.

XCOFF_DEBUGGING_INFO [Macro]

Define this macro if GCC should produce XCOFF format debugging output in response to the '-g' option. This is a variant of DBX format.

DEFAULT_GDB_EXTENSIONS [Macro]

Define this macro to control whether GCC should by default generate GDB's extended version of DBX debugging information (assuming DBX-format debugging information is enabled at all). If you don't define the macro, the default is 1: always generate the extended information if there is any occasion to.

DEBUG_SYMS_TEXT [Macro]

Define this macro if all .stabs commands should be output while in the text section.

ASM_STABS_OP [Macro]

A C string constant, including spacing, naming the assembler pseudo op to use instead of "\t.stabs\t" to define an ordinary debugging symbol. If you don't define this macro, "\t.stabs\t" is used. This macro applies only to DBX debugging information format.

ASM_STABD_OP [Macro]

A C string constant, including spacing, naming the assembler pseudo op to use instead of "\t.stabd\t" to define a debugging symbol whose value is the current location. If you don't define this macro, "\t.stabd\t" is used. This macro applies only to DBX debugging information format.

`ASM_STABN_OP` [Macro]

A C string constant, including spacing, naming the assembler pseudo op to use instead of `"\t.stabn\t"` to define a debugging symbol with no name. If you don't define this macro, `"\t.stabn\t"` is used. This macro applies only to DBX debugging information format.

`DBX_NO_XREFS` [Macro]

Define this macro if DBX on your system does not support the construct '`xs`*tagname*'. On some systems, this construct is used to describe a forward reference to a structure named *tagname*. On other systems, this construct is not supported at all.

`DBX_CONTIN_LENGTH` [Macro]

A symbol name in DBX-format debugging information is normally continued (split into two separate `.stabs` directives) when it exceeds a certain length (by default, 80 characters). On some operating systems, DBX requires this splitting; on others, splitting must not be done. You can inhibit splitting by defining this macro with the value zero. You can override the default splitting-length by defining this macro as an expression for the length you desire.

`DBX_CONTIN_CHAR` [Macro]

Normally continuation is indicated by adding a '\' character to the end of a `.stabs` string when a continuation follows. To use a different character instead, define this macro as a character constant for the character you want to use. Do not define this macro if backslash is correct for your system.

`DBX_STATIC_STAB_DATA_SECTION` [Macro]

Define this macro if it is necessary to go to the data section before outputting the '`.stabs`' pseudo-op for a non-global static variable.

`DBX_TYPE_DECL_STABS_CODE` [Macro]

The value to use in the "code" field of the `.stabs` directive for a typedef. The default is `N_LSYM`.

`DBX_STATIC_CONST_VAR_CODE` [Macro]

The value to use in the "code" field of the `.stabs` directive for a static variable located in the text section. DBX format does not provide any "right" way to do this. The default is `N_FUN`.

`DBX_REGPARM_STABS_CODE` [Macro]

The value to use in the "code" field of the `.stabs` directive for a parameter passed in registers. DBX format does not provide any "right" way to do this. The default is `N_RSYM`.

`DBX_REGPARM_STABS_LETTER` [Macro]

The letter to use in DBX symbol data to identify a symbol as a parameter passed in registers. DBX format does not customarily provide any way to do this. The default is `'P'`.

`DBX_FUNCTION_FIRST` [Macro]

Define this macro if the DBX information for a function and its arguments should precede the assembler code for the function. Normally, in DBX format, the debugging information entirely follows the assembler code.

`DBX_BLOCKS_FUNCTION_RELATIVE` [Macro]

Define this macro, with value 1, if the value of a symbol describing the scope of a block (`N_LBRAC` or `N_RBRAC`) should be relative to the start of the enclosing function. Normally, GCC uses an absolute address.

`DBX_LINES_FUNCTION_RELATIVE` [Macro]

Define this macro, with value 1, if the value of a symbol indicating the current line number (`N_SLINE`) should be relative to the start of the enclosing function. Normally, GCC uses an absolute address.

`DBX_USE_BINCL` [Macro]

Define this macro if GCC should generate `N_BINCL` and `N_EINCL` stabs for included header files, as on Sun systems. This macro also directs GCC to output a type number as a pair of a file number and a type number within the file. Normally, GCC does not generate `N_BINCL` or `N_EINCL` stabs, and it outputs a single number for a type number.

17.22.3 Open-Ended Hooks for DBX Format

These are hooks for DBX format.

`DBX_OUTPUT_SOURCE_LINE` (*stream*, *line*, *counter*) [Macro]

A C statement to output DBX debugging information before code for line number *line* of the current source file to the stdio stream *stream*. *counter* is the number of time the macro was invoked, including the current invocation; it is intended to generate unique labels in the assembly output.

This macro should not be defined if the default output is correct, or if it can be made correct by defining `DBX_LINES_FUNCTION_RELATIVE`.

`NO_DBX_FUNCTION_END` [Macro]

Some stabs encapsulation formats (in particular ECOFF), cannot handle the `.stabs "",N_FUN,,0,0,Lscope-function-1` gdb dbx extension construct. On those machines, define this macro to turn this feature off without disturbing the rest of the gdb extensions.

`NO_DBX_BNSYM_ENSYM` [Macro]

Some assemblers cannot handle the `.stabd BNSYM/ENSYM,0,0` gdb dbx extension construct. On those machines, define this macro to turn this feature off without disturbing the rest of the gdb extensions.

17.22.4 File Names in DBX Format

This describes file names in DBX format.

`DBX_OUTPUT_MAIN_SOURCE_FILENAME` (*stream*, *name*) [Macro]

A C statement to output DBX debugging information to the stdio stream *stream*, which indicates that file *name* is the main source file—the file specified as the input file for compilation. This macro is called only once, at the beginning of compilation.

This macro need not be defined if the standard form of output for DBX debugging information is appropriate.

It may be necessary to refer to a label equal to the beginning of the text section. You can use '`assemble_name (stream, ltext_label_name)`' to do so. If you do this, you must also set the variable *used_ltext_label_name* to `true`.

`NO_DBX_MAIN_SOURCE_DIRECTORY` [Macro]

Define this macro, with value 1, if GCC should not emit an indication of the current directory for compilation and current source language at the beginning of the file.

`NO_DBX_GCC_MARKER` [Macro]

Define this macro, with value 1, if GCC should not emit an indication that this object file was compiled by GCC. The default is to emit an `N_OPT` stab at the beginning of every source file, with '`gcc2_compiled.`' for the string and value 0.

`DBX_OUTPUT_MAIN_SOURCE_FILE_END` (*stream*, *name*) [Macro]

A C statement to output DBX debugging information at the end of compilation of the main source file *name*. Output should be written to the stdio stream *stream*.

If you don't define this macro, nothing special is output at the end of compilation, which is correct for most machines.

`DBX_OUTPUT_NULL_N_SO_AT_MAIN_SOURCE_FILE_END` [Macro]

Define this macro *instead of* defining `DBX_OUTPUT_MAIN_SOURCE_FILE_END`, if what needs to be output at the end of compilation is an `N_SO` stab with an empty string, whose value is the highest absolute text address in the file.

17.22.5 Macros for SDB and DWARF Output

Here are macros for SDB and DWARF output.

`SDB_DEBUGGING_INFO` [Macro]

Define this macro if GCC should produce COFF-style debugging output for SDB in response to the '`-g`' option.

`DWARF2_DEBUGGING_INFO` [Macro]

Define this macro if GCC should produce dwarf version 2 format debugging output in response to the '`-g`' option.

`int TARGET_DWARF_CALLING_CONVENTION` (*const_tree function*) [Target Hook]

Define this to enable the dwarf attribute `DW_AT_calling_convention` to be emitted for each function. Instead of an integer return the enum value for the `DW_CC_` tag.

To support optional call frame debugging information, you must also define `INCOMING_RETURN_ADDR_RTX` and either set `RTX_FRAME_RELATED_P` on the prologue insns if you use RTL for the prologue, or call `dwarf2out_def_cfa` and `dwarf2out_reg_save` as appropriate from `TARGET_ASM_FUNCTION_PROLOGUE` if you don't.

`DWARF2_FRAME_INFO` [Macro]

Define this macro to a nonzero value if GCC should always output Dwarf 2 frame information. If `TARGET_EXCEPT_UNWIND_INFO` (see Section 17.21.9 [Exception Region Output], page 551) returns `UI_DWARF2`, and exceptions are enabled, GCC will output this information not matter how you define `DWARF2_FRAME_INFO`.

`enum unwind_info_type TARGET_DEBUG_UNWIND_INFO` (*void*) [Target Hook]

This hook defines the mechanism that will be used for describing frame unwind information to the debugger. Normally the hook will return `UI_DWARF2` if DWARF 2 debug information is enabled, and return `UI_NONE` otherwise.

A target may return `UI_DWARF2` even when DWARF 2 debug information is disabled in order to always output DWARF 2 frame information.

A target may return `UI_TARGET` if it has ABI specified unwind tables. This will suppress generation of the normal debug frame unwind information.

`DWARF2_ASM_LINE_DEBUG_INFO` [Macro]

Define this macro to be a nonzero value if the assembler can generate Dwarf 2 line debug info sections. This will result in much more compact line number tables, and hence is desirable if it works.

`bool TARGET_WANT_DEBUG_PUB_SECTIONS` [Target Hook]

True if the `.debug_pubtypes` and `.debug_pubnames` sections should be emitted. These sections are not used on most platforms, and in particular GDB does not use them.

`bool TARGET_FORCE_AT_COMP_DIR` [Target Hook]

True if the `DW_AT_comp_dir` attribute should be emitted for each compilation unit. This attribute is required for the darwin linker to emit debug information.

`bool TARGET_DELAY_SCHED2` [Target Hook]

True if sched2 is not to be run at its normal place. This usually means it will be run as part of machine-specific reorg.

`bool TARGET_DELAY_VARTRACK` [Target Hook]

True if vartrack is not to be run at its normal place. This usually means it will be run as part of machine-specific reorg.

`ASM_OUTPUT_DWARF_DELTA` (*stream*, *size*, *label1*, *label2*) [Macro]

A C statement to issue assembly directives that create a difference *lab1* minus *lab2*, using an integer of the given *size*.

`ASM_OUTPUT_DWARF_VMS_DELTA` (*stream*, *size*, *label1*, *label2*) [Macro]

A C statement to issue assembly directives that create a difference between the two given labels in system defined units, e.g. instruction slots on IA64 VMS, using an integer of the given size.

`ASM_OUTPUT_DWARF_OFFSET` (*stream*, *size*, *label*, *section*) [Macro]

A C statement to issue assembly directives that create a section-relative reference to the given *label*, using an integer of the given *size*. The label is known to be defined in the given *section*.

`ASM_OUTPUT_DWARF_PCREL` (*stream*, *size*, *label*) [Macro]

A C statement to issue assembly directives that create a self-relative reference to the given *label*, using an integer of the given *size*.

`ASM_OUTPUT_DWARF_TABLE_REF` (*label*) [Macro]

A C statement to issue assembly directives that create a reference to the DWARF table identifier *label* from the current section. This is used on some systems to avoid garbage collecting a DWARF table which is referenced by a function.

`void TARGET_ASM_OUTPUT_DWARF_DTPREL` (*FILE *file*, *int size*, *rtx x*) [Target Hook]

If defined, this target hook is a function which outputs a DTP-relative reference to the given TLS symbol of the specified size.

`PUT_SDB_...` [Macro]

Define these macros to override the assembler syntax for the special SDB assembler directives. See '`sdbout.c`' for a list of these macros and their arguments. If the standard syntax is used, you need not define them yourself.

`SDB_DELIM` [Macro]

Some assemblers do not support a semicolon as a delimiter, even between SDB assembler directives. In that case, define this macro to be the delimiter to use (usually '`\n`'). It is not necessary to define a new set of `PUT_SDB_op` macros if this is the only change required.

`SDB_ALLOW_UNKNOWN_REFERENCES` [Macro]

Define this macro to allow references to unknown structure, union, or enumeration tags to be emitted. Standard COFF does not allow handling of unknown references, MIPS ECOFF has support for it.

`SDB_ALLOW_FORWARD_REFERENCES` [Macro]

Define this macro to allow references to structure, union, or enumeration tags that have not yet been seen to be handled. Some assemblers choke if forward tags are used, while some require it.

`SDB_OUTPUT_SOURCE_LINE` (*stream*, *line*) [Macro]

A C statement to output SDB debugging information before code for line number *line* of the current source file to the stdio stream *stream*. The default is to emit an `.ln` directive.

17.22.6 Macros for VMS Debug Format

Here are macros for VMS debug format.

`VMS_DEBUGGING_INFO` [Macro]

Define this macro if GCC should produce debugging output for VMS in response to the '`-g`' option. The default behavior for VMS is to generate minimal debug info for a traceback in the absence of '`-g`' unless explicitly overridden with '`-g0`'. This behavior is controlled by `TARGET_OPTION_OPTIMIZATION` and `TARGET_OPTION_OVERRIDE`.

17.23 Cross Compilation and Floating Point

While all modern machines use twos-complement representation for integers, there are a variety of representations for floating point numbers. This means that in a cross-compiler the representation of floating point numbers in the compiled program may be different from that used in the machine doing the compilation.

Because different representation systems may offer different amounts of range and precision, all floating point constants must be represented in the target machine's format. Therefore, the cross compiler cannot safely use the host machine's floating point arithmetic; it must emulate the target's arithmetic. To ensure consistency, GCC always uses emulation to work with floating point values, even when the host and target floating point formats are identical.

The following macros are provided by '`real.h`' for the compiler to use. All parts of the compiler which generate or optimize floating-point calculations must use these macros. They may evaluate their operands more than once, so operands must not have side effects.

`REAL_VALUE_TYPE` [Macro]

The C data type to be used to hold a floating point value in the target machine's format. Typically this is a `struct` containing an array of `HOST_WIDE_INT`, but all code should treat it as an opaque quantity.

`int REAL_VALUES_EQUAL (`*REAL_VALUE_TYPE* `x`, *REAL_VALUE_TYPE* `y)` [Macro]

Compares for equality the two values, x and y. If the target floating point format supports negative zeroes and/or NaNs, '`REAL_VALUES_EQUAL (-0.0, 0.0)`' is true, and '`REAL_VALUES_EQUAL (NaN, NaN)`' is false.

`int REAL_VALUES_LESS (`*REAL_VALUE_TYPE* `x`, *REAL_VALUE_TYPE* `y)` [Macro]

Tests whether x is less than y.

`HOST_WIDE_INT REAL_VALUE_FIX (`*REAL_VALUE_TYPE* `x)` [Macro]

Truncates x to a signed integer, rounding toward zero.

`unsigned HOST_WIDE_INT REAL_VALUE_UNSIGNED_FIX (`*REAL_VALUE_TYPE* `x)` [Macro]

Truncates x to an unsigned integer, rounding toward zero. If x is negative, returns zero.

`REAL_VALUE_TYPE REAL_VALUE_ATOF` (*const char* ***string***, *enum machine_mode* ***mode***) [Macro]

Converts *string* into a floating point number in the target machine's representation for mode *mode*. This routine can handle both decimal and hexadecimal floating point constants, using the syntax defined by the C language for both.

`int REAL_VALUE_NEGATIVE` (*REAL_VALUE_TYPE* ***x***) [Macro]

Returns 1 if *x* is negative (including negative zero), 0 otherwise.

`int REAL_VALUE_ISINF` (*REAL_VALUE_TYPE* ***x***) [Macro]

Determines whether *x* represents infinity (positive or negative).

`int REAL_VALUE_ISNAN` (*REAL_VALUE_TYPE* ***x***) [Macro]

Determines whether *x* represents a "NaN" (not-a-number).

`void REAL_ARITHMETIC` (*REAL_VALUE_TYPE* ***output***, *enum tree_code* ***code***, *REAL_VALUE_TYPE* ***x***, *REAL_VALUE_TYPE* ***y***) [Macro]

Calculates an arithmetic operation on the two floating point values *x* and *y*, storing the result in *output* (which must be a variable).

The operation to be performed is specified by *code*. Only the following codes are supported: `PLUS_EXPR`, `MINUS_EXPR`, `MULT_EXPR`, `RDIV_EXPR`, `MAX_EXPR`, `MIN_EXPR`.

If `REAL_ARITHMETIC` is asked to evaluate division by zero and the target's floating point format cannot represent infinity, it will call `abort`. Callers should check for this situation first, using `MODE_HAS_INFINITIES`. See Section 17.5 [Storage Layout], page 432.

`REAL_VALUE_TYPE REAL_VALUE_NEGATE` (*REAL_VALUE_TYPE* ***x***) [Macro]

Returns the negative of the floating point value *x*.

`REAL_VALUE_TYPE REAL_VALUE_ABS` (*REAL_VALUE_TYPE* ***x***) [Macro]

Returns the absolute value of *x*.

`void REAL_VALUE_TO_INT` (*HOST_WIDE_INT* ***low***, *HOST_WIDE_INT* ***high***, *REAL_VALUE_TYPE* ***x***) [Macro]

Converts a floating point value *x* into a double-precision integer which is then stored into *low* and *high*. If the value is not integral, it is truncated.

`void REAL_VALUE_FROM_INT` (*REAL_VALUE_TYPE* ***x***, *HOST_WIDE_INT* ***low***, *HOST_WIDE_INT* ***high***, *enum machine_mode* ***mode***) [Macro]

Converts a double-precision integer found in *low* and *high*, into a floating point value which is then stored into *x*. The value is truncated to fit in mode *mode*.

17.24 Mode Switching Instructions

The following macros control mode switching optimizations:

`OPTIMIZE_MODE_SWITCHING` (*entity*) [Macro]

Define this macro if the port needs extra instructions inserted for mode switching in an optimizing compilation.

For an example, the SH4 can perform both single and double precision floating point operations, but to perform a single precision operation, the FPSCR PR bit has to be cleared, while for a double precision operation, this bit has to be set. Changing the PR bit requires a general purpose register as a scratch register, hence these FPSCR sets have to be inserted before reload, i.e. you can't put this into instruction emitting or `TARGET_MACHINE_DEPENDENT_REORG`.

You can have multiple entities that are mode-switched, and select at run time which entities actually need it. `OPTIMIZE_MODE_SWITCHING` should return nonzero for any *entity* that needs mode-switching. If you define this macro, you also have to define `NUM_MODES_FOR_MODE_SWITCHING`, `MODE_NEEDED`, `MODE_PRIORITY_TO_MODE` and `EMIT_MODE_SET`. `MODE_AFTER`, `MODE_ENTRY`, and `MODE_EXIT` are optional.

`NUM_MODES_FOR_MODE_SWITCHING` [Macro]

If you define `OPTIMIZE_MODE_SWITCHING`, you have to define this as initializer for an array of integers. Each initializer element N refers to an entity that needs mode switching, and specifies the number of different modes that might need to be set for this entity. The position of the initializer in the initializer—starting counting at zero—determines the integer that is used to refer to the mode-switched entity in question. In macros that take mode arguments / yield a mode result, modes are represented as numbers 0 ... N − 1. N is used to specify that no mode switch is needed / supplied.

`MODE_NEEDED` (*entity*, *insn*) [Macro]

entity is an integer specifying a mode-switched entity. If `OPTIMIZE_MODE_SWITCHING` is defined, you must define this macro to return an integer value not larger than the corresponding element in `NUM_MODES_FOR_MODE_SWITCHING`, to denote the mode that *entity* must be switched into prior to the execution of *insn*.

`MODE_AFTER` (*entity*, *mode*, *insn*) [Macro]

entity is an integer specifying a mode-switched entity. If this macro is defined, it is evaluated for every *insn* during mode switching. It determines the mode that an insn results in (if different from the incoming mode).

`MODE_ENTRY` (*entity*) [Macro]

If this macro is defined, it is evaluated for every *entity* that needs mode switching. It should evaluate to an integer, which is a mode that *entity* is assumed to be switched to at function entry. If `MODE_ENTRY` is defined then `MODE_EXIT` must be defined.

`MODE_EXIT` (*entity*) [Macro]

If this macro is defined, it is evaluated for every *entity* that needs mode switching. It should evaluate to an integer, which is a mode that *entity* is assumed to be switched to at function exit. If `MODE_EXIT` is defined then `MODE_ENTRY` must be defined.

`MODE_PRIORITY_TO_MODE` (*entity*, *n*) [Macro]

This macro specifies the order in which modes for *entity* are processed. 0 is the highest priority, `NUM_MODES_FOR_MODE_SWITCHING[`*entity*`] - 1` the lowest. The value of the macro should be an integer designating a mode for *entity*. For any fixed *entity*, `mode_priority_to_mode` (*entity*, *n*) shall be a bijection in 0 ... `num_modes_for_mode_switching[`*entity*`] - 1`.

`EMIT_MODE_SET` (*entity*, *mode*, *hard_regs_live*) [Macro]

Generate one or more insns to set *entity* to *mode*. *hard_reg_live* is the set of hard registers live at the point where the insn(s) are to be inserted. Sets of a lower numbered entity will be emitted before sets of a higher numbered entity to a mode of the same or lower priority.

17.25 Defining target-specific uses of `__attribute__`

Target-specific attributes may be defined for functions, data and types. These are described using the following target hooks; they also need to be documented in '`extend.texi`'.

`const struct attribute_spec * TARGET_ATTRIBUTE_TABLE` [Target Hook]

If defined, this target hook points to an array of '`struct attribute_spec`' (defined in '`tree.h`') specifying the machine specific attributes for this target and some of the restrictions on the entities to which these attributes are applied and the arguments they take.

`bool TARGET_ATTRIBUTE_TAKES_IDENTIFIER_P` (*const_tree* *name*) [Target Hook]

If defined, this target hook is a function which returns true if the machine-specific attribute named *name* expects an identifier given as its first argument to be passed on as a plain identifier, not subjected to name lookup. If this is not defined, the default is false for all machine-specific attributes.

`int TARGET_COMP_TYPE_ATTRIBUTES` (*const_tree* *type1*, *const_tree* *type2*) [Target Hook]

If defined, this target hook is a function which returns zero if the attributes on *type1* and *type2* are incompatible, one if they are compatible, and two if they are nearly compatible (which causes a warning to be generated). If this is not defined, machine-specific attributes are supposed always to be compatible.

`void TARGET_SET_DEFAULT_TYPE_ATTRIBUTES` (*tree* *type*) [Target Hook]

If defined, this target hook is a function which assigns default attributes to the newly defined *type*.

`tree TARGET_MERGE_TYPE_ATTRIBUTES` (*tree* *type1*, *tree* *type2*) [Target Hook]

Define this target hook if the merging of type attributes needs special handling. If defined, the result is a list of the combined `TYPE_ATTRIBUTES` of *type1* and *type2*. It is assumed that `comptypes` has already been called and returned 1. This function may call `merge_attributes` to handle machine-independent merging.

`tree TARGET_MERGE_DECL_ATTRIBUTES` (*tree* *olddecl*, *tree* *newdecl*) [Target Hook]

Define this target hook if the merging of decl attributes needs special handling. If defined, the result is a list of the combined `DECL_ATTRIBUTES` of *olddecl* and *newdecl*. *newdecl* is a duplicate declaration of *olddecl*. Examples of when this is needed are when one attribute overrides another, or when an attribute is nullified by a subsequent definition. This function may call `merge_attributes` to handle machine-independent merging.

If the only target-specific handling you require is '`dllimport`' for Microsoft Windows targets, you should define the macro `TARGET_DLLIMPORT_DECL_ATTRIBUTES` to `1`.

The compiler will then define a function called `merge_dllimport_decl_attributes` which can then be defined as the expansion of `TARGET_MERGE_DECL_ATTRIBUTES`. You can also add `handle_dll_attribute` in the attribute table for your port to perform initial processing of the '`dllimport`' and '`dllexport`' attributes. This is done in '`i386/cygwin.h`' and '`i386/i386.c`', for example.

`bool TARGET_VALID_DLLIMPORT_ATTRIBUTE_P` (*const_tree* ***decl***) [Target Hook]

decl is a variable or function with `__attribute__((dllimport))` specified. Use this hook if the target needs to add extra validation checks to `handle_dll_attribute`.

`TARGET_DECLSPEC` [Macro]

Define this macro to a nonzero value if you want to treat `__declspec(X)` as equivalent to `__attribute((X))`. By default, this behavior is enabled only for targets that define `TARGET_DLLIMPORT_DECL_ATTRIBUTES`. The current implementation of `__declspec` is via a built-in macro, but you should not rely on this implementation detail.

`void TARGET_INSERT_ATTRIBUTES` (*tree* ***node***, *tree* ****attr_ptr***) [Target Hook]

Define this target hook if you want to be able to add attributes to a decl when it is being created. This is normally useful for back ends which wish to implement a pragma by using the attributes which correspond to the pragma's effect. The *node* argument is the decl which is being created. The *attr_ptr* argument is a pointer to the attribute list for this decl. The list itself should not be modified, since it may be shared with other decls, but attributes may be chained on the head of the list and ****attr_ptr*** modified to point to the new attributes, or a copy of the list may be made if further changes are needed.

`bool TARGET_FUNCTION_ATTRIBUTE_INLINABLE_P` (*const_tree* ***fndecl***) [Target Hook]

This target hook returns `true` if it is OK to inline *fndecl* into the current function, despite its having target-specific attributes, `false` otherwise. By default, if a function has a target specific attribute attached to it, it will not be inlined.

`bool TARGET_OPTION_VALID_ATTRIBUTE_P` (*tree* ***fndecl***, *tree* ***name***, *tree* ***args***, *int* ***flags***) [Target Hook]

This hook is called to parse `attribute(target("..."))`, which allows setting target-specific options on individual functions. These function-specific options may differ from the options specified on the command line. The hook should return `true` if the options are valid.

The hook should set the `DECL_FUNCTION_SPECIFIC_TARGET` field in the function declaration to hold a pointer to a target-specific `struct cl_target_option` structure.

`void TARGET_OPTION_SAVE` (*struct cl_target_option* ****ptr***, *struct gcc_options* ****opts***) [Target Hook]

This hook is called to save any additional target-specific information in the `struct cl_target_option` structure for function-specific options from the `struct gcc_options` structure. See Section 8.1 [Option file format], page 105.

void TARGET_OPTION_RESTORE (*struct gcc_options* ***opts**, *struct cl_target_option* ***ptr**) [Target Hook]

This hook is called to restore any additional target-specific information in the `struct cl_target_option` structure for function-specific options to the `struct gcc_options` structure.

void TARGET_OPTION_PRINT (*FILE* ***file**, *int* **indent**, *struct cl_target_option* ***ptr**) [Target Hook]

This hook is called to print any additional target-specific information in the `struct cl_target_option` structure for function-specific options.

bool TARGET_OPTION_PRAGMA_PARSE (*tree* **args**, *tree* **pop_target**) [Target Hook]

This target hook parses the options for `#pragma GCC target`, which sets the target-specific options for functions that occur later in the input stream. The options accepted should be the same as those handled by the `TARGET_OPTION_VALID_ATTRIBUTE_P` hook.

void TARGET_OPTION_OVERRIDE (*void*) [Target Hook]

Sometimes certain combinations of command options do not make sense on a particular target machine. You can override the hook `TARGET_OPTION_OVERRIDE` to take account of this. This hooks is called once just after all the command options have been parsed.

Don't use this hook to turn on various extra optimizations for '`-O`'. That is what `TARGET_OPTION_OPTIMIZATION` is for.

If you need to do something whenever the optimization level is changed via the optimize attribute or pragma, see `TARGET_OVERRIDE_OPTIONS_AFTER_CHANGE`

bool TARGET_OPTION_FUNCTION_VERSIONS (*tree* **decl1**, *tree* **decl2**) [Target Hook]

This target hook returns `true` if *DECL1* and *DECL2* are versions of the same function. *DECL1* and *DECL2* are function versions if and only if they have the same function signature and different target specific attributes, that is, they are compiled for different target machines.

bool TARGET_CAN_INLINE_P (*tree* **caller**, *tree* **callee**) [Target Hook]

This target hook returns `false` if the *caller* function cannot inline *callee*, based on target specific information. By default, inlining is not allowed if the callee function has function specific target options and the caller does not use the same options.

17.26 Emulating TLS

For targets whose psABI does not provide Thread Local Storage via specific relocations and instruction sequences, an emulation layer is used. A set of target hooks allows this emulation layer to be configured for the requirements of a particular target. For instance the psABI may in fact specify TLS support in terms of an emulation layer.

The emulation layer works by creating a control object for every TLS object. To access the TLS object, a lookup function is provided which, when given the address of the control object, will return the address of the current thread's instance of the TLS object.

`const char * TARGET_EMUTLS_GET_ADDRESS` [Target Hook]

Contains the name of the helper function that uses a TLS control object to locate a TLS instance. The default causes libgcc's emulated TLS helper function to be used.

`const char * TARGET_EMUTLS_REGISTER_COMMON` [Target Hook]

Contains the name of the helper function that should be used at program startup to register TLS objects that are implicitly initialized to zero. If this is `NULL`, all TLS objects will have explicit initializers. The default causes libgcc's emulated TLS registration function to be used.

`const char * TARGET_EMUTLS_VAR_SECTION` [Target Hook]

Contains the name of the section in which TLS control variables should be placed. The default of `NULL` allows these to be placed in any section.

`const char * TARGET_EMUTLS_TMPL_SECTION` [Target Hook]

Contains the name of the section in which TLS initializers should be placed. The default of `NULL` allows these to be placed in any section.

`const char * TARGET_EMUTLS_VAR_PREFIX` [Target Hook]

Contains the prefix to be prepended to TLS control variable names. The default of `NULL` uses a target-specific prefix.

`const char * TARGET_EMUTLS_TMPL_PREFIX` [Target Hook]

Contains the prefix to be prepended to TLS initializer objects. The default of `NULL` uses a target-specific prefix.

`tree TARGET_EMUTLS_VAR_FIELDS (`*tree* *type*, *tree* **name*`)` [Target Hook]

Specifies a function that generates the FIELD_DECLs for a TLS control object type. *type* is the RECORD_TYPE the fields are for and *name* should be filled with the structure tag, if the default of `__emutls_object` is unsuitable. The default creates a type suitable for libgcc's emulated TLS function.

`tree TARGET_EMUTLS_VAR_INIT (`*tree* *var*, *tree* *decl*, *tree* *tmpl_addr*`)` [Target Hook]

Specifies a function that generates the CONSTRUCTOR to initialize a TLS control object. *var* is the TLS control object, *decl* is the TLS object and *tmpl_addr* is the address of the initializer. The default initializes libgcc's emulated TLS control object.

`bool TARGET_EMUTLS_VAR_ALIGN_FIXED` [Target Hook]

Specifies whether the alignment of TLS control variable objects is fixed and should not be increased as some backends may do to optimize single objects. The default is false.

`bool TARGET_EMUTLS_DEBUG_FORM_TLS_ADDRESS` [Target Hook]

Specifies whether a DWARF `DW_OP_form_tls_address` location descriptor may be used to describe emulated TLS control objects.

17.27 Defining coprocessor specifics for MIPS targets.

The MIPS specification allows MIPS implementations to have as many as 4 coprocessors, each with as many as 32 private registers. GCC supports accessing these registers and transferring values between the registers and memory using asm-ized variables. For example:

```
register unsigned int cp0count asm ("c0r1");
unsigned int d;

d = cp0count + 3;
```

("c0r1" is the default name of register 1 in coprocessor 0; alternate names may be added as described below, or the default names may be overridden entirely in `SUBTARGET_CONDITIONAL_REGISTER_USAGE`.)

Coprocessor registers are assumed to be epilogue-used; sets to them will be preserved even if it does not appear that the register is used again later in the function.

Another note: according to the MIPS spec, coprocessor 1 (if present) is the FPU. One accesses COP1 registers through standard mips floating-point support; they are not included in this mechanism.

There is one macro used in defining the MIPS coprocessor interface which you may want to override in subtargets; it is described below.

17.28 Parameters for Precompiled Header Validity Checking

`void * TARGET_GET_PCH_VALIDITY` (*size_t *sz*) [Target Hook]

This hook returns a pointer to the data needed by `TARGET_PCH_VALID_P` and sets '**sz*' to the size of the data in bytes.

`const char * TARGET_PCH_VALID_P` (*const void *data, size_t sz*) [Target Hook]

This hook checks whether the options used to create a PCH file are compatible with the current settings. It returns `NULL` if so and a suitable error message if not. Error messages will be presented to the user and must be localized using '`_(msg)`'.

data is the data that was returned by `TARGET_GET_PCH_VALIDITY` when the PCH file was created and *sz* is the size of that data in bytes. It's safe to assume that the data was created by the same version of the compiler, so no format checking is needed.

The default definition of `default_pch_valid_p` should be suitable for most targets.

`const char * TARGET_CHECK_PCH_TARGET_FLAGS` (*int pch_flags*) [Target Hook]

If this hook is nonnull, the default implementation of `TARGET_PCH_VALID_P` will use it to check for compatible values of `target_flags`. *pch_flags* specifies the value that `target_flags` had when the PCH file was created. The return value is the same as for `TARGET_PCH_VALID_P`.

`void TARGET_PREPARE_PCH_SAVE` (*void*) [Target Hook]

Called before writing out a PCH file. If the target has some garbage-collected data that needs to be in a particular state on PCH loads, it can use this hook to enforce that state. Very few targets need to do anything here.

17.29 C++ ABI parameters

`tree TARGET_CXX_GUARD_TYPE (void)` [Target Hook]

Define this hook to override the integer type used for guard variables. These are used to implement one-time construction of static objects. The default is long_long_integer_type_node.

`bool TARGET_CXX_GUARD_MASK_BIT (void)` [Target Hook]

This hook determines how guard variables are used. It should return `false` (the default) if the first byte should be used. A return value of `true` indicates that only the least significant bit should be used.

`tree TARGET_CXX_GET_COOKIE_SIZE (tree type)` [Target Hook]

This hook returns the size of the cookie to use when allocating an array whose elements have the indicated *type*. Assumes that it is already known that a cookie is needed. The default is `max(sizeof (size_t), alignof(type))`, as defined in section 2.7 of the IA64/Generic C++ ABI.

`bool TARGET_CXX_COOKIE_HAS_SIZE (void)` [Target Hook]

This hook should return `true` if the element size should be stored in array cookies. The default is to return `false`.

`int TARGET_CXX_IMPORT_EXPORT_CLASS (tree type, int import_export)` [Target Hook]

If defined by a backend this hook allows the decision made to export class *type* to be overruled. Upon entry *import_export* will contain 1 if the class is going to be exported, −1 if it is going to be imported and 0 otherwise. This function should return the modified value and perform any other actions necessary to support the backend's targeted operating system.

`bool TARGET_CXX_CDTOR_RETURNS_THIS (void)` [Target Hook]

This hook should return `true` if constructors and destructors return the address of the object created/destroyed. The default is to return `false`.

`bool TARGET_CXX_KEY_METHOD_MAY_BE_INLINE (void)` [Target Hook]

This hook returns true if the key method for a class (i.e., the method which, if defined in the current translation unit, causes the virtual table to be emitted) may be an inline function. Under the standard Itanium C++ ABI the key method may be an inline function so long as the function is not declared inline in the class definition. Under some variants of the ABI, an inline function can never be the key method. The default is to return `true`.

`void TARGET_CXX_DETERMINE_CLASS_DATA_VISIBILITY (tree decl)` [Target Hook]

decl is a virtual table, virtual table table, typeinfo object, or other similar implicit class data object that will be emitted with external linkage in this translation unit. No ELF visibility has been explicitly specified. If the target needs to specify a visibility other than that of the containing class, use this hook to set `DECL_VISIBILITY` and `DECL_VISIBILITY_SPECIFIED`.

`bool TARGET_CXX_CLASS_DATA_ALWAYS_COMDAT (void)` [Target Hook]
This hook returns true (the default) if virtual tables and other similar implicit class data objects are always COMDAT if they have external linkage. If this hook returns false, then class data for classes whose virtual table will be emitted in only one translation unit will not be COMDAT.

`bool TARGET_CXX_LIBRARY_RTTI_COMDAT (void)` [Target Hook]
This hook returns true (the default) if the RTTI information for the basic types which is defined in the C++ runtime should always be COMDAT, false if it should not be COMDAT.

`bool TARGET_CXX_USE_AEABI_ATEXIT (void)` [Target Hook]
This hook returns true if `__aeabi_atexit` (as defined by the ARM EABI) should be used to register static destructors when '`-fuse-cxa-atexit`' is in effect. The default is to return false to use `__cxa_atexit`.

`bool TARGET_CXX_USE_ATEXIT_FOR_CXA_ATEXIT (void)` [Target Hook]
This hook returns true if the target `atexit` function can be used in the same manner as `__cxa_atexit` to register C++ static destructors. This requires that `atexit`-registered functions in shared libraries are run in the correct order when the libraries are unloaded. The default is to return false.

`void TARGET_CXX_ADJUST_CLASS_AT_DEFINITION (tree type)` [Target Hook]
type is a C++ class (i.e., RECORD_TYPE or UNION_TYPE) that has just been defined. Use this hook to make adjustments to the class (eg, tweak visibility or perform any other required target modifications).

`tree TARGET_CXX_DECL_MANGLING_CONTEXT (const_tree decl)` [Target Hook]
Return target-specific mangling context of *decl* or `NULL_TREE`.

17.30 Adding support for named address spaces

The draft technical report of the ISO/IEC JTC1 S22 WG14 N1275 standards committee, *Programming Languages - C - Extensions to support embedded processors*, specifies a syntax for embedded processors to specify alternate address spaces. You can configure a GCC port to support section 5.1 of the draft report to add support for address spaces other than the default address space. These address spaces are new keywords that are similar to the `volatile` and `const` type attributes.

Pointers to named address spaces can have a different size than pointers to the generic address space.

For example, the SPU port uses the `__ea` address space to refer to memory in the host processor, rather than memory local to the SPU processor. Access to memory in the `__ea` address space involves issuing DMA operations to move data between the host processor and the local processor memory address space. Pointers in the `__ea` address space are either 32 bits or 64 bits based on the '`-mea32`' or '`-mea64`' switches (native SPU pointers are always 32 bits).

Internally, address spaces are represented as a small integer in the range 0 to 15 with address space 0 being reserved for the generic address space.

To register a named address space qualifier keyword with the C front end, the target may call the `c_register_addr_space` routine. For example, the SPU port uses the following to declare `__ea` as the keyword for named address space #1:

```
#define ADDR_SPACE_EA 1
c_register_addr_space ("__ea", ADDR_SPACE_EA);
```

`enum machine_mode TARGET_ADDR_SPACE_POINTER_MODE` [Target Hook]
(*addr_space_t* `address_space`)

Define this to return the machine mode to use for pointers to *address_space* if the target supports named address spaces. The default version of this hook returns `ptr_mode` for the generic address space only.

`enum machine_mode TARGET_ADDR_SPACE_ADDRESS_MODE` [Target Hook]
(*addr_space_t* `address_space`)

Define this to return the machine mode to use for addresses in *address_space* if the target supports named address spaces. The default version of this hook returns `Pmode` for the generic address space only.

`bool TARGET_ADDR_SPACE_VALID_POINTER_MODE` (*enum machine_mode* `mode`, *addr_space_t* `as`) [Target Hook]

Define this to return nonzero if the port can handle pointers with machine mode *mode* to address space *as*. This target hook is the same as the `TARGET_VALID_POINTER_MODE` target hook, except that it includes explicit named address space support. The default version of this hook returns true for the modes returned by either the `TARGET_ADDR_SPACE_POINTER_MODE` or `TARGET_ADDR_SPACE_ADDRESS_MODE` target hooks for the given address space.

`bool TARGET_ADDR_SPACE_LEGITIMATE_ADDRESS_P` (*enum machine_mode* `mode`, *rtx* `exp`, *bool* `strict`, *addr_space_t* `as`) [Target Hook]

Define this to return true if *exp* is a valid address for mode *mode* in the named address space *as*. The *strict* parameter says whether strict addressing is in effect after reload has finished. This target hook is the same as the `TARGET_LEGITIMATE_ADDRESS_P` target hook, except that it includes explicit named address space support.

`rtx TARGET_ADDR_SPACE_LEGITIMIZE_ADDRESS` (*rtx* `x`, *rtx* `oldx`, *enum machine_mode* `mode`, *addr_space_t* `as`) [Target Hook]

Define this to modify an invalid address *x* to be a valid address with mode *mode* in the named address space *as*. This target hook is the same as the `TARGET_LEGITIMIZE_ADDRESS` target hook, except that it includes explicit named address space support.

`bool TARGET_ADDR_SPACE_SUBSET_P` (*addr_space_t* `subset`, *addr_space_t* `superset`) [Target Hook]

Define this to return whether the *subset* named address space is contained within the *superset* named address space. Pointers to a named address space that is a subset of another named address space will be converted automatically without a cast if used together in arithmetic operations. Pointers to a superset address space can be converted to pointers to a subset address space via explicit casts.

`rtx TARGET_ADDR_SPACE_CONVERT (rtx op, tree from_type, tree to_type)` [Target Hook]

Define this to convert the pointer expression represented by the RTL *op* with type *from_type* that points to a named address space to a new pointer expression with type *to_type* that points to a different named address space. When this hook it called, it is guaranteed that one of the two address spaces is a subset of the other, as determined by the `TARGET_ADDR_SPACE_SUBSET_P` target hook.

17.31 Miscellaneous Parameters

Here are several miscellaneous parameters.

`HAS_LONG_COND_BRANCH` [Macro]

Define this boolean macro to indicate whether or not your architecture has conditional branches that can span all of memory. It is used in conjunction with an optimization that partitions hot and cold basic blocks into separate sections of the executable. If this macro is set to false, gcc will convert any conditional branches that attempt to cross between sections into unconditional branches or indirect jumps.

`HAS_LONG_UNCOND_BRANCH` [Macro]

Define this boolean macro to indicate whether or not your architecture has unconditional branches that can span all of memory. It is used in conjunction with an optimization that partitions hot and cold basic blocks into separate sections of the executable. If this macro is set to false, gcc will convert any unconditional branches that attempt to cross between sections into indirect jumps.

`CASE_VECTOR_MODE` [Macro]

An alias for a machine mode name. This is the machine mode that elements of a jump-table should have.

`CASE_VECTOR_SHORTEN_MODE (min_offset, max_offset, body)` [Macro]

Optional: return the preferred mode for an `addr_diff_vec` when the minimum and maximum offset are known. If you define this, it enables extra code in branch shortening to deal with `addr_diff_vec`. To make this work, you also have to define `INSN_ALIGN` and make the alignment for `addr_diff_vec` explicit. The *body* argument is provided so that the offset_unsigned and scale flags can be updated.

`CASE_VECTOR_PC_RELATIVE` [Macro]

Define this macro to be a C expression to indicate when jump-tables should contain relative addresses. You need not define this macro if jump-tables never contain relative addresses, or jump-tables should contain relative addresses only when '`-fPIC`' or '`-fPIC`' is in effect.

`unsigned int TARGET_CASE_VALUES_THRESHOLD (void)` [Target Hook]

This function return the smallest number of different values for which it is best to use a jump-table instead of a tree of conditional branches. The default is four for machines with a `casesi` instruction and five otherwise. This is best for most machines.

`WORD_REGISTER_OPERATIONS` [Macro]

Define this macro if operations between registers with integral mode smaller than a word are always performed on the entire register. Most RISC machines have this property and most CISC machines do not.

`LOAD_EXTEND_OP (mem_mode)` [Macro]

Define this macro to be a C expression indicating when insns that read memory in *mem_mode*, an integral mode narrower than a word, set the bits outside of *mem_mode* to be either the sign-extension or the zero-extension of the data read. Return `SIGN_EXTEND` for values of *mem_mode* for which the insn sign-extends, `ZERO_EXTEND` for which it zero-extends, and `UNKNOWN` for other modes.

This macro is not called with *mem_mode* non-integral or with a width greater than or equal to `BITS_PER_WORD`, so you may return any value in this case. Do not define this macro if it would always return `UNKNOWN`. On machines where this macro is defined, you will normally define it as the constant `SIGN_EXTEND` or `ZERO_EXTEND`.

You may return a non-`UNKNOWN` value even if for some hard registers the sign extension is not performed, if for the `REGNO_REG_CLASS` of these hard registers `CANNOT_CHANGE_MODE_CLASS` returns nonzero when the *from* mode is *mem_mode* and the *to* mode is any integral mode larger than this but not larger than `word_mode`.

You must return `UNKNOWN` if for some hard registers that allow this mode, `CANNOT_CHANGE_MODE_CLASS` says that they cannot change to `word_mode`, but that they can change to another integral mode that is larger then *mem_mode* but still smaller than `word_mode`.

`SHORT_IMMEDIATES_SIGN_EXTEND` [Macro]

Define this macro if loading short immediate values into registers sign extends.

`unsigned int TARGET_MIN_DIVISIONS_FOR_RECIP_MUL (enum machine_mode mode)` [Target Hook]

When '`-ffast-math`' is in effect, GCC tries to optimize divisions by the same divisor, by turning them into multiplications by the reciprocal. This target hook specifies the minimum number of divisions that should be there for GCC to perform the optimization for a variable of mode *mode*. The default implementation returns 3 if the machine has an instruction for the division, and 2 if it does not.

`MOVE_MAX` [Macro]

The maximum number of bytes that a single instruction can move quickly between memory and registers or between two memory locations.

`MAX_MOVE_MAX` [Macro]

The maximum number of bytes that a single instruction can move quickly between memory and registers or between two memory locations. If this is undefined, the default is `MOVE_MAX`. Otherwise, it is the constant value that is the largest value that `MOVE_MAX` can have at run-time.

`SHIFT_COUNT_TRUNCATED` [Macro]

A C expression that is nonzero if on this machine the number of bits actually used for the count of a shift operation is equal to the number of bits needed to represent

the size of the object being shifted. When this macro is nonzero, the compiler will assume that it is safe to omit a sign-extend, zero-extend, and certain bitwise 'and' instructions that truncates the count of a shift operation. On machines that have instructions that act on bit-fields at variable positions, which may include 'bit test' instructions, a nonzero `SHIFT_COUNT_TRUNCATED` also enables deletion of truncations of the values that serve as arguments to bit-field instructions.

If both types of instructions truncate the count (for shifts) and position (for bit-field operations), or if no variable-position bit-field instructions exist, you should define this macro.

However, on some machines, such as the 80386 and the 680x0, truncation only applies to shift operations and not the (real or pretended) bit-field operations. Define `SHIFT_COUNT_TRUNCATED` to be zero on such machines. Instead, add patterns to the '`md`' file that include the implied truncation of the shift instructions.

You need not define this macro if it would always have the value of zero.

`unsigned HOST_WIDE_INT TARGET_SHIFT_TRUNCATION_MASK` (*enum machine_mode* `mode`) [Target Hook]

This function describes how the standard shift patterns for *mode* deal with shifts by negative amounts or by more than the width of the mode. See [shift patterns], page 357.

On many machines, the shift patterns will apply a mask *m* to the shift count, meaning that a fixed-width shift of *x* by *y* is equivalent to an arbitrary-width shift of *x* by *y* & *m*. If this is true for mode *mode*, the function should return *m*, otherwise it should return 0. A return value of 0 indicates that no particular behavior is guaranteed.

Note that, unlike `SHIFT_COUNT_TRUNCATED`, this function does *not* apply to general shift rtxes; it applies only to instructions that are generated by the named shift patterns.

The default implementation of this function returns `GET_MODE_BITSIZE (mode) - 1` if `SHIFT_COUNT_TRUNCATED` and 0 otherwise. This definition is always safe, but if `SHIFT_COUNT_TRUNCATED` is false, and some shift patterns nevertheless truncate the shift count, you may get better code by overriding it.

`TRULY_NOOP_TRUNCATION (outprec, inprec)` [Macro]

A C expression which is nonzero if on this machine it is safe to "convert" an integer of *inprec* bits to one of *outprec* bits (where *outprec* is smaller than *inprec*) by merely operating on it as if it had only *outprec* bits.

On many machines, this expression can be 1.

When `TRULY_NOOP_TRUNCATION` returns 1 for a pair of sizes for modes for which `MODES_TIEABLE_P` is 0, suboptimal code can result. If this is the case, making `TRULY_NOOP_TRUNCATION` return 0 in such cases may improve things.

`int TARGET_MODE_REP_EXTENDED` (*enum machine_mode* `mode`, *enum machine_mode* `rep_mode`) [Target Hook]

The representation of an integral mode can be such that the values are always extended to a wider integral mode. Return `SIGN_EXTEND` if values of *mode* are represented in sign-extended form to *rep_mode*. Return `UNKNOWN` otherwise. (Cur-

rently, none of the targets use zero-extended representation this way so unlike LOAD_EXTEND_OP, TARGET_MODE_REP_EXTENDED is expected to return either SIGN_EXTEND or UNKNOWN. Also no target extends *mode* to *rep_mode* so that *rep_mode* is not the next widest integral mode and currently we take advantage of this fact.)

Similarly to LOAD_EXTEND_OP you may return a non-UNKNOWN value even if the extension is not performed on certain hard registers as long as for the REGNO_REG_CLASS of these hard registers CANNOT_CHANGE_MODE_CLASS returns nonzero.

Note that TARGET_MODE_REP_EXTENDED and LOAD_EXTEND_OP describe two related properties. If you define TARGET_MODE_REP_EXTENDED (mode, word_mode) you probably also want to define LOAD_EXTEND_OP (mode) to return the same type of extension.

In order to enforce the representation of mode, TRULY_NOOP_TRUNCATION should return false when truncating to mode.

STORE_FLAG_VALUE [Macro]

A C expression describing the value returned by a comparison operator with an integral mode and stored by a store-flag instruction ('cstore*mode*4') when the condition is true. This description must apply to *all* the 'cstore*mode*4' patterns and all the comparison operators whose results have a MODE_INT mode.

A value of 1 or −1 means that the instruction implementing the comparison operator returns exactly 1 or −1 when the comparison is true and 0 when the comparison is false. Otherwise, the value indicates which bits of the result are guaranteed to be 1 when the comparison is true. This value is interpreted in the mode of the comparison operation, which is given by the mode of the first operand in the 'cstore*mode*4' pattern. Either the low bit or the sign bit of STORE_FLAG_VALUE be on. Presently, only those bits are used by the compiler.

If STORE_FLAG_VALUE is neither 1 or −1, the compiler will generate code that depends only on the specified bits. It can also replace comparison operators with equivalent operations if they cause the required bits to be set, even if the remaining bits are undefined. For example, on a machine whose comparison operators return an SImode value and where STORE_FLAG_VALUE is defined as '0x80000000', saying that just the sign bit is relevant, the expression

```
(ne:SI (and:SI x (const_int power-of-2)) (const_int 0))
```

can be converted to

```
(ashift:SI x (const_int n))
```

where *n* is the appropriate shift count to move the bit being tested into the sign bit.

There is no way to describe a machine that always sets the low-order bit for a true value, but does not guarantee the value of any other bits, but we do not know of any machine that has such an instruction. If you are trying to port GCC to such a machine, include an instruction to perform a logical-and of the result with 1 in the pattern for the comparison operators and let us know at gcc@gcc.gnu.org.

Often, a machine will have multiple instructions that obtain a value from a comparison (or the condition codes). Here are rules to guide the choice of value for STORE_FLAG_VALUE, and hence the instructions to be used:

- Use the shortest sequence that yields a valid definition for STORE_FLAG_VALUE. It is more efficient for the compiler to "normalize" the value (convert it to, e.g., 1 or

0) than for the comparison operators to do so because there may be opportunities to combine the normalization with other operations.

- For equal-length sequences, use a value of 1 or −1, with −1 being slightly preferred on machines with expensive jumps and 1 preferred on other machines.
- As a second choice, choose a value of '`0x80000001`' if instructions exist that set both the sign and low-order bits but do not define the others.
- Otherwise, use a value of '`0x80000000`'.

Many machines can produce both the value chosen for `STORE_FLAG_VALUE` and its negation in the same number of instructions. On those machines, you should also define a pattern for those cases, e.g., one matching

```
(set A (neg:m (ne:m B C)))
```

Some machines can also perform `and` or `plus` operations on condition code values with less instructions than the corresponding '`cstore`*mode*`4`' insn followed by `and` or `plus`. On those machines, define the appropriate patterns. Use the names `incscc` and `decscc`, respectively, for the patterns which perform `plus` or `minus` operations on condition code values. See '`rs6000.md`' for some examples. The GNU Superoptimizer can be used to find such instruction sequences on other machines.

If this macro is not defined, the default value, 1, is used. You need not define `STORE_FLAG_VALUE` if the machine has no store-flag instructions, or if the value generated by these instructions is 1.

`FLOAT_STORE_FLAG_VALUE` (*mode*) [Macro]

A C expression that gives a nonzero `REAL_VALUE_TYPE` value that is returned when comparison operators with floating-point results are true. Define this macro on machines that have comparison operations that return floating-point values. If there are no such operations, do not define this macro.

`VECTOR_STORE_FLAG_VALUE` (*mode*) [Macro]

A C expression that gives a rtx representing the nonzero true element for vector comparisons. The returned rtx should be valid for the inner mode of *mode* which is guaranteed to be a vector mode. Define this macro on machines that have vector comparison operations that return a vector result. If there are no such operations, do not define this macro. Typically, this macro is defined as `const1_rtx` or `constm1_rtx`. This macro may return `NULL_RTX` to prevent the compiler optimizing such vector comparison operations for the given mode.

`CLZ_DEFINED_VALUE_AT_ZERO` (*mode*, *value*) [Macro]
`CTZ_DEFINED_VALUE_AT_ZERO` (*mode*, *value*) [Macro]

A C expression that indicates whether the architecture defines a value for `clz` or `ctz` with a zero operand. A result of `0` indicates the value is undefined. If the value is defined for only the RTL expression, the macro should evaluate to `1`; if the value applies also to the corresponding optab entry (which is normally the case if it expands directly into the corresponding RTL), then the macro should evaluate to `2`. In the cases where the value is defined, *value* should be set to this value.

If this macro is not defined, the value of `clz` or `ctz` at zero is assumed to be undefined.

This macro must be defined if the target's expansion for `ffs` relies on a particular value to get correct results. Otherwise it is not necessary, though it may be used to optimize some corner cases, and to provide a default expansion for the `ffs` optab.

Note that regardless of this macro the "definedness" of `clz` and `ctz` at zero do *not* extend to the builtin functions visible to the user. Thus one may be free to adjust the value at will to match the target expansion of these operations without fear of breaking the API.

`Pmode` [Macro]

An alias for the machine mode for pointers. On most machines, define this to be the integer mode corresponding to the width of a hardware pointer; `SImode` on 32-bit machine or `DImode` on 64-bit machines. On some machines you must define this to be one of the partial integer modes, such as `PSImode`.

The width of `Pmode` must be at least as large as the value of `POINTER_SIZE`. If it is not equal, you must define the macro `POINTERS_EXTEND_UNSIGNED` to specify how pointers are extended to `Pmode`.

`FUNCTION_MODE` [Macro]

An alias for the machine mode used for memory references to functions being called, in `call` RTL expressions. On most CISC machines, where an instruction can begin at any byte address, this should be `QImode`. On most RISC machines, where all instructions have fixed size and alignment, this should be a mode with the same size and alignment as the machine instruction words - typically `SImode` or `HImode`.

`STDC_0_IN_SYSTEM_HEADERS` [Macro]

In normal operation, the preprocessor expands `__STDC__` to the constant 1, to signify that GCC conforms to ISO Standard C. On some hosts, like Solaris, the system compiler uses a different convention, where `__STDC__` is normally 0, but is 1 if the user specifies strict conformance to the C Standard.

Defining `STDC_0_IN_SYSTEM_HEADERS` makes GNU CPP follows the host convention when processing system header files, but when processing user files `__STDC__` will always expand to 1.

`const char * TARGET_C_PREINCLUDE` (*void*) [C Target Hook]

Define this hook to return the name of a header file to be included at the start of all compilations, as if it had been included with `#include <file>`. If this hook returns `NULL`, or is not defined, or the header is not found, or if the user specifies '`-ffreestanding`' or '`-nostdinc`', no header is included.

This hook can be used together with a header provided by the system C library to implement ISO C requirements for certain macros to be predefined that describe properties of the whole implementation rather than just the compiler.

`bool TARGET_CXX_IMPLICIT_EXTERN_C` (*const char**) [C Target Hook]

Define this hook to add target-specific C++ implicit extern C functions. If this function returns true for the name of a file-scope function, that function implicitly gets extern "C" linkage rather than whatever language linkage the declaration would normally have. An example of such function is WinMain on Win32 targets.

`NO_IMPLICIT_EXTERN_C` [Macro]

Define this macro if the system header files support C++ as well as C. This macro inhibits the usual method of using system header files in C++, which is to pretend that the file's contents are enclosed in '`extern "C" {...}`'.

`REGISTER_TARGET_PRAGMAS ()` [Macro]

Define this macro if you want to implement any target-specific pragmas. If defined, it is a C expression which makes a series of calls to `c_register_pragma` or `c_register_pragma_with_expansion` for each pragma. The macro may also do any setup required for the pragmas.

The primary reason to define this macro is to provide compatibility with other compilers for the same target. In general, we discourage definition of target-specific pragmas for GCC.

If the pragma can be implemented by attributes then you should consider defining the target hook '`TARGET_INSERT_ATTRIBUTES`' as well.

Preprocessor macros that appear on pragma lines are not expanded. All '`#pragma`' directives that do not match any registered pragma are silently ignored, unless the user specifies '`-Wunknown-pragmas`'.

`void c_register_pragma` (*const char *space, const char *name, void (*callback) (struct cpp_reader *)*) [Function]

`void c_register_pragma_with_expansion` (*const char *space, const char *name, void (*callback) (struct cpp_reader *)*) [Function]

Each call to `c_register_pragma` or `c_register_pragma_with_expansion` establishes one pragma. The *callback* routine will be called when the preprocessor encounters a pragma of the form

```
#pragma [space] name ...
```

space is the case-sensitive namespace of the pragma, or `NULL` to put the pragma in the global namespace. The callback routine receives *pfile* as its first argument, which can be passed on to cpplib's functions if necessary. You can lex tokens after the *name* by calling `pragma_lex`. Tokens that are not read by the callback will be silently ignored. The end of the line is indicated by a token of type `CPP_EOF`. Macro expansion occurs on the arguments of pragmas registered with `c_register_pragma_with_expansion` but not on the arguments of pragmas registered with `c_register_pragma`.

Note that the use of `pragma_lex` is specific to the C and C++ compilers. It will not work in the Java or Fortran compilers, or any other language compilers for that matter. Thus if `pragma_lex` is going to be called from target-specific code, it must only be done so when building the C and C++ compilers. This can be done by defining the variables `c_target_objs` and `cxx_target_objs` in the target entry in the '`config.gcc`' file. These variables should name the target-specific, language-specific object file which contains the code that uses `pragma_lex`. Note it will also be necessary to add a rule to the makefile fragment pointed to by `tmake_file` that shows how to build this object file.

`HANDLE_PRAGMA_PACK_WITH_EXPANSION` [Macro]

Define this macro if macros should be expanded in the arguments of '`#pragma pack`'.

`TARGET_DEFAULT_PACK_STRUCT` [Macro]

If your target requires a structure packing default other than 0 (meaning the machine default), define this macro to the necessary value (in bytes). This must be a value that would also be valid to use with '`#pragma pack()`' (that is, a small power of two).

`DOLLARS_IN_IDENTIFIERS` [Macro]

Define this macro to control use of the character '`$`' in identifier names for the C family of languages. 0 means '`$`' is not allowed by default; 1 means it is allowed. 1 is the default; there is no need to define this macro in that case.

`INSN_SETS_ARE_DELAYED (`*`insn`*`)` [Macro]

Define this macro as a C expression that is nonzero if it is safe for the delay slot scheduler to place instructions in the delay slot of *insn*, even if they appear to use a resource set or clobbered in *insn*. *insn* is always a `jump_insn` or an `insn`; GCC knows that every `call_insn` has this behavior. On machines where some `insn` or `jump_insn` is really a function call and hence has this behavior, you should define this macro.

You need not define this macro if it would always return zero.

`INSN_REFERENCES_ARE_DELAYED (`*`insn`*`)` [Macro]

Define this macro as a C expression that is nonzero if it is safe for the delay slot scheduler to place instructions in the delay slot of *insn*, even if they appear to set or clobber a resource referenced in *insn*. *insn* is always a `jump_insn` or an `insn`. On machines where some `insn` or `jump_insn` is really a function call and its operands are registers whose use is actually in the subroutine it calls, you should define this macro. Doing so allows the delay slot scheduler to move instructions which copy arguments into the argument registers into the delay slot of *insn*.

You need not define this macro if it would always return zero.

`MULTIPLE_SYMBOL_SPACES` [Macro]

Define this macro as a C expression that is nonzero if, in some cases, global symbols from one translation unit may not be bound to undefined symbols in another translation unit without user intervention. For instance, under Microsoft Windows symbols must be explicitly imported from shared libraries (DLLs).

You need not define this macro if it would always evaluate to zero.

`tree TARGET_MD_ASM_CLOBBERS (`*tree* *`outputs`*, *tree* *`inputs`*, *tree* *`clobbers`*`)` [Target Hook]

This target hook should add to *clobbers* `STRING_CST` trees for any hard regs the port wishes to automatically clobber for an asm. It should return the result of the last `tree_cons` used to add a clobber. The *outputs*, *inputs* and *clobber* lists are the corresponding parameters to the asm and may be inspected to avoid clobbering a register that is an input or output of the asm. You can use `tree_overlaps_hard_reg_set`, declared in '`tree.h`', to test for overlap with regards to asm-declared registers.

`MATH_LIBRARY` [Macro]

Define this macro as a C string constant for the linker argument to link in the system math library, minus the initial '`"-l"`', or '`""`' if the target does not have a separate math library.

You need only define this macro if the default of '`"m"`' is wrong.

`LIBRARY_PATH_ENV` [Macro]

Define this macro as a C string constant for the environment variable that specifies where the linker should look for libraries.

You need only define this macro if the default of '`"LIBRARY_PATH"`' is wrong.

`TARGET_POSIX_IO` [Macro]

Define this macro if the target supports the following POSIX file functions, access, mkdir and file locking with fcntl / F_SETLKW. Defining `TARGET_POSIX_IO` will enable the test coverage code to use file locking when exiting a program, which avoids race conditions if the program has forked. It will also create directories at run-time for cross-profiling.

`MAX_CONDITIONAL_EXECUTE` [Macro]

A C expression for the maximum number of instructions to execute via conditional execution instructions instead of a branch. A value of `BRANCH_COST`+1 is the default if the machine does not use cc0, and 1 if it does use cc0.

`IFCVT_MODIFY_TESTS` (*`ce_info`*, *`true_expr`*, *`false_expr`*) [Macro]

Used if the target needs to perform machine-dependent modifications on the conditionals used for turning basic blocks into conditionally executed code. *ce_info* points to a data structure, `struct ce_if_block`, which contains information about the currently processed blocks. *true_expr* and *false_expr* are the tests that are used for converting the then-block and the else-block, respectively. Set either *true_expr* or *false_expr* to a null pointer if the tests cannot be converted.

`IFCVT_MODIFY_MULTIPLE_TESTS` (*`ce_info`*, *`bb`*, *`true_expr`*, *`false_expr`*) [Macro]

Like `IFCVT_MODIFY_TESTS`, but used when converting more complicated if-statements into conditions combined by `and` and `or` operations. *bb* contains the basic block that contains the test that is currently being processed and about to be turned into a condition.

`IFCVT_MODIFY_INSN` (*`ce_info`*, *`pattern`*, *`insn`*) [Macro]

A C expression to modify the *PATTERN* of an *INSN* that is to be converted to conditional execution format. *ce_info* points to a data structure, `struct ce_if_block`, which contains information about the currently processed blocks.

`IFCVT_MODIFY_FINAL` (*`ce_info`*) [Macro]

A C expression to perform any final machine dependent modifications in converting code to conditional execution. The involved basic blocks can be found in the `struct ce_if_block` structure that is pointed to by *ce_info*.

`IFCVT_MODIFY_CANCEL` (*ce_info*) [Macro]

A C expression to cancel any machine dependent modifications in converting code to conditional execution. The involved basic blocks can be found in the `struct ce_if_block` structure that is pointed to by *ce_info*.

`IFCVT_MACHDEP_INIT` (*ce_info*) [Macro]

A C expression to initialize any machine specific data for if-conversion of the if-block in the `struct ce_if_block` structure that is pointed to by *ce_info*.

`void TARGET_MACHINE_DEPENDENT_REORG` (*void*) [Target Hook]

If non-null, this hook performs a target-specific pass over the instruction stream. The compiler will run it at all optimization levels, just before the point at which it normally does delayed-branch scheduling.

The exact purpose of the hook varies from target to target. Some use it to do transformations that are necessary for correctness, such as laying out in-function constant pools or avoiding hardware hazards. Others use it as an opportunity to do some machine-dependent optimizations.

You need not implement the hook if it has nothing to do. The default definition is null.

`void TARGET_INIT_BUILTINS` (*void*) [Target Hook]

Define this hook if you have any machine-specific built-in functions that need to be defined. It should be a function that performs the necessary setup.

Machine specific built-in functions can be useful to expand special machine instructions that would otherwise not normally be generated because they have no equivalent in the source language (for example, SIMD vector instructions or prefetch instructions).

To create a built-in function, call the function `lang_hooks.builtin_function` which is defined by the language front end. You can use any type nodes set up by `build_common_tree_nodes`; only language front ends that use those two functions will call '`TARGET_INIT_BUILTINS`'.

`tree TARGET_BUILTIN_DECL` (*unsigned* `code`, *bool* `initialize_p`) [Target Hook]

Define this hook if you have any machine-specific built-in functions that need to be defined. It should be a function that returns the builtin function declaration for the builtin function code *code*. If there is no such builtin and it cannot be initialized at this time if *initialize_p* is true the function should return `NULL_TREE`. If *code* is out of range the function should return `error_mark_node`.

`rtx TARGET_EXPAND_BUILTIN` (*tree* `exp`, *rtx* `target`, *rtx* `subtarget`, *enum machine_mode* `mode`, *int* `ignore`) [Target Hook]

Expand a call to a machine specific built-in function that was set up by '`TARGET_INIT_BUILTINS`'. *exp* is the expression for the function call; the result should go to *target* if that is convenient, and have mode *mode* if that is convenient. *subtarget* may be used as the target for computing one of *exp*'s operands. *ignore* is nonzero if the value is to be ignored. This function should return the result of the call to the built-in function.

`tree TARGET_RESOLVE_OVERLOADED_BUILTIN` (*unsigned int* `loc`, *tree* `fndecl`, *void* *`arglist`) [Target Hook]

Select a replacement for a machine specific built-in function that was set up by '`TARGET_INIT_BUILTINS`'. This is done *before* regular type checking, and so allows the target to implement a crude form of function overloading. *fndecl* is the declaration of the built-in function. *arglist* is the list of arguments passed to the built-in function. The result is a complete expression that implements the operation, usually another `CALL_EXPR`. *arglist* really has type '`VEC(tree,gc)*`'

`tree TARGET_FOLD_BUILTIN` (*tree* `fndecl`, *int* `n_args`, *tree* *`argp`, *bool* `ignore`) [Target Hook]

Fold a call to a machine specific built-in function that was set up by '`TARGET_INIT_BUILTINS`'. *fndecl* is the declaration of the built-in function. *n_args* is the number of arguments passed to the function; the arguments themselves are pointed to by *argp*. The result is another tree, valid for both GIMPLE and GENERIC, containing a simplified expression for the call's result. If *ignore* is true the value will be ignored.

`bool TARGET_GIMPLE_FOLD_BUILTIN` (*gimple_stmt_iterator* *`gsi`) [Target Hook]

Fold a call to a machine specific built-in function that was set up by '`TARGET_INIT_BUILTINS`'. *gsi* points to the gimple statement holding the function call. Returns true if any change was made to the GIMPLE stream.

`int TARGET_COMPARE_VERSION_PRIORITY` (*tree* `decl1`, *tree* `decl2`) [Target Hook]

This hook is used to compare the target attributes in two functions to determine which function's features get higher priority. This is used during function multi-versioning to figure out the order in which two versions must be dispatched. A function version with a higher priority is checked for dispatching earlier. *decl1* and *decl2* are the two function decls that will be compared.

`tree TARGET_GET_FUNCTION_VERSIONS_DISPATCHER` (*void* *`decl`) [Target Hook]

This hook is used to get the dispatcher function for a set of function versions. The dispatcher function is called to invoke the right function version at run-time. *decl* is one version from a set of semantically identical versions.

`tree TARGET_GENERATE_VERSION_DISPATCHER_BODY` (*void* *`arg`) [Target Hook]

This hook is used to generate the dispatcher logic to invoke the right function version at run-time for a given set of function versions. *arg* points to the callgraph node of the dispatcher function whose body must be generated.

`bool TARGET_CAN_USE_DOLOOP_P` (*double_int* `iterations`, *double_int* `iterations_max`, *unsigned int* `loop_depth`, *bool* `entered_at_top`) [Target Hook]

Return true if it is possible to use low-overhead loops (`doloop_end` and `doloop_begin`) for a particular loop. *iterations* gives the exact number of iterations, or 0 if not known. *iterations_max* gives the maximum number of iterations, or 0 if not known. *loop_depth* is the nesting depth of the loop, with 1 for innermost loops, 2 for loops that contain innermost loops, and so on. *entered_at_top* is true if the loop is only entered from the top.

This hook is only used if `doloop_end` is available. The default implementation returns true. You can use `can_use_doloop_if_innermost` if the loop must be the innermost, and if there are no other restrictions.

`const char * TARGET_INVALID_WITHIN_DOLOOP` (*const_rtx* ***insn***) [Target Hook]

Take an instruction in *insn* and return NULL if it is valid within a low-overhead loop, otherwise return a string explaining why doloop could not be applied.

Many targets use special registers for low-overhead looping. For any instruction that clobbers these this function should return a string indicating the reason why the doloop could not be applied. By default, the RTL loop optimizer does not use a present doloop pattern for loops containing function calls or branch on table instructions.

`bool TARGET_LEGITIMATE_COMBINED_INSN` (*rtx* ***insn***) [Target Hook]

Take an instruction in *insn* and return `false` if the instruction is not appropriate as a combination of two or more instructions. The default is to accept all instructions.

`MD_CAN_REDIRECT_BRANCH` (***branch1***, ***branch2***) [Macro]

Take a branch insn in *branch1* and another in *branch2*. Return true if redirecting *branch1* to the destination of *branch2* is possible.

On some targets, branches may have a limited range. Optimizing the filling of delay slots can result in branches being redirected, and this may in turn cause a branch offset to overflow.

`bool TARGET_CAN_FOLLOW_JUMP` (*const_rtx* ***follower***, *const_rtx* ***followee***) [Target Hook]

FOLLOWER and FOLLOWEE are JUMP_INSN instructions; return true if FOLLOWER may be modified to follow FOLLOWEE; false, if it can't. For example, on some targets, certain kinds of branches can't be made to follow through a hot/cold partitioning.

`bool TARGET_COMMUTATIVE_P` (*const_rtx* ***x***, *int* ***outer_code***) [Target Hook]

This target hook returns `true` if *x* is considered to be commutative. Usually, this is just COMMUTATIVE_P (*x*), but the HP PA doesn't consider PLUS to be commutative inside a MEM. *outer_code* is the rtx code of the enclosing rtl, if known, otherwise it is UNKNOWN.

`rtx TARGET_ALLOCATE_INITIAL_VALUE` (*rtx* ***hard_reg***) [Target Hook]

When the initial value of a hard register has been copied in a pseudo register, it is often not necessary to actually allocate another register to this pseudo register, because the original hard register or a stack slot it has been saved into can be used. `TARGET_ALLOCATE_INITIAL_VALUE` is called at the start of register allocation once for each hard register that had its initial value copied by using `get_func_hard_reg_initial_val` or `get_hard_reg_initial_val`. Possible values are `NULL_RTX`, if you don't want to do any special allocation, a `REG` rtx—that would typically be the hard register itself, if it is known not to be clobbered—or a `MEM`. If you are returning a `MEM`, this is only a hint for the allocator; it might decide to use another register anyways. You may use `current_function_is_leaf` or `REG_N_SETS` in the hook to determine

if the hard register in question will not be clobbered. The default value of this hook is `NULL`, which disables any special allocation.

`int TARGET_UNSPEC_MAY_TRAP_P (const_rtx x, unsigned flags)` [Target Hook]

This target hook returns nonzero if *x*, an `unspec` or `unspec_volatile` operation, might cause a trap. Targets can use this hook to enhance precision of analysis for `unspec` and `unspec_volatile` operations. You may call `may_trap_p_1` to analyze inner elements of *x* in which case *flags* should be passed along.

`void TARGET_SET_CURRENT_FUNCTION (tree decl)` [Target Hook]

The compiler invokes this hook whenever it changes its current function context (`cfun`). You can define this function if the back end needs to perform any initialization or reset actions on a per-function basis. For example, it may be used to implement function attributes that affect register usage or code generation patterns. The argument *decl* is the declaration for the new function context, and may be null to indicate that the compiler has left a function context and is returning to processing at the top level. The default hook function does nothing.

GCC sets `cfun` to a dummy function context during initialization of some parts of the back end. The hook function is not invoked in this situation; you need not worry about the hook being invoked recursively, or when the back end is in a partially-initialized state. `cfun` might be `NULL` to indicate processing at top level, outside of any function scope.

`TARGET_OBJECT_SUFFIX` [Macro]

Define this macro to be a C string representing the suffix for object files on your target machine. If you do not define this macro, GCC will use '`.o`' as the suffix for object files.

`TARGET_EXECUTABLE_SUFFIX` [Macro]

Define this macro to be a C string representing the suffix to be automatically added to executable files on your target machine. If you do not define this macro, GCC will use the null string as the suffix for executable files.

`COLLECT_EXPORT_LIST` [Macro]

If defined, `collect2` will scan the individual object files specified on its command line and create an export list for the linker. Define this macro for systems like AIX, where the linker discards object files that are not referenced from `main` and uses export lists.

`MODIFY_JNI_METHOD_CALL (mdecl)` [Macro]

Define this macro to a C expression representing a variant of the method call *mdecl*, if Java Native Interface (JNI) methods must be invoked differently from other methods on your target. For example, on 32-bit Microsoft Windows, JNI methods must be invoked using the `stdcall` calling convention and this macro is then defined as this expression:

```
build_type_attribute_variant (mdecl,
                              build_tree_list
                              (get_identifier ("stdcall"),
                               NULL))
```

`bool TARGET_CANNOT_MODIFY_JUMPS_P (void)` [Target Hook]

This target hook returns `true` past the point in which new jump instructions could be created. On machines that require a register for every jump such as the SHmedia ISA of SH5, this point would typically be reload, so this target hook should be defined to a function such as:

```
static bool
cannot_modify_jumps_past_reload_p ()
{
  return (reload_completed || reload_in_progress);
}
```

`reg_class_t TARGET_BRANCH_TARGET_REGISTER_CLASS (void)` [Target Hook]

This target hook returns a register class for which branch target register optimizations should be applied. All registers in this class should be usable interchangeably. After reload, registers in this class will be re-allocated and loads will be hoisted out of loops and be subjected to inter-block scheduling.

`bool TARGET_BRANCH_TARGET_REGISTER_CALLEE_SAVED (bool after_prologue_epilogue_gen)` [Target Hook]

Branch target register optimization will by default exclude callee-saved registers that are not already live during the current function; if this target hook returns true, they will be included. The target code must than make sure that all target registers in the class returned by '`TARGET_BRANCH_TARGET_REGISTER_CLASS`' that might need saving are saved. *after_prologue_epilogue_gen* indicates if prologues and epilogues have already been generated. Note, even if you only return true when *after_prologue_epilogue_gen* is false, you still are likely to have to make special provisions in `INITIAL_ELIMINATION_OFFSET` to reserve space for caller-saved target registers.

`bool TARGET_HAVE_CONDITIONAL_EXECUTION (void)` [Target Hook]

This target hook returns true if the target supports conditional execution. This target hook is required only when the target has several different modes and they have different conditional execution capability, such as ARM.

`unsigned TARGET_LOOP_UNROLL_ADJUST (unsigned nunroll, struct loop *loop)` [Target Hook]

This target hook returns a new value for the number of times *loop* should be unrolled. The parameter *nunroll* is the number of times the loop is to be unrolled. The parameter *loop* is a pointer to the loop, which is going to be checked for unrolling. This target hook is required only when the target has special constraints like maximum number of memory accesses.

`POWI_MAX_MULTS` [Macro]

If defined, this macro is interpreted as a signed integer C expression that specifies the maximum number of floating point multiplications that should be emitted when expanding exponentiation by an integer constant inline. When this value is defined, exponentiation requiring more than this number of multiplications is implemented by calling the system library's `pow`, `powf` or `powl` routines. The default value places no upper bound on the multiplication count.

void TARGET_EXTRA_INCLUDES (*const char* ***sysroot**, *const char* ***iprefix**, *int* **stdinc**) [Macro]

This target hook should register any extra include files for the target. The parameter *stdinc* indicates if normal include files are present. The parameter *sysroot* is the system root directory. The parameter *iprefix* is the prefix for the gcc directory.

void TARGET_EXTRA_PRE_INCLUDES (*const char* ***sysroot**, *const char* ***iprefix**, *int* **stdinc**) [Macro]

This target hook should register any extra include files for the target before any standard headers. The parameter *stdinc* indicates if normal include files are present. The parameter *sysroot* is the system root directory. The parameter *iprefix* is the prefix for the gcc directory.

void TARGET_OPTF (*char* ***path**) [Macro]

This target hook should register special include paths for the target. The parameter *path* is the include to register. On Darwin systems, this is used for Framework includes, which have semantics that are different from '`-I`'.

bool *TARGET_USE_LOCAL_THUNK_ALIAS_P* (*tree* **fndecl**) [Macro]

This target macro returns `true` if it is safe to use a local alias for a virtual function *fndecl* when constructing thunks, `false` otherwise. By default, the macro returns `true` for all functions, if a target supports aliases (i.e. defines `ASM_OUTPUT_DEF`), `false` otherwise,

TARGET_FORMAT_TYPES [Macro]

If defined, this macro is the name of a global variable containing target-specific format checking information for the '`-Wformat`' option. The default is to have no target-specific format checks.

TARGET_N_FORMAT_TYPES [Macro]

If defined, this macro is the number of entries in `TARGET_FORMAT_TYPES`.

TARGET_OVERRIDES_FORMAT_ATTRIBUTES [Macro]

If defined, this macro is the name of a global variable containing target-specific format overrides for the '`-Wformat`' option. The default is to have no target-specific format overrides. If defined, `TARGET_FORMAT_TYPES` must be defined, too.

TARGET_OVERRIDES_FORMAT_ATTRIBUTES_COUNT [Macro]

If defined, this macro specifies the number of entries in `TARGET_OVERRIDES_FORMAT_ATTRIBUTES`.

TARGET_OVERRIDES_FORMAT_INIT [Macro]

If defined, this macro specifies the optional initialization routine for target specific customizations of the system printf and scanf formatter settings.

bool TARGET_RELAXED_ORDERING [Target Hook]

If set to `true`, means that the target's memory model does not guarantee that loads which do not depend on one another will access main memory in the order of the instruction stream; if ordering is important, an explicit memory barrier must be used. This is true of many recent processors which implement a policy of "relaxed,"

"weak," or "release" memory consistency, such as Alpha, PowerPC, and ia64. The default is `false`.

`const char * TARGET_INVALID_ARG_FOR_UNPROTOTYPED_FN` [Target Hook]
(*const_tree* `typelist`, *const_tree* `funcdecl`, *const_tree* `val`)

If defined, this macro returns the diagnostic message when it is illegal to pass argument *val* to function *funcdecl* with prototype *typelist*.

`const char * TARGET_INVALID_CONVERSION` (*const_tree* `fromtype`, *const_tree* `totype`) [Target Hook]

If defined, this macro returns the diagnostic message when it is invalid to convert from *fromtype* to *totype*, or `NULL` if validity should be determined by the front end.

`const char * TARGET_INVALID_UNARY_OP` (*int* `op`, *const_tree* `type`) [Target Hook]

If defined, this macro returns the diagnostic message when it is invalid to apply operation *op* (where unary plus is denoted by `CONVERT_EXPR`) to an operand of type *type*, or `NULL` if validity should be determined by the front end.

`const char * TARGET_INVALID_BINARY_OP` (*int* `op`, *const_tree* `type1`, *const_tree* `type2`) [Target Hook]

If defined, this macro returns the diagnostic message when it is invalid to apply operation *op* to operands of types *type1* and *type2*, or `NULL` if validity should be determined by the front end.

`const char * TARGET_INVALID_PARAMETER_TYPE` (*const_tree* `type`) [Target Hook]

If defined, this macro returns the diagnostic message when it is invalid for functions to include parameters of type *type*, or `NULL` if validity should be determined by the front end. This is currently used only by the C and C++ front ends.

`const char * TARGET_INVALID_RETURN_TYPE` (*const_tree* `type`) [Target Hook]

If defined, this macro returns the diagnostic message when it is invalid for functions to have return type *type*, or `NULL` if validity should be determined by the front end. This is currently used only by the C and C++ front ends.

`tree TARGET_PROMOTED_TYPE` (*const_tree* `type`) [Target Hook]

If defined, this target hook returns the type to which values of *type* should be promoted when they appear in expressions, analogous to the integer promotions, or `NULL_TREE` to use the front end's normal promotion rules. This hook is useful when there are target-specific types with special promotion rules. This is currently used only by the C and C++ front ends.

`tree TARGET_CONVERT_TO_TYPE` (*tree* `type`, *tree* `expr`) [Target Hook]

If defined, this hook returns the result of converting *expr* to *type*. It should return the converted expression, or `NULL_TREE` to apply the front end's normal conversion rules. This hook is useful when there are target-specific types with special conversion rules. This is currently used only by the C and C++ front ends.

`TARGET_USE_JCR_SECTION` [Macro]

This macro determines whether to use the JCR section to register Java classes. By default, TARGET_USE_JCR_SECTION is defined to 1 if both SUPPORTS_WEAK and TARGET_HAVE_NAMED_SECTIONS are true, else 0.

`OBJC_JBLEN` [Macro]

This macro determines the size of the objective C jump buffer for the NeXT runtime. By default, OBJC_JBLEN is defined to an innocuous value.

`LIBGCC2_UNWIND_ATTRIBUTE` [Macro]

Define this macro if any target-specific attributes need to be attached to the functions in '`libgcc`' that provide low-level support for call stack unwinding. It is used in declarations in '`unwind-generic.h`' and the associated definitions of those functions.

`void TARGET_UPDATE_STACK_BOUNDARY` (*void*) [Target Hook]

Define this macro to update the current function stack boundary if necessary.

`rtx TARGET_GET_DRAP_RTX` (*void*) [Target Hook]

This hook should return an rtx for Dynamic Realign Argument Pointer (DRAP) if a different argument pointer register is needed to access the function's argument list due to stack realignment. Return `NULL` if no DRAP is needed.

`bool TARGET_ALLOCATE_STACK_SLOTS_FOR_ARGS` (*void*) [Target Hook]

When optimization is disabled, this hook indicates whether or not arguments should be allocated to stack slots. Normally, GCC allocates stacks slots for arguments when not optimizing in order to make debugging easier. However, when a function is declared with `__attribute__((naked))`, there is no stack frame, and the compiler cannot safely move arguments from the registers in which they are passed to the stack. Therefore, this hook should return true in general, but false for naked functions. The default implementation always returns true.

`unsigned HOST_WIDE_INT TARGET_CONST_ANCHOR` [Target Hook]

On some architectures it can take multiple instructions to synthesize a constant. If there is another constant already in a register that is close enough in value then it is preferable that the new constant is computed from this register using immediate addition or subtraction. We accomplish this through CSE. Besides the value of the constant we also add a lower and an upper constant anchor to the available expressions. These are then queried when encountering new constants. The anchors are computed by rounding the constant up and down to a multiple of the value of `TARGET_CONST_ANCHOR`. `TARGET_CONST_ANCHOR` should be the maximum positive value accepted by immediate-add plus one. We currently assume that the value of `TARGET_CONST_ANCHOR` is a power of 2. For example, on MIPS, where add-immediate takes a 16-bit signed value, `TARGET_CONST_ANCHOR` is set to '`0x8000`'. The default value is zero, which disables this optimization.

`unsigned HOST_WIDE_INT TARGET_ASAN_SHADOW_OFFSET` (*void*) [Target Hook]

Return the offset bitwise ored into shifted address to get corresponding Address Sanitizer shadow memory address. NULL if Address Sanitizer is not supported by the target.

`unsigned HOST_WIDE_INT TARGET_MEMMODEL_CHECK` (*unsigned HOST_WIDE_INT* `val`) [Target Hook]

Validate target specific memory model mask bits. When NULL no target specific memory model bits are allowed.

`unsigned char TARGET_ATOMIC_TEST_AND_SET_TRUEVAL` [Target Hook]

This value should be set if the result written by `atomic_test_and_set` is not exactly 1, i.e. the `bool true`.

`bool TARGET_HAS_IFUNC_P` (*void*) [Target Hook]

It returns true if the target supports GNU indirect functions. The support includes the assembler, linker and dynamic linker. The default value of this hook is based on target's libc.

`unsigned int TARGET_ATOMIC_ALIGN_FOR_MODE` (*enum machine_mode* `mode`) [Target Hook]

If defined, this function returns an appropriate alignment in bits for an atomic object of machine_mode *mode*. If 0 is returned then the default alignment for the specified mode is used.

`void TARGET_ATOMIC_ASSIGN_EXPAND_FENV` (*tree* `*hold`, *tree* `*clear`, *tree* `*update`) [Target Hook]

ISO C11 requires atomic compound assignments that may raise floating-point exceptions to raise exceptions corresponding to the arithmetic operation whose result was successfully stored in a compare-and-exchange sequence. This requires code equivalent to calls to `feholdexcept`, `feclearexcept` and `feupdateenv` to be generated at appropriate points in the compare-and-exchange sequence. This hook should set `*hold` to an expression equivalent to the call to `feholdexcept`, `*clear` to an expression equivalent to the call to `feclearexcept` and `*update` to an expression equivalent to the call to `feupdateenv`. The three expressions are `NULL_TREE` on entry to the hook and may be left as `NULL_TREE` if no code is required in a particular place. The default implementation leaves all three expressions as `NULL_TREE`. The `__atomic_feraiseexcept` function from `libatomic` may be of use as part of the code generated in `*update`.

18 Host Configuration

Most details about the machine and system on which the compiler is actually running are detected by the `configure` script. Some things are impossible for `configure` to detect; these are described in two ways, either by macros defined in a file named '`xm-machine.h`' or by hook functions in the file specified by the *out_host_hook_obj* variable in '`config.gcc`'. (The intention is that very few hosts will need a header file but nearly every fully supported host will need to override some hooks.)

If you need to define only a few macros, and they have simple definitions, consider using the `xm_defines` variable in your '`config.gcc`' entry instead of creating a host configuration header. See Section 6.3.2.2 [System Config], page 64.

18.1 Host Common

Some things are just not portable, even between similar operating systems, and are too difficult for autoconf to detect. They get implemented using hook functions in the file specified by the *host_hook_obj* variable in '`config.gcc`'.

`void HOST_HOOKS_EXTRA_SIGNALS` (*void*) [Host Hook]

This host hook is used to set up handling for extra signals. The most common thing to do in this hook is to detect stack overflow.

`void * HOST_HOOKS_GT_PCH_GET_ADDRESS` (*size_t* ***size***, *int* ***fd***) [Host Hook]

This host hook returns the address of some space that is likely to be free in some subsequent invocation of the compiler. We intend to load the PCH data at this address such that the data need not be relocated. The area should be able to hold *size* bytes. If the host uses `mmap`, *fd* is an open file descriptor that can be used for probing.

`int HOST_HOOKS_GT_PCH_USE_ADDRESS` (*void* * ***address***, *size_t* ***size***, *int* ***fd***, *size_t* ***offset***) [Host Hook]

This host hook is called when a PCH file is about to be loaded. We want to load *size* bytes from *fd* at *offset* into memory at *address*. The given address will be the result of a previous invocation of `HOST_HOOKS_GT_PCH_GET_ADDRESS`. Return −1 if we couldn't allocate *size* bytes at *address*. Return 0 if the memory is allocated but the data is not loaded. Return 1 if the hook has performed everything.

If the implementation uses reserved address space, free any reserved space beyond *size*, regardless of the return value. If no PCH will be loaded, this hook may be called with *size* zero, in which case all reserved address space should be freed.

Do not try to handle values of *address* that could not have been returned by this executable; just return −1. Such values usually indicate an out-of-date PCH file (built by some other GCC executable), and such a PCH file won't work.

`size_t HOST_HOOKS_GT_PCH_ALLOC_GRANULARITY` (*void*); [Host Hook]

This host hook returns the alignment required for allocating virtual memory. Usually this is the same as getpagesize, but on some hosts the alignment for reserving memory differs from the pagesize for committing memory.

18.2 Host Filesystem

GCC needs to know a number of things about the semantics of the host machine's filesystem. Filesystems with Unix and MS-DOS semantics are automatically detected. For other systems, you can define the following macros in '`xm-machine.h`'.

`HAVE_DOS_BASED_FILE_SYSTEM`
: This macro is automatically defined by '`system.h`' if the host file system obeys the semantics defined by MS-DOS instead of Unix. DOS file systems are case insensitive, file specifications may begin with a drive letter, and both forward slash and backslash ('`/`' and '`\`') are directory separators.

`DIR_SEPARATOR`
`DIR_SEPARATOR_2`
: If defined, these macros expand to character constants specifying separators for directory names within a file specification. '`system.h`' will automatically give them appropriate values on Unix and MS-DOS file systems. If your file system is neither of these, define one or both appropriately in '`xm-machine.h`'.

  However, operating systems like VMS, where constructing a pathname is more complicated than just stringing together directory names separated by a special character, should not define either of these macros.

`PATH_SEPARATOR`
: If defined, this macro should expand to a character constant specifying the separator for elements of search paths. The default value is a colon ('`:`'). DOS-based systems usually, but not always, use semicolon ('`;`').

`VMS`
: Define this macro if the host system is VMS.

`HOST_OBJECT_SUFFIX`
: Define this macro to be a C string representing the suffix for object files on your host machine. If you do not define this macro, GCC will use '`.o`' as the suffix for object files.

`HOST_EXECUTABLE_SUFFIX`
: Define this macro to be a C string representing the suffix for executable files on your host machine. If you do not define this macro, GCC will use the null string as the suffix for executable files.

`HOST_BIT_BUCKET`
: A pathname defined by the host operating system, which can be opened as a file and written to, but all the information written is discarded. This is commonly known as a *bit bucket* or *null device*. If you do not define this macro, GCC will use '`/dev/null`' as the bit bucket. If the host does not support a bit bucket, define this macro to an invalid filename.

`UPDATE_PATH_HOST_CANONICALIZE (path)`
: If defined, a C statement (sans semicolon) that performs host-dependent canonicalization when a path used in a compilation driver or preprocessor is canonicalized. *path* is a malloc-ed path to be canonicalized. If the C statement does canonicalize *path* into a different buffer, the old path should be freed and the new buffer should have been allocated with malloc.

`DUMPFILE_FORMAT`

Define this macro to be a C string representing the format to use for constructing the index part of debugging dump file names. The resultant string must fit in fifteen bytes. The full filename will be the concatenation of: the prefix of the assembler file name, the string resulting from applying this format to an index number, and a string unique to each dump file kind, e.g. '`rtl`'.

If you do not define this macro, GCC will use '`.%02d.`'. You should define this macro if using the default will create an invalid file name.

`DELETE_IF_ORDINARY`

Define this macro to be a C statement (sans semicolon) that performs host-dependent removal of ordinary temp files in the compilation driver.

If you do not define this macro, GCC will use the default version. You should define this macro if the default version does not reliably remove the temp file as, for example, on VMS which allows multiple versions of a file.

`HOST_LACKS_INODE_NUMBERS`

Define this macro if the host filesystem does not report meaningful inode numbers in struct stat.

18.3 Host Misc

`FATAL_EXIT_CODE`

A C expression for the status code to be returned when the compiler exits after serious errors. The default is the system-provided macro '`EXIT_FAILURE`', or '`1`' if the system doesn't define that macro. Define this macro only if these defaults are incorrect.

`SUCCESS_EXIT_CODE`

A C expression for the status code to be returned when the compiler exits without serious errors. (Warnings are not serious errors.) The default is the system-provided macro '`EXIT_SUCCESS`', or '`0`' if the system doesn't define that macro. Define this macro only if these defaults are incorrect.

`USE_C_ALLOCA`

Define this macro if GCC should use the C implementation of `alloca` provided by '`libiberty.a`'. This only affects how some parts of the compiler itself allocate memory. It does not change code generation.

When GCC is built with a compiler other than itself, the C `alloca` is always used. This is because most other implementations have serious bugs. You should define this macro only on a system where no stack-based `alloca` can possibly work. For instance, if a system has a small limit on the size of the stack, GCC's builtin `alloca` will not work reliably.

`COLLECT2_HOST_INITIALIZATION`

If defined, a C statement (sans semicolon) that performs host-dependent initialization when `collect2` is being initialized.

`GCC_DRIVER_HOST_INITIALIZATION`

If defined, a C statement (sans semicolon) that performs host-dependent initialization when a compilation driver is being initialized.

`HOST_LONG_LONG_FORMAT`
: If defined, the string used to indicate an argument of type `long long` to functions like `printf`. The default value is `"ll"`.

`HOST_LONG_FORMAT`
: If defined, the string used to indicate an argument of type `long` to functions like `printf`. The default value is `"l"`.

`HOST_PTR_PRINTF`
: If defined, the string used to indicate an argument of type `void *` to functions like `printf`. The default value is `"%p"`.

In addition, if `configure` generates an incorrect definition of any of the macros in '`auto-host.h`', you can override that definition in a host configuration header. If you need to do this, first see if it is possible to fix `configure`.

19 Makefile Fragments

When you configure GCC using the '`configure`' script, it will construct the file '`Makefile`' from the template file '`Makefile.in`'. When it does this, it can incorporate makefile fragments from the '`config`' directory. These are used to set Makefile parameters that are not amenable to being calculated by autoconf. The list of fragments to incorporate is set by '`config.gcc`' (and occasionally '`config.build`' and '`config.host`'); See Section 6.3.2.2 [System Config], page 64.

Fragments are named either '`t-`*`target`*' or '`x-`*`host`*', depending on whether they are relevant to configuring GCC to produce code for a particular target, or to configuring GCC to run on a particular host. Here *target* and *host* are mnemonics which usually have some relationship to the canonical system name, but no formal connection.

If these files do not exist, it means nothing needs to be added for a given target or host. Most targets need a few '`t-`*`target`*' fragments, but needing '`x-`*`host`*' fragments is rare.

19.1 Target Makefile Fragments

Target makefile fragments can set these Makefile variables.

`LIBGCC2_CFLAGS`
: Compiler flags to use when compiling '`libgcc2.c`'.

`LIB2FUNCS_EXTRA`
: A list of source file names to be compiled or assembled and inserted into '`libgcc.a`'.

`CRTSTUFF_T_CFLAGS`
: Special flags used when compiling '`crtstuff.c`'. See Section 17.21.5 [Initialization], page 542.

`CRTSTUFF_T_CFLAGS_S`
: Special flags used when compiling '`crtstuff.c`' for shared linking. Used if you use '`crtbeginS.o`' and '`crtendS.o`' in `EXTRA-PARTS`. See Section 17.21.5 [Initialization], page 542.

`MULTILIB_OPTIONS`
: For some targets, invoking GCC in different ways produces objects that can not be linked together. For example, for some targets GCC produces both big and little endian code. For these targets, you must arrange for multiple versions of '`libgcc.a`' to be compiled, one for each set of incompatible options. When GCC invokes the linker, it arranges to link in the right version of '`libgcc.a`', based on the command line options used.

  The `MULTILIB_OPTIONS` macro lists the set of options for which special versions of '`libgcc.a`' must be built. Write options that are mutually incompatible side by side, separated by a slash. Write options that may be used together separated by a space. The build procedure will build all combinations of compatible options.

  For example, if you set `MULTILIB_OPTIONS` to '`m68000/m68020 msoft-float`', '`Makefile`' will build special versions of '`libgcc.a`' using the following sets of

options: '-m68000', '-m68020', '-msoft-float', '-m68000 -msoft-float', and '-m68020 -msoft-float'.

MULTILIB_DIRNAMES

If MULTILIB_OPTIONS is used, this variable specifies the directory names that should be used to hold the various libraries. Write one element in MULTILIB_DIRNAMES for each element in MULTILIB_OPTIONS. If MULTILIB_DIRNAMES is not used, the default value will be MULTILIB_OPTIONS, with all slashes treated as spaces.

MULTILIB_DIRNAMES describes the multilib directories using GCC conventions and is applied to directories that are part of the GCC installation. When multilib-enabled, the compiler will add a subdirectory of the form *prefix/multilib* before each directory in the search path for libraries and crt files.

For example, if MULTILIB_OPTIONS is set to 'm68000/m68020 msoft-float', then the default value of MULTILIB_DIRNAMES is 'm68000 m68020 msoft-float'. You may specify a different value if you desire a different set of directory names.

MULTILIB_MATCHES

Sometimes the same option may be written in two different ways. If an option is listed in MULTILIB_OPTIONS, GCC needs to know about any synonyms. In that case, set MULTILIB_MATCHES to a list of items of the form 'option=option' to describe all relevant synonyms. For example, 'm68000=mc68000 m68020=mc68020'.

MULTILIB_EXCEPTIONS

Sometimes when there are multiple sets of MULTILIB_OPTIONS being specified, there are combinations that should not be built. In that case, set MULTILIB_EXCEPTIONS to be all of the switch exceptions in shell case syntax that should not be built.

For example the ARM processor cannot execute both hardware floating point instructions and the reduced size THUMB instructions at the same time, so there is no need to build libraries with both of these options enabled. Therefore MULTILIB_EXCEPTIONS is set to:

```
*mthumb/*mhard-float*
```

MULTILIB_REQUIRED

Sometimes when there are only a few combinations are required, it would be a big effort to come up with a MULTILIB_EXCEPTIONS list to cover all undesired ones. In such a case, just listing all the required combinations in MULTILIB_REQUIRED would be more straightforward.

The way to specify the entries in MULTILIB_REQUIRED is same with the way used for MULTILIB_EXCEPTIONS, only this time what are required will be specified. Suppose there are multiple sets of MULTILIB_OPTIONS and only two combinations are required, one for ARMv7-M and one for ARMv7-R with hard floating-point ABI and FPU, the MULTILIB_REQUIRED can be set to:

```
MULTILIB_REQUIRED =  mthumb/march=armv7-m
MULTILIB_REQUIRED += march=armv7-r/mfloat-abi=hard/mfpu=vfpv3-d16
```

The MULTILIB_REQUIRED can be used together with MULTILIB_EXCEPTIONS. The option combinations generated from MULTILIB_OPTIONS will be filtered by MULTILIB_EXCEPTIONS and then by MULTILIB_REQUIRED.

MULTILIB_REUSE

Sometimes it is desirable to reuse one existing multilib for different sets of options. Such kind of reuse can minimize the number of multilib variants. And for some targets it is better to reuse an existing multilib than to fall back to default multilib when there is no corresponding multilib. This can be done by adding reuse rules to MULTILIB_REUSE.

A reuse rule is comprised of two parts connected by equality sign. The left part is option set used to build multilib and the right part is option set that will reuse this multilib. The order of options in the left part matters and should be same with those specified in MULTILIB_REQUIRED or aligned with order in MULTILIB_OPTIONS. There is no such limitation for options in right part as we don't build multilib from them. But the equality sign in both parts should be replaced with period.

The MULTILIB_REUSE is different from MULTILIB_MATCHES in that it sets up relations between two option sets rather than two options. Here is an example to demo how we reuse libraries built in Thumb mode for applications built in ARM mode:

```
MULTILIB_REUSE = mthumb/march.armv7-r=marm/march.armv7-r
```

Before the advent of MULTILIB_REUSE, GCC select multilib by comparing command line options with options used to build multilib. The MULTILIB_REUSE is complementary to that way. Only when the original comparison matches nothing it will work to see if it is OK to reuse some existing multilib.

MULTILIB_EXTRA_OPTS

Sometimes it is desirable that when building multiple versions of 'libgcc.a' certain options should always be passed on to the compiler. In that case, set MULTILIB_EXTRA_OPTS to be the list of options to be used for all builds. If you set this, you should probably set CRTSTUFF_T_CFLAGS to a dash followed by it.

MULTILIB_OSDIRNAMES

If MULTILIB_OPTIONS is used, this variable specifies a list of subdirectory names, that are used to modify the search path depending on the chosen multilib. Unlike MULTILIB_DIRNAMES, MULTILIB_OSDIRNAMES describes the multilib directories using operating systems conventions, and is applied to the directories such as lib or those in the LIBRARY_PATH environment variable. The format is either the same as of MULTILIB_DIRNAMES, or a set of mappings. When it is the same as MULTILIB_DIRNAMES, it describes the multilib directories using operating system conventions, rather than GCC conventions. When it is a set of mappings of the form *gccdir*=*osdir*, the left side gives the GCC convention and the right gives the equivalent OS defined location. If the *osdir* part begins with a '!', GCC will not search in the non-multilib directory and use exclusively the multilib directory. Otherwise, the compiler will examine the search path for libraries and crt files twice; the first time it will add *multilib* to each directory in the search path, the second it will not.

For configurations that support both multilib and multiarch, MULTILIB_OSDIRNAMES also encodes the multiarch name, thus subsuming MULTIARCH_DIRNAME. The multiarch name is appended to each directory name, separated by a colon (e.g. '../lib32:i386-linux-gnu').

Each multiarch subdirectory will be searched before the corresponding OS multilib directory, for example '/lib/i386-linux-gnu' before '/lib/../lib32'. The multiarch name will also be used to modify the system header search path, as explained for MULTIARCH_DIRNAME.

MULTIARCH_DIRNAME

This variable specifies the multiarch name for configurations that are multiarch-enabled but not multilibbed configurations.

The multiarch name is used to augment the search path for libraries, crt files and system header files with additional locations. The compiler will add a multiarch subdirectory of the form *prefix*/*multiarch* before each directory in the library and crt search path. It will also add two directories LOCAL_INCLUDE_DIR/*multiarch* and NATIVE_SYSTEM_HEADER_DIR/*multiarch*) to the system header search path, respectively before LOCAL_INCLUDE_DIR and NATIVE_SYSTEM_HEADER_DIR.

MULTIARCH_DIRNAME is not used for configurations that support both multilib and multiarch. In that case, multiarch names are encoded in MULTILIB_OSDIRNAMES instead.

More documentation about multiarch can be found at http://wiki.debian.org/Multiarch.

SPECS

Unfortunately, setting MULTILIB_EXTRA_OPTS is not enough, since it does not affect the build of target libraries, at least not the build of the default multilib. One possible work-around is to use DRIVER_SELF_SPECS to bring options from the 'specs' file as if they had been passed in the compiler driver command line. However, you don't want to be adding these options after the toolchain is installed, so you can instead tweak the 'specs' file that will be used during the toolchain build, while you still install the original, built-in 'specs'. The trick is to set SPECS to some other filename (say 'specs.install'), that will then be created out of the built-in specs, and introduce a 'Makefile' rule to generate the 'specs' file that's going to be used at build time out of your 'specs.install'.

T_CFLAGS

These are extra flags to pass to the C compiler. They are used both when building GCC, and when compiling things with the just-built GCC. This variable is deprecated and should not be used.

19.2 Host Makefile Fragments

The use of 'x-*host*' fragments is discouraged. You should only use it for makefile dependencies.

20 collect2

GCC uses a utility called collect2 on nearly all systems to arrange to call various initialization functions at start time.

The program collect2 works by linking the program once and looking through the linker output file for symbols with particular names indicating they are constructor functions. If it finds any, it creates a new temporary '.c' file containing a table of them, compiles it, and links the program a second time including that file.

The actual calls to the constructors are carried out by a subroutine called __main, which is called (automatically) at the beginning of the body of main (provided main was compiled with GNU CC). Calling __main is necessary, even when compiling C code, to allow linking C and C++ object code together. (If you use '-nostdlib', you get an unresolved reference to __main, since it's defined in the standard GCC library. Include '-lgcc' at the end of your compiler command line to resolve this reference.)

The program collect2 is installed as ld in the directory where the passes of the compiler are installed. When collect2 needs to find the *real* ld, it tries the following file names:

- a hard coded linker file name, if GCC was configured with the '--with-ld' option.
- 'real-ld' in the directories listed in the compiler's search directories.
- 'real-ld' in the directories listed in the environment variable PATH.
- The file specified in the REAL_LD_FILE_NAME configuration macro, if specified.
- 'ld' in the compiler's search directories, except that collect2 will not execute itself recursively.
- 'ld' in PATH.

"The compiler's search directories" means all the directories where gcc searches for passes of the compiler. This includes directories that you specify with '-B'.

Cross-compilers search a little differently:

- 'real-ld' in the compiler's search directories.
- '*target*-real-ld' in PATH.
- The file specified in the REAL_LD_FILE_NAME configuration macro, if specified.
- 'ld' in the compiler's search directories.
- '*target*-ld' in PATH.

collect2 explicitly avoids running ld using the file name under which collect2 itself was invoked. In fact, it remembers up a list of such names—in case one copy of collect2 finds another copy (or version) of collect2 installed as ld in a second place in the search path.

collect2 searches for the utilities nm and strip using the same algorithm as above for ld.

21 Standard Header File Directories

`GCC_INCLUDE_DIR` means the same thing for native and cross. It is where GCC stores its private include files, and also where GCC stores the fixed include files. A cross compiled GCC runs `fixincludes` on the header files in '`$(tooldir)/include`'. (If the cross compilation header files need to be fixed, they must be installed before GCC is built. If the cross compilation header files are already suitable for GCC, nothing special need be done).

`GPLUSPLUS_INCLUDE_DIR` means the same thing for native and cross. It is where `g++` looks first for header files. The C++ library installs only target independent header files in that directory.

`LOCAL_INCLUDE_DIR` is used only by native compilers. GCC doesn't install anything there. It is normally '`/usr/local/include`'. This is where local additions to a packaged system should place header files.

`CROSS_INCLUDE_DIR` is used only by cross compilers. GCC doesn't install anything there.

`TOOL_INCLUDE_DIR` is used for both native and cross compilers. It is the place for other packages to install header files that GCC will use. For a cross-compiler, this is the equivalent of '`/usr/include`'. When you build a cross-compiler, `fixincludes` processes any header files in this directory.

22 Memory Management and Type Information

GCC uses some fairly sophisticated memory management techniques, which involve determining information about GCC's data structures from GCC's source code and using this information to perform garbage collection and implement precompiled headers.

A full C++ parser would be too complicated for this task, so a limited subset of C++ is interpreted and special markers are used to determine what parts of the source to look at. All `struct`, `union` and `template` structure declarations that define data structures that are allocated under control of the garbage collector must be marked. All global variables that hold pointers to garbage-collected memory must also be marked. Finally, all global variables that need to be saved and restored by a precompiled header must be marked. (The precompiled header mechanism can only save static variables if they're scalar. Complex data structures must be allocated in garbage-collected memory to be saved in a precompiled header.)

The full format of a marker is

```
GTY (([option] [(param)], [option] [(param)] ...))
```

but in most cases no options are needed. The outer double parentheses are still necessary, though: `GTY(())`. Markers can appear:

- In a structure definition, before the open brace;
- In a global variable declaration, after the keyword `static` or `extern`; and
- In a structure field definition, before the name of the field.

Here are some examples of marking simple data structures and globals.

```
struct GTY(()) tag
{
  fields...
};

typedef struct GTY(()) tag
{
  fields...
} *typename;

static GTY(()) struct tag *list;   /* points to GC memory */
static GTY(()) int counter;        /* save counter in a PCH */
```

The parser understands simple typedefs such as `typedef struct tag *name;` and `typedef int name;`. These don't need to be marked.

Since `gengtype`'s understanding of C++ is limited, there are several constructs and declarations that are not supported inside classes/structures marked for automatic GC code generation. The following C++ constructs produce a `gengtype` error on structures/classes marked for automatic GC code generation:

- Type definitions inside classes/structures are not supported.
- Enumerations inside classes/structures are not supported.

If you have a class or structure using any of the above constructs, you need to mark that class as `GTY ((user))` and provide your own marking routines (see section Section 22.3 [User GC], page 610 for details).

It is always valid to include function definitions inside classes. Those are always ignored by `gengtype`, as it only cares about data members.

22.1 The Inside of a GTY(())

Sometimes the C code is not enough to fully describe the type structure. Extra information can be provided with GTY options and additional markers. Some options take a parameter, which may be either a string or a type name, depending on the parameter. If an option takes no parameter, it is acceptable either to omit the parameter entirely, or to provide an empty string as a parameter. For example, GTY ((skip)) and GTY ((skip (""))) are equivalent.

When the parameter is a string, often it is a fragment of C code. Four special escapes may be used in these strings, to refer to pieces of the data structure being marked:

%h The current structure.

%1 The structure that immediately contains the current structure.

%0 The outermost structure that contains the current structure.

%a A partial expression of the form [i1][i2]... that indexes the array item currently being marked.

For instance, suppose that you have a structure of the form

```
struct A {
  ...
};
struct B {
  struct A foo[12];
};
```

and b is a variable of type struct B. When marking 'b.foo[11]', %h would expand to 'b.foo[11]', %0 and %1 would both expand to 'b', and %a would expand to '[11]'.

As in ordinary C, adjacent strings will be concatenated; this is helpful when you have a complicated expression.

```
GTY ((chain_next ("TREE_CODE (&%h.generic) == INTEGER_TYPE"
                  " ? TYPE_NEXT_VARIANT (&%h.generic)"
                  " : TREE_CHAIN (&%h.generic)")))
```

The available options are:

length ("*expression*")

There are two places the type machinery will need to be explicitly told the length of an array of non-atomic objects. The first case is when a structure ends in a variable-length array, like this:

```
struct GTY(()) rtvec_def {
  int num_elem;         /* number of elements */
  rtx GTY ((length ("%h.num_elem"))) elem[1];
};
```

In this case, the length option is used to override the specified array length (which should usually be 1). The parameter of the option is a fragment of C code that calculates the length.

The second case is when a structure or a global variable contains a pointer to an array, like this:

```
struct gimple_omp_for_iter * GTY((length ("%h.collapse"))) iter;
```

In this case, iter has been allocated by writing something like

```
x->iter = ggc_alloc_cleared_vec_gimple_omp_for_iter (collapse);
```

and the `collapse` provides the length of the field.

This second use of `length` also works on global variables, like:

```
static GTY((length("reg_known_value_size"))) rtx *reg_known_value;
```

Note that the `length` option is only meant for use with arrays of non-atomic objects, that is, objects that contain pointers pointing to other GTY-managed objects. For other GC-allocated arrays and strings you should use `atomic`.

`skip`

If `skip` is applied to a field, the type machinery will ignore it. This is somewhat dangerous; the only safe use is in a union when one field really isn't ever used.

`desc ("`*expression*`")`
`tag ("`*constant*`")`
`default`

The type machinery needs to be told which field of a `union` is currently active. This is done by giving each field a constant `tag` value, and then specifying a discriminator using `desc`. The value of the expression given by `desc` is compared against each `tag` value, each of which should be different. If no `tag` is matched, the field marked with `default` is used if there is one, otherwise no field in the union will be marked.

In the `desc` option, the "current structure" is the union that it discriminates. Use `%1` to mean the structure containing it. There are no escapes available to the `tag` option, since it is a constant.

For example,

```
struct GTY(()) tree_binding
{
  struct tree_common common;
  union tree_binding_u {
    tree GTY ((tag ("0"))) scope;
    struct cp_binding_level * GTY ((tag ("1"))) level;
  } GTY ((desc ("BINDING_HAS_LEVEL_P ((tree)&%0)"))) xscope;
  tree value;
};
```

In this example, the value of BINDING_HAS_LEVEL_P when applied to a `struct tree_binding *` is presumed to be 0 or 1. If 1, the type mechanism will treat the field `level` as being present and if 0, will treat the field `scope` as being present.

The `desc` and `tag` options can also be used for inheritance to denote which subclass an instance is. See Section 22.2 [Inheritance and GTY], page 609 for more information.

`param_is (`*type*`)`
`use_param`

Sometimes it's convenient to define some data structure to work on generic pointers (that is, `PTR`) and then use it with a specific type. `param_is` specifies the real type pointed to, and `use_param` says where in the generic data structure that type should be put.

For instance, to have a `htab_t` that points to trees, one would write the definition of `htab_t` like this:

```
typedef struct GTY(()) {
  ...
  void ** GTY ((use_param, ...)) entries;
  ...
} htab_t;
```

and then declare variables like this:

```
static htab_t GTY ((param_is (union tree_node))) ict;
```

`param`*n*`_is (`*type*`)`
`use_param`*n*

In more complicated cases, the data structure might need to work on several different types, which might not necessarily all be pointers. For this, `param1_is` through `param9_is` may be used to specify the real type of a field identified by `use_param1` through `use_param9`.

`use_params`

When a structure contains another structure that is parameterized, there's no need to do anything special, the inner structure inherits the parameters of the outer one. When a structure contains a pointer to a parameterized structure, the type machinery won't automatically detect this (it could, it just doesn't yet), so it's necessary to tell it that the pointed-to structure should use the same parameters as the outer structure. This is done by marking the pointer with the `use_params` option.

`deletable`

`deletable`, when applied to a global variable, indicates that when garbage collection runs, there's no need to mark anything pointed to by this variable, it can just be set to `NULL` instead. This is used to keep a list of free structures around for re-use.

`if_marked ("`*expression*`")`

Suppose you want some kinds of object to be unique, and so you put them in a hash table. If garbage collection marks the hash table, these objects will never be freed, even if the last other reference to them goes away. GGC has special handling to deal with this: if you use the `if_marked` option on a global hash table, GGC will call the routine whose name is the parameter to the option on each hash table entry. If the routine returns nonzero, the hash table entry will be marked as usual. If the routine returns zero, the hash table entry will be deleted.

The routine `ggc_marked_p` can be used to determine if an element has been marked already; in fact, the usual case is to use `if_marked ("ggc_marked_p")`.

`mark_hook ("`*hook-routine-name*`")`

If provided for a structure or union type, the given *hook-routine-name* (between double-quotes) is the name of a routine called when the garbage collector has just marked the data as reachable. This routine should not change the data, or call any ggc routine. Its only argument is a pointer to the just marked (const) structure or union.

`maybe_undef`

When applied to a field, `maybe_undef` indicates that it's OK if the structure that this fields points to is never defined, so long as this field is always `NULL`. This is used to avoid requiring backends to define certain optional structures. It doesn't work with language frontends.

`nested_ptr (`*type*`, "`*to expression*`", "`*from expression*`")`

The type machinery expects all pointers to point to the start of an object. Sometimes for abstraction purposes it's convenient to have a pointer which points inside an object. So long as it's possible to convert the original object to and from the pointer, such pointers can still be used. *type* is the type of the original object, the *to expression* returns the pointer given the original object, and the *from expression* returns the original object given the pointer. The pointer will be available using the `%h` escape.

`chain_next ("`*expression*`")`
`chain_prev ("`*expression*`")`
`chain_circular ("`*expression*`")`

It's helpful for the type machinery to know if objects are often chained together in long lists; this lets it generate code that uses less stack space by iterating along the list instead of recursing down it. `chain_next` is an expression for the next item in the list, `chain_prev` is an expression for the previous item. For singly linked lists, use only `chain_next`; for doubly linked lists, use both. The machinery requires that taking the next item of the previous item gives the original item. `chain_circular` is similar to `chain_next`, but can be used for circular single linked lists.

`reorder ("`*function name*`")`

Some data structures depend on the relative ordering of pointers. If the precompiled header machinery needs to change that ordering, it will call the function referenced by the `reorder` option, before changing the pointers in the object that's pointed to by the field the option applies to. The function must take four arguments, with the signature '`void *, void *, gt_pointer_operator, void *`'. The first parameter is a pointer to the structure that contains the object being updated, or the object itself if there is no containing structure. The second parameter is a cookie that should be ignored. The third parameter is a routine that, given a pointer, will update it to its correct new value. The fourth parameter is a cookie that must be passed to the second parameter.

PCH cannot handle data structures that depend on the absolute values of pointers. `reorder` functions can be expensive. When possible, it is better to depend on properties of the data, like an ID number or the hash of a string instead.

`variable_size`

The type machinery expects the types to be of constant size. When this is not true, for example, with structs that have array fields or unions, the type machinery cannot tell how many bytes need to be allocated at each allocation. The `variable_size` is used to mark such types. The type machinery then provides allocators that take a parameter indicating an exact size of object

being allocated. Note that the size must be provided in bytes whereas the `length` option works with array lengths in number of elements.

For example,

```
struct GTY((variable_size)) sorted_fields_type {
  int len;
  tree GTY((length ("%h.len"))) elts[1];
};
```

Then the objects of `struct sorted_fields_type` are allocated in GC memory as follows:

```
field_vec = ggc_alloc_sorted_fields_type (size);
```

If *field_vec->elts* stores *n* elements, then *size* could be calculated as follows:

```
size_t size = sizeof (struct sorted_fields_type) + n * sizeof (tree);
```

`atomic`

The `atomic` option can only be used with pointers. It informs the GC machinery that the memory that the pointer points to does not contain any pointers, and hence it should be treated by the GC and PCH machinery as an "atomic" block of memory that does not need to be examined when scanning memory for pointers. In particular, the machinery will not scan that memory for pointers to mark them as reachable (when marking pointers for GC) or to relocate them (when writing a PCH file).

The `atomic` option differs from the `skip` option. `atomic` keeps the memory under Garbage Collection, but makes the GC ignore the contents of the memory. `skip` is more drastic in that it causes the pointer and the memory to be completely ignored by the Garbage Collector. So, memory marked as `atomic` is automatically freed when no longer reachable, while memory marked as `skip` is not.

The `atomic` option must be used with great care, because all sorts of problem can occur if used incorrectly, that is, if the memory the pointer points to does actually contain a pointer.

Here is an example of how to use it:

```
struct GTY(()) my_struct {
  int number_of_elements;
  unsigned int * GTY ((atomic)) elements;
};
```

In this case, `elements` is a pointer under GC, and the memory it points to needs to be allocated using the Garbage Collector, and will be freed automatically by the Garbage Collector when it is no longer referenced. But the memory that the pointer points to is an array of `unsigned int` elements, and the GC must not try to scan it to find pointers to mark or relocate, which is why it is marked with the `atomic` option.

Note that, currently, global variables can not be marked with `atomic`; only fields of a struct can. This is a known limitation. It would be useful to be able to mark global pointers with `atomic` to make the PCH machinery aware of them so that they are saved and restored correctly to PCH files.

`special ("name")`

The `special` option is used to mark types that have to be dealt with by special case machinery. The parameter is the name of the special case. See '`gengtype.c`' for further details. Avoid adding new special cases unless there is no other alternative.

`user`

The `user` option indicates that the code to mark structure fields is completely handled by user-provided routines. See section Section 22.3 [User GC], page 610 for details on what functions need to be provided.

22.2 Support for inheritance

gengtype has some support for simple class hierarchies. You can use this to have gengtype autogenerate marking routines, provided:

- There must be a concrete base class, with a discriminator expression that can be used to identify which subclass an instance is.
- Only single inheritance is used.
- None of the classes within the hierarchy are templates.

If your class hierarchy does not fit in this pattern, you must use Section 22.3 [User GC], page 610 instead.

The base class and its discriminator must be identified using the "desc" option. Each concrete subclass must use the "tag" option to identify which value of the discriminator it corresponds to.

Every class in the hierarchy must have a `GTY(())` marker, as gengtype will only attempt to parse classes that have such a marker[1].

```
class GTY((desc("%h.kind"), tag("0"))) example_base
{
public:
    int kind;
    tree a;
};

class GTY((tag("1")) some_subclass : public example_base
{
public:
    tree b;
};

class GTY((tag("2")) some_other_subclass : public example_base
{
public:
    tree c;
};
```

The generated marking routines for the above will contain a "switch" on "kind", visiting all appropriate fields. For example, if kind is 2, it will cast to "some_other_subclass" and visit fields a, b, and c.

[1] Classes lacking such a marker will not be identified as being part of the hierarchy, and so the marking routines will not handle them, leading to a assertion failure within the marking routines due to an unknown tag value (assuming that assertions are enabled).

22.3 Support for user-provided GC marking routines

The garbage collector supports types for which no automatic marking code is generated. For these types, the user is required to provide three functions: one to act as a marker for garbage collection, and two functions to act as marker and pointer walker for pre-compiled headers.

Given a structure `struct GTY((user)) my_struct`, the following functions should be defined to mark `my_struct`:

```
void gt_ggc_mx (my_struct *p)
{
  /* This marks field 'fld'.  */
  gt_ggc_mx (p->fld);
}

void gt_pch_nx (my_struct *p)
{
  /* This marks field 'fld'.  */
  gt_pch_nx (tp->fld);
}

void gt_pch_nx (my_struct *p, gt_pointer_operator op, void *cookie)
{
  /* For every field 'fld', call the given pointer operator.  */
  op (&(tp->fld), cookie);
}
```

In general, each marker `M` should call `M` for every pointer field in the structure. Fields that are not allocated in GC or are not pointers must be ignored.

For embedded lists (e.g., structures with a `next` or `prev` pointer), the marker must follow the chain and mark every element in it.

Note that the rules for the pointer walker `gt_pch_nx (my_struct *, gt_pointer_operator, void *)` are slightly different. In this case, the operation `op` must be applied to the *address* of every pointer field.

22.3.1 User-provided marking routines for template types

When a template type `TP` is marked with `GTY`, all instances of that type are considered user-provided types. This means that the individual instances of `TP` do not need to be marked with `GTY`. The user needs to provide template functions to mark all the fields of the type.

The following code snippets represent all the functions that need to be provided. Note that type `TP` may reference to more than one type. In these snippets, there is only one type `T`, but there could be more.

```
template<typename T>
void gt_ggc_mx (TP<T> *tp)
{
  extern void gt_ggc_mx (T&);

  /* This marks field 'fld' of type 'T'.  */
  gt_ggc_mx (tp->fld);
}

template<typename T>
void gt_pch_nx (TP<T> *tp)
{
```

```
  extern void gt_pch_nx (T&);

  /* This marks field 'fld' of type 'T'.  */
  gt_pch_nx (tp->fld);
}

template<typename T>
void gt_pch_nx (TP<T *> *tp, gt_pointer_operator op, void *cookie)
{
  /* For every field 'fld' of 'tp' with type 'T *', call the given
     pointer operator.  */
  op (&(tp->fld), cookie);
}

template<typename T>
void gt_pch_nx (TP<T> *tp, gt_pointer_operator, void *cookie)
{
  extern void gt_pch_nx (T *, gt_pointer_operator, void *);

  /* For every field 'fld' of 'tp' with type 'T', call the pointer
     walker for all the fields of T.  */
  gt_pch_nx (&(tp->fld), op, cookie);
}
```

Support for user-defined types is currently limited. The following restrictions apply:

1. Type `TP` and all the argument types `T` must be marked with `GTY`.
2. Type `TP` can only have type names in its argument list.
3. The pointer walker functions are different for `TP<T>` and `TP<T *>`. In the case of `TP<T>`, references to `T` must be handled by calling `gt_pch_nx` (which will, in turn, walk all the pointers inside fields of `T`). In the case of `TP<T *>`, references to `T *` must be handled by calling the `op` function on the address of the pointer (see the code snippets above).

22.4 Marking Roots for the Garbage Collector

In addition to keeping track of types, the type machinery also locates the global variables (*roots*) that the garbage collector starts at. Roots must be declared using one of the following syntaxes:

- `extern GTY(([`*options*`])) `*type name*`;`
- `static GTY(([`*options*`])) `*type name*`;`

The syntax

- `GTY(([`*options*`])) `*type name*`;`

is *not* accepted. There should be an `extern` declaration of such a variable in a header somewhere—mark that, not the definition. Or, if the variable is only used in one file, make it `static`.

22.5 Source Files Containing Type Information

Whenever you add `GTY` markers to a source file that previously had none, or create a new source file containing `GTY` markers, there are three things you need to do:

1. You need to add the file to the list of source files the type machinery scans. There are four cases:

   a. For a back-end file, this is usually done automatically; if not, you should add it to `target_gtfiles` in the appropriate port's entries in '`config.gcc`'.
   b. For files shared by all front ends, add the filename to the `GTFILES` variable in '`Makefile.in`'.
   c. For files that are part of one front end, add the filename to the `gtfiles` variable defined in the appropriate '`config-lang.in`'. Headers should appear before non-headers in this list.
   d. For files that are part of some but not all front ends, add the filename to the `gtfiles` variable of *all* the front ends that use it.
2. If the file was a header file, you'll need to check that it's included in the right place to be visible to the generated files. For a back-end header file, this should be done automatically. For a front-end header file, it needs to be included by the same file that includes '`gtype-`*`lang`*`.h`'. For other header files, it needs to be included in '`gtype-desc.c`', which is a generated file, so add it to `ifiles` in `open_base_file` in '`gengtype.c`'.

   For source files that aren't header files, the machinery will generate a header file that should be included in the source file you just changed. The file will be called '`gt-`*`path`*`.h`' where *path* is the pathname relative to the '`gcc`' directory with slashes replaced by `-`, so for example the header file to be included in '`cp/parser.c`' is called '`gt-cp-parser.c`'. The generated header file should be included after everything else in the source file. Don't forget to mention this file as a dependency in the '`Makefile`'!

For language frontends, there is another file that needs to be included somewhere. It will be called '`gtype-`*`lang`*`.h`', where *lang* is the name of the subdirectory the language is contained in.

Plugins can add additional root tables. Run the `gengtype` utility in plugin mode as `gengtype -P pluginout.h` *`source-dir file-list plugin*.c`* with your plugin files *plugin*.c* using `GTY` to generate the *pluginout.h* file. The GCC build tree is needed to be present in that mode.

22.6 How to invoke the garbage collector

The GCC garbage collector GGC is only invoked explicitly. In contrast with many other garbage collectors, it is not implicitly invoked by allocation routines when a lot of memory has been consumed. So the only way to have GGC reclaim storage is to call the `ggc_collect` function explicitly. This call is an expensive operation, as it may have to scan the entire heap. Beware that local variables (on the GCC call stack) are not followed by such an invocation (as many other garbage collectors do): you should reference all your data from static or external `GTY`-ed variables, and it is advised to call `ggc_collect` with a shallow call stack. The GGC is an exact mark and sweep garbage collector (so it does not scan the call stack for pointers). In practice GCC passes don't often call `ggc_collect` themselves, because it is called by the pass manager between passes.

At the time of the `ggc_collect` call all pointers in the GC-marked structures must be valid or `NULL`. In practice this means that there should not be uninitialized pointer fields in the structures even if your code never reads or writes those fields at a particular instance. One way to ensure this is to use cleared versions of allocators unless all the fields are initialized manually immediately after allocation.

22.7 Troubleshooting the garbage collector

With the current garbage collector implementation, most issues should show up as GCC compilation errors. Some of the most commonly encountered issues are described below.

- Gengtype does not produce allocators for a `GTY`-marked type. Gengtype checks if there is at least one possible path from GC roots to at least one instance of each type before outputting allocators. If there is no such path, the `GTY` markers will be ignored and no allocators will be output. Solve this by making sure that there exists at least one such path. If creating it is unfeasible or raises a "code smell", consider if you really must use GC for allocating such type.
- Link-time errors about undefined `gt_ggc_r_foo_bar` and similarly-named symbols. Check if your '`foo_bar`' source file has `#include "gt-foo_bar.h"` as its very last line.

23 Plugins

GCC plugin is a loadable module that provides extra features to the compiler, which they can further pass around as a shareable module.

GCC plugins provide developers with a rich subset of the GCC API to allow them to extend GCC as they see fit. Whether it is writing an additional optimization pass, transforming code, or analyzing information, plugins can be quite useful.

23.1 Loading Plugins

Plugins are supported on platforms that support '`-ldl -rdynamic`'. They are loaded by the compiler using `dlopen` and invoked at pre-determined locations in the compilation process.

Plugins are loaded with

'`-fplugin=/path/to/name.so`' '`-fplugin-arg-name-key1[=value1]`'

The plugin arguments are parsed by GCC and passed to respective plugins as key-value pairs. Multiple plugins can be invoked by specifying multiple '`-fplugin`' arguments.

A plugin can be simply given by its short name (no dots or slashes). When simply passing '`-fplugin=name`', the plugin is loaded from the '`plugin`' directory, so '`-fplugin=name`' is the same as '`-fplugin=`` gcc -print-file-name=plugin`/name.so`', using backquote shell syntax to query the '`plugin`' directory.

23.2 Plugin API

Plugins are activated by the compiler at specific events as defined in '`gcc-plugin.h`'. For each event of interest, the plugin should call `register_callback` specifying the name of the event and address of the callback function that will handle that event.

The header '`gcc-plugin.h`' must be the first gcc header to be included.

23.2.1 Plugin license check

Every plugin should define the global symbol `plugin_is_GPL_compatible` to assert that it has been licensed under a GPL-compatible license. If this symbol does not exist, the compiler will emit a fatal error and exit with the error message:

```
fatal error: plugin name is not licensed under a GPL-compatible license
name: undefined symbol: plugin_is_GPL_compatible
compilation terminated
```

The declared type of the symbol should be int, to match a forward declaration in '`gcc-plugin.h`' that suppresses C++ mangling. It does not need to be in any allocated section, though. The compiler merely asserts that the symbol exists in the global scope. Something like this is enough:

```
int plugin_is_GPL_compatible;
```

23.2.2 Plugin initialization

Every plugin should export a function called `plugin_init` that is called right after the plugin is loaded. This function is responsible for registering all the callbacks required by the plugin and do any other required initialization.

This function is called from `compile_file` right before invoking the parser. The arguments to `plugin_init` are:

- `plugin_info`: Plugin invocation information.
- `version`: GCC version.

The `plugin_info` struct is defined as follows:

```
struct plugin_name_args
{
  char *base_name;              /* Short name of the plugin
                                   (filename without .so suffix). */
  const char *full_name;        /* Path to the plugin as specified with
                                   -fplugin=. */
  int argc;                     /* Number of arguments specified with
                                   -fplugin-arg-.... */
  struct plugin_argument *argv; /* Array of ARGC key-value pairs. */
  const char *version;          /* Version string provided by plugin. */
  const char *help;             /* Help string provided by plugin. */
}
```

If initialization fails, `plugin_init` must return a non-zero value. Otherwise, it should return 0.

The version of the GCC compiler loading the plugin is described by the following structure:

```
struct plugin_gcc_version
{
  const char *basever;
  const char *datestamp;
  const char *devphase;
  const char *revision;
  const char *configuration_arguments;
};
```

The function `plugin_default_version_check` takes two pointers to such structure and compare them field by field. It can be used by the plugin's `plugin_init` function.

The version of GCC used to compile the plugin can be found in the symbol `gcc_version` defined in the header '`plugin-version.h`'. The recommended version check to perform looks like

```
#include "plugin-version.h"
...

int
plugin_init (struct plugin_name_args *plugin_info,
             struct plugin_gcc_version *version)
{
  if (!plugin_default_version_check (version, &gcc_version))
    return 1;

}
```

but you can also check the individual fields if you want a less strict check.

23.2.3 Plugin callbacks

Callback functions have the following prototype:

```
/* The prototype for a plugin callback function.
     gcc_data  - event-specific data provided by GCC
     user_data - plugin-specific data provided by the plug-in.  */
typedef void (*plugin_callback_func)(void *gcc_data, void *user_data);
```

Callbacks can be invoked at the following pre-determined events:

```
enum plugin_event
{
  PLUGIN_PASS_MANAGER_SETUP,    /* To hook into pass manager.  */
  PLUGIN_FINISH_TYPE,           /* After finishing parsing a type.  */
  PLUGIN_FINISH_DECL,           /* After finishing parsing a declaration. */
  PLUGIN_FINISH_UNIT,           /* Useful for summary processing.  */
  PLUGIN_PRE_GENERICIZE,        /* Allows to see low level AST in C and C++ frontends.  */
  PLUGIN_FINISH,                /* Called before GCC exits.  */
  PLUGIN_INFO,                  /* Information about the plugin. */
  PLUGIN_GGC_START,             /* Called at start of GCC Garbage Collection. */
  PLUGIN_GGC_MARKING,           /* Extend the GGC marking. */
  PLUGIN_GGC_END,               /* Called at end of GGC. */
  PLUGIN_REGISTER_GGC_ROOTS,    /* Register an extra GGC root table. */
  PLUGIN_REGISTER_GGC_CACHES,   /* Register an extra GGC cache table. */
  PLUGIN_ATTRIBUTES,            /* Called during attribute registration */
  PLUGIN_START_UNIT,            /* Called before processing a translation unit.  */
  PLUGIN_PRAGMAS,               /* Called during pragma registration. */
  /* Called before first pass from all_passes.  */
  PLUGIN_ALL_PASSES_START,
  /* Called after last pass from all_passes.  */
  PLUGIN_ALL_PASSES_END,
  /* Called before first ipa pass.  */
  PLUGIN_ALL_IPA_PASSES_START,
  /* Called after last ipa pass.  */
  PLUGIN_ALL_IPA_PASSES_END,
  /* Allows to override pass gate decision for current_pass.  */
  PLUGIN_OVERRIDE_GATE,
  /* Called before executing a pass.  */
  PLUGIN_PASS_EXECUTION,
  /* Called before executing subpasses of a GIMPLE_PASS in
     execute_ipa_pass_list.  */
  PLUGIN_EARLY_GIMPLE_PASSES_START,
  /* Called after executing subpasses of a GIMPLE_PASS in
     execute_ipa_pass_list.  */
  PLUGIN_EARLY_GIMPLE_PASSES_END,
  /* Called when a pass is first instantiated.  */
  PLUGIN_NEW_PASS,
/* Called when a file is #include-d or given via the #line directive.
   This could happen many times.  The event data is the included file path,
   as a const char* pointer.  */
  PLUGIN_INCLUDE_FILE,

  PLUGIN_EVENT_FIRST_DYNAMIC    /* Dummy event used for indexing callback
                                   array.  */
};
```

In addition, plugins can also look up the enumerator of a named event, and / or generate new events dynamically, by calling the function `get_named_event_id`.

To register a callback, the plugin calls `register_callback` with the arguments:

- `char *name`: Plugin name.
- `int event`: The event code.
- `plugin_callback_func callback`: The function that handles `event`.
- `void *user_data`: Pointer to plugin-specific data.

For the *PLUGIN_PASS_MANAGER_SETUP*, *PLUGIN_INFO*, *PLUGIN_REGISTER_GGC_ROOTS* and *PLUGIN_REGISTER_GGC_CACHES* pseudo-events the `callback` should be null, and the `user_data` is specific.

When the *PLUGIN_PRAGMAS* event is triggered (with a null pointer as data from GCC), plugins may register their own pragmas. Notice that pragmas are not available from '`lto1`', so plugins used with `-flto` option to GCC during link-time optimization cannot use pragmas and do not even see functions like `c_register_pragma` or `pragma_lex`.

The *PLUGIN_INCLUDE_FILE* event, with a `const char*` file path as GCC data, is triggered for processing of `#include` or `#line` directives.

The *PLUGIN_FINISH* event is the last time that plugins can call GCC functions, notably emit diagnostics with `warning`, `error` etc.

23.3 Interacting with the pass manager

There needs to be a way to add/reorder/remove passes dynamically. This is useful for both analysis plugins (plugging in after a certain pass such as CFG or an IPA pass) and optimization plugins.

Basic support for inserting new passes or replacing existing passes is provided. A plugin registers a new pass with GCC by calling `register_callback` with the `PLUGIN_PASS_MANAGER_SETUP` event and a pointer to a `struct register_pass_info` object defined as follows

```
enum pass_positioning_ops
{
  PASS_POS_INSERT_AFTER,  // Insert after the reference pass.
  PASS_POS_INSERT_BEFORE, // Insert before the reference pass.
  PASS_POS_REPLACE        // Replace the reference pass.
};

struct register_pass_info
{
  struct opt_pass *pass;            /* New pass provided by the plugin.  */
  const char *reference_pass_name;  /* Name of the reference pass for hooking
                                       up the new pass.  */
  int ref_pass_instance_number;     /* Insert the pass at the specified
                                       instance number of the reference pass.  */
                                    /* Do it for every instance if it is 0.  */
  enum pass_positioning_ops pos_op; /* how to insert the new pass.  */
};


/* Sample plugin code that registers a new pass.  */
int
plugin_init (struct plugin_name_args *plugin_info,
             struct plugin_gcc_version *version)
{
  struct register_pass_info pass_info;

  ...

  /* Code to fill in the pass_info object with new pass information.  */

  ...
```

```
  /* Register the new pass.  */
  register_callback (plugin_info->base_name, PLUGIN_PASS_MANAGER_SETUP, NULL, &pass_info);

  ...
}
```

23.4 Interacting with the GCC Garbage Collector

Some plugins may want to be informed when GGC (the GCC Garbage Collector) is running. They can register callbacks for the `PLUGIN_GGC_START` and `PLUGIN_GGC_END` events (for which the callback is called with a null `gcc_data`) to be notified of the start or end of the GCC garbage collection.

Some plugins may need to have GGC mark additional data. This can be done by registering a callback (called with a null `gcc_data`) for the `PLUGIN_GGC_MARKING` event. Such callbacks can call the `ggc_set_mark` routine, preferably through the `ggc_mark` macro (and conversely, these routines should usually not be used in plugins outside of the `PLUGIN_GGC_MARKING` event).

Some plugins may need to add extra GGC root tables, e.g. to handle their own `GTY`-ed data. This can be done with the `PLUGIN_REGISTER_GGC_ROOTS` pseudo-event with a null callback and the extra root table (of type `struct ggc_root_tab*`) as `user_data`. Plugins that want to use the `if_marked` hash table option can add the extra GGC cache tables generated by `gengtype` using the `PLUGIN_REGISTER_GGC_CACHES` pseudo-event with a null callback and the extra cache table (of type `struct ggc_cache_tab*`) as `user_data`. Running the `gengtype -p` *`source-dir file-list plugin*.c ...`* utility generates these extra root tables.

You should understand the details of memory management inside GCC before using `PLUGIN_GGC_MARKING`, `PLUGIN_REGISTER_GGC_ROOTS` or `PLUGIN_REGISTER_GGC_CACHES`.

23.5 Giving information about a plugin

A plugin should give some information to the user about itself. This uses the following structure:

```
struct plugin_info
{
  const char *version;
  const char *help;
};
```

Such a structure is passed as the `user_data` by the plugin's init routine using `register_callback` with the `PLUGIN_INFO` pseudo-event and a null callback.

23.6 Registering custom attributes or pragmas

For analysis (or other) purposes it is useful to be able to add custom attributes or pragmas.

The `PLUGIN_ATTRIBUTES` callback is called during attribute registration. Use the `register_attribute` function to register custom attributes.

```
/* Attribute handler callback */
static tree
handle_user_attribute (tree *node, tree name, tree args,
                       int flags, bool *no_add_attrs)
```

```
{
  return NULL_TREE;
}

/* Attribute definition */
static struct attribute_spec user_attr =
  { "user", 1, 1, false,  false, false, handle_user_attribute, false };

/* Plugin callback called during attribute registration.
Registered with register_callback (plugin_name, PLUGIN_ATTRIBUTES, register_attributes, NULL)
*/
static void
register_attributes (void *event_data, void *data)
{
  warning (0, G_("Callback to register attributes"));
  register_attribute (&user_attr);
}
```

The *PLUGIN_PRAGMAS* callback is called once during pragmas registration. Use the `c_register_pragma`, `c_register_pragma_with_data`, `c_register_pragma_with_expansion`, `c_register_pragma_with_expansion_and_data` functions to register custom pragmas and their handlers (which often want to call `pragma_lex`) from '`c-family/c-pragma.h`'.

```
/* Plugin callback called during pragmas registration. Registered with
     register_callback (plugin_name, PLUGIN_PRAGMAS,
                        register_my_pragma, NULL);
*/
static void
register_my_pragma (void *event_data, void *data)
{
  warning (0, G_("Callback to register pragmas"));
  c_register_pragma ("GCCPLUGIN", "sayhello", handle_pragma_sayhello);
}
```

It is suggested to pass `"GCCPLUGIN"` (or a short name identifying your plugin) as the "space" argument of your pragma.

Pragmas registered with `c_register_pragma_with_expansion` or `c_register_pragma_with_expansion_and_data` support preprocessor expansions. For example:

```
#define NUMBER 10
#pragma GCCPLUGIN foothreshold (NUMBER)
```

23.7 Recording information about pass execution

The event PLUGIN_PASS_EXECUTION passes the pointer to the executed pass (the same as current_pass) as `gcc_data` to the callback. You can also inspect cfun to find out about which function this pass is executed for. Note that this event will only be invoked if the gate check (if applicable, modified by PLUGIN_OVERRIDE_GATE) succeeds. You can use other hooks, like `PLUGIN_ALL_PASSES_START`, `PLUGIN_ALL_PASSES_END`, `PLUGIN_ALL_IPA_PASSES_START`, `PLUGIN_ALL_IPA_PASSES_END`, `PLUGIN_EARLY_GIMPLE_PASSES_START`, and/or `PLUGIN_EARLY_GIMPLE_PASSES_END` to manipulate global state in your plugin(s) in order to get context for the pass execution.

23.8 Controlling which passes are being run

After the original gate function for a pass is called, its result - the gate status - is stored as an integer. Then the event `PLUGIN_OVERRIDE_GATE` is invoked, with a pointer to the gate status in the `gcc_data` parameter to the callback function. A nonzero value of the gate status means that the pass is to be executed. You can both read and write the gate status via the passed pointer.

23.9 Keeping track of available passes

When your plugin is loaded, you can inspect the various pass lists to determine what passes are available. However, other plugins might add new passes. Also, future changes to GCC might cause generic passes to be added after plugin loading. When a pass is first added to one of the pass lists, the event `PLUGIN_NEW_PASS` is invoked, with the callback parameter `gcc_data` pointing to the new pass.

23.10 Building GCC plugins

If plugins are enabled, GCC installs the headers needed to build a plugin (somewhere in the installation tree, e.g. under '`/usr/local`'). In particular a '`plugin/include`' directory is installed, containing all the header files needed to build plugins.

On most systems, you can query this `plugin` directory by invoking `gcc -print-file-name=plugin` (replace if needed `gcc` with the appropriate program path).

Inside plugins, this `plugin` directory name can be queried by calling `default_plugin_dir_name ()`.

Plugins may know, when they are compiled, the GCC version for which '`plugin-version.h`' is provided. The constant macros `GCCPLUGIN_VERSION_MAJOR`, `GCCPLUGIN_VERSION_MINOR`, `GCCPLUGIN_VERSION_PATCHLEVEL`, `GCCPLUGIN_VERSION` are integer numbers, so a plugin could ensure it is built for GCC 4.7 with

```
#if GCCPLUGIN_VERSION != 4007
#error this GCC plugin is for GCC 4.7
#endif
```

The following GNU Makefile excerpt shows how to build a simple plugin:

```
HOST_GCC=g++
TARGET_GCC=gcc
PLUGIN_SOURCE_FILES= plugin1.c plugin2.cc
GCCPLUGINS_DIR:= $(shell $(TARGET_GCC) -print-file-name=plugin)
CXXFLAGS+= -I$(GCCPLUGINS_DIR)/include -fPIC -fno-rtti -O2

plugin.so: $(PLUGIN_SOURCE_FILES)
   $(HOST_GCC) -shared $(CXXFLAGS) $^ -o $@
```

A single source file plugin may be built with `g++ -I`gcc -print-file-name=plugin`/include -fPIC -shared -fno-rtti -O2 plugin.c -o plugin.so`, using backquote shell syntax to query the '`plugin`' directory.

When a plugin needs to use `gengtype`, be sure that both '`gengtype`' and '`gtype.state`' have the same version as the GCC for which the plugin is built.

24 Link Time Optimization

Link Time Optimization (LTO) gives GCC the capability of dumping its internal representation (GIMPLE) to disk, so that all the different compilation units that make up a single executable can be optimized as a single module. This expands the scope of inter-procedural optimizations to encompass the whole program (or, rather, everything that is visible at link time).

24.1 Design Overview

Link time optimization is implemented as a GCC front end for a bytecode representation of GIMPLE that is emitted in special sections of `.o` files. Currently, LTO support is enabled in most ELF-based systems, as well as darwin, cygwin and mingw systems.

Since GIMPLE bytecode is saved alongside final object code, object files generated with LTO support are larger than regular object files. This "fat" object format makes it easy to integrate LTO into existing build systems, as one can, for instance, produce archives of the files. Additionally, one might be able to ship one set of fat objects which could be used both for development and the production of optimized builds. A, perhaps surprising, side effect of this feature is that any mistake in the toolchain that leads to LTO information not being used (e.g. an older `libtool` calling `ld` directly). This is both an advantage, as the system is more robust, and a disadvantage, as the user is not informed that the optimization has been disabled.

The current implementation only produces "fat" objects, effectively doubling compilation time and increasing file sizes up to 5x the original size. This hides the problem that some tools, such as `ar` and `nm`, need to understand symbol tables of LTO sections. These tools were extended to use the plugin infrastructure, and with these problems solved, GCC will also support "slim" objects consisting of the intermediate code alone.

At the highest level, LTO splits the compiler in two. The first half (the "writer") produces a streaming representation of all the internal data structures needed to optimize and generate code. This includes declarations, types, the callgraph and the GIMPLE representation of function bodies.

When '`-flto`' is given during compilation of a source file, the pass manager executes all the passes in `all_lto_gen_passes`. Currently, this phase is composed of two IPA passes:

- `pass_ipa_lto_gimple_out` This pass executes the function `lto_output` in '`lto-streamer-out.c`', which traverses the call graph encoding every reachable declaration, type and function. This generates a memory representation of all the file sections described below.
- `pass_ipa_lto_finish_out` This pass executes the function `produce_asm_for_decls` in '`lto-streamer-out.c`', which takes the memory image built in the previous pass and encodes it in the corresponding ELF file sections.

The second half of LTO support is the "reader". This is implemented as the GCC front end '`lto1`' in '`lto/lto.c`'. When '`collect2`' detects a link set of `.o`/`.a` files with LTO information and the '`-flto`' is enabled, it invokes '`lto1`' which reads the set of files and aggregates them into a single translation unit for optimization. The main entry point for the reader is '`lto/lto.c`':`lto_main`.

24.1.1 LTO modes of operation

One of the main goals of the GCC link-time infrastructure was to allow effective compilation of large programs. For this reason GCC implements two link-time compilation modes.

1. *LTO mode*, in which the whole program is read into the compiler at link-time and optimized in a similar way as if it were a single source-level compilation unit.
2. *WHOPR or partitioned mode*, designed to utilize multiple CPUs and/or a distributed compilation environment to quickly link large applications. WHOPR stands for WHOle Program optimizeR (not to be confused with the semantics of '`-fwhole-program`'). It partitions the aggregated callgraph from many different `.o` files and distributes the compilation of the sub-graphs to different CPUs.

   Note that distributed compilation is not implemented yet, but since the parallelism is facilitated via generating a `Makefile`, it would be easy to implement.

WHOPR splits LTO into three main stages:

1. Local generation (LGEN) This stage executes in parallel. Every file in the program is compiled into the intermediate language and packaged together with the local call-graph and summary information. This stage is the same for both the LTO and WHOPR compilation mode.
2. Whole Program Analysis (WPA) WPA is performed sequentially. The global call-graph is generated, and a global analysis procedure makes transformation decisions. The global call-graph is partitioned to facilitate parallel optimization during phase 3. The results of the WPA stage are stored into new object files which contain the partitions of program expressed in the intermediate language and the optimization decisions.
3. Local transformations (LTRANS) This stage executes in parallel. All the decisions made during phase 2 are implemented locally in each partitioned object file, and the final object code is generated. Optimizations which cannot be decided efficiently during the phase 2 may be performed on the local call-graph partitions.

WHOPR can be seen as an extension of the usual LTO mode of compilation. In LTO, WPA and LTRANS are executed within a single execution of the compiler, after the whole program has been read into memory.

When compiling in WHOPR mode, the callgraph is partitioned during the WPA stage. The whole program is split into a given number of partitions of roughly the same size. The compiler tries to minimize the number of references which cross partition boundaries. The main advantage of WHOPR is to allow the parallel execution of LTRANS stages, which are the most time-consuming part of the compilation process. Additionally, it avoids the need to load the whole program into memory.

24.2 LTO file sections

LTO information is stored in several ELF sections inside object files. Data structures and enum codes for sections are defined in '`lto-streamer.h`'.

These sections are emitted from '`lto-streamer-out.c`' and mapped in all at once from '`lto/lto.c`':`lto_file_read`. The individual functions dealing with the reading/writing of each section are described below.

- Command line options (`.gnu.lto_.opts`)

  This section contains the command line options used to generate the object files. This is used at link time to determine the optimization level and other settings when they are not explicitly specified at the linker command line.

  Currently, GCC does not support combining LTO object files compiled with different set of the command line options into a single binary. At link time, the options given on the command line and the options saved on all the files in a link-time set are applied globally. No attempt is made at validating the combination of flags (other than the usual validation done by option processing). This is implemented in '`lto/lto.c`':`lto_read_all_file_options`.

- Symbol table (`.gnu.lto_.symtab`)

  This table replaces the ELF symbol table for functions and variables represented in the LTO IL. Symbols used and exported by the optimized assembly code of "fat" objects might not match the ones used and exported by the intermediate code. This table is necessary because the intermediate code is less optimized and thus requires a separate symbol table.

  Additionally, the binary code in the "fat" object will lack a call to a function, since the call was optimized out at compilation time after the intermediate language was streamed out. In some special cases, the same optimization may not happen during link-time optimization. This would lead to an undefined symbol if only one symbol table was used.

  The symbol table is emitted in '`lto-streamer-out.c`':`produce_symtab`.

- Global declarations and types (`.gnu.lto_.decls`)

  This section contains an intermediate language dump of all declarations and types required to represent the callgraph, static variables and top-level debug info.

  The contents of this section are emitted in '`lto-streamer-out.c`':`produce_asm_for_decls`. Types and symbols are emitted in a topological order that preserves the sharing of pointers when the file is read back in ('`lto.c`':`read_cgraph_and_symbols`).

- The callgraph (`.gnu.lto_.cgraph`)

  This section contains the basic data structure used by the GCC inter-procedural optimization infrastructure. This section stores an annotated multi-graph which represents the functions and call sites as well as the variables, aliases and top-level `asm` statements.

  This section is emitted in '`lto-streamer-out.c`':`output_cgraph` and read in '`lto-cgraph.c`':`input_cgraph`.

- IPA references (`.gnu.lto_.refs`)

  This section contains references between function and static variables. It is emitted by '`lto-cgraph.c`':`output_refs` and read by '`lto-cgraph.c`':`input_refs`.

- Function bodies (`.gnu.lto_.function_body.<name>`)

  This section contains function bodies in the intermediate language representation. Every function body is in a separate section to allow copying of the section independently to different object files or reading the function on demand.

  Functions are emitted in '`lto-streamer-out.c`':`output_function` and read in '`lto-streamer-in.c`':`input_function`.

- Static variable initializers (`.gnu.lto_.vars`)

  This section contains all the symbols in the global variable pool. It is emitted by '`lto-cgraph.c`':`output_varpool` and read in '`lto-cgraph.c`':`input_cgraph`.
- Summaries and optimization summaries used by IPA passes (`.gnu.lto_.<xxx>`, where `<xxx>` is one of `jmpfuncs`, `pureconst` or `reference`)

  These sections are used by IPA passes that need to emit summary information during LTO generation to be read and aggregated at link time. Each pass is responsible for implementing two pass manager hooks: one for writing the summary and another for reading it in. The format of these sections is entirely up to each individual pass. The only requirement is that the writer and reader hooks agree on the format.

24.3 Using summary information in IPA passes

Programs are represented internally as a *callgraph* (a multi-graph where nodes are functions and edges are call sites) and a *varpool* (a list of static and external variables in the program).

The inter-procedural optimization is organized as a sequence of individual passes, which operate on the callgraph and the varpool. To make the implementation of WHOPR possible, every inter-procedural optimization pass is split into several stages that are executed at different times during WHOPR compilation:

- LGEN time
  1. *Generate summary* (`generate_summary` in `struct ipa_opt_pass_d`). This stage analyzes every function body and variable initializer is examined and stores relevant information into a pass-specific data structure.
  2. *Write summary* (`write_summary` in `struct ipa_opt_pass_d`). This stage writes all the pass-specific information generated by `generate_summary`. Summaries go into their own `LTO_section_*` sections that have to be declared in '`lto-streamer.h`':`enum lto_section_type`. A new section is created by calling `create_output_block` and data can be written using the `lto_output_*` routines.
- WPA time
  1. *Read summary* (`read_summary` in `struct ipa_opt_pass_d`). This stage reads all the pass-specific information in exactly the same order that it was written by `write_summary`.
  2. *Execute* (`execute` in `struct opt_pass`). This performs inter-procedural propagation. This must be done without actual access to the individual function bodies or variable initializers. Typically, this results in a transitive closure operation over the summary information of all the nodes in the callgraph.
  3. *Write optimization summary* (`write_optimization_summary` in `struct ipa_opt_pass_d`). This writes the result of the inter-procedural propagation into the object file. This can use the same data structures and helper routines used in `write_summary`.
- LTRANS time
  1. *Read optimization summary* (`read_optimization_summary` in `struct ipa_opt_pass_d`). The counterpart to `write_optimization_summary`. This reads the interprocedural optimization decisions in exactly the same format emitted by `write_optimization_summary`.

2. *Transform* (`function_transform` and `variable_transform` in `struct ipa_opt_pass_d`). The actual function bodies and variable initializers are updated based on the information passed down from the *Execute* stage.

The implementation of the inter-procedural passes are shared between LTO, WHOPR and classic non-LTO compilation.

- During the traditional file-by-file mode every pass executes its own *Generate summary*, *Execute*, and *Transform* stages within the single execution context of the compiler.
- In LTO compilation mode, every pass uses *Generate summary* and *Write summary* stages at compilation time, while the *Read summary*, *Execute*, and *Transform* stages are executed at link time.
- In WHOPR mode all stages are used.

To simplify development, the GCC pass manager differentiates between normal inter-procedural passes and small inter-procedural passes. A *small inter-procedural pass* (`SIMPLE_IPA_PASS`) is a pass that does everything at once and thus it can not be executed during WPA in WHOPR mode. It defines only the *Execute* stage and during this stage it accesses and modifies the function bodies. Such passes are useful for optimization at LGEN or LTRANS time and are used, for example, to implement early optimization before writing object files. The simple inter-procedural passes can also be used for easier prototyping and development of a new inter-procedural pass.

24.3.1 Virtual clones

One of the main challenges of introducing the WHOPR compilation mode was addressing the interactions between optimization passes. In LTO compilation mode, the passes are executed in a sequence, each of which consists of analysis (or *Generate summary*), propagation (or *Execute*) and *Transform* stages. Once the work of one pass is finished, the next pass sees the updated program representation and can execute. This makes the individual passes dependent on each other.

In WHOPR mode all passes first execute their *Generate summary* stage. Then summary writing marks the end of the LGEN stage. At WPA time, the summaries are read back into memory and all passes run the *Execute* stage. Optimization summaries are streamed and sent to LTRANS, where all the passes execute the *Transform* stage.

Most optimization passes split naturally into analysis, propagation and transformation stages. But some do not. The main problem arises when one pass performs changes and the following pass gets confused by seeing different callgraphs between the *Transform* stage and the *Generate summary* or *Execute* stage. This means that the passes are required to communicate their decisions with each other.

To facilitate this communication, the GCC callgraph infrastructure implements *virtual clones*, a method of representing the changes performed by the optimization passes in the callgraph without needing to update function bodies.

A *virtual clone* in the callgraph is a function that has no associated body, just a description of how to create its body based on a different function (which itself may be a virtual clone).

The description of function modifications includes adjustments to the function's signature (which allows, for example, removing or adding function arguments), substitutions to

perform on the function body, and, for inlined functions, a pointer to the function that it will be inlined into.

It is also possible to redirect any edge of the callgraph from a function to its virtual clone. This implies updating of the call site to adjust for the new function signature.

Most of the transformations performed by inter-procedural optimizations can be represented via virtual clones. For instance, a constant propagation pass can produce a virtual clone of the function which replaces one of its arguments by a constant. The inliner can represent its decisions by producing a clone of a function whose body will be later integrated into a given function.

Using *virtual clones*, the program can be easily updated during the *Execute* stage, solving most of pass interactions problems that would otherwise occur during *Transform*.

Virtual clones are later materialized in the LTRANS stage and turned into real functions. Passes executed after the virtual clone were introduced also perform their *Transform* stage on new functions, so for a pass there is no significant difference between operating on a real function or a virtual clone introduced before its *Execute* stage.

Optimization passes then work on virtual clones introduced before their *Execute* stage as if they were real functions. The only difference is that clones are not visible during the *Generate Summary* stage.

To keep function summaries updated, the callgraph interface allows an optimizer to register a callback that is called every time a new clone is introduced as well as when the actual function or variable is generated or when a function or variable is removed. These hooks are registered in the *Generate summary* stage and allow the pass to keep its information intact until the *Execute* stage. The same hooks can also be registered during the *Execute* stage to keep the optimization summaries updated for the *Transform* stage.

24.3.2 IPA references

GCC represents IPA references in the callgraph. For a function or variable `A`, the *IPA reference* is a list of all locations where the address of `A` is taken and, when `A` is a variable, a list of all direct stores and reads to/from `A`. References represent an oriented multi-graph on the union of nodes of the callgraph and the varpool. See '`ipa-reference.c`':`ipa_reference_write_optimization_summary` and '`ipa-reference.c`':`ipa_reference_read_optimization_summary` for details.

24.3.3 Jump functions

Suppose that an optimization pass sees a function `A` and it knows the values of (some of) its arguments. The *jump function* describes the value of a parameter of a given function call in function `A` based on this knowledge.

Jump functions are used by several optimizations, such as the inter-procedural constant propagation pass and the devirtualization pass. The inliner also uses jump functions to perform inlining of callbacks.

24.4 Whole program assumptions, linker plugin and symbol visibilities

Link-time optimization gives relatively minor benefits when used alone. The problem is that propagation of inter-procedural information does not work well across functions and

variables that are called or referenced by other compilation units (such as from a dynamically linked library). We say that such functions and variables are *externally visible*.

To make the situation even more difficult, many applications organize themselves as a set of shared libraries, and the default ELF visibility rules allow one to overwrite any externally visible symbol with a different symbol at runtime. This basically disables any optimizations across such functions and variables, because the compiler cannot be sure that the function body it is seeing is the same function body that will be used at runtime. Any function or variable not declared `static` in the sources degrades the quality of inter-procedural optimization.

To avoid this problem the compiler must assume that it sees the whole program when doing link-time optimization. Strictly speaking, the whole program is rarely visible even at link-time. Standard system libraries are usually linked dynamically or not provided with the link-time information. In GCC, the whole program option ('`-fwhole-program`') asserts that every function and variable defined in the current compilation unit is static, except for function `main` (note: at link time, the current unit is the union of all objects compiled with LTO). Since some functions and variables need to be referenced externally, for example by another DSO or from an assembler file, GCC also provides the function and variable attribute `externally_visible` which can be used to disable the effect of '`-fwhole-program`' on a specific symbol.

The whole program mode assumptions are slightly more complex in C++, where inline functions in headers are put into *COMDAT* sections. COMDAT function and variables can be defined by multiple object files and their bodies are unified at link-time and dynamic link-time. COMDAT functions are changed to local only when their address is not taken and thus un-sharing them with a library is not harmful. COMDAT variables always remain externally visible, however for readonly variables it is assumed that their initializers cannot be overwritten by a different value.

GCC provides the function and variable attribute `visibility` that can be used to specify the visibility of externally visible symbols (or alternatively an '`-fdefault-visibility`' command line option). ELF defines the `default`, `protected`, `hidden` and `internal` visibilities.

The most commonly used is visibility is `hidden`. It specifies that the symbol cannot be referenced from outside of the current shared library. Unfortunately, this information cannot be used directly by the link-time optimization in the compiler since the whole shared library also might contain non-LTO objects and those are not visible to the compiler.

GCC solves this problem using linker plugins. A *linker plugin* is an interface to the linker that allows an external program to claim the ownership of a given object file. The linker then performs the linking procedure by querying the plugin about the symbol table of the claimed objects and once the linking decisions are complete, the plugin is allowed to provide the final object file before the actual linking is made. The linker plugin obtains the symbol resolution information which specifies which symbols provided by the claimed objects are bound from the rest of a binary being linked.

Currently, the linker plugin works only in combination with the Gold linker, but a GNU ld implementation is under development.

GCC is designed to be independent of the rest of the toolchain and aims to support linkers without plugin support. For this reason it does not use the linker plugin by default. Instead,

the object files are examined by `collect2` before being passed to the linker and objects found to have LTO sections are passed to `lto1` first. This mode does not work for library archives. The decision on what object files from the archive are needed depends on the actual linking and thus GCC would have to implement the linker itself. The resolution information is missing too and thus GCC needs to make an educated guess based on '`-fwhole-program`'. Without the linker plugin GCC also assumes that symbols are declared `hidden` and not referred by non-LTO code by default.

24.5 Internal flags controlling `lto1`

The following flags are passed into `lto1` and are not meant to be used directly from the command line.

- -fwpa This option runs the serial part of the link-time optimizer performing the inter-procedural propagation (WPA mode). The compiler reads in summary information from all inputs and performs an analysis based on summary information only. It generates object files for subsequent runs of the link-time optimizer where individual object files are optimized using both summary information from the WPA mode and the actual function bodies. It then drives the LTRANS phase.
- -fltrans This option runs the link-time optimizer in the local-transformation (LTRANS) mode, which reads in output from a previous run of the LTO in WPA mode. In the LTRANS mode, LTO optimizes an object and produces the final assembly.
- -fltrans-output-list=*file* This option specifies a file to which the names of LTRANS output files are written. This option is only meaningful in conjunction with '`-fwpa`'.
- -fresolution=*file* This option specifies the linker resolution file. This option is only meaningful in conjunction with '`-fwpa`' and as option to pass through to the LTO linker plugin.

Funding Free Software

If you want to have more free software a few years from now, it makes sense for you to help encourage people to contribute funds for its development. The most effective approach known is to encourage commercial redistributors to donate.

Users of free software systems can boost the pace of development by encouraging for-a-fee distributors to donate part of their selling price to free software developers—the Free Software Foundation, and others.

The way to convince distributors to do this is to demand it and expect it from them. So when you compare distributors, judge them partly by how much they give to free software development. Show distributors they must compete to be the one who gives the most.

To make this approach work, you must insist on numbers that you can compare, such as, "We will donate ten dollars to the Frobnitz project for each disk sold." Don't be satisfied with a vague promise, such as "A portion of the profits are donated," since it doesn't give a basis for comparison.

Even a precise fraction "of the profits from this disk" is not very meaningful, since creative accounting and unrelated business decisions can greatly alter what fraction of the sales price counts as profit. If the price you pay is $50, ten percent of the profit is probably less than a dollar; it might be a few cents, or nothing at all.

Some redistributors do development work themselves. This is useful too; but to keep everyone honest, you need to inquire how much they do, and what kind. Some kinds of development make much more long-term difference than others. For example, maintaining a separate version of a program contributes very little; maintaining the standard version of a program for the whole community contributes much. Easy new ports contribute little, since someone else would surely do them; difficult ports such as adding a new CPU to the GNU Compiler Collection contribute more; major new features or packages contribute the most.

By establishing the idea that supporting further development is "the proper thing to do" when distributing free software for a fee, we can assure a steady flow of resources into making more free software.

Copyright © 1994 Free Software Foundation, Inc.
Verbatim copying and redistribution of this section is permitted
without royalty; alteration is not permitted.

The GNU Project and GNU/Linux

The GNU Project was launched in 1984 to develop a complete Unix-like operating system which is free software: the GNU system. (GNU is a recursive acronym for "GNU's Not Unix"; it is pronounced "guh-NEW".) Variants of the GNU operating system, which use the kernel Linux, are now widely used; though these systems are often referred to as "Linux", they are more accurately called GNU/Linux systems.

For more information, see:

http://www.gnu.org/
http://www.gnu.org/gnu/linux-and-gnu.html

GNU General Public License

Version 3, 29 June 2007

Copyright © 2007 Free Software Foundation, Inc. http://fsf.org/

Everyone is permitted to copy and distribute verbatim copies of this license document, but changing it is not allowed.

Preamble

The GNU General Public License is a free, copyleft license for software and other kinds of works.

The licenses for most software and other practical works are designed to take away your freedom to share and change the works. By contrast, the GNU General Public License is intended to guarantee your freedom to share and change all versions of a program–to make sure it remains free software for all its users. We, the Free Software Foundation, use the GNU General Public License for most of our software; it applies also to any other work released this way by its authors. You can apply it to your programs, too.

When we speak of free software, we are referring to freedom, not price. Our General Public Licenses are designed to make sure that you have the freedom to distribute copies of free software (and charge for them if you wish), that you receive source code or can get it if you want it, that you can change the software or use pieces of it in new free programs, and that you know you can do these things.

To protect your rights, we need to prevent others from denying you these rights or asking you to surrender the rights. Therefore, you have certain responsibilities if you distribute copies of the software, or if you modify it: responsibilities to respect the freedom of others.

For example, if you distribute copies of such a program, whether gratis or for a fee, you must pass on to the recipients the same freedoms that you received. You must make sure that they, too, receive or can get the source code. And you must show them these terms so they know their rights.

Developers that use the GNU GPL protect your rights with two steps: (1) assert copyright on the software, and (2) offer you this License giving you legal permission to copy, distribute and/or modify it.

For the developers' and authors' protection, the GPL clearly explains that there is no warranty for this free software. For both users' and authors' sake, the GPL requires that modified versions be marked as changed, so that their problems will not be attributed erroneously to authors of previous versions.

Some devices are designed to deny users access to install or run modified versions of the software inside them, although the manufacturer can do so. This is fundamentally incompatible with the aim of protecting users' freedom to change the software. The systematic pattern of such abuse occurs in the area of products for individuals to use, which is precisely where it is most unacceptable. Therefore, we have designed this version of the GPL to prohibit the practice for those products. If such problems arise substantially in other domains, we stand ready to extend this provision to those domains in future versions of the GPL, as needed to protect the freedom of users.

Finally, every program is threatened constantly by software patents. States should not allow patents to restrict development and use of software on general-purpose computers, but in those that do, we wish to avoid the special danger that patents applied to a free program could make it effectively proprietary. To prevent this, the GPL assures that patents cannot be used to render the program non-free.

The precise terms and conditions for copying, distribution and modification follow.

TERMS AND CONDITIONS

0. Definitions.

   "This License" refers to version 3 of the GNU General Public License.

   "Copyright" also means copyright-like laws that apply to other kinds of works, such as semiconductor masks.

   "The Program" refers to any copyrightable work licensed under this License. Each licensee is addressed as "you". "Licensees" and "recipients" may be individuals or organizations.

   To "modify" a work means to copy from or adapt all or part of the work in a fashion requiring copyright permission, other than the making of an exact copy. The resulting work is called a "modified version" of the earlier work or a work "based on" the earlier work.

   A "covered work" means either the unmodified Program or a work based on the Program.

   To "propagate" a work means to do anything with it that, without permission, would make you directly or secondarily liable for infringement under applicable copyright law, except executing it on a computer or modifying a private copy. Propagation includes copying, distribution (with or without modification), making available to the public, and in some countries other activities as well.

   To "convey" a work means any kind of propagation that enables other parties to make or receive copies. Mere interaction with a user through a computer network, with no transfer of a copy, is not conveying.

   An interactive user interface displays "Appropriate Legal Notices" to the extent that it includes a convenient and prominently visible feature that (1) displays an appropriate copyright notice, and (2) tells the user that there is no warranty for the work (except to the extent that warranties are provided), that licensees may convey the work under this License, and how to view a copy of this License. If the interface presents a list of user commands or options, such as a menu, a prominent item in the list meets this criterion.

1. Source Code.

   The "source code" for a work means the preferred form of the work for making modifications to it. "Object code" means any non-source form of a work.

   A "Standard Interface" means an interface that either is an official standard defined by a recognized standards body, or, in the case of interfaces specified for a particular programming language, one that is widely used among developers working in that language.

The "System Libraries" of an executable work include anything, other than the work as a whole, that (a) is included in the normal form of packaging a Major Component, but which is not part of that Major Component, and (b) serves only to enable use of the work with that Major Component, or to implement a Standard Interface for which an implementation is available to the public in source code form. A "Major Component", in this context, means a major essential component (kernel, window system, and so on) of the specific operating system (if any) on which the executable work runs, or a compiler used to produce the work, or an object code interpreter used to run it.

The "Corresponding Source" for a work in object code form means all the source code needed to generate, install, and (for an executable work) run the object code and to modify the work, including scripts to control those activities. However, it does not include the work's System Libraries, or general-purpose tools or generally available free programs which are used unmodified in performing those activities but which are not part of the work. For example, Corresponding Source includes interface definition files associated with source files for the work, and the source code for shared libraries and dynamically linked subprograms that the work is specifically designed to require, such as by intimate data communication or control flow between those subprograms and other parts of the work.

The Corresponding Source need not include anything that users can regenerate automatically from other parts of the Corresponding Source.

The Corresponding Source for a work in source code form is that same work.

2. Basic Permissions.

   All rights granted under this License are granted for the term of copyright on the Program, and are irrevocable provided the stated conditions are met. This License explicitly affirms your unlimited permission to run the unmodified Program. The output from running a covered work is covered by this License only if the output, given its content, constitutes a covered work. This License acknowledges your rights of fair use or other equivalent, as provided by copyright law.

   You may make, run and propagate covered works that you do not convey, without conditions so long as your license otherwise remains in force. You may convey covered works to others for the sole purpose of having them make modifications exclusively for you, or provide you with facilities for running those works, provided that you comply with the terms of this License in conveying all material for which you do not control copyright. Those thus making or running the covered works for you must do so exclusively on your behalf, under your direction and control, on terms that prohibit them from making any copies of your copyrighted material outside their relationship with you.

   Conveying under any other circumstances is permitted solely under the conditions stated below. Sublicensing is not allowed; section 10 makes it unnecessary.

3. Protecting Users' Legal Rights From Anti-Circumvention Law.

   No covered work shall be deemed part of an effective technological measure under any applicable law fulfilling obligations under article 11 of the WIPO copyright treaty adopted on 20 December 1996, or similar laws prohibiting or restricting circumvention of such measures.

When you convey a covered work, you waive any legal power to forbid circumvention of technological measures to the extent such circumvention is effected by exercising rights under this License with respect to the covered work, and you disclaim any intention to limit operation or modification of the work as a means of enforcing, against the work's users, your or third parties' legal rights to forbid circumvention of technological measures.

4. Conveying Verbatim Copies.

   You may convey verbatim copies of the Program's source code as you receive it, in any medium, provided that you conspicuously and appropriately publish on each copy an appropriate copyright notice; keep intact all notices stating that this License and any non-permissive terms added in accord with section 7 apply to the code; keep intact all notices of the absence of any warranty; and give all recipients a copy of this License along with the Program.

   You may charge any price or no price for each copy that you convey, and you may offer support or warranty protection for a fee.

5. Conveying Modified Source Versions.

   You may convey a work based on the Program, or the modifications to produce it from the Program, in the form of source code under the terms of section 4, provided that you also meet all of these conditions:

   a. The work must carry prominent notices stating that you modified it, and giving a relevant date.
   b. The work must carry prominent notices stating that it is released under this License and any conditions added under section 7. This requirement modifies the requirement in section 4 to "keep intact all notices".
   c. You must license the entire work, as a whole, under this License to anyone who comes into possession of a copy. This License will therefore apply, along with any applicable section 7 additional terms, to the whole of the work, and all its parts, regardless of how they are packaged. This License gives no permission to license the work in any other way, but it does not invalidate such permission if you have separately received it.
   d. If the work has interactive user interfaces, each must display Appropriate Legal Notices; however, if the Program has interactive interfaces that do not display Appropriate Legal Notices, your work need not make them do so.

   A compilation of a covered work with other separate and independent works, which are not by their nature extensions of the covered work, and which are not combined with it such as to form a larger program, in or on a volume of a storage or distribution medium, is called an "aggregate" if the compilation and its resulting copyright are not used to limit the access or legal rights of the compilation's users beyond what the individual works permit. Inclusion of a covered work in an aggregate does not cause this License to apply to the other parts of the aggregate.

6. Conveying Non-Source Forms.

   You may convey a covered work in object code form under the terms of sections 4 and 5, provided that you also convey the machine-readable Corresponding Source under the terms of this License, in one of these ways:

a. Convey the object code in, or embodied in, a physical product (including a physical distribution medium), accompanied by the Corresponding Source fixed on a durable physical medium customarily used for software interchange.
b. Convey the object code in, or embodied in, a physical product (including a physical distribution medium), accompanied by a written offer, valid for at least three years and valid for as long as you offer spare parts or customer support for that product model, to give anyone who possesses the object code either (1) a copy of the Corresponding Source for all the software in the product that is covered by this License, on a durable physical medium customarily used for software interchange, for a price no more than your reasonable cost of physically performing this conveying of source, or (2) access to copy the Corresponding Source from a network server at no charge.
c. Convey individual copies of the object code with a copy of the written offer to provide the Corresponding Source. This alternative is allowed only occasionally and noncommercially, and only if you received the object code with such an offer, in accord with subsection 6b.
d. Convey the object code by offering access from a designated place (gratis or for a charge), and offer equivalent access to the Corresponding Source in the same way through the same place at no further charge. You need not require recipients to copy the Corresponding Source along with the object code. If the place to copy the object code is a network server, the Corresponding Source may be on a different server (operated by you or a third party) that supports equivalent copying facilities, provided you maintain clear directions next to the object code saying where to find the Corresponding Source. Regardless of what server hosts the Corresponding Source, you remain obligated to ensure that it is available for as long as needed to satisfy these requirements.
e. Convey the object code using peer-to-peer transmission, provided you inform other peers where the object code and Corresponding Source of the work are being offered to the general public at no charge under subsection 6d.

A separable portion of the object code, whose source code is excluded from the Corresponding Source as a System Library, need not be included in conveying the object code work.

A "User Product" is either (1) a "consumer product", which means any tangible personal property which is normally used for personal, family, or household purposes, or (2) anything designed or sold for incorporation into a dwelling. In determining whether a product is a consumer product, doubtful cases shall be resolved in favor of coverage. For a particular product received by a particular user, "normally used" refers to a typical or common use of that class of product, regardless of the status of the particular user or of the way in which the particular user actually uses, or expects or is expected to use, the product. A product is a consumer product regardless of whether the product has substantial commercial, industrial or non-consumer uses, unless such uses represent the only significant mode of use of the product.

"Installation Information" for a User Product means any methods, procedures, authorization keys, or other information required to install and execute modified versions of a covered work in that User Product from a modified version of its Corresponding Source.

The information must suffice to ensure that the continued functioning of the modified object code is in no case prevented or interfered with solely because modification has been made.

If you convey an object code work under this section in, or with, or specifically for use in, a User Product, and the conveying occurs as part of a transaction in which the right of possession and use of the User Product is transferred to the recipient in perpetuity or for a fixed term (regardless of how the transaction is characterized), the Corresponding Source conveyed under this section must be accompanied by the Installation Information. But this requirement does not apply if neither you nor any third party retains the ability to install modified object code on the User Product (for example, the work has been installed in ROM).

The requirement to provide Installation Information does not include a requirement to continue to provide support service, warranty, or updates for a work that has been modified or installed by the recipient, or for the User Product in which it has been modified or installed. Access to a network may be denied when the modification itself materially and adversely affects the operation of the network or violates the rules and protocols for communication across the network.

Corresponding Source conveyed, and Installation Information provided, in accord with this section must be in a format that is publicly documented (and with an implementation available to the public in source code form), and must require no special password or key for unpacking, reading or copying.

7. Additional Terms.

   "Additional permissions" are terms that supplement the terms of this License by making exceptions from one or more of its conditions. Additional permissions that are applicable to the entire Program shall be treated as though they were included in this License, to the extent that they are valid under applicable law. If additional permissions apply only to part of the Program, that part may be used separately under those permissions, but the entire Program remains governed by this License without regard to the additional permissions.

   When you convey a copy of a covered work, you may at your option remove any additional permissions from that copy, or from any part of it. (Additional permissions may be written to require their own removal in certain cases when you modify the work.) You may place additional permissions on material, added by you to a covered work, for which you have or can give appropriate copyright permission.

   Notwithstanding any other provision of this License, for material you add to a covered work, you may (if authorized by the copyright holders of that material) supplement the terms of this License with terms:

   a. Disclaiming warranty or limiting liability differently from the terms of sections 15 and 16 of this License; or
   b. Requiring preservation of specified reasonable legal notices or author attributions in that material or in the Appropriate Legal Notices displayed by works containing it; or
   c. Prohibiting misrepresentation of the origin of that material, or requiring that modified versions of such material be marked in reasonable ways as different from the original version; or

d. Limiting the use for publicity purposes of names of licensors or authors of the material; or

e. Declining to grant rights under trademark law for use of some trade names, trademarks, or service marks; or

f. Requiring indemnification of licensors and authors of that material by anyone who conveys the material (or modified versions of it) with contractual assumptions of liability to the recipient, for any liability that these contractual assumptions directly impose on those licensors and authors.

All other non-permissive additional terms are considered "further restrictions" within the meaning of section 10. If the Program as you received it, or any part of it, contains a notice stating that it is governed by this License along with a term that is a further restriction, you may remove that term. If a license document contains a further restriction but permits relicensing or conveying under this License, you may add to a covered work material governed by the terms of that license document, provided that the further restriction does not survive such relicensing or conveying.

If you add terms to a covered work in accord with this section, you must place, in the relevant source files, a statement of the additional terms that apply to those files, or a notice indicating where to find the applicable terms.

Additional terms, permissive or non-permissive, may be stated in the form of a separately written license, or stated as exceptions; the above requirements apply either way.

8. Termination.

You may not propagate or modify a covered work except as expressly provided under this License. Any attempt otherwise to propagate or modify it is void, and will automatically terminate your rights under this License (including any patent licenses granted under the third paragraph of section 11).

However, if you cease all violation of this License, then your license from a particular copyright holder is reinstated (a) provisionally, unless and until the copyright holder explicitly and finally terminates your license, and (b) permanently, if the copyright holder fails to notify you of the violation by some reasonable means prior to 60 days after the cessation.

Moreover, your license from a particular copyright holder is reinstated permanently if the copyright holder notifies you of the violation by some reasonable means, this is the first time you have received notice of violation of this License (for any work) from that copyright holder, and you cure the violation prior to 30 days after your receipt of the notice.

Termination of your rights under this section does not terminate the licenses of parties who have received copies or rights from you under this License. If your rights have been terminated and not permanently reinstated, you do not qualify to receive new licenses for the same material under section 10.

9. Acceptance Not Required for Having Copies.

You are not required to accept this License in order to receive or run a copy of the Program. Ancillary propagation of a covered work occurring solely as a consequence of using peer-to-peer transmission to receive a copy likewise does not require acceptance.

However, nothing other than this License grants you permission to propagate or modify any covered work. These actions infringe copyright if you do not accept this License. Therefore, by modifying or propagating a covered work, you indicate your acceptance of this License to do so.

10. Automatic Licensing of Downstream Recipients.

    Each time you convey a covered work, the recipient automatically receives a license from the original licensors, to run, modify and propagate that work, subject to this License. You are not responsible for enforcing compliance by third parties with this License.

    An "entity transaction" is a transaction transferring control of an organization, or substantially all assets of one, or subdividing an organization, or merging organizations. If propagation of a covered work results from an entity transaction, each party to that transaction who receives a copy of the work also receives whatever licenses to the work the party's predecessor in interest had or could give under the previous paragraph, plus a right to possession of the Corresponding Source of the work from the predecessor in interest, if the predecessor has it or can get it with reasonable efforts.

    You may not impose any further restrictions on the exercise of the rights granted or affirmed under this License. For example, you may not impose a license fee, royalty, or other charge for exercise of rights granted under this License, and you may not initiate litigation (including a cross-claim or counterclaim in a lawsuit) alleging that any patent claim is infringed by making, using, selling, offering for sale, or importing the Program or any portion of it.

11. Patents.

    A "contributor" is a copyright holder who authorizes use under this License of the Program or a work on which the Program is based. The work thus licensed is called the contributor's "contributor version".

    A contributor's "essential patent claims" are all patent claims owned or controlled by the contributor, whether already acquired or hereafter acquired, that would be infringed by some manner, permitted by this License, of making, using, or selling its contributor version, but do not include claims that would be infringed only as a consequence of further modification of the contributor version. For purposes of this definition, "control" includes the right to grant patent sublicenses in a manner consistent with the requirements of this License.

    Each contributor grants you a non-exclusive, worldwide, royalty-free patent license under the contributor's essential patent claims, to make, use, sell, offer for sale, import and otherwise run, modify and propagate the contents of its contributor version.

    In the following three paragraphs, a "patent license" is any express agreement or commitment, however denominated, not to enforce a patent (such as an express permission to practice a patent or covenant not to sue for patent infringement). To "grant" such a patent license to a party means to make such an agreement or commitment not to enforce a patent against the party.

    If you convey a covered work, knowingly relying on a patent license, and the Corresponding Source of the work is not available for anyone to copy, free of charge and under the terms of this License, through a publicly available network server or other readily accessible means, then you must either (1) cause the Corresponding Source to be so

available, or (2) arrange to deprive yourself of the benefit of the patent license for this particular work, or (3) arrange, in a manner consistent with the requirements of this License, to extend the patent license to downstream recipients. "Knowingly relying" means you have actual knowledge that, but for the patent license, your conveying the covered work in a country, or your recipient's use of the covered work in a country, would infringe one or more identifiable patents in that country that you have reason to believe are valid.

If, pursuant to or in connection with a single transaction or arrangement, you convey, or propagate by procuring conveyance of, a covered work, and grant a patent license to some of the parties receiving the covered work authorizing them to use, propagate, modify or convey a specific copy of the covered work, then the patent license you grant is automatically extended to all recipients of the covered work and works based on it.

A patent license is "discriminatory" if it does not include within the scope of its coverage, prohibits the exercise of, or is conditioned on the non-exercise of one or more of the rights that are specifically granted under this License. You may not convey a covered work if you are a party to an arrangement with a third party that is in the business of distributing software, under which you make payment to the third party based on the extent of your activity of conveying the work, and under which the third party grants, to any of the parties who would receive the covered work from you, a discriminatory patent license (a) in connection with copies of the covered work conveyed by you (or copies made from those copies), or (b) primarily for and in connection with specific products or compilations that contain the covered work, unless you entered into that arrangement, or that patent license was granted, prior to 28 March 2007.

Nothing in this License shall be construed as excluding or limiting any implied license or other defenses to infringement that may otherwise be available to you under applicable patent law.

12. No Surrender of Others' Freedom.

    If conditions are imposed on you (whether by court order, agreement or otherwise) that contradict the conditions of this License, they do not excuse you from the conditions of this License. If you cannot convey a covered work so as to satisfy simultaneously your obligations under this License and any other pertinent obligations, then as a consequence you may not convey it at all. For example, if you agree to terms that obligate you to collect a royalty for further conveying from those to whom you convey the Program, the only way you could satisfy both those terms and this License would be to refrain entirely from conveying the Program.

13. Use with the GNU Affero General Public License.

    Notwithstanding any other provision of this License, you have permission to link or combine any covered work with a work licensed under version 3 of the GNU Affero General Public License into a single combined work, and to convey the resulting work. The terms of this License will continue to apply to the part which is the covered work, but the special requirements of the GNU Affero General Public License, section 13, concerning interaction through a network will apply to the combination as such.

14. Revised Versions of this License.

The Free Software Foundation may publish revised and/or new versions of the GNU General Public License from time to time. Such new versions will be similar in spirit to the present version, but may differ in detail to address new problems or concerns.

Each version is given a distinguishing version number. If the Program specifies that a certain numbered version of the GNU General Public License "or any later version" applies to it, you have the option of following the terms and conditions either of that numbered version or of any later version published by the Free Software Foundation. If the Program does not specify a version number of the GNU General Public License, you may choose any version ever published by the Free Software Foundation.

If the Program specifies that a proxy can decide which future versions of the GNU General Public License can be used, that proxy's public statement of acceptance of a version permanently authorizes you to choose that version for the Program.

Later license versions may give you additional or different permissions. However, no additional obligations are imposed on any author or copyright holder as a result of your choosing to follow a later version.

15. Disclaimer of Warranty.

    THERE IS NO WARRANTY FOR THE PROGRAM, TO THE EXTENT PERMITTED BY APPLICABLE LAW. EXCEPT WHEN OTHERWISE STATED IN WRITING THE COPYRIGHT HOLDERS AND/OR OTHER PARTIES PROVIDE THE PROGRAM "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESSED OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. THE ENTIRE RISK AS TO THE QUALITY AND PERFORMANCE OF THE PROGRAM IS WITH YOU. SHOULD THE PROGRAM PROVE DEFECTIVE, YOU ASSUME THE COST OF ALL NECESSARY SERVICING, REPAIR OR CORRECTION.

16. Limitation of Liability.

    IN NO EVENT UNLESS REQUIRED BY APPLICABLE LAW OR AGREED TO IN WRITING WILL ANY COPYRIGHT HOLDER, OR ANY OTHER PARTY WHO MODIFIES AND/OR CONVEYS THE PROGRAM AS PERMITTED ABOVE, BE LIABLE TO YOU FOR DAMAGES, INCLUDING ANY GENERAL, SPECIAL, INCIDENTAL OR CONSEQUENTIAL DAMAGES ARISING OUT OF THE USE OR INABILITY TO USE THE PROGRAM (INCLUDING BUT NOT LIMITED TO LOSS OF DATA OR DATA BEING RENDERED INACCURATE OR LOSSES SUSTAINED BY YOU OR THIRD PARTIES OR A FAILURE OF THE PROGRAM TO OPERATE WITH ANY OTHER PROGRAMS), EVEN IF SUCH HOLDER OR OTHER PARTY HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

17. Interpretation of Sections 15 and 16.

    If the disclaimer of warranty and limitation of liability provided above cannot be given local legal effect according to their terms, reviewing courts shall apply local law that most closely approximates an absolute waiver of all civil liability in connection with the Program, unless a warranty or assumption of liability accompanies a copy of the Program in return for a fee.

END OF TERMS AND CONDITIONS

How to Apply These Terms to Your New Programs

If you develop a new program, and you want it to be of the greatest possible use to the public, the best way to achieve this is to make it free software which everyone can redistribute and change under these terms.

To do so, attach the following notices to the program. It is safest to attach them to the start of each source file to most effectively state the exclusion of warranty; and each file should have at least the "copyright" line and a pointer to where the full notice is found.

```
one line to give the program's name and a brief idea of what it does.
Copyright (C) year name of author

This program is free software: you can redistribute it and/or modify
it under the terms of the GNU General Public License as published by
the Free Software Foundation, either version 3 of the License, or (at
your option) any later version.

This program is distributed in the hope that it will be useful, but
WITHOUT ANY WARRANTY; without even the implied warranty of
MERCHANTABILITY or FITNESS FOR A PARTICULAR PURPOSE.  See the GNU
General Public License for more details.

You should have received a copy of the GNU General Public License
along with this program.  If not, see http://www.gnu.org/licenses/.
```

Also add information on how to contact you by electronic and paper mail.

If the program does terminal interaction, make it output a short notice like this when it starts in an interactive mode:

```
program Copyright (C) year name of author
This program comes with ABSOLUTELY NO WARRANTY; for details type 'show w'.
This is free software, and you are welcome to redistribute it
under certain conditions; type 'show c' for details.
```

The hypothetical commands '`show w`' and '`show c`' should show the appropriate parts of the General Public License. Of course, your program's commands might be different; for a GUI interface, you would use an "about box".

You should also get your employer (if you work as a programmer) or school, if any, to sign a "copyright disclaimer" for the program, if necessary. For more information on this, and how to apply and follow the GNU GPL, see http://www.gnu.org/licenses/.

The GNU General Public License does not permit incorporating your program into proprietary programs. If your program is a subroutine library, you may consider it more useful to permit linking proprietary applications with the library. If this is what you want to do, use the GNU Lesser General Public License instead of this License. But first, please read http://www.gnu.org/philosophy/why-not-lgpl.html.

GNU Free Documentation License

Version 1.3, 3 November 2008

Copyright © 2000, 2001, 2002, 2007, 2008 Free Software Foundation, Inc.
http://fsf.org/

Everyone is permitted to copy and distribute verbatim copies
of this license document, but changing it is not allowed.

0. PREAMBLE

The purpose of this License is to make a manual, textbook, or other functional and useful document *free* in the sense of freedom: to assure everyone the effective freedom to copy and redistribute it, with or without modifying it, either commercially or non-commercially. Secondarily, this License preserves for the author and publisher a way to get credit for their work, while not being considered responsible for modifications made by others.

This License is a kind of "copyleft", which means that derivative works of the document must themselves be free in the same sense. It complements the GNU General Public License, which is a copyleft license designed for free software.

We have designed this License in order to use it for manuals for free software, because free software needs free documentation: a free program should come with manuals providing the same freedoms that the software does. But this License is not limited to software manuals; it can be used for any textual work, regardless of subject matter or whether it is published as a printed book. We recommend this License principally for works whose purpose is instruction or reference.

1. APPLICABILITY AND DEFINITIONS

This License applies to any manual or other work, in any medium, that contains a notice placed by the copyright holder saying it can be distributed under the terms of this License. Such a notice grants a world-wide, royalty-free license, unlimited in duration, to use that work under the conditions stated herein. The "Document", below, refers to any such manual or work. Any member of the public is a licensee, and is addressed as "you". You accept the license if you copy, modify or distribute the work in a way requiring permission under copyright law.

A "Modified Version" of the Document means any work containing the Document or a portion of it, either copied verbatim, or with modifications and/or translated into another language.

A "Secondary Section" is a named appendix or a front-matter section of the Document that deals exclusively with the relationship of the publishers or authors of the Document to the Document's overall subject (or to related matters) and contains nothing that could fall directly within that overall subject. (Thus, if the Document is in part a textbook of mathematics, a Secondary Section may not explain any mathematics.) The relationship could be a matter of historical connection with the subject or with related matters, or of legal, commercial, philosophical, ethical or political position regarding them.

The "Invariant Sections" are certain Secondary Sections whose titles are designated, as being those of Invariant Sections, in the notice that says that the Document is released

under this License. If a section does not fit the above definition of Secondary then it is not allowed to be designated as Invariant. The Document may contain zero Invariant Sections. If the Document does not identify any Invariant Sections then there are none.

The "Cover Texts" are certain short passages of text that are listed, as Front-Cover Texts or Back-Cover Texts, in the notice that says that the Document is released under this License. A Front-Cover Text may be at most 5 words, and a Back-Cover Text may be at most 25 words.

A "Transparent" copy of the Document means a machine-readable copy, represented in a format whose specification is available to the general public, that is suitable for revising the document straightforwardly with generic text editors or (for images composed of pixels) generic paint programs or (for drawings) some widely available drawing editor, and that is suitable for input to text formatters or for automatic translation to a variety of formats suitable for input to text formatters. A copy made in an otherwise Transparent file format whose markup, or absence of markup, has been arranged to thwart or discourage subsequent modification by readers is not Transparent. An image format is not Transparent if used for any substantial amount of text. A copy that is not "Transparent" is called "Opaque".

Examples of suitable formats for Transparent copies include plain ASCII without markup, Texinfo input format, LaTeX input format, SGML or XML using a publicly available DTD, and standard-conforming simple HTML, PostScript or PDF designed for human modification. Examples of transparent image formats include PNG, XCF and JPG. Opaque formats include proprietary formats that can be read and edited only by proprietary word processors, SGML or XML for which the DTD and/or processing tools are not generally available, and the machine-generated HTML, PostScript or PDF produced by some word processors for output purposes only.

The "Title Page" means, for a printed book, the title page itself, plus such following pages as are needed to hold, legibly, the material this License requires to appear in the title page. For works in formats which do not have any title page as such, "Title Page" means the text near the most prominent appearance of the work's title, preceding the beginning of the body of the text.

The "publisher" means any person or entity that distributes copies of the Document to the public.

A section "Entitled XYZ" means a named subunit of the Document whose title either is precisely XYZ or contains XYZ in parentheses following text that translates XYZ in another language. (Here XYZ stands for a specific section name mentioned below, such as "Acknowledgements", "Dedications", "Endorsements", or "History".) To "Preserve the Title" of such a section when you modify the Document means that it remains a section "Entitled XYZ" according to this definition.

The Document may include Warranty Disclaimers next to the notice which states that this License applies to the Document. These Warranty Disclaimers are considered to be included by reference in this License, but only as regards disclaiming warranties: any other implication that these Warranty Disclaimers may have is void and has no effect on the meaning of this License.

2. VERBATIM COPYING

You may copy and distribute the Document in any medium, either commercially or noncommercially, provided that this License, the copyright notices, and the license notice saying this License applies to the Document are reproduced in all copies, and that you add no other conditions whatsoever to those of this License. You may not use technical measures to obstruct or control the reading or further copying of the copies you make or distribute. However, you may accept compensation in exchange for copies. If you distribute a large enough number of copies you must also follow the conditions in section 3.

You may also lend copies, under the same conditions stated above, and you may publicly display copies.

3. COPYING IN QUANTITY

   If you publish printed copies (or copies in media that commonly have printed covers) of the Document, numbering more than 100, and the Document's license notice requires Cover Texts, you must enclose the copies in covers that carry, clearly and legibly, all these Cover Texts: Front-Cover Texts on the front cover, and Back-Cover Texts on the back cover. Both covers must also clearly and legibly identify you as the publisher of these copies. The front cover must present the full title with all words of the title equally prominent and visible. You may add other material on the covers in addition. Copying with changes limited to the covers, as long as they preserve the title of the Document and satisfy these conditions, can be treated as verbatim copying in other respects.

   If the required texts for either cover are too voluminous to fit legibly, you should put the first ones listed (as many as fit reasonably) on the actual cover, and continue the rest onto adjacent pages.

   If you publish or distribute Opaque copies of the Document numbering more than 100, you must either include a machine-readable Transparent copy along with each Opaque copy, or state in or with each Opaque copy a computer-network location from which the general network-using public has access to download using public-standard network protocols a complete Transparent copy of the Document, free of added material. If you use the latter option, you must take reasonably prudent steps, when you begin distribution of Opaque copies in quantity, to ensure that this Transparent copy will remain thus accessible at the stated location until at least one year after the last time you distribute an Opaque copy (directly or through your agents or retailers) of that edition to the public.

   It is requested, but not required, that you contact the authors of the Document well before redistributing any large number of copies, to give them a chance to provide you with an updated version of the Document.

4. MODIFICATIONS

   You may copy and distribute a Modified Version of the Document under the conditions of sections 2 and 3 above, provided that you release the Modified Version under precisely this License, with the Modified Version filling the role of the Document, thus licensing distribution and modification of the Modified Version to whoever possesses a copy of it. In addition, you must do these things in the Modified Version:

   A. Use in the Title Page (and on the covers, if any) a title distinct from that of the Document, and from those of previous versions (which should, if there were any,

be listed in the History section of the Document). You may use the same title as a previous version if the original publisher of that version gives permission.

B. List on the Title Page, as authors, one or more persons or entities responsible for authorship of the modifications in the Modified Version, together with at least five of the principal authors of the Document (all of its principal authors, if it has fewer than five), unless they release you from this requirement.

C. State on the Title page the name of the publisher of the Modified Version, as the publisher.

D. Preserve all the copyright notices of the Document.

E. Add an appropriate copyright notice for your modifications adjacent to the other copyright notices.

F. Include, immediately after the copyright notices, a license notice giving the public permission to use the Modified Version under the terms of this License, in the form shown in the Addendum below.

G. Preserve in that license notice the full lists of Invariant Sections and required Cover Texts given in the Document's license notice.

H. Include an unaltered copy of this License.

I. Preserve the section Entitled "History", Preserve its Title, and add to it an item stating at least the title, year, new authors, and publisher of the Modified Version as given on the Title Page. If there is no section Entitled "History" in the Document, create one stating the title, year, authors, and publisher of the Document as given on its Title Page, then add an item describing the Modified Version as stated in the previous sentence.

J. Preserve the network location, if any, given in the Document for public access to a Transparent copy of the Document, and likewise the network locations given in the Document for previous versions it was based on. These may be placed in the "History" section. You may omit a network location for a work that was published at least four years before the Document itself, or if the original publisher of the version it refers to gives permission.

K. For any section Entitled "Acknowledgements" or "Dedications", Preserve the Title of the section, and preserve in the section all the substance and tone of each of the contributor acknowledgements and/or dedications given therein.

L. Preserve all the Invariant Sections of the Document, unaltered in their text and in their titles. Section numbers or the equivalent are not considered part of the section titles.

M. Delete any section Entitled "Endorsements". Such a section may not be included in the Modified Version.

N. Do not retitle any existing section to be Entitled "Endorsements" or to conflict in title with any Invariant Section.

O. Preserve any Warranty Disclaimers.

If the Modified Version includes new front-matter sections or appendices that qualify as Secondary Sections and contain no material copied from the Document, you may at your option designate some or all of these sections as invariant. To do this, add their

titles to the list of Invariant Sections in the Modified Version's license notice. These titles must be distinct from any other section titles.

You may add a section Entitled "Endorsements", provided it contains nothing but endorsements of your Modified Version by various parties—for example, statements of peer review or that the text has been approved by an organization as the authoritative definition of a standard.

You may add a passage of up to five words as a Front-Cover Text, and a passage of up to 25 words as a Back-Cover Text, to the end of the list of Cover Texts in the Modified Version. Only one passage of Front-Cover Text and one of Back-Cover Text may be added by (or through arrangements made by) any one entity. If the Document already includes a cover text for the same cover, previously added by you or by arrangement made by the same entity you are acting on behalf of, you may not add another; but you may replace the old one, on explicit permission from the previous publisher that added the old one.

The author(s) and publisher(s) of the Document do not by this License give permission to use their names for publicity for or to assert or imply endorsement of any Modified Version.

5. COMBINING DOCUMENTS

   You may combine the Document with other documents released under this License, under the terms defined in section 4 above for modified versions, provided that you include in the combination all of the Invariant Sections of all of the original documents, unmodified, and list them all as Invariant Sections of your combined work in its license notice, and that you preserve all their Warranty Disclaimers.

   The combined work need only contain one copy of this License, and multiple identical Invariant Sections may be replaced with a single copy. If there are multiple Invariant Sections with the same name but different contents, make the title of each such section unique by adding at the end of it, in parentheses, the name of the original author or publisher of that section if known, or else a unique number. Make the same adjustment to the section titles in the list of Invariant Sections in the license notice of the combined work.

   In the combination, you must combine any sections Entitled "History" in the various original documents, forming one section Entitled "History"; likewise combine any sections Entitled "Acknowledgements", and any sections Entitled "Dedications". You must delete all sections Entitled "Endorsements."

6. COLLECTIONS OF DOCUMENTS

   You may make a collection consisting of the Document and other documents released under this License, and replace the individual copies of this License in the various documents with a single copy that is included in the collection, provided that you follow the rules of this License for verbatim copying of each of the documents in all other respects.

   You may extract a single document from such a collection, and distribute it individually under this License, provided you insert a copy of this License into the extracted document, and follow this License in all other respects regarding verbatim copying of that document.

7. AGGREGATION WITH INDEPENDENT WORKS

   A compilation of the Document or its derivatives with other separate and independent documents or works, in or on a volume of a storage or distribution medium, is called an "aggregate" if the copyright resulting from the compilation is not used to limit the legal rights of the compilation's users beyond what the individual works permit. When the Document is included in an aggregate, this License does not apply to the other works in the aggregate which are not themselves derivative works of the Document.

   If the Cover Text requirement of section 3 is applicable to these copies of the Document, then if the Document is less than one half of the entire aggregate, the Document's Cover Texts may be placed on covers that bracket the Document within the aggregate, or the electronic equivalent of covers if the Document is in electronic form. Otherwise they must appear on printed covers that bracket the whole aggregate.

8. TRANSLATION

   Translation is considered a kind of modification, so you may distribute translations of the Document under the terms of section 4. Replacing Invariant Sections with translations requires special permission from their copyright holders, but you may include translations of some or all Invariant Sections in addition to the original versions of these Invariant Sections. You may include a translation of this License, and all the license notices in the Document, and any Warranty Disclaimers, provided that you also include the original English version of this License and the original versions of those notices and disclaimers. In case of a disagreement between the translation and the original version of this License or a notice or disclaimer, the original version will prevail.

   If a section in the Document is Entitled "Acknowledgements", "Dedications", or "History", the requirement (section 4) to Preserve its Title (section 1) will typically require changing the actual title.

9. TERMINATION

   You may not copy, modify, sublicense, or distribute the Document except as expressly provided under this License. Any attempt otherwise to copy, modify, sublicense, or distribute it is void, and will automatically terminate your rights under this License.

   However, if you cease all violation of this License, then your license from a particular copyright holder is reinstated (a) provisionally, unless and until the copyright holder explicitly and finally terminates your license, and (b) permanently, if the copyright holder fails to notify you of the violation by some reasonable means prior to 60 days after the cessation.

   Moreover, your license from a particular copyright holder is reinstated permanently if the copyright holder notifies you of the violation by some reasonable means, this is the first time you have received notice of violation of this License (for any work) from that copyright holder, and you cure the violation prior to 30 days after your receipt of the notice.

   Termination of your rights under this section does not terminate the licenses of parties who have received copies or rights from you under this License. If your rights have been terminated and not permanently reinstated, receipt of a copy of some or all of the same material does not give you any rights to use it.

10. FUTURE REVISIONS OF THIS LICENSE

    The Free Software Foundation may publish new, revised versions of the GNU Free Documentation License from time to time. Such new versions will be similar in spirit to the present version, but may differ in detail to address new problems or concerns. See http://www.gnu.org/copyleft/.

    Each version of the License is given a distinguishing version number. If the Document specifies that a particular numbered version of this License "or any later version" applies to it, you have the option of following the terms and conditions either of that specified version or of any later version that has been published (not as a draft) by the Free Software Foundation. If the Document does not specify a version number of this License, you may choose any version ever published (not as a draft) by the Free Software Foundation. If the Document specifies that a proxy can decide which future versions of this License can be used, that proxy's public statement of acceptance of a version permanently authorizes you to choose that version for the Document.

11. RELICENSING

    "Massive Multiauthor Collaboration Site" (or "MMC Site") means any World Wide Web server that publishes copyrightable works and also provides prominent facilities for anybody to edit those works. A public wiki that anybody can edit is an example of such a server. A "Massive Multiauthor Collaboration" (or "MMC") contained in the site means any set of copyrightable works thus published on the MMC site.

    "CC-BY-SA" means the Creative Commons Attribution-Share Alike 3.0 license published by Creative Commons Corporation, a not-for-profit corporation with a principal place of business in San Francisco, California, as well as future copyleft versions of that license published by that same organization.

    "Incorporate" means to publish or republish a Document, in whole or in part, as part of another Document.

    An MMC is "eligible for relicensing" if it is licensed under this License, and if all works that were first published under this License somewhere other than this MMC, and subsequently incorporated in whole or in part into the MMC, (1) had no cover texts or invariant sections, and (2) were thus incorporated prior to November 1, 2008.

    The operator of an MMC Site may republish an MMC contained in the site under CC-BY-SA on the same site at any time before August 1, 2009, provided the MMC is eligible for relicensing.

ADDENDUM: How to use this License for your documents

To use this License in a document you have written, include a copy of the License in the document and put the following copyright and license notices just after the title page:

```
Copyright (C)  year  your name.
Permission is granted to copy, distribute and/or modify this document
under the terms of the GNU Free Documentation License, Version 1.3
or any later version published by the Free Software Foundation;
with no Invariant Sections, no Front-Cover Texts, and no Back-Cover
Texts.  A copy of the license is included in the section entitled ``GNU
Free Documentation License''.
```

If you have Invariant Sections, Front-Cover Texts and Back-Cover Texts, replace the "with...Texts." line with this:

```
with the Invariant Sections being list their titles, with
the Front-Cover Texts being list, and with the Back-Cover Texts
being list.
```

If you have Invariant Sections without Cover Texts, or some other combination of the three, merge those two alternatives to suit the situation.

If your document contains nontrivial examples of program code, we recommend releasing these examples in parallel under your choice of free software license, such as the GNU General Public License, to permit their use in free software.

Contributors to GCC

The GCC project would like to thank its many contributors. Without them the project would not have been nearly as successful as it has been. Any omissions in this list are accidental. Feel free to contact law@redhat.com or gerald@pfeifer.com if you have been left out or some of your contributions are not listed. Please keep this list in alphabetical order.

- Analog Devices helped implement the support for complex data types and iterators.
- John David Anglin for threading-related fixes and improvements to libstdc++-v3, and the HP-UX port.
- James van Artsdalen wrote the code that makes efficient use of the Intel 80387 register stack.
- Abramo and Roberto Bagnara for the SysV68 Motorola 3300 Delta Series port.
- Alasdair Baird for various bug fixes.
- Giovanni Bajo for analyzing lots of complicated C++ problem reports.
- Peter Barada for his work to improve code generation for new ColdFire cores.
- Gerald Baumgartner added the signature extension to the C++ front end.
- Godmar Back for his Java improvements and encouragement.
- Scott Bambrough for help porting the Java compiler.
- Wolfgang Bangerth for processing tons of bug reports.
- Jon Beniston for his Microsoft Windows port of Java and port to Lattice Mico32.
- Daniel Berlin for better DWARF2 support, faster/better optimizations, improved alias analysis, plus migrating GCC to Bugzilla.
- Geoff Berry for his Java object serialization work and various patches.
- David Binderman tests weekly snapshots of GCC trunk against Fedora Rawhide for several architectures.
- Uros Bizjak for the implementation of x87 math built-in functions and for various middle end and i386 back end improvements and bug fixes.
- Eric Blake for helping to make GCJ and libgcj conform to the specifications.
- Janne Blomqvist for contributions to GNU Fortran.
- Segher Boessenkool for various fixes.
- Hans-J. Boehm for his garbage collector, IA-64 libffi port, and other Java work.
- Neil Booth for work on cpplib, lang hooks, debug hooks and other miscellaneous clean-ups.
- Steven Bosscher for integrating the GNU Fortran front end into GCC and for contributing to the tree-ssa branch.
- Eric Botcazou for fixing middle- and backend bugs left and right.
- Per Bothner for his direction via the steering committee and various improvements to the infrastructure for supporting new languages. Chill front end implementation. Initial implementations of cpplib, fix-header, config.guess, libio, and past C++ library (libg++) maintainer. Dreaming up, designing and implementing much of GCJ.

- Devon Bowen helped port GCC to the Tahoe.
- Don Bowman for mips-vxworks contributions.
- Dave Brolley for work on cpplib and Chill.
- Paul Brook for work on the ARM architecture and maintaining GNU Fortran.
- Robert Brown implemented the support for Encore 32000 systems.
- Christian Bruel for improvements to local store elimination.
- Herman A.J. ten Brugge for various fixes.
- Joerg Brunsmann for Java compiler hacking and help with the GCJ FAQ.
- Joe Buck for his direction via the steering committee.
- Craig Burley for leadership of the G77 Fortran effort.
- Stephan Buys for contributing Doxygen notes for libstdc++.
- Paolo Carlini for libstdc++ work: lots of efficiency improvements to the C++ strings, streambufs and formatted I/O, hard detective work on the frustrating localization issues, and keeping up with the problem reports.
- John Carr for his alias work, SPARC hacking, infrastructure improvements, previous contributions to the steering committee, loop optimizations, etc.
- Stephane Carrez for 68HC11 and 68HC12 ports.
- Steve Chamberlain for support for the Renesas SH and H8 processors and the PicoJava processor, and for GCJ config fixes.
- Glenn Chambers for help with the GCJ FAQ.
- John-Marc Chandonia for various libgcj patches.
- Denis Chertykov for contributing and maintaining the AVR port, the first GCC port for an 8-bit architecture.
- Scott Christley for his Objective-C contributions.
- Eric Christopher for his Java porting help and clean-ups.
- Branko Cibej for more warning contributions.
- The GNU Classpath project for all of their merged runtime code.
- Nick Clifton for arm, mcore, fr30, v850, m32r, msp430 rx work, '`--help`', and other random hacking.
- Michael Cook for libstdc++ cleanup patches to reduce warnings.
- R. Kelley Cook for making GCC buildable from a read-only directory as well as other miscellaneous build process and documentation clean-ups.
- Ralf Corsepius for SH testing and minor bug fixing.
- Stan Cox for care and feeding of the x86 port and lots of behind the scenes hacking.
- Alex Crain provided changes for the 3b1.
- Ian Dall for major improvements to the NS32k port.
- Paul Dale for his work to add uClinux platform support to the m68k backend.
- Dario Dariol contributed the four varieties of sample programs that print a copy of their source.
- Russell Davidson for fstream and stringstream fixes in libstdc++.

- Bud Davis for work on the G77 and GNU Fortran compilers.
- Mo DeJong for GCJ and libgcj bug fixes.
- DJ Delorie for the DJGPP port, build and libiberty maintenance, various bug fixes, and the M32C, MeP, MSP430, and RL78 ports.
- Arnaud Desitter for helping to debug GNU Fortran.
- Gabriel Dos Reis for contributions to G++, contributions and maintenance of GCC diagnostics infrastructure, libstdc++-v3, including `valarray<>`, `complex<>`, maintaining the numerics library (including that pesky `<limits>` :-) and keeping up-to-date anything to do with numbers.
- Ulrich Drepper for his work on glibc, testing of GCC using glibc, ISO C99 support, CFG dumping support, etc., plus support of the C++ runtime libraries including for all kinds of C interface issues, contributing and maintaining `complex<>`, sanity checking and disbursement, configuration architecture, libio maintenance, and early math work.
- François Dumont for his work on libstdc++-v3, especially maintaining and improving `debug-mode` and associative and unordered containers.
- Zdenek Dvorak for a new loop unroller and various fixes.
- Michael Eager for his work on the Xilinx MicroBlaze port.
- Richard Earnshaw for his ongoing work with the ARM.
- David Edelsohn for his direction via the steering committee, ongoing work with the RS6000/PowerPC port, help cleaning up Haifa loop changes, doing the entire AIX port of libstdc++ with his bare hands, and for ensuring GCC properly keeps working on AIX.
- Kevin Ediger for the floating point formatting of num_put::do_put in libstdc++.
- Phil Edwards for libstdc++ work including configuration hackery, documentation maintainer, chief breaker of the web pages, the occasional iostream bug fix, and work on shared library symbol versioning.
- Paul Eggert for random hacking all over GCC.
- Mark Elbrecht for various DJGPP improvements, and for libstdc++ configuration support for locales and fstream-related fixes.
- Vadim Egorov for libstdc++ fixes in strings, streambufs, and iostreams.
- Christian Ehrhardt for dealing with bug reports.
- Ben Elliston for his work to move the Objective-C runtime into its own subdirectory and for his work on autoconf.
- Revital Eres for work on the PowerPC 750CL port.
- Marc Espie for OpenBSD support.
- Doug Evans for much of the global optimization framework, arc, m32r, and SPARC work.
- Christopher Faylor for his work on the Cygwin port and for caring and feeding the gcc.gnu.org box and saving its users tons of spam.
- Fred Fish for BeOS support and Ada fixes.
- Ivan Fontes Garcia for the Portuguese translation of the GCJ FAQ.
- Peter Gerwinski for various bug fixes and the Pascal front end.

- Kaveh R. Ghazi for his direction via the steering committee, amazing work to make '`-W -Wall -W* -Werror`' useful, and testing GCC on a plethora of platforms. Kaveh extends his gratitude to the CAIP Center at Rutgers University for providing him with computing resources to work on Free Software from the late 1980s to 2010.
- John Gilmore for a donation to the FSF earmarked improving GNU Java.
- Judy Goldberg for c++ contributions.
- Torbjorn Granlund for various fixes and the c-torture testsuite, multiply- and divide-by-constant optimization, improved long long support, improved leaf function register allocation, and his direction via the steering committee.
- Anthony Green for his '`-Os`' contributions, the moxie port, and Java front end work.
- Stu Grossman for gdb hacking, allowing GCJ developers to debug Java code.
- Michael K. Gschwind contributed the port to the PDP-11.
- Richard Biener for his ongoing middle-end contributions and bug fixes and for release management.
- Ron Guilmette implemented the `protoize` and `unprotoize` tools, the support for Dwarf symbolic debugging information, and much of the support for System V Release 4. He has also worked heavily on the Intel 386 and 860 support.
- Sumanth Gundapaneni for contributing the CR16 port.
- Mostafa Hagog for Swing Modulo Scheduling (SMS) and post reload GCSE.
- Bruno Haible for improvements in the runtime overhead for EH, new warnings and assorted bug fixes.
- Andrew Haley for his amazing Java compiler and library efforts.
- Chris Hanson assisted in making GCC work on HP-UX for the 9000 series 300.
- Michael Hayes for various thankless work he's done trying to get the c30/c40 ports functional. Lots of loop and unroll improvements and fixes.
- Dara Hazeghi for wading through myriads of target-specific bug reports.
- Kate Hedstrom for staking the G77 folks with an initial testsuite.
- Richard Henderson for his ongoing SPARC, alpha, ia32, and ia64 work, loop opts, and generally fixing lots of old problems we've ignored for years, flow rewrite and lots of further stuff, including reviewing tons of patches.
- Aldy Hernandez for working on the PowerPC port, SIMD support, and various fixes.
- Nobuyuki Hikichi of Software Research Associates, Tokyo, contributed the support for the Sony NEWS machine.
- Kazu Hirata for caring and feeding the Renesas H8/300 port and various fixes.
- Katherine Holcomb for work on GNU Fortran.
- Manfred Hollstein for his ongoing work to keep the m88k alive, lots of testing and bug fixing, particularly of GCC configury code.
- Steve Holmgren for MachTen patches.
- Mat Hostetter for work on the TILE-Gx and TILEPro ports.
- Jan Hubicka for his x86 port improvements.
- Falk Hueffner for working on C and optimization bug reports.

- Bernardo Innocenti for his m68k work, including merging of ColdFire improvements and uClinux support.
- Christian Iseli for various bug fixes.
- Kamil Iskra for general m68k hacking.
- Lee Iverson for random fixes and MIPS testing.
- Andreas Jaeger for testing and benchmarking of GCC and various bug fixes.
- Jakub Jelinek for his SPARC work and sibling call optimizations as well as lots of bug fixes and test cases, and for improving the Java build system.
- Janis Johnson for ia64 testing and fixes, her quality improvement sidetracks, and web page maintenance.
- Kean Johnston for SCO OpenServer support and various fixes.
- Tim Josling for the sample language treelang based originally on Richard Kenner's "toy" language.
- Nicolai Josuttis for additional libstdc++ documentation.
- Klaus Kaempf for his ongoing work to make alpha-vms a viable target.
- Steven G. Kargl for work on GNU Fortran.
- David Kashtan of SRI adapted GCC to VMS.
- Ryszard Kabatek for many, many libstdc++ bug fixes and optimizations of strings, especially member functions, and for auto_ptr fixes.
- Geoffrey Keating for his ongoing work to make the PPC work for GNU/Linux and his automatic regression tester.
- Brendan Kehoe for his ongoing work with G++ and for a lot of early work in just about every part of libstdc++.
- Oliver M. Kellogg of Deutsche Aerospace contributed the port to the MIL-STD-1750A.
- Richard Kenner of the New York University Ultracomputer Research Laboratory wrote the machine descriptions for the AMD 29000, the DEC Alpha, the IBM RT PC, and the IBM RS/6000 as well as the support for instruction attributes. He also made changes to better support RISC processors including changes to common subexpression elimination, strength reduction, function calling sequence handling, and condition code support, in addition to generalizing the code for frame pointer elimination and delay slot scheduling. Richard Kenner was also the head maintainer of GCC for several years.
- Mumit Khan for various contributions to the Cygwin and Mingw32 ports and maintaining binary releases for Microsoft Windows hosts, and for massive libstdc++ porting work to Cygwin/Mingw32.
- Robin Kirkham for cpu32 support.
- Mark Klein for PA improvements.
- Thomas Koenig for various bug fixes.
- Bruce Korb for the new and improved fixincludes code.
- Benjamin Kosnik for his G++ work and for leading the libstdc++-v3 effort.
- Charles LaBrec contributed the support for the Integrated Solutions 68020 system.
- Asher Langton and Mike Kumbera for contributing Cray pointer support to GNU Fortran, and for other GNU Fortran improvements.

- Jeff Law for his direction via the steering committee, coordinating the entire egcs project and GCC 2.95, rolling out snapshots and releases, handling merges from GCC2, reviewing tons of patches that might have fallen through the cracks else, and random but extensive hacking.
- Walter Lee for work on the TILE-Gx and TILEPro ports.
- Marc Lehmann for his direction via the steering committee and helping with analysis and improvements of x86 performance.
- Victor Leikehman for work on GNU Fortran.
- Ted Lemon wrote parts of the RTL reader and printer.
- Kriang Lerdsuwanakij for C++ improvements including template as template parameter support, and many C++ fixes.
- Warren Levy for tremendous work on libgcj (Java Runtime Library) and random work on the Java front end.
- Alain Lichnewsky ported GCC to the MIPS CPU.
- Oskar Liljeblad for hacking on AWT and his many Java bug reports and patches.
- Robert Lipe for OpenServer support, new testsuites, testing, etc.
- Chen Liqin for various S+core related fixes/improvement, and for maintaining the S+core port.
- Weiwen Liu for testing and various bug fixes.
- Manuel López-Ibáñez for improving '`-Wconversion`' and many other diagnostics fixes and improvements.
- Dave Love for his ongoing work with the Fortran front end and runtime libraries.
- Martin von Löwis for internal consistency checking infrastructure, various C++ improvements including namespace support, and tons of assistance with libstdc++/compiler merges.
- H.J. Lu for his previous contributions to the steering committee, many x86 bug reports, prototype patches, and keeping the GNU/Linux ports working.
- Greg McGary for random fixes and (someday) bounded pointers.
- Andrew MacLeod for his ongoing work in building a real EH system, various code generation improvements, work on the global optimizer, etc.
- Vladimir Makarov for hacking some ugly i960 problems, PowerPC hacking improvements to compile-time performance, overall knowledge and direction in the area of instruction scheduling, and design and implementation of the automaton based instruction scheduler.
- Bob Manson for his behind the scenes work on dejagnu.
- Philip Martin for lots of libstdc++ string and vector iterator fixes and improvements, and string clean up and testsuites.
- All of the Mauve project contributors, for Java test code.
- Bryce McKinlay for numerous GCJ and libgcj fixes and improvements.
- Adam Megacz for his work on the Microsoft Windows port of GCJ.
- Michael Meissner for LRS framework, ia32, m32r, v850, m88k, MIPS, powerpc, haifa, ECOFF debug support, and other assorted hacking.

- Jason Merrill for his direction via the steering committee and leading the G++ effort.
- Martin Michlmayr for testing GCC on several architectures using the entire Debian archive.
- David Miller for his direction via the steering committee, lots of SPARC work, improvements in jump.c and interfacing with the Linux kernel developers.
- Gary Miller ported GCC to Charles River Data Systems machines.
- Alfred Minarik for libstdc++ string and ios bug fixes, and turning the entire libstdc++ testsuite namespace-compatible.
- Mark Mitchell for his direction via the steering committee, mountains of C++ work, load/store hoisting out of loops, alias analysis improvements, ISO C `restrict` support, and serving as release manager from 2000 to 2011.
- Alan Modra for various GNU/Linux bits and testing.
- Toon Moene for his direction via the steering committee, Fortran maintenance, and his ongoing work to make us make Fortran run fast.
- Jason Molenda for major help in the care and feeding of all the services on the gcc.gnu.org (formerly egcs.cygnus.com) machine—mail, web services, ftp services, etc etc. Doing all this work on scrap paper and the backs of envelopes would have been. . . difficult.
- Catherine Moore for fixing various ugly problems we have sent her way, including the haifa bug which was killing the Alpha & PowerPC Linux kernels.
- Mike Moreton for his various Java patches.
- David Mosberger-Tang for various Alpha improvements, and for the initial IA-64 port.
- Stephen Moshier contributed the floating point emulator that assists in cross-compilation and permits support for floating point numbers wider than 64 bits and for ISO C99 support.
- Bill Moyer for his behind the scenes work on various issues.
- Philippe De Muyter for his work on the m68k port.
- Joseph S. Myers for his work on the PDP-11 port, format checking and ISO C99 support, and continuous emphasis on (and contributions to) documentation.
- Nathan Myers for his work on libstdc++-v3: architecture and authorship through the first three snapshots, including implementation of locale infrastructure, string, shadow C headers, and the initial project documentation (DESIGN, CHECKLIST, and so forth). Later, more work on MT-safe string and shadow headers.
- Felix Natter for documentation on porting libstdc++.
- Nathanael Nerode for cleaning up the configuration/build process.
- NeXT, Inc. donated the front end that supports the Objective-C language.
- Hans-Peter Nilsson for the CRIS and MMIX ports, improvements to the search engine setup, various documentation fixes and other small fixes.
- Geoff Noer for his work on getting cygwin native builds working.
- Diego Novillo for his work on Tree SSA, OpenMP, SPEC performance tracking web pages, GIMPLE tuples, and assorted fixes.

- David O'Brien for the FreeBSD/alpha, FreeBSD/AMD x86-64, FreeBSD/ARM, FreeBSD/PowerPC, and FreeBSD/SPARC64 ports and related infrastructure improvements.
- Alexandre Oliva for various build infrastructure improvements, scripts and amazing testing work, including keeping libtool issues sane and happy.
- Stefan Olsson for work on mt_alloc.
- Melissa O'Neill for various NeXT fixes.
- Rainer Orth for random MIPS work, including improvements to GCC's o32 ABI support, improvements to dejagnu's MIPS support, Java configuration clean-ups and porting work, and maintaining the IRIX, Solaris 2, and Tru64 UNIX ports.
- Hartmut Penner for work on the s390 port.
- Paul Petersen wrote the machine description for the Alliant FX/8.
- Alexandre Petit-Bianco for implementing much of the Java compiler and continued Java maintainership.
- Matthias Pfaller for major improvements to the NS32k port.
- Gerald Pfeifer for his direction via the steering committee, pointing out lots of problems we need to solve, maintenance of the web pages, and taking care of documentation maintenance in general.
- Andrew Pinski for processing bug reports by the dozen.
- Ovidiu Predescu for his work on the Objective-C front end and runtime libraries.
- Jerry Quinn for major performance improvements in C++ formatted I/O.
- Ken Raeburn for various improvements to checker, MIPS ports and various cleanups in the compiler.
- Rolf W. Rasmussen for hacking on AWT.
- David Reese of Sun Microsystems contributed to the Solaris on PowerPC port.
- Volker Reichelt for keeping up with the problem reports.
- Joern Rennecke for maintaining the sh port, loop, regmove & reload hacking and developing and maintaining the Epiphany port.
- Loren J. Rittle for improvements to libstdc++-v3 including the FreeBSD port, threading fixes, thread-related configury changes, critical threading documentation, and solutions to really tricky I/O problems, as well as keeping GCC properly working on FreeBSD and continuous testing.
- Craig Rodrigues for processing tons of bug reports.
- Ola Rönnerup for work on mt_alloc.
- Gavin Romig-Koch for lots of behind the scenes MIPS work.
- David Ronis inspired and encouraged Craig to rewrite the G77 documentation in texinfo format by contributing a first pass at a translation of the old '`g77-0.5.16/f/DOC`' file.
- Ken Rose for fixes to GCC's delay slot filling code.
- Paul Rubin wrote most of the preprocessor.
- Pétur Runólfsson for major performance improvements in C++ formatted I/O and large file support in C++ filebuf.

- Chip Salzenberg for libstdc++ patches and improvements to locales, traits, Makefiles, libio, libtool hackery, and "long long" support.
- Juha Sarlin for improvements to the H8 code generator.
- Greg Satz assisted in making GCC work on HP-UX for the 9000 series 300.
- Roger Sayle for improvements to constant folding and GCC's RTL optimizers as well as for fixing numerous bugs.
- Bradley Schatz for his work on the GCJ FAQ.
- Peter Schauer wrote the code to allow debugging to work on the Alpha.
- William Schelter did most of the work on the Intel 80386 support.
- Tobias Schlüter for work on GNU Fortran.
- Bernd Schmidt for various code generation improvements and major work in the reload pass, serving as release manager for GCC 2.95.3, and work on the Blackfin and C6X ports.
- Peter Schmid for constant testing of libstdc++—especially application testing, going above and beyond what was requested for the release criteria—and libstdc++ header file tweaks.
- Jason Schroeder for jcf-dump patches.
- Andreas Schwab for his work on the m68k port.
- Lars Segerlund for work on GNU Fortran.
- Dodji Seketeli for numerous C++ bug fixes and debug info improvements.
- Tim Shen for major work on `<regex>`.
- Joel Sherrill for his direction via the steering committee, RTEMS contributions and RTEMS testing.
- Nathan Sidwell for many C++ fixes/improvements.
- Jeffrey Siegal for helping RMS with the original design of GCC, some code which handles the parse tree and RTL data structures, constant folding and help with the original VAX & m68k ports.
- Kenny Simpson for prompting libstdc++ fixes due to defect reports from the LWG (thereby keeping GCC in line with updates from the ISO).
- Franz Sirl for his ongoing work with making the PPC port stable for GNU/Linux.
- Andrey Slepuhin for assorted AIX hacking.
- Trevor Smigiel for contributing the SPU port.
- Christopher Smith did the port for Convex machines.
- Danny Smith for his major efforts on the Mingw (and Cygwin) ports.
- Randy Smith finished the Sun FPA support.
- Ed Smith-Rowland for his continuous work on libstdc++-v3, special functions, `<random>`, and various improvements to C++11 features.
- Scott Snyder for queue, iterator, istream, and string fixes and libstdc++ testsuite entries. Also for providing the patch to G77 to add rudimentary support for `INTEGER*1`, `INTEGER*2`, and `LOGICAL*1`.
- Zdenek Sojka for running automated regression testing of GCC and reporting numerous bugs.

- Jayant Sonar for contributing the CR16 port.
- Brad Spencer for contributions to the GLIBCPP_FORCE_NEW technique.
- Richard Stallman, for writing the original GCC and launching the GNU project.
- Jan Stein of the Chalmers Computer Society provided support for Genix, as well as part of the 32000 machine description.
- Nigel Stephens for various mips16 related fixes/improvements.
- Jonathan Stone wrote the machine description for the Pyramid computer.
- Graham Stott for various infrastructure improvements.
- John Stracke for his Java HTTP protocol fixes.
- Mike Stump for his Elxsi port, G++ contributions over the years and more recently his vxworks contributions
- Jeff Sturm for Java porting help, bug fixes, and encouragement.
- Shigeya Suzuki for this fixes for the bsdi platforms.
- Ian Lance Taylor for the Go frontend, the initial mips16 and mips64 support, general configury hacking, fixincludes, etc.
- Holger Teutsch provided the support for the Clipper CPU.
- Gary Thomas for his ongoing work to make the PPC work for GNU/Linux.
- Philipp Thomas for random bug fixes throughout the compiler
- Jason Thorpe for thread support in libstdc++ on NetBSD.
- Kresten Krab Thorup wrote the run time support for the Objective-C language and the fantastic Java bytecode interpreter.
- Michael Tiemann for random bug fixes, the first instruction scheduler, initial C++ support, function integration, NS32k, SPARC and M88k machine description work, delay slot scheduling.
- Andreas Tobler for his work porting libgcj to Darwin.
- Teemu Torma for thread safe exception handling support.
- Leonard Tower wrote parts of the parser, RTL generator, and RTL definitions, and of the VAX machine description.
- Daniel Towner and Hariharan Sandanagobalane contributed and maintain the picoChip port.
- Tom Tromey for internationalization support and for his many Java contributions and libgcj maintainership.
- Lassi Tuura for improvements to config.guess to determine HP processor types.
- Petter Urkedal for libstdc++ CXXFLAGS, math, and algorithms fixes.
- Andy Vaught for the design and initial implementation of the GNU Fortran front end.
- Brent Verner for work with the libstdc++ cshadow files and their associated configure steps.
- Todd Vierling for contributions for NetBSD ports.
- Jonathan Wakely for contributing libstdc++ Doxygen notes and XHTML guidance.
- Dean Wakerley for converting the install documentation from HTML to texinfo in time for GCC 3.0.

- Krister Walfridsson for random bug fixes.
- Feng Wang for contributions to GNU Fortran.
- Stephen M. Webb for time and effort on making libstdc++ shadow files work with the tricky Solaris 8+ headers, and for pushing the build-time header tree. Also, for starting and driving the `<regex>` effort.
- John Wehle for various improvements for the x86 code generator, related infrastructure improvements to help x86 code generation, value range propagation and other work, WE32k port.
- Ulrich Weigand for work on the s390 port.
- Zack Weinberg for major work on cpplib and various other bug fixes.
- Matt Welsh for help with Linux Threads support in GCJ.
- Urban Widmark for help fixing java.io.
- Mark Wielaard for new Java library code and his work integrating with Classpath.
- Dale Wiles helped port GCC to the Tahoe.
- Bob Wilson from Tensilica, Inc. for the Xtensa port.
- Jim Wilson for his direction via the steering committee, tackling hard problems in various places that nobody else wanted to work on, strength reduction and other loop optimizations.
- Paul Woegerer and Tal Agmon for the CRX port.
- Carlo Wood for various fixes.
- Tom Wood for work on the m88k port.
- Chung-Ju Wu for his work on the Andes NDS32 port.
- Canqun Yang for work on GNU Fortran.
- Masanobu Yuhara of Fujitsu Laboratories implemented the machine description for the Tron architecture (specifically, the Gmicro).
- Kevin Zachmann helped port GCC to the Tahoe.
- Ayal Zaks for Swing Modulo Scheduling (SMS).
- Xiaoqiang Zhang for work on GNU Fortran.
- Gilles Zunino for help porting Java to Irix.

The following people are recognized for their contributions to GNAT, the Ada front end of GCC:

- Bernard Banner
- Romain Berrendonner
- Geert Bosch
- Emmanuel Briot
- Joel Brobecker
- Ben Brosgol
- Vincent Celier
- Arnaud Charlet
- Chien Chieng

- Cyrille Comar
- Cyrille Crozes
- Robert Dewar
- Gary Dismukes
- Robert Duff
- Ed Falis
- Ramon Fernandez
- Sam Figueroa
- Vasiliy Fofanov
- Michael Friess
- Franco Gasperoni
- Ted Giering
- Matthew Gingell
- Laurent Guerby
- Jerome Guitton
- Olivier Hainque
- Jerome Hugues
- Hristian Kirtchev
- Jerome Lambourg
- Bruno Leclerc
- Albert Lee
- Sean McNeil
- Javier Miranda
- Laurent Nana
- Pascal Obry
- Dong-Ik Oh
- Laurent Pautet
- Brett Porter
- Thomas Quinot
- Nicolas Roche
- Pat Rogers
- Jose Ruiz
- Douglas Rupp
- Sergey Rybin
- Gail Schenker
- Ed Schonberg
- Nicolas Setton
- Samuel Tardieu

The following people are recognized for their contributions of new features, bug reports, testing and integration of classpath/libgcj for GCC version 4.1:

- Lillian Angel for `JTree` implementation and lots Free Swing additions and bug fixes.
- Wolfgang Baer for `GapContent` bug fixes.
- Anthony Balkissoon for `JList`, Free Swing 1.5 updates and mouse event fixes, lots of Free Swing work including `JTable` editing.
- Stuart Ballard for RMI constant fixes.
- Goffredo Baroncelli for `HTTPURLConnection` fixes.
- Gary Benson for `MessageFormat` fixes.
- Daniel Bonniot for `Serialization` fixes.
- Chris Burdess for lots of gnu.xml and http protocol fixes, `StAX` and `DOM` `xml:id` support.
- Ka-Hing Cheung for `TreePath` and `TreeSelection` fixes.
- Archie Cobbs for build fixes, VM interface updates, `URLClassLoader` updates.
- Kelley Cook for build fixes.
- Martin Cordova for Suggestions for better `SocketTimeoutException`.
- David Daney for `BitSet` bug fixes, `HttpURLConnection` rewrite and improvements.
- Thomas Fitzsimmons for lots of upgrades to the gtk+ AWT and Cairo 2D support. Lots of imageio framework additions, lots of AWT and Free Swing bug fixes.
- Jeroen Frijters for `ClassLoader` and nio cleanups, serialization fixes, better `Proxy` support, bug fixes and IKVM integration.
- Santiago Gala for `AccessControlContext` fixes.
- Nicolas Geoffray for `VMClassLoader` and `AccessController` improvements.
- David Gilbert for `basic` and `metal` icon and plaf support and lots of documenting, Lots of Free Swing and metal theme additions. `MetalIconFactory` implementation.
- Anthony Green for `MIDI` framework, `ALSA` and `DSSI` providers.
- Andrew Haley for `Serialization` and `URLClassLoader` fixes, gcj build speedups.
- Kim Ho for `JFileChooser` implementation.
- Andrew John Hughes for `Locale` and net fixes, URI RFC2986 updates, `Serialization` fixes, `Properties` XML support and generic branch work, VMIntegration guide update.
- Bastiaan Huisman for `TimeZone` bug fixing.
- Andreas Jaeger for mprec updates.
- Paul Jenner for better '`-Werror`' support.
- Ito Kazumitsu for `NetworkInterface` implementation and updates.
- Roman Kennke for `BoxLayout`, `GrayFilter` and `SplitPane`, plus bug fixes all over. Lots of Free Swing work including styled text.
- Simon Kitching for `String` cleanups and optimization suggestions.
- Michael Koch for configuration fixes, `Locale` updates, bug and build fixes.
- Guilhem Lavaux for configuration, thread and channel fixes and Kaffe integration. JCL native `Pointer` updates. Logger bug fixes.
- David Lichteblau for JCL support library global/local reference cleanups.

- Aaron Luchko for JDWP updates and documentation fixes.
- Ziga Mahkovec for `Graphics2D` upgraded to Cairo 0.5 and new regex features.
- Sven de Marothy for BMP imageio support, CSS and `TextLayout` fixes. `GtkImage` rewrite, 2D, awt, free swing and date/time fixes and implementing the Qt4 peers.
- Casey Marshall for crypto algorithm fixes, `FileChannel` lock, `SystemLogger` and `FileHandler` rotate implementations, NIO `FileChannel.map` support, security and policy updates.
- Bryce McKinlay for RMI work.
- Audrius Meskauskas for lots of Free Corba, RMI and HTML work plus testing and documenting.
- Kalle Olavi Niemitalo for build fixes.
- Rainer Orth for build fixes.
- Andrew Overholt for `File` locking fixes.
- Ingo Proetel for `Image`, `Logger` and `URLClassLoader` updates.
- Olga Rodimina for `MenuSelectionManager` implementation.
- Jan Roehrich for `BasicTreeUI` and `JTree` fixes.
- Julian Scheid for documentation updates and gjdoc support.
- Christian Schlichtherle for zip fixes and cleanups.
- Robert Schuster for documentation updates and beans fixes, `TreeNode` enumerations and `ActionCommand` and various fixes, XML and URL, AWT and Free Swing bug fixes.
- Keith Seitz for lots of JDWP work.
- Christian Thalinger for 64-bit cleanups, Configuration and VM interface fixes and `CACAO` integration, `fdlibm` updates.
- Gael Thomas for `VMClassLoader` boot packages support suggestions.
- Andreas Tobler for Darwin and Solaris testing and fixing, `Qt4` support for Darwin/OS X, `Graphics2D` support, `gtk+` updates.
- Dalibor Topic for better `DEBUG` support, build cleanups and Kaffe integration. `Qt4` build infrastructure, `SHA1PRNG` and `GdkPixbugDecoder` updates.
- Tom Tromey for Eclipse integration, generics work, lots of bug fixes and gcj integration including coordinating The Big Merge.
- Mark Wielaard for bug fixes, packaging and release management, `Clipboard` implementation, system call interrupts and network timeouts and `GdkPixpufDecoder` fixes.

In addition to the above, all of which also contributed time and energy in testing GCC, we would like to thank the following for their contributions to testing:

- Michael Abd-El-Malek
- Thomas Arend
- Bonzo Armstrong
- Steven Ashe
- Chris Baldwin
- David Billinghurst

- Jim Blandy
- Stephane Bortzmeyer
- Horst von Brand
- Frank Braun
- Rodney Brown
- Sidney Cadot
- Bradford Castalia
- Robert Clark
- Jonathan Corbet
- Ralph Doncaster
- Richard Emberson
- Levente Farkas
- Graham Fawcett
- Mark Fernyhough
- Robert A. French
- Jörgen Freyh
- Mark K. Gardner
- Charles-Antoine Gauthier
- Yung Shing Gene
- David Gilbert
- Simon Gornall
- Fred Gray
- John Griffin
- Patrik Hagglund
- Phil Hargett
- Amancio Hasty
- Takafumi Hayashi
- Bryan W. Headley
- Kevin B. Hendricks
- Joep Jansen
- Christian Joensson
- Michel Kern
- David Kidd
- Tobias Kuipers
- Anand Krishnaswamy
- A. O. V. Le Blanc
- llewelly
- Damon Love
- Brad Lucier

- Matthias Klose
- Martin Knoblauch
- Rick Lutowski
- Jesse Macnish
- Stefan Morrell
- Anon A. Mous
- Matthias Mueller
- Pekka Nikander
- Rick Niles
- Jon Olson
- Magnus Persson
- Chris Pollard
- Richard Polton
- Derk Reefman
- David Rees
- Paul Reilly
- Tom Reilly
- Torsten Rueger
- Danny Sadinoff
- Marc Schifer
- Erik Schnetter
- Wayne K. Schroll
- David Schuler
- Vin Shelton
- Tim Souder
- Adam Sulmicki
- Bill Thorson
- George Talbot
- Pedro A. M. Vazquez
- Gregory Warnes
- Ian Watson
- David E. Young
- And many others

And finally we'd like to thank everyone who uses the compiler, provides feedback and generally reminds us why we're doing this work in the first place.

Option Index

GCC's command line options are indexed here without any initial '-' or '--'. Where an option has both positive and negative forms (such as '-f*option*' and '-fno-*option*'), relevant entries in the manual are indexed under the most appropriate form; it may sometimes be useful to look up both forms.

F

`fltrans` 630
`fltrans-output-list` 630
`fresolution` 630
`fwpa` 630

M

`msoft-float` 12

Concept Index

!

'!' in constraint 315

#

'#' in constraint 316
in template 303
#pragma 579

%

'%' in constraint 316
% in GTY option 604
'%' in template 303

&

'&' in constraint 315

(

(nil) 224

*

'*' in constraint 316
* in template 304

+

'+' in constraint 315

-

'-fsection-anchors' 229, 505

/

'/c' in RTL dump 233
'/f' in RTL dump 233
'/i' in RTL dump 234
'/j' in RTL dump 234
'/s' in RTL dump 234
'/u' in RTL dump 234
'/v' in RTL dump 235

<

'<' in constraint 311

=

'=' in constraint 315

>

'>' in constraint 311

?

'?' in constraint 315

_

__absvdi2 11
__absvsi2 11
__addda3 22
__adddf3 12
__adddq3 22
__addha3 22
__addhq3 22
__addqq3 22
__addsa3 22
__addsf3 12
__addsq3 22
__addta3 22
__addtf3 12
__adduda3 23
__addudq3 22
__adduha3 22
__adduhq3 22
__adduqq3 22
__addusa3 23
__addusq3 22
__adduta3 23
__addvdi3 11
__addvsi3 11
__addxf3 12
__ashlda3 28
__ashldi3 9
__ashldq3 28
__ashlha3 28
__ashlhq3 28
__ashlqq3 28
__ashlsa3 28
__ashlsi3 9
__ashlsq3 28
__ashlta3 28
__ashlti3 9
__ashluda3 28
__ashludq3 28
__ashluha3 28
__ashluhq3 28
__ashluqq3 28
__ashlusa3 28
__ashlusq3 28
__ashluta3 28
__ashrda3 29
__ashrdi3 9

__ashrdq3 ... 29
__ashrha3 ... 29
__ashrhq3 ... 29
__ashrqq3 ... 29
__ashrsa3 ... 29
__ashrsi3 ... 9
__ashrsq3 ... 29
__ashrta3 ... 29
__ashrti3 ... 9
__bid_adddd3 ... 17
__bid_addsd3 ... 17
__bid_addtd3 ... 17
__bid_divdd3 ... 17
__bid_divsd3 ... 17
__bid_divtd3 ... 17
__bid_eqdd2 ... 21
__bid_eqsd2 ... 21
__bid_eqtd2 ... 21
__bid_extendddtd2 ... 18
__bid_extendddtf ... 18
__bid_extendddxf ... 18
__bid_extenddfdd ... 19
__bid_extenddftd ... 18
__bid_extendsddd2 ... 17
__bid_extendsddf ... 18
__bid_extendsdtd2 ... 17
__bid_extendsdtf ... 18
__bid_extendsdxf ... 18
__bid_extendsfdd ... 18
__bid_extendsfsd ... 19
__bid_extendsftd ... 18
__bid_extendtftd ... 19
__bid_extendxftd ... 18
__bid_fixdddi ... 19
__bid_fixddsi ... 19
__bid_fixsddi ... 19
__bid_fixsdsi ... 19
__bid_fixtddi ... 19
__bid_fixtdsi ... 19
__bid_fixunsdddi ... 19
__bid_fixunsddsi ... 19
__bid_fixunssddi ... 19
__bid_fixunssdsi ... 19
__bid_fixunstddi ... 19
__bid_fixunstdsi ... 19
__bid_floatdidd ... 20
__bid_floatdisd ... 20
__bid_floatditd ... 20
__bid_floatsidd ... 20
__bid_floatsisd ... 20
__bid_floatsitd ... 20
__bid_floatunsdidd ... 20
__bid_floatunsdisd ... 20
__bid_floatunsditd ... 20
__bid_floatunssidd ... 20
__bid_floatunssisd ... 20
__bid_floatunssitd ... 20
__bid_gedd2 ... 21
__bid_gesd2 ... 21
__bid_getd2 ... 21
__bid_gtdd2 ... 22
__bid_gtsd2 ... 22
__bid_gttd2 ... 22
__bid_ledd2 ... 21
__bid_lesd2 ... 21
__bid_letd2 ... 21
__bid_ltdd2 ... 21
__bid_ltsd2 ... 21
__bid_lttd2 ... 21
__bid_muldd3 ... 17
__bid_mulsd3 ... 17
__bid_multd3 ... 17
__bid_nedd2 ... 21
__bid_negdd2 ... 17
__bid_negsd2 ... 17
__bid_negtd2 ... 17
__bid_nesd2 ... 21
__bid_netd2 ... 21
__bid_subdd3 ... 17
__bid_subsd3 ... 17
__bid_subtd3 ... 17
__bid_truncdddf ... 19
__bid_truncddsd2 ... 18
__bid_truncddsf ... 18
__bid_truncdfsd ... 18
__bid_truncsdsf ... 19
__bid_trunctddd2 ... 18
__bid_trunctddf ... 18
__bid_trunctdsd2 ... 18
__bid_trunctdsf ... 18
__bid_trunctdtf ... 19
__bid_trunctdxf ... 18
__bid_trunctfdd ... 18
__bid_trunctfsd ... 18
__bid_truncxfdd ... 18
__bid_truncxfsd ... 18
__bid_unorddd2 ... 20
__bid_unordsd2 ... 20
__bid_unordtd2 ... 20
__bswapdi2 ... 12
__bswapsi2 ... 12
__builtin_classify_type ... 494
__builtin_next_arg ... 494
__builtin_saveregs ... 493
__clear_cache ... 57
__clzdi2 ... 11
__clzsi2 ... 11
__clzti2 ... 11
__cmpda2 ... 30
__cmpdf2 ... 15
__cmpdi2 ... 10
__cmpdq2 ... 30
__cmpha2 ... 30
__cmphq2 ... 30
__cmpqq2 ... 30
__cmpsa2 ... 30

__cmpsf2 ... 15
__cmpsq2 ... 30
__cmpta2 ... 30
__cmptf2 ... 15
__cmpti2 ... 10
__cmpuda2 ... 30
__cmpudq2 ... 30
__cmpuha2 ... 30
__cmpuhq2 ... 30
__cmpuqq2 ... 30
__cmpusa2 ... 30
__cmpusq2 ... 30
__cmputa2 ... 30
__CTOR_LIST__ ... 543
__ctzdi2 ... 11
__ctzsi2 ... 11
__ctzti2 ... 11
__divda3 ... 26
__divdc3 ... 16
__divdf3 ... 12
__divdi3 ... 9
__divdq3 ... 26
__divha3 ... 26
__divhq3 ... 26
__divqq3 ... 26
__divsa3 ... 26
__divsc3 ... 16
__divsf3 ... 12
__divsi3 ... 9
__divsq3 ... 26
__divta3 ... 26
__divtc3 ... 16
__divtf3 ... 12
__divti3 ... 9
__divxc3 ... 16
__divxf3 ... 12
__dpd_adddd3 ... 17
__dpd_addsd3 ... 17
__dpd_addtd3 ... 17
__dpd_divdd3 ... 17
__dpd_divsd3 ... 17
__dpd_divtd3 ... 17
__dpd_eqdd2 ... 21
__dpd_eqsd2 ... 21
__dpd_eqtd2 ... 21
__dpd_extendddtd2 ... 17
__dpd_extendddtf ... 18
__dpd_extendddxf ... 18
__dpd_extenddfdd ... 19
__dpd_extenddftd ... 18
__dpd_extendsddd2 ... 17
__dpd_extendsddf ... 18
__dpd_extendsdtd2 ... 17
__dpd_extendsdtf ... 18
__dpd_extendsdxf ... 18
__dpd_extendsfdd ... 18
__dpd_extendsfsd ... 19
__dpd_extendsftd ... 18
__dpd_extendtftd ... 19
__dpd_extendxftd ... 18
__dpd_fixdddi ... 19
__dpd_fixddsi ... 19
__dpd_fixsddi ... 19
__dpd_fixsdsi ... 19
__dpd_fixtddi ... 19
__dpd_fixtdsi ... 19
__dpd_fixunsdddi ... 19
__dpd_fixunsddsi ... 19
__dpd_fixunssddi ... 19
__dpd_fixunssdsi ... 19
__dpd_fixunstddi ... 19
__dpd_fixunstdsi ... 19
__dpd_floatdidd ... 20
__dpd_floatdisd ... 20
__dpd_floatditd ... 20
__dpd_floatsidd ... 20
__dpd_floatsisd ... 20
__dpd_floatsitd ... 20
__dpd_floatunsdidd ... 20
__dpd_floatunsdisd ... 20
__dpd_floatunsditd ... 20
__dpd_floatunssidd ... 20
__dpd_floatunssisd ... 20
__dpd_floatunssitd ... 20
__dpd_gedd2 ... 21
__dpd_gesd2 ... 21
__dpd_getd2 ... 21
__dpd_gtdd2 ... 22
__dpd_gtsd2 ... 22
__dpd_gttd2 ... 22
__dpd_ledd2 ... 21
__dpd_lesd2 ... 21
__dpd_letd2 ... 21
__dpd_ltdd2 ... 21
__dpd_ltsd2 ... 21
__dpd_lttd2 ... 21
__dpd_muldd3 ... 17
__dpd_mulsd3 ... 17
__dpd_multd3 ... 17
__dpd_nedd2 ... 21
__dpd_negdd2 ... 17
__dpd_negsd2 ... 17
__dpd_negtd2 ... 17
__dpd_nesd2 ... 21
__dpd_netd2 ... 21
__dpd_subdd3 ... 17
__dpd_subsd3 ... 17
__dpd_subtd3 ... 17
__dpd_truncdddf ... 19
__dpd_truncddsd2 ... 18
__dpd_truncddsf ... 18
__dpd_truncdfsd ... 18
__dpd_truncsdsf ... 19
__dpd_trunctddd2 ... 18
__dpd_trunctddf ... 18
__dpd_trunctdsd2 ... 18

__dpd_trunctdsf 18
__dpd_trunctdtf 19
__dpd_trunctdxf 18
__dpd_trunctfdd 18
__dpd_trunctfsd 18
__dpd_truncxfdd 18
__dpd_truncxfsd 18
__dpd_unorddd2 20
__dpd_unordsd2 20
__dpd_unordtd2 20
__DTOR_LIST__ 543
__eqdf2 15
__eqsf2 15
__eqtf2 15
__extenddftf2 13
__extenddfxf2 13
__extendsfdf2 13
__extendsftf2 13
__extendsfxf2 13
__ffsdi2 11
__ffsti2 11
__fixdfdi 13
__fixdfsi 13
__fixdfti 13
__fixsfdi 13
__fixsfsi 13
__fixsfti 13
__fixtfdi 13
__fixtfsi 13
__fixtfti 13
__fixunsdfdi 13
__fixunsdfsi 13
__fixunsdfti 14
__fixunssfdi 13
__fixunssfsi 13
__fixunssfti 14
__fixunstfdi 13
__fixunstfsi 13
__fixunstfti 14
__fixunsxfdi 13
__fixunsxfsi 13
__fixunsxfti 14
__fixxfdi 13
__fixxfsi 13
__fixxfti 13
__floatdidf 14
__floatdisf 14
__floatditf 14
__floatdixf 14
__floatsidf 14
__floatsisf 14
__floatsitf 14
__floatsixf 14
__floattidf 14
__floattisf 14
__floattitf 14
__floattixf 14
__floatundidf 14
__floatundisf 14
__floatunditf 14
__floatundixf 14
__floatunsidf 14
__floatunsisf 14
__floatunsitf 14
__floatunsixf 14
__floatuntidf 14
__floatuntisf 14
__floatuntitf 14
__floatuntixf 14
__fractdadf 34
__fractdadi 34
__fractdadq 33
__fractdaha2 33
__fractdahi 33
__fractdahq 33
__fractdaqi 33
__fractdaqq 33
__fractdasa2 33
__fractdasf 34
__fractdasi 34
__fractdasq 33
__fractdata2 33
__fractdati 34
__fractdauda 33
__fractdaudq 33
__fractdauha 33
__fractdauhq 33
__fractdauqq 33
__fractdausa 33
__fractdausq 33
__fractdauta 33
__fractdfda 41
__fractdfdq 41
__fractdfha 41
__fractdfhq 41
__fractdfqq 41
__fractdfsa 41
__fractdfsq 41
__fractdfta 41
__fractdfuda 41
__fractdfudq 41
__fractdfuha 41
__fractdfuhq 41
__fractdfuqq 41
__fractdfusa 41
__fractdfusq 41
__fractdfuta 41
__fractdida 40
__fractdidq 40
__fractdiha 40
__fractdihq 40
__fractdiqq 40
__fractdisa 40
__fractdisq 40
__fractdita 40
__fractdiuda 40

__fractdiudq 40
__fractdiuha 40
__fractdiuhq 40
__fractdiuqq 40
__fractdiusa 40
__fractdiusq 40
__fractdiuta 40
__fractdqda 32
__fractdqdf 32
__fractdqdi 32
__fractdqha 32
__fractdqhi 32
__fractdqhq2 32
__fractdqqi 32
__fractdqqq2 32
__fractdqsa 32
__fractdqsf 32
__fractdqsi 32
__fractdqsq2 32
__fractdqta 32
__fractdqti 32
__fractdquda 32
__fractdqudq 32
__fractdquha 32
__fractdquhq 32
__fractdquqq 32
__fractdqusa 32
__fractdqusq 32
__fractdquta 32
__fracthada2 32
__fracthadf 33
__fracthadi 33
__fracthadq 32
__fracthahi 33
__fracthahq 32
__fracthaqi 33
__fracthaqq 32
__fracthasa2 32
__fracthasf 33
__fracthasi 33
__fracthasq 32
__fracthata2 32
__fracthati 33
__fracthauda 32
__fracthaudq 32
__fracthauha 32
__fracthauhq 32
__fracthauqq 32
__fracthausa 32
__fracthausq 32
__fracthauta 33
__fracthida 39
__fracthidq 39
__fracthiha 39
__fracthihq 39
__fracthiqq 39
__fracthisa 39
__fracthisq 39
__fracthita 39
__fracthiuda 39
__fracthiudq 39
__fracthiuha 39
__fracthiuhq 39
__fracthiuqq 39
__fracthiusa 39
__fracthiusq 39
__fracthiuta 39
__fracthqda 31
__fracthqdf 31
__fracthqdi 31
__fracthqdq2 31
__fracthqha 31
__fracthqhi 31
__fracthqqi 31
__fracthqqq2 31
__fracthqsa 31
__fracthqsf 31
__fracthqsi 31
__fracthqsq2 31
__fracthqta 31
__fracthqti 31
__fracthquda 31
__fracthqudq 31
__fracthquha 31
__fracthquhq 31
__fracthquqq 31
__fracthqusa 31
__fracthqusq 31
__fracthquta 31
__fractqida 39
__fractqidq 39
__fractqiha 39
__fractqihq 39
__fractqiqq 39
__fractqisa 39
__fractqisq 39
__fractqita 39
__fractqiuda 39
__fractqiudq 39
__fractqiuha 39
__fractqiuhq 39
__fractqiuqq 39
__fractqiusa 39
__fractqiusq 39
__fractqiuta 39
__fractqqda 30
__fractqqdf 31
__fractqqdi 31
__fractqqdq2 30
__fractqqha 30
__fractqqhi 31
__fractqqhq2 30
__fractqqqi 31
__fractqqsa 30
__fractqqsf 31
__fractqqsi 31

__fractqqsq2 30
__fractqqta 30
__fractqqti 31
__fractqquda 31
__fractqqudq 31
__fractqquha 31
__fractqquhq 30
__fractqquqq 30
__fractqqusa 31
__fractqqusq 30
__fractqquta 31
__fractsada2 33
__fractsadf 33
__fractsadi 33
__fractsadq 33
__fractsaha2 33
__fractsahi 33
__fractsahq 33
__fractsaqi 33
__fractsaqq 33
__fractsasf 33
__fractsasi 33
__fractsasq 33
__fractsata2 33
__fractsati 33
__fractsauda 33
__fractsaudq 33
__fractsauha 33
__fractsauhq 33
__fractsauqq 33
__fractsausa 33
__fractsausq 33
__fractsauta 33
__fractsfda 40
__fractsfdq 40
__fractsfha 40
__fractsfhq 40
__fractsfqq 40
__fractsfsa 40
__fractsfsq 40
__fractsfta 40
__fractsfuda 41
__fractsfudq 41
__fractsfuha 41
__fractsfuhq 41
__fractsfuqq 41
__fractsfusa 41
__fractsfusq 41
__fractsfuta 41
__fractsida 39
__fractsidq 39
__fractsiha 39
__fractsihq 39
__fractsiqq 39
__fractsisa 39
__fractsisq 39
__fractsita 39
__fractsiuda 40
__fractsiudq 40
__fractsiuha 40
__fractsiuhq 40
__fractsiuqq 39
__fractsiusa 40
__fractsiusq 40
__fractsiuta 40
__fractsqda 31
__fractsqdf 32
__fractsqdi 32
__fractsqdq2 31
__fractsqha 31
__fractsqhi 32
__fractsqhq2 31
__fractsqqi 32
__fractsqqq2 31
__fractsqsa 31
__fractsqsf 32
__fractsqsi 32
__fractsqta 31
__fractsqti 32
__fractsquda 32
__fractsqudq 31
__fractsquha 31
__fractsquhq 31
__fractsquqq 31
__fractsqusa 31
__fractsqusq 31
__fractsquta 32
__fracttada2 34
__fracttadf 34
__fracttadi 34
__fracttadq 34
__fracttaha2 34
__fracttahi 34
__fracttahq 34
__fracttaqi 34
__fracttaqq 34
__fracttasa2 34
__fracttasf 34
__fracttasi 34
__fracttasq 34
__fracttati 34
__fracttauda 34
__fracttaudq 34
__fracttauha 34
__fracttauhq 34
__fracttauqq 34
__fracttausa 34
__fracttausq 34
__fracttauta 34
__fracttida 40
__fracttidq 40
__fracttiha 40
__fracttihq 40
__fracttiqq 40
__fracttisa 40
__fracttisq 40

__fracttita 40
__fracttiuda 40
__fracttiudq 40
__fracttiuha 40
__fracttiuhq 40
__fracttiuqq 40
__fracttiusa 40
__fracttiusq 40
__fracttiuta 40
__fractudada 38
__fractudadf 38
__fractudadi 38
__fractudadq 38
__fractudaha 38
__fractudahi 38
__fractudahq 37
__fractudaqi 38
__fractudaqq 37
__fractudasa 38
__fractudasf 38
__fractudasi 38
__fractudasq 38
__fractudata 38
__fractudati 38
__fractudaudq 38
__fractudauha2 38
__fractudauhq 38
__fractudauqq 38
__fractudausa2 38
__fractudausq 38
__fractudauta2 38
__fractudqda 36
__fractudqdf 36
__fractudqdi 36
__fractudqdq 36
__fractudqha 36
__fractudqhi 36
__fractudqhq 36
__fractudqqi 36
__fractudqqq 36
__fractudqsa 36
__fractudqsf 36
__fractudqsi 36
__fractudqsq 36
__fractudqta 36
__fractudqti 36
__fractudquda 36
__fractudquha 36
__fractudquhq2 36
__fractudquqq2 36
__fractudqusa 36
__fractudqusq2 36
__fractudquta 36
__fractuhada 37
__fractuhadf 37
__fractuhadi 37
__fractuhadq 36
__fractuhaha 36
__fractuhahi 37
__fractuhahq 36
__fractuhaqi 37
__fractuhaqq 36
__fractuhasa 36
__fractuhasf 37
__fractuhasi 37
__fractuhasq 36
__fractuhata 37
__fractuhati 37
__fractuhauda2 37
__fractuhaudq 37
__fractuhauhq 37
__fractuhauqq 37
__fractuhausa2 37
__fractuhausq 37
__fractuhauta2 37
__fractuhqda 35
__fractuhqdf 35
__fractuhqdi 35
__fractuhqdq 35
__fractuhqha 35
__fractuhqhi 35
__fractuhqhq 35
__fractuhqqi 35
__fractuhqqq 35
__fractuhqsa 35
__fractuhqsf 35
__fractuhqsi 35
__fractuhqsq 35
__fractuhqta 35
__fractuhqti 35
__fractuhquda 35
__fractuhqudq2 35
__fractuhquha 35
__fractuhquqq2 35
__fractuhqusa 35
__fractuhqusq2 35
__fractuhquta 35
__fractunsdadi 51
__fractunsdahi 51
__fractunsdaqi 51
__fractunsdasi 51
__fractunsdati 51
__fractunsdida 53
__fractunsdidq 53
__fractunsdiha 53
__fractunsdihq 53
__fractunsdiqq 53
__fractunsdisa 53
__fractunsdisq 53
__fractunsdita 53
__fractunsdiuda 53
__fractunsdiudq 53
__fractunsdiuha 53
__fractunsdiuhq 53
__fractunsdiuqq 53
__fractunsdiusa 53

__fractunsdiusq 53
__fractunsdiuta 53
__fractunsdqdi 50
__fractunsdqhi 50
__fractunsdqqi 50
__fractunsdqsi 50
__fractunsdqti 50
__fractunshadi 51
__fractunshahi 51
__fractunshaqi 50
__fractunshasi 51
__fractunshati 51
__fractunshida 52
__fractunshidq 52
__fractunshiha 52
__fractunshihq 52
__fractunshiqq 52
__fractunshisa 52
__fractunshisq 52
__fractunshita 53
__fractunshiuda 53
__fractunshiudq 53
__fractunshiuha 53
__fractunshiuhq 53
__fractunshiuqq 53
__fractunshiusa 53
__fractunshiusq 53
__fractunshiuta 53
__fractunshqdi 50
__fractunshqhi 50
__fractunshqqi 50
__fractunshqsi 50
__fractunshqti 50
__fractunsqida 52
__fractunsqidq 52
__fractunsqiha 52
__fractunsqihq 52
__fractunsqiqq 52
__fractunsqisa 52
__fractunsqisq 52
__fractunsqita 52
__fractunsqiuda 52
__fractunsqiudq 52
__fractunsqiuha 52
__fractunsqiuhq 52
__fractunsqiuqq 52
__fractunsqiusa 52
__fractunsqiusq 52
__fractunsqiuta 52
__fractunsqqdi 50
__fractunsqqhi 50
__fractunsqqqi 50
__fractunsqqsi 50
__fractunsqqti 50
__fractunssadi 51
__fractunssahi 51
__fractunssaqi 51
__fractunssasi 51
__fractunssati 51
__fractunssida 53
__fractunssidq 53
__fractunssiha 53
__fractunssihq 53
__fractunssiqq 53
__fractunssisa 53
__fractunssisq 53
__fractunssita 53
__fractunssiuda 53
__fractunssiudq 53
__fractunssiuha 53
__fractunssiuhq 53
__fractunssiuqq 53
__fractunssiusa 53
__fractunssiusq 53
__fractunssiuta 53
__fractunssqdi 50
__fractunssqhi 50
__fractunssqqi 50
__fractunssqsi 50
__fractunssqti 50
__fractunstadi 51
__fractunstahi 51
__fractunstaqi 51
__fractunstasi 51
__fractunstati 51
__fractunstida 54
__fractunstidq 54
__fractunstiha 54
__fractunstihq 54
__fractunstiqq 54
__fractunstisa 54
__fractunstisq 54
__fractunstita 54
__fractunstiuda 54
__fractunstiudq 54
__fractunstiuha 54
__fractunstiuhq 54
__fractunstiuqq 54
__fractunstiusa 54
__fractunstiusq 54
__fractunstiuta 54
__fractunsudadi 52
__fractunsudahi 52
__fractunsudaqi 52
__fractunsudasi 52
__fractunsudati 52
__fractunsudqdi 51
__fractunsudqhi 51
__fractunsudqqi 51
__fractunsudqsi 51
__fractunsudqti 51
__fractunsuhadi 51
__fractunsuhahi 51
__fractunsuhaqi 51
__fractunsuhasi 51
__fractunsuhati 52

__fractunsuhqdi ... 51
__fractunsuhqhi ... 51
__fractunsuhqqi ... 51
__fractunsuhqsi ... 51
__fractunsuhqti ... 51
__fractunsuqqdi ... 51
__fractunsuqqhi ... 51
__fractunsuqqqi ... 51
__fractunsuqqsi ... 51
__fractunsuqqti ... 51
__fractunsusadi ... 52
__fractunsusahi ... 52
__fractunsusaqi ... 52
__fractunsusasi ... 52
__fractunsusati ... 52
__fractunsusqdi ... 51
__fractunsusqhi ... 51
__fractunsusqqi ... 51
__fractunsusqsi ... 51
__fractunsusqti ... 51
__fractunsutadi ... 52
__fractunsutahi ... 52
__fractunsutaqi ... 52
__fractunsutasi ... 52
__fractunsutati ... 52
__fractuqqda ... 34
__fractuqqdf ... 35
__fractuqqdi ... 35
__fractuqqdq ... 34
__fractuqqha ... 34
__fractuqqhi ... 35
__fractuqqhq ... 34
__fractuqqqi ... 35
__fractuqqqq ... 34
__fractuqqsa ... 34
__fractuqqsf ... 35
__fractuqqsi ... 35
__fractuqqsq ... 34
__fractuqqta ... 34
__fractuqqti ... 35
__fractuqquda ... 34
__fractuqqudq2 ... 34
__fractuqquha ... 34
__fractuqquhq2 ... 34
__fractuqqusa ... 34
__fractuqqusq2 ... 34
__fractuqquta ... 35
__fractusada ... 37
__fractusadf ... 37
__fractusadi ... 37
__fractusadq ... 37
__fractusaha ... 37
__fractusahi ... 37
__fractusahq ... 37
__fractusaqi ... 37
__fractusaqq ... 37
__fractusasa ... 37
__fractusasf ... 37
__fractusasi ... 37
__fractusasq ... 37
__fractusata ... 37
__fractusati ... 37
__fractusauda2 ... 37
__fractusaudq ... 37
__fractusauha2 ... 37
__fractusauhq ... 37
__fractusauqq ... 37
__fractusausq ... 37
__fractusauta2 ... 37
__fractusqda ... 35
__fractusqdf ... 36
__fractusqdi ... 36
__fractusqdq ... 35
__fractusqha ... 35
__fractusqhi ... 36
__fractusqhq ... 35
__fractusqqi ... 36
__fractusqqq ... 35
__fractusqsa ... 35
__fractusqsf ... 36
__fractusqsi ... 36
__fractusqsq ... 35
__fractusqta ... 35
__fractusqti ... 36
__fractusquda ... 36
__fractusqudq2 ... 35
__fractusquha ... 36
__fractusquhq2 ... 35
__fractusquqq2 ... 35
__fractusqusa ... 36
__fractusquta ... 36
__fractutada ... 38
__fractutadf ... 39
__fractutadi ... 39
__fractutadq ... 38
__fractutaha ... 38
__fractutahi ... 39
__fractutahq ... 38
__fractutaqi ... 38
__fractutaqq ... 38
__fractutasa ... 38
__fractutasf ... 39
__fractutasi ... 39
__fractutasq ... 38
__fractutata ... 38
__fractutati ... 39
__fractutauda2 ... 38
__fractutaudq ... 38
__fractutauha2 ... 38
__fractutauhq ... 38
__fractutauqq ... 38
__fractutausa2 ... 38
__fractutausq ... 38
__gedf2 ... 15
__gesf2 ... 15
__getf2 ... 15

__gtdf2 ... 16
__gtsf2 ... 16
__gttf2 ... 16
__ledf2 ... 16
__lesf2 ... 16
__letf2 ... 16
__lshrdi3 ... 9
__lshrsi3 ... 9
__lshrti3 ... 9
__lshruda3 ... 29
__lshrudq3 ... 29
__lshruha3 ... 29
__lshruhq3 ... 29
__lshruqq3 ... 29
__lshrusa3 ... 29
__lshrusq3 ... 29
__lshruta3 ... 29
__ltdf2 ... 15
__ltsf2 ... 15
__lttf2 ... 15
__main ... 599
__moddi3 ... 10
__modsi3 ... 10
__modti3 ... 10
__morestack_current_segment ... 58
__morestack_initial_sp ... 58
__morestack_segments ... 58
__mulda3 ... 25
__muldc3 ... 16
__muldf3 ... 12
__muldi3 ... 10
__muldq3 ... 25
__mulha3 ... 25
__mulhq3 ... 25
__mulqq3 ... 25
__mulsa3 ... 25
__mulsc3 ... 16
__mulsf3 ... 12
__mulsi3 ... 10
__mulsq3 ... 25
__multa3 ... 25
__multc3 ... 16
__multf3 ... 12
__multi3 ... 10
__muluda3 ... 25
__muludq3 ... 25
__muluha3 ... 25
__muluhq3 ... 25
__muluqq3 ... 25
__mulusa3 ... 25
__mulusq3 ... 25
__muluta3 ... 25
__mulvdi3 ... 11
__mulvsi3 ... 11
__mulxc3 ... 16
__mulxf3 ... 12
__nedf2 ... 15
__negda2 ... 27
__negdf2 ... 12
__negdi2 ... 10
__negdq2 ... 27
__negha2 ... 27
__neghq2 ... 27
__negqq2 ... 27
__negsa2 ... 27
__negsf2 ... 12
__negsq2 ... 27
__negta2 ... 27
__negtf2 ... 12
__negti2 ... 10
__neguda2 ... 27
__negudq2 ... 27
__neguha2 ... 27
__neguhq2 ... 27
__neguqq2 ... 27
__negusa2 ... 27
__negusq2 ... 27
__neguta2 ... 27
__negvdi2 ... 11
__negvsi2 ... 11
__negxf2 ... 12
__nesf2 ... 15
__netf2 ... 15
__paritydi2 ... 11
__paritysi2 ... 11
__parityti2 ... 11
__popcountdi2 ... 12
__popcountsi2 ... 12
__popcountti2 ... 12
__powidf2 ... 16
__powisf2 ... 16
__powitf2 ... 16
__powixf2 ... 16
__satfractdadq ... 43
__satfractdaha2 ... 43
__satfractdahq ... 43
__satfractdaqq ... 43
__satfractdasa2 ... 43
__satfractdasq ... 43
__satfractdata2 ... 43
__satfractdauda ... 43
__satfractdaudq ... 43
__satfractdauha ... 43
__satfractdauhq ... 43
__satfractdauqq ... 43
__satfractdausa ... 43
__satfractdausq ... 43
__satfractdauta ... 43
__satfractdfda ... 50
__satfractdfdq ... 50
__satfractdfha ... 50
__satfractdfhq ... 50
__satfractdfqq ... 50
__satfractdfsa ... 50
__satfractdfsq ... 50
__satfractdfta ... 50

__satfractdfuda 50
__satfractdfudq 50
__satfractdfuha 50
__satfractdfuhq 50
__satfractdfuqq 50
__satfractdfusa 50
__satfractdfusq 50
__satfractdfuta 50
__satfractdida 49
__satfractdidq 49
__satfractdiha 49
__satfractdihq 49
__satfractdiqq 49
__satfractdisa 49
__satfractdisq 49
__satfractdita 49
__satfractdiuda 49
__satfractdiudq 49
__satfractdiuha 49
__satfractdiuhq 49
__satfractdiuqq 49
__satfractdiusa 49
__satfractdiusq 49
__satfractdiuta 49
__satfractdqda 42
__satfractdqha 42
__satfractdqhq2 42
__satfractdqqq2 42
__satfractdqsa 42
__satfractdqsq2 42
__satfractdqta 42
__satfractdquda 42
__satfractdqudq 42
__satfractdquha 42
__satfractdquhq 42
__satfractdquqq 42
__satfractdqusa 42
__satfractdqusq 42
__satfractdquta 42
__satfracthada2 43
__satfracthadq 43
__satfracthahq 42
__satfracthaqq 42
__satfracthasa2 43
__satfracthasq 42
__satfracthata2 43
__satfracthauda 43
__satfracthaudq 43
__satfracthauha 43
__satfracthauhq 43
__satfracthauqq 43
__satfracthausa 43
__satfracthausq 43
__satfracthauta 43
__satfracthida 48
__satfracthidq 48
__satfracthiha 48
__satfracthihq 48
__satfracthiqq 48
__satfracthisa 48
__satfracthisq 48
__satfracthita 48
__satfracthiuda 48
__satfracthiudq 48
__satfracthiuha 48
__satfracthiuhq 48
__satfracthiuqq 48
__satfracthiusa 48
__satfracthiusq 48
__satfracthiuta 48
__satfracthqda 42
__satfracthqdq2 41
__satfracthqha 42
__satfracthqqq2 41
__satfracthqsa 42
__satfracthqsq2 41
__satfracthqta 42
__satfracthquda 42
__satfracthqudq 42
__satfracthquha 42
__satfracthquhq 42
__satfracthquqq 42
__satfracthqusa 42
__satfracthqusq 42
__satfracthquta 42
__satfractqida 48
__satfractqidq 48
__satfractqiha 48
__satfractqihq 48
__satfractqiqq 48
__satfractqisa 48
__satfractqisq 48
__satfractqita 48
__satfractqiuda 48
__satfractqiudq 48
__satfractqiuha 48
__satfractqiuhq 48
__satfractqiuqq 48
__satfractqiusa 48
__satfractqiusq 48
__satfractqiuta 48
__satfractqqda 41
__satfractqqdq2 41
__satfractqqha 41
__satfractqqhq2 41
__satfractqqsa 41
__satfractqqsq2 41
__satfractqqta 41
__satfractqquda 41
__satfractqqudq 41
__satfractqquha 41
__satfractqquhq 41
__satfractqquqq 41
__satfractqqusa 41
__satfractqqusq 41
__satfractqquta 41

__satfractsada2 43
__satfractsadq 43
__satfractsaha2 43
__satfractsahq 43
__satfractsaqq 43
__satfractsasq 43
__satfractsata2 43
__satfractsauda 43
__satfractsaudq 43
__satfractsauha 43
__satfractsauhq 43
__satfractsauqq 43
__satfractsausa 43
__satfractsausq 43
__satfractsauta 43
__satfractsfda 49
__satfractsfdq 49
__satfractsfha 49
__satfractsfhq 49
__satfractsfqq 49
__satfractsfsa 49
__satfractsfsq 49
__satfractsfta 49
__satfractsfuda 50
__satfractsfudq 50
__satfractsfuha 50
__satfractsfuhq 50
__satfractsfuqq 49
__satfractsfusa 50
__satfractsfusq 50
__satfractsfuta 50
__satfractsida 48
__satfractsidq 48
__satfractsiha 48
__satfractsihq 48
__satfractsiqq 48
__satfractsisa 48
__satfractsisq 48
__satfractsita 48
__satfractsiuda 49
__satfractsiudq 49
__satfractsiuha 49
__satfractsiuhq 48
__satfractsiuqq 48
__satfractsiusa 49
__satfractsiusq 49
__satfractsiuta 49
__satfractsqda 42
__satfractsqdq2 42
__satfractsqha 42
__satfractsqhq2 42
__satfractsqqq2 42
__satfractsqsa 42
__satfractsqta 42
__satfractsquda 42
__satfractsqudq 42
__satfractsquha 42
__satfractsquhq 42
__satfractsquqq 42
__satfractsqusa 42
__satfractsqusq 42
__satfractsquta 42
__satfracttada2 44
__satfracttadq 44
__satfracttaha2 44
__satfracttahq 44
__satfracttaqq 43
__satfracttasa2 44
__satfracttasq 44
__satfracttauda 44
__satfracttaudq 44
__satfracttauha 44
__satfracttauhq 44
__satfracttauqq 44
__satfracttausa 44
__satfracttausq 44
__satfracttauta 44
__satfracttida 49
__satfracttidq 49
__satfracttiha 49
__satfracttihq 49
__satfracttiqq 49
__satfracttisa 49
__satfracttisq 49
__satfracttita 49
__satfracttiuda 49
__satfracttiudq 49
__satfracttiuha 49
__satfracttiuhq 49
__satfracttiuqq 49
__satfracttiusa 49
__satfracttiusq 49
__satfracttiuta 49
__satfractudada 47
__satfractudadq 47
__satfractudaha 47
__satfractudahq 47
__satfractudaqq 47
__satfractudasa 47
__satfractudasq 47
__satfractudata 47
__satfractudaudq 47
__satfractudauha2 47
__satfractudauhq 47
__satfractudauqq 47
__satfractudausa2 47
__satfractudausq 47
__satfractudauta2 47
__satfractudqda 45
__satfractudqdq 45
__satfractudqha 45
__satfractudqhq 45
__satfractudqqq 45
__satfractudqsa 45
__satfractudqsq 45
__satfractudqta 45

__satfractudquda 46
__satfractudquha 46
__satfractudquhq2 45
__satfractudquqq2 45
__satfractudqusa 46
__satfractudqusq2 45
__satfractudquta 46
__satfractuhada 46
__satfractuhadq 46
__satfractuhaha 46
__satfractuhahq 46
__satfractuhaqq 46
__satfractuhasa 46
__satfractuhasq 46
__satfractuhata 46
__satfractuhauda2 46
__satfractuhaudq 46
__satfractuhauhq 46
__satfractuhauqq 46
__satfractuhausa2 46
__satfractuhausq 46
__satfractuhauta2 46
__satfractuhqda 44
__satfractuhqdq 44
__satfractuhqha 44
__satfractuhqhq 44
__satfractuhqqq 44
__satfractuhqsa 44
__satfractuhqsq 44
__satfractuhqta 44
__satfractuhquda 45
__satfractuhqudq2 45
__satfractuhquha 45
__satfractuhquqq2 44
__satfractuhqusa 45
__satfractuhqusq2 45
__satfractuhquta 45
__satfractunsdida 56
__satfractunsdidq 55
__satfractunsdiha 56
__satfractunsdihq 55
__satfractunsdiqq 55
__satfractunsdisa 56
__satfractunsdisq 55
__satfractunsdita 56
__satfractunsdiuda 56
__satfractunsdiudq 56
__satfractunsdiuha 56
__satfractunsdiuhq 56
__satfractunsdiuqq 56
__satfractunsdiusa 56
__satfractunsdiusq 56
__satfractunsdiuta 56
__satfractunshida 55
__satfractunshidq 55
__satfractunshiha 55
__satfractunshihq 55
__satfractunshiqq 55
__satfractunshisa 55
__satfractunshisq 55
__satfractunshita 55
__satfractunshiuda 55
__satfractunshiudq 55
__satfractunshiuha 55
__satfractunshiuhq 55
__satfractunshiuqq 55
__satfractunshiusa 55
__satfractunshiusq 55
__satfractunshiuta 55
__satfractunsqida 54
__satfractunsqidq 54
__satfractunsqiha 54
__satfractunsqihq 54
__satfractunsqiqq 54
__satfractunsqisa 54
__satfractunsqisq 54
__satfractunsqita 54
__satfractunsqiuda 54
__satfractunsqiudq 54
__satfractunsqiuha 54
__satfractunsqiuhq 54
__satfractunsqiuqq 54
__satfractunsqiusa 54
__satfractunsqiusq 54
__satfractunsqiuta 54
__satfractunssida 55
__satfractunssidq 55
__satfractunssiha 55
__satfractunssihq 55
__satfractunssiqq 55
__satfractunssisa 55
__satfractunssisq 55
__satfractunssita 55
__satfractunssiuda 55
__satfractunssiudq 55
__satfractunssiuha 55
__satfractunssiuhq 55
__satfractunssiuqq 55
__satfractunssiusa 55
__satfractunssiusq 55
__satfractunssiuta 55
__satfractunstida 56
__satfractunstidq 56
__satfractunstiha 56
__satfractunstihq 56
__satfractunstiqq 56
__satfractunstisa 56
__satfractunstisq 56
__satfractunstita 56
__satfractunstiuda 56
__satfractunstiudq 56
__satfractunstiuha 56
__satfractunstiuhq 56
__satfractunstiuqq 56
__satfractunstiusa 56
__satfractunstiusq 56

__satfractunstiuta 56
__satfractuqqda 44
__satfractuqqdq 44
__satfractuqqha 44
__satfractuqqhq 44
__satfractuqqqq 44
__satfractuqqsa 44
__satfractuqqsq 44
__satfractuqqta 44
__satfractuqquda 44
__satfractuqqudq2 44
__satfractuqquha 44
__satfractuqquhq2 44
__satfractuqqusa 44
__satfractuqqusq2 44
__satfractuqquta 44
__satfractusada 46
__satfractusadq 46
__satfractusaha 46
__satfractusahq 46
__satfractusaqq 46
__satfractusasa 46
__satfractusasq 46
__satfractusata 46
__satfractusauda2 47
__satfractusaudq 46
__satfractusauha2 46
__satfractusauhq 46
__satfractusauqq 46
__satfractusausq 46
__satfractusauta2 47
__satfractusqda 45
__satfractusqdq 45
__satfractusqha 45
__satfractusqhq 45
__satfractusqqq 45
__satfractusqsa 45
__satfractusqsq 45
__satfractusqta 45
__satfractusquda 45
__satfractusqudq2 45
__satfractusquha 45
__satfractusquhq2 45
__satfractusquqq2 45
__satfractusqusa 45
__satfractusquta 45
__satfractutada 47
__satfractutadq 47
__satfractutaha 47
__satfractutahq 47
__satfractutaqq 47
__satfractutasa 47
__satfractutasq 47
__satfractutata 47
__satfractutauda2 48
__satfractutaudq 47
__satfractutauha2 47
__satfractutauhq 47
__satfractutauqq 47
__satfractutausa2 47
__satfractutausq 47
__splitstack_find 57
__ssaddda3 23
__ssadddq3 23
__ssaddha3 23
__ssaddhq3 23
__ssaddqq3 23
__ssaddsa3 23
__ssaddsq3 23
__ssaddta3 23
__ssashlda3 29
__ssashldq3 29
__ssashlha3 29
__ssashlhq3 29
__ssashlsa3 29
__ssashlsq3 29
__ssashlta3 29
__ssdivda3 27
__ssdivdq3 27
__ssdivha3 27
__ssdivhq3 27
__ssdivqq3 27
__ssdivsa3 27
__ssdivsq3 27
__ssdivta3 27
__ssmulda3 25
__ssmuldq3 25
__ssmulha3 25
__ssmulhq3 25
__ssmulqq3 25
__ssmulsa3 25
__ssmulsq3 25
__ssmulta3 25
__ssnegda2 28
__ssnegdq2 28
__ssnegha2 28
__ssneghq2 28
__ssnegqq2 28
__ssnegsa2 28
__ssnegsq2 28
__ssnegta2 28
__sssubda3 24
__sssubdq3 24
__sssubha3 24
__sssubhq3 24
__sssubqq3 24
__sssubsa3 24
__sssubsq3 24
__sssubta3 24
__subda3 24
__subdf3 12
__subdq3 23
__subha3 24
__subhq3 23
__subqq3 23
__subsa3 24

__subsf3 ... 12
__subsq3 ... 23
__subta3 ... 24
__subtf3 ... 12
__subuda3 ... 24
__subudq3 ... 24
__subuha3 ... 24
__subuhq3 ... 23
__subuqq3 ... 23
__subusa3 ... 24
__subusq3 ... 24
__subuta3 ... 24
__subvdi3 ... 11
__subvsi3 ... 11
__subxf3 ... 12
__truncdfsf2 ... 13
__trunctfdf2 ... 13
__trunctfsf2 ... 13
__truncxfdf2 ... 13
__truncxfsf2 ... 13
__ucmpdi2 ... 10
__ucmpti2 ... 10
__udivdi3 ... 10
__udivmoddi4 ... 10
__udivmodti4 ... 10
__udivsi3 ... 10
__udivti3 ... 10
__udivuda3 ... 26
__udivudq3 ... 26
__udivuha3 ... 26
__udivuhq3 ... 26
__udivuqq3 ... 26
__udivusa3 ... 26
__udivusq3 ... 26
__udivuta3 ... 26
__umoddi3 ... 10
__umodsi3 ... 10
__umodti3 ... 10
__unorddf2 ... 15
__unordsf2 ... 15
__unordtf2 ... 15
__usadduda3 ... 23
__usaddudq3 ... 23
__usadduha3 ... 23
__usadduhq3 ... 23
__usadduqq3 ... 23
__usaddusa3 ... 23
__usaddusq3 ... 23
__usadduta3 ... 23
__usashluda3 ... 30
__usashludq3 ... 29
__usashluha3 ... 29
__usashluhq3 ... 29
__usashluqq3 ... 29
__usashlusa3 ... 29
__usashlusq3 ... 29
__usashluta3 ... 30
__usdivuda3 ... 27
__usdivudq3 ... 27
__usdivuha3 ... 27
__usdivuhq3 ... 27
__usdivuqq3 ... 27
__usdivusa3 ... 27
__usdivusq3 ... 27
__usdivuta3 ... 27
__usmuluda3 ... 26
__usmuludq3 ... 26
__usmuluha3 ... 26
__usmuluhq3 ... 26
__usmuluqq3 ... 26
__usmulusa3 ... 26
__usmulusq3 ... 26
__usmuluta3 ... 26
__usneguda2 ... 28
__usnegudq2 ... 28
__usneguha2 ... 28
__usneguhq2 ... 28
__usneguqq2 ... 28
__usnegusa2 ... 28
__usnegusq2 ... 28
__usneguta2 ... 28
__ussubuda3 ... 24
__ussubudq3 ... 24
__ussubuha3 ... 24
__ussubuhq3 ... 24
__ussubuqq3 ... 24
__ussubusa3 ... 24
__ussubusq3 ... 24
__ussubuta3 ... 24

\

\ ... 303

0

'0' in constraint ... 312

A

abort ... 5
abs ... 252
abs and attributes ... 397
ABS_EXPR ... 144
absence_set ... 407
abs*m*2 instruction pattern ... 358
absolute value ... 252
access to operands ... 226
access to special operands ... 227
accessors ... 226
ACCUM_TYPE_SIZE ... 443
ACCUMULATE_OUTGOING_ARGS ... 477
ACCUMULATE_OUTGOING_ARGS and stack frames ... 490
ADA_LONG_TYPE_SIZE ... 442
Adding a new GIMPLE statement code ... 209

ADDITIONAL_REGISTER_NAMES 546
add*m*3 instruction pattern 353
add*mode*cc instruction pattern 365
addpt*rm*3 instruction pattern 353
addr_diff_vec 262
addr_diff_vec, length of 401
ADDR_EXPR 143
addr_vec 262
addr_vec, length of 401
address constraints 312
address_operand 307, 312
addressing modes 499
ADJUST_FIELD_ALIGN 435
ADJUST_INSN_LENGTH 401
ADJUST_REG_ALLOC_ORDER 449
aggregates as return values 486
alias 220
ALL_REGS 453
allocate_stack instruction pattern 370
alternate entry points 267
anchored addresses 505
and 251
and and attributes 396
and, canonicalization of 382
and*m*3 instruction pattern 354
ANNOTATE_EXPR 144
annotations 211
APPLY_RESULT_SIZE 486
ARG_POINTER_CFA_OFFSET 468
ARG_POINTER_REGNUM 473
ARG_POINTER_REGNUM and virtual registers 243
arg_pointer_rtx 474
ARGS_GROW_DOWNWARD 465
argument passing 7
arguments in registers 478
arguments on stack 476
arithmetic library 12
arithmetic shift 251
arithmetic shift with signed saturation 251
arithmetic shift with unsigned saturation 251
arithmetic, in RTL 249
ARITHMETIC_TYPE_P 163
array 131
ARRAY_RANGE_REF 143
ARRAY_REF 143
ARRAY_TYPE 131
AS_NEEDS_DASH_FOR_PIPED_INPUT 423
ashift 251
ashift and attributes 397
ashiftrt 251
ashiftrt and attributes 397
ashl*m*3 instruction pattern 357
ashr*m*3 instruction pattern 358
ASM_APP_OFF 528
ASM_APP_ON 528
ASM_COMMENT_START 528
ASM_DECLARE_FUNCTION_NAME 537
ASM_DECLARE_FUNCTION_SIZE 537
ASM_DECLARE_OBJECT_NAME 537
ASM_DECLARE_REGISTER_GLOBAL 537
ASM_FINAL_SPEC 423
ASM_FINISH_DECLARE_OBJECT 537
ASM_FORMAT_PRIVATE_NAME 541
asm_fprintf 548
ASM_FPRINTF_EXTENSIONS 549
ASM_GENERATE_INTERNAL_LABEL 541
asm_input 262
asm_input and '/v' 231
ASM_MAYBE_OUTPUT_ENCODED_ADDR_RTX 470
ASM_NO_SKIP_IN_TEXT 555
asm_noperands 269
asm_operands and '/v' 231
asm_operands, RTL sharing 275
asm_operands, usage 264
ASM_OUTPUT_ADDR_DIFF_ELT 550
ASM_OUTPUT_ADDR_VEC_ELT 550
ASM_OUTPUT_ALIGN 555
ASM_OUTPUT_ALIGN_WITH_NOP 555
ASM_OUTPUT_ALIGNED_BSS 534
ASM_OUTPUT_ALIGNED_COMMON 534
ASM_OUTPUT_ALIGNED_DECL_COMMON 534
ASM_OUTPUT_ALIGNED_DECL_LOCAL 535
ASM_OUTPUT_ALIGNED_LOCAL 535
ASM_OUTPUT_ASCII 531
ASM_OUTPUT_CASE_END 550
ASM_OUTPUT_CASE_LABEL 550
ASM_OUTPUT_COMMON 533
ASM_OUTPUT_DEBUG_LABEL 541
ASM_OUTPUT_DEF 541
ASM_OUTPUT_DEF_FROM_DECLS 541
ASM_OUTPUT_DWARF_DELTA 560
ASM_OUTPUT_DWARF_OFFSET 561
ASM_OUTPUT_DWARF_PCREL 561
ASM_OUTPUT_DWARF_TABLE_REF 561
ASM_OUTPUT_DWARF_VMS_DELTA 560
ASM_OUTPUT_EXTERNAL 539
ASM_OUTPUT_FDESC 532
ASM_OUTPUT_FUNCTION_LABEL 535
ASM_OUTPUT_INTERNAL_LABEL 535
ASM_OUTPUT_LABEL 535
ASM_OUTPUT_LABEL_REF 540
ASM_OUTPUT_LABELREF 540
ASM_OUTPUT_LOCAL 534
ASM_OUTPUT_MAX_SKIP_ALIGN 555
ASM_OUTPUT_MEASURED_SIZE 536
ASM_OUTPUT_OPCODE 547
ASM_OUTPUT_POOL_EPILOGUE 532
ASM_OUTPUT_POOL_PROLOGUE 532
ASM_OUTPUT_REG_POP 550
ASM_OUTPUT_REG_PUSH 549
ASM_OUTPUT_SIZE_DIRECTIVE 536
ASM_OUTPUT_SKIP 554
ASM_OUTPUT_SOURCE_FILENAME 529
ASM_OUTPUT_SPECIAL_POOL_ENTRY 532
ASM_OUTPUT_SYMBOL_REF 540
ASM_OUTPUT_TYPE_DIRECTIVE 536

ASM_OUTPUT_WEAK_ALIAS 542
ASM_OUTPUT_WEAKREF 538
ASM_PREFERRED_EH_DATA_FORMAT 470
ASM_SPEC 423
ASM_STABD_OP 556
ASM_STABN_OP 557
ASM_STABS_OP 556
ASM_WEAKEN_DECL 538
ASM_WEAKEN_LABEL 538
assemble_name 535
assemble_name_raw 535
assembler format 527
assembler instructions in RTL 264
ASSEMBLER_DIALECT 549
assigning attribute values to insns 398
ASSUME_EXTENDED_UNWIND_CONTEXT 474
asterisk in template 304
atan2*m*3 instruction pattern 359
atomic 608
atomic_add_fetch*mode* instruction pattern 377
atomic_add*mode* instruction pattern 377
atomic_and_fetch*mode* instruction pattern 377
atomic_and*mode* instruction pattern 377
atomic_compare_and_swap*mode* instruction pattern 376
atomic_exchange*mode* instruction pattern 377
atomic_fetch_add*mode* instruction pattern 377
atomic_fetch_and*mode* instruction pattern 377
atomic_fetch_nand*mode* instruction pattern .. 377
atomic_fetch_or*mode* instruction pattern 377
atomic_fetch_sub*mode* instruction pattern 377
atomic_fetch_xor*mode* instruction pattern 377
atomic_load*mode* instruction pattern 376
atomic_nand_fetch*mode* instruction pattern .. 377
atomic_nand*mode* instruction pattern 377
atomic_or_fetch*mode* instruction pattern 377
atomic_or*mode* instruction pattern 377
atomic_store*mode* instruction pattern 377
atomic_sub_fetch*mode* instruction pattern 377
atomic_sub*mode* instruction pattern 377
atomic_test_and_set instruction pattern 378
atomic_xor_fetch*mode* instruction pattern 377
atomic_xor*mode* instruction pattern 377
attr 398, 399
attr_flag 398
attribute expressions 396
attribute specifications 400
attribute specifications example 400
ATTRIBUTE_ALIGNED_VALUE 435
attributes 140
attributes, defining 394
attributes, target-specific 565
autoincrement addressing, availability 5
autoincrement/decrement addressing 310
automata_option 408
automaton based pipeline description 404
automaton based scheduler 404
AVOID_CCMODE_COPIES 452

B

backslash 303
barrier 267
barrier and '/f' 231
barrier and '/v' 230
BASE_REG_CLASS 455
basic block 277
Basic Statements 153
basic-block.h 277
basic_block 277
BASIC_BLOCK 277
BB_HEAD, BB_END 284
bb_seq 206
BIGGEST_ALIGNMENT 435
BIGGEST_FIELD_ALIGNMENT 435
BImode 235
BIND_EXPR 144
BINFO_TYPE 165
bit-fields 254
BIT_AND_EXPR 144
BIT_IOR_EXPR 144
BIT_NOT_EXPR 144
BIT_XOR_EXPR 144
BITFIELD_NBYTES_LIMITED 438
BITS_BIG_ENDIAN 432
BITS_BIG_ENDIAN, effect on sign_extract 254
BITS_PER_UNIT 240
BITS_PER_WORD 433
bitwise complement 251
bitwise exclusive-or 251
bitwise inclusive-or 251
bitwise logical-and 251
BLKmode 237
BLKmode, and function return values 273
BLOCK_FOR_INSN, gimple_bb 283
BLOCK_REG_PADDING 482
blockage instruction pattern 374
Blocks 154
bool 587
BOOL_TYPE_SIZE 442
BOOLEAN_TYPE 131
branch prediction 282
BRANCH_COST 512
break_out_memory_refs 500
BREAK_STMT 169
BSS_SECTION_ASM_OP 522
bswap 252
bswap*m*2 instruction pattern 358
btrunc*m*2 instruction pattern 359
build0 130
build1 130
build2 130
build3 130
build4 130
build5 130
build6 130
builtin_longjmp instruction pattern 372

builtin_setjmp_receiver instruction pattern ... 372
builtin_setjmp_setup instruction pattern ... 372
byte_mode ... 240
BYTES_BIG_ENDIAN ... 432
BYTES_BIG_ENDIAN, effect on subreg ... 246

C

C statements for assembler output ... 304
C_COMMON_OVERRIDE_OPTIONS ... 430
c_register_pragma ... 579
c_register_pragma_with_expansion ... 579
call ... 233, 259
call instruction pattern ... 366
call usage ... 273
call, in call_insn ... 230
call, in mem ... 231
call-clobbered register ... 448
call-saved register ... 448
call-used register ... 448
CALL_EXPR ... 144
call_insn ... 266
call_insn and '/c' ... 230
call_insn and '/f' ... 231
call_insn and '/i' ... 230
call_insn and '/j' ... 232
call_insn and '/s' ... 230, 232
call_insn and '/u' ... 230
call_insn and '/u' or '/i' ... 230
call_insn and '/v' ... 230
CALL_INSN_FUNCTION_USAGE ... 266
call_pop instruction pattern ... 367
CALL_POPS_ARGS ... 478
CALL_REALLY_USED_REGISTERS ... 448
CALL_USED_REGISTERS ... 448
call_used_regs ... 448
call_value instruction pattern ... 367
call_value_pop instruction pattern ... 367
CALLER_SAVE_PROFITABLE ... 488
calling conventions ... 465
calling functions in RTL ... 273
can_create_pseudo_p ... 350
can_fallthru ... 278
canadian ... 61
CANNOT_CHANGE_MODE_CLASS ... 462
CANNOT_CHANGE_MODE_CLASS and subreg semantics ... 247
canonicalization of instructions ... 382
canonicalize_funcptr_for_compare instruction pattern ... 369
CASE_VECTOR_MODE ... 573
CASE_VECTOR_PC_RELATIVE ... 573
CASE_VECTOR_SHORTEN_MODE ... 573
casesi instruction pattern ... 368
cbranch*mode*4 instruction pattern ... 366
cc_status ... 507
CC_STATUS_MDEP ... 507
CC_STATUS_MDEP_INIT ... 507
cc0 ... 247, 507
cc0, RTL sharing ... 274
cc0_rtx ... 247
CC1_SPEC ... 422
CC1PLUS_SPEC ... 423
CCmode ... 237, 508
CDImode ... 238
CEIL_DIV_EXPR ... 144
CEIL_MOD_EXPR ... 144
ceil*m*2 instruction pattern ... 359
CFA_FRAME_BASE_OFFSET ... 468
CFG verification ... 285
CFG, Control Flow Graph ... 277
cfghooks.h ... 283
cgraph_finalize_function ... 113
chain_circular ... 607
chain_next ... 607
chain_prev ... 607
change_address ... 350
CHAR_TYPE_SIZE ... 442
check_stack instruction pattern ... 371
CHImode ... 238
CILK_PLUS ... 114
class definitions, register ... 453
class preference constraints ... 315
class, scope ... 165
CLASS_MAX_NREGS ... 461
CLASS_TYPE_P ... 163
classes of RTX codes ... 224
CLASSTYPE_DECLARED_CLASS ... 165
CLASSTYPE_HAS_MUTABLE ... 166
CLASSTYPE_NON_POD_P ... 166
CLEANUP_DECL ... 169
CLEANUP_EXPR ... 169
CLEANUP_POINT_EXPR ... 144
CLEANUP_STMT ... 169
Cleanups ... 155
CLEAR_BY_PIECES_P ... 513
clear_cache instruction pattern ... 379
CLEAR_INSN_CACHE ... 497
CLEAR_RATIO ... 513
clobber ... 259
clrsb ... 252
clz ... 252
CLZ_DEFINED_VALUE_AT_ZERO ... 577
clz*m*2 instruction pattern ... 360
cmpmem*m* instruction pattern ... 362
cmpstr*m* instruction pattern ... 362
cmpstrn*m* instruction pattern ... 362
code generation RTL sequences ... 383
code iterators in '.md' files ... 417
code_label ... 266
CODE_LABEL ... 278
code_label and '/i' ... 230
code_label and '/v' ... 230
CODE_LABEL_NUMBER ... 266
codes, RTL expression ... 223

COImode ... 238
COLLECT_EXPORT_LIST ... 585
COLLECT_SHARED_FINI_FUNC ... 545
COLLECT_SHARED_INIT_FUNC ... 544
COLLECT2_HOST_INITIALIZATION ... 593
commit_edge_insertions ... 284
compare ... 249
compare, canonicalization of ... 382
comparison_operator ... 308
compiler passes and files ... 113
complement, bitwise ... 251
COMPLEX_CST ... 141
COMPLEX_EXPR ... 144
COMPLEX_TYPE ... 131
COMPONENT_REF ... 143
Compound Expressions ... 182
Compound Lvalues ... 182
COMPOUND_EXPR ... 144
COMPOUND_LITERAL_EXPR ... 144
COMPOUND_LITERAL_EXPR_DECL ... 150
COMPOUND_LITERAL_EXPR_DECL_EXPR ... 150
computed jump ... 280
computing the length of an insn ... 401
concat ... 248
concatn ... 248
cond ... 254
cond and attributes ... 396
cond_exec ... 261
COND_EXPR ... 144
condition code register ... 247
condition code status ... 506
condition codes ... 253
conditional execution ... 409
Conditional Expressions ... 183
conditions, in patterns ... 298
configuration file ... 592, 593
configure terms ... 61
CONJ_EXPR ... 144
const ... 242
CONST_DECL ... 136
const_double ... 241
const_double, RTL sharing ... 274
CONST_DOUBLE_LOW ... 241
CONST_DOUBLE_OK_FOR_CONSTRAINT_P ... 464
CONST_DOUBLE_OK_FOR_LETTER_P ... 463
const_double_operand ... 306
const_fixed ... 241
const_int ... 240
const_int and attribute tests ... 396
const_int and attributes ... 396
const_int, RTL sharing ... 274
const_int_operand ... 306
CONST_OK_FOR_CONSTRAINT_P ... 463
CONST_OK_FOR_LETTER_P ... 463
const_string ... 242
const_string and attributes ... 396
const_true_rtx ... 241
const_vector ... 241
const_vector, RTL sharing ... 274
const0_rtx ... 241
CONST0_RTX ... 242
const1_rtx ... 241
CONST1_RTX ... 242
const2_rtx ... 241
CONST2_RTX ... 242
constant attributes ... 402
constant definitions ... 413
CONSTANT_ADDRESS_P ... 499
CONSTANT_ALIGNMENT ... 436
CONSTANT_P ... 499
CONSTANT_POOL_ADDRESS_P ... 230
CONSTANT_POOL_BEFORE_FUNCTION ... 532
constants in constraints ... 311
constm1_rtx ... 241
constraint modifier characters ... 315
constraint, matching ... 312
CONSTRAINT_LEN ... 463
constraint_num ... 348
constraint_satisfied_p ... 349
constraints ... 310
constraints, defining ... 346
constraints, defining, obsolete method ... 463
constraints, machine specific ... 317
constraints, testing ... 348
CONSTRUCTOR ... 144
constructors, automatic calls ... 599
constructors, output of ... 542
container ... 131
CONTINUE_STMT ... 169
contributors ... 655
controlling register usage ... 448
controlling the compilation driver ... 422
conventions, run-time ... 7
conversions ... 255
CONVERT_EXPR ... 144
copy_rtx ... 501
copy_rtx_if_shared ... 275
copysignm3 instruction pattern ... 360
cosm2 instruction pattern ... 358
costs of instructions ... 510
CP_INTEGRAL_TYPE ... 163
cp_namespace_decls ... 164
CP_TYPE_CONST_NON_VOLATILE_P ... 162
CP_TYPE_CONST_P ... 162
cp_type_quals ... 162
CP_TYPE_RESTRICT_P ... 162
CP_TYPE_VOLATILE_P ... 162
CPLUSPLUS_CPP_SPEC ... 422
CPP_SPEC ... 422
CQImode ... 238
cross compilation and floating point ... 562
CRT_CALL_STATIC_FUNCTION ... 523
crtl->args.pops_args ... 490
crtl->args.pretend_args_size ... 490
crtl->outgoing_args_size ... 477
CRTSTUFF_T_CFLAGS ... 595

CRTSTUFF_T_CFLAGS_S 595
CSImode 238
cstore*mode*4 instruction pattern 366
CTImode 238
ctrap*MM*4 instruction pattern 373
ctz 252
CTZ_DEFINED_VALUE_AT_ZERO 577
ctz*m*2 instruction pattern 360
CUMULATIVE_ARGS 480
current_function_is_leaf 453
current_function_uses_only_leaf_regs 453
current_insn_predicate 410

D

DAmode 237
data bypass 405, 406
data dependence delays 404
Data Dependency Analysis 293
data structures 431
DATA_ABI_ALIGNMENT 436
DATA_ALIGNMENT 436
DATA_SECTION_ASM_OP 522
DBR_OUTPUT_SEQEND 548
dbr_sequence_length 548
DBX_BLOCKS_FUNCTION_RELATIVE 558
DBX_CONTIN_CHAR 557
DBX_CONTIN_LENGTH 557
DBX_DEBUGGING_INFO 556
DBX_FUNCTION_FIRST 558
DBX_LINES_FUNCTION_RELATIVE 558
DBX_NO_XREFS 557
DBX_OUTPUT_MAIN_SOURCE_FILE_END 559
DBX_OUTPUT_MAIN_SOURCE_FILENAME 559
DBX_OUTPUT_NULL_N_SO_AT_MAIN_SOURCE_FILE_END 559
DBX_OUTPUT_SOURCE_LINE 558
DBX_REGISTER_NUMBER 555
DBX_REGPARM_STABS_CODE 557
DBX_REGPARM_STABS_LETTER 557
DBX_STATIC_CONST_VAR_CODE 557
DBX_STATIC_STAB_DATA_SECTION 557
DBX_TYPE_DECL_STABS_CODE 557
DBX_USE_BINCL 558
DCmode 238
DDmode 236
De Morgan's law 382
dead_or_set_p 391
debug_expr 264
DEBUG_EXPR_DECL 136
debug_insn 268
DEBUG_SYMS_TEXT 556
DEBUGGER_ARG_OFFSET 556
DEBUGGER_AUTO_OFFSET 555
decimal float library 16
DECL_ALIGN 136
DECL_ANTICIPATED 167
DECL_ARGUMENTS 159
DECL_ARRAY_DELETE_OPERATOR_P 169
DECL_ARTIFICIAL 136, 158, 160
DECL_ASSEMBLER_NAME 158, 159
DECL_ATTRIBUTES 141
DECL_BASE_CONSTRUCTOR_P 168
DECL_COMPLETE_CONSTRUCTOR_P 168
DECL_COMPLETE_DESTRUCTOR_P 168
DECL_CONST_MEMFUNC_P 168
DECL_CONSTRUCTOR_P 168
DECL_CONTEXT 164
DECL_CONV_FN_P 168
DECL_COPY_CONSTRUCTOR_P 168
DECL_DESTRUCTOR_P 168
DECL_EXTERN_C_FUNCTION_P 167
DECL_EXTERNAL 136, 160
DECL_FUNCTION_MEMBER_P 167
DECL_FUNCTION_SPECIFIC_OPTIMIZATION 158, 161
DECL_FUNCTION_SPECIFIC_TARGET 158, 161
DECL_GLOBAL_CTOR_P 168
DECL_GLOBAL_DTOR_P 168
DECL_INITIAL 136, 159
DECL_LINKONCE_P 167
DECL_LOCAL_FUNCTION_P 167
DECL_MAIN_P 167
DECL_NAME 136, 158, 164
DECL_NAMESPACE_ALIAS 164
DECL_NAMESPACE_STD_P 164
DECL_NON_THUNK_FUNCTION_P 169
DECL_NONCONVERTING_P 168
DECL_NONSTATIC_MEMBER_FUNCTION_P 168
DECL_OVERLOADED_OPERATOR_P 168
DECL_PURE_P 160
DECL_RESULT 159
DECL_SAVED_TREE 159
DECL_SIZE 136
DECL_STATIC_FUNCTION_P 168
DECL_STMT 169
DECL_STMT_DECL 169
DECL_THUNK_P 168
DECL_VIRTUAL_P 160
DECL_VOLATILE_MEMFUNC_P 168
declaration 136
declarations, RTL 257
DECLARE_LIBRARY_RENAMES 497
decrement_and_branch_until_zero instruction pattern 369
default 605
default_file_start 527
DEFAULT_GDB_EXTENSIONS 556
DEFAULT_PCC_STRUCT_RETURN 487
DEFAULT_SIGNED_CHAR 444
define_address_constraint 347
define_asm_attributes 400
define_attr 394
define_automaton 404
define_bypass 406
define_c_enum 414

define_code_attr ... 417
define_code_iterator ... 417
define_cond_exec ... 410
define_constants ... 413
define_constraint ... 346
define_cpu_unit ... 405
define_delay ... 403
define_enum ... 415
define_enum_attr ... 395, 415
define_expand ... 383
define_insn ... 297
define_insn example ... 298
define_insn_and_split ... 389
define_insn_reservation ... 405
define_int_attr ... 419
define_int_iterator ... 419
define_memory_constraint ... 347
define_mode_attr ... 416
define_mode_iterator ... 416
define_peephole ... 391
define_peephole2 ... 393
define_predicate ... 308
define_query_cpu_unit ... 405
define_register_constraint ... 346
define_reservation ... 406
define_special_predicate ... 308
define_split ... 386
define_subst ... 411
define_subst ... 412, 413
define_subst ... 420
define_subst_attr ... 420
defining attributes and their values ... 394
defining constraints ... 346
defining constraints, obsolete method ... 463
defining jump instruction patterns ... 380
defining looping instruction patterns ... 380
defining peephole optimizers ... 390
defining predicates ... 308
defining RTL sequences for code generation ... 383
delay slots, defining ... 403
deletable ... 606
DELETE_IF_ORDINARY ... 593
Dependent Patterns ... 379
desc ... 605
destructors, output of ... 542
deterministic finite state automaton ... 404, 408
DF_SIZE ... 443
DFmode ... 236
digits in constraint ... 312
DImode ... 236
DIR_SEPARATOR ... 592
DIR_SEPARATOR_2 ... 592
directory options .md ... 390
disabling certain registers ... 448
dispatch table ... 550
div ... 250
div and attributes ... 397
division ... 250, 251
divm3 instruction pattern ... 354
divmodm4 instruction pattern ... 357
DO_BODY ... 169
DO_COND ... 169
DO_STMT ... 169
DOLLARS_IN_IDENTIFIERS ... 580
doloop_begin instruction pattern ... 369
doloop_end instruction pattern ... 369
DONE ... 384
DONT_USE_BUILTIN_SETJMP ... 552
DOUBLE_TYPE_SIZE ... 442
DQmode ... 236
driver ... 422
DRIVER_SELF_SPECS ... 422
dump examples ... 128
dump setup ... 126
dump types ... 127
dump verbosity ... 127
dump_basic_block ... 128
dump_generic_expr ... 128
dump_gimple_stmt ... 128
dump_printf ... 127
DUMPFILE_FORMAT ... 593
DWARF_ALT_FRAME_RETURN_COLUMN ... 467
DWARF_CIE_DATA_ALIGNMENT ... 553
DWARF_FRAME_REGISTERS ... 474
DWARF_FRAME_REGNUM ... 474
DWARF_REG_TO_UNWIND_COLUMN ... 474
DWARF_ZERO_REG ... 467
DWARF2_ASM_LINE_DEBUG_INFO ... 560
DWARF2_DEBUGGING_INFO ... 559
DWARF2_FRAME_INFO ... 560
DWARF2_FRAME_REG_OUT ... 474
DWARF2_UNWIND_INFO ... 552
DYNAMIC_CHAIN_ADDRESS ... 466

E

'E' in constraint ... 311
earlyclobber operand ... 315
edge ... 279
edge in the flow graph ... 279
edge iterators ... 279
edge splitting ... 284
EDGE_ABNORMAL ... 280
EDGE_ABNORMAL, EDGE_ABNORMAL_CALL ... 281
EDGE_ABNORMAL, EDGE_EH ... 280
EDGE_ABNORMAL, EDGE_SIBCALL ... 280
EDGE_FALLTHRU, force_nonfallthru ... 280
EDOM, implicit usage ... 498
EH_FRAME_IN_DATA_SECTION ... 551
EH_FRAME_SECTION_NAME ... 551
eh_return instruction pattern ... 372
EH_RETURN_DATA_REGNO ... 469
EH_RETURN_HANDLER_RTX ... 469
EH_RETURN_STACKADJ_RTX ... 469
EH_TABLES_CAN_BE_READ_ONLY ... 552
EH_USES ... 490

ei_edge ... 279
ei_end_p ... 279
ei_last ... 279
ei_next ... 279
ei_one_before_end_p ... 279
ei_prev ... 279
ei_safe_safe ... 279
ei_start ... 279
ELIMINABLE_REGS ... 475
ELSE_CLAUSE ... 169
Embedded C ... 22
EMIT_MODE_SET ... 565
Empty Statements ... 155
EMPTY_CLASS_EXPR ... 169
EMPTY_FIELD_BOUNDARY ... 437
Emulated TLS ... 567
enabled ... 345
ENDFILE_SPEC ... 424
endianness ... 5
ENTRY_BLOCK_PTR, EXIT_BLOCK_PTR ... 277
enum machine_mode ... 235
enum reg_class ... 454
ENUMERAL_TYPE ... 131
enumerations ... 414
epilogue ... 488
epilogue instruction pattern ... 373
EPILOGUE_USES ... 490
eq ... 253
eq and attributes ... 397
eq_attr ... 397
EQ_EXPR ... 144
equal ... 253
errno, implicit usage ... 498
EXACT_DIV_EXPR ... 144
examining SSA_NAMEs ... 219
exception handling ... 280, 469
exception_receiver instruction pattern ... 372
exclamation point ... 315
exclusion_set ... 407
exclusive-or, bitwise ... 251
EXIT_EXPR ... 144
EXIT_IGNORE_STACK ... 490
expander definitions ... 383
exp*m*2 instruction pattern ... 359
EXPR_FILENAME ... 136
EXPR_LINENO ... 136
expr_list ... 273
EXPR_STMT ... 169
EXPR_STMT_EXPR ... 169
expression ... 141
expression codes ... 223
extend*mn*2 instruction pattern ... 363
extensible constraints ... 312
EXTRA_ADDRESS_CONSTRAINT ... 464
EXTRA_CONSTRAINT ... 464
EXTRA_CONSTRAINT_STR ... 464
EXTRA_MEMORY_CONSTRAINT ... 464
EXTRA_SPECS ... 425
extv instruction pattern ... 365
extv*m* instruction pattern ... 364
extvmisalign*m* instruction pattern ... 364
extzv instruction pattern ... 365
extzv*m* instruction pattern ... 364
extzvmisalign*m* instruction pattern ... 364

F

'F' in constraint ... 311
FAIL ... 384
fall-thru ... 279
FATAL_EXIT_CODE ... 593
FDL, GNU Free Documentation License ... 647
features, optional, in system conventions ... 429
ffs ... 252
ffs*m*2 instruction pattern ... 360
FIELD_DECL ... 136
file_end_indicate_exec_stack ... 528
files and passes of the compiler ... 113
files, generated ... 611
final_absence_set ... 407
FINAL_PRESCAN_INSN ... 547
final_presence_set ... 407
final_sequence ... 548
FIND_BASE_TERM ... 500
FINI_ARRAY_SECTION_ASM_OP ... 523
FINI_SECTION_ASM_OP ... 523
finite state automaton minimization ... 408
FIRST_PARM_OFFSET ... 466
FIRST_PARM_OFFSET and virtual registers ... 243
FIRST_PSEUDO_REGISTER ... 447
FIRST_STACK_REG ... 453
FIRST_VIRTUAL_REGISTER ... 243
fix ... 256
FIX_TRUNC_EXPR ... 144
fix_trunc*mn*2 instruction pattern ... 363
fixed register ... 447
fixed-point fractional library ... 22
FIXED_CONVERT_EXPR ... 144
FIXED_CST ... 141
FIXED_POINT_TYPE ... 131
FIXED_REGISTERS ... 447
fixed_regs ... 448
fix*mn*2 instruction pattern ... 363
fixuns_trunc*mn*2 instruction pattern ... 363
fixuns*mn*2 instruction pattern ... 363
flags in RTL expression ... 230
float ... 256
FLOAT_EXPR ... 144
float_extend ... 256
FLOAT_LIB_COMPARE_RETURNS_BOOL ... 497
FLOAT_STORE_FLAG_VALUE ... 577
float_truncate ... 256
FLOAT_TYPE_SIZE ... 442
FLOAT_WORDS_BIG_ENDIAN ... 433
FLOAT_WORDS_BIG_ENDIAN, (lack of) effect on subreg ... 246

floating point and cross compilation 562
float*mn*2 instruction pattern 363
floatuns*mn*2 instruction pattern 363
FLOOR_DIV_EXPR 144
FLOOR_MOD_EXPR 144
floor*m*2 instruction pattern 359
flow-insensitive alias analysis 220
flow-sensitive alias analysis 220
fma 250
fma*m*4 instruction pattern 354
fmod*m*3 instruction pattern 358
fms*m*4 instruction pattern 354
fnma*m*4 instruction pattern 354
fnms*m*4 instruction pattern 354
FOR_BODY 169
FOR_COND 169
FOR_EXPR 169
FOR_INIT_STMT 169
FOR_STMT 169
FORCE_CODE_SECTION_ALIGN 524
force_reg 350
fract_convert 256
FRACT_TYPE_SIZE 442
fractional types 22
fract*mn*2 instruction pattern 363
fractuns*mn*2 instruction pattern 364
frame layout 465
FRAME_ADDR_RTX 467
FRAME_GROWS_DOWNWARD 465
FRAME_GROWS_DOWNWARD and virtual registers .. 244
FRAME_POINTER_CFA_OFFSET 468
frame_pointer_needed 488
FRAME_POINTER_REGNUM 472
FRAME_POINTER_REGNUM and virtual registers .. 244
frame_pointer_rtx 474
frame_related 233
frame_related, in insn, call_insn, jump_insn, barrier, and set 231
frame_related, in mem 231
frame_related, in reg 231
frame_related, in symbol_ref 232
frequency, count, BB_FREQ_BASE 282
ftrunc*m*2 instruction pattern 363
function 158, 167
function call conventions 7
function entry and exit 488
function entry point, alternate function entry point 281
function properties 160
function-call insns 273
FUNCTION_ARG_OFFSET 481
FUNCTION_ARG_PADDING 481
FUNCTION_ARG_REGNO_P 482
FUNCTION_BOUNDARY 435
FUNCTION_DECL 158, 167
FUNCTION_MODE 578
FUNCTION_PROFILER 491
FUNCTION_TYPE 131
FUNCTION_VALUE 485
FUNCTION_VALUE_REGNO_P 486
functions, leaf 452
fundamental type 131

G

'g' in constraint 312
'G' in constraint 311
garbage collector, invocation 612
garbage collector, troubleshooting 613
GCC and portability 5
GCC_DRIVER_HOST_INITIALIZATION 593
gcov_type 282
ge 254
ge and attributes 397
GE_EXPR 144
GEN_ERRNO_RTX 498
gencodes 122
general_operand 308
GENERAL_REGS 454
generated files 611
generating assembler output 304
generating insns 299
GENERIC 113, 129
generic predicates 306
genflags 122
get_attr 397
get_attr_length 401
GET_CLASS_NARROWEST_MODE 240
GET_CODE 223
get_frame_size 475
get_insns 265
get_last_insn 265
GET_MODE 239
GET_MODE_ALIGNMENT 240
GET_MODE_BITSIZE 239
GET_MODE_CLASS 239
GET_MODE_FBIT 239
GET_MODE_IBIT 239
GET_MODE_MASK 239
GET_MODE_NAME 239
GET_MODE_NUNITS 240
GET_MODE_SIZE 239
GET_MODE_UNIT_SIZE 240
GET_MODE_WIDER_MODE 239
GET_RTX_CLASS 224
GET_RTX_FORMAT 226
GET_RTX_LENGTH 226
get_thread_pointer*mode* instruction pattern 378
geu 254
geu and attributes 397
GGC 603
ggc_collect 612
GIMPLE 113, 115, 175
GIMPLE Exception Handling 181
GIMPLE instruction set 180

GIMPLE sequences 205
GIMPLE statement iterators 278, 283
gimple_addresses_taken 187
GIMPLE_ASM 188
gimple_asm_clobber_op 189
gimple_asm_input_op 188
gimple_asm_nclobbers 188
gimple_asm_ninputs 188
gimple_asm_noutputs 188
gimple_asm_output_op 189
gimple_asm_set_clobber_op 189
gimple_asm_set_input_op 189
gimple_asm_set_output_op 189
gimple_asm_set_volatile 189
gimple_asm_string 189
gimple_asm_volatile_p 189
GIMPLE_ASSIGN 189
gimple_assign_cast_p 185, 190
gimple_assign_lhs 190
gimple_assign_lhs_ptr 190
gimple_assign_rhs_class 190
gimple_assign_rhs_code 190
gimple_assign_rhs1 190
gimple_assign_rhs1_ptr 190
gimple_assign_rhs2 190
gimple_assign_rhs2_ptr 190
gimple_assign_rhs3 190
gimple_assign_rhs3_ptr 190
gimple_assign_set_lhs 190
gimple_assign_set_rhs1 190
gimple_assign_set_rhs2 190
gimple_assign_set_rhs3 190
gimple_bb 186
GIMPLE_BIND 191
gimple_bind_add_seq 191
gimple_bind_add_stmt 191
gimple_bind_append_vars 191
gimple_bind_block 191
gimple_bind_body 191
gimple_bind_set_block 191
gimple_bind_set_body 191
gimple_bind_set_vars 191
gimple_bind_vars 191
gimple_block 186
gimple_build_asm 188
gimple_build_asm_vec 188
gimple_build_assign 189
gimple_build_assign_with_ops 189
gimple_build_bind 191
gimple_build_call 191
gimple_build_call_from_tree 191
gimple_build_call_vec 192
gimple_build_catch 193
gimple_build_cond 193
gimple_build_cond_from_tree 193
gimple_build_debug_bind 194
gimple_build_eh_filter 195
gimple_build_goto 196
gimple_build_label 196
gimple_build_nop 196
gimple_build_omp_atomic_load 197
gimple_build_omp_atomic_store 197
gimple_build_omp_continue 197
gimple_build_omp_critical 198
gimple_build_omp_for 198
gimple_build_omp_master 199
gimple_build_omp_ordered 199
gimple_build_omp_parallel 200
gimple_build_omp_return 201
gimple_build_omp_section 201
gimple_build_omp_sections 201
gimple_build_omp_sections_switch 201
gimple_build_omp_single 202
gimple_build_resx 202
gimple_build_return 203
gimple_build_switch 203
gimple_build_try 204
gimple_build_wce 204
GIMPLE_CALL 191
gimple_call_arg 192
gimple_call_arg_ptr 192
gimple_call_cannot_inline_p 193
gimple_call_chain 192
gimple_call_copy_skip_args 193
gimple_call_fn 192
gimple_call_fndecl 192
gimple_call_lhs 192
gimple_call_lhs_ptr 192
gimple_call_mark_uninlinable 193
gimple_call_noreturn_p 193
gimple_call_num_args 192
gimple_call_return_type 192
gimple_call_set_arg 192
gimple_call_set_chain 192
gimple_call_set_fn 192
gimple_call_set_fndecl 192
gimple_call_set_lhs 192
gimple_call_set_tail 192
gimple_call_tail_p 193
GIMPLE_CATCH 193
gimple_catch_handler 193
gimple_catch_set_handler 193
gimple_catch_set_types 193
gimple_catch_types 193
gimple_catch_types_ptr 193
gimple_code 186
GIMPLE_COND 193
gimple_cond_code 194
gimple_cond_false_label 194
gimple_cond_lhs 194
gimple_cond_make_false 194
gimple_cond_make_true 194
gimple_cond_rhs 194
gimple_cond_set_code 194
gimple_cond_set_false_label 194
gimple_cond_set_lhs 194

gimple_cond_set_rhs 194
gimple_cond_set_true_label 194
gimple_cond_true_label 194
gimple_copy 188
GIMPLE_DEBUG 194
GIMPLE_DEBUG_BIND 194
gimple_debug_bind_get_value 195
gimple_debug_bind_get_value_ptr 195
gimple_debug_bind_get_var 195
gimple_debug_bind_has_value_p 195
gimple_debug_bind_p 185
gimple_debug_bind_reset_value 195
gimple_debug_bind_set_value 195
gimple_debug_bind_set_var 195
gimple_def_ops 187
GIMPLE_EH_FILTER 195
gimple_eh_filter_failure 196
gimple_eh_filter_must_not_throw 196
gimple_eh_filter_set_failure 196
gimple_eh_filter_set_must_not_throw 196
gimple_eh_filter_set_types 196
gimple_eh_filter_types 195
gimple_eh_filter_types_ptr 196
gimple_expr_code 186
gimple_expr_type 186
gimple_goto_dest 196
gimple_goto_set_dest 196
gimple_has_mem_ops 187
gimple_has_ops 187
gimple_has_volatile_ops 188
GIMPLE_LABEL 196
gimple_label_label 196
gimple_label_set_label 196
gimple_loaded_syms 187
gimple_locus 186
gimple_locus_empty_p 186
gimple_modified_p 188
gimple_no_warning_p 186
GIMPLE_NOP 196
gimple_nop_p 196
gimple_num_ops 184, 187
GIMPLE_OMP_ATOMIC_LOAD 197
gimple_omp_atomic_load_lhs 197
gimple_omp_atomic_load_rhs 197
gimple_omp_atomic_load_set_lhs 197
gimple_omp_atomic_load_set_rhs 197
GIMPLE_OMP_ATOMIC_STORE 197
gimple_omp_atomic_store_set_val 197
gimple_omp_atomic_store_val 197
gimple_omp_body 200
GIMPLE_OMP_CONTINUE 197
gimple_omp_continue_control_def 197
gimple_omp_continue_control_def_ptr 197
gimple_omp_continue_control_use 197
gimple_omp_continue_control_use_ptr 197
gimple_omp_continue_set_control_def 197
gimple_omp_continue_set_control_use 197
GIMPLE_OMP_CRITICAL 198
gimple_omp_critical_name 198
gimple_omp_critical_name_ptr 198
gimple_omp_critical_set_name 198
GIMPLE_OMP_FOR 198
gimple_omp_for_clauses 198
gimple_omp_for_clauses_ptr 198
gimple_omp_for_cond 199
gimple_omp_for_final 199
gimple_omp_for_final_ptr 199
gimple_omp_for_incr 199
gimple_omp_for_incr_ptr 199
gimple_omp_for_index 198
gimple_omp_for_index_ptr 198
gimple_omp_for_initial 198
gimple_omp_for_initial_ptr 198
gimple_omp_for_pre_body 199
gimple_omp_for_set_clauses 198
gimple_omp_for_set_cond 199
gimple_omp_for_set_final 199
gimple_omp_for_set_incr 199
gimple_omp_for_set_index 198
gimple_omp_for_set_initial 199
gimple_omp_for_set_pre_body 199
GIMPLE_OMP_MASTER 199
GIMPLE_OMP_ORDERED 199
GIMPLE_OMP_PARALLEL 200
gimple_omp_parallel_child_fn 200
gimple_omp_parallel_child_fn_ptr 200
gimple_omp_parallel_clauses 200
gimple_omp_parallel_clauses_ptr 200
gimple_omp_parallel_combined_p 200
gimple_omp_parallel_data_arg 200
gimple_omp_parallel_data_arg_ptr 200
gimple_omp_parallel_set_child_fn 200
gimple_omp_parallel_set_clauses 200
gimple_omp_parallel_set_combined_p 200
gimple_omp_parallel_set_data_arg 200
GIMPLE_OMP_RETURN 201
gimple_omp_return_nowait_p 201
gimple_omp_return_set_nowait 201
GIMPLE_OMP_SECTION 201
gimple_omp_section_last_p 201
gimple_omp_section_set_last 201
GIMPLE_OMP_SECTIONS 201
gimple_omp_sections_clauses 201
gimple_omp_sections_clauses_ptr 201
gimple_omp_sections_control 201
gimple_omp_sections_control_ptr 201
gimple_omp_sections_set_clauses 201
gimple_omp_sections_set_control 201
gimple_omp_set_body 200
GIMPLE_OMP_SINGLE 202
gimple_omp_single_clauses 202
gimple_omp_single_clauses_ptr 202
gimple_omp_single_set_clauses 202
gimple_op 184, 187
gimple_op_ptr 187
gimple_ops 184, 187

GIMPLE_PHI ... 202
gimple_phi_arg ... 202, 217
gimple_phi_arg_def ... 217
gimple_phi_arg_edge ... 217
gimple_phi_capacity ... 202
gimple_phi_num_args ... 202, 217
gimple_phi_result ... 202, 217
gimple_phi_result_ptr ... 202
gimple_phi_set_arg ... 202
gimple_phi_set_result ... 202
gimple_plf ... 186
GIMPLE_RESX ... 202
gimple_resx_region ... 203
gimple_resx_set_region ... 203
GIMPLE_RETURN ... 203
gimple_return_retval ... 203
gimple_return_set_retval ... 203
gimple_seq_add_seq ... 205
gimple_seq_add_stmt ... 205
gimple_seq_alloc ... 205
gimple_seq_copy ... 205
gimple_seq_deep_copy ... 205
gimple_seq_empty_p ... 206
gimple_seq_first ... 205
gimple_seq_init ... 205
gimple_seq_last ... 205
gimple_seq_reverse ... 205
gimple_seq_set_first ... 205
gimple_seq_set_last ... 205
gimple_seq_singleton_p ... 206
gimple_set_block ... 186
gimple_set_def_ops ... 187
gimple_set_has_volatile_ops ... 188
gimple_set_locus ... 186
gimple_set_op ... 187
gimple_set_plf ... 186
gimple_set_use_ops ... 187
gimple_set_vdef_ops ... 187
gimple_set_visited ... 186
gimple_set_vuse_ops ... 187
gimple_statement_base ... 176
gimple_statement_with_ops ... 177
gimple_stored_syms ... 188
GIMPLE_SWITCH ... 203
gimple_switch_default_label ... 203
gimple_switch_index ... 203
gimple_switch_label ... 203
gimple_switch_num_labels ... 203
gimple_switch_set_default_label ... 203
gimple_switch_set_index ... 203
gimple_switch_set_label ... 203
gimple_switch_set_num_labels ... 203
GIMPLE_TRY ... 204
gimple_try_catch_is_cleanup ... 204
gimple_try_cleanup ... 204
gimple_try_eval ... 204
gimple_try_kind ... 204
gimple_try_set_catch_is_cleanup ... 204
gimple_try_set_cleanup ... 204
gimple_try_set_eval ... 204
gimple_use_ops ... 187
gimple_vdef_ops ... 187
gimple_visited_p ... 186
gimple_vuse_ops ... 187
gimple_wce_cleanup ... 204
gimple_wce_cleanup_eh_only ... 204
gimple_wce_set_cleanup ... 204
gimple_wce_set_cleanup_eh_only ... 204
GIMPLE_WITH_CLEANUP_EXPR ... 204
gimplification ... 113, 115
gimplifier ... 113
gimplify_assign ... 189
gimplify_expr ... 115
gimplify_function_tree ... 115
GLOBAL_INIT_PRIORITY ... 169
global_regs ... 448
GO_IF_LEGITIMATE_ADDRESS ... 500
greater than ... 253, 254
gsi_after_labels ... 207
gsi_bb ... 207
gsi_commit_edge_inserts ... 209, 284
gsi_commit_one_edge_insert ... 209
gsi_end_p ... 207, 284
gsi_for_stmt ... 208
gsi_insert_after ... 208, 284
gsi_insert_before ... 208, 284
gsi_insert_on_edge ... 209, 284
gsi_insert_on_edge_immediate ... 209
gsi_insert_seq_after ... 208
gsi_insert_seq_before ... 208
gsi_insert_seq_on_edge ... 209
gsi_last ... 206, 284
gsi_last_bb ... 206
gsi_link_after ... 208
gsi_link_before ... 207
gsi_link_seq_after ... 207
gsi_link_seq_before ... 207
gsi_move_after ... 208
gsi_move_before ... 208
gsi_move_to_bb_end ... 208
gsi_next ... 207, 284
gsi_one_before_end_p ... 207
gsi_prev ... 207, 284
gsi_remove ... 207, 284
gsi_replace ... 208
gsi_seq ... 207
gsi_split_seq_after ... 208
gsi_split_seq_before ... 208
gsi_start ... 206, 283
gsi_start_bb ... 206
gsi_stmt ... 207
gsi_stmt_ptr ... 207
gt ... 253
gt and attributes ... 397
GT_EXPR ... 144
gtu ... 253

gtu and attributes ... 397
GTY ... 603

H

'H' in constraint ... 311
HAmode ... 237
HANDLE_PRAGMA_PACK_WITH_EXPANSION ... 579
HANDLER ... 169
HANDLER_BODY ... 169
HANDLER_PARMS ... 169
hard registers ... 243
HARD_FRAME_POINTER_IS_ARG_POINTER ... 473
HARD_FRAME_POINTER_IS_FRAME_POINTER ... 473
HARD_FRAME_POINTER_REGNUM ... 472
HARD_REGNO_CALL_PART_CLOBBERED ... 448
HARD_REGNO_CALLER_SAVE_MODE ... 488
HARD_REGNO_MODE_OK ... 451
HARD_REGNO_NREGS ... 450
HARD_REGNO_NREGS_HAS_PADDING ... 450
HARD_REGNO_NREGS_WITH_PADDING ... 450
HARD_REGNO_RENAME_OK ... 451
HAS_INIT_SECTION ... 544
HAS_LONG_COND_BRANCH ... 573
HAS_LONG_UNCOND_BRANCH ... 573
HAVE_DOS_BASED_FILE_SYSTEM ... 592
HAVE_POST_DECREMENT ... 499
HAVE_POST_INCREMENT ... 499
HAVE_POST_MODIFY_DISP ... 499
HAVE_POST_MODIFY_REG ... 499
HAVE_PRE_DECREMENT ... 499
HAVE_PRE_INCREMENT ... 499
HAVE_PRE_MODIFY_DISP ... 499
HAVE_PRE_MODIFY_REG ... 499
HCmode ... 238
HFmode ... 236
high ... 242
HImode ... 235
HImode, in insn ... 269
HONOR_REG_ALLOC_ORDER ... 449
host configuration ... 591
host functions ... 591
host hooks ... 591
host makefile fragment ... 598
HOST_BIT_BUCKET ... 592
HOST_EXECUTABLE_SUFFIX ... 592
HOST_HOOKS_EXTRA_SIGNALS ... 591
HOST_HOOKS_GT_PCH_ALLOC_GRANULARITY ... 591
HOST_HOOKS_GT_PCH_GET_ADDRESS ... 591
HOST_HOOKS_GT_PCH_USE_ADDRESS ... 591
HOST_LACKS_INODE_NUMBERS ... 593
HOST_LONG_FORMAT ... 594
HOST_LONG_LONG_FORMAT ... 594
HOST_OBJECT_SUFFIX ... 592
HOST_PTR_PRINTF ... 594
HOT_TEXT_SECTION_NAME ... 522
HQmode ... 236

I

'i' in constraint ... 311
'I' in constraint ... 311
identifier ... 131
IDENTIFIER_LENGTH ... 131
IDENTIFIER_NODE ... 131
IDENTIFIER_OPNAME_P ... 131
IDENTIFIER_POINTER ... 131
IDENTIFIER_TYPENAME_P ... 131
IEEE 754-2008 ... 16
IF_COND ... 169
if_marked ... 606
IF_STMT ... 169
if_then_else ... 254
if_then_else and attributes ... 396
if_then_else usage ... 258
IFCVT_MACHDEP_INIT ... 582
IFCVT_MODIFY_CANCEL ... 582
IFCVT_MODIFY_FINAL ... 581
IFCVT_MODIFY_INSN ... 581
IFCVT_MODIFY_MULTIPLE_TESTS ... 581
IFCVT_MODIFY_TESTS ... 581
IMAGPART_EXPR ... 144
Immediate Uses ... 215
immediate_operand ... 306
IMMEDIATE_PREFIX ... 549
in_struct ... 234
in_struct, in code_label and note ... 230
in_struct, in insn and jump_insn and call_insn ... 230
in_struct, in insn, call_insn, jump_insn and jump_table_data ... 232
in_struct, in subreg ... 233
include ... 389
INCLUDE_DEFAULTS ... 427
inclusive-or, bitwise ... 251
INCOMING_FRAME_SP_OFFSET ... 468
INCOMING_REGNO ... 448
INCOMING_RETURN_ADDR_RTX ... 467
INCOMING_STACK_BOUNDARY ... 435
INDEX_REG_CLASS ... 455
indirect_jump instruction pattern ... 368
indirect_operand ... 307
INDIRECT_REF ... 143
INIT_ARRAY_SECTION_ASM_OP ... 523
INIT_CUMULATIVE_ARGS ... 480
INIT_CUMULATIVE_INCOMING_ARGS ... 481
INIT_CUMULATIVE_LIBCALL_ARGS ... 481
INIT_ENVIRONMENT ... 427
INIT_EXPANDERS ... 432
INIT_EXPR ... 144
init_machine_status ... 432
init_one_libfunc ... 497
INIT_SECTION_ASM_OP ... 523, 544
INITIAL_ELIMINATION_OFFSET ... 476
INITIAL_FRAME_ADDRESS_RTX ... 466
INITIAL_FRAME_POINTER_OFFSET ... 475
initialization routines ... 542

inlining ... 566
insert_insn_on_edge ... 284
insn ... 265
insn and '/f' ... 231
insn and '/j' ... 232
insn and '/s' ... 230, 232
insn and '/u' ... 230
insn and '/v' ... 230
insn attributes ... 394
insn canonicalization ... 382
insn includes ... 389
insn lengths, computing ... 401
insn notes, notes ... 278
insn splitting ... 386
insn-attr.h ... 395
INSN_ANNULLED_BRANCH_P ... 230
INSN_CODE ... 269
INSN_DELETED_P ... 230
INSN_FROM_TARGET_P ... 230
insn_list ... 273
INSN_REFERENCES_ARE_DELAYED ... 580
INSN_SETS_ARE_DELAYED ... 580
INSN_UID ... 265
INSN_VAR_LOCATION ... 268
insns ... 265
insns, generating ... 299
insns, recognizing ... 299
instruction attributes ... 394
instruction latency time ... 404, 405, 406
instruction patterns ... 297
instruction splitting ... 386
insv instruction pattern ... 365
insv*m* instruction pattern ... 364
insvmisalign*m* instruction pattern ... 365
int iterators in '.md' files ... 419
INT_FAST16_TYPE ... 446
INT_FAST32_TYPE ... 446
INT_FAST64_TYPE ... 446
INT_FAST8_TYPE ... 446
INT_LEAST16_TYPE ... 445
INT_LEAST32_TYPE ... 445
INT_LEAST64_TYPE ... 445
INT_LEAST8_TYPE ... 445
INT_TYPE_SIZE ... 441
INT16_TYPE ... 445
INT32_TYPE ... 445
INT64_TYPE ... 445
INT8_TYPE ... 445
INTEGER_CST ... 141
INTEGER_TYPE ... 131
Interdependence of Patterns ... 379
interfacing to GCC output ... 7
interlock delays ... 404
intermediate representation lowering ... 113
INTMAX_TYPE ... 445
INTPTR_TYPE ... 446
introduction ... 1
INVOKE__main ... 545
ior ... 251
ior and attributes ... 396
ior, canonicalization of ... 382
ior*m*3 instruction pattern ... 354
IRA_HARD_REGNO_ADD_COST_MULTIPLIER ... 450
IS_ASM_LOGICAL_LINE_SEPARATOR ... 533
is_gimple_addressable ... 184
is_gimple_asm_val ... 185
is_gimple_assign ... 185
is_gimple_call ... 185
is_gimple_call_addr ... 185
is_gimple_constant ... 185
is_gimple_debug ... 185
is_gimple_ip_invariant ... 185
is_gimple_ip_invariant_address ... 185
is_gimple_mem_ref_addr ... 185
is_gimple_min_invariant ... 185
is_gimple_omp ... 185
is_gimple_val ... 184
iterators in '.md' files ... 415
IV analysis on GIMPLE ... 291
IV analysis on RTL ... 292

J

JMP_BUF_SIZE ... 552
jump ... 234
jump instruction pattern ... 366
jump instruction patterns ... 380
jump instructions and set ... 258
jump, in call_insn ... 232
jump, in insn ... 232
jump, in mem ... 231
JUMP_ALIGN ... 553
jump_insn ... 265
jump_insn and '/f' ... 231
jump_insn and '/s' ... 230, 232
jump_insn and '/u' ... 230
jump_insn and '/v' ... 230
JUMP_LABEL ... 266
jump_table_data ... 267
jump_table_data and '/s' ... 232
jump_table_data and '/v' ... 230
JUMP_TABLES_IN_TEXT_SECTION ... 524
Jumps ... 155

L

LABEL_ALIGN ... 554
LABEL_ALIGN_AFTER_BARRIER ... 554
LABEL_ALT_ENTRY_P ... 267
LABEL_ALTERNATE_NAME ... 281
LABEL_DECL ... 136
LABEL_KIND ... 267
LABEL_NUSES ... 267
LABEL_PRESERVE_P ... 230
label_ref ... 242
label_ref and '/v' ... 231

label_ref, RTL sharing ... 274
LABEL_REF_NONLOCAL_P ... 231
lang_hooks.gimplify_expr ... 115
lang_hooks.parse_file ... 113
language-dependent trees ... 161
language-independent intermediate representation ... 113
large return values ... 486
LARGEST_EXPONENT_IS_NORMAL ... 440
LAST_STACK_REG ... 453
LAST_VIRTUAL_REGISTER ... 243
lceil*mn*2 ... 360
LCSSA ... 290
LD_FINI_SWITCH ... 544
LD_INIT_SWITCH ... 544
LDD_SUFFIX ... 546
le ... 254
le and attributes ... 397
LE_EXPR ... 144
leaf functions ... 452
leaf_function_p ... 368
LEAF_REG_REMAP ... 452
LEAF_REGISTERS ... 452
left rotate ... 252
left shift ... 251
LEGITIMATE_PIC_OPERAND_P ... 527
LEGITIMIZE_RELOAD_ADDRESS ... 501
length ... 604
less than ... 253
less than or equal ... 254
leu ... 254
leu and attributes ... 397
lfloor*mn*2 ... 360
LIB_SPEC ... 423
LIB2FUNCS_EXTRA ... 595
LIBCALL_VALUE ... 485
'libgcc.a' ... 497
LIBGCC_SPEC ... 423
LIBGCC2_CFLAGS ... 595
LIBGCC2_GNU_PREFIX ... 443
LIBGCC2_HAS_DF_MODE ... 443
LIBGCC2_HAS_TF_MODE ... 443
LIBGCC2_HAS_XF_MODE ... 443
LIBGCC2_LONG_DOUBLE_TYPE_SIZE ... 443
LIBGCC2_UNWIND_ATTRIBUTE ... 589
library subroutine names ... 497
LIBRARY_PATH_ENV ... 581
LIMIT_RELOAD_CLASS ... 458
LINK_COMMAND_SPEC ... 425
LINK_EH_SPEC ... 424
LINK_GCC_C_SEQUENCE_SPEC ... 425
LINK_LIBGCC_SPECIAL_1 ... 425
LINK_SPEC ... 423
list ... 131
Liveness representation ... 285
lo_sum ... 249
load address instruction ... 312
LOAD_EXTEND_OP ... 574
load_multiple instruction pattern ... 351
Local Register Allocator (LRA) ... 125
LOCAL_ALIGNMENT ... 436
LOCAL_CLASS_P ... 166
LOCAL_DECL_ALIGNMENT ... 437
LOCAL_INCLUDE_DIR ... 427
LOCAL_LABEL_PREFIX ... 549
LOCAL_REGNO ... 449
LOG_LINKS ... 269
Logical Operators ... 183
logical-and, bitwise ... 251
LOGICAL_OP_NON_SHORT_CIRCUIT ... 514
log*m*2 instruction pattern ... 359
LONG_ACCUM_TYPE_SIZE ... 443
LONG_DOUBLE_TYPE_SIZE ... 442
LONG_FRACT_TYPE_SIZE ... 442
LONG_LONG_ACCUM_TYPE_SIZE ... 443
LONG_LONG_FRACT_TYPE_SIZE ... 442
LONG_LONG_TYPE_SIZE ... 442
LONG_TYPE_SIZE ... 442
longjmp and automatic variables ... 7
Loop analysis ... 287
Loop manipulation ... 290
Loop querying ... 289
Loop representation ... 287
Loop-closed SSA form ... 290
LOOP_ALIGN ... 554
LOOP_EXPR ... 144
looping instruction patterns ... 380
lowering, language-dependent intermediate representation ... 113
lrint*mn*2 ... 360
lround*mn*2 ... 360
LSHIFT_EXPR ... 144
lshiftrt ... 251
lshiftrt and attributes ... 397
lshr*m*3 instruction pattern ... 358
lt ... 253
lt and attributes ... 397
LT_EXPR ... 144
LTGT_EXPR ... 144
lto ... 623
ltrans ... 623
ltu ... 253

M

'm' in constraint ... 310
machine attributes ... 565
machine description macros ... 421
machine descriptions ... 297
machine mode conversions ... 255
machine modes ... 235
machine specific constraints ... 317
machine-independent predicates ... 306
macros, target description ... 421
madd*mn*4 instruction pattern ... 356
MAKE_DECL_ONE_ONLY ... 539

make_safe_from ... 386
makefile fragment ... 595
makefile targets ... 66
MALLOC_ABI_ALIGNMENT ... 435
Manipulating GIMPLE statements ... 185
mark_hook ... 606
marking roots ... 611
MASK_RETURN_ADDR ... 552
match_dup ... 300, 393
match_dup and attributes ... 401
match_op_dup ... 301
match_operand ... 299
match_operand and attributes ... 397
match_operator ... 300
match_par_dup ... 302
match_parallel ... 302
match_scratch ... 300, 393
match_test and attributes ... 397
matching constraint ... 312
matching operands ... 303
math library ... 12
math, in RTL ... 249
MATH_LIBRARY ... 581
matherr ... 498
MAX_BITS_PER_WORD ... 433
MAX_BITSIZE_MODE_ANY_INT ... 240
MAX_BITSIZE_MODE_ANY_MODE ... 240
MAX_CONDITIONAL_EXECUTE ... 581
MAX_FIXED_MODE_SIZE ... 439
MAX_MOVE_MAX ... 574
MAX_OFILE_ALIGNMENT ... 435
MAX_REGS_PER_ADDRESS ... 499
MAX_STACK_ALIGNMENT ... 435
max*m*3 instruction pattern ... 354
may_trap_p, tree_could_trap_p ... 280
maybe_undef ... 606
mcount ... 491
MD_CAN_REDIRECT_BRANCH ... 584
MD_EXEC_PREFIX ... 426
MD_FALLBACK_FRAME_STATE_FOR ... 470
MD_HANDLE_UNWABI ... 470
MD_STARTFILE_PREFIX ... 426
MD_STARTFILE_PREFIX_1 ... 426
mem ... 248
mem and '/c' ... 231
mem and '/f' ... 231
mem and '/j' ... 231
mem and '/u' ... 232
mem and '/v' ... 231
mem, RTL sharing ... 274
MEM_ADDR_SPACE ... 228
MEM_ALIAS_SET ... 227
MEM_ALIGN ... 228
MEM_EXPR ... 227
MEM_KEEP_ALIAS_SET_P ... 231
MEM_NOTRAP_P ... 231
MEM_OFFSET ... 228
MEM_OFFSET_KNOWN_P ... 227
MEM_POINTER ... 231
MEM_READONLY_P ... 232
MEM_REF ... 143
mem_signal_fence*mode* instruction pattern ... 378
MEM_SIZE ... 228
MEM_SIZE_KNOWN_P ... 228
mem_thread_fence*mode* instruction pattern ... 378
MEM_VOLATILE_P ... 231
memory model ... 222
memory reference, nonoffsettable ... 314
memory references in constraints ... 310
memory_barrier instruction pattern ... 374
MEMORY_MOVE_COST ... 511
memory_operand ... 307
METHOD_TYPE ... 131
MIN_UNITS_PER_WORD ... 433
MINIMUM_ALIGNMENT ... 437
MINIMUM_ATOMIC_ALIGNMENT ... 435
min*m*3 instruction pattern ... 354
minus ... 249
minus and attributes ... 397
minus, canonicalization of ... 382
MINUS_EXPR ... 144
MIPS coprocessor-definition macros ... 569
mnemonic attribute ... 402
mod ... 251
mod and attributes ... 397
mode classes ... 238
mode iterators in '.md' files ... 415
mode switching ... 563
MODE_ACCUM ... 238
MODE_AFTER ... 564
MODE_BASE_REG_CLASS ... 455
MODE_BASE_REG_REG_CLASS ... 455
MODE_CC ... 239, 508
MODE_CODE_BASE_REG_CLASS ... 455
MODE_COMPLEX_FLOAT ... 239
MODE_COMPLEX_INT ... 239
MODE_DECIMAL_FLOAT ... 238
MODE_ENTRY ... 564
MODE_EXIT ... 564
MODE_FLOAT ... 238
MODE_FRACT ... 238
MODE_FUNCTION ... 239
MODE_INT ... 238
MODE_NEEDED ... 564
MODE_PARTIAL_INT ... 238
MODE_PRIORITY_TO_MODE ... 564
MODE_RANDOM ... 239
MODE_UACCUM ... 238
MODE_UFRACT ... 238
MODES_TIEABLE_P ... 452
modifiers in constraints ... 315
MODIFY_EXPR ... 144
MODIFY_JNI_METHOD_CALL ... 585
mod*m*3 instruction pattern ... 354
modulo scheduling ... 124
MOVE_BY_PIECES_P ... 512

MOVE_MAX ... 574
MOVE_MAX_PIECES ... 513
MOVE_RATIO ... 512
mov*m* instruction pattern ... 349
movmem*m* instruction pattern ... 361
movmisalign*m* instruction pattern ... 351
mov*mode*cc instruction pattern ... 365
movstr instruction pattern ... 361
movstrict*m* instruction pattern ... 351
msub*mn*4 instruction pattern ... 357
mulhisi3 instruction pattern ... 356
mul*m*3 instruction pattern ... 354
mulqihi3 instruction pattern ... 356
mulsidi3 instruction pattern ... 356
mult ... 250
mult and attributes ... 397
mult, canonicalization of ... 382, 383
MULT_EXPR ... 144
MULT_HIGHPART_EXPR ... 144
MULTIARCH_DIRNAME ... 598
MULTILIB_DEFAULTS ... 426
MULTILIB_DIRNAMES ... 596
MULTILIB_EXCEPTIONS ... 596
MULTILIB_EXTRA_OPTS ... 597
MULTILIB_MATCHES ... 596
MULTILIB_OPTIONS ... 595
MULTILIB_OSDIRNAMES ... 597
MULTILIB_REQUIRED ... 596
MULTILIB_REUSE ... 597
multiple alternative constraints ... 314
MULTIPLE_SYMBOL_SPACES ... 580
multiplication ... 250
multiplication with signed saturation ... 250
multiplication with unsigned saturation ... 250

N

'n' in constraint ... 311
N_REG_CLASSES ... 454
name ... 131
named address spaces ... 571
named patterns and conditions ... 298
names, pattern ... 349
namespace, scope ... 164
NAMESPACE_DECL ... 136, 164
NATIVE_SYSTEM_HEADER_COMPONENT ... 427
ne ... 253
ne and attributes ... 397
NE_EXPR ... 144
nearbyint*m*2 instruction pattern ... 359
neg ... 250
neg and attributes ... 397
neg, canonicalization of ... 382
NEGATE_EXPR ... 144
negation ... 250
negation with signed saturation ... 250
negation with unsigned saturation ... 250
neg*m*2 instruction pattern ... 358
nested functions, trampolines for ... 495
nested_ptr ... 607
next_bb, prev_bb, FOR_EACH_BB, FOR_ALL_BB ... 277
NEXT_INSN ... 265
NEXT_OBJC_RUNTIME ... 498
nil ... 224
NM_FLAGS ... 546
NO_DBX_BNSYM_ENSYM ... 558
NO_DBX_FUNCTION_END ... 558
NO_DBX_GCC_MARKER ... 559
NO_DBX_MAIN_SOURCE_DIRECTORY ... 559
NO_DOLLAR_IN_LABEL ... 536
NO_DOT_IN_LABEL ... 536
NO_FUNCTION_CSE ... 514
NO_IMPLICIT_EXTERN_C ... 579
NO_PROFILE_COUNTERS ... 492
NO_REGS ... 453
NON_LVALUE_EXPR ... 144
nondeterministic finite state automaton ... 408
nonimmediate_operand ... 307
nonlocal goto handler ... 281
nonlocal_goto instruction pattern ... 371
nonlocal_goto_receiver instruction pattern ... 371
nonmemory_operand ... 307
nonoffsettable memory reference ... 314
nop instruction pattern ... 368
NOP_EXPR ... 144
normal predicates ... 306
not ... 251
not and attributes ... 396
not equal ... 253
not, canonicalization of ... 382
note ... 267
note and '/i' ... 230
note and '/v' ... 230
NOTE_INSN_BASIC_BLOCK ... 278
NOTE_INSN_BLOCK_BEG ... 268
NOTE_INSN_BLOCK_END ... 268
NOTE_INSN_DELETED ... 267
NOTE_INSN_DELETED_LABEL ... 267
NOTE_INSN_EH_REGION_BEG ... 268
NOTE_INSN_EH_REGION_END ... 268
NOTE_INSN_FUNCTION_BEG ... 268
NOTE_INSN_VAR_LOCATION ... 268
NOTE_LINE_NUMBER ... 267
NOTE_SOURCE_FILE ... 267
NOTE_VAR_LOCATION ... 268
NOTICE_UPDATE_CC ... 507
NUM_MACHINE_MODES ... 239
NUM_MODES_FOR_MODE_SWITCHING ... 564
Number of iterations analysis ... 292

O

'o' in constraint ... 310
OBJC_GEN_METHOD_LABEL ... 542

OBJC_JBLEN ... 589
OBJECT_FORMAT_COFF ... 545
OFFSET_TYPE ... 131
offsettable address ... 310
OImode ... 236
Omega a solver for linear programming problems ... 295
OMP_ATOMIC ... 156
OMP_CLAUSE ... 156
OMP_CONTINUE ... 156
OMP_CRITICAL ... 156
OMP_FOR ... 156
OMP_MASTER ... 156
OMP_ORDERED ... 156
OMP_PARALLEL ... 156
OMP_RETURN ... 156
OMP_SECTION ... 156
OMP_SECTIONS ... 156
OMP_SINGLE ... 156
one_cmpl*m*2 instruction pattern ... 361
operand access ... 226
Operand Access Routines ... 213
operand constraints ... 310
Operand Iterators ... 213
operand predicates ... 305
operand substitution ... 303
operands ... 211
operands ... 298
Operands ... 182
operator predicates ... 305
'optc-gen.awk' ... 105
OPTGROUP_ALL ... 126
OPTGROUP_INLINE ... 126
OPTGROUP_IPA ... 126
OPTGROUP_LOOP ... 126
OPTGROUP_OTHER ... 126
OPTGROUP_VEC ... 126
optimization dumps ... 126
optimization groups ... 126
optimization info file names ... 127
Optimization infrastructure for GIMPLE ... 211
OPTIMIZE_MODE_SWITCHING ... 563
option specification files ... 105
OPTION_DEFAULT_SPECS ... 422
optional hardware or system features ... 429
options, directory search ... 390
order of register allocation ... 449
ordered_comparison_operator ... 308
ORDERED_EXPR ... 144
Ordering of Patterns ... 379
ORIGINAL_REGNO ... 228
other register constraints ... 312
outgoing_args_size ... 477
OUTGOING_REG_PARM_STACK_SPACE ... 477
OUTGOING_REGNO ... 449
output of assembler code ... 527
output statements ... 304
output templates ... 303
output_asm_insn ... 304
OUTPUT_QUOTED_STRING ... 529
OVERLAPPING_REGISTER_NAMES ... 546
OVERLOAD ... 167
OVERRIDE_ABI_FORMAT ... 480
OVL_CURRENT ... 167
OVL_NEXT ... 167

P

'p' in constraint ... 312
PAD_VARARGS_DOWN ... 482
parallel ... 260
param_is ... 605
parameters, c++ abi ... 570
parameters, miscellaneous ... 573
parameters, precompiled headers ... 569
param*n*_is ... 606
parity ... 252
parity*m*2 instruction pattern ... 361
PARM_BOUNDARY ... 434
PARM_DECL ... 136
PARSE_LDD_OUTPUT ... 546
pass dumps ... 113
pass_duplicate_computed_gotos ... 281
passes and files of the compiler ... 113
passing arguments ... 7
PATH_SEPARATOR ... 592
PATTERN ... 269
pattern conditions ... 298
pattern names ... 349
Pattern Ordering ... 379
patterns ... 297
pc ... 248
pc and attributes ... 401
pc, RTL sharing ... 274
PC_REGNUM ... 449
pc_rtx ... 248
PCC_BITFIELD_TYPE_MATTERS ... 437
PCC_STATIC_STRUCT_RETURN ... 487
PDImode ... 235
peephole optimization, RTL representation ... 261
peephole optimizer definitions ... 390
per-function data ... 431
percent sign ... 303
PHI nodes ... 217
PIC ... 527
PIC_OFFSET_TABLE_REG_CALL_CLOBBERED ... 527
PIC_OFFSET_TABLE_REGNUM ... 527
pipeline hazard recognizer ... 404
Plugins ... 615
plus ... 249
plus and attributes ... 397
plus, canonicalization of ... 382
PLUS_EXPR ... 144
Pmode ... 578
pmode_register_operand ... 306
pointer ... 131

POINTER_PLUS_EXPR ... 144
POINTER_SIZE ... 433
POINTER_TYPE ... 131
POINTERS_EXTEND_UNSIGNED ... 433
pop_operand ... 307
popcount ... 252
popcount*m*2 instruction pattern ... 361
pops_args ... 490
portability ... 5
position independent code ... 527
post_dec ... 263
post_inc ... 263
post_modify ... 263
post_order_compute, inverted_post_order_compute, walk_dominator_tree ... 277
POSTDECREMENT_EXPR ... 144
POSTINCREMENT_EXPR ... 144
POWI_MAX_MULTS ... 586
pow*m*3 instruction pattern ... 359
pragma ... 579
pre_dec ... 263
PRE_GCC3_DWARF_FRAME_REGISTERS ... 474
pre_inc ... 263
pre_modify ... 263
PREDECREMENT_EXPR ... 144
predefined macros ... 428
predicates ... 305
predicates and machine modes ... 306
predication ... 409
predict.def ... 282
PREFERRED_DEBUGGING_TYPE ... 556
PREFERRED_RELOAD_CLASS ... 457
PREFERRED_STACK_BOUNDARY ... 434
prefetch ... 262
prefetch and '/v' ... 233
prefetch instruction pattern ... 373
PREFETCH_SCHEDULE_BARRIER_P ... 233
PREINCREMENT_EXPR ... 144
presence_set ... 407
preserving SSA form ... 217
preserving virtual SSA form ... 219
pretend_args_size ... 490
prev_active_insn ... 391
PREV_INSN ... 265
PRINT_OPERAND ... 548
PRINT_OPERAND_ADDRESS ... 548
PRINT_OPERAND_PUNCT_VALID_P ... 548
probe_stack instruction pattern ... 371
probe_stack_address instruction pattern ... 371
processor functional units ... 404, 405
processor pipeline description ... 404
product ... 250
profile feedback ... 282
profile representation ... 282
PROFILE_BEFORE_PROLOGUE ... 492
PROFILE_HOOK ... 492
profiling, code generation ... 491
program counter ... 248
prologue ... 488
prologue instruction pattern ... 372
PROMOTE_MODE ... 433
pseudo registers ... 243
PSImode ... 235
PTRDIFF_TYPE ... 444
purge_dead_edges ... 280, 284
push address instruction ... 312
PUSH_ARGS ... 476
PUSH_ARGS_REVERSED ... 476
push_operand ... 307
push_reload ... 501
PUSH_ROUNDING ... 476
push*m*1 instruction pattern ... 353
PUT_CODE ... 223
PUT_MODE ... 239
PUT_REG_NOTE_KIND ... 270
PUT_SDB_... ... 561

Q

QCmode ... 238
QFmode ... 236
QImode ... 235
QImode, in insn ... 269
QQmode ... 236
qualified type ... 131, 162
querying function unit reservations ... 405
question mark ... 315
quotient ... 250

R

'r' in constraint ... 311
RDIV_EXPR ... 144
READONLY_DATA_SECTION_ASM_OP ... 522
real operands ... 211
REAL_ARITHMETIC ... 563
REAL_CST ... 141
REAL_LIBGCC_SPEC ... 424
REAL_NM_FILE_NAME ... 546
REAL_TYPE ... 131
REAL_VALUE_ABS ... 563
REAL_VALUE_ATOF ... 563
REAL_VALUE_FIX ... 562
REAL_VALUE_FROM_INT ... 563
REAL_VALUE_ISINF ... 563
REAL_VALUE_ISNAN ... 563
REAL_VALUE_NEGATE ... 563
REAL_VALUE_NEGATIVE ... 563
REAL_VALUE_TO_INT ... 563
REAL_VALUE_TO_TARGET_DECIMAL128 ... 533
REAL_VALUE_TO_TARGET_DECIMAL32 ... 533
REAL_VALUE_TO_TARGET_DECIMAL64 ... 533
REAL_VALUE_TO_TARGET_DOUBLE ... 533
REAL_VALUE_TO_TARGET_LONG_DOUBLE ... 533
REAL_VALUE_TO_TARGET_SINGLE ... 533

REAL_VALUE_TYPE ... 562
REAL_VALUE_UNSIGNED_FIX ... 562
REAL_VALUES_EQUAL ... 562
REAL_VALUES_LESS ... 562
REALPART_EXPR ... 144
recog_data.operand ... 547
recognizing insns ... 299
RECORD_TYPE ... 131, 165
redirect_edge_and_branch ... 283
redirect_edge_and_branch, redirect_jump ... 284
reduc_smax_*m* instruction pattern ... 354
reduc_smin_*m* instruction pattern ... 354
reduc_splus_*m* instruction pattern ... 354
reduc_umax_*m* instruction pattern ... 354
reduc_umin_*m* instruction pattern ... 354
reduc_uplus_*m* instruction pattern ... 354
reference ... 131
REFERENCE_TYPE ... 131
reg ... 243
reg and '/f' ... 231
reg and '/i' ... 231
reg and '/v' ... 231
reg, RTL sharing ... 274
REG_ALLOC_ORDER ... 449
REG_BR_PRED ... 273
REG_BR_PROB ... 273
REG_BR_PROB_BASE, BB_FREQ_BASE, count ... 283
REG_BR_PROB_BASE, EDGE_FREQUENCY ... 282
REG_CC_SETTER ... 272
REG_CC_USER ... 272
reg_class_contents ... 448
REG_CLASS_CONTENTS ... 455
REG_CLASS_FROM_CONSTRAINT ... 463
REG_CLASS_FROM_LETTER ... 463
REG_CLASS_NAMES ... 455
REG_CROSSING_JUMP ... 271
REG_DEAD ... 270
REG_DEAD, REG_UNUSED ... 285
REG_DEP_ANTI ... 273
REG_DEP_OUTPUT ... 273
REG_DEP_TRUE ... 273
REG_EH_REGION, EDGE_ABNORMAL_CALL ... 280
REG_EQUAL ... 271
REG_EQUIV ... 271
REG_EXPR ... 228
REG_FRAME_RELATED_EXPR ... 273
REG_FUNCTION_VALUE_P ... 231
REG_INC ... 270
reg_label and '/v' ... 231
REG_LABEL_OPERAND ... 270
REG_LABEL_TARGET ... 271
reg_names ... 448, 548
REG_NONNEG ... 270
REG_NOTE_KIND ... 270
REG_NOTES ... 269
REG_OFFSET ... 228
REG_OK_STRICT ... 500
REG_PARM_STACK_SPACE ... 477
REG_PARM_STACK_SPACE, and TARGET_FUNCTION_ARG ... 479
REG_POINTER ... 231
REG_SETJMP ... 271
REG_UNUSED ... 270
REG_USERVAR_P ... 231
REG_VALUE_IN_UNWIND_CONTEXT ... 474
REG_WORDS_BIG_ENDIAN ... 433
regclass_for_constraint ... 349
register allocation order ... 449
register class definitions ... 453
register class preference constraints ... 315
register pairs ... 451
Register Transfer Language (RTL) ... 223
register usage ... 447
REGISTER_MOVE_COST ... 510
REGISTER_NAMES ... 546
register_operand ... 306
REGISTER_PREFIX ... 549
REGISTER_TARGET_PRAGMAS ... 579
registers arguments ... 478
registers in constraints ... 311
REGMODE_NATURAL_SIZE ... 450
REGNO_MODE_CODE_OK_FOR_BASE_P ... 456
REGNO_MODE_OK_FOR_BASE_P ... 456
REGNO_MODE_OK_FOR_REG_BASE_P ... 456
REGNO_OK_FOR_BASE_P ... 456
REGNO_OK_FOR_INDEX_P ... 456
REGNO_REG_CLASS ... 455
regs_ever_live ... 488
regular expressions ... 404, 405
relative costs ... 510
RELATIVE_PREFIX_NOT_LINKDIR ... 426
reload_completed ... 368
reload_in instruction pattern ... 351
reload_in_progress ... 350
reload_out instruction pattern ... 351
reloading ... 124
remainder ... 251
remainder*m*3 instruction pattern ... 358
reorder ... 607
representation of RTL ... 223
reservation delays ... 404
rest_of_decl_compilation ... 113
rest_of_type_compilation ... 113
restore_stack_block instruction pattern ... 370
restore_stack_function instruction pattern ... 370
restore_stack_nonlocal instruction pattern ... 370
RESULT_DECL ... 136
return ... 258
return instruction pattern ... 367
return values in registers ... 484
RETURN_ADDR_IN_PREVIOUS_FRAME ... 467
RETURN_ADDR_OFFSET ... 469
RETURN_ADDR_RTX ... 467

RETURN_ADDRESS_POINTER_REGNUM 473
RETURN_EXPR 169
RETURN_STMT 169
return_val 234
return_val, in call_insn 230
return_val, in reg 231
return_val, in symbol_ref 233
returning aggregate values 486
returning structures and unions 7
reverse probability 283
REVERSE_CONDITION 509
REVERSIBLE_CC_MODE 509
right rotate 252
right shift 251
rintm2 instruction pattern 360
RISC 404, 407
roots, marking 611
rotate 252
rotatert 252
rotlm3 instruction pattern 358
rotrm3 instruction pattern 358
ROUND_DIV_EXPR 144
ROUND_MOD_EXPR 144
ROUND_TOWARDS_ZERO 440
ROUND_TYPE_ALIGN 439
roundm2 instruction pattern 359
RSHIFT_EXPR 144
RTL addition 249
RTL addition with signed saturation 249
RTL addition with unsigned saturation 249
RTL classes 224
RTL comparison 249
RTL comparison operations 253
RTL constant expression types 240
RTL constants 240
RTL declarations 257
RTL difference 249
RTL expression 223
RTL expressions for arithmetic 249
RTL format 225
RTL format characters 225
RTL function-call insns 273
RTL insn template 299
RTL integers 223
RTL memory expressions 243
RTL object types 223
RTL postdecrement 263
RTL postincrement 263
RTL predecrement 263
RTL preincrement 263
RTL register expressions 243
RTL representation 223
RTL side effect expressions 257
RTL strings 223
RTL structure sharing assumptions 274
RTL subtraction 249
RTL subtraction with signed saturation 249
RTL subtraction with unsigned saturation 249
RTL sum 249
RTL vectors 223
RTL_CONST_CALL_P 230
RTL_CONST_OR_PURE_CALL_P 230
RTL_LOOPING_CONST_OR_PURE_CALL_P 230
RTL_PURE_CALL_P 230
RTX (See RTL) 223
RTX codes, classes of 224
RTX_FRAME_RELATED_P 231
run-time conventions 7
run-time target specification 428

S

's' in constraint 311
same_type_p 133
SAmode 237
sat_fract 257
satfractmn2 instruction pattern 364
satfractunsmn2 instruction pattern 364
satisfies_constraint_m 349
SAVE_EXPR 144
save_stack_block instruction pattern 370
save_stack_function instruction pattern 370
save_stack_nonlocal instruction pattern 370
SBSS_SECTION_ASM_OP 523
Scalar evolutions 291
scalars, returned as values 484
SCHED_GROUP_P 232
SCmode 238
scratch 247
scratch operands 247
scratch, RTL sharing 274
scratch_operand 307
SDATA_SECTION_ASM_OP 522
SDB_ALLOW_FORWARD_REFERENCES 561
SDB_ALLOW_UNKNOWN_REFERENCES 561
SDB_DEBUGGING_INFO 559
SDB_DELIM 561
SDB_OUTPUT_SOURCE_LINE 561
SDmode 236
sdot_prodm instruction pattern 354
search options 390
SECONDARY_INPUT_RELOAD_CLASS 459
SECONDARY_MEMORY_NEEDED 460
SECONDARY_MEMORY_NEEDED_MODE 461
SECONDARY_MEMORY_NEEDED_RTX 460
SECONDARY_OUTPUT_RELOAD_CLASS 459
SECONDARY_RELOAD_CLASS 459
SELECT_CC_MODE 508
sequence 261
Sequence iterators 206
set 257
set and '/f' 231
SET_ASM_OP 541
set_attr 399
set_attr_alternative 399
set_bb_seq 206

SET_BY_PIECES_P ... 513
SET_DEST ... 258
SET_IS_RETURN_P ... 232
SET_LABEL_KIND ... 267
set_optab_libfunc ... 497
SET_RATIO ... 513
SET_SRC ... 258
set_thread_pointer*mode* instruction pattern ... 378
SET_TYPE_STRUCTURAL_EQUALITY ... 131, 133
setmem*m* instruction pattern ... 362
SETUP_FRAME_ADDRESSES ... 466
SF_SIZE ... 443
SFmode ... 236
sharing of RTL components ... 274
shift ... 251
SHIFT_COUNT_TRUNCATED ... 574
SHLIB_SUFFIX ... 546
SHORT_ACCUM_TYPE_SIZE ... 443
SHORT_FRACT_TYPE_SIZE ... 442
SHORT_IMMEDIATES_SIGN_EXTEND ... 574
SHORT_TYPE_SIZE ... 441
sibcall_epilogue instruction pattern ... 373
sibling call ... 280
SIBLING_CALL_P ... 232
SIG_ATOMIC_TYPE ... 445
sign_extend ... 256
sign_extract ... 254
sign_extract, canonicalization of ... 383
signed division ... 250
signed division with signed saturation ... 250
signed maximum ... 251
signed minimum ... 251
SImode ... 235
simple constraints ... 310
simple_return ... 258
simple_return instruction pattern ... 367
sincos*m*3 instruction pattern ... 358
sin*m*2 instruction pattern ... 358
SIZE_ASM_OP ... 535
SIZE_TYPE ... 444
SIZETYPE ... 444
skip ... 605
SLOW_BYTE_ACCESS ... 512
SLOW_UNALIGNED_ACCESS ... 512
smax ... 251
smin ... 251
sms, swing, software pipelining ... 124
smul*m*3_highpart instruction pattern ... 356
soft float library ... 12
special ... 608
special predicates ... 306
SPECS ... 598
speed of instructions ... 510
split_block ... 284
splitting instructions ... 386
SQmode ... 236
sqrt ... 252
sqrt*m*2 instruction pattern ... 358
square root ... 252
ss_abs ... 252
ss_ashift ... 251
ss_div ... 250
ss_minus ... 249
ss_mult ... 250
ss_neg ... 250
ss_plus ... 249
ss_truncate ... 256
SSA ... 216
SSA_NAME_DEF_STMT ... 220
SSA_NAME_VERSION ... 220
ssadd*m*3 instruction pattern ... 354
ssashl*m*3 instruction pattern ... 357
ssdiv*m*3 instruction pattern ... 354
ssmadd*mn*4 instruction pattern ... 357
ssmsub*mn*4 instruction pattern ... 357
ssmul*m*3 instruction pattern ... 354
ssneg*m*2 instruction pattern ... 358
sssub*m*3 instruction pattern ... 354
ssum_widen*m3* instruction pattern ... 355
stack arguments ... 476
stack frame layout ... 465
stack smashing protection ... 493
STACK_ALIGNMENT_NEEDED ... 465
STACK_BOUNDARY ... 434
STACK_CHECK_BUILTIN ... 471
STACK_CHECK_FIXED_FRAME_SIZE ... 472
STACK_CHECK_MAX_FRAME_SIZE ... 472
STACK_CHECK_MAX_VAR_SIZE ... 472
STACK_CHECK_MOVING_SP ... 471
STACK_CHECK_PROBE_INTERVAL_EXP ... 471
STACK_CHECK_PROTECT ... 471
STACK_CHECK_STATIC_BUILTIN ... 471
STACK_DYNAMIC_OFFSET ... 466
STACK_DYNAMIC_OFFSET and virtual registers ... 244
STACK_GROWS_DOWNWARD ... 465
STACK_PARMS_IN_REG_PARM_AREA ... 477
STACK_POINTER_OFFSET ... 466
STACK_POINTER_OFFSET and virtual registers ... 244
STACK_POINTER_REGNUM ... 472
STACK_POINTER_REGNUM and virtual registers ... 244
stack_pointer_rtx ... 474
stack_protect_set instruction pattern ... 378
stack_protect_test instruction pattern ... 379
STACK_PUSH_CODE ... 465
STACK_REG_COVER_CLASS ... 453
STACK_REGS ... 453
STACK_SAVEAREA_MODE ... 439
STACK_SIZE_MODE ... 439
STACK_SLOT_ALIGNMENT ... 436
standard pattern names ... 349
STANDARD_STARTFILE_PREFIX ... 426
STANDARD_STARTFILE_PREFIX_1 ... 426
STANDARD_STARTFILE_PREFIX_2 ... 426
STARTFILE_SPEC ... 424
STARTING_FRAME_OFFSET ... 465

STARTING_FRAME_OFFSET and virtual registers ... 244
Statement and operand traversals ... 209
Statement Sequences ... 155
statements ... 160, 169
Statements ... 153
Static profile estimation ... 282
static single assignment ... 216
STATIC_CHAIN_INCOMING_REGNUM ... 473
STATIC_CHAIN_REGNUM ... 473
'stdarg.h' and register arguments ... 479
STDC_0_IN_SYSTEM_HEADERS ... 578
STMT_EXPR ... 144
STMT_IS_FULL_EXPR_P ... 169
storage layout ... 432
STORE_BY_PIECES_P ... 513
STORE_FLAG_VALUE ... 576
'store_multiple' instruction pattern ... 352
strcpy ... 436
STRICT_ALIGNMENT ... 437
strict_low_part ... 257
strict_memory_address_p ... 501
STRING_CST ... 141
STRING_POOL_ADDRESS_P ... 232
strlen*m* instruction pattern ... 363
structure value address ... 486
STRUCTURE_SIZE_BOUNDARY ... 437
structures, returning ... 7
sub*m*3 instruction pattern ... 354
SUBOBJECT ... 169
SUBOBJECT_CLEANUP ... 169
subreg ... 244
subreg and '/s' ... 233
subreg and '/u' ... 233
subreg and '/u' and '/v' ... 232
subreg, in strict_low_part ... 257
SUBREG_BYTE ... 247
SUBREG_PROMOTED_UNSIGNED_P ... 232
SUBREG_PROMOTED_UNSIGNED_SET ... 233
SUBREG_PROMOTED_VAR_P ... 233
SUBREG_REG ... 247
subst iterators in '.md' files ... 420
SUCCESS_EXIT_CODE ... 593
SUPPORTS_INIT_PRIORITY ... 545
SUPPORTS_ONE_ONLY ... 539
SUPPORTS_WEAK ... 538
SWITCH_BODY ... 169
SWITCH_COND ... 169
SWITCH_STMT ... 169
SWITCHABLE_TARGET ... 431
SYMBOL_FLAG_ANCHOR ... 229
SYMBOL_FLAG_EXTERNAL ... 229
SYMBOL_FLAG_FUNCTION ... 229
SYMBOL_FLAG_HAS_BLOCK_INFO ... 229
SYMBOL_FLAG_LOCAL ... 229
SYMBOL_FLAG_SMALL ... 229
SYMBOL_FLAG_TLS_SHIFT ... 229
symbol_ref ... 242
symbol_ref and '/f' ... 232
symbol_ref and '/i' ... 233
symbol_ref and '/u' ... 230
symbol_ref and '/v' ... 233
symbol_ref, RTL sharing ... 274
SYMBOL_REF_ANCHOR_P ... 229
SYMBOL_REF_BLOCK ... 229
SYMBOL_REF_BLOCK_OFFSET ... 229
SYMBOL_REF_CONSTANT ... 228
SYMBOL_REF_DATA ... 228
SYMBOL_REF_DECL ... 228
SYMBOL_REF_EXTERNAL_P ... 229
SYMBOL_REF_FLAG ... 233
SYMBOL_REF_FLAG, in TARGET_ENCODE_SECTION_INFO ... 526
SYMBOL_REF_FLAGS ... 229
SYMBOL_REF_FUNCTION_P ... 229
SYMBOL_REF_HAS_BLOCK_INFO_P ... 229
SYMBOL_REF_LOCAL_P ... 229
SYMBOL_REF_SMALL_P ... 229
SYMBOL_REF_TLS_MODEL ... 229
SYMBOL_REF_USED ... 233
SYMBOL_REF_WEAK ... 233
symbolic label ... 274
sync_add*mode* instruction pattern ... 375
sync_and*mode* instruction pattern ... 375
sync_compare_and_swap*mode* instruction pattern ... 374
sync_ior*mode* instruction pattern ... 375
sync_lock_release*mode* instruction pattern ... 376
sync_lock_test_and_set*mode* instruction pattern ... 375
sync_nand*mode* instruction pattern ... 375
sync_new_add*mode* instruction pattern ... 375
sync_new_and*mode* instruction pattern ... 375
sync_new_ior*mode* instruction pattern ... 375
sync_new_nand*mode* instruction pattern ... 375
sync_new_sub*mode* instruction pattern ... 375
sync_new_xor*mode* instruction pattern ... 375
sync_old_add*mode* instruction pattern ... 375
sync_old_and*mode* instruction pattern ... 375
sync_old_ior*mode* instruction pattern ... 375
sync_old_nand*mode* instruction pattern ... 375
sync_old_sub*mode* instruction pattern ... 375
sync_old_xor*mode* instruction pattern ... 375
sync_sub*mode* instruction pattern ... 375
sync_xor*mode* instruction pattern ... 375
SYSROOT_HEADERS_SUFFIX_SPEC ... 424
SYSROOT_SUFFIX_SPEC ... 424

T

't-*target*' ... 595
table jump ... 278
tablejump instruction pattern ... 368
tag ... 605
tagging insns ... 398
tail calls ... 492

TAmode ... 237
target attributes ... 565
target description macros ... 421
target functions ... 421
target hooks ... 421
target makefile fragment ... 595
target specifications ... 428
TARGET_ADDR_SPACE_ADDRESS_MODE ... 572
TARGET_ADDR_SPACE_CONVERT ... 573
TARGET_ADDR_SPACE_LEGITIMATE_ADDRESS_P ... 572
TARGET_ADDR_SPACE_LEGITIMIZE_ADDRESS ... 572
TARGET_ADDR_SPACE_POINTER_MODE ... 572
TARGET_ADDR_SPACE_SUBSET_P ... 572
TARGET_ADDR_SPACE_VALID_POINTER_MODE ... 572
TARGET_ADDRESS_COST ... 515
TARGET_ALIGN_ANON_BITFIELD ... 438
TARGET_ALLOCATE_INITIAL_VALUE ... 584
TARGET_ALLOCATE_STACK_SLOTS_FOR_ARGS ... 589
TARGET_ALWAYS_STRIP_DOTDOT ... 426
TARGET_ARG_PARTIAL_BYTES ... 479
TARGET_ARM_EABI_UNWINDER ... 553
TARGET_ARRAY_MODE_SUPPORTED_P ... 483
TARGET_ASAN_SHADOW_OFFSET ... 589
TARGET_ASM_ALIGNED_DI_OP ... 531
TARGET_ASM_ALIGNED_HI_OP ... 531
TARGET_ASM_ALIGNED_SI_OP ... 531
TARGET_ASM_ALIGNED_TI_OP ... 531
TARGET_ASM_ASSEMBLE_VISIBILITY ... 539
TARGET_ASM_BYTE_OP ... 531
TARGET_ASM_CAN_OUTPUT_MI_THUNK ... 491
TARGET_ASM_CLOSE_PAREN ... 533
TARGET_ASM_CODE_END ... 528
TARGET_ASM_CONSTRUCTOR ... 545
TARGET_ASM_DECLARE_CONSTANT_NAME ... 537
TARGET_ASM_DESTRUCTOR ... 545
TARGET_ASM_EMIT_EXCEPT_PERSONALITY ... 551
TARGET_ASM_EMIT_EXCEPT_TABLE_LABEL ... 551
TARGET_ASM_EMIT_UNWIND_LABEL ... 551
TARGET_ASM_EXTERNAL_LIBCALL ... 540
TARGET_ASM_FILE_END ... 528
TARGET_ASM_FILE_START ... 527
TARGET_ASM_FILE_START_APP_OFF ... 527
TARGET_ASM_FILE_START_FILE_DIRECTIVE ... 528
TARGET_ASM_FINAL_POSTSCAN_INSN ... 547
TARGET_ASM_FUNCTION_BEGIN_EPILOGUE ... 489
TARGET_ASM_FUNCTION_END_PROLOGUE ... 489
TARGET_ASM_FUNCTION_EPILOGUE ... 489
TARGET_ASM_FUNCTION_PROLOGUE ... 488
TARGET_ASM_FUNCTION_RODATA_SECTION ... 525
TARGET_ASM_FUNCTION_SECTION ... 529
TARGET_ASM_FUNCTION_SWITCHED_TEXT_SECTIONS ... 529
TARGET_ASM_GLOBALIZE_DECL_NAME ... 538
TARGET_ASM_GLOBALIZE_LABEL ... 538
TARGET_ASM_INIT_SECTIONS ... 524
TARGET_ASM_INTEGER ... 531
TARGET_ASM_INTERNAL_LABEL ... 540
TARGET_ASM_JUMP_ALIGN_MAX_SKIP ... 554
TARGET_ASM_LABEL_ALIGN_AFTER_BARRIER_MAX_SKIP ... 554
TARGET_ASM_LABEL_ALIGN_MAX_SKIP ... 554
TARGET_ASM_LOOP_ALIGN_MAX_SKIP ... 554
TARGET_ASM_LTO_END ... 528
TARGET_ASM_LTO_START ... 528
TARGET_ASM_MARK_DECL_PRESERVED ... 540
TARGET_ASM_MERGEABLE_RODATA_PREFIX ... 525
TARGET_ASM_NAMED_SECTION ... 529
TARGET_ASM_OPEN_PAREN ... 533
TARGET_ASM_OUTPUT_ADDR_CONST_EXTRA ... 531
TARGET_ASM_OUTPUT_ANCHOR ... 506
TARGET_ASM_OUTPUT_DWARF_DTPREL ... 561
TARGET_ASM_OUTPUT_IDENT ... 529
TARGET_ASM_OUTPUT_MI_THUNK ... 491
TARGET_ASM_OUTPUT_SOURCE_FILENAME ... 529
TARGET_ASM_RECORD_GCC_SWITCHES ... 530
TARGET_ASM_RECORD_GCC_SWITCHES_SECTION ... 531
TARGET_ASM_RELOC_RW_MASK ... 524
TARGET_ASM_SELECT_RTX_SECTION ... 525
TARGET_ASM_SELECT_SECTION ... 524
TARGET_ASM_TM_CLONE_TABLE_SECTION ... 525
TARGET_ASM_TRAMPOLINE_TEMPLATE ... 496
TARGET_ASM_TTYPE ... 553
TARGET_ASM_UNALIGNED_DI_OP ... 531
TARGET_ASM_UNALIGNED_HI_OP ... 531
TARGET_ASM_UNALIGNED_SI_OP ... 531
TARGET_ASM_UNALIGNED_TI_OP ... 531
TARGET_ASM_UNIQUE_SECTION ... 525
TARGET_ASM_UNWIND_EMIT ... 551
TARGET_ASM_UNWIND_EMIT_BEFORE_INSN ... 551
TARGET_ATOMIC_ALIGN_FOR_MODE ... 590
TARGET_ATOMIC_ASSIGN_EXPAND_FENV ... 590
TARGET_ATOMIC_TEST_AND_SET_TRUEVAL ... 590
TARGET_ATTRIBUTE_TABLE ... 565
TARGET_ATTRIBUTE_TAKES_IDENTIFIER_P ... 565
TARGET_BINDS_LOCAL_P ... 526
TARGET_BRANCH_TARGET_REGISTER_CALLEE_SAVED ... 586
TARGET_BRANCH_TARGET_REGISTER_CLASS ... 586
TARGET_BUILD_BUILTIN_VA_LIST ... 482
TARGET_BUILTIN_DECL ... 582
TARGET_BUILTIN_RECIPROCAL ... 503
TARGET_BUILTIN_SETJMP_FRAME_VALUE ... 466
TARGET_C_PREINCLUDE ... 578
TARGET_CALLEE_COPIES ... 480
TARGET_CAN_ELIMINATE ... 476
TARGET_CAN_FOLLOW_JUMP ... 584
TARGET_CAN_INLINE_P ... 567
TARGET_CAN_USE_DOLOOP_P ... 583
TARGET_CANNOT_FORCE_CONST_MEM ... 502
TARGET_CANNOT_MODIFY_JUMPS_P ... 586
TARGET_CANONICAL_VA_LIST_TYPE ... 483
TARGET_CANONICALIZE_COMPARISON ... 509
TARGET_CASE_VALUES_THRESHOLD ... 573
TARGET_CC_MODES_COMPATIBLE ... 510
TARGET_CHECK_PCH_TARGET_FLAGS ... 569
TARGET_CHECK_STRING_OBJECT_FORMAT_ARG ... 430

TARGET_CLASS_LIKELY_SPILLED_P 461
TARGET_CLASS_MAX_NREGS 461
TARGET_COMMUTATIVE_P 584
TARGET_COMP_TYPE_ATTRIBUTES 565
TARGET_COMPARE_VERSION_PRIORITY 583
TARGET_CONDITIONAL_REGISTER_USAGE 448
TARGET_CONST_ANCHOR 589
TARGET_CONST_NOT_OK_FOR_DEBUG_P 502
TARGET_CONVERT_TO_TYPE 588
TARGET_CPU_CPP_BUILTINS 428
TARGET_CSTORE_MODE 462
TARGET_CXX_ADJUST_CLASS_AT_DEFINITION ... 571
TARGET_CXX_CDTOR_RETURNS_THIS 570
TARGET_CXX_CLASS_DATA_ALWAYS_COMDAT 571
TARGET_CXX_COOKIE_HAS_SIZE 570
TARGET_CXX_DECL_MANGLING_CONTEXT 571
TARGET_CXX_DETERMINE_CLASS_DATA_VISIBILITY 570
TARGET_CXX_GET_COOKIE_SIZE 570
TARGET_CXX_GUARD_MASK_BIT 570
TARGET_CXX_GUARD_TYPE 570
TARGET_CXX_IMPLICIT_EXTERN_C 578
TARGET_CXX_IMPORT_EXPORT_CLASS 570
TARGET_CXX_KEY_METHOD_MAY_BE_INLINE 570
TARGET_CXX_LIBRARY_RTTI_COMDAT 571
TARGET_CXX_USE_AEABI_ATEXIT 571
TARGET_CXX_USE_ATEXIT_FOR_CXA_ATEXIT 571
TARGET_DEBUG_UNWIND_INFO 560
TARGET_DECIMAL_FLOAT_SUPPORTED_P 440
TARGET_DECLSPEC 566
TARGET_DEFAULT_PACK_STRUCT 580
TARGET_DEFAULT_SHORT_ENUMS 444
TARGET_DEFAULT_TARGET_FLAGS 429
TARGET_DEFERRED_OUTPUT_DEFS 542
TARGET_DELAY_SCHED2 560
TARGET_DELAY_VARTRACK 560
TARGET_DELEGITIMIZE_ADDRESS 502
TARGET_DIFFERENT_ADDR_DISPLACEMENT_P 462
TARGET_DLLIMPORT_DECL_ATTRIBUTES 565
TARGET_DWARF_CALLING_CONVENTION 559
TARGET_DWARF_HANDLE_FRAME_UNSPEC 468
TARGET_DWARF_REGISTER_SPAN 553
TARGET_EDOM 498
TARGET_EMUTLS_DEBUG_FORM_TLS_ADDRESS 568
TARGET_EMUTLS_GET_ADDRESS 568
TARGET_EMUTLS_REGISTER_COMMON 568
TARGET_EMUTLS_TMPL_PREFIX 568
TARGET_EMUTLS_TMPL_SECTION 568
TARGET_EMUTLS_VAR_ALIGN_FIXED 568
TARGET_EMUTLS_VAR_FIELDS 568
TARGET_EMUTLS_VAR_INIT 568
TARGET_EMUTLS_VAR_PREFIX 568
TARGET_EMUTLS_VAR_SECTION 568
TARGET_ENCODE_SECTION_INFO 525
TARGET_ENCODE_SECTION_INFO and address validation 500
TARGET_ENCODE_SECTION_INFO usage 548
TARGET_ENUM_VA_LIST_P 482
TARGET_EXCEPT_UNWIND_INFO 552
TARGET_EXECUTABLE_SUFFIX 585
TARGET_EXPAND_BUILTIN 582
TARGET_EXPAND_BUILTIN_SAVEREGS 494
TARGET_EXPAND_TO_RTL_HOOK 441
TARGET_EXPR 144
TARGET_EXTRA_INCLUDES 587
TARGET_EXTRA_LIVE_ON_ENTRY 492
TARGET_EXTRA_PRE_INCLUDES 587
TARGET_FIXED_CONDITION_CODE_REGS 510
TARGET_FIXED_POINT_SUPPORTED_P 440
target_flags 429
TARGET_FLAGS_REGNUM 484
TARGET_FLOAT_EXCEPTIONS_ROUNDING_SUPPORTED_P 431
TARGET_FLT_EVAL_METHOD 444
TARGET_FN_ABI_VA_LIST 483
TARGET_FOLD_BUILTIN 583
TARGET_FORCE_AT_COMP_DIR 560
TARGET_FORMAT_TYPES 587
TARGET_FRAME_POINTER_REQUIRED 475
TARGET_FUNCTION_ARG 478
TARGET_FUNCTION_ARG_ADVANCE 481
TARGET_FUNCTION_ARG_BOUNDARY 482
TARGET_FUNCTION_ARG_ROUND_BOUNDARY 482
TARGET_FUNCTION_ATTRIBUTE_INLINABLE_P ... 566
TARGET_FUNCTION_INCOMING_ARG 479
TARGET_FUNCTION_OK_FOR_SIBCALL 492
TARGET_FUNCTION_VALUE 485
TARGET_FUNCTION_VALUE_REGNO_P 486
TARGET_GENERATE_VERSION_DISPATCHER_BODY 583
TARGET_GET_DRAP_RTX 589
TARGET_GET_FUNCTION_VERSIONS_DISPATCHER 583
TARGET_GET_PCH_VALIDITY 569
TARGET_GET_RAW_ARG_MODE 488
TARGET_GET_RAW_RESULT_MODE 487
TARGET_GIMPLE_FOLD_BUILTIN 583
TARGET_GIMPLIFY_VA_ARG_EXPR 483
TARGET_HANDLE_C_OPTION 429
TARGET_HANDLE_OPTION 429
TARGET_HARD_REGNO_SCRATCH_OK 452
TARGET_HAS_IFUNC_P 590
TARGET_HAS_NO_HW_DIVIDE 498
TARGET_HAVE_CONDITIONAL_EXECUTION 586
TARGET_HAVE_CTORS_DTORS 545
TARGET_HAVE_NAMED_SECTIONS 529
TARGET_HAVE_SRODATA_SECTION 526
TARGET_HAVE_SWITCHABLE_BSS_SECTIONS 530
TARGET_HAVE_TLS 526
TARGET_IN_SMALL_DATA_P 526
TARGET_INIT_BUILTINS 582
TARGET_INIT_DWARF_REG_SIZES_EXTRA 553
TARGET_INIT_LIBFUNCS 497
TARGET_INSERT_ATTRIBUTES 566
TARGET_INSTANTIATE_DECLS 441
TARGET_INVALID_ARG_FOR_UNPROTOTYPED_FN .. 588

TARGET_INVALID_BINARY_OP 588
TARGET_INVALID_CONVERSION 588
TARGET_INVALID_PARAMETER_TYPE 588
TARGET_INVALID_RETURN_TYPE 588
TARGET_INVALID_UNARY_OP 588
TARGET_INVALID_WITHIN_DOLOOP 584
TARGET_LEGITIMATE_ADDRESS_P 499
TARGET_LEGITIMATE_COMBINED_INSN 584
TARGET_LEGITIMATE_CONSTANT_P 502
TARGET_LEGITIMIZE_ADDRESS 500
TARGET_LIB_INT_CMP_BIASED 498
TARGET_LIBC_HAS_FUNCTION 498
TARGET_LIBCALL_VALUE 485
TARGET_LIBFUNC_GNU_PREFIX 497
TARGET_LIBGCC_CMP_RETURN_MODE 439
TARGET_LIBGCC_SDATA_SECTION 523
TARGET_LIBGCC_SHIFT_COUNT_MODE 440
TARGET_LOOP_UNROLL_ADJUST 586
TARGET_LRA_P 462
TARGET_MACHINE_DEPENDENT_REORG 582
TARGET_MANGLE_ASSEMBLER_NAME 540
TARGET_MANGLE_DECL_ASSEMBLER_NAME 525
TARGET_MANGLE_TYPE 441
TARGET_MAX_ANCHOR_OFFSET 506
TARGET_MD_ASM_CLOBBERS 580
TARGET_MEM_CONSTRAINT 500
TARGET_MEM_REF 143
TARGET_MEMBER_TYPE_FORCES_BLK 439
TARGET_MEMMODEL_CHECK 590
TARGET_MEMORY_MOVE_COST 511
TARGET_MERGE_DECL_ATTRIBUTES 565
TARGET_MERGE_TYPE_ATTRIBUTES 565
TARGET_MIN_ANCHOR_OFFSET 506
TARGET_MIN_DIVISIONS_FOR_RECIP_MUL 574
TARGET_MODE_DEPENDENT_ADDRESS_P 502
TARGET_MODE_REP_EXTENDED 575
TARGET_MS_BITFIELD_LAYOUT_P 440
TARGET_MUST_PASS_IN_STACK 479
TARGET_MUST_PASS_IN_STACK, and
TARGET_FUNCTION_ARG 479
TARGET_N_FORMAT_TYPES 587
TARGET_NARROW_VOLATILE_BITFIELD 439
TARGET_OBJC_CONSTRUCT_STRING_OBJECT 430
TARGET_OBJC_DECLARE_CLASS_DEFINITION 430
TARGET_OBJC_DECLARE_UNRESOLVED_CLASS_
REFERENCE 430
TARGET_OBJECT_SUFFIX 585
TARGET_OBJFMT_CPP_BUILTINS 429
TARGET_OPTF 587
TARGET_OPTION_DEFAULT_PARAMS 431
TARGET_OPTION_FUNCTION_VERSIONS 567
TARGET_OPTION_INIT_STRUCT 431
TARGET_OPTION_OPTIMIZATION_TABLE 430
TARGET_OPTION_OVERRIDE 567
TARGET_OPTION_PRAGMA_PARSE 567
TARGET_OPTION_PRINT 567
TARGET_OPTION_RESTORE 567
TARGET_OPTION_SAVE 566
TARGET_OPTION_VALID_ATTRIBUTE_P 566
TARGET_OS_CPP_BUILTINS 429
TARGET_OVERRIDE_OPTIONS_AFTER_CHANGE 430
TARGET_OVERRIDES_FORMAT_ATTRIBUTES 587
TARGET_OVERRIDES_FORMAT_ATTRIBUTES_COUNT
..... 587
TARGET_OVERRIDES_FORMAT_INIT 587
TARGET_PASS_BY_REFERENCE 480
TARGET_PCH_VALID_P 569
TARGET_POSIX_IO 581
TARGET_PREFERRED_OUTPUT_RELOAD_CLASS 458
TARGET_PREFERRED_RELOAD_CLASS 457
TARGET_PREFERRED_RENAME_CLASS 456
TARGET_PREPARE_PCH_SAVE 569
TARGET_PRETEND_OUTGOING_VARARGS_NAMED ... 495
TARGET_PROFILE_BEFORE_PROLOGUE 526
TARGET_PROMOTE_FUNCTION_MODE 434
TARGET_PROMOTE_PROTOTYPES 476
TARGET_PROMOTED_TYPE 588
TARGET_PTRMEMFUNC_VBIT_LOCATION 446
TARGET_REF_MAY_ALIAS_ERRNO 483
TARGET_REGISTER_MOVE_COST 510
TARGET_REGISTER_PRIORITY 462
TARGET_REGISTER_USAGE_LEVELING_P 462
TARGET_RELAXED_ORDERING 587
TARGET_RESOLVE_OVERLOADED_BUILTIN 583
TARGET_RETURN_IN_MEMORY 487
TARGET_RETURN_IN_MSB 486
TARGET_RETURN_POPS_ARGS 477
TARGET_RTX_COSTS 514
TARGET_SCALAR_MODE_SUPPORTED_P 483
TARGET_SCHED_ADJUST_COST 516
TARGET_SCHED_ADJUST_PRIORITY 516
TARGET_SCHED_ALLOC_SCHED_CONTEXT 520
TARGET_SCHED_CLEAR_SCHED_CONTEXT 520
TARGET_SCHED_DEPENDENCIES_EVALUATION_HOOK
..... 517
TARGET_SCHED_DFA_NEW_CYCLE 519
TARGET_SCHED_DFA_POST_ADVANCE_CYCLE 518
TARGET_SCHED_DFA_POST_CYCLE_INSN 518
TARGET_SCHED_DFA_PRE_ADVANCE_CYCLE 518
TARGET_SCHED_DFA_PRE_CYCLE_INSN 517
TARGET_SCHED_DISPATCH 521
TARGET_SCHED_DISPATCH_DO 521
TARGET_SCHED_EXPOSED_PIPELINE 521
TARGET_SCHED_FINISH 517
TARGET_SCHED_FINISH_GLOBAL 517
TARGET_SCHED_FIRST_CYCLE_MULTIPASS_
BACKTRACK 519
TARGET_SCHED_FIRST_CYCLE_MULTIPASS_BEGIN
..... 519
TARGET_SCHED_FIRST_CYCLE_MULTIPASS_DFA_
LOOKAHEAD 518
TARGET_SCHED_FIRST_CYCLE_MULTIPASS_DFA_
LOOKAHEAD_GUARD 518
TARGET_SCHED_FIRST_CYCLE_MULTIPASS_DFA_
LOOKAHEAD_GUARD_SPEC 521
TARGET_SCHED_FIRST_CYCLE_MULTIPASS_END .. 519

TARGET_SCHED_FIRST_CYCLE_MULTIPASS_FINI 519
TARGET_SCHED_FIRST_CYCLE_MULTIPASS_INIT 519
TARGET_SCHED_FIRST_CYCLE_MULTIPASS_ISSUE 519
TARGET_SCHED_FREE_SCHED_CONTEXT 520
TARGET_SCHED_GEN_SPEC_CHECK 520
TARGET_SCHED_H_I_D_EXTENDED 520
TARGET_SCHED_INIT 517
TARGET_SCHED_INIT_DFA_POST_CYCLE_INSN ... 518
TARGET_SCHED_INIT_DFA_PRE_CYCLE_INSN..... 518
TARGET_SCHED_INIT_GLOBAL 517
TARGET_SCHED_INIT_SCHED_CONTEXT 520
TARGET_SCHED_IS_COSTLY_DEPENDENCE 519
TARGET_SCHED_ISSUE_RATE 515
TARGET_SCHED_MACRO_FUSION_P 516
TARGET_SCHED_MACRO_FUSION_PAIR_P 517
TARGET_SCHED_NEEDS_BLOCK_P 520
TARGET_SCHED_REASSOCIATION_WIDTH 521
TARGET_SCHED_REORDER 516
TARGET_SCHED_REORDER2 516
TARGET_SCHED_SET_SCHED_CONTEXT 520
TARGET_SCHED_SET_SCHED_FLAGS 521
TARGET_SCHED_SMS_RES_MII 521
TARGET_SCHED_SPECULATE_INSN 520
TARGET_SCHED_VARIABLE_ISSUE 515
TARGET_SECONDARY_RELOAD 458
TARGET_SECTION_TYPE_FLAGS 530
TARGET_SET_CURRENT_FUNCTION 585
TARGET_SET_DEFAULT_TYPE_ATTRIBUTES 565
TARGET_SET_UP_BY_PROLOGUE 492
TARGET_SETUP_INCOMING_VARARGS 494
TARGET_SHIFT_TRUNCATION_MASK 575
TARGET_SIMD_CLONE_ADJUST 505
TARGET_SIMD_CLONE_COMPUTE_VECSIZE_AND_SIMDLEN 505
TARGET_SIMD_CLONE_USABLE 505
TARGET_SMALL_REGISTER_CLASSES_FOR_MODE_P 484
TARGET_SPILL_CLASS 462
TARGET_SPLIT_COMPLEX_ARG 482
TARGET_STACK_PROTECT_FAIL 493
TARGET_STACK_PROTECT_GUARD 493
TARGET_STATIC_CHAIN 473
TARGET_STRICT_ARGUMENT_NAMING 495
TARGET_STRING_OBJECT_REF_TYPE_P 430
TARGET_STRIP_NAME_ENCODING 526
TARGET_STRUCT_VALUE_RTX 487
TARGET_SUPPORTS_SPLIT_STACK 493
TARGET_SUPPORTS_WEAK 539
TARGET_TERMINATE_DW2_EH_FRAME_INFO 553
TARGET_TRAMPOLINE_ADJUST_ADDRESS 496
TARGET_TRAMPOLINE_INIT 496
TARGET_UNSPEC_MAY_TRAP_P 585
TARGET_UNWIND_TABLES_DEFAULT 552
TARGET_UNWIND_WORD_MODE 440
TARGET_UPDATE_STACK_BOUNDARY 589
TARGET_USE_ANCHORS_FOR_SYMBOL_P 506
TARGET_USE_BLOCKS_FOR_CONSTANT_P 502
TARGET_USE_BLOCKS_FOR_DECL_P 503
TARGET_USE_JCR_SECTION 589
TARGET_USES_WEAK_UNWIND_INFO 470
TARGET_VALID_DLLIMPORT_ATTRIBUTE_P 566
TARGET_VALID_POINTER_MODE 483
TARGET_VECTOR_ALIGNMENT 436
TARGET_VECTOR_MODE_SUPPORTED_P 483
TARGET_VECTORIZE_ADD_STMT_COST 504
TARGET_VECTORIZE_AUTOVECTORIZE_VECTOR_SIZES 504
TARGET_VECTORIZE_BUILTIN_CONVERSION 504
TARGET_VECTORIZE_BUILTIN_GATHER 505
TARGET_VECTORIZE_BUILTIN_MASK_FOR_LOAD .. 503
TARGET_VECTORIZE_BUILTIN_TM_LOAD 505
TARGET_VECTORIZE_BUILTIN_TM_STORE 505
TARGET_VECTORIZE_BUILTIN_VECTORIZATION_COST 503
TARGET_VECTORIZE_BUILTIN_VECTORIZED_FUNCTION 504
TARGET_VECTORIZE_DESTROY_COST_DATA 505
TARGET_VECTORIZE_FINISH_COST 505
TARGET_VECTORIZE_INIT_COST 504
TARGET_VECTORIZE_PREFERRED_SIMD_MODE 504
TARGET_VECTORIZE_SUPPORT_VECTOR_MISALIGNMENT 504
TARGET_VECTORIZE_VEC_PERM_CONST_OK 503
TARGET_VECTORIZE_VECTOR_ALIGNMENT_REACHABLE 503
TARGET_VTABLE_DATA_ENTRY_DISTANCE 447
TARGET_VTABLE_ENTRY_ALIGN 447
TARGET_VTABLE_USES_DESCRIPTORS 447
TARGET_WANT_DEBUG_PUB_SECTIONS 560
TARGET_WARN_FUNC_RETURN 492
TARGET_WEAK_NOT_IN_ARCHIVE_TOC 539
targetm 421
targets, makefile 66
TCmode 238
TDmode 236
TEMPLATE_DECL 136
Temporaries 181
termination routines 542
testing constraints 348
TEXT_SECTION_ASM_OP 522
TF_SIZE 443
TFmode 236
THEN_CLAUSE 169
THREAD_MODEL_SPEC 424
THROW_EXPR 144
THUNK_DECL 136
THUNK_DELTA 136
TImode 236
TImode, in insn 269
TLS_COMMON_ASM_OP 523
TLS_SECTION_ASM_FLAG 523
'tm.h' macros 421
TQFmode 236

TQmode ... 237
TRAMPOLINE_ALIGNMENT ... 496
TRAMPOLINE_SECTION ... 496
TRAMPOLINE_SIZE ... 496
trampolines for nested functions ... 495
TRANSFER_FROM_TRAMPOLINE ... 497
trap instruction pattern ... 373
tree ... 129, 130
Tree SSA ... 211
TREE_CHAIN ... 130
TREE_CODE ... 129
tree_int_cst_equal ... 141
TREE_INT_CST_HIGH ... 141
TREE_INT_CST_LOW ... 141
tree_int_cst_lt ... 141
TREE_LIST ... 131
TREE_OPERAND ... 141
TREE_PUBLIC ... 158, 160
TREE_PURPOSE ... 131
TREE_READONLY ... 160
tree_size ... 130
TREE_STATIC ... 160
TREE_STRING_LENGTH ... 141
TREE_STRING_POINTER ... 141
TREE_THIS_VOLATILE ... 160
TREE_TYPE ... 130, 131, 136, 141, 159, 162
TREE_VALUE ... 131
TREE_VEC ... 131
TREE_VEC_ELT ... 131
TREE_VEC_LENGTH ... 131
TRULY_NOOP_TRUNCATION ... 575
TRUNC_DIV_EXPR ... 144
TRUNC_MOD_EXPR ... 144
truncate ... 256
trunc*mn*2 instruction pattern ... 363
TRUTH_AND_EXPR ... 144
TRUTH_ANDIF_EXPR ... 144
TRUTH_NOT_EXPR ... 144
TRUTH_OR_EXPR ... 144
TRUTH_ORIF_EXPR ... 144
TRUTH_XOR_EXPR ... 144
TRY_BLOCK ... 169
TRY_HANDLERS ... 169
TRY_STMTS ... 169
Tuple specific accessors ... 188
tuples ... 176
type ... 131
type declaration ... 136
TYPE_ALIGN ... 131, 132, 162
TYPE_ARG_TYPES ... 131, 162
TYPE_ASM_OP ... 536
TYPE_ATTRIBUTES ... 141
TYPE_BINFO ... 165
TYPE_BUILT_IN ... 163
TYPE_CANONICAL ... 131, 132
TYPE_CONTEXT ... 131, 162
TYPE_DECL ... 136
TYPE_FIELDS ... 131, 162, 165
TYPE_HAS_ARRAY_NEW_OPERATOR ... 166
TYPE_HAS_DEFAULT_CONSTRUCTOR ... 166
TYPE_HAS_MUTABLE_P ... 166
TYPE_HAS_NEW_OPERATOR ... 166
TYPE_MAIN_VARIANT ... 131, 132, 162
TYPE_MAX_VALUE ... 131
TYPE_METHOD_BASETYPE ... 131, 162
TYPE_METHODS ... 165
TYPE_MIN_VALUE ... 131
TYPE_NAME ... 131, 132, 162
TYPE_NOTHROW_P ... 169
TYPE_OFFSET_BASETYPE ... 131, 162
TYPE_OPERAND_FMT ... 536
TYPE_OVERLOADS_ARRAY_REF ... 166
TYPE_OVERLOADS_ARROW ... 166
TYPE_OVERLOADS_CALL_EXPR ... 166
TYPE_POLYMORPHIC_P ... 166
TYPE_PRECISION ... 131, 162
TYPE_PTR_P ... 163
TYPE_PTRDATAMEM_P ... 162, 163
TYPE_PTRFN_P ... 163
TYPE_PTROB_P ... 163
TYPE_PTROBV_P ... 162
TYPE_QUAL_CONST ... 131, 162
TYPE_QUAL_RESTRICT ... 131, 162
TYPE_QUAL_VOLATILE ... 131, 162
TYPE_RAISES_EXCEPTIONS ... 169
TYPE_SIZE ... 131, 132, 162
TYPE_STRUCTURAL_EQUALITY_P ... 131, 133
TYPE_UNQUALIFIED ... 131, 162
TYPE_VFIELD ... 165
TYPENAME_TYPE ... 162
TYPENAME_TYPE_FULLNAME ... 131, 162
TYPEOF_TYPE ... 162

U

UDAmode ... 237
udiv ... 251
udiv*m*3 instruction pattern ... 354
udivmod*m*4 instruction pattern ... 357
udot_prod*m* instruction pattern ... 355
UDQmode ... 237
UHAmode ... 237
UHQmode ... 237
UINT_FAST16_TYPE ... 446
UINT_FAST32_TYPE ... 446
UINT_FAST64_TYPE ... 446
UINT_FAST8_TYPE ... 446
UINT_LEAST16_TYPE ... 445
UINT_LEAST32_TYPE ... 445
UINT_LEAST64_TYPE ... 445
UINT_LEAST8_TYPE ... 445
UINT16_TYPE ... 445
UINT32_TYPE ... 445
UINT64_TYPE ... 445
UINT8_TYPE ... 445
UINTMAX_TYPE ... 445

UINTPTR_TYPE ... 446
umadd*mn*4 instruction pattern ... 357
umax ... 251
umax*m*3 instruction pattern ... 354
umin ... 251
umin*m*3 instruction pattern ... 354
umod ... 251
umod*m*3 instruction pattern ... 354
umsub*mn*4 instruction pattern ... 357
umulhisi3 instruction pattern ... 356
umul*m*3_highpart instruction pattern ... 356
umulqihi3 instruction pattern ... 356
umulsidi3 instruction pattern ... 356
unchanging ... 234
unchanging, in call_insn ... 230
unchanging, in jump_insn, call_insn and insn ... 230
unchanging, in mem ... 232
unchanging, in subreg ... 232, 233
unchanging, in symbol_ref ... 230
UNEQ_EXPR ... 144
UNGE_EXPR ... 144
UNGT_EXPR ... 144
UNION_TYPE ... 131, 165
unions, returning ... 7
UNITS_PER_WORD ... 433
UNKNOWN_TYPE ... 131, 162
UNLE_EXPR ... 144
UNLIKELY_EXECUTED_TEXT_SECTION_NAME ... 522
UNLT_EXPR ... 144
UNORDERED_EXPR ... 144
unshare_all_rtl ... 275
unsigned division ... 251
unsigned division with unsigned saturation ... 251
unsigned greater than ... 253, 254
unsigned less than ... 253, 254
unsigned minimum and maximum ... 251
unsigned_fix ... 256
unsigned_float ... 256
unsigned_fract_convert ... 257
unsigned_sat_fract ... 257
unspec ... 262, 415
unspec_volatile ... 262, 415
untyped_call instruction pattern ... 367
untyped_return instruction pattern ... 368
UPDATE_PATH_HOST_CANONICALIZE (*path*) ... 592
update_ssa ... 217
update_stmt ... 188, 211
update_stmt_if_modified ... 188
UQQmode ... 237
us_ashift ... 251
us_minus ... 249
us_mult ... 250
us_neg ... 250
us_plus ... 249
us_truncate ... 256
usadd*m*3 instruction pattern ... 354
USAmode ... 237
usashl*m*3 instruction pattern ... 357
usdiv*m*3 instruction pattern ... 354
use ... 260
USE_C_ALLOCA ... 593
USE_LD_AS_NEEDED ... 424
USE_LOAD_POST_DECREMENT ... 513
USE_LOAD_POST_INCREMENT ... 513
USE_LOAD_PRE_DECREMENT ... 514
USE_LOAD_PRE_INCREMENT ... 513
use_param ... 605
use_param*n* ... 606
use_params ... 606
USE_SELECT_SECTION_FOR_FUNCTIONS ... 524
USE_STORE_POST_DECREMENT ... 514
USE_STORE_POST_INCREMENT ... 514
USE_STORE_PRE_DECREMENT ... 514
USE_STORE_PRE_INCREMENT ... 514
used ... 234
used, in symbol_ref ... 233
user ... 609
user gc ... 610
USER_LABEL_PREFIX ... 549
USING_STMT ... 169
usmadd*mn*4 instruction pattern ... 357
usmsub*mn*4 instruction pattern ... 357
usmulhisi3 instruction pattern ... 356
usmul*m*3 instruction pattern ... 354
usmulqihi3 instruction pattern ... 356
usmulsidi3 instruction pattern ... 356
usneg*m*2 instruction pattern ... 358
USQmode ... 237
ussub*m*3 instruction pattern ... 354
usum_widen*m3* instruction pattern ... 355
UTAmode ... 237
UTQmode ... 237

V

'V' in constraint ... 311
VA_ARG_EXPR ... 144
values, returned by functions ... 484
VAR_DECL ... 136
var_location ... 264
varargs implementation ... 493
variable ... 136
Variable Location Debug Information in RTL ... 264
variable_size ... 607
vashl*m*3 instruction pattern ... 358
vashr*m*3 instruction pattern ... 358
vcond*mn* instruction pattern ... 352
vec_concat ... 255
vec_duplicate ... 255
vec_extract*m* instruction pattern ... 352
vec_init*m* instruction pattern ... 352
vec_load_lanes*mn* instruction pattern ... 352
VEC_LSHIFT_EXPR ... 151
vec_merge ... 255

VEC_PACK_FIX_TRUNC_EXPR ... 151
VEC_PACK_SAT_EXPR ... 151
vec_pack_sfix_trunc_*m* instruction pattern .. 355
vec_pack_ssat_*m* instruction pattern ... 355
VEC_PACK_TRUNC_EXPR ... 151
vec_pack_trunc_*m* instruction pattern ... 355
vec_pack_ufix_trunc_*m* instruction pattern .. 355
vec_pack_usat_*m* instruction pattern ... 355
vec_perm_const*m* instruction pattern ... 353
vec_perm*m* instruction pattern ... 353
VEC_RSHIFT_EXPR ... 151
vec_select ... 255
vec_set*m* instruction pattern ... 352
vec_shl_*m* instruction pattern ... 355
vec_shr_*m* instruction pattern ... 355
vec_store_lanes*mn* instruction pattern ... 352
VEC_UNPACK_FLOAT_HI_EXPR ... 151
VEC_UNPACK_FLOAT_LO_EXPR ... 151
VEC_UNPACK_HI_EXPR ... 151
VEC_UNPACK_LO_EXPR ... 151
vec_unpacks_float_hi_*m* instruction pattern ... 355
vec_unpacks_float_lo_*m* instruction pattern ... 355
vec_unpacks_hi_*m* instruction pattern ... 355
vec_unpacks_lo_*m* instruction pattern ... 355
vec_unpacku_float_hi_*m* instruction pattern ... 355
vec_unpacku_float_lo_*m* instruction pattern ... 355
vec_unpacku_hi_*m* instruction pattern ... 355
vec_unpacku_lo_*m* instruction pattern ... 355
VEC_WIDEN_MULT_HI_EXPR ... 151
VEC_WIDEN_MULT_LO_EXPR ... 151
vec_widen_smult_even_*m* instruction pattern ... 356
vec_widen_smult_hi_*m* instruction pattern ... 356
vec_widen_smult_lo_*m* instruction pattern ... 356
vec_widen_smult_odd_*m* instruction pattern .. 356
vec_widen_sshiftl_hi_*m* instruction pattern ... 356
vec_widen_sshiftl_lo_*m* instruction pattern ... 356
vec_widen_umult_even_*m* instruction pattern ... 356
vec_widen_umult_hi_*m* instruction pattern ... 356
vec_widen_umult_lo_*m* instruction pattern ... 356
vec_widen_umult_odd_*m* instruction pattern .. 356
vec_widen_ushiftl_hi_*m* instruction pattern ... 356
vec_widen_ushiftl_lo_*m* instruction pattern ... 356
vector ... 131
vector operations ... 255
VECTOR_CST ... 141
VECTOR_STORE_FLAG_VALUE ... 577
verify_flow_info ... 285
virtual operands ... 211
VIRTUAL_INCOMING_ARGS_REGNUM ... 243
VIRTUAL_OUTGOING_ARGS_REGNUM ... 244
VIRTUAL_STACK_DYNAMIC_REGNUM ... 244
VIRTUAL_STACK_VARS_REGNUM ... 244
VLIW ... 404, 407
vlshr*m*3 instruction pattern ... 358
VMS ... 592
VMS_DEBUGGING_INFO ... 562
VOID_TYPE ... 131
VOIDmode ... 237
volatil ... 235
volatil, in insn, call_insn, jump_insn, code_label, jump_table_data, barrier, and note ... 230
volatil, in label_ref and reg_label ... 231
volatil, in mem, asm_operands, and asm_input ... 231
volatil, in reg ... 231
volatil, in subreg ... 232, 233
volatil, in symbol_ref ... 233
volatile memory references ... 235
volatile, in prefetch ... 233
voting between constraint alternatives ... 315
vrotl*m*3 instruction pattern ... 358
vrotr*m*3 instruction pattern ... 358

W

walk_dominator_tree ... 220
walk_gimple_op ... 210
walk_gimple_seq ... 210
walk_gimple_stmt ... 209
WCHAR_TYPE ... 445
WCHAR_TYPE_SIZE ... 445
which_alternative ... 304
WHILE_BODY ... 169
WHILE_COND ... 169
WHILE_STMT ... 169
whopr ... 623
WIDEST_HARDWARE_FP_SIZE ... 444
window_save instruction pattern ... 373
WINT_TYPE ... 445
word_mode ... 240
WORD_REGISTER_OPERATIONS ... 574
WORDS_BIG_ENDIAN ... 432
WORDS_BIG_ENDIAN, effect on subreg ... 246
wpa ... 623

X

'X' in constraint ... 312
'*x-host*' ... 598
XCmode ... 238
XCOFF_DEBUGGING_INFO ... 556
XEXP ... 226
XF_SIZE ... 443
XFmode ... 236
XImode ... 236

XINT 226
'xm-*machine*.h' 592, 593
xor 251
xor, canonicalization of 383
xor*m*3 instruction pattern 354
XSTR 226
XVEC 227
XVECEXP 227
XVECLEN 227
XWINT 226

Z

zero_extend 256
zero_extend*mn*2 instruction pattern 363
zero_extract 254
zero_extract, canonicalization of 383